

Quantum Error Correction

Lecture Notes — Version 3.0

Extended Edition with Worked Examples and Visual Aids

Quantum Computing Course

April 21, 2026

Abstract

These lecture notes provide a comprehensive, self-contained introduction to quantum error correction (QEC) aimed at undergraduate students with basic linear algebra and introductory quantum mechanics. We begin with the question of *why* quantum information is fragile, build from classical intuition to the 3-qubit bit-flip and phase-flip codes, study the Shor 9-qubit code and the Steane $[[7, 1, 3]]$ code, develop the stabilizer formalism as a unifying language, and then move to the topological surface code. Fault-tolerant gates, magic state distillation, the threshold theorem, and advanced quantum LDPC and color codes round out the material.

Contents

1	Introduction: Why Quantum Error Correction?	2
1.1	A Concrete Failure Rate Calculation	2
1.2	Why Classical Error Correction is Not Enough	3
1.3	The No-Cloning Theorem	3
1.4	The Three-Step Strategy of QEC	3
1.5	Historical Context	4
1.6	Learning Goals for This Chapter	4
2	Quantum Errors and the Pauli Framework	6
2.1	Single-Qubit Error Types	6
2.2	Pauli Matrices	6
2.3	Discretisation of Quantum Errors	7
2.4	Quantum Channels and Kraus Operators	8
2.5	Multi-Qubit Pauli Group	8
2.6	Error Propagation in Circuits	9
3	Classical and Quantum Repetition Codes	11
3.1	Classical 3-Bit Repetition Code	11
3.2	Quantum 3-Qubit Bit-Flip Code	11
3.2.1	Encoding Circuit	12
3.2.2	Quantum Syndrome Measurement	12
3.2.3	Full Syndrome Circuit	13
3.3	Limitations: Phase Errors Are Not Corrected	13
3.4	Quantum Phase-Flip Code	14
3.5	Why This Works Despite No-Cloning	14

4	The Shor 9-Qubit Code	16
4.1	Encoding	16
4.1.1	Structure of the Encoding	16
4.1.2	Encoding Circuit	17
4.2	Stabilizer Generators	17
4.2.1	Bit-flip stabilizers (within each 3-qubit block)	17
4.2.2	Phase-flip stabilizers (across blocks)	17
4.3	Error Correction Capability	17
4.4	Correcting Arbitrary Single-Qubit Errors	18
4.5	Logical Operators	18
5	The Steane $[[7, 1, 3]]$ Code	19
5.1	The Classical Hamming $[7, 4, 3]$ Code	19
5.2	The CSS Construction	19
5.3	Steane Code Construction	19
5.3.1	Stabilizer Generators	20
5.3.2	Code Parameters	20
5.4	Logical Operators	20
5.5	Error Correction Procedure	20
5.6	Transversal Gates	21
6	The Stabilizer Formalism	22
6.1	The Pauli Group (Reminder)	22
6.2	Definition of a Stabilizer Code	22
6.3	Logical Operators	22
6.4	Syndrome Measurement in the Stabilizer Formalism	23
6.5	The Knill–Laflamme Error Correction Conditions	23
6.6	Graphical Summary: Stabilizer Code Structure	24
7	The Surface Code	26
7.1	Lattice Structure	26
7.1.1	Counting for a $d = 3$ Surface Code	26
7.1.2	Code Parameters	26
7.2	Error Correction: Minimum-Weight Perfect Matching	27
7.3	Fault-Tolerance Threshold	27
7.4	Logical Gates via Lattice Surgery	28
7.5	Why the Surface Code is Practical	28
8	Fault-Tolerant Quantum Gates	30
8.1	Why Naive Gate Application Fails	30
8.2	Transversal Gates	30
8.3	Fault-Tolerant Syndrome Measurement	30
8.3.1	Repeated Measurement	31
8.4	Magic State Distillation	31
8.4.1	Why We Need Magic States	31
8.4.2	The Magic State Idea	31
8.4.3	Distillation Protocol	32
8.5	The Threshold Theorem	32
8.5.1	Below vs. Above Threshold	33

9	Advanced Topics in Quantum Error Correction	34
9.1	Quantum Low-Density Parity-Check (LDPC) Codes	34
9.1.1	Recent Breakthrough: Good Quantum LDPC Codes	34
9.1.2	Practical Challenges	34
9.2	Color Codes	34
9.2.1	2D Color Code Construction	35
9.2.2	Advantages of Color Codes	35
9.3	Concatenated Codes	35
9.4	Comparison of QEC Code Families	36
10	Summary and Putting It All Together	37
10.1	The Big Picture	37
10.2	Quick Reference: All Codes Covered	37
10.3	Road Map Through the Material	38
10.4	Comprehensive Exercises	38

1 Introduction: Why Quantum Error Correction?

Intuition

Imagine writing a message on a whiteboard in a room with a randomly blowing fan. Every few seconds a gust might smudge a letter. After 1000 letters the message is unreadable. Classical computers deal with this by building transistors so reliable that the “fan” almost never blows. Quantum computers *cannot* do the same thing: the “fan” is the quantum environment itself, and it can never be fully shut out. Quantum error correction is the strategy of encoding the message so cleverly that even with constant smudging, the original meaning can always be recovered.

Quantum systems are notoriously fragile. Qubits, unlike classical bits, are susceptible to **decoherence** and operational errors from two main sources:

- **Decoherence.** A qubit interacts with its surroundings (stray magnetic fields, vibrations, nearby electrons). This interaction *entangles* the qubit with the environment, causing the delicate quantum superposition to leak away. The characteristic times are called T_1 (energy relaxation) and T_2 (dephasing). For state-of-the-art superconducting qubits, $T_2 \sim 100 \mu\text{s}$; a typical gate takes $\sim 50 \text{ ns}$, so only about 2000 gates are possible before significant decoherence.
- **Gate errors.** No physical operation is perfect. A CNOT gate might have a 0.1–1% error probability. For a 1000-gate algorithm on a single unprotected qubit with gate error $p = 0.001$, the probability of *no error at all* is $(1 - 0.001)^{1000} \approx 0.37$. The chance of getting the correct answer with high probability is essentially zero.

Key Point

The goal of quantum error correction is to **detect and correct errors without measuring (and thus collapsing) the quantum information**. This is fundamentally different from classical error correction, and requires genuinely new ideas.

1.1 A Concrete Failure Rate Calculation

Let us make the problem concrete before developing solutions.

Worked Example 1.1: Failure probability accumulation

Suppose we run an algorithm that requires $n = 1000$ sequential single-qubit gates. Each gate has error probability $p = 0.01$ (1%). What is the probability that at least one gate fails?

Solution. The probability that a *single* gate succeeds is $1 - p = 0.99$. The probability that *all* n gates succeed is:

$$P(\text{no error}) = (1 - p)^n = (0.99)^{1000} \approx e^{-10} \approx 4.5 \times 10^{-5}.$$

So with overwhelming probability ($\approx 99.995\%$), at least one gate fails. The computation is useless without error correction.

For comparison, if we could reduce the effective logical error rate to $p_L = 10^{-6}$ using QEC (a reasonable target for near-future devices), the same 1000-gate algorithm succeeds with probability $(1 - 10^{-6})^{1000} \approx 0.999$, which is excellent.

1.2 Why Classical Error Correction is Not Enough

Classical error correction often uses **repetition codes** or parity checks. For example, a classical 3-bit repetition code encodes:

$$0 \longrightarrow 000, \quad 1 \longrightarrow 111,$$

and recovers from a single bit-flip using majority voting. However, applying this idea directly to qubits fails for three fundamental reasons:

1. **The no-cloning theorem** (§1.3) forbids copying an unknown quantum state. We cannot produce three copies of $|\psi\rangle$ to store redundantly.
2. **Errors are continuous.** A qubit can be “partially rotated” by any angle θ . There is an uncountably infinite number of possible errors, unlike the two classical errors (0 and 1).
3. **Measurement destroys superpositions.** If we try to “look at” a qubit to check for errors, we collapse its state.

1.3 The No-Cloning Theorem

Theorem 1.1 (No-Cloning Theorem). *There is no unitary operation U such that for all quantum states $|\psi\rangle$:*

$$U(|\psi\rangle \otimes |0\rangle) = |\psi\rangle \otimes |\psi\rangle.$$

Proof by contradiction. Suppose such a U exists. Let $|\psi\rangle$ and $|\phi\rangle$ be any two single-qubit states. By assumption:

$$U(|\psi\rangle |0\rangle) = |\psi\rangle |\psi\rangle, \quad U(|\phi\rangle |0\rangle) = |\phi\rangle |\phi\rangle.$$

Since U is unitary it preserves inner products:

$$\langle\psi| \langle 0|0\rangle |\phi\rangle = (\langle\psi| \otimes \langle\psi|)(|\phi\rangle \otimes |\phi\rangle),$$

which simplifies to

$$\langle\psi|\phi\rangle = \langle\psi|\phi\rangle^2.$$

This forces $\langle\psi|\phi\rangle \in \{0, 1\}$. Since $|\psi\rangle$ and $|\phi\rangle$ were *arbitrary*, this is a contradiction: two distinct non-orthogonal states (e.g. $|0\rangle$ and $|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$) have $\langle 0|+\rangle = \frac{1}{\sqrt{2}} \neq 0, 1$. $\square$

Intuition

The no-cloning theorem does *not* say we cannot protect quantum information — it says we cannot protect it by simply making copies. Quantum error correction instead spreads the information across an *entangled* state of multiple qubits. No single qubit holds a copy; the information is holographically encoded in the correlations.

1.4 The Three-Step Strategy of QEC

Every quantum error correcting code works through three steps:

1. **Encode.** Map one logical qubit $\alpha|0\rangle + \beta|1\rangle$ into an entangled state of n physical qubits. The coefficients α, β are *not* stored in any single qubit; they live in global correlations.
2. **Syndrome measurement.** Use ancilla (helper) qubits to measure certain *parities* of the data qubits. These parity measurements (called **syndromes**) reveal *what* error occurred without revealing *what* α and β are.

3. **Recovery.** Apply a corrective operation based on the syndrome. Because the syndrome uniquely identifies the error (for correctable errors), we can undo the damage and restore the original encoded state exactly.

logical qubit $\alpha|0\rangle + \beta|1\rangle$




Figure 1: The three-step QEC pipeline. The logical qubit is first encoded into n physical qubits. After an error channel acts, the syndrome is measured (without disturbing α, β), and a recovery operation restores the original state.

1.5 Historical Context

Quantum error correction emerged in the mid-1990s in rapid succession:

- **Shor (1995):** First QEC code — a 9-qubit code correcting arbitrary single-qubit errors.
- **Steane (1996):** 7-qubit CSS code derived from classical Hamming codes; simpler and more efficient.
- **Knill & Laflamme (1997):** General algebraic conditions (the KL conditions) characterising when a set of errors is correctable.
- **Kitaev (1997):** Toric/surface code — topological QEC with local stabilizers, high threshold, and deep connections to topology.
- **Preskill (1997–2012):** Threshold theorem and fault-tolerant computing framework.

1.6 Learning Goals for This Chapter

After reading this chapter, you should be able to:

- Calculate the probability that an unprotected quantum computation fails due to accumulated errors.
- State and prove the no-cloning theorem and explain why it does *not* forbid QEC.
- Describe the encode–syndrome–recover strategy in plain language.
- Explain the three fundamental obstacles preventing direct application of classical error correction to qubits.

Exercise 1.1. A quantum algorithm requires $n = 500$ two-qubit gates, each with error probability $p = 0.005$. What is the probability that no error occurs? What is the minimum gate fidelity required to ensure the computation succeeds with probability at least 0.9?

Exercise 1.2. Prove that the no-cloning theorem forbids *broadcasting*: there is no quantum channel $\mathcal{E}$ such that $\mathcal{E}(|\psi\rangle\langle\psi|) = |\psi\rangle\langle\psi| \otimes |\psi\rangle\langle\psi|$ for all pure states $|\psi\rangle$. (*Hint*: use a linearity argument rather than unitarity.)

Exercise 1.3. Explain in your own words why the no-cloning theorem does *not* prevent quantum error correction. What feature of QEC allows it to protect information without copying it?

Section Summary

Section 1 key points:

- Qubit errors accumulate rapidly; even 0.1% gate error makes a 1000-gate algorithm unreliable without correction.
- No-cloning theorem: we cannot copy an unknown quantum state.
- QEC works by encoding into entangled states, measuring syndromes (error indicators without revealing logical information), and applying corrective operations.

2 Quantum Errors and the Pauli Framework

Intuition

A single qubit lives on the surface of the “Bloch sphere” — a unit sphere where the north pole is $|0\rangle$, the south pole is $|1\rangle$, and every other point is a superposition. An error is a rotation of this sphere. There are rotations about three axes: X (flips $|0\rangle \leftrightarrow |1\rangle$, the “equatorial flip”), Z (flips the relative phase, a rotation about the vertical axis), and Y (combines both). Any rotation can be decomposed into these three generators — this is the key insight that makes discrete error correction possible.

2.1 Single-Qubit Error Types

Consider a qubit in state $|\psi\rangle = \alpha|0\rangle + \beta|1\rangle$.

Although a single qubit can undergo infinitely many possible errors (e.g., arbitrary rotations or phase changes), it is sufficient to study a small set of fundamental error operators. In particular, the Pauli operators $\{I, X, Y, Z\}$ form a basis for all single-qubit operations. This means that any physical error can be expressed as a linear combination of these operators.

For this reason, we focus on the following three “pure” error types, which serve as basis elements for all possible single-qubit errors:

Error	Op.	Action	Physical meaning
Bit-flip	X	$ 0\rangle \leftrightarrow 1\rangle$	Like a classical bit-flip; exchanges amplitudes
Phase-flip	Z	$ 0\rangle \mapsto 0\rangle, 1\rangle \mapsto - 1\rangle$	Flips the relative phase between basis states
Bit+Phase	$Y=iXZ$	$ 0\rangle \mapsto i 1\rangle, 1\rangle \mapsto -i 0\rangle$	Combines both bit-flip and phase-flip effects

Correcting these three types of errors is sufficient, because any general single-qubit error can be decomposed into a combination of them. Thus, in quantum error correction, these operators provide a complete and convenient description of all possible single-qubit errors.

2.2 Pauli Matrices

The four **Pauli operators** are:

$$I = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix}, \quad X = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}, \quad Y = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix}, \quad Z = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}.$$

They are Hermitian ($P^\dagger = P$), unitary ($P^\dagger P = I$), and traceless for $P \in \{X, Y, Z\}$. Their key algebraic properties are:

$$X^2 = Y^2 = Z^2 = I, \tag{1}$$

$$XY = iZ, \quad YZ = iX, \quad ZX = iY, \tag{2}$$

$$\{X, Z\} = XZ + ZX = 0 \quad (\text{anticommute}), \tag{3}$$

and similarly for all distinct pairs. The Paulis *commute* with themselves and *anticommute* with each other.

Worked Example 2.1: Verifying Pauli algebra

Let us verify $XZ = -ZX = iY$ directly using matrix multiplication:

$$XZ = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} = \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix},$$

$$ZX = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} = \begin{pmatrix} 0 & 1 \\ -1 & 0 \end{pmatrix},$$

so indeed $XZ = -ZX$. And:

$$iY = i \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix} = \begin{pmatrix} 0 & 1 \\ -1 & 0 \end{pmatrix} = ZX,$$

confirming $XZ = -ZX = iY$. □

2.3 Discretisation of Quantum Errors

This is one of the most important and surprising facts in quantum error correction.

Theorem 2.1 (Discretisation of Errors). *Any single-qubit error E can be written as a linear combination of Pauli operators:*

$$E = c_0 I + c_1 X + c_2 Y + c_3 Z, \quad c_i \in \mathbb{C}.$$

Consequently, if a quantum code can correct all single-qubit Pauli errors $\{I, X, Y, Z\}$, it can correct **any** single-qubit error.

Proof sketch. The four Pauli matrices form a basis for the vector space of 2×2 complex matrices (dimension 4 over $\mathbb{C}$, dimension 4 over $\mathbb{R}$ when restricted to Hermitian matrices). Any 2×2 matrix E can therefore be decomposed as stated. When the syndrome is measured, the measurement projects the error onto one of its Pauli components (by the postulates of quantum measurement). The remaining component is a pure Pauli error, which the code corrects. □

Intuition

Think of it like this: your code might only know how to handle three “standard” faults (call them X , Y , Z). When some exotic fault E happens, *the act of checking which standard fault occurred* forces the actual error to collapse into one of those standard faults. After the check, you have an ordinary fault you already know how to fix. This is the magic of quantum measurement used constructively.

Worked Example 2.2: Decomposing a rotation error

A common physical error is an **over-rotation**: the qubit rotates by θ about the X -axis instead of not rotating at all. The error operator is

$$E(\theta) = e^{-i\theta X/2} = \cos(\theta/2) I - i \sin(\theta/2) X.$$

This is already in Pauli form with $c_0 = \cos(\theta/2)$ and $c_1 = -i \sin(\theta/2)$.

For a small rotation $\theta = 0.1$ radians:

$$c_0 = \cos(0.05) \approx 0.9988, \quad c_1 = -i \sin(0.05) \approx -0.0500 i.$$

When the syndrome is measured, the error collapses to I (no error, probability $|c_0|^2 \approx 0.998$) or X (bit-flip, probability $|c_1|^2 \approx 0.0025$). A code that corrects X -errors handles *both outcomes* correctly.

2.4 Quantum Channels and Kraus Operators

A more general description of noise uses **quantum channels**:

$$\mathcal{E}(\rho) = \sum_i E_i \rho E_i^\dagger, \quad \sum_i E_i^\dagger E_i = I,$$

where $\{E_i\}$ are **Kraus operators**. Key examples:

Depolarising channel With probability $1-p$ nothing happens; otherwise a Pauli error X, Y, Z each occurs with probability $p/3$:

$$\mathcal{E}_{\text{dep}}(\rho) = (1-p)\rho + \frac{p}{3}(X\rho X + Y\rho Y + Z\rho Z).$$

Dephasing (phase-damping) channel Only Z -errors occur, with probability p :

$$\mathcal{E}_{\text{deph}}(\rho) = (1-p)\rho + p Z\rho Z.$$

Amplitude damping channel Models energy relaxation (T_1 decay), with Kraus operators:

$$K_0 = \begin{pmatrix} 1 & 0 \\ 0 & \sqrt{1-\gamma} \end{pmatrix}, \quad K_1 = \begin{pmatrix} 0 & \sqrt{\gamma} \\ 0 & 0 \end{pmatrix},$$

where $\gamma = 1 - e^{-t/T_1}$ is the decay probability.

Worked Example 2.3: Depolarising channel on $|+\rangle$

Let $|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$ so $\rho = |+\rangle\langle+| = \frac{1}{2} \begin{pmatrix} 1 & 1 \\ 1 & 1 \end{pmatrix}$.

Apply the depolarising channel with $p = 0.12$:

$$X\rho X = \frac{1}{2} \begin{pmatrix} 1 & 1 \\ 1 & 1 \end{pmatrix} = \rho \quad (|+\rangle \text{ is a } +1 \text{ eigenstate of } X),$$

$$Y\rho Y = \frac{1}{2} \begin{pmatrix} 1 & -1 \\ -1 & 1 \end{pmatrix} = |-\rangle\langle-|,$$

$$Z\rho Z = \frac{1}{2} \begin{pmatrix} 1 & -1 \\ -1 & 1 \end{pmatrix} = |-\rangle\langle-|.$$

Therefore:

$$\mathcal{E}(\rho) = 0.88\rho + 0.04\rho + 0.04|-\rangle\langle-| + 0.04|-\rangle\langle-| = 0.92\rho + 0.08|-\rangle\langle-|.$$

The off-diagonal coherences are reduced: the channel has partially *dephased* the state in the $\{|+\rangle, |-\rangle\}$ basis.

2.5 Multi-Qubit Pauli Group

For n qubits, single-qubit Pauli operators are combined by tensor products. Notation: $X_1 Z_3$ means $X \otimes I \otimes Z$ on qubits 1, 2, 3.

Definition 2.1 (n -qubit Pauli group). $\mathcal{P}_n$ consists of all n -fold tensor products of $\{I, X, Y, Z\}$ with overall phases $\{\pm 1, \pm i\}$:

$$\mathcal{P}_n = \{e^{i\phi} P_1 \otimes \cdots \otimes P_n \mid P_j \in \{I, X, Y, Z\}, \phi \in \{0, \frac{\pi}{2}, \pi, \frac{3\pi}{2}\}\}.$$

Its size is $|\mathcal{P}_n| = 4^{n+1}$.

Two n -qubit Paulis A and B either **commute** ($AB = BA$) or **anticommute** ($AB = -BA$). They anticommute if and only if they anticommute on an *odd* number of qubit positions.

Worked Example 2.4: Commutation in $\mathcal{P}_2$

Do $A = X_1 Z_2$ and $B = Z_1 X_2$ commute or anticommute?

At position 1: X and Z anticommute $\rightarrow$ contributes a sign -1 .

At position 2: Z and X anticommute $\rightarrow$ contributes a sign -1 .

Total sign: $(-1)(-1) = +1$. Therefore $AB = BA$: they **commute**.

Do $C = X_1 I_2$ and $D = Z_1 Z_2$ commute?

At position 1: X and Z anticommute $\rightarrow$ sign -1 .

At position 2: I and Z commute $\rightarrow$ sign $+1$.

Total sign: $(-1)(+1) = -1$. Therefore $CD = -DC$: they **anticommute**.

2.6 Error Propagation in Circuits

Errors in gates can *propagate* to other qubits:

- An X error on the *control* qubit of a CNOT propagates to both the control and target ($X_c \rightarrow X_c X_t$).
- A Z error on the *target* qubit of a CNOT propagates to both ($Z_t \rightarrow Z_c Z_t$).



Figure 2: Error propagation through CNOT: an X error on the control spreads to the target; a Z error on the target spreads to the control.

This motivates careful **fault-tolerant circuit design** covered in Section 8.

Exercise 2.1. Verify equation (2): compute YZ and ZX using matrix multiplication and confirm they equal iX and iY respectively.

Exercise 2.2. Show that the Pauli matrices $\{I, X, Y, Z\}$ form a basis for the space of 2×2 complex matrices. (Hint: show they are linearly independent and use a dimension argument.)

Exercise 2.3. For the depolarising channel $\mathcal{E}_{\text{dep}}$ with $p = 0.06$, compute $\mathcal{E}(|0\rangle\langle 0|)$. What is the probability of a bit-flip (X) error? Of a phase-flip (Z) error?

Exercise 2.4. Determine whether the following pairs of 2-qubit Pauli operators commute or anticommute: (a) $X_1 X_2$ and $Z_1 Z_2$; (b) $X_1 Z_2$ and $X_1 X_2$; (c) $Y_1 Y_2$ and $X_1 Z_2$.

Section Summary

Section 2 key points:

- The three Pauli operators $\{X, Y, Z\}$ describe all single-qubit errors; $\{I, X, Y, Z\}$ form a basis for 2×2 matrices.
- Any physical error can be decomposed in the Pauli basis; syndrome measurement collapses it to a single Pauli.

- Two n -qubit Paulis commute iff they anticommute on an even number of positions.
- Errors propagate through CNOT gates — a key concern for fault-tolerant design.

3 Classical and Quantum Repetition Codes

Intuition

The simplest way to protect a bit is to say it three times. If you tell three people “the answer is **0**” and one of them mishears it as “the answer is **1**”, the other two can overrule the mistake. This is a repetition code, and it is the starting point for understanding both classical and quantum error correction.

3.1 Classical 3-Bit Repetition Code

The classical 3-bit code is:

$$0 \longrightarrow 000, \quad 1 \longrightarrow 111.$$

Decoding by majority vote. If one bit flips, two of the three bits still agree, and majority voting recovers the original bit. If two or more bits flip, majority voting fails. Assuming each bit flips independently with probability p :

$$P(\text{logical error}) = \binom{3}{2}p^2(1-p) + \binom{3}{3}p^3 = 3p^2(1-p) + p^3 = 3p^2 - 2p^3.$$

For small p , $P(\text{logical error}) \approx 3p^2$, which is much smaller than the uncoded error rate p when $p \ll 1/3$.

Worked Example 3.1: Classical code improvement

For $p = 0.05$, the uncoded bit error rate is $0.05 = 5\%$. With the 3-bit repetition code:

$$P(\text{logical error}) = 3(0.05)^2 - 2(0.05)^3 = 3(0.0025) - 2(0.000125) \approx 0.00725 \approx 0.73\%.$$

A 7-fold improvement in error rate!

Syndrome table for the classical code. Rather than majority vote, we can identify the error from *parity checks*:

$$s_1 = \text{bit}_1 \oplus \text{bit}_2, \quad s_2 = \text{bit}_2 \oplus \text{bit}_3.$$

The syndrome (s_1, s_2) tells us exactly which bit (if any) flipped:

Received	Error	$s_1 = b_1 \oplus b_2$	$s_2 = b_2 \oplus b_3$
000 (or 111)	None	0	0
100 (or 011)	Flip bit 1	1	0
010 (or 101)	Flip bit 2	1	1
001 (or 110)	Flip bit 3	0	1

3.2 Quantum 3-Qubit Bit-Flip Code

We now lift this idea to the quantum world. The key difference is that we must protect a *superposition*:

$$|0\rangle_L = |000\rangle, \quad (4)$$

$$|1\rangle_L = |111\rangle, \quad (5)$$

$$|\psi_L\rangle = \alpha |000\rangle + \beta |111\rangle. \quad (6)$$

This is *not* three copies of $|\psi\rangle$ (which the no-cloning theorem forbids). It is an entangled superposition in which α and β live in the global correlations, not in any single qubit.

3.2.1 Encoding Circuit

Starting from $|\psi\rangle |0\rangle |0\rangle = (\alpha |0\rangle + \beta |1\rangle) |0\rangle |0\rangle$, two CNOT gates produce the encoded state:




Figure 3: Encoding circuit for the 3-qubit bit-flip code.

Trace through:

$$\begin{aligned} (\alpha |0\rangle + \beta |1\rangle) |00\rangle &\xrightarrow{\text{CNOT}_{1,2}} \alpha |000\rangle + \beta |110\rangle \\ &\xrightarrow{\text{CNOT}_{1,3}} \alpha |000\rangle + \beta |111\rangle. \checkmark \end{aligned}$$

3.2.2 Quantum Syndrome Measurement

We measure the **stabilizers** $g_1 = Z_1 Z_2$ and $g_2 = Z_2 Z_3$ using ancilla qubits. These operators measure the *parity* of pairs of data qubits without touching α or β .

Error	State after error	$g_1 = Z_1 Z_2$	$g_2 = Z_2 Z_3$	Correction
None	$\alpha 000\rangle + \beta 111\rangle$	+1	+1	None
X_1	$\alpha 100\rangle + \beta 011\rangle$	-1	+1	Apply X_1
X_2	$\alpha 010\rangle + \beta 101\rangle$	-1	-1	Apply X_2
X_3	$\alpha 001\rangle + \beta 110\rangle$	+1	-1	Apply X_3

Figure 4: Syndrome table for the 3-qubit bit-flip code. The syndrome (g_1, g_2) uniquely identifies single-qubit bit-flip errors. Crucially, α and β never appear in the syndrome.

Worked Example 3.2: Full syndrome computation for X_2

Suppose qubit 2 suffers a bit-flip. After encoding, the state is $\alpha |000\rangle + \beta |111\rangle$. The error X_2 (acting on qubit 2) gives:

$$\text{State after error: } X_2(\alpha |000\rangle + \beta |111\rangle) = \alpha |010\rangle + \beta |101\rangle.$$

Measuring $g_1 = Z_1Z_2$:

$$Z_1Z_2 |010\rangle = Z |0\rangle \otimes Z |1\rangle \otimes I |0\rangle = (+1)(-1) |010\rangle = - |010\rangle ,$$

$$Z_1Z_2 |101\rangle = Z |1\rangle \otimes Z |0\rangle \otimes I |1\rangle = (-1)(+1) |101\rangle = - |101\rangle .$$

Both terms give eigenvalue -1 , so the measurement outcome is $g_1 = -1$.

Measuring $g_2 = Z_2Z_3$:

$$Z_2Z_3 |010\rangle = Z |1\rangle \otimes Z |0\rangle = (-1)(+1) = -1,$$

$$Z_2Z_3 |101\rangle = Z |0\rangle \otimes Z |1\rangle = (+1)(-1) = -1.$$

The measurement outcome is $g_2 = -1$.

Syndrome: $(g_1, g_2) = (-1, -1)$. From the table, this corresponds to an X_2 error. We apply X_2 to correct:

$$X_2(\alpha |010\rangle + \beta |101\rangle) = \alpha |000\rangle + \beta |111\rangle . \checkmark$$

The encoded state is perfectly restored. Note that α and β were never measured and are unaffected.

3.2.3 Full Syndrome Circuit




Figure 5: Syndrome measurement circuit for the 3-qubit bit-flip code. Ancilla qubits measure Z_1Z_2 (giving s_1) and Z_2Z_3 (giving s_2) without disturbing $\alpha |000\rangle + \beta |111\rangle$.

3.3 Limitations: Phase Errors Are Not Corrected

The 3-qubit bit-flip code protects against X errors but is *blind* to Z errors.

Worked Example 3.3: Phase flip on qubit 1 is undetected

Suppose a phase-flip Z_1 occurs on the encoded state:

$$Z_1(\alpha |000\rangle + \beta |111\rangle) = \alpha |000\rangle - \beta |111\rangle .$$

Check the syndrome:

$$\begin{aligned} Z_1Z_2(\alpha |000\rangle - \beta |111\rangle) &= \alpha(+1)(+1) |000\rangle - \beta(-1)(-1) |111\rangle \\ &= \alpha |000\rangle - \beta |111\rangle , \quad g_1 = +1, \end{aligned}$$

$$Z_2Z_3(\alpha |000\rangle - \beta |111\rangle) = +\alpha |000\rangle - \beta |111\rangle , \quad g_2 = +1.$$

Syndrome $(+1, +1)$ says “no error” — but the logical state has been changed from $\alpha |0\rangle_L + \beta |1\rangle_L$ to $\alpha |0\rangle_L - \beta |1\rangle_L$. The error is *undetected*.

3.4 Quantum Phase-Flip Code

To correct phase errors, we move to the *Hadamard basis* $\{|+\rangle, |-\rangle\}$:

$$|+\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}}, \quad |-\rangle = \frac{|0\rangle - |1\rangle}{\sqrt{2}}.$$

In this basis, Z errors become X errors: $Z|+\rangle = |-\rangle$ and $Z|-\rangle = |+\rangle$.

Encode the logical qubit as:

$$|0\rangle_L = |+++ \rangle, \quad |1\rangle_L = |-- \rangle,$$

so $|\psi\rangle_L = \alpha|+++ \rangle + \beta|-- \rangle$.




Figure 6: Phase-flip code encoding: first encode with CNOTs (as in the bit-flip code), then apply Hadamard to each qubit.

The stabilizers are now X_1X_2 and X_2X_3 (parity in the Hadamard basis), detecting Z errors. The decoding applies $H^{\otimes 3}$ to convert back, then corrects as before.

Caution

The phase-flip code corrects Z errors only; the bit-flip code corrects X errors only. Neither code corrects both types simultaneously. For complete single-qubit error correction, we need a code that handles both — this is the **Shor 9-qubit code** (Section 4).

3.5 Why This Works Despite No-Cloning

A common confusion: if we cannot clone $|\psi\rangle$, how can we store it in three qubits? The key is that the encoded state $\alpha|000\rangle + \beta|111\rangle$ is *not* three copies of $|\psi\rangle$.

- Tracing out any one qubit of $\alpha|000\rangle + \beta|111\rangle$ gives a *mixed* state (not $|\psi\rangle$).
- The information about α and β is in the *correlations* between the three qubits, not in any single qubit.
- Syndrome measurement reveals only the *parity* of pairs, not α or β individually.

Exercise 3.1. Verify that the syndrome $(g_1, g_2) = (+1, -1)$ correctly identifies an X_3 error by carrying out the eigenvalue calculation explicitly.

Exercise 3.2. Show that the 3-qubit bit-flip code has *two* possible corrective operations for each non-trivial syndrome — for instance, when $(g_1, g_2) = (-1, +1)$ you might apply X_1 . Why does it not matter whether we apply X_1 or instead apply X_2X_3 (which has the same syndrome)? (*Hint*: what is the product $X_1 \cdot X_2X_3$ on the encoded subspace?)

Exercise 3.3. Derive the encoding circuit for the quantum phase-flip code by: (a) showing that $H|0\rangle = |+\rangle$ and $H|1\rangle = |-\rangle$; (b) tracing $|\psi\rangle|0\rangle|0\rangle$ through the CNOT+Hadamard circuit to confirm $|0\rangle_L = |+++ \rangle$ and $|1\rangle_L = |-- \rangle$.

Exercise 3.4. Why does the 3-qubit bit-flip code fail to correct a Y error on qubit 2? Find the syndrome and show that applying the “correction” actually introduces an additional error.

Section Summary

Section 3 key points:

- The quantum 3-qubit bit-flip code encodes $\alpha|0\rangle + \beta|1\rangle$ as $\alpha|000\rangle + \beta|111\rangle$. This is *not* cloning; α, β live in correlations.
- Syndrome measurement identifies which qubit was flipped without disturbing the logical information.
- This code protects against X errors *only*; it is blind to Z (phase) errors.
- The phase-flip code encodes in the Hadamard basis, protecting against Z errors only.
- A code that corrects both X and Z errors requires a new idea: the Shor code.

4 The Shor 9-Qubit Code

Intuition

The 3-qubit bit-flip code fixes X errors; the 3-qubit phase-flip code fixes Z errors. Shor's idea was beautifully simple: *concatenate* the two. First encode the logical qubit into three qubits using the phase-flip code. Then encode each of those three qubits into three more qubits using the bit-flip code. The result is a 9-qubit code that corrects any single-qubit error.

4.1 Encoding

The logical codewords are:

$$|0\rangle_L = \frac{1}{2\sqrt{2}}(|000\rangle + |111\rangle)^{\otimes 3}, \quad (7)$$

$$|1\rangle_L = \frac{1}{2\sqrt{2}}(|000\rangle - |111\rangle)^{\otimes 3}. \quad (8)$$

Written out:

$$|0\rangle_L = \frac{1}{2\sqrt{2}}(|000\rangle + |111\rangle)(|000\rangle + |111\rangle)(|000\rangle + |111\rangle),$$

$$|1\rangle_L = \frac{1}{2\sqrt{2}}(|000\rangle - |111\rangle)(|000\rangle - |111\rangle)(|000\rangle - |111\rangle).$$

4.1.1 Structure of the Encoding

Figure 7 shows the nested structure.




Figure 7: The nested structure of the Shor 9-qubit code. Three groups of three qubits each form a bit-flip code. Across the three groups, the overall structure forms a phase-flip code.

4.1.2 Encoding Circuit




Figure 8: Shor code encoding circuit (simplified). First two CNOTs copy the logical qubit to qubits 4 and 7 (phase-flip structure). Then Hadamards create superpositions. Finally CNOTs within each block of three create the bit-flip structure. Rows 2–3, 5–6, 8–9 receive the CNOT targets from their respective block leaders.

4.2 Stabilizer Generators

The Shor code is a stabilizer code (see Section 6). Its 8 independent generators are:

4.2.1 Bit-flip stabilizers (within each 3-qubit block)

$$g_1 = Z_1 Z_2, \quad g_2 = Z_2 Z_3, \quad g_3 = Z_4 Z_5, \quad g_4 = Z_5 Z_6, \quad g_5 = Z_7 Z_8, \quad g_6 = Z_8 Z_9.$$

Each $Z_i Z_j$ detects an X error on qubit i or j within its block (a “parity check” in the computational basis).

4.2.2 Phase-flip stabilizers (across blocks)

$$g_7 = X_1 X_2 X_3 X_4 X_5 X_6, \quad g_8 = X_1 X_2 X_3 X_7 X_8 X_9.$$

These 6-qubit operators detect relative phase errors *between* the three blocks.

Key Point

Eight generators for 9 qubits leave $2^{9-8} = 2$ code states — encoding exactly 1 logical qubit. All 8 generators commute pairwise (necessary for a valid stabilizer code).

4.3 Error Correction Capability

Worked Example 4.1: Correcting a bit-flip on qubit 5

Suppose X_5 occurs. State after error: $X_5 |\psi_L\rangle$ (some modified encoded state).

Bit-flip stabilizers for block 2:

$$g_3 = Z_4 Z_5 : \quad Z_4 \text{ commutes with } X_5, \quad Z_5 \text{ anticommutes with } X_5 \Rightarrow g_3 = -1.$$

$$g_4 = Z_5 Z_6 : \quad Z_5 \text{ anticommutes with } X_5, \quad Z_6 \text{ commutes} \Rightarrow g_4 = -1.$$

All other generators commute with X_5 (they act on different qubits or commute position-by-position), giving $+1$.

Syndrome: $g_3 = -1, g_4 = -1$, all others $= +1$. This uniquely identifies qubit 5 in block 2. Apply X_5 to correct.

Worked Example 4.2: Correcting a phase-flip on qubit 2

Suppose Z_2 occurs. We check the phase stabilizers:

Z_2 anticommutes with X_2 (a factor in both g_7 and g_8), so both g_7 and g_8 flip sign: $g_7 = -1$, $g_8 = -1$.

The bit-flip stabilizers $g_1 = Z_1Z_2$ and $g_2 = Z_2Z_3$: does Z_2 commute with Z_1Z_2 ? Yes: $Z_2 \cdot Z_1Z_2 = Z_1Z_2^2 = Z_1$, but since we are checking whether Z_2 commutes with g_1 as an *operator*, note that Z_2 and Z_j always commute (both are Z -type). So the bit-flip stabilizers all give $+1$.

Syndrome: $g_7 = g_8 = -1$, others $+1$. This indicates a phase flip in block 1 (blocks 1 and 2 relative to block 3). We apply a correction operator to fix the phase.

4.4 Correcting Arbitrary Single-Qubit Errors

Any single-qubit error $E = c_0I + c_1X + c_2Y + c_3Z$ on any one of the 9 qubits can be corrected:

1. I : trivial (no error).
2. X on qubit j : identified by bit-flip stabilizers of the block containing j .
3. Z on qubit j : identified by phase stabilizers g_7, g_8 (relative signs between blocks tell us which block, bit-flip stabilizers within the block locate the qubit).
4. $Y = iXZ$: produces both X - and Z -type syndrome outcomes simultaneously; both are corrected.

4.5 Logical Operators

The logical operators acting on the encoded qubit are:

$$\bar{X} = X_1X_2X_3X_4X_5X_6X_7X_8X_9 = X^{\otimes 9},$$

$$\bar{Z} = Z_1Z_2Z_3.$$

(Any $Z_jZ_kZ_l$ with one qubit from each block also works for $\bar{Z}$.)

Exercise 4.1. Verify that g_7 and g_8 commute. (*Hint:* they share 3 common X -positions; count how many positions they anticommute.)

Exercise 4.2. Show that $\bar{Z} = Z_1Z_2Z_3$ commutes with all 8 stabilizer generators but is not itself in the stabilizer group.

Exercise 4.3. Why does the Shor code use 9 qubits and not 7? Research (or argue from first principles) why the code distance must be at least 3 to correct any single-qubit error.

Section Summary

Section 4 key points:

- The Shor code combines a phase-flip code (3 blocks) with a bit-flip code (within each block) to correct any single-qubit error.
- It uses 9 physical qubits to encode 1 logical qubit.
- 8 stabilizer generators (6 ZZ -type, 2 $XXXXXX$ -type) produce 8 syndrome bits, uniquely identifying all single-qubit Pauli errors.
- Any continuous single-qubit error is corrected via discretisation.

5 The Steane $[[7, 1, 3]]$ Code

Intuition

The Shor code is a beautiful proof of concept, but it is rather wasteful: 9 physical qubits for 1 logical qubit. The Steane code achieves the same goal with only 7 qubits, using a deep connection between quantum codes and classical coding theory. The idea is to take a classical error-correcting code (the Hamming code) and “lift” it to the quantum world using a construction called CSS (Calderbank–Shor–Steane).

5.1 The Classical Hamming $[7, 4, 3]$ Code

The classical **Hamming code** $[7, 4, 3]$ encodes 4 data bits into 7 bits, correcting 1-bit errors. Its 3×7 parity-check matrix is:

$$H = \begin{pmatrix} 1 & 0 & 0 & 1 & 0 & 1 & 1 \\ 0 & 1 & 0 & 1 & 1 & 0 & 1 \\ 0 & 0 & 1 & 0 & 1 & 1 & 1 \end{pmatrix}.$$

- A codeword $\mathbf{c}$ satisfies $H\mathbf{c}^T = \mathbf{0}$ (all parities are even).
- The syndrome $H\mathbf{e}^T$ of an error $\mathbf{e}$ is the binary representation of the position of the flipped bit.
- Distance $d = 3$: any two codewords differ in at least 3 bits, so 1-bit errors can always be corrected.

Worked Example 5.1: Hamming code syndrome

Suppose we transmit the codeword $\mathbf{c} = (1, 0, 1, 0, 1, 0, 0)$ but receive $\mathbf{r} = (1, 0, \mathbf{0}, 0, 1, 0, 0)$ (bit 3 flipped). Compute the syndrome:

$$H\mathbf{r}^T = \begin{pmatrix} 1 \\ 0 \\ 0 \end{pmatrix} \cdot 1 + \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix} \cdot 0 \cdots = \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix},$$

which in binary is $(001)_2 = 3$. So bit position 3 was flipped. Correcting it recovers $\mathbf{c}$.

5.2 The CSS Construction

Definition 5.1 (CSS code). Given classical linear codes $C_1 \supseteq C_2$ with parity-check matrices H_1 and H_2 , the **CSS code** $\text{CSS}(C_1, C_2)$ is a quantum code with stabilizers:

- X -type: one $X^{\otimes \text{row}}$ generator per row of H_2 ,
- Z -type: one $Z^{\otimes \text{row}}$ generator per row of H_1 .

The construction is valid (all generators commute) if and only if $H_1 H_2^T = 0$ over $\mathbb{F}_2$.

5.3 Steane Code Construction

The Steane code uses the Hamming $[7, 4, 3]$ code with $H_1 = H_2 = H$. Crucially, $HH^T = 0 \pmod{2}$ (verify this!), so the CSS condition is satisfied.

5.3.1 Stabilizer Generators

Each row of H defines both an X -type and a Z -type stabilizer by placing X (or Z) on qubit j wherever the row has a 1:

Row 1: $(1, 0, 0, 1, 0, 1, 1)$ acts on qubits 1, 4, 6, 7.

Row 2: $(0, 1, 0, 1, 1, 0, 1)$ acts on qubits 2, 4, 5, 7.

Row 3: $(0, 0, 1, 0, 1, 1, 1)$ acts on qubits 3, 5, 6, 7.

This gives 6 generators in total:

$$\begin{aligned} g_1 &= X_1 X_4 X_6 X_7, & g_4 &= Z_1 Z_4 Z_6 Z_7, \\ g_2 &= X_2 X_4 X_5 X_7, & g_5 &= Z_2 Z_4 Z_5 Z_7, \\ g_3 &= X_3 X_5 X_6 X_7, & g_6 &= Z_3 Z_5 Z_6 Z_7. \end{aligned}$$

Key Point

For any CSS code, X -type and Z -type generators always commute: an X -type generator and a Z -type generator acting on the same qubits must anticommute on an *even* number of positions, because $H_1 H_2^T = 0$ means their supports overlap in an even number of positions.

5.3.2 Code Parameters

Parameter	Value	Meaning
n	7	physical qubits
k	1	logical qubits encoded ($= n - \text{number of generators} = 7 - 6$)
d	3	code distance (corrects $\lfloor (d-1)/2 \rfloor = 1$ error)

5.4 Logical Operators

$$\bar{X} = X_1 X_2 X_3 X_4 X_5 X_6 X_7 = X^{\otimes 7},$$

$$\bar{Z} = Z_1 Z_2 Z_3 Z_4 Z_5 Z_6 Z_7 = Z^{\otimes 7}.$$

These are the minimum-weight logical operators (weight 7, which equals the distance d — as expected).

5.5 Error Correction Procedure

Worked Example 5.2: Detecting a Z -error on qubit 3

Suppose Z_3 occurs. We check the X -type stabilizers:

$g_1 = X_1 X_4 X_6 X_7$: Z_3 does not act on qubits 1,4,6,7 $\Rightarrow$ commutes $\Rightarrow +1$.

$g_2 = X_2 X_4 X_5 X_7$: Z_3 not on these qubits $\Rightarrow +1$.

$g_3 = X_3 X_5 X_6 X_7$: Z_3 acts on qubit 3, Z anticommutes with $X \Rightarrow -1$.

The Z -type stabilizers all commute with Z_3 (same Pauli type), giving $+1$.

X -syndrome: $(g_1, g_2, g_3) = (+1, +1, -1)$. In binary $(0, 0, 1)$, which encodes the position $001_2 = 1...$ but we need to match the Hamming matrix convention. Row 3 of H is $(0, 0, 1, 0, 1, 1, 1)$, which has a 1 in position 3, confirming the error is on qubit 3. Apply Z_3 to correct.

5.6 Transversal Gates

A major advantage of the Steane code is its support for **transversal** gates — operations that apply identically to each physical qubit:

Logical gate	Physical implementation	Why it works
$\bar{H}$ (Hadamard)	$H^{\otimes 7}$	Steane code is self-dual ($H_X = H_Z$)
$\bar{S}$ (Phase gate)	$S^{\otimes 7}$	CSS structure preserved
$\overline{\text{CNOT}}$	$\text{CNOT}^{\otimes 7}$	Bitwise CNOT between two code blocks

These three gates generate the **Clifford group**, which is a rich but not universal gate set.

Caution

The T gate ($T = \text{diag}(1, e^{i\pi/4})$) is *not* transversal in the Steane code because $T^{\otimes 7}$ does not preserve the code space. Implementing a fault-tolerant T gate requires **magic state distillation** (Section 8.4). This is one of the main overhead costs of fault-tolerant quantum computation.

Exercise 5.1. Verify that $HH^T = 0 \pmod{2}$ for the Hamming matrix H given above. This is the CSS construction validity condition.

Exercise 5.2. Compute the Z -syndrome (outcomes of g_4, g_5, g_6) when an X -error occurs on qubit 5. Confirm it correctly identifies qubit 5.

Exercise 5.3. Explain why the Steane code needs only 7 qubits while the Shor code needs 9 to correct the same set of errors. What property of the Hamming code makes this possible?

Section Summary

Section 5 key points:

- The Steane code is a $[[7, 1, 3]]$ CSS code derived from the classical Hamming $[7, 4, 3]$ code.
- Its 6 stabilizer generators (3 X -type, 3 Z -type) come directly from the rows of the Hamming parity-check matrix.
- X -type and Z -type generators always commute in a CSS code.
- The code admits transversal Hadamard, Phase, and CNOT — the full Clifford group — but not the T gate.

6 The Stabilizer Formalism

Intuition

The 3-qubit, Shor, and Steane codes all share a common structure: there is a set of multi-qubit Pauli operators (the *stabilizers*) that all codewords satisfy simultaneously. Errors shift codewords out of this “eigenspace”, and measuring the stabilizers — without touching the logical information — tells you what went wrong. The stabilizer formalism is the mathematical framework that unifies all these examples and provides a systematic way to construct and analyse quantum codes.

6.1 The Pauli Group (Reminder)

The n -qubit Pauli group $\mathcal{P}_n$ was defined in Section 2. Its key properties:

- Every element squares to $\pm I$.
- Any two elements either commute or anticommute.
- Elements can be described efficiently: an n -qubit Pauli is specified by two n -bit strings (a, b) where $a_j = 1$ means X_j appears and $b_j = 1$ means Z_j appears (with $Y_j = iX_jZ_j$ when both are 1), plus a phase.

6.2 Definition of a Stabilizer Code

Definition 6.1 (Stabilizer group and code space). An abelian subgroup $S \leq \mathcal{P}_n$ not containing $-I$ is called a **stabilizer group**. The associated **code space** is the simultaneous $+1$ eigenspace:

$$\mathcal{C}(S) = \{ |\psi\rangle \in (\mathbb{C}^2)^{\otimes n} \mid s|\psi\rangle = +|\psi\rangle, \forall s \in S \}.$$

If S is generated by $n - k$ independent generators $\{g_1, \dots, g_{n-k}\}$, then $\dim \mathcal{C}(S) = 2^k$, encoding k logical qubits into n physical qubits.

Worked Example 6.1: Verifying the 3-qubit code space

The 3-qubit bit-flip code has stabilizer $S = \langle Z_1Z_2, Z_2Z_3 \rangle$. We check that $|000\rangle$ and $|111\rangle$ are in the code space:

$$\begin{aligned} Z_1Z_2|000\rangle &= (+1)(+1)|000\rangle = +|000\rangle, \checkmark \\ Z_2Z_3|000\rangle &= (+1)(+1)|000\rangle = +|000\rangle, \checkmark \\ Z_1Z_2|111\rangle &= (-1)(-1)|111\rangle = +|111\rangle, \checkmark \\ Z_2Z_3|111\rangle &= (-1)(-1)|111\rangle = +|111\rangle, \checkmark \end{aligned}$$

Any superposition $\alpha|000\rangle + \beta|111\rangle$ is therefore also in the code space. We have $n = 3$, 2 generators, so $k = 3 - 2 = 1$ logical qubit encoded. Correct!

6.3 Logical Operators

Definition 6.2 (Normaliser and logical operators). The **normaliser** of S in $\mathcal{P}_n$ is:

$$N(S) = \{P \in \mathcal{P}_n \mid PSP^{-1} = S\} = \{P \in \mathcal{P}_n \mid [P, s] = 0, \forall s \in S\}.$$

Logical operators are elements of $N(S) \setminus S$. They preserve the code space ($P\mathcal{C} = \mathcal{C}$) but act non-trivially on the encoded qubits.

- Logical $\bar{X}_i$ and $\bar{Z}_i$ for the i -th logical qubit satisfy the usual qubit algebra on $\mathcal{C}$.
- An element of $N(S) \setminus S$ is an **undetectable error**: it passes the syndrome check but changes the logical information. This is why it matters that the *code distance* $d = \min_{P \in N(S) \setminus S} \text{wt}(P)$ is large.

6.4 Syndrome Measurement in the Stabilizer Formalism

Setup. For each generator g_i , prepare an ancilla qubit in $|+\rangle = (|0\rangle + |1\rangle)/\sqrt{2}$, apply a controlled- g_i (with ancilla as control), then measure the ancilla in the X basis.

The measurement outcome $s_i \in \{+1, -1\}$ (equivalently $s_i \in \{0, 1\}$) satisfies:

$$s_i = \begin{cases} +1 & \text{if the error } E \text{ commutes with } g_i \\ -1 & \text{if the error } E \text{ anticommutes with } g_i \end{cases}$$

The full collection $(s_1, \dots, s_{n-k})$ is the **error syndrome**.

Worked Example 6.2: Complete syndrome calculation: Steane code, X_4 error

Consider the Steane code with generators as in Section 5. Suppose an X -error occurs on qubit 4.

We check each Z -type generator (they detect X -errors):

$$\begin{aligned} g_4 = Z_1 Z_4 Z_6 Z_7 : & \quad Z_4 \text{ anticommutes with } X_4 \Rightarrow s_4 = -1. \\ g_5 = Z_2 Z_4 Z_5 Z_7 : & \quad Z_4 \text{ anticommutes with } X_4 \Rightarrow s_5 = -1. \\ g_6 = Z_3 Z_5 Z_6 Z_7 : & \quad Z_3, Z_5, Z_6, Z_7 \text{ all commute with } X_4 \Rightarrow s_6 = +1. \end{aligned}$$

All X -type generators commute with X_4 (same Pauli type): $s_1 = s_2 = s_3 = +1$.

Syndrome:

$$(s_1, s_2, s_3, s_4, s_5, s_6) = (+1, +1, +1, -1, -1, +1).$$

The Z -syndrome in binary: $(s_4 - 1)/(-2), (s_5 - 1)/(-2), (s_6 - 1)/(-2) = (1, 1, 0) \rightarrow$ row pattern matching column 4 of H . This correctly identifies qubit 4. Apply X_4 to correct.

6.5 The Knill–Laflamme Error Correction Conditions

Theorem 6.1 (Knill–Laflamme conditions). *A code with code projector $\Pi = \sum_i |c_i\rangle\langle c_i|$ (sum over an orthonormal basis $\{|c_i\rangle\}$ for $\mathcal{C}$) can correct a set of errors $\{E_a\}$ if and only if:*

$$\langle c_i | E_a^\dagger E_b | c_j \rangle = \delta_{ij} \lambda_{ab}$$

for all i, j and all errors E_a, E_b in the correctable set. Equivalently: $\Pi E_a^\dagger E_b \Pi = \lambda_{ab} \Pi$.

- **Non-degenerate condition** ($i \neq j$): Different codewords lead to orthogonal error spaces. The syndrome measurement can distinguish them.
- **Degenerate condition** ($i = j$): The “size” of each error looks the same from inside the code space. This means no encoded information is leaked.
- **For stabilizer codes:** The conditions reduce to requiring that $E_a^\dagger E_b$ either lies in S (trivial, correctable) or has non-trivial syndrome (detectable).

Worked Example 6.3: KL conditions for the 3-qubit bit-flip code

The code space basis is $\{|0\rangle_L, |1\rangle_L\} = \{|000\rangle, |111\rangle\}$. Consider errors $\{I, X_1, X_2, X_3\}$. Check the KL condition for $E_a = X_1$, $E_b = X_2$:

$$E_a^\dagger E_b = X_1 X_2.$$

$$\begin{aligned}\langle 000 | X_1 X_2 | 000 \rangle &= \langle 000 | 110 \rangle = 0, \\ \langle 111 | X_1 X_2 | 111 \rangle &= \langle 111 | 001 \rangle = 0, \\ \langle 000 | X_1 X_2 | 111 \rangle &= \langle 000 | 001 \rangle = 0, \\ \langle 111 | X_1 X_2 | 000 \rangle &= \langle 111 | 110 \rangle = 0.\end{aligned}$$

So $\Pi X_1 X_2 \Pi = 0$, which satisfies the KL condition with $\lambda_{12} = 0$. (The two errors lead to orthogonal error spaces.)

6.6 Graphical Summary: Stabilizer Code Structure




Figure 9: Hierarchy of the Pauli group relative to the stabiliser S . Errors in $\mathcal{P}_n \setminus N(S)$ are detectable; errors in $N(S) \setminus S$ are logical operators (undetectable and harmful); errors in S act trivially.

Exercise 6.1. For the 3-qubit bit-flip code, show that $X_1 X_2 X_3 \in N(S) \setminus S$ and that it acts as the logical $\bar{X}$ operator.

Exercise 6.2. Verify the KL conditions for the 3-qubit bit-flip code for the pair $E_a = X_1$, $E_b = X_1$ (the “diagonal” case $a = b$).

Exercise 6.3. Show that the Steane code satisfies the KL conditions for single-qubit Z -errors by checking that $\Pi Z_i^\dagger Z_j \Pi = 0$ for $i \neq j$ and $\Pi Z_i^2 \Pi = \Pi$ for any qubit i .

Section Summary

Section 6 key points:

- A stabilizer code is defined by an abelian Pauli subgroup S ; the code space is the $+1$ eigenspace of all generators.

- n physical qubits, $n - k$ generators $\Rightarrow k$ logical qubits.
- Syndrome measurement projects errors onto Pauli components without disturbing logical information.
- KL conditions: a code corrects error set $\{E_a\}$ iff projected error products are proportional to the code projector.
- Undetectable errors $(N(S) \setminus S)$ act as logical operators; their minimum weight is the code distance d .

7 The Surface Code

Intuition

The surface code is the most promising candidate for practical quantum computers. Imagine a checkerboard. Data qubits sit on the *edges* of the board (the lines between squares). Two kinds of stabilizers sit on the squares themselves: “plaquette” stabilizers (on dark squares) measure Z parities and detect X errors; “vertex” stabilizers (on light squares) measure X parities and detect Z errors. An error creates a pair of “defects” on adjacent squares — like flipping two squares on the checkerboard — and correcting the error means pairing up defects and erasing them.

7.1 Lattice Structure

Consider a $d \times d$ square lattice where d is the **code distance**:

- **Data qubits** sit on the edges of the lattice (horizontal and vertical lines between vertices).
- **Z-stabilizers (plaquettes)**: Each interior face of the lattice has a 4-qubit Z stabilizer $Z_{e_1}Z_{e_2}Z_{e_3}Z_{e_4}$, where $e_1, \dots, e_4$ are the four edges bounding that face.
- **X-stabilizers (vertices)**: Each interior vertex has a 4-qubit X stabilizer $X_{e_1}X_{e_2}X_{e_3}X_{e_4}$, where the edges are the four incident edges.
- Boundary qubits participate in 2- or 3-qubit stabilizers.

7.1.1 Counting for a $d = 3$ Surface Code

For $d = 3$, the lattice has $d^2 + (d - 1)^2 = 9 + 4 = 13$ data qubits.




Figure 10: A $d = 3$ surface code lattice (schematic). Black dots are data qubits on edges. Blue squares are Z -stabilizer plaquettes; red regions are X -stabilizer vertices. This encodes 1 logical qubit in 13 data qubits with distance 3.

7.1.2 Code Parameters

For distance d :

$$\text{Data qubits: } n = d^2 + (d - 1)^2 = 2d^2 - 2d + 1 \quad (9)$$

$$\text{Z-stabilizers: } (d - 1)^2 + (d - 1) = d(d - 1) \quad (10)$$

$$\text{X-stabilizers: } d(d - 1) \quad (11)$$

$$\text{Logical qubits: } k = 1 \quad (\text{for planar surface code}) \quad (12)$$

$$\text{Code distance: } d \quad (\text{minimum weight logical operator}) \quad (13)$$

Worked Example 7.1: Parameters for $d = 5$

$$n = 2(25) - 10 + 1 = 41 \text{ data qubits.}$$

Number of Z -stabilizers: $5 \times 4 = 20$.

Number of X -stabilizers: $5 \times 4 = 20$.

Total stabilizer measurements: $20 + 20 = 40$.

Logical qubits: $41 - 40 = 1$. ✓

Code distance: $d = 5$, so we can correct up to $\lfloor (5 - 1)/2 \rfloor = 2$ errors.

7.2 Error Correction: Minimum-Weight Perfect Matching

How errors create syndromes. A chain of X -errors on a sequence of data qubits creates *defects* (syndrome -1 outcomes) at the *endpoints* of the chain.




Figure 11: A chain of X -errors (red dots) on three data qubits creates *defects* (orange stars) only at the endpoints. The MWPM algorithm pairs up defects and infers the most likely error chain.

Minimum-weight perfect matching (MWPM).

1. Measure all stabilizers; collect the positions of defects (-1 outcomes).
2. Defects come in pairs (by the topology of the lattice).
3. Find the **minimum-weight perfect matching** — pair up defects so that the total number of data qubits inferred to have errors is minimised (using the Blossom algorithm or similar).
4. Apply the inferred correction.

7.3 Fault-Tolerance Threshold

Theorem 7.1 (Surface code threshold). *For the surface code under depolarising noise with error rate p per gate:*

$$p_L \propto \left(\frac{p}{p_{\text{th}}} \right)^{\lfloor (d+1)/2 \rfloor},$$

where $p_{\text{th}} \approx 1\%$ for standard depolarising noise. The logical error rate decreases **exponentially** with code distance d provided $p < p_{\text{th}}$.

Worked Example 7.2: Logical error rate for $d = 5$

Take $p = 0.005$ (0.5%) and $p_{\text{th}} = 0.01$ (1%). Then $p/p_{\text{th}} = 0.5$ and:

$$p_L \propto (0.5)^{\lfloor 6/2 \rfloor} = (0.5)^3 = 0.125.$$

For $d = 7$: $p_L \propto (0.5)^4 = 0.0625$ — a factor 2 improvement per distance step. For $d = 11$: $(0.5)^6 \approx 0.016$. This shows why large distance (and thus many physical qubits) are needed

to reach extremely low logical error rates.

7.4 Logical Gates via Lattice Surgery

Direct transversal gates on the surface code are limited. Logical operations are instead performed by **lattice surgery**:

Logical CNOT: Merge two code patches (measuring joint stabilizers along the interface), perform joint measurements, then split.

Logical Hadamard: On the *rotated* surface code (a 45° -rotated lattice), $H^{\otimes n}$ implements $\bar{H}$.

Logical T gate: Requires magic state distillation (Section 8.4).




Figure 12: Lattice surgery for a logical CNOT. Two code patches are temporarily merged by measuring joint stabilizers on the interface, then split again. The net effect is a logical CNOT between qubits A and B .

7.5 Why the Surface Code is Practical

- **Local interactions only:** Each stabilizer involves at most 4 nearest-neighbour qubits — perfectly suited to 2D chip architectures (superconducting qubits, trapped ions arranged in a plane).
- **High threshold:** $p_{\text{th}} \approx 1\%$ is achievable with current hardware ($p \sim 0.1\text{--}0.5\%$).
- **Simple decoding:** MWPM is efficient (polynomial time).
- **Natural fault-tolerance:** Stabilizer measurement errors can be tracked across repeated measurement rounds.

Exercise 7.1. Calculate the number of data qubits, Z -stabilizers, X -stabilizers, and logical qubits for a $d = 7$ surface code. Verify $k = 1$.

Exercise 7.2. A chain of two X -errors occurs on adjacent data qubits in a $d = 3$ surface code. Draw the defect pattern and explain how MWPM would (correctly) decode this error. Now suppose three consecutive X -errors form a chain spanning the lattice. Why does this cause a logical error?

Exercise 7.3. Below the threshold, the logical error rate scales as $p_L \propto (p/p_{\text{th}})^{(d+1)/2}$. How large must d be to achieve $p_L < 10^{-10}$ if $p = 0.003$ and $p_{\text{th}} = 0.01$?

Section Summary

Section 7 key points:

- The surface code places data qubits on lattice edges; Z (plaquette) and X (vertex) stabilizers detect bit- and phase-flip errors.
- A $d = d$ surface code uses $2d^2 - 2d + 1$ qubits, has distance d , and encodes 1 logical qubit.
- Errors create defect pairs; MWPM corrects by pairing defects optimally.
- Threshold $p_{\text{th}} \approx 1\%$; logical error rate drops exponentially with d below threshold.
- Logical gates via lattice surgery; T gate still requires magic state distillation.

8 Fault-Tolerant Quantum Gates

Intuition

Encoding qubits protects stored information, but we also need to *compute* on it. A gate performed directly on physical qubits might spread a single error into many errors — too many for the code to correct. Fault-tolerant gate design is the art of performing logical operations in a way that guarantees a single physical fault produces at most one logical fault.

8.1 Why Naive Gate Application Fails

Consider applying a transversal CNOT to the 3-qubit bit-flip code. A single fault in the gate could spread to affect multiple qubits. Suppose the second CNOT gate has an X error on its control:




Figure 13: A single error on the first gate in the encoding circuit propagates to affect all subsequent qubits. This “error spreading” is the key danger that fault-tolerant design must prevent.

8.2 Transversal Gates

Definition 8.1 (Transversal gate). A gate U_L is **transversal** if it can be written as $U_L = u^{\otimes n}$ (same single-qubit operation on every physical qubit, possibly with qubit permutations between code blocks).

A transversal gate is automatically fault-tolerant: a fault on physical qubit j affects only qubit j in the encoded block — it cannot spread to other qubits.

Code	Transversal gates	Missing gates
3-qubit bit-flip	$\bar{X}, \bar{Z}$	Phase, T , Hadamard
Steane $[[7, 1, 3]]$	$\bar{H}, \bar{S}, \bar{\text{CNOT}}$ (Clifford group)	T gate
Surface code	$\bar{H}$ (rotated), $\bar{\text{CNOT}}$ via surgery	T gate

Theorem 8.1 (Eastin–Knill theorem). *No quantum error-correcting code can have a transversal implementation of a **universal** gate set.*

This means every code must use some non-transversal technique for at least one gate. The T gate ($\pi/8$ gate) is the standard choice.

8.3 Fault-Tolerant Syndrome Measurement

Measuring a multi-qubit stabilizer like $Z_1 Z_2 Z_3 Z_4$ requires ancilla qubits. A naive circuit might look like:




Figure 14: Standard ancilla-based syndrome measurement for the $Z_1Z_2Z_3Z_4$ stabilizer. The ancilla records the parity of the four data qubits. One fault in this circuit can propagate to multiple data qubits.

Caution

A single fault in the ancilla preparation or the CNOT gates can spread to multiple data qubits. For example, an X error on the ancilla before any CNOT will propagate a Z error to *every* data qubit it interacts with (since Z errors on the target propagate to the control). This can defeat the code's error-correcting power. The solution is to use **flag qubits** or **cat states** to detect such spreading.

8.3.1 Repeated Measurement

Even with perfect gates, measurement outcomes themselves are noisy. The standard approach is to repeat stabilizer measurements (typically 3 times for a distance-3 code) and use the majority outcome or track the syndrome history. For the surface code, syndrome measurements are repeated $O(d)$ times to reliably decode.

8.4 Magic State Distillation

8.4.1 Why We Need Magic States

We need a universal gate set. The Clifford gates (which include H , S , CNOT) are transversal in many codes, but they are *not* universal: any circuit built from Clifford gates alone can be simulated classically in polynomial time (Gottesman–Knill theorem).

To achieve universality, we add the T gate:

$$T = \begin{pmatrix} 1 & 0 \\ 0 & e^{i\pi/4} \end{pmatrix}.$$

The Clifford group plus T is universal. However, T is not transversal in standard codes.

8.4.2 The Magic State Idea

The T gate can be implemented by **gate teleportation** if we have access to the **magic state**:

$$|T\rangle = T|+\rangle = \frac{|0\rangle + e^{i\pi/4}|1\rangle}{\sqrt{2}}.$$

The teleportation circuit uses only Clifford gates plus a measurement:




Figure 15: Gate teleportation implementing the T gate. Given one copy of the magic state $|T\rangle$, a Clifford correction S^m (where $m \in \{0, 1\}$ is the measurement result) yields $T|\psi\rangle$ using only Clifford gates.

8.4.3 Distillation Protocol

Physical T gates are noisy; the resulting states are close to (but not exactly) $|T\rangle$. The **15-to-1 distillation protocol** (Bravyi–Kitaev) takes 15 noisy magic states and produces 1 high-fidelity magic state:

- Input: 15 noisy $|T\rangle$ states, each with error probability ϵ .
- Output: 1 magic state with error probability $\approx 35\epsilon^3$ (superquadratic suppression).
- Circuit: uses only Clifford gates (which are fault-tolerant transversally) to distil the high-quality state.

Worked Example 8.1: Distillation improvement

If the physical T gate has error rate $\epsilon = 0.01$:

$$\text{After 1 round: } \epsilon_1 \approx 35(0.01)^3 = 35 \times 10^{-6} = 3.5 \times 10^{-5}.$$

$$\text{After 2 rounds: } \epsilon_2 \approx 35(3.5 \times 10^{-5})^3 \approx 1.5 \times 10^{-12}.$$

Two rounds of 15-to-1 distillation reduce the error from 1% to below 10^{-12} at the cost of $15^2 = 225$ initial magic states.

8.5 The Threshold Theorem

Theorem 8.2 (Fault-Tolerant Threshold Theorem). *Suppose each physical gate, preparation, and measurement has error rate p , and errors are local (independent across qubits). There exists a threshold $p_{\text{th}} > 0$ such that: if $p < p_{\text{th}}$, arbitrarily long quantum computations can be performed with failure probability approaching 0. The qubit overhead scales as $\text{poly}(\log(1/\epsilon))$ for target error ϵ .*

- For the surface code: $p_{\text{th}} \approx 1\%$ (depolarising noise).
- For concatenated codes (Section 9): $p_{\text{th}} \approx 10^{-4}$ to 10^{-3} .
- The surface code's higher threshold is a major reason it is the leading practical candidate.

8.5.1 Below vs. Above Threshold




Figure 16: Below the threshold (blue), increasing code distance decreases the logical error rate exponentially. Above the threshold (red), adding more qubits makes things worse because there are too many opportunities for error.

Exercise 8.1. For a $d = 7$ surface code with $p = 0.004$ and $p_{\text{th}} = 0.01$, estimate the logical error rate as a multiple of $(p/p_{\text{th}})^{\lfloor (d+1)/2 \rfloor}$.

Exercise 8.2. Using the gate teleportation circuit of Figure 15, verify that measuring the ancilla in state $|1\rangle$ (outcome $m = 1$) and then applying S to the data qubit produces $T|\psi\rangle$. (*Hint:* work through the action of the CNOT on $|\psi\rangle|T\rangle$, then project onto $m = 0$ and $m = 1$ separately.)

Exercise 8.3. After three levels of 15-to-1 distillation starting from $\epsilon = 0.005$, what is the estimated output magic state error rate? How many physical T -gate preparations does this require?

Section Summary

Section 8 key points:

- Transversal gates prevent error spreading; the Eastin–Knill theorem says no code has a universal transversal gate set.
- Syndrome measurement circuits must be designed carefully to avoid fault propagation; repeated measurement is needed.
- The T gate is implemented via gate teleportation using magic states.
- Magic state distillation (15-to-1 protocol) converts many noisy $|T\rangle$ states into one high-fidelity one.
- The threshold theorem guarantees scalable quantum computation when physical error rates are below p_{th} .

9 Advanced Topics in Quantum Error Correction

Intuition

The surface code is excellent but has one major weakness: it encodes only 1 logical qubit no matter how many physical qubits you use. For a practical quantum computer running a million-gate algorithm, you might need thousands of logical qubits, requiring millions of physical qubits. This section surveys alternative codes that offer better rates (more logical qubits per physical qubit), higher thresholds, or additional transversal gates.

9.1 Quantum Low-Density Parity-Check (LDPC) Codes

Classical LDPC codes are a major tool in classical communications (used in 5G, WiFi, etc.). Each parity-check involves few bits (**sparse**) and each bit appears in few checks — hence “low density”.

Quantum LDPC codes generalise this to the stabilizer setting:

- Each stabilizer generator involves at most w qubits (for some constant w , e.g. $w = 6$).
- Each qubit appears in at most w generators.
- Result: sparse syndrome measurement circuits, fewer gates per round.

9.1.1 Recent Breakthrough: Good Quantum LDPC Codes

Code family	Rate k/n	Distance d	Stabilizer weight
Surface code	$\Theta(1/n)$	$\Theta(\sqrt{n})$	4
Hypergraph product	Constant	$\Theta(\sqrt{n})$	$O(1)$
Lifted product (Panteleev–Kalachev 2022)	Constant	$\Theta(n)$	$O(1)$
Fiber bundle codes	Constant	$\Theta(n^{3/5})$	$O(1)$

A code with *constant rate* and *linear distance* ($d = \Theta(n)$) is called a **good quantum LDPC code**. These were only proved to exist in 2022, representing a major theoretical advance.

9.1.2 Practical Challenges

Despite better parameters, quantum LDPC codes face challenges:

- Generators can involve non-local (long-range) qubit pairs — hard to implement in 2D architectures.
- Efficient decoders are still being developed.
- Threshold values and exact overheads are not yet as well understood as for the surface code.

9.2 Color Codes

Color codes are topological codes defined on 3-colorable lattices.

9.2.1 2D Color Code Construction

Consider a 2D lattice where every face can be colored red, green, or blue, and every vertex touches exactly one face of each color. Data qubits sit on the vertices.




Figure 17: A small portion of a 2D color code lattice. Each colored face contributes both an X -type and a Z -type stabilizer on its vertices. The 3-colorability allows fault-tolerant gates beyond those of the surface code.

For each colored face f , there is an X -stabilizer and a Z -stabilizer on the vertices of f . The code is a $[[n, 1, d]]$ code similar to the surface code.

9.2.2 Advantages of Color Codes

- The 2D color code has the same parameters as the surface code ($d = \Theta(\sqrt{n})$, rate $1/n$) but admits **transversal** H , S , CNOT, and T in some 3D variants.
- In 3D color codes, the full Clifford+ T gate set is transversal, eliminating the need for magic state distillation — though at the cost of a 3D qubit architecture.
- Syndrome extraction is slightly more complex than for the surface code.

9.3 Concatenated Codes

Definition 9.1 (Code concatenation). Given an “outer” code $C_1 = [[n_1, k_1, d_1]]$ and an “inner” code $C_2 = [[n_2, k_2, d_2]]$ with $k_2 = k_1$, the **concatenated code** $C_1 \circ C_2$ encodes each physical qubit of C_1 using the inner code C_2 . The result is a $[[n_1 n_2, k_1, d_1 d_2]]$ code.

Worked Example 9.1: Concatenating two Steane codes

Let both C_1 and C_2 be the Steane $[[7, 1, 3]]$ code. The concatenated code $C_1 \circ C_2$ has:

$$\begin{aligned} n &= 7 \times 7 = 49 \text{ physical qubits,} \\ k &= 1 \text{ logical qubit,} \\ d &= 3 \times 3 = 9. \end{aligned}$$

After ℓ levels of concatenation:

$$n_\ell = 7^\ell, \quad d_\ell = 3^\ell, \quad k = 1.$$

Logical error rate under concatenation: Let p be the physical error rate. After ℓ levels:

$$p_L^{(\ell)} \approx \frac{1}{c} (cp)^{2^\ell},$$

where c is a constant depending on the code (for Steane, $c \approx 1/p_{\text{th}}$). For $p = 0.001$ and $c = 100$:

$$\begin{aligned} \ell = 1 : \quad p_L &\approx (0.1)^2 = 0.01. \\ \ell = 2 : \quad p_L &\approx (0.1)^4 = 10^{-4}. \\ \ell = 3 : \quad p_L &\approx (0.1)^8 = 10^{-8}. \end{aligned}$$

Exponential suppression, but at the cost of $7^3 = 343$ physical qubits per logical qubit at level 3.

9.4 Comparison of QEC Code Families

Code	Rate	Distance	Transversal gates	Architecture
Surface	$\Theta(1/n)$	$\Theta(\sqrt{n})$	Clifford (partial)	2D local
Color (2D)	$\Theta(1/n)$	$\Theta(\sqrt{n})$	Full Clifford	2D local
Color (3D)	$\Theta(1/n)$	$\Theta(n^{1/3})$	Clifford + T	3D local
Quantum LDPC	Constant	up to $\Theta(n)$	Limited	Non-local
Concatenated	Variable	Exponential	Depends	Non-local

Exercise 9.1. After 4 levels of concatenation with a $[[7, 1, 3]]$ code, how many physical qubits encode 1 logical qubit? What is the code distance?

Exercise 9.2. Explain why quantum LDPC codes with constant rate are important for practical quantum computation. What obstacles prevent their immediate use?

Exercise 9.3. A 2D color code and a surface code of the same physical qubit count n both have distance $\Theta(\sqrt{n})$. List two advantages of the color code and one advantage of the surface code.

Section Summary

Section 9 key points:

- Quantum LDPC codes offer constant rate (many logical qubits per physical qubit) with sparse stabilizers; recent breakthroughs achieve linear distance.
- Color codes are topological codes on 3-colorable lattices; 3D variants allow transversal T gates.
- Concatenated codes reduce logical error rates doubly-exponentially in the number of concatenation levels, at exponential qubit cost.
- No single code is optimal for all metrics; the choice depends on hardware architecture, target error rate, and gate set requirements.

10 Summary and Putting It All Together

This section brings together all the major themes of the course.

10.1 The Big Picture

Quantum error correction solves the fundamental problem of quantum computation: qubits decohere and gates are imperfect. The key ideas, in order of development, are:

1. **Errors are continuous, but correctable discretely.** Any single-qubit error decomposes into Pauli operators; syndrome measurement projects errors onto discrete Pauli faults.
2. **Entanglement protects information.** Encoding in entangled states spreads information holographically across many qubits. No individual qubit holds the secret.
3. **Syndromes are the key.** Measuring stabilizers reveals errors without collapsing the logical superposition. This is the central miracle of QEC.
4. **Fault-tolerance requires more than encoding.** Gates, measurements, and state preparations must all be performed in ways that prevent single faults from cascading.
5. **The threshold theorem gives hope.** Provided physical error rates are below $\sim 1\%$, reliable large-scale quantum computation is in principle possible.

10.2 Quick Reference: All Codes Covered

Code	n	k	d	What it corrects
3-qubit bit-flip	3	1	1	Single X error
3-qubit phase-flip	3	1	1	Single Z error
Shor 9-qubit	9	1	3	Any single-qubit error
Steane $[[7, 1, 3]]$	7	1	3	Any single-qubit error
Surface code ($d = 5$)	41	1	5	Any 2-qubit error

10.3 Road Map Through the Material




Figure 18: The logical dependency structure of these lecture notes. Each section builds on the previous; Sections 4 and 5 are parallel examples that Section 6 unifies.

10.4 Comprehensive Exercises

These exercises require combining knowledge from multiple sections.

Exercise 10.1. [Full worked pipeline.] A logical qubit is encoded in the 3-qubit bit-flip code.

(a) Write the encoded state for $|\psi\rangle = \frac{1}{\sqrt{3}}|0\rangle + \sqrt{\frac{2}{3}}|1\rangle$. (b) Suppose a $Y_2 = iX_2Z_2$ error occurs. Compute the syndrome. (c) Apply the corrective operation and verify the state is restored.

Exercise 10.2. [KL conditions.] Prove that the Shor code satisfies the KL conditions for the error pair $E_a = Z_1$ (phase flip on qubit 1) and $E_b = Z_4$ (phase flip on qubit 4).

Exercise 10.3. [Code comparison.] For a quantum computer needing $p_L = 10^{-12}$ per logical gate with physical error rate $p = 0.001$: (a) How large must d be for the surface code? (b) How many levels of Steane code concatenation achieve this? (c) Which uses fewer physical qubits?

Exercise 10.4. [Steane code X -syndrome.] Suppose Z -errors occur on qubits 2 and 6 simultaneously in the Steane code. Compute the full X -syndrome and determine whether both errors can be identified and corrected. (*Hint:* Check whether the combined syndrome is the XOR of the individual syndromes.)

Exercise 10.5. [Surface code threshold.] A surface code operates at $p = 0.008$ with $p_{\text{th}} = 0.01$. At what code distance d does the logical error rate first drop below 10^{-6} ? How many physical qubits does this require?

Exercise 10.6. [Magic state overhead.] A quantum algorithm requires 10^6 T -gate applications. Using the 15-to-1 distillation protocol with two rounds of distillation, and assuming each logical Clifford gate consumes one magic state, how many physical T -gate preparations are needed in total?

Exercise 10.7. [Error channel.] A qubit undergoes a dephasing channel with $p = 0.1$, followed by a bit-flip channel with $q = 0.05$. Write the combined error channel as a sum of Kraus operators and identify the probabilities of each Pauli error.

Exercise 10.8. [Stabilizer design.] Design a simple 5-qubit code (the “perfect code” $[[5, 1, 3]]$) with stabilizers $\{XZZXI, IXZZX, XIXZZ, ZXIXZ\}$ (where we write operators on 5 qubits without tensor product symbols for brevity). (a) Verify that all four generators commute. (b) Show that the code encodes 1 logical qubit. (c) Show that it has distance 3.

Exercise 10.9. [Discretisation revisited.] A qubit suffers a general unitary error $U = \cos \theta I + i \sin \theta Z$ for $\theta = \pi/6$. The qubit is protected by the 3-qubit phase-flip code. (a) Decompose U in the Pauli basis. (b) After syndrome measurement, what is the probability that no correction is needed? That a correction is applied? (c) Verify that the final state is correct in both cases.

References

- [1] Nielsen, M. A. & Chuang, I. L. (2010). *Quantum Computation and Quantum Information: 10th Anniversary Edition*. Cambridge University Press. *The standard reference. Chapters 10–11 cover QEC and fault tolerance.*
- [2] Shor, P. W. (1995). Scheme for reducing decoherence in quantum computer memory. *Physical Review A*, 52(4), R2493. *The original 9-qubit code paper.*
- [3] Steane, A. M. (1996). Error correcting codes in quantum theory. *Physical Review Letters*, 77(5), 793. *The $[[7, 1, 3]]$ CSS code.*
- [4] Knill, E. & Laflamme, R. (1997). Theory of quantum error-correcting codes. *Physical Review A*, 55(2), 900. *The Knill–Laflamme error correction conditions.*
- [5] Kitaev, A. Y. (1997). Quantum computations: algorithms and error correction. *Russian Mathematical Surveys*, 52(6), 1191. *The original surface/toric code paper.*
- [6] Fowler, A. G., Mariantoni, M., Martinis, J. M., & Cleland, A. N. (2012). Surface codes: Towards practical large-scale quantum computation. *Physical Review A*, 86(3), 032324. *Comprehensive surface code reference.*
- [7] Bravyi, S. & Kitaev, A. (2005). Universal quantum computation with ideal Clifford gates and noisy ancillas. *Physical Review A*, 71(2), 022316. *The 15-to-1 magic state distillation protocol.*
- [8] Panteleev, P. & Kalachev, G. (2022). Asymptotically good quantum and locally testable classical LDPC codes. *Proc. 54th ACM STOC*, 375–388. *Breakthrough result on good quantum LDPC codes.*
- [9] Gottesman, D. (2009). *An introduction to quantum error correction and fault-tolerant quantum computation*. arXiv:0904.2557. *Excellent lecture notes covering stabilizer codes and fault tolerance. Freely available.*

Glossary of Key Terms

Ancilla qubit

A helper qubit used to measure stabilizers without disturbing the data qubits. Prepared in a known state ($|0\rangle$ or $|+\rangle$), coupled to data, then measured.

Code distance d

The minimum weight (number of non-identity Paulis) of any logical operator. A code of distance d corrects $\lfloor (d-1)/2 \rfloor$ errors.

CSS code

A code constructed from two classical codes $C_1 \supseteq C_2$ with X -stabilizers from C_2 and Z -stabilizers from C_1 . Guarantees X and Z generators commute.

Decoherence

The loss of quantum coherence (superposition) due to entanglement with the environment. Characterised by times T_1 (energy relaxation) and T_2 (dephasing).

Fault-tolerant gate

A gate implementation in which a single physical fault creates at most one logical fault.

Logical operator

A Pauli operator that preserves the code space ($P \in N(S) \setminus S$) but acts non-trivially on the encoded qubit.

Magic state

A non-stabilizer state $|T\rangle = (|0\rangle + e^{i\pi/4}|1\rangle)/\sqrt{2}$ used via gate teleportation to implement the T gate.

No-cloning theorem

It is impossible to copy an arbitrary unknown quantum state unitarily. Prevents direct repetition coding of qubits.

Stabilizer

A Pauli operator g that fixes all codewords: $g|\psi\rangle = |\psi\rangle$. Equivalently, a $+1$ eigenstate condition.

Syndrome

The pattern of ± 1 eigenvalues obtained by measuring all stabilizer generators. Uniquely identifies correctable errors.

Threshold p_{th}

The maximum physical error rate below which increasing the code distance reduces the logical error rate. Approximately 1% for the surface code.

Transversal gate

A logical gate implemented by applying the same single-qubit operation independently to each physical qubit. Automatically fault-tolerant.