Exploring the Trade-offs Between Audio Fidelity and Computational Efficiency in a Custom Real-Time Browser-Based Synthesizer

Tim Fan (SID: 550790019)
repo: https://github.com/fanchenhao2206/elec5305-project-550790019

How do different oscillator anti-aliasing techniques and digital filter architectures influence the relationship between audio fidelity and computational efficiency in real-time browser-based synthesis?

I. Literature Review

Digital signal processing (DSP) refers to the manipulation of signals represented in discrete form, such as those stored or processed by computers. In computer music, DSP provides the theoretical and practical foundation for digitally modelling and recreating the behaviour of analog audio systems, including oscillators and filters. However, accurately translating analog oscillators and filters into the digital domain presents several technical challenges. Specifically, the choice of oscillator anti-aliasing techniques and digital filter architectures introduces different considerations that influence the accuracy, stability, and computational efficiency of the resulting audio. These considerations become particularly important in real-time browser-based synthesis, where audio fidelity must be balanced against computational constraints.

This section examines these challenges through a review of existing literature, focusing on the methods or approaches used or proposed to address them.

A. Digital Oscillators

Analog oscillators generate the fundamental voltage signals used in analog synthesisers, while digital oscillators aim to reproduce equivalent waveforms in the discrete-time domain. Common waveforms include the sine, sawtooth, square and triangle waves, each with distinct harmonic characteristics that contribute to its perceived timbre.

A naive digital oscillator generates waveforms directly from mathematical functions or phase-based calculations. A sawtooth, for example, can be produced with a phase accumulator, which advances its phase on every sample by an amount determined by the oscillator frequency and the sample rate. The phase is mapped to an amplitude range and, once it reaches its maximum, wraps back to the minimum, producing the characteristic sawtooth shape. This abrupt jump is known as a *discontinuity*, and it introduces infinitely many high-frequency harmonics. The Nyquist–Shannon sampling theorem states that a signal can only be represented accurately if it contains no components above the Nyquist frequency, which is half the sampling frequency. A sawtooth always contains harmonics above this limit, so they cannot be represented and instead fold back into the audible range as inharmonic distortion known as aliasing.

The problem worsens as the fundamental frequency rises. This applies to any waveform with discontinuities, such as the sawtooth and also the square wave, because a greater proportion of their harmonics then lies above the Nyquist frequency.

B. Anti-Aliasing Techniques

Anti-aliasing refers to techniques that reduce the effect of aliasing. One approach is the Band-Limited Step (BLEP) method. The idea is to replace the abrupt discontinuity in the naive waveform with a band-limited approximation, which reduces the high-frequency content introduced by the discontinuity and so improves the accuracy of the eventual reconstruction.

An ideal step is the integral of an impulse, and an ideal band-limited step is therefore the integral of a band-limited impulse, typically a windowed sinc function[1]. Rather than synthesising the entire waveform from band-limited components, the BLEP method computes only the *residual*—the difference between the band-limited step and the naive (non-band-limited) step—and applies it as a correction to the naive waveform in the immediate vicinity of each discontinuity, reducing the effect of aliasing.

A widely used variant is the polynomial BLEP (PolyBLEP), which approximates the residual with a low-order polynomial instead of a table of sinc-derived values[2]. For a normalised phase $t \in [0, 1)$ and a per-sample phase increment $\Delta t = f_0/f_s$, where f_0 is the oscillator frequency and f_s the sampling frequency, a two-sample PolyBLEP residual is given by

$$r(t) = \begin{cases} 2\dfrac{t}{\Delta t} - \left(\dfrac{t}{\Delta t}\right)^2 - 1, & 0 \le t < \Delta t, \\ \left(\dfrac{t-1}{\Delta t}\right)^2 + 2\dfrac{t-1}{\Delta t} + 1, & 1 - \Delta t < t < 1, \\ 0, & \text{otherwise.} \end{cases} \tag{1}$$

The corrected sawtooth is then obtained by subtracting this residual from the ideal but naive sawtooth waveform $s(t)$, also smoothing the wrap-around over the samples adjacent to the discontinuity. The naive sawtooth wave is chosen to be $s(t) = 2t - 1$ for simplicity of residual calculation and thus

implementation of PolyBLEP, because it reaches its minimal extreme of $s(t) = -1$ at $t = 0$, and the maximum extreme of $s(t) = 1$ at $t = 1$; the discontinuities exist at integer intervals.

A square wave may be treated as the sum of two sawtooth-like discontinuities, one rising and one falling, so the same residual is applied at both transitions (with opposite sign). A triangle wave, being continuous, has no step discontinuities, but its first derivative is discontinuous; the slope discontinuity can be corrected with an analogous polynomial band-limited ramp (PolyBLAMP) residual[3]

The principal advantages of PolyBLEP and PolyBLAMP are their low computational cost, the lack of lookup tables, and suitability for real-time use with modulated frequency, since the correction depends only on the current phase and phase increment. Its limitation is that a low-order polynomial only approximates the ideal band-limited step, so some residual aliasing remains, particularly at high fundamental frequencies, where it is attenuated rather than eliminated.

Alternative approaches offer different trade-offs. Oversampling reduces aliasing by generating waveforms at higher sampling rates before filtering and decimation, but increases computational cost [4]. Wavetable synthesis uses precomputed band-limited waveforms to suppress harmonics above the Nyquist frequency, but requires additional memory and table selection, reducing flexibility especially during dynamic modulation[5].

II. Methods

hello world

III. Results

hello world

IV. Discussion

hello world

V. Conclusion

Hello world

References

[1] E. Brandt, "Hard sync without aliasing," *Proceedings of the International Computer Music Conference, Havana, Cuba*, 2001.

[2] V. Välimäki, "Perceptually informed synthesis of bandlimited classical waveforms using integrated polynomial interpolation," *The Journal of the Acoustical Society of America*, vol. 131, pp. 974–986, 2001.

[3] F. Esqueda, "Aliasing reduction in soft-clipping algorithms," *European Signal Processing Conference, Nice, France*, 2015.

[4] "Oversampling for nonlinear waveshaping: Choosing the right filters," *Journal of the Audio Engineering Society*, vol. 67, pp. 440–449, 2019.

[5] "Higher-order integrated wavetable synthesis," *Proceedings of the 15th International Conference on Digital Audio EFfects (DAFx-12), York, UK*, 2012.