

SPEAR3 RF System

RF Physics, Control Theory and Physical Plant

Document ID	Doc P
Revision	R0
Status	Draft
Author	Faya Wang
Reviewer	Jim Sebek and others
Classification	Tier 1 — Physics and Plant Reference (implementation-independent)
Affiliation	SSRL, SLAC National Accelerator Laboratory
Date	29 September 2026

This document states the physics of the SPEAR3 RF plant and the control problem that follows from it: what disturbs the cavity field, over what frequency range, and which loop is responsible for each band. It is *implementation-independent* — the content does not change when the VXI hardware is replaced by the LLRF9 controller. Hardware-specific detail belongs in Doc L (legacy plant) and Doc 0 (upgrade design).

Contents

Document Scope and Provenance	6
1 System Overview and Field Stability Requirements	6
1.1 The Control Problem in One Sentence	6
1.2 Storage Ring Parameters	6
1.3 RF System Configuration	7
1.4 Field Stability Requirements	7
2 Plant Physics Model	7
2.1 High-Level System Block Diagram	8
2.2 RF Cavity as a Narrowband Resonator	8
2.3 Klystron as the Actuator	11
2.4 Loop Delay Budget — The Fundamental Bandwidth Ceiling	12
2.5 Complete Open-Loop Plant Transfer Function	13
3 I/Q Signal Processing Framework	13
3.1 Baseband I/Q Representation	13
3.2 Baseband I/Q Modulator	13
3.3 I/Q Demodulation	13
3.4 Cavity Probe Vector Sum	13
3.5 Error Signal Generation	14
4 Disturbance Analysis and Control Problem Statement	14
4.1 Disturbance Taxonomy	14
4.2 D1/D2: Beam Loading — The Dominant Disturbance	14
4.3 D3: Robinson Instability	15
4.4 D4: Coupled-Bunch Modes	15
4.5 D5: HVPS Ripple	16
4.6 D6: Klystron Gain Variation	17
4.7 D7/D8: Microphonics and Thermal Detuning	17
4.8 D9: Ring Circumference Thermal Drift — Long-Term RF Frequency Migration	17
4.9 Frequency-Domain Summary: The Disturbance Spectrum	18
5 Control Architecture: From Disturbances to Loops	19
5.1 The Design Logic: Bandwidth Matching	19
5.2 Feedback Fundamentals: Loop Gain, Closed Loop and Effective Impedance	19
5.3 Multi-Loop Stability: The Bandwidth Separation Principle	20
6 Loop-by-Loop Transfer Functions and Design	21
6.1 Loop Overview and Implementation Summary	21
6.2 Direct Loop — Wideband RF Field Regulation	22
6.3 Comb Loop — Narrowband Enhancement at Revolution Harmonics	22
6.4 LFB Woofer — Longitudinal Feedback via RF Modulation	23
6.5 Ripple Loop — HVPS Harmonic Rejection	24
6.6 Gap Feedforward Loop	25
6.7 HVPS Loop — Klystron Operating Point Regulation	26
6.8 Tuner Loop — Cavity Resonant Frequency Tracking	26

6.9	DAC Loop — Outermost Amplitude Regulation	27
6.10	Gain Tracking Function	28
7	Transient Operation: Matching Under Changing Beam Current and RF Frequency	29
7.1	Reflected Power as a Function of Detuning and Beam Current	29
7.2	Required Detuning Versus Beam Current	30
7.3	What Happens When the Tuner Lags	30
7.4	Division of Labour: the Direct Loop Holds the Field, the Tuner Restores the Match	31
8	HVPS Plant Model and Dynamics	32
8.1	Power Supply Architecture	32
8.2	HVPS Electrical Parameters	32
8.3	SCR Phase Control Dynamics	33
8.4	PLC Voltage Regulation Loop	33
8.5	Klystron Arc Protection	33
8.6	HVPS Dynamic Response Summary	33
9	Tuner Mechanics and Resonant Frequency Control	34
9.1	Cavity Tuner Physical Description	34
9.2	Tuning Physics	34
10	Performance Requirements and Verification	35
10.1	Disturbance Rejection Summary	35
10.2	LLRF9 Commissioning Results	35
10.3	Performance Margins	35
10.4	Calibration Data	35
A	SPEAR3 RF System Parameter Table	37
A.1	Storage Ring Parameters	37
A.2	Cavity Parameters (Per Cavity)	38
A.3	Klystron Parameters	38
A.4	Feedback Loop Parameters	38
B	Source Document Reference Index	39
B.1	Published Papers	39
B.2	Textbooks	39
B.3	Repository Documents	40
B.4	External Web References	41
C	Symbol and Notation Conventions	41
C.1	Cavity and Beam Parameters	41
C.2	Klystron and Drive Parameters	42
C.3	Loop Transfer Functions and Compensator Parameters	42
C.4	Comb Filter and Group Delay Equalization Parameters	43
C.5	LFB Woofer Parameters	43
C.6	Ripple Loop Parameters	43
C.7	Slow Loop Parameters	44
C.8	Calibration Parameters	44
C.9	I/Q Signal Processing	44

C.10 Conventions	45
----------------------------	----

List of Figures

1	The SPEAR3 RF plant as a control system: the klystron and cavity chain is the plant, the LLRF processor is the controller, and the beam is the principal disturbance.	8
2	Beam loading phasor diagram in steady state at 500 mA. The cavity is detuned so that the generator sees a real load: the reactive part of the beam-induced voltage is cancelled by the detuning angle ψ	11
3	Comb filter response. The peaks sit at multiples of the revolution frequency, one per coupled-bunch mode; between them the gain returns towards unity, so the filter adds no broadband noise. Drawn from the digital comb magnitude with pole radius $K = 0.98$ and comb gain 30 to show the characteristic shape — these are not fitted SPEAR3 values.	16
4	Disturbance spectrum and the loop assigned to each band. Loop bandwidths are separated by roughly a decade so that adjacent loops do not interact.	19
5	Cavity detuning required to cancel the reactive beam loading, as a function of beam current. The frequency offset (top) is linear in current; the loaded detuning angle measured by the tuner loop (bottom) is its arctangent and so compresses at high current.	30
6	Reflected power at the input coupler against cavity tuning, with and without beam. The minima sit at different detunings, so a cavity tuned for one beam condition is badly mismatched in the other. With no beam the over-coupled cavity cannot be matched at all: the best it can do on resonance is 34 % reflected.	32

Document Scope and Provenance

This document is the **Tier 1 physics and plant reference** for the SPEAR3 RF system. It describes the RF physics, control theory, and physical plant parameters that are **independent of the specific control hardware implementation**. The content does not change when VXI hardware is replaced with the LLRF9 controller — it describes the *why* behind the control system design.

The SPEAR3 LLRF control architecture is uniquely determined by the disturbance landscape of the RF plant. Each feedback loop exists because a specific class of disturbance threatens RF field stability, and the loop's bandwidth and gain are set by the magnitude and frequency content of that disturbance.

All technical content is traceable to original source documents; every numbered [R*n*] tag in the text links to its entry in §B. Where this document derives a value rather than quoting one, the derivation is given as a numbered equation.

1 System Overview and Field Stability Requirements

1.1 The Control Problem in One Sentence

The SPEAR3 RF system must deliver a 476.3 MHz accelerating voltage of ~ 2.85 MV across four cavities with amplitude stability $< 0.1\%$ RMS and phase stability $< 0.1^\circ$ RMS, in the presence of beam loading forces that — without feedback — would drive the system unstable within microseconds.

1.2 Storage Ring Parameters

Lattice and beam parameters are from [R1], [R2] and [R3]; RF-specific operating values are from [R4] and [R5]. §A.1 repeats this table with a per-row source column.

Parameter	Symbol	Value	Unit
Beam energy	E_0	3.0	GeV
Beam current (top-off)	I_b	500	mA
Circumference	C	234.14	m
Revolution frequency	f_{rev}	1.2804	MHz
Revolution period	T_{rev}	0.781	μs
Harmonic number	h	372	—
RF frequency	f_{RF}	476.3	MHz
Momentum compaction	α_c	1.18×10^{-3}	—
Energy loss per turn	U_0	1.02	MeV
Total accelerating voltage (design)	V_{RF}	3.2	MV
Total accelerating voltage (operational)	V_{RF}	~ 2.85	MV
Synchrotron frequency	f_s	~ 10.1	kHz
Synchrotron tune	ν_s	~ 0.008	—
Longitudinal radiation damping time	τ_s	~ 2.9	ms

Parameter	Symbol	Value	Unit
Transverse radiation damping time	$\tau_{x,y}$	$\sim 4.2, 5.1$	ms

Note on f_{RF} : The nominal RF frequency is 476.3 MHz. The precise frequency (e.g. 476.3051755 MHz as measured) varies slightly as the ring circumference changes. For consistency, 476.3 MHz is used throughout this document as nominal.

Note on U_0 : The current operational energy loss per turn is $U_0 = 1.02$ MeV. This is validated by the measured generator power of ~ 200 kW/cavity (§2.2.3). The value 0.91 MeV appearing in some earlier references [R1] corresponds to a different set of insertion-device contributions; the current ID complement increases U_0 .

Note on V_{RF} : The **design** value of 3.2 MV (800 kV/cavity) is from the original SPEAR3 RF system specification [R1]. The **operational** value of ~ 2.85 MV (712 kV/cavity) is from LLRF9 commissioning measurements [R4], and is also the current nominal operating point at 500 mA. It is used throughout the beam loading calculations in this document.

Note on α_c : Published values range from 0.0011 (SSRL parameter page [R3]) to 0.00118 (used in this document) depending on the specific lattice optics. Differences of $\sim 7\%$ in α_c produce $\sim 3\%$ differences in f_s .

1.3 RF System Configuration

The RF station consists of: a single 1.5 MW CW klystron (Marconi/CPI K3512S) $\rightarrow$ waveguide circulator $\rightarrow 3 \times$ Magic-Tee power splitter $\rightarrow$ four PEP-II-type single-cell HOM-damped copper cavities [R1], [R6]. A single I/Q modulator at the klystron input is the primary actuator for all fast feedback loops.

1.4 Field Stability Requirements

The requirement column is the specification [R5]; the achieved column is from LLRF9 commissioning [R4].

Parameter	Requirement	Typical Achieved	Rationale
Amplitude stability	$< 0.1\%$ RMS	$< 0.05\%$ RMS	Photon beam position, energy spread
Phase stability	$< 0.1^\circ$ RMS	$< 0.05^\circ$ RMS	Bunch timing, longitudinal emittance
HVPS voltage regulation	$< \pm 0.5\%$	$< \pm 0.3\%$	Klystron gain/phase stability
HVPS ripple	$< 1\%$ P-P	$< 0.5\%$ P-P	RF phase modulation budget

2 Plant Physics Model

This section derives the mathematical models of the three physical subsystems that the LLRF controller must regulate: the RF cavity, the klystron amplifier, and the HVPS.




Figure 1: The SPEAR3 RF plant as a control system: the klystron and cavity chain is the plant, the LLRF processor is the controller, and the beam is the principal disturbance.

2.1 High-Level System Block Diagram

Figure 1 shows the full RF control architecture — four cavities driven by one klystron, with multiple feedback loops spanning seven decades of frequency.

Key architectural features:

- **Single klystron, four cavities:** One I/Q modulator drives all four cavities simultaneously. Field regulation uses the vector sum of all four cavity probes.
- **Bandwidth hierarchy:** Direct (800 kHz) $\gg$ Ripple (300 Hz) $\gg$ HVPS/Tuner (~ 1 Hz) $\gg$ DAC (0.1 Hz) — natural frequency-domain decoupling.
- **Analog fast path:** The direct loop operates entirely in analog baseband for minimum delay (~ 270 – 500 ns total loop delay).

2.2 RF Cavity as a Narrowband Resonator

2.2.1 Equivalent Circuit

Near its fundamental mode at $\omega_0 = 2\pi \times 476.3$ MHz, each cavity is modeled as a parallel RLC circuit. The cavity parameters (per cavity, linac convention $R_s = V^2/2P$):

Parameter	Symbol	Value	Unit
Resonant frequency	f_0	≈ 476.3	MHz
Shunt impedance	R_s	3.73	M Ω

Parameter	Symbol	Value	Unit
Unloaded Q	Q_0	32,000	—
Loaded Q	Q_L	6,700	—
Coupling coefficient	$\beta = Q_0/Q_{\text{ext}}$	3.78	—

Traceability note: $R_s = 3.73 \text{ M}\Omega$ and $Q_0 = 32,000$ are taken directly from [R6], which reports $\beta_{\text{actual}} = 3.72$ and $\beta_{\text{optimum}} = 3.84$ for PEP-II HER, giving $Q_L = 6,780$. The value $\beta = 3.78$ used here is a derived operating point (intermediate between actual and optimum) consistent with $Q_L \approx 6,700$ via $Q_L = Q_0/(1 + \beta) = 32,000/4.78 = 6,695$; Doc L quotes the [R6] value $Q_L = 6,780$ directly, and the 1% difference is immaterial to every result below. [R1] reports $R_s = 3.8 \text{ M}\Omega$ in the accelerator convention ($= 2 \times R_s^{\text{linac}} = 7.6 \text{ M}\Omega$, consistent with $R_a = 7.5 \text{ M}\Omega$ in [R6]). Cavity geometry and measured impedance spectra are in [R7] and [R17].

2.2.2 Cavity Transfer Function

The cavity voltage response to a driving current near resonance:

$$H_{\text{cav}}(s) = \frac{R_s \omega_{1/2}}{s + \omega_{1/2} + j\Delta\omega} \quad (2.1)$$

where $\omega_{1/2} = \omega_0/(2Q_L)$ is the cavity half-bandwidth. The **impedance seen by the beam** at frequency offset $\Delta\omega$ from ω_{RF} :

$$Z_{\text{cav}}(\Delta\omega) = \frac{R_s}{1 + j 2Q_L \Delta\omega/\omega_0} \quad (2.2)$$

Cavity half-bandwidth:

$$\Delta f_{1/2} = \frac{f_0}{2Q_L} = \frac{476.3 \text{ MHz}}{2 \times 6700} = 35.5 \text{ kHz} \quad (2.3)$$

This determines the cavity natural response time $\tau_{\text{cav}} = 1/(2\pi\Delta f_{1/2}) \approx 4.5 \mu\text{s}$.

2.2.3 Beam Loading — Steady-State Phasor Analysis

A bunched beam of DC current I_b presents a fundamental RF current $I_{b1} = 2I_b$ to the cavity, so at 500 mA the cavity sees 1.0 A at the RF frequency. Its steady-state induced voltage in the *loaded* cavity, on resonance, is

$$V_{b,\text{res}} = \frac{I_{b1}R_s}{1 + \beta} = \frac{1.0 \text{ A} \times 3.73 \text{ M}\Omega}{4.78} = 0.78 \text{ MV} \quad (2.4)$$

— comparable to the 712 kV the generator is asked to establish. The sharper statement of the same fact is the power split: the beam draws 1.88 times as much power as the cavity walls dissipate (Eqs. (2.12) to (2.13)). **Beam loading, not wall loss, is what sets the design of this station.**

Synchronous phase — In the convention where ϕ_s is measured from the voltage crest (SLAC convention, used throughout this document):

$$V_{\text{RF}} \cos \phi_s = U_0 \quad (2.5)$$

$$\cos \phi_s = \frac{U_0}{V_{\text{RF}}} = \frac{1.02 \text{ MeV}}{2.85 \text{ MV}} = 0.358 \implies \phi_s \approx 69.0^\circ \quad (2.6)$$

Note: $\sin \phi_s = \sin(69.0^\circ) = 0.934$, which appears in the beam loading compensation formulas below.
Synchrotron frequency:

$$\nu_s = \sqrt{\frac{h \alpha_c V_{\text{RF}} \sin \phi_s}{2\pi E_0}} \quad (2.7)$$

With $V_{\text{RF}} = 2.85$ MV, $\sin \phi_s = 0.934$ and E_0 expressed in the same units as V_{RF} ($E_0 = 3000$ MeV): $\nu_s = \sqrt{372 \times 0.00118 \times 2.85 \times 0.934 / (2\pi \times 3000)} \approx 0.0079$, giving $f_s = \nu_s f_{\text{rev}} \approx 10.1$ kHz. Published values: $Q_s = 0.008$ [R1], $\nu_s = 0.007$ [R3] — the range reflects differences in operational V_{RF} and α_c across lattice configurations. For control design, the key constraint is that the direct loop bandwidth (~ 800 kHz) $\gg f_s$.

Optimum detuning — The cavity is detuned so that its susceptance cancels the reactive part of the beam-induced current, leaving the generator driving a real load. Writing $G = 1/R_s$ for the cavity conductance (so that $P_{\text{wall}} = \frac{1}{2} V_{\text{gap}}^2 G$, consistent with Eq. (2.12)), the reactive balance $V_{\text{gap}} G \tan \psi_0 + I_{b1} \sin \phi_s = 0$ gives

$$\tan \psi_{0,\text{opt}} = -\frac{I_{b1} R_s \sin \phi_s}{V_{\text{gap}}} = -\frac{1.0 \times 3.73 \times 10^6 \times 0.934}{712 \times 10^3} = -4.89 \quad (2.8)$$

Here ψ_0 is referred to the *unloaded* bandwidth. The angle the tuner loop actually measures — the phase between the cavity probe and the forward wave — is referred to the *loaded* bandwidth, and the two are related by $\tan \psi_L = \tan \psi_0 / (1 + \beta)$:

$$\tan \psi_{L,\text{opt}} = \frac{-4.89}{1 + 3.78} = -1.02 \implies \psi_{L,\text{opt}} \approx -45.7^\circ \quad (2.9)$$

Derivation note: Equation (2.8) is the condition that the reactive component of the generator current vanish, which minimizes the power reflected at the input coupler. Two factors must be carried correctly and are easy to lose. **(i)** A bunched beam of DC current I_b presents a *fundamental* RF current $I_{b1} = 2I_b$ to the cavity; it is I_{b1} , not I_b , that appears in the reactive balance. **(ii)** The cavity conductance in the circuit convention $P_{\text{wall}} = V_{\text{gap}}^2 / (2R_s)$ is $G = 1/R_s$. An equivalent and convenient form uses the geometry factor $R/Q = R_s/Q_0 = 116.6 \Omega$, which removes Q from the expression entirely and is the form used in Eq. (2.10). The result is cross-checked by the power split: $I_{b1} R_s \cos \phi_s / V_{\text{gap}} = 1.88 = P_{\text{beam}} / P_{\text{wall}}$, matching Eqs. (2.12) to (2.13) exactly [R10], [R11], [R12], [R13].

Optimum frequency detuning — converting the unloaded angle to a frequency offset with $\tan \psi_0 = 2Q_0 \Delta f / f_0$:

$$\Delta f_{\text{opt}} = \frac{f_0}{2Q_0} \tan \psi_{0,\text{opt}} = -\frac{(R/Q) I_{b1} \sin \phi_s f_0}{2 V_{\text{gap}}} = -\frac{116.6 \Omega \times 1.0 \text{ A} \times 0.934 \times 476.3 \text{ MHz}}{2 \times 712 \text{ kV}} \approx -36.4 \text{ kHz} \quad (2.10)$$

The cavity must therefore be tuned about 36 kHz **below** f_{RF} at 500 mA — roughly one cavity half-bandwidth (2.3), which is why the detuning angle comes out near -45° . Figure 2 shows the resulting steady-state phasor balance; §7 follows what happens when the beam current or f_{RF} moves away from this operating point.

Required generator power per cavity — At optimum coupling (β_{opt}) and optimum detuning (ψ_{opt}), the minimum generator power per cavity is the sum of cavity wall losses and beam power:

$$P_{\text{gen/cav}} = P_{\text{wall}} + \frac{P_{\text{beam}}}{n_{\text{cav}}} = \frac{V_{\text{gap}}^2}{2R_s} + \frac{I_b U_0}{n_{\text{cav}}} \quad (2.11)$$

Evaluation:




Figure 2: Beam loading phasor diagram in steady state at 500 mA. The cavity is detuned so that the generator sees a real load: the reactive part of the beam-induced voltage is cancelled by the detuning angle ψ .

$$P_{\text{wall}} = \frac{V_{\text{gap}}^2}{2R_s} = \frac{(712 \text{ kV})^2}{2 \times 3.73 \text{ M}\Omega} = 68 \text{ kW/cavity} \quad (2.12)$$

$$\frac{P_{\text{beam}}}{n_{\text{cav}}} = \frac{I_b U_0}{n_{\text{cav}}} = \frac{0.5 \text{ A} \times 1.02 \text{ MeV}}{4} = 127.5 \text{ kW/cavity} \quad (2.13)$$

$$P_{\text{gen/cav}} = 68 + 127.5 \approx 196 \text{ kW/cavity} \quad (2.14)$$

Total RF power: $4 \times 195.6 \approx 782 \text{ kW}$ — within the 1.5 MW klystron capacity, leaving $\sim 48\%$ headroom. The measured forward power at 500 mA is $\sim 200 \text{ kW/cavity}$, consistent with this calculation (the small excess accounts for reflected power at non-ideal coupling).

Note: Eq. (2.11) is the minimum-power condition at optimum coupling. In the general case with arbitrary coupling β and detuning ψ , the generator power includes reflected power terms. The important identity is that beam power per cavity $= I_b V_{\text{gap}} \cos \phi_s = I_b U_0 / n_{\text{cav}}$.

2.3 Klystron as the Actuator

For control analysis, the klystron is modeled as:

$$G_{\text{kly}}(s) = K_{\text{kly}} \cdot e^{-s\tau_{\text{kly}}} \quad (2.15)$$

where K_{kly} is the small-signal gain and $\tau_{\text{kly}} < 150 \text{ ns}$.

Parameter	Value	Unit
Maximum output power	1.5 MW	CW
Gain	43 dB (min)	—
Bandwidth	5 MHz	−3 dB
Group delay	< 150 ns	—
Perveance $K = I_k/ V_k ^{3/2}$	$\sim 1.0 \times 10^{-6}$	A/V ^{3/2}

Klystron ratings are from [R1]; the perveance follows from the HVPS operating point of §8.2 (−77 kV at 22 A gives $K = 22/(7.7 \times 10^4)^{3/2} = 1.03 \times 10^{-6}$ A/V^{3/2}) and agrees with the measured cathode readbacks recorded in Doc L. The value 2.0×10^{-6} that appears in the HVPS simulation configuration [R23] is not consistent with that operating point and is not used here.

Saturation model:

$$P_{\text{out}} = P_{\text{sat}} \cdot \frac{P_{\text{in}}/P_{\text{in,sat}}}{1 + P_{\text{in}}/P_{\text{in,sat}}} \quad (2.16)$$

AM-PM conversion — klystron output phase sensitivity to cathode voltage [R15]:

$$\Delta\phi_{\text{kly}} \propto \frac{\Delta V_k}{V_k} \quad (2.17)$$

2.4 Loop Delay Budget — The Fundamental Bandwidth Ceiling

The delay around the direct loop sets a hard ceiling on its crossover frequency. A pure delay τ_d contributes a phase lag $-2\pi f\tau_d$ that grows without bound, so the usable crossover is fixed by the delay alone:

$$f_{c,\text{max}} \approx \frac{1}{4\tau_d} \quad (2.18)$$

This is the single most important constraint in the entire control design. It is an engineering rule of thumb: at $f_c = 1/(4\tau_d)$ the transport delay alone has consumed 90° of phase, which leaves a workable margin once the lead compensator has offset the cavity pole. It is not a stability proof — the actual margin must be read from the gain/phase budget in §6.2.

Component	Legacy (analog)	LLRF9 (digital)
Klystron group delay	< 150 ns	< 150 ns
I/Q modulator	< 5 ns	< 5 ns
Cable propagation	~ 50 ns	~ 50 ns
Electronics/computation	~ 300 ns	~ 65 ns
Total τ_d	~ 500 ns	~ 270 ns
$f_{c,\text{max}}$	~ 500 kHz	~ 926 kHz

Note: The 270 ns figure for the LLRF9 column is the direct-loop delay quoted in the vendor manual [R4]; it is assumed here to be the total loop delay as itemised above [to be confirmed].

2.5 Complete Open-Loop Plant Transfer Function

$$G_{\text{plant}}(s) = G_0 \cdot H_{\text{cav}}(s) \cdot e^{-s\tau_d} = \frac{G_0 \omega_{1/2}}{s + \omega_{1/2} + j\Delta\omega} e^{-s\tau_d} \quad (2.19)$$

The cavity bandwidth (35.5 kHz) and the loop delay together define the limits of what feedback can achieve.

3 I/Q Signal Processing Framework

3.1 Baseband I/Q Representation

All RF feedback loops use baseband In-phase and Quadrature (I/Q) techniques:

$$V_{\text{RF}}(t) = A(t) \cos[\omega_{\text{RF}}t + \phi(t)] = I(t) \cos(\omega_{\text{RF}}t) - Q(t) \sin(\omega_{\text{RF}}t) \quad (3.1)$$

where $I(t) = A(t) \cos \phi(t)$ and $Q(t) = A(t) \sin \phi(t)$, with inverse relations:

$$A(t) = \sqrt{I^2 + Q^2}, \quad \phi(t) = \text{atan2}(Q, I) \quad (3.2)$$

3.2 Baseband I/Q Modulator

The I/Q modulator performs a scaled rotation:

$$\begin{pmatrix} I_{\text{out}} \\ Q_{\text{out}} \end{pmatrix} = G \begin{pmatrix} \cos \theta & -\sin \theta \\ \sin \theta & \cos \theta \end{pmatrix} \begin{pmatrix} I_{\text{in}} \\ Q_{\text{in}} \end{pmatrix} \quad (3.3)$$

Implementation: Each baseband I/Q modulator uses four AD834 four-quadrant multipliers (DC to 500 MHz) [R18] plus two EL2073 summing amplifiers to implement the 2×2 matrix. Group delay < 5 ns, full-power bandwidth > 40 MHz, dynamic range > 50 dB [R14], [R15].

SPEAR3 modulator count: 4 cavity combining modulators (one per probe) + 1 drive modulator (direct loop gain/phase) = **5 baseband I/Q modulators**, with associated Octal DAC channels on the RFP module for the 2×2 matrix coefficients.

PEP-II comparison: The PEP-II HER system used 7 baseband I/Q modulators (4 cavity combining + 1 direct loop + 1 comb filter adjust + 1 ripple) with 56 DAC channels [R15]. SPEAR3 requires fewer because: (a) the comb loop is not used, (b) the ripple correction is applied via DSP rather than a dedicated modulator. The AD834 multipliers and EL2073 op-amps are the same components.

3.3 I/Q Demodulation

RF signals are converted to baseband I/Q using +13 dBm demodulators. Outputs: AC-coupled into 50 Ω , low-pass filtered ($F_c = 225$ MHz), video amplified (17 dB) to ± 1 V.

3.4 Cavity Probe Vector Sum

Each of the 4 cavity probe signals is demodulated to I/Q and combined through a programmable combining network (4 I/Q baseband modulators + 2 summing amplifiers on the RFP module) to form the **total accelerating RF vector**. The DAC weights for each modulator set the complex gain for each cavity's contribution to the vector sum.

3.5 Error Signal Generation

$$\vec{E} = \vec{V}_{\text{ref}} - \vec{V}_{\text{probe}} \quad (3.4)$$

$$\vec{V}_{\text{drive}} = G_{\text{loop}} \cdot \vec{E} = G_{\text{loop}} (\vec{V}_{\text{ref}} - \vec{V}_{\text{probe}}) \quad (3.5)$$

The error signals ΔI , ΔQ are then combined with the reference I , Q to compute the rotation angle and multipliers of Eq. (3.3) for cavity field regulation. The I/Q baseband representation developed in this section is used throughout §§4–10 to express all loop transfer functions in the complex baseband domain [R14], [R15].

4 Disturbance Analysis and Control Problem Statement

The control architecture follows inevitably from the disturbance landscape.

4.1 Disturbance Taxonomy

The nine disturbance classes below are referred to as D1–D9 throughout the rest of this document; each one is the reason that a particular loop exists.

#	Disturbance	Frequency	Magnitude	Impact
D1	Beam loading (steady-state)	DC	$V_b = 0.78$ MV/cavity	Dominates voltage budget
D2	Beam loading (transient)	DC–100 kHz	Growth rates $< T_{\text{rev}}$	Longitudinal instability
D3	Robinson instability	$f_s \sim 10$ kHz (2.7)	Exponential growth	Beam loss
D4	Coupled-bunch modes	$n \cdot f_{\text{rev}}$	$1/\tau_{cb}$	Beam oscillation
D5	HVPS ripple	360, 720, 1080... Hz	$< 1\%$ P-P voltage	Phase modulation
D6	Klystron gain drift	0.01–1 Hz	up to 7 dB	Loop gain variation
D7	Microphonics	1–300 Hz	$\Delta f \sim 1$ –10 Hz	Cavity detuning
D8	Thermal detuning (cavity)	< 0.01 Hz	$\Delta f \sim 1$ –100 Hz	Slow frequency drift
D9	Ring circumference thermal drift	Seasonal ($\ll 0.001$ Hz)	$\Delta f_{RF} \sim 4$ kHz/year	Secular tuner setpoint migration

4.2 D1/D2: Beam Loading — The Dominant Disturbance

D1 — Steady-state beam loading: Each bunch extracts energy from the cavity field. The beam-induced voltage $V_{b,\text{res}} = 0.78$ MV per cavity (2.4) is comparable to the gap voltage itself, and the beam draws 1.88 times the wall-loss power. Without active compensation the generator would also have to supply the beam’s reactive loading. Detuning the cavity (§2.2.3) brings that reactive component to zero at the operating current, but any current deviation re-creates the mismatch — see §7.

D2 — Transient beam loading: Current transients (injection, ion-clearing gap, bunch-by-bunch variations) cause rapid changes in the beam-induced voltage. These transients drive cavity field oscillations at frequencies up to $\sim f_{\text{rev}}$.

How feedback suppresses D1/D2: The direct feedback loop divides the cavity impedance seen by the beam by the return difference $1 + G_{OL}$ (Eq. (5.3)).

At DC and low frequencies where $|G_{OL}| \gg 1$ (proportional gain ~ 15 dB + integrator), the impedance reduction is ~ 40 dB ($\times 100$). This has two physical effects:

1. **Voltage regulation:** The beam-induced voltage perturbation $\Delta V_b = \Delta I_b \cdot Z_{\text{eff}}$ is reduced by the loop gain. A 1% current transient that would cause ~ 19 kV field perturbation without feedback produces only ~ 190 V with 40 dB impedance reduction.
2. **Stability:** The beam-cavity interaction becomes stable because the reduced impedance eliminates the conditions for exponential growth. The **growth rate** for coupled-bunch instability from the fundamental mode [R15]:

$$\frac{1}{\tau} = \frac{I_b \alpha_c f_{\text{RF}}}{2 \nu_s \beta^2 (E/e)} R_{cb} \quad (4.1)$$

where $R_{cb} = \sum_n \text{Re} [Z_{\text{eff}}(\omega_{\text{RF}} + n\omega_{\text{rev}} + \omega_s) - Z_{\text{eff}}(\omega_{\text{RF}} + n\omega_{\text{rev}} - \omega_s)]$.

With feedback, Z_{eff} replaces Z_{cav} in the sum, reducing growth rates by the same factor as the impedance reduction. **Without feedback**, the peak cavity impedance of ~ 750 k Ω produces growth rates faster than $T_{\text{rev}} \approx 0.78$ μs . This single fact drove the PEP-II system design to include multiple feedback loops [R15]. The steady-state phasor balance that the detuning establishes is drawn in Figure 2.

4.3 D3: Robinson Instability

Robinson stability criterion (above transition):

$$\text{Re}\{Z_{\text{eff}}(\omega_{\text{RF}} + \omega_s)\} < \text{Re}\{Z_{\text{eff}}(\omega_{\text{RF}} - \omega_s)\} \quad (4.2)$$

Robinson growth rate:

$$\frac{1}{\tau_{\text{Rob}}} = \frac{\alpha_c \omega_{\text{rev}} I_b}{4 \omega_s (E/e)} [\text{Re}\{Z(\omega_{\text{RF}} + \omega_s)\} - \text{Re}\{Z(\omega_{\text{RF}} - \omega_s)\}] \quad (4.3)$$

Direct feedback reduces $Z_{\text{eff}} = Z_{\text{cav}}/(1 + G_{OL})$, reducing the growth rate by the same factor [R11], [R13], [R16].

4.4 D4: Coupled-Bunch Modes

With $h = 372$ RF buckets the beam supports 372 coupled-bunch modes; each mode m is driven by the impedance sampled at revolution harmonics:

$$\frac{1}{\tau_m} = \frac{\alpha_c \omega_{\text{rev}} I_b}{4 \omega_s (E/e)} \sum_p [\text{Re}\{Z((ph + m)\omega_{\text{rev}} + \omega_s)\} - \text{Re}\{Z((ph + m)\omega_{\text{rev}} - \omega_s)\}] \quad (4.4)$$

Physics of the comb filter: The comb filter provides additional impedance reduction at revolution frequency harmonics — precisely where beam-driven modes exist — without raising gain, and therefore noise, at the frequencies between harmonics. Its transfer function (6.2) has gain peaks at integer multiples of f_{rev} , giving the characteristic comb-tooth response of Figure 3.

Why SPEAR3 does not need the comb filter: The key ratio is $f_{\text{rev}}/\Delta f_{1/2}$:

- **SPEAR3:** $f_{\text{rev}} = 1.28$ MHz $\gg \Delta f_{1/2} = 35.5$ kHz $\rightarrow$ ratio ≈ 36 . In this regime, only the central RF harmonic lies within the cavity bandwidth, while all revolution sidebands are many cavity linewidths away and therefore do not significantly couple through the cavity impedance. The cavity effectively behaves as a narrowband filter, responding primarily to the carrier component of the beam current.




Figure 3: Comb filter response. The peaks sit at multiples of the revolution frequency, one per coupled-bunch mode; between them the gain returns towards unity, so the filter adds no broadband noise. Drawn from the digital comb magnitude with pole radius $K = 0.98$ and comb gain 30 to show the characteristic shape — these are not fitted SPEAR3 values.

- As a result, beam-induced disturbances at revolution harmonics are not directly amplified by the cavity, and the interaction is dominated by the fundamental RF component. The SPEAR3 beam current is also much lower than PEP-II's, so the system is correspondingly less sensitive to revolution-harmonic coupling and comb filtering is not necessary for fine control or disturbance rejection.
- **PEP-II:** $f_{\text{rev}} \approx 136$ kHz, comparable to $\Delta f_{1/2} \rightarrow$ ratio ≈ 4 . Although only the central RF harmonic lies strictly within the cavity bandwidth, the nearby revolution harmonics are only a few cavity linewidths away and therefore couple significantly through the cavity impedance.
- As a result, multiple revolution sidebands contribute to the beam–cavity interaction and must be actively controlled at PEP-II. That regime requires a comb filter, which suppresses selectively at the revolution harmonics and so mitigates beam-induced disturbances without the broadband noise amplification a purely wideband loop would introduce.

4.5 D5: HVPS Ripple

The 12-pulse SCR rectifier produces two families of harmonics:

12-pulse fundamental harmonics (ideal 12-pulse cancellation):

$$f_{12p} = 12n \times f_{\text{line}} = 720, 1440, 2160, \dots \text{ Hz} \quad (4.5)$$

Residual 6-pulse harmonics (from imperfect phase balance between the two 6-pulse bridges):

$$f_{6p} = 6n \times f_{\text{line}} = 360, 720, 1080, \dots \text{ Hz} \quad (4.6)$$

The 360 Hz component (the first 6-pulse harmonic, absent in ideal 12-pulse operation) is the **dominant residual** and the primary target of the ripple loop. Additional low-order harmonics at 60, 120, 180 and 240 Hz may appear at reduced levels (~ 20 – 40 dB below 360 Hz) depending on SCR firing symmetry [R21], [R22]. The ripple couples into the RF field through klystron AM-PM conversion:

$$\Delta\phi_{\text{RF}} \sim \frac{\partial P_{\text{kly}} / \partial V_k}{P_{\text{kly}}} \cdot \Delta V_{\text{ripple}} \quad (4.7)$$

4.6 D6: Klystron Gain Variation

Source of gain variation: As beam current changes from 0 to 500 mA, the HVPS loop adjusts cathode voltage V_k to maintain the klystron $\sim 10\%$ below saturation. As V_k changes, the small-signal gain (slope of the P_{out} vs P_{in} curve) varies by up to ~ 7 dB. This shifts the open-loop gain of the direct feedback loop, potentially affecting stability margins.

Gain tracking implementation: The baseband modulator on the RFP module (4 Gilbert-cell multipliers in a 2×2 matrix) has its matrix coefficients controlled by 12-bit Octal DACs. A slow EPICS loop (~ 1 Hz) reads the klystron forward power and drive power monitors, computes the current gain, and adjusts the modulator matrix so that the product $G_{\text{modulator}} \cdot G_{\text{klystron}}(V_k)$ stays constant (§6.10).

The MATLAB calibration routine `ConfDirect` (initiated from the EPICS feedback panel) performs the initial gain tracking setup by measuring klystron gain at the current operating point and writing the appropriate 2×2 matrix coefficients to the quad DAC.

Note: In PEP-II, the ripple loop also applied gain/phase correction via a dedicated I/Q modulator. At SPEAR3, the ripple loop phase correction is handled by the DSP (AT&T DSP1610), and the slow gain tracking is handled by the baseband modulator coefficients on the RFP module.

4.7 D7/D8: Microphonics and Thermal Detuning

For normal-conducting copper cavities: microphonic excursions < 10 Hz (negligible vs. $\Delta f_{1/2} = 35.5$ kHz).

Thermal detuning estimation: The resonant frequency of a copper cavity scales inversely with its linear dimensions: $\Delta f/f = -\alpha_{\text{Cu}} \cdot \Delta T$, where $\alpha_{\text{Cu}} \approx 16.5 \times 10^{-6} / ^\circ\text{C}$ is the linear thermal expansion coefficient of copper. For a simple cavity at 476.3 MHz, this gives:

$$\frac{\partial f_0}{\partial T} \approx -f_0 \cdot \alpha_{\text{Cu}} = -476.3 \text{ MHz} \times 16.5 \times 10^{-6} \approx -7.9 \text{ kHz}/^\circ\text{C} \quad (4.8)$$

Note: This first-principles estimate ($-7.9 \text{ kHz}/^\circ\text{C}$) applies to the uncooled cavity body. In practice the PEP-II-type cavities at SPEAR3 run on a regulated water-cooling circuit that holds the body temperature to within $\sim \pm 0.1^\circ\text{C}$, so the *observed* drift referred to the cooling-water setpoint is roughly an order of magnitude smaller — of order $-1 \text{ kHz}/^\circ\text{C}$ (§9.2).

The tuner loop (§6.8) tracks both microphonics and thermal drift, maintaining the cavity at the optimum detuning angle ψ_{opt} (2.9).

4.8 D9: Ring Circumference Thermal Drift — Long-Term RF Frequency Migration

Physical origin: The RF harmonic condition requires the RF operating frequency to equal an integer multiple of the revolution frequency:

$$f_{\text{RF}} = h \cdot f_{\text{rev}} = \frac{h \cdot c}{C} \quad (4.9)$$

The ring circumference $C = 234.14$ m is set by the physical path of the beam through the tunnel. As the building structure thermally expands and contracts with seasonal temperature changes, C varies slowly on a monthly-to-annual timescale. By the harmonic condition, the correct RF operating frequency must shift accordingly. A nominally fixed RF master oscillator becomes progressively detuned from the correct harmonic as the circumference drifts.

Measured magnitude at SPEAR3: The RF operating frequency migrates by approximately $|\Delta f_{\text{RF}}| \approx 4$ kHz over one year. Differentiating the harmonic condition at fixed h gives $\Delta C/C = -\Delta f_{\text{RF}}/f_{\text{RF}}$, so the fractional change in circumference is

$$\left| \frac{\Delta C}{C} \right| = \left| \frac{\Delta f_{\text{RF}}}{f_{\text{RF}}} \right| = \frac{4 \text{ kHz}}{476.3 \text{ MHz}} = 8.4 \times 10^{-6} \quad (4.10)$$

$$|\Delta C| = 8.4 \times 10^{-6} \times 234.14 \text{ m} \approx 2.0 \text{ mm} \quad (4.11)$$

The circumference and the required RF frequency move in *opposite* directions: a warmer, longer tunnel needs a lower f_{RF} . A 2 mm annual change in the 234 m circumference is consistent with a tunnel temperature variation of $\sim 0.8^\circ\text{C}$ (concrete/steel: $\alpha_{\text{struct}} \approx 10\text{--}12 \times 10^{-6}/^\circ\text{C}$), physically plausible for a building with seasonal HVAC cycling.

Contrast with D8 (cavity body thermal detuning):

	D8: Cavity thermal detuning	D9: Ring circumference drift
Physical origin	Cavity copper temperature $\rightarrow f_0$ shifts	Tunnel/building temperature $\rightarrow C$ changes $\rightarrow$ required f_{RF} shifts
Rate	$-7.9 \text{ kHz}/^\circ\text{C}$ (4.8)	$\sim 4 \text{ kHz/year}$ (measured operational data)
Timescale	Short-term (hourly)	Long-term (seasonal/annual)
Control variable	Tuner re-tracks f_0 relative to f_{RF}	Tuner re-converges to new equilibrium as f_{RF} migrates; RF master oscillator updated periodically

Impact on the control system: The operating detuning $\Delta f = f_0 - f_{\text{RF}}$ (§C.10) defines the tuner equilibrium. Both D8 and D9 shift Δf , but from opposite sides — D8 moves f_0 (cavity geometry changes), while D9 moves f_{RF} (ring geometry changes). The tuner loop (§6.8) is closed around the detuning angle $\psi = \arctan(2Q_L \Delta f / f_0)$, so it automatically re-converges to ψ_{opt} when f_{RF} changes, provided:

1. The tuner mechanical range and total step count are sufficient to reach the new equilibrium position.
2. The RF master oscillator frequency is updated periodically by feedback system to track the ring operating point.

4.9 Frequency-Domain Summary: The Disturbance Spectrum

Figure 4 is the Rosetta Stone of the control design: every loop in §6 exists because one or more of the disturbances D1–D9 occupies a specific frequency band, and the loop bandwidths are laid out so that each band has exactly one owner.




Figure 4: Disturbance spectrum and the loop assigned to each band. Loop bandwidths are separated by roughly a decade so that adjacent loops do not interact.

5 Control Architecture: From Disturbances to Loops

5.1 The Design Logic: Bandwidth Matching

The fundamental principle: **match the loop bandwidth to the disturbance frequency content**. For SPEAR3:

$$\text{DAC (0.1 Hz)} \ll \text{HVPS/Tuner } (\sim 1 \text{ Hz}) \ll \text{Ripple (300 Hz)} \ll \text{Direct } (\sim 800 \text{ kHz})$$

Bandwidth separations of $10\times$ – $1000\times$ provide natural frequency-domain decoupling.

5.2 Feedback Fundamentals: Loop Gain, Closed Loop and Effective Impedance

The three relations below apply to any of the RF field loops; the block-by-block forms and numerical parameters for each individual loop are given in §6.

Open-loop transfer function:

$$G_{\text{OL}}(s) = G_{\text{prop}} \cdot G_{\text{lead}}(s) \cdot G_{\text{int}}(s) \cdot G_{\text{kly}}(s) \cdot H_{\text{cav}}(s) \cdot e^{-s\tau_d} \quad (5.1)$$

Every symbol is defined in §C.3; the explicit compensator forms and the crossover gain/phase budget are in §6.2.

Closed-loop transfer function:

$$T(s) = \frac{G_{OL}(s)}{1 + G_{OL}(s)} \quad (5.2)$$

At frequencies well below f_c , $|G_{OL}| \gg 1$ and $T \approx 1$; above f_c , $T \rightarrow 0$.

Effective cavity impedance seen by the beam:

$$Z_{\text{eff}}(\omega) = \frac{Z_{\text{cav}}(\omega)}{1 + G_{OL}(\omega)} \quad (5.3)$$

This is the central result. The direct loop **transforms the cavity from a high-impedance resonator into a low-impedance broadband structure** [R15], [R14], [R11]:

- At DC: impedance reduction ~ 40 dB (integrator provides very high gain)
- At $f_s \approx 10$ kHz: ~ 30 dB (Robinson sidebands well suppressed)
- At $\Delta f_{1/2} = 35.5$ kHz: ~ 15 dB
- At $f > f_c$: no reduction ($Z_{\text{eff}} \approx Z_{\text{cav}}$)

5.3 Multi-Loop Stability: The Bandwidth Separation Principle

Formal argument: Consider two feedback loops acting on the same plant. Let $L_1(s)$ be the loop transfer function (return ratio) of the fast loop and $L_2(s)$ be that of the slow loop, where:

- $L_1(s) = G_{OL,\text{fast}}(s)$: the open-loop transfer function of the fast loop (e.g., the direct loop, with bandwidth $f_1 \sim 800$ kHz)
- $L_2(s) = G_{OL,\text{slow}}(s)$: the open-loop transfer function of the slow loop (e.g., the ripple loop, with bandwidth $f_2 \sim 300$ Hz)

The combined loop transfer function for the two nested loops is:

$$L_{\text{total}}(s) = (1 + L_1(s))(1 + L_2(s)) - 1 = L_1(s) + L_2(s) + L_1(s)L_2(s) \quad (5.4)$$

The cross-term $L_1(s) \cdot L_2(s)$ represents the interaction between the two loops. At frequencies near f_1 , $|L_2(j\omega)| \ll 1$ (the slow loop has negligible gain), so $L_{\text{total}} \approx L_1$ — the fast loop sees the slow loop as transparent. Conversely, at frequencies near f_2 , $|L_1(j\omega)| \gg 1$ (the fast loop has high gain), but the cross-term simply augments the slow loop's authority without introducing new phase crossings, provided the bandwidth separation is sufficient.

The condition for safe decoupling — ensuring the cross-term does not introduce additional gain or phase crossings near either loop's crossover frequency:

$$\frac{f_i}{f_{i+1}} \geq 10 \quad \text{for all adjacent loop pairs} \quad (5.5)$$

This ensures that at each loop's crossover frequency, all other loops are either at very high gain (inner loops) or very low gain (outer loops), so the Nyquist criterion can be applied to each loop independently.

SPEAR3 satisfies this with large margins: DAC $\rightarrow$ HVPS ($10\times$), HVPS $\rightarrow$ Ripple ($300\times$), Ripple $\rightarrow$ Direct ($2700\times$). The smallest separation (DAC $\rightarrow$ HVPS, $10\times$) is adequate because both are slow integrating loops with well-separated crossover frequencies [R14], [R15], [R40].

6 Loop-by-Loop Transfer Functions and Design

This section provides the transfer function, control law, and design rationale for each feedback loop. The subsections follow a consistent structure: **purpose** → **signal flow** → **transfer function** → **key parameters** → **design constraints**.

6.1 Loop Overview and Implementation Summary

The bandwidth requirement of each disturbance dictates the implementation technology. Microsecond-scale beam loading demands analog hardware with continuous processing. Millisecond-scale HVPS ripple is handled by a dedicated DSP. Second-scale drift is corrected by IOC software running in EPICS. This principle — **disturbance timescale** → **implementation tier** — makes the entire multi-loop architecture a natural consequence of the physics.

Loop	Sec- Implementation	Update Rate	Controller Type	Band- width	SPEAR3 Status
Direct	§6.2 Analog hardware (VXI RFP module)	Continu- ous	Lead-lag + PI	~800 kHz	Active
Comb	§6.3 Digital hardware (VXI CFM, IIR + FIR)	~10 MHz	IIR comb + FIR equalizer	~2 MHz span	Not used
LFB Woofer	§6.4 Digital hardware (GVF module, TAXI fiber)	~10 MHz	External injection	~1 MHz	Not used
Ripple	§6.5 Digital hardware (AT&T DSP1610)	23 kHz	Adaptive harmonic estimator	~300 Hz	Active
Gap FF	§6.6 Digital hardware (GVF module DSP)	~10 MHz	Feed-forward	~100 Hz	Not used
HVPS	§6.7 Real-time software (EPICS SNL)	~1 Hz	Proportional + dead-band	~1 Hz	Active
Tuner	§6.8 Real-time software (EPICS SNL)	~1 Hz	Bang-bang	~0.01–1 Hz	Active
DAC	§6.9 Real-time software (EPICS SNL)	Event / 10 s	Proportional + dead-band	~0.1 Hz	Active
Gain Tracking	§6.10 Supervisory software (EPICS CA)	~2 Hz	Ratio maintenance	~0.5 Hz	Active

The loops naturally partition into four implementation tiers:

1. **Analog hardware** (continuous): The direct loop — minimum latency path for the fastest disturbances (D1–D4).
2. **Digital hardware** (MHz-rate): Comb, woofer, gap feedforward, and ripple loops — dedicated DSP/FPGA processing for structured disturbances (D4, D5).
3. **Real-time software** (~1 Hz): HVPS, tuner, and DAC loops — EPICS programs managing slow plant dynamics (D6–D9).
4. **Supervisory software** (~0.1–2 Hz): Gain tracking — EPICS Channel Access for calibration maintenance.

6.2 Direct Loop — Wideband RF Field Regulation

Purpose: Reduces the effective cavity impedance seen by the beam by ~ 40 dB at low frequencies, suppressing Robinson instability (D3), coupled-bunch growth (D4), and regulating against beam loading transients (D1–D2). This is the primary stability loop.

Signal flow: Cavity probe I/Q (4 cavities, vector-summed) $\rightarrow$ error amplifier (compare to reference) $\rightarrow$ lead/integral compensator $\rightarrow$ baseband modulator (gain tracking) $\rightarrow$ I/Q RF modulator $\rightarrow$ drive amplifier $\rightarrow$ klystron $\rightarrow$ cavities.

Open-loop transfer function (Eq. (5.1) with the component forms written out):

$$G_{OL}(s) = K_p \cdot \frac{1 + s/\omega_z}{1 + s/\omega_p} \cdot \left(1 + \frac{\omega_i}{s}\right) \cdot K_{kly} \cdot \frac{R_s \omega_{1/2}}{s + \omega_{1/2}} \cdot e^{-s\tau_d} \quad (6.1)$$

where the terms are (left to right): proportional gain, lead compensator, PI integrator, klystron gain, cavity response, and transport delay. Every symbol is defined in §C.3.

Gain and phase budget at crossover ($f_c \approx 800$ kHz legacy, ≈ 930 kHz LLRF9):

Contributor	Gain at f_c	Phase at f_c
Proportional K_p	+15 dB	0°
Lead compensator	+3 to +6 dB	$+30^\circ$ to $+50^\circ$ (advance)
PI integrator	≈ 0 dB (above ω_i)	$\approx 0^\circ$
Cavity H_{cav}	$-20 \log_{10}(f_c/\Delta f_{1/2})$	$-90^\circ + \arctan(\Delta f_{1/2}/f_c)$
Transport delay	0 dB	$-360^\circ \cdot f_c \cdot \tau_d$
Net at crossover	0 dB (by definition)	$> -135^\circ$ (PM $> 45^\circ$)

Stability margins: Phase margin $\geq 45^\circ$ (required), gain margin ≥ 6 dB (required). The lead compensator zero and pole frequencies are chosen to provide sufficient phase advance at crossover to compensate the cavity pole (-90°) and delay lag ($-\omega_c \tau_d$).

Parameter	Value	Notes
Addresses	D1–D4	Primary stability loop
Measurement	Cavity probe vector sum (I/Q)	After combining network
Actuator	I/Q modulator on klystron drive	Direct analog path, minimum delay
Bandwidth f_c	~ 800 kHz (legacy) / ~ 930 kHz (LLRF9)	Limited by τ_d via Eq. (2.18)
Proportional gain K_p	~ 15 dB (≈ 5.6)	Adjustable via EPICS PV
Integrator frequency ω_i	$\sim 2\pi \times 30$ kHz	Rejects DC errors
Phase margin	$\geq 45^\circ$	Maintained by lead compensation
DC impedance reduction	~ 40 dB	$\approx 100\times$ reduction in $ Z_{eff} $
SPEAR3 status	Active	—

6.3 Comb Loop — Narrowband Enhancement at Revolution Harmonics

Purpose: Provides an additional ~ 20 dB of impedance reduction at revolution frequency harmonics — precisely where coupled-bunch modes are driven (D4) — complementing the broadband reduction of the

direct loop. Between revolution harmonics, the comb gain returns to unity, avoiding unnecessary noise amplification.

Signal flow: Cavity probe I/Q → ADC → IIR comb filter → FIR group delay equalizer → one-turn delay + vernier → DAC → summing node (added to direct loop output).

IIR comb transfer function [R15]:

$$H_{\text{comb}}(z) = G \frac{z^{-1} - z^{-n}}{1 - 2K \cos(2\pi\nu_s) z^{-n} + K^2 z^{-2n}} \quad (6.2)$$

The filter produces gain peaks at $f = m \cdot f_{\text{rev}} \pm f_s$ for integer m , precisely targeting the revolution-harmonic sidebands that drive coupled-bunch instabilities (4.4). The peak gain at each comb tooth is $G_{\text{peak}} = G/(1 - K)$, and the -3 dB bandwidth per tooth is approximately $(1 - K) \cdot f_{\text{rev}}/\pi$. For typical PEP-II parameters ($K \approx 0.95$, $G \approx 0.05$), peak gain ≈ 1 (unity) and tooth bandwidth ≈ 2.2 kHz — narrow enough to target individual synchrotron sidebands without amplifying inter-harmonic noise.

Closed-loop impedance with Direct + Comb: The combined impedance reduction at a revolution harmonic $m \cdot f_{\text{rev}}$ is:

$$Z_{\text{eff,D+C}}(\omega) = \frac{Z_{\text{cav}}(\omega)}{1 + G_{\text{OL,direct}}(\omega) + G_{\text{OL,comb}}(\omega)} \quad (6.3)$$

At revolution harmonics where both loops have authority, the impedance reduction is the product of the individual factors: the direct loop provides ~ 20 dB broadband, and the comb adds ~ 20 dB at targeted harmonics, for a combined ~ 40 dB at revolution sidebands.

Group delay equalization: A 32-tap FIR filter compensates for the frequency-dependent group delay of the cavity and transport path across the comb filter's operating range (~ 4 MHz centered on f_{RF}). The FIR coefficients are designed for the worst-case detuned cavity condition, maintaining phase linearity to $< 10^\circ$ over the full bandwidth. The one-turn delay is implemented as a FIFO and fine-adjusted with shift registers at 25 ns steps to match the revolution period to sub-ns precision.

$$H_{\text{eq}}(z) = \sum_{k=0}^{31} c_k z^{-k} \quad (6.4)$$

The complete comb path transfer function including equalization:

$$G_{\text{OL,comb}}(z) = H_{\text{comb}}(z) \cdot H_{\text{eq}}(z) \cdot z^{-n_{\text{delay}}} \quad (6.5)$$

where n_{delay} accounts for the hardware transport delay (ADC + DAC + cable propagation).

6.4 LFB Woofer — Longitudinal Feedback via RF Modulation

Purpose: Provides broadband damping of low-order coupled-bunch modes ($|n| < 10$) by using the RF station as a longitudinal "sub-woofer" kicker (D2). In the multi-band longitudinal feedback architecture, the woofer handles the low-frequency content of the bunch oscillation spectrum (up to ~ 1 MHz), while a dedicated stripline kicker (the "tweeter") handles high-frequency content. This is the standard PEP-II/ALS/APS longitudinal damping architecture [R15], [R41].

Signal flow: LFB BPM pickup → bunch-by-bunch DSP processing (external system) → 10-bit fiber-optic TAXI link at 10 MHz → GVF module DAC → FIR group delay equalizer → injection summing node → I/Q reference modulation.

Transfer function: The woofer acts as an additive correction to the static I/Q reference:

$$\vec{V}_{\text{ref,total}}(s) = \vec{V}_{\text{ref,static}} + K_{\text{woofer}} \cdot H_{\text{FIR}}(s) \cdot e^{-s\tau_{\text{woofer}}} \cdot \Delta \vec{V}_{\text{LFB}}(s) \quad (6.6)$$

where:

- K_{woofer} is the woofer injection gain (adjustable), setting the strength of RF modulation per unit LFB correction signal
- $H_{\text{FIR}}(s)$ is the same 32-tap group delay equalizer used for the comb filter (6.4), compensating cavity and transport delay across the woofer bandwidth
- τ_{woofer} is the one-turn injection delay (matching the revolution period for proper bunch alignment)
- $\Delta \tilde{V}_{\text{LFB}}(s)$ is the LFB correction signal received over the TAXI fiber link

Woofer/Tweeter complementarity: The longitudinal feedback system partitions the correction bandwidth between two actuators:

Actuator	Mechanism	Bandwidth	Modes Addressed
Woofer (RF station)	Modulates cavity voltage via I/Q reference injection	DC – ~1 MHz	Low-order
Tweeter (stripline kicker)	Direct longitudinal kick via broadband kicker	~1 – ~200 MHz	High-order

The RF station woofer is effective for low-order modes because these modes require large energy corrections at low frequency — naturally suited to the high-power RF cavity. Higher-order modes require fast, broadband corrections — suited to the stripline kicker's low latency.

Interaction with direct loop: The woofer injection enters upstream of the direct loop error point (at the reference input), so the direct loop sees the modified reference as its setpoint and tracks it. This means the woofer operates *through* the direct loop rather than in parallel, and the direct loop's bandwidth (~ 800 kHz) sets an upper limit on the effective woofer bandwidth.

Parameter	PEP-II Value	SPEAR3 Notes
Addresses	D2, D4 (low-order coupled-bunch)	—
External system	LFB bunch-by-bunch DSP	Not installed
Data link	TAXI fiber, 10-bit, 10 MHz	—
Injection hardware	GVF VXI module	Present but unused
FIR equalizer	32-tap (shared design with comb)	—
One-turn delay	$\approx 7.34 \mu\text{s}$ (PEP-II)	—
Effective bandwidth	DC – ~1 MHz	—
SPEAR3 status	—	Not used

Why not needed at SPEAR3: SPEAR3 does not have a longitudinal feedback system installed. At 500 mA beam current with $h = 372$, the coupled-bunch instability growth rates are manageable with the direct loop alone. PEP-II required the woofer to damp strong coupled-bunch oscillations driven by the high beam current (> 1 A) and large harmonic number ($h = 3,492$) where many more revolution harmonics drive unstable modes.

6.5 Ripple Loop — HVPS Harmonic Rejection

Purpose: Cancels RF amplitude and phase modulation caused by HVPS switching ripple (D5). The ripple appears as harmonics of 60 Hz on the klystron cathode voltage, modulating klystron gain and phase via AM-PM conversion.

Signal flow: Klystron forward I/Q → I/Q demodulation → DSP phase/amplitude extraction → harmonic estimator → correction I/Q → DAC → summing node with direct loop.

Key design choice: Measures the **klystron forward signal** (not cavity probe), because the ripple frequencies (< 2 kHz) are well within the cavity bandwidth (35.5 kHz) and the correction must be applied upstream.

Harmonic estimator algorithm (from `ripple.s.v` [R36]): The DSP implements an adaptive harmonic tracker — for each harmonic k :

$$\hat{A}_k[n] = \hat{A}_k[n-1] + \mu_k \cdot e[n] \cdot \cos(2\pi k f_{\text{line}} n T_s) \quad (6.7)$$

$$\hat{B}_k[n] = \hat{B}_k[n-1] + \mu_k \cdot e[n] \cdot \sin(2\pi k f_{\text{line}} n T_s) \quad (6.8)$$

$$u[n] = \sum_k \left[\hat{A}_k \cos(2\pi k f_{\text{line}} n T_s) + \hat{B}_k \sin(2\pi k f_{\text{line}} n T_s) \right] \quad (6.9)$$

where $e[n] = \phi_{\text{ref}} - \phi_{\text{kly}}$ is the phase error at sample n , $\hat{A}_k, \hat{B}_k$ are the estimated cosine/sine coefficients of the k -th harmonic, μ_k is the adaptation gain for harmonic k , $f_{\text{line}} = 60$ Hz, and $T_s = 1/23$ kHz is the sampling period. This is a **narrowband adaptive notch** algorithm that converges on the exact amplitude and phase of each harmonic [R14].

Dual-rate processing: 6 fast harmonics (60–360 Hz, every cycle at 23 kHz) + 8 slow harmonics (420–840 Hz, round-robin at ~ 2.9 kHz effective rate). Fixed-point: q13 (phase), q11 (accumulators with $[-16, +16]$ headroom), q15 (gains).

Parameter	Value	Notes
Addresses	D5 (HVPS ripple)	Harmonic rejection
Measurement	Klystron forward I/Q	Upstream of cavity
Effective bandwidth	~ 300 Hz (fast) / ~ 1.5 kHz (slow)	Limited by DSP sample rate
Algorithm	Adaptive harmonic estimator	6 fast + 8 slow harmonics
Sample rate	~ 23 kHz	Hardware ripple clock on RFP module
DSP	AT&T DSP1610 (16-bit fixed-point)	On RFP VXI module
SPEAR3 status	Active (primarily as slow phase tracker)	

Note: In SPEAR3 operations, the ripple loop is deployed primarily as a **slow phase tracker** compensating for klystron phase shifts across cathode voltage changes (D6). The LLRF9 inherently rejects HVPS ripple through its high-bandwidth direct loop, making the legacy DSP-based ripple loop unnecessary in the upgrade.

6.6 Gap Feedforward Loop

Not used at SPEAR3. Addresses D2 (ion clearing gap transient). In PEP-II, the GVF module provided pre-computed I/Q correction waveforms via DSP firmware (`gvff.s`). Not needed at SPEAR3 due to smaller harmonic number ($h = 372$ vs. PEP-II $h = 3,492$).

6.7 HVPS Loop — Klystron Operating Point Regulation

Purpose: Adjusts the klystron cathode voltage V_k to maintain the klystron operating point at $\sim 10\%$ below saturation (D6), ensuring the direct loop has sufficient headroom for fast corrections.

Signal flow: Klystron forward power monitor (or station gap voltage) $\rightarrow$ EPICS SNL (`rf_hvps_loop.st,v`) $\rightarrow$ PLC HVPS voltage setpoint $\rightarrow$ Enerpro SCR firing angle $\rightarrow$ cathode voltage V_k [R14].

Control law (from `rf_hvps_loop.st,v`): Operates in two modes:

1. **Processing mode** (STATION_PROC): Slowly ramps V_k upward while monitoring cavity vacuum, conditioning the cavities by gradually increasing RF power.
2. **Operating mode** (STATION_ON_CW): Proportional controller with deadband and rate limiting:

$$\Delta V_k[n] = \begin{cases} K_{\text{HVPS}} \cdot (P_{\text{target}} - P_{\text{measured}}) & \text{if } |P_{\text{target}} - P_{\text{measured}}| > P_{\text{deadband}} \\ 0 & \text{otherwise} \end{cases} \quad (6.10)$$

where K_{HVPS} is the proportional gain (voltage step per unit power error), clamped to a maximum step size per cycle.

Parameter	Value	Notes
Addresses	D6	Operating point regulation
Measurement	Klystron forward power or station gap voltage	Mode-selectable
Actuator	HVPS cathode voltage V_k	Via PLC $\rightarrow$ Enerpro firing angle
Bandwidth	~ 1 Hz	Set by the supervisory update rate, not by the plant (§8.6)
Update rate	~ 2 Hz (~ 0.5 s cycle)	Configurable via <code>hvps_loop_delay</code>
Control law	Proportional with deadband	Rate-limited output
Implementation	EPICS SNL: <code>rf_hvps_loop.st,v</code> (343 lines, 4 states)	States: init, off, proc, on
SPEAR3 status	Active	

6.8 Tuner Loop — Cavity Resonant Frequency Tracking

Purpose: Adjusts the mechanical cavity tuner to maintain the optimum detuning angle ψ_{opt} (2.9), compensating for beam loading (the dominant term), cavity thermal drift (D8) and microphonics (D7). It also re-converges to the new equilibrium following a ring-circumference-driven shift in the RF operating frequency (D9).

Signal flow: Cavity probe phase and klystron forward phase $\rightarrow$ phase subtraction $\rightarrow$ comparison to ψ_{target} $\rightarrow$ deadband logic $\rightarrow$ stepper motor command $\rightarrow$ mechanical tuner.

Control law (from `rf_tuner_loop.st,v` [R34]):

$$\varepsilon = [\angle(V_{\text{probe}}) - \angle(V_{\text{fwd}})] - \psi_{\text{target}} \quad (6.11)$$

$$\text{Step command} = \begin{cases} +N_{\text{step}} & \text{if } \varepsilon > \varepsilon_{\text{deadband}} \\ -N_{\text{step}} & \text{if } \varepsilon < -\varepsilon_{\text{deadband}} \\ 0 & \text{otherwise} \end{cases} \quad (6.12)$$

Frequency offset estimation (from `subSysFreqOff` in `subSys.c`):

$$\Delta f_{\text{est}}(x, V) = p_0 + p_1(x - x_{\text{home}}) + p_2(x - x_{\text{home}})^2 + p_3(x - x_{\text{home}})^3 + t_1 V^2 \quad (6.13)$$

where x is the tuner position (steps), x_{home} is the home position, $p_0 \dots p_3$ are polynomial coefficients from calibration, and $t_1 V^2$ accounts for voltage-dependent detuning. Exponential smoothing is applied to the estimate [R14], [R34].

Parameter	Value	Notes
Addresses	D7, D8, D9	Frequency tracking (microphonics + cavity thermal + ring circ. drift)
Measurement	$\angle(\text{probe}) - \angle(\text{fwd})$	Detuning angle proxy
Actuator	Stepper motor $\rightarrow$ mechanical tuner plunger	Per cavity (4 independent loops)
Bandwidth	$\sim 0.01\text{--}1$ Hz	Limited by mechanical response
Control law	Bang-bang with deadband	N_{step} steps per correction cycle
Tuning resolution	~ 1 Hz/step	Worm gear mechanism, self-locking
Implementation	EPICS SNL: <code>rf_tuner_loop.st,v</code> (555 lines)	States: init, unknown, reset, off, on
Motor controller	AB 1746-HSTP1 (in service). Galil DMC-4143 Rev 1.3h is in development, not installed — test moves were made Aug 2025 [R35]; it goes online when the LLRF upgrade completes	—
SPEAR3 status	Active	

6.9 DAC Loop — Outermost Amplitude Regulation

Purpose: Maintains the cavity gap voltage (or klystron drive power) at the software setpoint by adjusting the I/Q modulator baseline DAC values. This is the outermost and slowest feedback loop, compensating for long-term drifts.

Signal flow: Gap voltage readback (cavity probe amplitude) or drive power readback $\rightarrow$ error calculation $\rightarrow$ proportional controller with deadband $\rightarrow$ DAC count adjustment $\rightarrow$ RFP Octal DAC $\rightarrow$ I/Q modulator baseline.

Control law (from `rf_dac_loop.st,v` and `subIQcounts` in `subIQ.c`):

$$\Delta C_{\text{DAC}}[n] = K_{\text{DAC}} \cdot (V_{\text{set}} - V_{\text{meas}}) \cdot D_{\text{conv}} \cdot (1 + G_{\text{loop}}) \quad (6.14)$$

where ΔC_{DAC} is the DAC count change, K_{DAC} is proportional gain (0–1), D_{conv} is the calibration conversion factor (counts/kV), and G_{loop} is the direct loop gain correction. Output subject to deadband, rate limiting ($|\Delta C| \leq \Delta C_{\text{max}}$), and range limiting (± 2047 counts, 12-bit DAC).

Operating modes (station-state dependent):

Station State	DAC Loop Mode	Controlled Variable
STATION_OFF / STATION_PARK	Inactive	—
STATION_TUNE	Drive power regulation	Tune-mode DAC
STATION_ON_CW, direct loop OFF	Drive power regulation	RFP DAC

Station State		DAC Loop Mode	Controlled Variable
STATION_ON_CW, direct loop ON		Gap voltage regulation	RFP DAC

Parameter	Value	Notes
Bandwidth	~ 0.1 Hz	Limited by scan rate and smoothing
Update rate	Event-driven or ≤ 10 s timeout	DAC_LOOP_MAX_INTERVAL = 10.0
DAC range	± 2047 counts (12-bit)	Minimum delta: 0.5 counts
Implementation	EPICS SNL: rf_dac_loop.st,v (290 lines, 4 states)	init, off, tune, on
SPEAR3 status	Active	

6.10 Gain Tracking Function

Purpose: Compensates for klystron gain variation (D6) as cathode voltage changes. The klystron small-signal gain varies by up to ~ 7 dB across the operating range; without tracking, this shifts the direct loop's open-loop gain and stability margins.

Control law:

$$G_{\text{modulator}} \cdot G_{\text{klystron}}(V_k) = G_{\text{loop,target}} \text{ (constant)} \quad (6.15)$$

$$\therefore G_{\text{modulator}} = G_{\text{loop,target}} / G_{\text{klystron}}(V_k) \quad (6.16)$$

Implementation: A slow EPICS calculation (~ 2 Hz) reads klystron forward and drive power monitors, computes current gain $G_{\text{kly}} = P_{\text{fwd}}/P_{\text{drive}}$, and writes updated 2×2 matrix coefficients to the RFP Octal DAC [R14], [R15]. The ConfDirect calibration routine performs initial gain measurement and matrix setup.

The DC gain coefficient tracking in subSysDCcoeff adjusts the ripple loop's DC coefficient based on klystron gain deviations with deadband limiting:

$$\Delta G_{\text{DC}} = D_{\text{scale}} \cdot 10^{(G_{\text{desired}} + L_{\text{accum}})/20} - G_{\text{actual}} \quad (6.17)$$

7 Transient Operation: Matching Under Changing Beam Current and RF Frequency

Everything in §2.2.3 is a *steady-state* result: it describes the station at one beam current, with the cavity already sitting at the detuning that matches it. Operationally the station is almost never in that state. Three things move the operating point, on three very different timescales:

- **Beam current** changes over a fill, a top-off shot or a beam loss (D1, D2). It fixes the fundamental beam current $I_{b1} = 2I_b$ and hence the detuning the cavity needs.
- **The RF frequency** migrates as the ring circumference breathes with tunnel temperature (D9, §4.8), by roughly 4 kHz per year. The cavity has to follow f_{RF} , not the other way round.
- **The cavity resonance** itself drifts with copper temperature and moves with microphonics (D7, D8).

All three arrive at the coupler as the same single quantity — a detuning error — and all three are corrected by the same single actuator, the mechanical tuner. What distinguishes them is only how fast they move and how far.

7.1 Reflected Power as a Function of Detuning and Beam Current

With the direct loop holding the gap voltage at V_{gap} , the load presented to the input coupler is the cavity in parallel with the beam. Normalising the total gap admittance to the external (coupler) conductance βG , and introducing the two dimensionless beam-loading parameters together with the detuning variable

$$a \equiv \frac{I_{b1} R_s \cos \phi_s}{V_{\text{gap}}} = \frac{P_{\text{beam}}}{P_{\text{wall}}}, \quad b \equiv \frac{I_{b1} R_s \sin \phi_s}{V_{\text{gap}}}, \quad t \equiv \tan \psi_0 = \frac{2Q_0 \Delta f}{f_0}, \quad (7.1)$$

the normalised load admittance is $y_L = [(1 + a) + j(t + b)] / \beta$, and the fraction of forward power reflected at the coupler is

$$|\Gamma|^2 = \left| \frac{1 - y_L}{1 + y_L} \right|^2 = \frac{(\beta - 1 - a)^2 + (t + b)^2}{(\beta + 1 + a)^2 + (t + b)^2} \quad (7.2)$$

At 500 mA, $a = 1.88$ and $b = 4.89$. Two consequences follow immediately.

The tuner owns the imaginary part. Equation (7.2) is minimised over tuning when $t = -b$, which is precisely the optimum detuning of Eq. (2.8). Driving $t + b$ to zero is the entire job of the tuner loop, and it is the *only* loop that can do it.

The coupler sets the floor. At $t = -b$ the residual reflection is

$$|\Gamma|_{\min}^2 = \left(\frac{\beta - 1 - a}{\beta + 1 + a} \right)^2 \quad (7.3)$$

which vanishes only when $\beta = 1 + a$. Perfect matching at 500 mA would need $\beta_{\text{opt}} = 2.88$; the installed PEP-II coupler gives $\beta = 3.78$. The station is therefore **over-coupled at its design current** and carries a residual $|\Gamma|_{\min}^2 = 1.8\%$. Solving $1 + a = \beta$ gives the current at which the installed coupler would be exactly matched, $I_b \approx 740$ mA — a reminder that the coupler was sized for PEP-II, not for SPEAR3.

This closes a loop left open in §2.2.3. With the field held at V_{gap} , the cavity and beam absorb $P_{\text{wall}} + P_{\text{beam}} = 195.6$ kW per cavity (2.14), so the klystron must deliver $P_{\text{fwd}} = (P_{\text{wall}} + P_{\text{beam}}) / (1 - |\Gamma|^2) = 195.6 / 0.982 = 199$ kW per cavity. The measured forward power at 500 mA is ~ 200 kW per cavity. The 1.8% coupler mismatch is the “small excess” that §2.2.3 attributes to non-ideal coupling.




Figure 5: Cavity detuning required to cancel the reactive beam loading, as a function of beam current. The frequency offset (top) is linear in current; the loaded detuning angle measured by the tuner loop (bottom) is its arctangent and so compresses at high current.

7.2 Required Detuning Versus Beam Current

Because ϕ_s depends only on U_0 and V_{RF} , and not on current, the detuning the cavity needs is **linear in beam current**: $\Delta f_{\text{opt}} = -72.8 \text{ Hz/mA} \times I_b$. Figure 5 shows both the frequency offset and the loaded angle the tuner serves on. Filling from zero to 500 mA therefore requires the tuner to walk the cavity through the full 36.4 kHz, about one cavity half-bandwidth; the loaded angle swings from 0° to -45.7° .

The practical consequence is that the tuner setpoint is never static. It tracks the stored current continuously, and superimposed on that are the slow drifts of D7–D9.

7.3 What Happens When the Tuner Lags

Figure 6 evaluates Eq. (7.2) against cavity tuning for the two extreme beam conditions. The two curves have minima in different places, and that displacement is the whole story of transient matching.

Event	Detuning error	$ \Gamma ^2$	$P_{\text{fwd}}/\text{cavity}$	Consequence
Steady 500 mA, tuner converged	0	1.8%	199 kW	The normal operating point
Top-off shot, ± 5 mA	0.4 kHz	1.8%	199 kW	Below the tuner deadband; invisible
Circumference drift, one year	4 kHz	2.5%	201 kW	Absorbed as a slow migration of the tuner setpoint (D9)
Fill 0 $\rightarrow$ 500 mA, tuner still on resonance	36.4 kHz	36%	307 kW	$4 \times 307 = 1.23 \text{ MW}$, or 82% of the klystron rating

Event	Detuning error	$ \Gamma ^2$	$P_{\text{fwd}}/\text{cavity}$	Consequence
Beam loss 500 $\rightarrow$ 0 mA, cavity still detuned	36.4 kHz	68%	211 kW	Only wall loss is delivered, but the circulator load takes 143 kW/cavity
No beam, cavity on resonance	0	34%	103 kW	The over-coupled floor; cannot be improved without beam

The two rows that matter operationally are the fill and the beam loss. Both leave the cavity a full half-bandwidth from its matching point, and in both cases a third or more of the forward power goes into the circulator load until the tuner catches up. This is why a fill is done at reduced gap voltage or slowly enough for the tuner to track, and why the circulator load, not the klystron, is the component sized by the transient.

7.4 Division of Labour: the Direct Loop Holds the Field, the Tuner Restores the Match

Two loops respond to these transients, and it is worth stating plainly that neither can do the other's job.

The direct loop regulates the field, and it is fast. With 800 kHz of bandwidth (2.18) it corrects a beam-current step within a few microseconds — far faster than the $4.5 \mu\text{s}$ cavity fill time (2.3), and faster than any mechanical motion. But it holds V_{gap} by *demanding more generator current*. It does not change y_L : the cavity is exactly as mismatched as before, and the extra forward power is delivered, reflected, and dumped in the circulator load. **A field-regulation loop cannot reduce reflected power.**

The tuner restores the match, and it is slow. Only the tuner changes t , and it does so at 0.01–1 Hz through a stepper motor and a mechanical plunger (§6.8 and §9). It is seven to eight decades slower than the direct loop.

The resulting sequence for any current transient is therefore always the same:

1. The beam current changes, which changes a and b essentially instantaneously.
2. The direct loop holds V_{gap} through the change. Field amplitude and phase never leave specification.
3. The reflected power jumps to the value given by Eq. (7.2) at the *old* tuning, and the klystron carries the extra forward power.
4. The tuner walks t back to $-b$ over seconds, and the reflected power decays to the coupler floor.

The separation of timescales is what makes this safe. Because the direct loop is roughly 10^6 times faster than the tuner, the two never interact dynamically — the tuner sees a cavity whose field is already regulated, and the direct loop sees a detuning that is constant on its own timescale. That is the same bandwidth-separation argument as Eq. (5.5), applied to the one pair of loops that share an actuator path. The cost of the separation is that mismatch is corrected slowly, so transient reflected power must be budgeted as a hardware rating rather than regulated away.

Not covered here: this analysis is quasi-static in the tuner variable — it evaluates Eq. (7.2) at each tuning, but does not model the tuner's own closed-loop trajectory, its deadband limit cycle, or the coupled dynamics of four independently tuned cavities driven from one klystron. A measured tuner step response and a fill record with synchronised current, forward and reflected power would let those be added; neither is currently in the repository.




Figure 6: Reflected power at the input coupler against cavity tuning, with and without beam. The minima sit at different detunings, so a cavity tuned for one beam condition is badly mismatched in the other. With no beam the over-coupled cavity cannot be matched at all: the best it can do on resonance is 34 % reflected.

8 HVPS Plant Model and Dynamics

8.1 Power Supply Architecture

The SPEAR3 klystron HVPS is a PEP-II design: a 12-pulse, primary-side SCR phase-controlled rectifier fed from a 12.47 kV substation feeder [R21], [R22]. Two complete units (SPEAR1 and SPEAR2) are installed; one is energized at a time.

8.2 HVPS Electrical Parameters

Parameter	Value	Unit
Input voltage	12,470 V RMS L-L	3-phase 60 Hz
Output voltage range	0 to -90 kV	DC
Maximum current	27 A	DC
Nominal operating	-77 kV, 22 A	DC
Complete-supply rating	2,750 kVA (12.5 kV at 127 A RMS)	nameplate
Voltage regulation	< $\pm 0.5\%$	at > 65 kV
Voltage ripple	< 1% P-P, < 0.2% RMS	at > 60 kV
Filter inductors (L_1, L_2)	0.3 H each	85 A DC
Filter capacitors (C)	8 μ F per stage $\times$ 4 series stages	at 30 kV
SCR crowbar arc energy	< 5 J (with), < 20 J (without)	—

Ratings are from the HVPS technical specification [R22] and the original design paper [R21]. The as-built plant detail behind these numbers — nameplate, tank contents and stored energy — is in Doc L.

8.3 SCR Phase Control Dynamics

$$V_{dc} = V_{dc,max} \cos \alpha \quad (8.1)$$

The installed firing electronics is an Enerpro FCOG6100 six-pulse board with an FCOAUX60 auxiliary gate-drive board [R26]; the FCOG1200 named in some upgrade material is the *replacement* part and is not in service. The board's phase-locked loop free-runs at $384 \times f_{line} = 23.04$ kHz and locks to the AC mains zero crossings, so the delay angle α is referenced to the line rather than to an internal ramp.

For small-signal control analysis the firing chain is modelled as a single-pole lag:

$$H_{Enerpro}(s) = \frac{1}{1 + s/\omega_{Enerpro}} \quad (8.2)$$

with $\omega_{Enerpro} \approx 415$ rad/s, i.e. -3 dB at 66 Hz. That figure comes from the published loop-filter analysis of this firing-circuit family [R25], which also gives unity DC gain, a $+0.81$ dB peak at 60 rad/s and -45° phase margin at 339 rad/s. The single pole is therefore a simplification — the measured response peaks slightly, so it is mildly underdamped rather than exactly first order.

Small-signal bandwidth and step settling are different numbers, and one does not follow from the other. The 415 rad/s pole corresponds to $\tau = 1/\omega_{Enerpro} = 2.4$ ms, but a *step* in the SIG HI command settles in **2–3 AC line cycles**, that is 33–50 ms [R25]. This is not a contradiction: phase control is a sampled-data process, so a new delay angle can only take effect at the next thyristor firing instant — one every $1/(12f_{line}) = 1.39$ ms in the 12-pulse configuration — and the PLL has to re-acquire after a large disturbance. The 415 rad/s pole shapes the small-signal loop; the 2–3 cycle figure is how long a setpoint change actually takes to arrive.

8.4 PLC Voltage Regulation Loop

The SLC-500 PLC implements a first-order IIR filter with scan period $T = 10$ ms:

$$y[n] = (1 - \alpha) y[n - 1] + \alpha x[n] \quad (8.3)$$

with $\alpha = 0.4$, giving time constant $\tau = -T/\ln(1 - \alpha) \approx 20$ ms [R27], [R23].

8.5 Klystron Arc Protection

Four mechanisms limit the energy an arc can deposit in the klystron: the SCR crowbar, the star-point bypass, the 500Ω filter isolation resistors and the cable termination inductors. The published PEP-II result is < 5 J to the klystron with the crowbar operating and $I^2 t < 40$ A²s [R21].

Timing and component caveats: the crowbar conduction delay is $\approx 10 \mu\text{s}$, not sub-microsecond, and primary current interruption takes 4–8 ms; the termination inductors are **350 μH as built**, not the 200 μH design figure of [R21]. Both corrections come from the as-built drawing review recorded in Doc L. These are published design/test results, not an acceptance certification of the installed SPEAR3 units.

8.6 HVPS Dynamic Response Summary

The elements below are listed fastest first. Each row states the physical time it describes; they are *not* interchangeable, and the equivalent frequency is quoted only where a single-pole or resonant interpretation is meaningful.

Element	Characteristic time	Equivalent frequency	What the number is
SCR commutation overlap	$\sim 100 \mu\text{s}$	$\sim 1.6 \text{ kHz}$	Current transfer between thyristors; not a control-loop limit
Output LC filter	$\sqrt{LC} = 775 \mu\text{s}$	$f_0 \approx 205 \text{ Hz}$	0.3 H per leg into the $2 \mu\text{F}$ net series bank (§8.2); lightly damped resonance
12-pulse firing interval	1.39 ms between firings; $\approx 0.69 \text{ ms}$ mean transport lag	$\sim 230 \text{ Hz}$	Sampling limit of phase control: α can change only at a firing instant
Enerpro small-signal pole	$\tau = 2.4 \text{ ms}$	66 Hz (−3 dB)	Equation (8.2), $\omega_{\text{Enerpro}} = 415 \text{ rad/s}$ [R25]
Enerpro step settling	2–3 line cycles, 33–50 ms	—	Large-signal settling after a SIG HI step [R25]
PLC digital filter	$\tau = 20 \text{ ms}$	$\sim 8 \text{ Hz}$	Equation (8.3), $\alpha = 0.4$ at a 10 ms scan
Open-loop voltage step	$\approx 50\text{--}70 \text{ ms}$	$\sim 3 \text{ Hz}$	Enerpro settling and PLC filter in series
Supervisory update	$\sim 0.5 \text{ s}$	$\sim 1 \text{ Hz}$	EPICS SNL loop rate (§6.7)

Nothing in the plant limits the closed HVPS loop. The loop is closed in EPICS software at roughly 2 Hz (§6.7), so its $\sim 1 \text{ Hz}$ bandwidth is more than an order of magnitude slower than the slowest plant element above. The HVPS is therefore a quasi-static actuator as far as the RF control system is concerned — which is precisely why HVPS ripple (D5, §4.5) must be rejected downstream by the ripple loop and by the direct loop, and cannot be regulated away by the HVPS controller itself.

9 Tuner Mechanics and Resonant Frequency Control

9.1 Cavity Tuner Physical Description

Mechanism and motor data are from the tuner documentation set [R29]–[R33]; the 2023 mechanical inspection findings are in [R28].

Parameter	Value
Motor	Superior Electric Slo-Syn M093-FC11 (NEMA 34D)
Drive mechanism	Worm gear (self-locking)
Tuning range	$\sim \pm 200 \text{ kHz}$
Step resolution	$\sim 1 \text{ Hz/step}$
Distance per microstep	$3.175 \mu\text{m}$ (legacy), $0.05 \mu\text{m}$ (Galil)

9.2 Tuning Physics

The cavity resonant frequency is a smooth, monotonic function of plunger insertion depth over the working range. It is represented in the control software by the cubic-plus-quadratic-voltage model of Eq. (6.13), whose coefficients $p_0 \dots p_3$ and t_1 are obtained by the frequency/detuning calibration described in §10.4.4.

The cavity body also drifts with copper temperature. The first-principles coefficient for an uncooled body is $-7.9 \text{ kHz/}^\circ\text{C}$ (4.8); with the regulated water-cooling circuit in service the *observed* drift referred to

the cavity cooling-water setpoint is roughly an order of magnitude smaller, ~ -1 kHz/°C. The tuner loop of §6.8 absorbs both.

10 Performance Requirements and Verification

10.1 Disturbance Rejection Summary

Disturbance	Frequency	Open-Loop Impact	Rejection	Residual
Beam loading (D1–D2)	DC–100 kHz	Unstable	~ 40 dB	Stable
Robinson (D3)	~ 10 kHz (2.7)	Exponential growth	~ 40 dB	$\ll 1/\tau_s$
HVPS ripple (D5)	360–2000 Hz	$\sim 1\%$ phase	~ 40 dB	$< 0.01\%$
Thermal drift (D8)	< 0.01 Hz	~ 100 Hz/hr	Tuner tracks	< 1 Hz
Klystron gain (D6)	0.01–1 Hz	~ 7 dB var.	Gain tracking	< 0.5 dB

10.2 LLRF9 Commissioning Results

From [R4]: the LLRF9 controller [W4] achieves an improved noise floor relative to the legacy VXI system at 500 mA. Overall amplitude stability $< 0.05\%$ RMS and phase stability $< 0.05^\circ$ RMS — both better than the requirements of §1.4.

10.3 Performance Margins

Parameter	Capacity	Typical	Margin
Klystron power	1.5 MW	~ 782 kW (4×195.6)	$\sim 48\%$
HVPS voltage	90 kV	~ 72 – 77 kV	$\sim 15\%$
Gap voltage/cavity	1 MV	~ 712 kV	$\sim 40\%$
Direct loop BW	~ 930 kHz	~ 800 kHz	$\sim 16\%$
Impedance reduction	~ 40 dB	Required ~ 30 dB	> 10 dB margin

10.4 Calibration Data

Calibration establishes the numerical relationships between raw hardware signals (ADC counts, DAC counts, detector voltages) and physical quantities (kV, kW, degrees, Hz). It is essential for closing all feedback loops accurately. This section is a high-level summary; the measured coefficient tables themselves live with the calibration data files [R38], [R39].

10.4.1 Calibration Sequence Overview

The master calibration is executed by `rf_calib.st,v` (3,345 lines, 28 states including setup and abort handling). It runs as an EPICS SNL program and requires the station to be OFF (no RF power). The sequence progresses through the following phases:

Phase	States	What It Does
Initialization	Startup, CombCheck, Setup	Registers with RFP module, verifies hardware, sets known baseline
Zero all multipliers	ZeroCavMults, ZeroDirMults, ZeroCombMults	Writes zero to all I/Q modulator DACs — establishes the "no signal" baseline for offset measurement
Combiner calibration	Combiner	Calibrates the 4 cavity combining modulators: measures each probe independently, adjusts I/Q matrix for accurate vector sum
Direct loop calibration	Direct, SummingNodeI/Q, GainStageI/Q	Characterizes direct loop gain stages and summing node offsets. I and Q channels measured independently to resolve cross-coupling
Klystron chain	ZeroKlysMults, DiffNodeOffsets, KlysStage, CompStage, CombStage, Klys-Demod	Calibrates klystron forward path: drive modulator offsets, klystron gain, compensator stages, demodulator phase alignment
Tuner & modulator	TuneStage, NullModulator	Calibrates tune-mode drive path; nulls RF modulator output (zero DAC → zero RF)
Completion	Finish/Done or Abort/Abend	Restores operational configuration, reports success/failure

Each state includes retry logic (NUM_TRIES iterations), severity checking on PV readbacks, and abort handling. The entire sequence takes ~2–5 minutes.

10.4.2 Drive Amplitude Calibration

Establishes the mapping from DAC counts to klystron input drive power. Data files: `driveAmpCalibration.xlsx`, `klystronCouplerDriveAmpCalibrations.xlsx`.

The key relationship is the **drive conversion constant** D_{conv} (counts/kV), computed by `subIQamp12conv`:

$$D_{\text{conv}} = \frac{A_{\text{ref}}}{V_{\text{gap}} \cdot (1 + G_{\text{loop}})} \quad (10.1)$$

where A_{ref} is the reference amplitude (counts), V_{gap} is the measured gap voltage (kV), and G_{loop} is the feedback loop gain. This constant is used by the DAC loop (6.14) and recomputed whenever the operating point changes.

10.4.3 Power Measurement Calibration

Maps RF detector voltages to physical power levels. Data files: `reflectedPowerCalibrations.xlsx`, `pulsarCouplerCalibration2049.xlsx`.

The **RF detector conversion loss** measured during calibration (`subIQamp12loss`):

$$L_{\text{det}} = 20 \cdot \log_{10} \left(\frac{E_{\text{conv}} \cdot \sqrt{P_{\text{cal}}}}{A_{\text{det}}} \right) \text{ dB} \quad (10.2)$$

where $E_{\text{conv}} = 0.31623$ (power conversion constant), P_{cal} is calibration power (mW), and A_{det} is measured detector amplitude (V). Accounts for cable attenuation, coupler directivity, and detector nonlinearity.

The **coupling factor** (VSWR-based, `subIQamp1Cp1g`):

$$\beta_{\text{meas}} = \frac{1 + r}{1 - r}, \quad r = \frac{A_{\text{refl}}}{A_{\text{fwd}}} \quad (10.3)$$

10.4.4 Frequency and Detuning Calibration

Maps tuner motor position to cavity resonant frequency offset. The polynomial model (6.13) is fitted from measured data: the tuner is stepped across its range and the resonant frequency measured at each position. Calibration coefficients $p_0, \dots, p_3$ and temperature coefficient t_1 are stored in EPICS PVs.

10.4.5 Tuner Mode DAC Calibration

Data file: `tuneModeDacCalibration.xlsx`. Establishes DAC counts-to-drive-power for the `STATION_TUNE` state (low-power cavity conditioning). Separate from operational drive calibration (§10.4.2) because the operating point differs.

10.4.6 Signal Routing and Patch Panel

Data file: `b132R11PatchPanel.xlsx`. Documents physical signal routing in Building 132 R11: cable lengths, attenuation values, connector types, and signal naming. Essential for verifying the delay budget (§2.4) and signal levels.

Upgrade note: Many calibrations will need adaptation for the LLRF9 system (different ADC/DAC ranges, signal levels, processing gains). The polynomial frequency model (6.13) and combiner matrix calibration are expected to transfer; drive and power detector calibrations require new measurements.

A SPEAR3 RF System Parameter Table

A.1 Storage Ring Parameters

Parameter	Symbol	Value	Unit	Source
Beam energy	E_0	3.0	GeV	[R1]
Beam current	I_b	500	mA	[R1]
Circumference	C	234.14	m	[R2]
Revolution frequency	f_{rev}	1.2804	MHz	Derived
Harmonic number	h	372	—	[R1]
RF frequency	f_{RF}	476.3	MHz	[R4]
Momentum compaction	α_c	1.18×10^{-3}	—	[R2]
Energy loss per turn	U_0	1.02	MeV	Operational (current IDs)
Total RF voltage (design)	V_{RF}	3.2	MV	[R1] [R3]
Total RF voltage (operational)	V_{RF}	~2.85	MV	[R4] [R5]
Synchronous phase	ϕ_s	69.0	deg	Eq. (2.6) (cos convention)
Synchrotron tune	ν_s	~0.008	—	Eq. (2.7); [R1]
Synchrotron frequency	f_s	~10.1	kHz	Eq. (2.7)
Long. radiation damping time	τ_s	2.87	ms	[R1]
Trans. radiation damping time	$\tau_{x,y}$	4.24, 5.14	ms	[R1]

A.2 Cavity Parameters (Per Cavity)

Parameter	Symbol	Value	Unit	Source
Resonant frequency	f_0	≈ 476.3	MHz	[R6]
Shunt impedance (linac)	R_s	3.73	M Ω	[R6]
R/Q	R/Q	~ 116	Ω	[R7]
Unloaded Q	Q_0	32,000	—	[R6]
Loaded Q	Q_L	6,700	—	Derived from $\beta = 3.78$
Coupling coefficient (this doc)	β	3.78	—	Derived
Coupling coefficient (Schwarz actual)	β	3.72	—	[R6]
Coupling coefficient (Schwarz optimum)	β	3.84	—	[R6]
Cavity half-bandwidth	$\Delta f_{1/2}$	35.5	kHz	Derived
Operational gap voltage	V_{gap}	~ 712	kV	[R5]
Beam-induced voltage	$V_{b,\text{res}}$	0.78	MV/cav	Eq. (2.4)
Optimum detuning angle (loaded)	$\psi_{L,\text{opt}}$	≈ -45.7	deg	Eq. (2.9)
Optimum frequency detuning	Δf_{opt}	≈ -36.4	kHz	Eq. (2.10)
Cavity wall losses	P_{wall}	~ 68.1	kW/cav	Eq. (2.12)
Beam power per cavity	$P_{\text{beam}}/n_{\text{cav}}$	~ 127.5	kW/cav	Eq. (2.13)
Generator power per cavity	$P_{\text{gen/cav}}$	~ 196	kW	Eq. (2.14)
Total RF power (4 cav)	$P_{\text{gen,tot}}$	~ 782	kW	$4 \times P_{\text{gen/cav}}$

A.3 Klystron Parameters

Parameter	Value	Unit	Source
Type	Marconi/CPI K3512S	—	[R1]
Maximum power	1.5 MW CW	—	[R1]
Gain	43 dB min	—	[R1]
Bandwidth	5 MHz (-3 dB)	—	[R1]
Group delay	< 150 ns	—	[R1]
Drive power	~ 29 W	—	[R5]
Perveance K	$\sim 1.0 \times 10^{-6}$	A/V $^{3/2}$	§2.3

A.4 Feedback Loop Parameters

Loop	Bandwidth	SPEAR3 Status	Addresses	Source
Direct	~ 800 kHz	Active	D1–D4	[R14]
Comb	2 MHz	Not used	D4	[R14]

Loop	Bandwidth	SPEAR3 Status	Addresses	Source
Ripple	~ 300 Hz	Active	D5	[R14]
Gap FF	100 Hz	Not used	D2	[R14]
HVPS	~ 1 Hz	Active	D6	[R14]
Tuner	~ 0.01 – 1 Hz	Active	D7, D8, D9	[R14]
DAC	~ 0.1 Hz	Active	Amplitude drift	[R14]
LFB Woofer	1 MHz	Not used	D2, D4	[R15], [R41]

B Source Document Reference Index

B.1 Published Papers

The **Web** column links to the external locator listed in §B.4.

Ref	Citation	Web
[R1]	McIntosh, P. et al., "The SPEAR3 RF System," SLAC-PUB-10983, EPAC 2004	[W1], [W2]
[R2]	Hettel, R. et al., "Design of the SPEAR 3 Light Source," PAC 1999	—
[R7]	Rimmer, R.A. et al., "RF Cavity Development for the PEP-II B Factory," LBL-33360, 1992	—
[R11]	Gamp, A., "Beam-Cavity Interaction," CAS 2011, arXiv:1112.3203	[W3]
[R12]	Wilson, P.B., "Fundamental-Mode RF Design," SLAC-PUB-6062, 1993	—
[R13]	Boussard, D., "Control of Cavities with High Beam Loading," PAC 1985	[W5]
[R15]	Corredoura, P., "Architecture and Performance of the PEP-II Low-Level RF System," SLAC-PUB-8124, PAC 1999	—
[R16]	Robinson, K.W., "Stability of Beam in RF Systems," CEA-CEAL-1010, 1964	—
[R17]	Rimmer, R.A. et al., "Comparison of Calculated, Measured, and Beam Sampled Impedances," PRSTAB 3, 102001, 2000	—
[R21]	Cassel, R. and Nguyen, M.N., "A Unique Power Supply for the PEP II Klystron," SLAC-PUB-7591, PAC 1997. Repository copy: hvps/architecture/originalDocuments/slac-pub-7591.pdf	—
[R25]	Bourbeau, E.J., "Application of PLL Techniques to SCR Drives," IEEE 1983	—
[R41]	Fox, J.D. et al., "Multi-Bunch Longitudinal Feedback — Woofer and Kicker Architecture," PEP-II LFB system design note	—

B.2 Textbooks

Ref	Citation
[R3]	SSRL SPEAR Storage Ring Parameters, https://www-ssrl.slac.stanford.edu/accphy/spear_parameters.html (last updated 26 Apr 2002, H.-D. Nuhn)
[R10]	Wiedemann, H., <i>Particle Accelerator Physics</i> , 4th ed., Springer, 2015
[R18]	Analog Devices AD834 datasheet
[R40]	Åström, K.J. and Murray, R.M., <i>Feedback Systems: An Introduction for Scientists and Engineers</i> , 2nd ed., Princeton, 2021 (Ch. 12, loop interaction)

B.3 Repository Documents

Ref	Document	Path
[R4]	LLRF9 Commissioning Tests	11rf/tests/11rf9Tests.pdf
[R5]	System Design Report	Designs/tex/doc0-system-design/0_system_design_report.pdf
[R6]	RF System Description (Schwarz)	11rf/documentation/legacyArchitecture/ps3403305100.pdf
[R14]	Feedback Loop Description (Schwarz, PS-340-330-52-R0)	11rf/documentation/legacyArchitecture/ feedbackLoopDescriptionps3403305200.pdf
[R22]	HVPS Technical Spec (PS-341-360-01-R2)	hvps/architecture/originalDocuments/ps3413600102.pdf
[R23]	HVPS Simulation Config	hvps/simulation/hvps_sim/config.py
[R26]	Enerpro firing-board schematics and manuals (FCOG6100 in service, FCOG1200 for the upgrade)	hvps/controls/enerpro/enerproDocuments/
[R27]	Cassel PLC Code	hvps/documentation/plc/CasselPLCCode.pdf
[R28]	Cavity Tuner Inspection Report, 13 June 2023	11rf/tuners/cavityTunerInspections20230613.docx
[R29]	Tuner mechanical design paper, PAC 1997	11rf/tuners/tunerDesignPac97HDS8P030.PDF
[R30]	Superior Electric SLO-SYN stepper motor data	11rf/tuners/SLO-SYN.pdf
[R31]	SLO-SYN MD808 Stepper Drive Manual	11rf/tuners/SLO-SYN_MD808_Stepper_Drive_Manual.pdf
[R32]	SLO-SYN SS2000MD4M Step Drive / Translator Manual	11rf/tuners/SLO-SYN_SS2000MD4M_Step_Drive_Translator_ Manual.pdf
[R33]	Superior Electric stepper catalogue (legacy)	11rf/tuners/Old Stepper Catalog_Superior Electric_0.pdf
[R34]	Tuner Loop Source Code	spear-rf-code-legacy/rfApp/src/seq/rf_tuner_loop.st,v
[R35]	Galil Commissioning Notes	11rf/tuners/galil/GalilCommissioning.docx
[R36]	DSP Ripple Firmware	spear-rf-code-legacy/rfApp/src/dsp/rfpDsp/ripple.s,v
[R38]	RF Calibration Data	11rf/calibrations/*.xlsx
[R39]	RF Document Index	11rf/documentation/RfSystemDocumentIndexR3.xlsx

B.4 External Web References

Ref	URL	Content
[W1]	https://inspirehep.net/files/945e7ff73cc428af4c018fd1bdb6afa7	[R1] McIntosh, EPAC 2004
[W2]	https://www.osti.gov/biblio/839730	[R1] OSTI record, SLAC-PUB-10983
[W3]	https://export.arxiv.org/pdf/1112.3203v1.pdf	[R11] Gamp, CAS 2011
[W4]	https://www.dimtel.com/products/11rf9	Dimtel LLRF9 product page (upgrade controller)
[W5]	https://proceedings.jacow.org/p85/PDF/PAC1985_1852.PDF	[R13] Boussard, PAC 1985

C Symbol and Notation Conventions

C.1 Cavity and Beam Parameters

Symbol	Definition	Unit	First Ref
f_0	Cavity resonant frequency	MHz	Eq. (2.2)
f_{RF}	RF operating frequency ($= h \cdot f_{\text{rev}}$)	MHz	§1.2
f_{rev}	Revolution frequency	MHz	§1.2
ω_0	Angular resonant frequency ($= 2\pi f_0$)	rad/s	Eq. (2.2)
$\omega_{1/2}$	Cavity half-bandwidth ($= \omega_0/2Q_L = 2\pi \times 35.5 \text{ kHz}$)	rad/s	Eq. (2.1)
$\Delta f_{1/2}$	Cavity half-bandwidth (linear frequency)	kHz	Eq. (2.3)
Q_0	Unloaded quality factor	—	§2.2.1
Q_L	Loaded quality factor	—	§2.2.1
Q_{ext}	External quality factor (coupling port)	—	§2.2.1
β	Coupling coefficient ($= Q_0/Q_{\text{ext}}$)	—	§2.2.1
R_s	Shunt impedance (circuit convention: $V^2/2P$)	M Ω	§2.2.1
R_a	Shunt impedance (accelerator convention: $V^2/P = 2R_s$)	M Ω	§C.2
V_{gap}	Gap voltage per cavity	kV	§2.2.1
V_{RF}	Total RF voltage ($= n_{\text{cav}} \times V_{\text{gap}}$)	MV	§2.2.3
I_b	DC beam current	A	§2.2.3
I_{b1}	Fundamental RF component of the bunched beam current ($= 2I_b$)	A	Eq. (2.4)
$V_{b,\text{res}}$	Beam-induced voltage at resonance ($= I_b R_s$)	MV	Eq. (2.4)
ϕ_s	Synchronous phase angle (from voltage crest)	de-grees	Eq. (2.5)
ψ	Detuning angle	de-grees	Eq. (2.8)
ψ_0, ψ_L	Detuning angle referred to the unloaded / loaded bandwidth ($\tan \psi_L = \tan \psi_0/(1 + \beta)$)	de-grees	Eq. (2.9)

Symbol	Definition	Unit	First Ref
ψ_{opt}	Optimum detuning angle	de-grees	Eq. (2.9)
a	Beam loading parameter, real part ($= P_{\text{beam}}/P_{\text{wall}}$)	—	Eq. (7.1)
b	Beam loading parameter, reactive part	—	Eq. (7.1)
t	Normalised detuning ($= \tan \psi_0 = 2Q_0 \Delta f / f_0$)	—	Eq. (7.1)
Γ	Voltage reflection coefficient at the input coupler	—	Eq. (7.2)
β_{opt}	Coupling that matches the loaded cavity ($= 1 + a$)	—	Eq. (7.3)
Δf	Frequency detuning ($= f_0 - f_{\text{RF}}$)	kHz	Eq. (2.10)
$\Delta \omega$	Angular frequency offset from RF	rad/s	Eq. (2.2)
U_0	Energy loss per turn (synchrotron radiation)	MeV	§1.2
h	Harmonic number ($= f_{\text{RF}}/f_{\text{rev}}$)	—	§1.2
α_c	Momentum compaction factor	—	Eq. (2.7)
ν_s	Synchrotron tune ($= f_s/f_{\text{rev}}$)	—	Eq. (2.7)
f_s	Synchrotron frequency	kHz	Eq. (2.7)
E_0	Beam energy (3.0 GeV; expressed in MeV when used with V_{RF} in MV)	GeV	Eq. (2.7)
n_{cav}	Number of cavities	—	Eq. (2.11)

C.2 Klystron and Drive Parameters

Symbol	Definition	Unit	First Ref
K_{kly}	Klystron small-signal voltage gain	— or dB	Eq. (2.15)
τ_{kly}	Klystron group delay	ns	Eq. (2.15)
$G_{\text{kly}}(s)$	Klystron transfer function ($K_{\text{kly}} e^{-s\tau_{\text{kly}}}$)	—	Eq. (5.1)
P_{sat}	Klystron saturation power	MW	Eq. (2.16)
$P_{\text{in,sat}}$	Klystron input power at saturation	W	Eq. (2.16)
V_k	Klystron cathode voltage	kV	§6.7
P_{fwd}	Klystron forward power	kW	§6.10
P_{drive}	Klystron drive power	W	§6.10

C.3 Loop Transfer Functions and Compensator Parameters

Symbol	Definition	Unit	First Ref
$G_{\text{OL}}(s)$	Direct loop open-loop transfer function	—	Eq. (5.1)
G_{prop}, K_p	Proportional gain	— or dB	Eq. (5.1)
$G_{\text{lead}}(s)$	Lead compensator: $(1 + s/\omega_z)/(1 + s/\omega_p)$	—	Eq. (5.1)
$G_{\text{int}}(s)$	PI integrator: $1 + \omega_i/s$	—	Eq. (5.1)

Symbol	Definition	Unit	First Ref
ω_z	Lead compensator zero frequency	rad/s	§6.2
ω_p	Lead compensator pole frequency	rad/s	§6.2
ω_i	Integrator unity-gain frequency ($\approx 2\pi \times 30$ kHz)	rad/s	§6.2
$H_{\text{cav}}(s)$	Cavity transfer function	—	Eq. (2.1)
τ_d	Total loop delay	ns	Eq. (2.18)
f_c	Crossover frequency (where $ G_{\text{OL}} = 1$)	kHz	Eq. (2.18)
$T(s)$	Closed-loop transfer function	—	Eq. (5.2)
Z_{eff}	Effective impedance with feedback	Ω	Eq. (5.3)
Z_{cav}	Cavity impedance without feedback	Ω	Eq. (2.2)
$L_1(s), L_2(s)$	Fast and slow loop transfer functions	—	Eq. (5.4)
G_0	DC plant gain	—	Eq. (2.19)

C.4 Comb Filter and Group Delay Equalization Parameters

Symbol	Definition	Unit	First Ref
z	Z-transform variable ($e^{j\omega T_s}$)	—	Eq. (6.2)
n	Comb delay in samples, one revolution period ($= f_{\text{samp}}/f_{\text{rev}}$)	—	Eq. (6.2)
G	Comb feed-forward gain	—	Eq. (6.2)
K	Comb feedback coefficient ($ K < 1$)	—	Eq. (6.2)
G_{peak}	Comb tooth peak gain ($= G/(1 - K)$)	—	§6.3
$H_{\text{eq}}(z)$	Group delay equalizer (32-tap FIR)	—	Eq. (6.4)
c_k	FIR equalizer coefficients ($k = 0 \dots 31$)	—	Eq. (6.4)
$G_{\text{OL,comb}}(z)$	Comb path open-loop transfer function	—	Eq. (6.5)
n_{delay}	Hardware transport delay (samples)	—	Eq. (6.5)
$Z_{\text{eff,D+C}}$	Effective impedance with Direct + Comb	Ω	Eq. (6.3)

C.5 LFB Woofer Parameters

Symbol	Definition	Unit	First Ref
K_{woofer}	Woofer injection gain	—	Eq. (6.6)
$H_{\text{FIR}}(s)$	Woofer group delay equalizer (shared with comb)	—	Eq. (6.6)
τ_{woofer}	Woofer one-turn injection delay	μs	Eq. (6.6)
$\Delta \vec{V}_{\text{LFB}}(s)$	LFB correction signal (from TAXI fiber)	V	Eq. (6.6)
$\vec{V}_{\text{ref,total}}$	Total I/Q reference (static + woofer)	V	Eq. (6.6)

C.6 Ripple Loop Parameters

Symbol	Definition	Unit	First Ref
$\hat{A}_k, \hat{B}_k$	Estimated harmonic coefficients (cosine, sine)	counts	Eqs. (6.7) and (6.8)
μ_k	Adaptation gain for harmonic k	—	Eq. (6.7)
f_{line}	AC line frequency (60 Hz)	Hz	Eq. (6.7)
T_s	DSP sampling period (1/23 kHz)	s	Eq. (6.7)
$e[n]$	Phase error at sample n	rad	Eq. (6.7)

C.7 Slow Loop Parameters

Symbol	Definition	Unit	First Ref
K_{HVPS}	HVPS loop proportional gain	V/W	Eq. (6.10)
P_{deadband}	HVPS loop deadband	W	Eq. (6.10)
ε	Tuner detuning angle error	degrees	Eq. (6.11)
ψ_{target}	Target detuning angle	degrees	Eq. (6.11)
N_{step}	Tuner steps per correction cycle	steps	Eq. (6.12)
$p_0 \dots p_3$	Frequency offset polynomial coefficients	kHz, kHz/step, ...	Eq. (6.13)
t_1	Voltage-dependent detuning coefficient	kHz/kV ²	Eq. (6.13)
x, x_{home}	Tuner position, home position	steps	Eq. (6.13)
K_{DAC}	DAC loop proportional gain (0–1)	—	Eq. (6.14)
D_{conv}	DAC conversion factor	counts/kV	Eq. (6.14)
G_{loop}	Direct loop gain correction factor	—	Eq. (6.14)
$G_{\text{modulator}}$	Baseband modulator gain (adjustable)	—	Eq. (6.15)
$G_{\text{loop,target}}$	Target constant loop gain	—	Eq. (6.15)

C.8 Calibration Parameters

Symbol	Definition	Unit	First Ref
D_{conv}	Drive conversion constant (counts/kV)	counts/kV	Eq. (10.1)
A_{ref}	Reference DAC amplitude	counts	Eq. (10.1)
L_{det}	RF detector conversion loss	dB	Eq. (10.2)
E_{conv}	Power conversion constant (0.31623)	—	Eq. (10.2)
P_{cal}	Calibration power	mW	Eq. (10.2)
β_{meas}	Measured coupling factor (VSWR-based)	—	Eq. (10.3)
r	Reflection coefficient magnitude	—	Eq. (10.3)

C.9 I/Q Signal Processing

Symbol	Definition	Unit	First Ref
$I(t), Q(t)$	In-phase, quadrature baseband components	V	Eq. (3.1)
$A(t)$	Amplitude $[= \sqrt{I^2 + Q^2}]$	V	Eq. (3.2)
$\phi(t)$	Phase $[= \text{atan2}(Q, I)]$	rad	Eq. (3.2)
G (in Eq. (3.3))	Baseband modulator gain	—	Eq. (3.3)
θ	Baseband modulator rotation angle	rad	Eq. (3.3)
$\vec{E}$	Error vector $[= \vec{V}_{\text{ref}} - \vec{V}_{\text{probe}}]$	V	Eq. (3.4)

C.10 Conventions

1. **Shunt impedance:** $R_s = V^2/(2P)$ throughout (circuit convention). Accelerator convention $R_a = 2R_s$.
2. **Synchronous phase:** ϕ_s measured from voltage crest (SLAC convention): $V_{\text{RF}} \cos \phi_s = U_0$.
3. **Detuning:** $\Delta f = f_0 - f_{\text{RF}}$. Negative = cavity below RF (normal above transition).
4. **Laplace variable:** $s = \sigma + j\omega$; for frequency response analysis, $s = j\omega$.
5. **Arrow notation:** Baseband I/Q vectors (e.g. $\vec{V}_{\text{ref}}$, $\vec{E}$).
6. **Hat notation:** Estimated quantities (e.g. $\hat{A}_k$).
7. **Reference tags:** $[Rn]$ = numbered reference (§B), $[Wn]$ = external web locator, Dn = disturbance class (§4.1).
8. **Equation numbering:** equations are numbered automatically as (section.sequence) and are always cited through a cross-reference, never by a literal number.

End of Document