Tab-88 Bluetooth Keyboard Specification
V0.1

System Requirements:

- APPLE MAC PRO / iPad / iPad 2/ iPhone 4 which build in Bluetooth receiver.
- MAC OS 10.xx or later.

Features:

- Support Language: US, Europe, Chinese, Japanese
- Ultra Slim & Scissors structure design
- Compatibility with Mac Pro, iPad, iPad 2, iPhone 4, Galaxy Tab.
- Keyboard duo Function: F1 to F12 have duo functions are for iPad, iPhone.
- Active Range: around 10 meter
- Auto Connect Button: Available
- Built-in Reed Switch to control power ON/OFF is for convenient design.
- 3 LED indicators 4 status for Battery Low alert, Recharge and Bluetooth Connectivity (Caps Lock).

Specifications:
- Bluetooth V 3.0 specification compliant.
- Bluetooth HID profile V 1.1 compliant.
- Frequency Range: 2.4G ~ 2.4835GHz
- Peak Power consumption: 2.5 mA Max
- Build in 3.7V, 300mA Lithium Battery, can be rechargeable.
- Sleep mode Power consumption: 30uA
- Security Encryption: 128 bits
- Support AFH (Adaptive Frequency Hopping).
- Key Force: 55±7g
- Key Travel: 2.0+/- 0.3mm
- Switch Life: 10 Million Cycles
- Keyboard Dimensions: 285(L) x 170(W) x 8 (H) mm
- Weight: 180 ± 20 g

Safety

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.