

---

# **Yangtze Alligator Mouse User Manual**

---

**2.4GHz Wireless Multimedia GameMouse  
with  
PC Remote Control Function**

MSN Online Support: [support@quickerstyle.com](mailto:support@quickerstyle.com)

[www.quickerstyle.com](http://www.quickerstyle.com)

©GOEASILY INT'L CO., Ltd. 2010

## Package List

- Yangtze Alligator Mouse;
- Nano Receiver;
- MouseWare Disc;
- 1pc Disposable AA Battery.



## Product Parameter List

### Basic Parameters:

Brand Name	QuickerStyle
Featured Type	Multimedia Wireless GameMouse With Remote Control Function
Mouse Type	Optical Mouse/Laser Mouse
Connection Type	Wireless
Transmission Band	2.4GHz
Buttons & Keys	Mouse: 7 keys、1 scroll wheel
	Joypad: 14 buttons
Interface Type	USB1.1 version / Plug & Forget / Intelligent ID Link
Rated Operational Voltage	1.5V
Rated Operational Current	Optical Mouse:30mA / Laser Mouse:20mA
System Platform	Windows 95/98/2000/NT/ME/XP/Vista/Win 7
Weight	115g (without battery inside)

### Technical Parameters:

Resolution	Optical Sensor: 400/800/1000/1200/1600dpi (adjustable)
	Laser Sensor: 800/1000/1200/1600/2000dpi (adjustable)
Sampling Frequency	125Hz
Ergonomics	Support
Optical Sensor	Pixart Sensor

### Other Parameters:

Other Features	Macro Definition, Shortcut Key Settings & Custom Application Settings
	Multimedia PC Remote Control, Game Joypad Function

## Functionality Outline


- Hi-performance low-power consumption central processor;
- 1pc AA battery power supply;
- Multi-Work Modes: Mouse Mode / Joypad Mode / Remote Control Mode / Customize Pad Mode / Mouse & Joypad Mode / Mouse & Remote Control Mode / Mouse & Customize Pad Mode;
- Hi-quality dynamic 2.4GHz frequency hopping communication technology, barrier-free transmission in a range of 10-15 meters;
- 2.4GHz two-way communication technology stably expedites data transmission;
- Nano receiver can be pocketed inside the mouse, more manageable & unforgettable to carry;
- Hi-performance single chip receiver supports standard USB1.1 communication protocol;
- High sensitive optical sensor supports 400/800/1000/1200/1600dpi switch (Laser sensor supports 800/1000/1200/1600/2000dpi switch);
- Built in charging circuit, low battery & charging status LED indicator (Low battery, red LED flickers; LED becomes green while charging and lights off after battery is fully charged);
- After MouseWare is installed, mouse 7 keys' functions can be redefined in GameMouse Setting page;
- After switching to Joypad Mode, you can enjoy all PC games that support joypad operation;
- Under Joypad Mode, joypad buttons' functions can be customized according to your gaming habits;
- Two 3D analog sticks on the joypad can achieve different functions in different PC games;
- Marco Definition: you can record keyboard activities for mouse buttons to simplify & accelerate your operation;
- Under Remote Control Mode, Yangtze Alligator Mouse can be applied as PC remote control. (After relevant settings in Remote Control page, you can control your PC conveniently and remotely, such as: media player control, opening applications, PC sleep & wake-up, PC power off etc.);

- p) Mouse firmware fully complies with “HID compliant game controller” standard and “HID compliant optical mouse” standard;
- q) Firmware auto-sleep & move wake-up capability.


### **Product Mould Information**

- a) Streamlined design, stylish appearance, comfortable handfeel, flexible operation;
- b) Pull-Button Battery Cover Design & Receiver Pocketed-Inside Principle make Yangtze Alligator Mouse more elegant and manageable;
- c) Creative Gear-Lock can effectively lock mouse left & right buttons to avoid interference while playing games.

### **MouseWare Installation**








- a) Pull-open mouse battery cover upwards, take out receiver, correctly fix battery and close battery cover;
- b) Plug receiver into PC USB port, turning on mouse power after device initialization is completed, after ID link between mouse & receiver is well established, mouse can be workable within a range of 10-15 meters;
- c) Place MouseWare Disc into PC CD-ROM, find & double click on icon , then follow on screen instructions to finish MouseWare installation:
- d) After MouseWare is fully installed, we recommend you to choose restart your computer, especially Vista system;

- e) After restart, a mouse icon  will appear in the taskbar at the right

bottom of the screen, right click that icon, a menu  will pop up (You can redefine mouse parameters and hide icon etc.):

### **Work Modes**

Yangtze Alligator Mouse has the following seven work modes:

-  Mouse Mode;
-  Joypad Mode;
-  Remote Control Mode;
-  Customize Pad Mode;
-  Mouse & Joypad Mode;
-  Mouse & Remote Control Mode;
-  Mouse & Customize Pad Mode.

After switching work mode, the corresponding mode status icon will appear in the taskbar,

e.g. .

### **Other Precautions**

- a) Battery Specification: AA battery (⚠ While battery charging, do make sure your battery is rechargeable. Manufacturer takes no responsibility for the results caused by wrong operation.);
- b) The complimentary AA battery inside the package is disposable, please purchase rechargeable battery, mini USB data cable or battery charger by yourself;
- c) To successfully establish ID link, please keep mouse & receiver within 1 meter;
- d) After ID link is established, only mouse function & joypad function are available without installing MouseWare; if you want to enjoy PC remote control function, macro definition & custom application program settings, please install MouseWare;
- e) Under Mouse & Joypad Mode, the 4 mouse side buttons will perform joypad L1,L2,R1 & R2's duty;
- f) Under Joypad Mode or Mouse & Joypade Mode, please press down "SELECT" & "START" buttons together to activate Remote Control Mode;

- g) To reuse mouse after power is cut off, please directly turn on battery power and use, no need to replug receiver and re-establish ID link;
- h) Don't dismantle mouse and nano receiver if you're non-professional so as to avoid internal component damage;
- i) Please use dry and soft cotton cloth to clean the mouse;
- j) Please put the exhausted batteries into battery recycling bin, don't arbitrarily discard or throw them into the fire.

**FCC ID: YDXQX-169A**

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.