Superconducting Devices

From Strong Magnetic Fields to Ultra-Sensitive Sensing

Superconductivity and Quantum Materials

Filippo Vicidomini
Ca' Foscari University of Venice

April 2026

Contents

1 Superconducting Devices: From Strong Magnetic Fields to Ultra-Sensitive Sensing 2

1.1 Introduction . . . 2

1.2 One Physics, Two Device Families . . . 2

1.3 What is a Superconductor? . . . 2

1.3.1 What Changes at the Quantum Level? . . . 3

1.4 Macroscopic Phase and Josephson Effect . . . 3

1.5 From Josephson Junction to SQUID . . . 4

1.6 Why SQUIDs Matter . . . 5

2 Applications 5

2.1 Magnetoencephalography (MEG) . . . 5

2.1.1 MEG System and Advantages . . . 6

2.2 Buried-Metal Detection . . . 6

2.2.1 Buried-Metal Detection: Why SQUIDs? . . . 7

2.3 Water Treatment . . . 7

2.3.1 Water Treatment: Role of Superconductivity . . . 8

2.4 Comparison . . . 8

3 Limits and Outlook 9

4 Conclusion 9

5 References 10

1 Superconducting Devices: From Strong Magnetic Fields to Ultra-Sensitive Sensing

1.1 Introduction

What to say:
Superconductivity is often introduced as a beautiful but quite abstract topic in condensed matter physics. In this talk, I want to show the opposite perspective: the same physical principles can be turned into very concrete technologies.

In particular, superconductivity opens two complementary routes. On one side, it allows us to generate very strong magnetic fields with very low dissipation. On the other side, it allows us to detect extremely weak magnetic signals with extraordinary precision.

So the main message of the talk is simple: one underlying physics, but two very different device families, leading to very different applications.

1.2 One Physics, Two Device Families

Slide content:
Superconductivity → High-field magnets / SQUID sensors

Applications:

- Water treatment
- MEG
- Buried-metal detection

What to say:
The structure of the talk is intentionally simple. I will begin with the essential physical properties of superconductors, then move to the Josephson effect, which is the key ingredient for superconducting electronics.

From there, I will show how the same physics leads to two device families. The first is based on producing strong magnetic fields, mainly through superconducting magnets. The second is based on ultra-sensitive magnetic sensing, mainly through SQUIDs.

Finally, I will connect these ideas to three concrete applications: water treatment, magnetoencephalography, and buried-metal detection.

1.3 What is a Superconductor?

Slide content:

- Zero electrical resistance
- Meissner effect
- Type-II vortices

What to say:
A superconductor is not just a material with very low resistance. It is a distinct quantum state of matter that appears below a critical temperature.

The first famous property is zero electrical resistance, meaning that an electric current can flow without dissipation. But this alone is not the full story.

The defining feature is the Meissner effect: magnetic fields are expelled from the interior of the material. This tells us that superconductivity is not simply perfect conductivity, but a new thermodynamic phase with its own electromagnetic behavior.

In many practical materials, especially type-II superconductors, magnetic flux can still enter in the form of quantized vortices when the external field is high enough. This is extremely important technologically, because it allows superconductivity to survive even in strong magnetic fields.

So the key point to remember here is this: superconductivity combines zero resistance, magnetic-field expulsion, and quantized magnetic behavior in the same physical state. The next question is why matter reorganizes itself in this way at the quantum level.

1.3.1 What Changes at the Quantum Level?

Slide content:

- In a normal metal, electrons scatter independently
- Below T_c, electrons form Cooper pairs
- Pairs condense into one coherent quantum state
- An energy gap Δ protects the condensate

What to say:
This is the microscopic transition behind superconductivity.

In an ordinary metal, electrons behave mostly as independent particles. As they move through the crystal, they scatter off lattice vibrations, defects, and other excitations, and this scattering is what produces electrical resistance.

Below the critical temperature, the situation changes. An effective attractive interaction, usually mediated by lattice vibrations, allows electrons near the Fermi surface to form bound pairs, called Cooper pairs. Each pair contains two electrons with opposite momentum and opposite spin.

These pairs do not act like isolated molecules. A macroscopic number of them condenses into the same collective quantum state, so the material develops long-range coherence.

At the same time, an energy gap opens in the excitation spectrum. This means that small perturbations are no longer enough to break pairs or scatter the condensate in the usual way.

So the matter is reorganized at the quantum level: instead of many independent electrons, we have a coherent condensate of paired electrons. This microscopic change is what later gives us zero resistance, flux quantization, and the Josephson effect.

1.4 Macroscopic Phase and Josephson Effect

Slide content:

$$\psi = |\psi| e^{i\theta}$$

$$I_s = I_c \sin \varphi$$

(Optional)

$$\frac{d\varphi}{dt} = \frac{2eV}{\hbar}$$

What to say:
Once this coherent condensate exists, the superconducting state can be described by a macroscopic wavefunction, written as $\psi = |\psi|e^{i\theta}$. The important quantity here is the phase θ.

In a normal conductor, phase is not something we can use at the macroscopic level. In a superconductor, instead, the phase remains coherent over large distances and becomes physically meaningful.

This leads directly to the Josephson effect. If two superconductors are separated by a very thin insulating barrier, Cooper pairs can tunnel from one side to the other.

The first Josephson relation tells us that the supercurrent depends on the phase difference: $I_s = I_c \sin\varphi$. So a quantum variable, the phase difference, directly controls a measurable current.

The second relation says that if a voltage is applied, the phase difference changes in time, $\frac{d\varphi}{dt} = \frac{2eV}{\hbar}$. So current is linked to phase, and voltage is also linked to phase.

This is the conceptual bridge we need for the rest of the talk. Superconductivity is not only about lossless current transport, but also about controlling a macroscopic quantum phase. And once phase becomes accessible, we can build devices based on interference.

1.5 From Josephson Junction to SQUID

Slide content:

- Superconducting loop
- Two Josephson junctions
- Magnetic flux modifies interference

$$\Delta\Phi \to \Delta V$$

What to say:
If we place two Josephson junctions in a superconducting loop, we obtain a SQUID: a Superconducting Quantum Interference Device.

The key idea is that the superconducting phase around the loop cannot vary arbitrarily. Because of flux quantization, the total phase change around the loop is constrained by the magnetic flux threading the loop.

So when an external magnetic flux is applied, it changes the phase configuration of the device. The two junctions therefore interfere with each other, and the total critical current becomes a periodic function of magnetic flux.

In practice, the device is biased in a regime where this dependence is very steep. Then even a tiny change in magnetic flux produces a measurable change in the electrical output, usually a voltage.

So the chain is the following: magnetic flux changes the phase, the phase changes the interference, and the interference changes the electrical signal.

This is why the SQUID is such a powerful sensor: it converts extremely small magnetic signals into measurable voltages through quantum interference.

1.6 Why SQUIDs Matter

Slide content:

- Ultra-high sensitivity
- Detects fields far below Earth's background
- Passive sensing
- Works where other sensors fail

What to say:
The main reason SQUIDs are so important is their extraordinary sensitivity. They are among the most sensitive magnetometers ever developed.

Under suitable conditions, they can detect magnetic fields down to the femtotesla range. To appreciate how small this is, the Earth's magnetic field is of the order of tens of microtesla, so SQUIDs can detect signals many orders of magnitude weaker than the magnetic background around us.

This makes them essential in applications where the signal is extremely weak, where the measurement must be non-invasive, or where low-frequency performance is crucial. In many of these situations, conventional magnetic sensors are simply not sensitive enough.

2 Applications

2.1 Magnetoencephalography (MEG)

Slide content:

- Neuronal currents $\rightarrow$ magnetic fields
- Signals $\sim$ 10–100 fT
- Non-invasive measurement
- SQUID array ($\sim$300 sensors)

What to say:
Magnetoencephalography, or MEG, is one of the clearest real-world applications of SQUID technology.

The signal originates from neuronal currents in the brain, mainly due to synchronized activity of pyramidal neurons. These currents generate magnetic fields that extend outside the head.

However, these signals are extremely weak, typically in the range of 10 to 100 femtotesla. To give a sense of scale, they are about a billion times smaller than the Earth's magnetic field.

This is exactly where SQUIDs become essential. Their extreme sensitivity allows us to detect these signals in a completely non-invasive way.

In practice, MEG systems use large arrays of SQUID sensors, often around 300 channels, placed inside a cryogenic helmet surrounding the head. The system records brain activity with millisecond temporal resolution, making it ideal for studying fast neural dynamics.

2.1.1 MEG System and Advantages

Slide content:

- Cryogenic helmet (dewar)
- ms temporal resolution
- Less distortion than EEG
- Better source localization

What to say:
From a system perspective, MEG relies on a cryogenic environment. The SQUID sensors must be kept at very low temperature, typically using liquid helium, inside what is called a dewar.

One of the main strengths of MEG is its excellent temporal resolution, on the order of milliseconds, which allows us to follow brain activity in real time.

Compared to EEG, magnetic fields are less affected by the skull and scalp. This means that the measured signals are less distorted, and source localization is more direct.

So overall, MEG combines non-invasive measurement, high temporal resolution, and relatively accurate spatial localization, making it a powerful tool both in neuroscience research and in clinical applications such as epilepsy diagnosis.

2.2 Buried-Metal Detection

Slide content:

- Excitation field
- Induced currents in target
- Weak secondary field
- SQUID detection

What to say:
This application belongs to the sensing branch, but the mechanism is different from MEG. Here the key idea is electromagnetic induction.

A primary coil generates an alternating magnetic field that penetrates the ground. When this field encounters a buried metallic object, it induces circulating currents inside the target, called eddy currents.

These eddy currents generate a secondary magnetic field. So the buried object does not simply block the field: it produces its own magnetic response, and this response carries information about the presence, size, and shape of the object.

At this point, the natural question is: why are SQUIDs useful here, instead of an ordinary metal detector?

The answer is that the secondary field is extremely weak compared both to the excitation field and to the environmental magnetic background. So the real challenge is not generating the signal, but detecting it reliably.

2.2.1 Buried-Metal Detection: Why SQUIDs?

Slide content:

- Extremely weak secondary field
- High sensitivity in the fT range
- Low-frequency operation → deeper penetration
- UXO and mine detection

What to say:
This is exactly where SQUID sensors become valuable.

Because of their extremely high sensitivity, they can detect the weak secondary magnetic field produced by the buried target, even in a noisy environment.

Another important advantage is that SQUIDs can operate at low frequencies. This is useful because lower frequencies penetrate deeper into the ground, so the system can detect objects buried at greater depths.

This is why SQUID-based systems are interesting not only for generic metal detection, but also for more demanding applications such as unexploded ordnance detection.

In that context, the goal is not just to say that some metal is present. The system should help distinguish dangerous buried objects from harmless metallic debris, which is one of the reasons why high sensitivity and better signal characterization matter.

2.3 Water Treatment

Slide content:

- Magnetic tagging of pollutants
- HGMS as a magnetic filter
- Strong local gradients: need high $B\nabla B$
- Removal efficiency >95%

What to say:
This application shows the strong-field branch of superconductivity.

The starting point is that most pollutants are not magnetic, so we cannot remove them directly using a magnetic field.

To solve this, we first attach pollutants to magnetic particles, typically iron oxide particles or nanoparticles. In this way, contaminants become magnetically responsive.

The water is then sent through a high-gradient magnetic separation system, or HGMS. In practical terms, an HGMS system includes an excitation coil, a magnetic yoke, and a separation region containing a ferromagnetic matrix. In some industrial designs, there is also a rotating ring or pulsating mechanism that helps continuous operation and reduces clogging.

Under the action of the water flow, the suspension enters the separator. Inside the magnetic field, the tagged particles are attracted toward the magnetized matrix and form magnetic aggregates, while the non-magnetic part of the flow continues forward.

As the separator rotates or as the flow is periodically flushed, the captured material is carried to a lower-field region and removed. So the process is not only capture, but also continuous collection and discharge of the concentrated waste.

Because of the ferromagnetic structure, very large local field gradients are created. These gradients generate the magnetic force that pulls the tagged particles toward the matrix, while cleaner water continues to flow.

In many practical implementations, removal efficiencies above 95% are reported, even for very small particles, which makes this technique highly effective for water purification.

2.3.1 Water Treatment: Role of Superconductivity

Slide content:

- Need strong magnetic field
- Create high gradients
- Continuous separation
- Energy-efficient at scale

What to say:
The key technological role of superconductivity here is to generate strong and stable magnetic fields.

These strong fields magnetize the iron yoke and the ferromagnetic matrix inside the separator, creating the high-gradient conditions needed for capture. So the important quantity is not only the field itself, but also its spatial variation.

This is why HGMS is more than simply putting water near a magnet. The device must combine field generation, flow control, and an engineered magnetic structure that concentrates the gradients where separation takes place.

Superconducting magnets are especially useful because they can provide these strong fields continuously with low energy dissipation, which is very important for large-scale systems.

So, differently from MEG, where superconductivity is used for sensitivity, here it is used to create the magnetic environment needed to physically separate contaminants from water.

2.4 Comparison

Slide content:

Application	Main need	Device
MEG	Extreme sensitivity	SQUID
Metal detection	Weak-signal detection	SQUID
Water treatment	Strong magnetic force	Magnet

What to say:
Although these three applications look very different, they fit into one simple framework.

In MEG and buried-metal detection, the central requirement is sensitivity to extremely weak magnetic signals. In both cases, the enabling device is the SQUID.

In water treatment, instead, the important quantity is magnetic force, which depends on strong fields and strong gradients. There the enabling technology is the superconducting magnet.

So the underlying physics is shared, but the engineering objective changes. In one case we use superconductivity to measure tiny magnetic signals. In the other, we use it to generate the magnetic conditions needed for separation.

3 Limits and Outlook

Slide content:
Current limits

- Cryogenic cooling still needed
- Magnetic noise and shielding requirements
- Cost and system complexity

Future outlook

- High-T_c superconductors
- Simpler and more compact cryogenics
- Wider real-world deployment

What to say:
This slide summarizes both the current limitations and the future direction of superconducting technologies.

On the limitations side, the first and most important issue is cryogenic cooling. Both SQUID sensors and superconducting magnets must operate below a critical temperature, which requires dedicated cooling systems. This increases cost, size, and operational complexity.

A second limitation is magnetic noise. In applications like MEG or buried-metal detection, the signals we want to measure are extremely weak. This means that shielding, calibration, and noise reduction are not optional, but fundamental parts of the system.

Finally, there is the broader issue of system complexity. A superconducting device is never standalone: it must be integrated with electronics, thermal management, and mechanical structures, which makes real-world deployment more challenging.

At the same time, the outlook is very promising. High-temperature superconductors are reducing the need for extreme cooling, making systems easier to operate.

In parallel, cryogenic technology itself is improving, with more compact and reliable cryocoolers replacing large liquid-helium systems.

As a result, these technologies are gradually moving out of specialized laboratories and into wider real-world applications.

So the key idea is that while the physics is already extremely powerful, the main progress now is on the engineering side, making these systems more practical and accessible.

4 Conclusion

Slide content:
One physics, two technological routes

- Strong magnetic fields

- Ultra-sensitive magnetic sensing

Applications shown

- Water treatment
- MEG
- Buried-metal detection

Final message

- From quantum physics to real-world impact

What to say:
To conclude, the main idea of this talk is that superconductivity is not only an elegant topic in quantum physics, but also a very powerful technological platform.

The same underlying physics leads to two complementary routes. One route is the generation of strong magnetic fields through superconducting magnets. The other is the detection of extremely weak magnetic signals through SQUID sensors.

The three applications presented today show this clearly. Water treatment belongs to the strong-field branch, because the goal is to create the magnetic force needed for separation. MEG and buried-metal detection belong to the sensing branch, because the goal is to detect signals that would otherwise be too weak to measure.

So, even though these applications look very different, they are connected by the same core idea: superconductivity allows us to control magnetism in ways that conventional technologies often cannot.

And this is why superconducting devices matter: they take a quantum phenomenon and turn it into tools with real scientific, medical, environmental, and technological impact.

5 References

Slide content:
Course material

- R. Arpaia, Lecture 4 – Superconductivity: Key Phenomena and Concepts
- R. Arpaia, Lecture 7 – Superconductivity: London Equations (I)
- R. Arpaia, Lecture 15 – The Josephson Effect: Gateway to Superconducting Device Physics (II)
- R. Arpaia, Lecture 18 – Josephson Junction Devices: From Quantum Qubits to SQUIDs in Neuroscience

Selected references

- J. Clarke, "SQUIDs," *Scientific American*
- NHMFL, "Intro to High-Temperature Superconductors – Magnet Academy"
- S. Q. Li et al., "Application of superconducting HGMS technology on turbid wastewater treatment from converter"

- J. Lin, M. Wang, and J. Zhao, “Progress in SQUID-Based Geophysical Precision Measurement Technology”
- M. Pinto et al., “Application of magnetic nanoparticles for water purification”
- S. P. Singh, “Magnetoencephalography: Basic principles”
- “The Feynman Lectures on Physics,” Vol. III, Ch. 21

What to say:
This final slide lists the main sources used for the talk.

The theoretical introduction is mainly based on the course lectures, especially for the core concepts of superconductivity, the London description, the Josephson effect, and SQUID devices.

For the applications, I used representative references on SQUID sensing, high-temperature superconductors, magnetic water purification, geophysical and buried-metal detection, and MEG.

I am not going to discuss these references in detail, but I include them here to show the scientific basis of the material presented in this talk.