LAB 4 — CONNECTIVITY OVERVIEW

Front and rear are the terminated ends. Cockpit taps both backbones.
Each zone has its own two isolation groups; termination remains on the bus side.
Actuator connectors / motor protection / physical layout remain unfinished.


Front zone
+3V3
+6V6_SERVO
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L
+5V
+3V3
+6V6_SERVO
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L
+5V
File: Front.kicad_sch


Cockpit zone
+3V3
+5V
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L
+3V3
+5V
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L
File: Cockpit.kicad_sch


Rear zone
+3V3
+5V
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L
VBAT_PROTECTED
+3V3
+5V
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L
VBAT_PROTECTED
File: Rear.kicad_sch


Power
+3V3
+5V
+6V6_SERVO
GND
VBAT_PROTECTED
+3V3
+5V
+6V6_SERVO
GND
VBAT_PROTECTED
File: Power.kicad_sch

CAN_A_H/L and CAN_B_H/L are separate root nets. Same-name local labels on this root join the shown sheet pins. Child labels connect only through those ports.

Power flags document external battery power and outputs after passive filters; they do not prove current capacity, regulation, thermal behavior or PCB completeness.

See Verification.txt and Design-review.csv for current checks and open decisions.

Shared nets: two CAN backbones, power and ground only.
PRELIMINARY – incomplete board; not for fabrication
Team 4
Sheet: /
File: Lab4.kicad_sch
Title: Lab 4 — three-zone controller
Size: A2 Date: 2026-10-20 **Rev: 0.3**
KiCad E.D.A. 10.0.4 Id: 1/5

Front zone — CAN and servo current sensing

CAN A: 16 MHz / 500 kbit/s / 3.3 V



RS = GND: high—speed mode. Termination remains on BUS side.
No SPI or clock net is shared between zones. Separate crystal per controller.

CAN B: 16 MHz / 500 kbit/s / 3.3 V



RS = GND: high—speed mode. Termination remains on BUS side.
No SPI or clock net is shared between zones. Separate crystal per controller.

SERVO SHUNT — calculated proposal (not measured)



6.6 V regulator —> 10 mOhm shunt —> servo +
Servo GND returns directly to power ground.
Kelvin sense: separate thin traces from shunt pads to IN+/IN—.
Gain 50: Vout = 0.5 V/A. Proposed range 0—5 A —> 0—2.5 V.
12—bit / 3.3 V: 1.61 mA/count (ideal quantization).
At 5 A: shunt drop 50 mV; loss 0.25 W. Select >=1 W.
RC: 4.7k + 100n —> 339 Hz; proposed ADC 4 ksample/s.
Near—zero amplifier output clips; calibrate offset and gain.
This unidirectional circuit cannot measure regenerated current.
No servo idle/stall/noise measurements yet.
5 A measurement range is NOT a 5 A driver or regulator rating.

LAB3 header follows handout p17 top—to—bottom. Two GND pins first.
SRV/PWM_OUT probe actual actuator PWM; timing markers remain separate.
Physical header position / accessibility will be checked during PCB layout.



Servo and lamp circuits are below. Connector cable adapters still need physical verification.

STM32F401RET6 — independent HSI/PLL, no ST—LINK clock dependency



VCAP1 is the INTERNAL regulator output. Only its local capacitor connects here.
Keep every 100n beside its VDD pin; keep the VCAP loop short. DS10086 Fig.2 / Fig.18.

SWD: pin1 VTref senses target voltage; do not feed a second 3.3V supply.
UART header is TX/RX/GND, not RS—232. NRST pulls low to reset.
BOOT0 low boots flash; fit recovery shunt only for bootloader recovery.

TEST: active low on PC13, 10k/100n = 1ms release RC.
Firmware must debounce and meet the 10ms local—fault deadline.
Reset and self—test are separate buttons.

Shared rails and CAN backbone connect through the root sheet. SPI, clocks and reset stay within each zone.



SERVO AND VEHICLE LAMP OUTPUTS



Servo supply passes through R1. PWM uses PA9 and retains its reset pulldown.
J90 uses a new rated 3.96mm connector, not the existing servo plug.
Adapter must preserve GND / supply / signal; confirm the servo accepts 3.3V PWM.

Engineering review; actuator/protection and mechanical sign—off pending.
PRELIMINARY — incomplete board; not for fabrication
Team 4
Sheet: /Front zone/
File: Front.kicad_sch
Title: Front zone — integrated logic and interfaces
Size: A0 | Date: 2026—10—23 | **Rev: 0.3**
KiCad E.D.A. 10.0.4 | Id: 2/5

Rear zone — CAN and motor current sensing
CAN A: 16 MHz / 500 kbit/s / 3.3 V
U20
MCP2515T-I/ST
U21
SN65HVD231DR
CAN B: 16 MHz / 500 kbit/s / 3.3 V
U25
SN65HVD231DR
J24
CAN B isolation
LEFT MOTOR: L298 output -> ACS712 -> motor lead
RIGHT MOTOR: L298 output -> ACS712 -> motor lead
J605
Reserved / encoder probes
STM32F401RET6 — independent HSI/PLL, no ST-LINK clock dependency
U60
STM32F401RET6TR
C600
100n VDD19
C601
100n VDD32
C602
100n VDD48
C603
100n VDD64
C605
4.7u VDD bulk
C606
4.7u VCAP1
FB60
600R @100MHz
C607
100n VDDA
J601
SWD (2.54mm)
R602
10k TEST pullup
R611
1k
D611
ERR red
R633
10k boot pulldown
R634
10k boot pulldown
MOTOR POWER STAGE — cooling / stall behavior to verify
U80
L298N
C803
100n

RS = GND: high-speed mode. Termination remains on BUS side.
No SPI or clock net is shared between zones. Separate crystal per controller.

RS = GND: high-speed mode. Termination remains on BUS side.
No SPI or clock net is shared between zones. Separate crystal per controller.

LAB3 header follows handout p17 top-to-bottom. Two GND pins first.
SRV/PWM_OUT probe actual actuator PWM; timing markers remain separate.
Physical header position / accessibility will be checked during PCB layout.

L298 and output circuits are below. Current limiting and heatsink remain unresolved; no motor-power sign-off.

Each motor: +/-5 A; VADC = 1.25 V + 0.0925 V/A * I.
Ideal 12-bit scale: 8.71 mA/count at VREF=3.3 V.
10k/10k divider keeps a 5 V sensor output at 2.5 V.
Filter source resistance: (10k || 10k) + 1k = 6k.
6k * 100n -> 265 Hz. Proposed ADC: 4 ksample/s/channel.
Stop motors before zero calibration; preserve signed readings.
Hall sensor has internal conductor, not an external shunt.
At 5 A and typical 1.2 mOhm, conductor loss = 30 mW.
Motor return lead connects to the OTHER L298 output, not GND.

VCAP1 is the INTERNAL regulator output. Only its local capacitor connects here.
Keep every 100n beside its VDD pin; keep the VCAP loop short. DS10086 Fig.2 / Fig.18.

SWD: pin1 VTref senses target voltage; do not feed a second 3.3V supply.
UART header is TX/RX/GND, not RS-232. NRST pulls low to reset.
BOOT0 low boots flash; fit recovery shunt only for bootloader recovery.

TEST: active low on PC13, 10k/100n = 1ms release RC.
Firmware must debounce and meet the 10ms local-fault deadline.
Reset and self-test are separate buttons.

Shared rails and CAN backbone connect through the root sheet. SPI, clocks and reset stay within each zone.

ENCODER INPUTS: board pins 1=3.3V nominal, 2=GND, 3=A, 4=B. Verify actual cable order.
10k pullups support open-collector outputs; push-pull input must stay <=5.5V.
U81 at 3.3V gives Schmitt hysteresis and MCU-safe outputs; unused inputs grounded.
Both A and B invert. Check direction/counts after the PCB firmware port.

OUT1/OUT3 -> ACS712 IP+ -> IP- -> motor lead. Other lead -> OUT2/OUT4, NEVER ground.
ENA/ENB high + equal direction inputs gives dynamic braking. Enable low gives coast.
Existing 10k pulldowns keep enables low during reset. SENSE_A/B return to power ground.
This schematic has no autonomous motor-current limiter. A fuse and filtered ADC are not substitutes.
Keep the course L298N; check cooling and course stall-test expectations. 3.2A is a motor stall specification, not normal current.
The eight diodes clamp each bridge output to protected battery and ground. Keep loops short.

Engineering review; actuator/protection and mechanical sign-off pending.
PRELIMINARY — incomplete board; not for fabrication
Team 4
Sheet: /Rear zone/
File: Rear.kicad_sch
Title: Rear zone — integrated logic and interfaces
Size: A0 Date: 2026-10-23 **Rev: 0.3**
KiCad E.D.A. 10.0.4 Id: 3/5

Cockpit zone — dual CAN

CAN A: 16 MHz / 500 kbit/s / 3.3 V

RS = GND: high-speed mode. Termination remains on BUS side.
No SPI or clock net is shared between zones. Separate crystal per controller.

CAN B: 16 MHz / 500 kbit/s / 3.3 V

RS = GND: high-speed mode. Termination remains on BUS side.
No SPI or clock net is shared between zones. Separate crystal per controller.

RASPBERRY PI 4 — 40-pin board socket

Pins 2/4 receive board 5.1V. Pi 3.3V pins 1/17 are NOT joined to board 3.3V.
Do not attach independent USB-C power while board 5.1V is connected.
Confirm socket orientation with a 1:1 print and the actual Pi before routing.

Rows 9–13 intentionally unused on Pi (Lab3 p17).
Two GND pins per probe group. Active-high LED outputs.
Physical reachability is a layout check, not established by this schematic.

Local bypass is not a load-step proof. Pi bulk capacitance / rail transient test remains open.

All Pi GPIOs are 3.3V signals. Header pin number is NOT BCM GPIO number.
Independent board 3.3V supplies the six CAN interfaces.
A=CE0/IRQ25; B=CE1/IRQ24; confirm Linux labels against the installed overlay.

Shared rails and CAN backbone connect through the root sheet. SPI, clocks and reset stay within each zone.

U30
MCP2515T-I/ST
U31
SN65HVD231DR
J30
CAN A isolation
J31
CAN A test
Y30
16 MHz
C300
18p C0G 50V
C301
18p C0G 50V
R300
10k
R301
10k
C302
C303
C304
100n
U34
MCP2515T-I/ST
U35
SN65HVD231DR
J34
CAN B isolation
J35
CAN B test
Y34
16 MHz
C340
18p C0G 50V
C341
18p C0G 50V
R340
10k
R341
10k
C342
C343
C344
100n
J70
Raspberry Pi4 GPIO
GPIO12/PWM0
GPIO13/PWM1
GPIO14/UART_TXD
GPIO15/UART_RXD
GPIO16/SPI1_CE2
GPIO17/SPI1_CE1
GPIO18/SPI1_CE0/PCM_CLK/PWM0
GPIO19/SPI1_MISO/PCM_FS
GPIO20/SPI1_MOSI/PCM_DIN/PWM1
GPIO21/SPI1_SCLK/PCM_DOUT
GPIO22/SDIO_CLK
GPIO23/SDIO_CMD
GPIO24/SDIO_DAT0
GPIO25/SDIO_DAT1
GPIO26/SDIO_DAT2
GPIO27/SDIO_DAT3
5V
3V3
ID_SD_I2C0/GPIO00
ID_SC_I2C0/GPIO01
SDA_I2C1/GPIO02
SCL_I2C1/GPIO03
GPCLK0/GPIO04
GPCLK1/GPIO05
GPCLK2/GPIO06
CE1_SPI0/GPIO07
CE0_SPI0/GPIO08
MISO_SPI0/GPIO09
MOSI_SPI0/GPIO10
SCLK_SPI0/GPIO11
GND
PI_ERROR_LED
PI_STATUS_LED
PI_SELFTEST_BUTTON
PI_UDP_RX_MARKER
PI_TX_A_MARKER
PI_TX_B_MARKER
PI_INT_B
PI_INT_A
PI_CMD_TX_MARKER
PI_DEG_A_LED
PI_DEG_B_LED
PI_CS_B
PI_CS_A
PI_MISO
PI_MOSI
PI_SCK
J703
LAB3 rows 1-13
J704
Pi extra probes
C700
22u /16V
C701
100n
R700
10k TEST pullup
SW70
C702
R710
1k
D710
STATUS green
R711
1k
D711
ERR red
R712
1k
D712
DEG_A yellow
R713
1k
D713
DEG_B yellow
+3V3
+5V
GND
CAN_A_H
CAN_A_L
CAN_B_H
CAN_B_L

Engineering review; actuator/protection and mechanical sign–off pending.
PRELIMINARY – incomplete board; not for fabrication
Team 4
Sheet: /Cockpit zone/
File: Cockpit.kicad_sch
Title: Cockpit zone – integrated logic and interfaces
Size: A1 Date: 2026–10–23 **Rev: 0.3**
KiCad E.D.A. 10.0.4 Id: 4/5

NiMH PACK INPUT — 10 cells; AA or Sub—C pack selection pending

Design input envelope: 8—15 V at the protected node; verify real cells, contact resistance and sag.
Battery / motor rail is UNREGULATED. No lithium charger or lithium BMS is included.


J40
Battery input: 1=+ 2=GND
BAT_PLUS 1
GND 2
F1
BAT_PLUS
Fuse: rating TBD
BAT_FUSED
Q1
BAT_FUSED
DMPH3010LK3—13
RP_GATE
VBAT_PROTECTED
R400
RP_GATE
10k
GND
R401
VBAT_PROTECTED
47k
RP_GATE
D40
12V gate clamp
VBAT_PROTECTED
RP_GATE
C400
VBAT_PROTECTED
10000u / 25V
GND
J41
VBAT test
VBAT_PROTECTED 1
GND 2

Q1 loss at 10 A: 1 W using 10 mOhm at 25 C; hotter silicon has higher resistance.
F1/holder/cable limits, transient overvoltage and thermal layout are open release checks.
J40 is Hirose DF63M—2P—3.96DSA; verify mating contacts, wire gauge, polarity and fuse coordination.

SERVO: 6.6 V; allocation 4 A; TPS564252 (4 A device rating)


U40
TPS564252DRLR
VBAT_PROTECTED 1 VIN
P_SERVO_EN 5 EN
P_SERVO_FB 6 FB
GND 3
SW 2 P_SERVO_SW
PG 4 P_SERVO_PG
GND
L1
P_SERVO_SW
4.7uH / 5.8A
+6V6_SERVO
C410
VBAT_PROTECTED
22u / 25V
GND
C411
VBAT_PROTECTED
100n / 50V
GND
C412
+6V6_SERVO
22u / 16V
GND
C413
+6V6_SERVO
22u / 16V
GND
R410
+6V6_SERVO
100k 1%
P_SERVO_FB
R411
P_SERVO_FB
10k 1%
GND
C414
+6V6_SERVO
22p C0G
P_SERVO_FB
R412
VBAT_PROTECTED
47k
P_SERVO_EN
R413
P_SERVO_EN
10k
GND
R414
+3V3
10k PG pullup
P_SERVO_PG
J42
Rail / PG / GND
+6V6_SERVO 1
P_SERVO_PG 2
GND 3

Local CIN beside VIN/GND; short SW loop. Return FB lower resistor to quiet local GND.
44uF nominal COUT; effective value/stability and full—load thermal performance need validation.

5V: 5.1 V; allocation 3.3 A; TPS564252 (4 A device rating)


U41
TPS564252DRLR
VBAT_PROTECTED 1 VIN
P_5V_EN 5 EN
P_5V_FB 6 FB
GND 3
SW 2 P_5V_SW
PG 4 P_5V_PG
GND
L2
P_5V_SW
4.7uH / 5.8A
+5V
C420
VBAT_PROTECTED
22u / 25V
GND
C421
VBAT_PROTECTED
100n / 50V
GND
C422
+5V
22u / 16V
GND
C423
+5V
22u / 16V
GND
R420
+5V
75k 0.1%
P_5V_FB
R421
P_5V_FB
10k 0.1%
GND
C424
+5V
22p C0G
P_5V_FB
R422
VBAT_PROTECTED
33k
P_5V_EN
R423
P_5V_EN
10k
GND
R424
+3V3
10k PG pullup
P_5V_PG
J43
Rail / PG / GND
+5V 1
P_5V_PG 2
GND 3

Local CIN beside VIN/GND; short SW loop. Return FB lower resistor to quiet local GND.
44uF nominal COUT; effective value/stability and full—load thermal performance need validation.

3V3: 3.318 V; allocation 0.8 A; TPS564252 (4 A device rating)


U42
TPS564252DRLR
VBAT_PROTECTED 1 VIN
P_3V3_EN 5 EN
P_3V3_FB 6 FB
GND 3
SW 2 P_3V3_SW
PG 4 P_3V3_PG
GND
L3
P_3V3_SW
4.7uH / 5.8A
+3V3
C430
VBAT_PROTECTED
22u / 25V
GND
C431
VBAT_PROTECTED
100n / 50V
GND
C432
+3V3
22u / 16V
GND
C433
+3V3
22u / 16V
GND
R430
+3V3
45.3k 1%
P_3V3_FB
R431
P_3V3_FB
10k 1%
GND
C434
+3V3
22p C0G
P_3V3_FB
R432
VBAT_PROTECTED
22k
P_3V3_EN
R433
P_3V3_EN
10k
GND
R434
+3V3
10k PG pullup
P_3V3_PG
J44
Rail / PG / GND
+3V3 1
P_3V3_PG 2
GND 3
PWR_FLAG
BAT_PLUS
PWR_FLAG
GND
PWR_FLAG
VBAT_PROTECTED
PWR_FLAG
+3V3
PWR_FLAG
+5V
PWR_FLAG
+6V6_SERVO

Local CIN beside VIN/GND; short SW loop. Return FB lower resistor to quiet local GND.
44uF nominal COUT; effective value/stability and full—load thermal performance need validation.


+3V3
+3V3
+5V
+5V
+6V6_SERVO
+6V6_SERVO
GND
GND
VBAT_PROTECTED
VBAT_PROTECTED

Engineering review; actuator/protection and mechanical sign—off pending.
PRELIMINARY — incomplete board; not for fabrication
Team 4

Sheet: /Power/
File: Power.kicad_sch

Title: Power — NiMH input and three buck converters

Size: A2
Date: 2026—10—23
Rev: 0.3
KiCad E.D.A. 10.0.4
Id: 5/5