

ECx00U&EGx00U Series

AT Commands Manual

LTE Standard Module Series

Version: 1.0.0

Date: 2021-03-09

Status: Preliminary



Our aim is to provide customers with timely and comprehensive service. For any assistance, please contact our company headquarters:

Quectel Wireless Solutions Co., Ltd.

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai 200233, China

Tel: +86 21 5108 6236

Email: info@quectel.com

Or our local office. For more information, please visit:

<http://www.quectel.com/support/sales.htm>.

For technical support, or to report documentation errors, please visit:

<http://www.quectel.com/support/technical.htm>

Or email to support@quectel.com.

General Notes

Quectel offers the information as a service to its customers. The information provided is based upon customers' requirements. Quectel makes every effort to ensure the quality of the information it makes available. Quectel does not make any warranty as to the information contained herein, and does not accept any liability for any injury, loss or damage of any kind incurred by use of or reliance upon the information. All information supplied herein is subject to change without prior notice.

Disclaimer

While Quectel has made efforts to ensure that the functions and features under development are free from errors, it is possible that these functions and features could contain errors, inaccuracies and omissions. Unless otherwise provided by valid agreement, Quectel makes no warranties of any kind, implied or express, with respect to the use of features and functions under development. To the maximum extent permitted by law, Quectel excludes all liability for any loss or damage suffered in connection with the use of the functions and features under development, regardless of whether such loss or damage may have been foreseeable.

Duty of Confidentiality

The Receiving Party shall keep confidential all documentation and information provided by Quectel, except when the specific permission has been granted by Quectel. The Receiving Party shall not access or use Quectel's documentation and information for any purpose except as expressly provided herein. Furthermore, the Receiving Party shall not disclose any of the Quectel's documentation and information to any third party without the prior written consent by Quectel. For any noncompliance to the above requirements, unauthorized use, or other illegal or malicious use of the documentation and information, Quectel will reserve the right to take legal action.

Copyright

The information contained here is proprietary technical information of Quectel. Transmitting, reproducing, disseminating and editing this document as well as using the content without permission are forbidden. Offenders will be held liable for payment of damages. All rights are reserved in the event of a patent grant or registration of a utility model or design.

Copyright © Quectel Wireless Solutions Co., Ltd. 2021. All rights reserved.

About the Document

Revision History

Version	Date	Author	Description
-	2021-03-08	Fei XUE	Creation of the document
1.0.0	2021-03-09	Fei XUE	Preliminary

Contents

About the Document	3
Contents	4
Table Index	9
1 Introduction	10
1.1. Scope of the Document	10
1.2. Definitions	10
1.3. AT Command Syntax	10
1.4. Supported Character Sets	12
1.5. AT Command Interface	12
1.6. Unsolicited Result Code	12
1.7. Turn off Procedure	12
1.8. Declaration of AT Command Examples	13
2 General Commands	14
2.1. ATI Display Product Identification Information	14
2.2. AT+GMI Request Manufacturer Identification	15
2.3. AT+GMM Request TA Model Identification	15
2.4. AT+GMR Request TA Firmware Revision Identification	16
2.5. AT+CGMI Request Manufacturer Identification	16
2.6. AT+CGMM Request Model Identification	17
2.7. AT+CGMR Request TA Firmware Revision Identification	17
2.8. AT+GSN Request International Mobile Equipment Identity (IMEI)	18
2.9. AT+CGSN Request Product Serial Number Identification	19
2.10. AT&F Set all Current Parameters to Manufacturer Defaults	20
2.11. AT&V Display Current Configuration	21
2.12. AT&W Store Current Settings to User-defined Profile	21
2.13. ATZ Set all Current Parameters to User Defined Profile	22
2.14. ATQ Set Result Code Presentation Mode	22
2.15. ATV TA Response Format	23
2.16. ATE Set Command Echo Mode	25
2.17. A/ Repeat Previous Command Line	25
2.18. ATS3 Set Command Line Termination Character	26
2.19. ATS4 Set Response Formatting Character	27
2.20. ATS5 Set Command Line Editing Character	27
2.21. ATX Set CONNECT Result Code Format and Monitor Call Progress	28
2.22. AT+CFUN Set UE Functionality	29
2.23. AT+CMEE Error Message Format	30
2.24. AT+CSCS Select TE Character Set	31
2.25. AT+QURCCFG Configure URC Indication Option	33
3 Serial Interface Control Commands	35

3.1.	AT&C	Set DCD Function Mode	35
3.2.	AT&D	Set DTR Function Mode	35
3.3.	AT+IFC	Set TE-TA Local Data Flow Control.....	36
3.4.	AT+ICF	Set TE-TA Control Character Framing	37
3.5.	AT+IPR	Set TE-TA Fixed Local Rate	38
4	Status Control Commands	40	
4.1.	AT+CPAS	Mobile Equipment Activity Status	40
4.2.	AT+CEER	Extended Error Report	41
4.3.	AT+QINDCFG	URC Indication Configuration	42
5	(U)SIM Related Commands	45	
5.1.	AT+CIMI	Request International Mobile Subscriber Identity (IMSI).....	45
5.2.	AT+CLCK	Facility Lock	46
5.3.	AT+CPIN	Enter PIN	47
5.4.	AT+CPWD	Change Password	49
5.5.	AT+CSIM	Generic (U)SIM Access	50
5.6.	AT+CRSM	Restricted (U)SIM Access	51
5.7.	AT+QCCID	Show ICCID	52
5.8.	AT+QINISTAT	Query Initialization Status of (U)SIM Card	53
5.9.	AT+QSIMDET	(U)SIM Card Detection.....	54
5.10.	AT+QSIMSTAT	(U)SIM Card Insertion Status Report	55
5.11.	AT+CCHO	Open Logical Channel	56
5.12.	AT+CGLA	UICC Logical Channel Access.....	58
5.13.	AT+CCHC	Close Logical Channel	59
6	Network Service Commands	60	
6.1.	AT+COPS	Operator Selection	60
6.2.	AT+CREG	Network Registration Status	62
6.3.	AT+CSQ	Signal Quality Report.....	63
6.4.	AT+CPOL	Preferred Operator List.....	65
6.5.	AT+COPN	Read Operator Names.....	66
6.6.	AT+CTZU	Automatic Time Zone Update	67
6.7.	AT+CTZR	Time Zone Reporting	68
6.8.	AT+QLTS	Obtain the Latest Time Synchronized Through Network	70
6.9.	AT+QNWINFO	Query Network Information.....	71
6.10.	AT+QSPN	Display the Name of Registered Network.....	72
6.11.	AT+QCSQ	Query and Report Signal Strength	73
6.12.	AT+QENG	Switching on/off Engineering Mode	75
6.13.	AT+CIND	Command of Control Instructions.....	79
7	Call Related Commands.....	81	
7.1.	ATA	Answer an Incoming Call	81
7.2.	ATD	Mobile Originated Call to Dial a Number	82
7.3.	ATH	Disconnect Existing Connection	83
7.4.	AT+CVHU	Voice Hang up Control	83

7.5.	AT+CHUP	Hang up Voice Call.....	84
7.6.	+++	Switch from Data Mode to Command Mode	85
7.7.	ATO	Switch from Command Mode to Data Mode	85
7.8.	ATS0	Set Number of Rings before Automatical Answering.....	86
7.9.	ATS7	Set Time to Wait for Connection Completion.....	87
7.10.	AT+CSTA	Select Type of Address	88
7.11.	AT+CLCC	List Current Calls of ME.....	89
7.12.	AT+CRC	Set Cellular Result Codes for Incoming Call Indication	90
7.13.	AT+QECCNUM	Configure Emergency Call Numbers.....	91
7.14.	AT+QHUP	Hang up Call with a Specific Release Cause	93
7.15.	AT+QCHLDIPMTY	Hang Up a Call in the VoLTE Conference	95
8	Phonebook Commands.....		97
8.1.	AT+CNUM	Subscriber Number.....	97
8.2.	AT+CPBF	Find Phonebook Entries	98
8.3.	AT+CPBR	Read Phonebook Entries	99
8.4.	AT+CPBS	Select Phonebook Memory Storage	100
8.5.	AT+CPBW	Write Phonebook Entry.....	101
9	Short Message Service Commands.....		103
9.1.	AT+CSMS	Select Message Service	103
9.2.	AT+CMGF	Message Format.....	104
9.3.	AT+CSCA	Service Center Address.....	105
9.4.	AT+CPMS	Preferred Message Storage.....	106
9.5.	AT+CMGD	Delete Message	108
9.6.	AT+CMGL	List Message	109
9.7.	AT+CMGR	Read Message	113
9.8.	AT+CMGS	Send Message.....	117
9.9.	AT+CMMS	More Messages to Send	119
9.10.	AT+CMGW	Write Message to Memory.....	120
9.11.	AT+CMSS	Send Message from Storage	122
9.12.	AT+CNMA	New Message Acknowledgement to UE/TE	124
9.13.	AT+CNMI	SMS Event Reporting Configuration.....	125
9.14.	AT+CSDH	Show SMS Text Mode Parameters.....	128
9.15.	AT+CSMP	Set SMS Text Mode Parameters	129
9.16.	AT+QCMGS	Send Concatenated Messages	130
9.17.	AT+QCMGR	Read Concatenated Messages.....	132
10	Packet Domain Commands		134
10.1.	AT+CGATT	Attachment or Detachment of PS.....	134
10.2.	AT+CGDCONT	Define PDP Context	135
10.3.	AT+CGQREQ	Quality of Service Profile (Requested).....	137
10.4.	AT+CGQMIN	Quality of Service Profile (Minimum Acceptable).....	139
10.5.	AT+CGACT	Activate or Deactivate PDP Context.....	142
10.6.	AT+CGDATA	Enter Data State.....	143
10.7.	AT+CGPADDR	Show PDP Address	144

10.8.	AT+CGCLASS	GPRS Mobile Station Class	145
10.9.	AT+CGREG	Network Registration Status	146
10.10.	AT+CGEREP	Packet Domain Event Reporting.....	148
10.11.	AT+CGSMS	Select Service for MO SMS Messages.....	150
10.12.	AT+CEREG	EPS Network Registration Status	151
10.13.	AT+QGDCNT	Packet Data Counter	152
10.14.	AT+QAUGDCNT	Auto Save Packet Data Counter	154
10.15.	AT+CGCONTRDP	PDP Context Read Dynamic Parameters.....	155
11	Supplementary Service Commands	158	
11.1.	AT+CCFC	Call Forwarding Number and Conditions Control	158
11.2.	AT+CCWA	Call Waiting Control	160
11.3.	AT+CHLD	Call Related Supplementary Services.....	162
11.4.	AT+CLIP	Calling Line Identification Presentation.....	164
11.5.	AT+CLIR	Calling Line Identification Restriction.....	166
11.6.	AT+COLP	Connected Line Identification Presentation.....	167
11.7.	AT+CSSN	Supplementary Service Notifications	168
11.8.	AT+CUSD	Unstructured Supplementary Service Data	170
12	Audio Commands	172	
12.1.	AT+CLVL	Loudspeaker Volume Level Selection	172
12.2.	AT+QAUDLOOP	Enable/Disable Audio Loop Test.....	173
12.3.	AT+VTS	DTMF and Tone Generation.....	173
12.4.	AT+VTD	Set Tone Duration.....	174
12.5.	AT+QAUDRD	Record Media File.....	175
12.6.	AT+QPSND	Play Media File	177
12.7.	AT+QAUDPLAY	Play Media File	179
12.8.	AT+QAUDMOD	Set Audio Mode	180
12.9.	AT+QIIC	IIC Read/Write.....	181
12.10.	AT+QAUDSW	Codec Switching	182
12.11.	AT+QAUDPASW	Audio PA Type Switching.....	183
13	Hardware Related Commands.....	185	
13.1.	AT+QPOWD	Power off	185
13.2.	AT+CCLK	Clock	186
13.3.	AT+CBC	Battery Charge.....	187
13.4.	AT+QADC	Read ADC Value	188
13.5.	AT+QSCLK	Enable/Disable Low Power Mode.....	188
14	Appendix.....	190	
14.1.	References	190	
14.2.	Factory Default Settings Restorable with AT&F	197	
14.3.	AT Command Settings Storable with AT&W.....	198	
14.4.	AT Command Settings Storable with ATZ	199	
14.5.	Summary of CME ERROR Codes.....	200	
14.6.	Summary of CMS ERROR Codes.....	202	

14.7.	Summary of URC.....	203
14.8.	SMS Character Sets Conversions.....	206
14.9.	Release Cause Text List of AT+CEER	212

Table Index

Table 1: Applicable Modules.....	10
Table 1: Type of AT Commands and Responses.....	11
Table 2: AT&V Response.....	21
Table 3: ATV0&ATV1 Result Codes Numeric Equivalents and Brief Description.....	24
Table 4: Delay Class.....	139
Table 5: The Description of <code> in URC +QAUDRIND: 0,<code>.....	177
Table 6: Related Documents.....	190
Table 7: Terms and Abbreviations.....	190
Table 8: Factory Default Settings Restorable with AT&F.....	197
Table 9: AT Command Settings Storable with AT&W.....	198
Table 10: AT Command Settings Storable with ATZ.....	199
Table 11: Different Coding Schemes of +CME ERROR: <err>.....	200
Table 12: Different Coding Schemes of +CMS ERROR: <err>.....	202
Table 13: Summary of URC.....	203
Table 14: The Way of SMS Text Input or Output.....	206
Table 15: The Input Conversions Table (DCS = GSM 7 bit and AT+CSCS="GSM").....	206
Table 16: The Output Conversions Table (DCS = GSM 7 bit and AT+CSCS="GSM").....	207
Table 17: GSM Extended Characters.....	208
Table 18: The Input Conversions Table (DCS = GSM 7 bit and AT+CSCS="IRA").....	208
Table 19: IRA Extended Characters.....	209
Table 20: The Output Conversions Table (DCS = GSM 7 bit and AT+CSCS="IRA").....	210
Table 21: GSM Extended Characters.....	211
Table 22: List of Location ID List.....	212
Table 23: List of Cause.....	212

1 Introduction

1.1. Scope of the Document

This document presents the AT command set supported by Quectel ECx00U&EGx00U series modules.

Table 1: Applicable Modules

Module Series	Model
ECx00U Series	EC200U-CN
	EC600U-CN
EGx00U Series	EG700U-CN
	EG500U-CN

1.2. Definitions

- **<CR>** Carriage return character.
- **<LF>** Line feed character.
- **<...>** Parameter name. Angle brackets do not appear on command line.
- **[...]** Optional parameter of a command or an optional part of TA information response. Square brackets do not appear on command line. When an optional parameter is not given, the new value equals to its previous value or its default setting, unless otherwise specified.
- **Underline** Default setting of a parameter.

1.3. AT Command Syntax

The **AT** or **at** prefix must be added at the beginning of each command line. Entering **<CR>** will terminate a command line. Commands are usually followed by a response that includes

<CR><LF><response><CR><LF>. Throughout this document, only the response <response> will be presented, <CR><LF> are omitted intentionally.

AT commands implemented by modules can be separated into two categories syntactically: “Basic”, and “Extended”, as listed below:

- **Basic Syntax**

These AT commands have the format of **AT<x><n>**, or **AT&<x><n>**, where <x> is the command, and <n> is/are the argument(s) for that command. An example of this is **ATE<n>**, which tells the DCE (Data Circuit-terminating Equipment) whether received characters should be echoed back to the DTE (Data Terminal Equipment) according to the value of <n>. <n> is optional and a default will be used if it is omitted.

- **Extended Syntax**

These commands can be operated in several modes, as following table:

Table 2: Type of AT Commands and Responses

Test Command	AT+<cmd>=?	This command returns the list of parameters and value ranges set by the corresponding Write Command or internal processes.
Read Command	AT+<cmd>?	This command returns the currently set value of the parameter or parameters.
Write Command	AT+<cmd>=<p1> [,<p2>[,<p3>[...]]]	This command sets the user-definable parameter values.
Execution Command	AT+<cmd>	This command reads non-variable parameters affected by internal processes in the module.

Multiple commands can be placed on a single line using a semi-colon (;) between commands. Only the first command should have **AT** prefix. Commands can be in upper or lower case.

When entering AT commands, spaces are ignored except the following cases:

- Within quoted strings, where they are preserved;
- Within an unquoted string or numeric parameter;
- Within an IP address;
- Within the AT command name up to and including a =, ? or =?.

On input, at least a carriage return is required. A newline character is ignored so it is permissible to use carriage return/line feed pairs on the input.

If no command is entered after the **AT** token, **OK** will be returned. If an invalid command is entered, **ERROR** will be returned.

Optional parameters, unless explicitly stated, need to be provided up to the last parameter being entered.

1.4. Supported Character Sets

The AT command interface of ECx00U&EGx00U series modules default to the **GSM** character set. ECx00U&EGx00U series modules support the following character sets:

- GSM format
- UCS2
- IRA

The character set can be configured and interrogated by using the **AT+CSCS** command (3GPP TS 27.007) and it is defined in 3GPP TS 27.005. The character set affects transmission and reception of SMS and SMS Cell Broadcast Messages, as well as the entry and display of phonebook entries text field.

1.5. AT Command Interface

ECx00U&EGx00U series modules AT command interface includes two USB ports (USB MODEM port and USB AT port) and one main UART port. The main UART port and two USB ports support AT command communication and data transfer.

1.6. Unsolicited Result Code

As an Unsolicited Result Code and a report message, URC is not issued as part of the response related to an executed AT command. URC is issued by the ECx00U&EGx00U series modules without being requested by the TE and it is issued automatically when a certain event occurs. Typical events leading to URCs are incoming calls (**RING**), received short messages, etc.

1.7. Turn off Procedure

It is recommended to execute **AT+QPOWD** command to turn off the module, as it is the safest and best way. This procedure is realized by letting the module log off from the network and allowing the software to enter into a secure and safe data state before disconnecting the power supply.

After sending **AT+QPOWD**, do not enter any other AT commands. The module outputs message, **POWERED DOWN** and sets the STATUS pin as low to enter into the shutdown state. In order to avoid

data loss, it is suggested to wait for 1s to switch off the VBAT after the STATUS pin is set as low and the URC **POWERED DOWN** is outputted. If **POWERED DOWN** has not been received after 65s, the VBAT shall be switched off compulsorily.

1.8. Declaration of AT Command Examples

The AT command examples in this document are provided to help you familiarize with AT commands and learn how to use them. The examples, however, should not be taken as Quectel's recommendation or suggestions about how you should design a program flow or what status you should set the module into. Sometimes multiple examples may be provided for one AT command. However, this does not mean that there exists a correlation among these examples and that they should be executed in a given sequence.

2 General Commands

2.1. ATI Display Product Identification Information

This command delivers the product information text.

ATI Display Product Identification Information

Execution Command

ATI

Response

Quectel

<objectID>

Revision: <revision>

OK

Maximum Response Time

300 ms

Characteristics

/

Reference

V.25ter

Parameter

<objectID> String type. Identifier of device type.

<revision> String type. Identification text of product software version.

Example

ATI

Quectel

EC200U

Revision: EC200UCNAAR01A04M08

OK

2.2. AT+GMI Request Manufacturer Identification

This command returns the manufacturer identification text. It is identical with **AT+CGMI**.

AT+GMI Request Manufacturer Identification	
Test Command AT+GMI=?	Response OK
Execution Command AT+GMI	Response Quectel OK
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

2.3. AT+GMM Request TA Model Identification

This command returns a product model identification text. It is identical with **AT+CGMM**.

AT+GMM Request TA Model Identification	
Test Command AT+GMM=?	Response OK
Execution Command AT+GMM	Response <objectID> OK
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

Parameter

<objectID>	String type. Identifier of device type.
-------------------------	---

2.4. AT+GMR Request TA Firmware Revision Identification

This command delivers the product firmware version identification text. It is identical with **AT+CGMR**.

AT+GMR Request TA Firmware Revision Identification

Test Command AT+GMR=?	Response OK
Execution Command AT+GMR	Response <revision> OK
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

Parameter

<revision> String type. Identification text of product software version.

Example

```
AT+GMR
EC200UCNAAR01A04M08
OK
```

2.5. AT+CGMI Request Manufacturer Identification

This command returns the manufacturer identification text. It is identical with **AT+GMI**.

AT+CGMI Request Manufacturer Identification

Test Command AT+CGMI=?	Response OK
Execution Command AT+CGMI	Response Quectel OK

Maximum Response Time	300 ms
Characteristics	/
Reference	
3GPP TS 27.007	

2.6. AT+CGMM Request Model Identification

This command returns the product model identification text. It is identical with **AT+GMM**.

AT+CGMM Request Model Identification	
Test Command AT+CGMM=?	Response OK
Execution Command AT+CGMM	Response EC200U OK
Maximum Response Time	300 ms
Characteristics	/
Reference	
3GPP TS 27.007	

2.7. AT+CGMR Request TA Firmware Revision Identification

This command delivers the product firmware version identification text. It is identical with **AT+GMR**.

AT+CGMR Request TA Firmware Revision Identification	
Test Command AT+CGMR=?	Response OK
Execution Command AT+CGMR	Response <revision> OK
Maximum Response Time	300 ms
Characteristics	/
Reference	
3GPP TS 27.007	

Parameter

<revision> String type. Identification text of product software version.

2.8. AT+GSN Request International Mobile Equipment Identity (IMEI)

This command returns the International Mobile Equipment Identity (IMEI) number and Serial Number (SN) of ME. It is identical with **AT+CGSN**.

AT+GSN Request Product Serial Number Identification

Test Command
AT+GSN=?

Response
+GSN: (list of supported <snt>s)

OK

Write Command
AT+GSN=<snt>

Response
If <snt>=0, query SN of the ME:
+GSN: <SN>

OK
If <snt>=1, query IMEI of the ME:
+GSN: <IMEI>

OK

Execution Command
AT+GSN

Response
<IMEI>

OK
Or
ERROR

If there is any error related to ME functionality:
+CMS ERROR: <err>

Maximum Response Time

300 ms

Characteristics

/

Reference
3GPP TS 27.007

Parameter

<snt>	Integer type. Control to query SN or IMEI of the ME. 0 Query SN of the ME 1 Query IMEI of the ME
<IMEI>	String type. IMEI of the ME.
<err>	Error codes. For more details, please refer to Chapter 14.6 .

NOTE

The serial number (IMEI) varies with the individual ME device.

2.9. AT+CGSN Request Product Serial Number Identification

This command returns the International Mobile Equipment Identity (IMEI) number and Serial Number (SN) of ME. It is identical with **AT+GSN**.

AT+CGSN Request Product Serial Number Identification

Test Command AT+CGSN=?	Response +CGSN: (list of supported <snt>s) OK
----------------------------------	---

Write Command AT+CGSN=<snt>	Response If <snt>=0 , query SN of the ME: +CGSN: <SN> OK If <snt>=1 , query IMEI of the ME: +CGSN: <IMEI> OK
---	--

Execution Command AT+CGSN	Response <IMEI> OK Or ERROR If there is any error related to ME functionality: +CMS ERROR: <err>
-------------------------------------	--

Maximum Response Time	300 ms
Characteristics	/
Reference	3GPP TS 27.007

Parameter

<snt>	Integer type. Control to query SN or IMEI of the ME. 0 Query SN of the ME 1 Query IMEI of the ME
<SN>	String type. SN of the ME
<IMEI>	String type. IMEI of the ME
<err>	Error codes. For more details, please refer to Chapter 14.6 .

NOTE

The serial number (IMEI) varies with the individual ME device.

2.10. AT&F Set all Current Parameters to Manufacturer Defaults

This command resets AT command settings to their factory default values. (See **Table 17**).

AT&F Set all Current Parameters to Manufacturer Defaults

Execution Command	Response
AT&F[<value>]	OK
Maximum Response Time	300 ms
Characteristics	/
Reference	V.25ter

Parameter

<value>	Integer type. <u>0</u> Set all TA parameters to manufacturer defaults
----------------------	--

2.11. AT&V Display Current Configuration

This command displays the current settings of several AT command parameters (See **Table 2**), including the single-letter AT command parameters which are not readable otherwise.

AT&V Display Current Configuration

Execution Command AT&V	Response OK
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

Table 3: AT&V Response

AT&V
&C: 1
&D: 2
&F: 0
&W: 0
E: 1
Q: 0
V: 1
X: 4
Z: 0
S0: 0
S3: 13
S4: 10
S5: 8
S7: 0
OK

2.12. AT&W Store Current Settings to User-defined Profile

This command stores the current AT command settings to a user-defined profile in non-volatile memory. (See **Table 18**).

AT&W Store Current Settings to User-defined Profile

Execution Command AT&W[<n>]	Response OK
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

Parameter

<n>	Integer type. <u>0</u> Profile number to store current AT command settings.
-----	--

2.13. ATZ Set all Current Parameters to User Defined Profile

This command restores the current AT command settings to the user-defined profile in non-volatile memory, if they have been stored with **AT&W** before (See **Table 19**). Any additional AT command on the same command line may be ignored.

ATZ Set all Current Parameters to User Defined Profile

Execution Command ATZ[<value>]	Response OK
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

Parameter

<value>	Integer type. <u>0</u> Reset to profile number 0
---------	---

2.14. ATQ Set Result Code Presentation Mode

This command controls whether the result code is transmitted to the TE. Other information text transmitted as response is not affected.

ATQ Set Result Code Presentation Mode

Execution Command ATQ<n>	Response If <n>=0: OK If <n>=1: (none)
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<n>	Integer type.
0	TA transmits result code
1	Result codes are suppressed and not transmitted

2.15. ATV TA Response Format

This command determines the contents of header and trailer transmitted with AT command result codes and information responses.

The result codes, their numeric equivalents and brief descriptions of the use of each are listed in the following **Table 3**.

ATV TA Response Format

Execution Command ATV<value>	Response This parameter setting determines the contents of the header and trailer transmitted with result codes and information responses. When <value>=0 0 When <value>=1 OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .

Reference
V.25ter

Parameter

<value>	Integer type.
0	Information response: <text><CR><LF> Short result code format: <numeric code><CR>
1	Information response: <CR><LF><text><CR><LF> Long result code format: <CR><LF><verbose code><CR><LF>

Example

```

ATV1                                     //Set <value>=1
OK
AT+CSQ
+CSQ: 30,99

OK                                     //When <value>=1, the result code is OK.

ATV0                                     //Set <value>=0
0
AT+CSQ
+CSQ: 30,99
0                                     //When <value>=0, the result code is 0.

```

Table 4: ATV0&ATV1 Result Codes Numeric Equivalents and Brief Description

ATV1	ATV0	Description
OK	0	Acknowledges execution of a command
CONNECT	1	A connection has been established; the DCE is moving from command mode to data mode
RING	2	The DCE has detected an incoming call signal from network
NO CARRIER	3	The connection has been terminated or the attempt to establish a connection failed
ERROR	4	Command not recognized, command line maximum length exceeded, parameter value invalid, or other problem with processing the command line
NO DIALTONE	6	No dial tone detected

BUSY	7	Engaged (busy) signal detected
NO ANSWER	8	"@" (Wait for Quiet Answer) dial modifier was used, but remote ringing followed by five seconds of silence was not detected before expiration of the connection timer (S7)

2.16. ATE Set Command Echo Mode

This command controls whether TA echoes characters received from TE or not during AT command mode.

ATE Set Command Echo Mode

Execution Command ATE<value>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<value>	Integer type.
0	Echo mode OFF
<u>1</u>	Echo mode ON

2.17. A/ Repeat Previous Command Line

This command repeats previous AT command line, and "/" acts as the line terminating character.

A/ Repeat Previous Command Line

Execution Command A/	Response Repeat the previous command
Reference V.25ter	

Example

```

ATI
Quectel
EC200U
Revision: EC200UCNAAR01A04M08

OK
A/                                     //Repeat the previous command
Quectel
EC200U
Revision: EC200UCNAAR01A04M08

OK

```

2.18. ATS3 Set Command Line Termination Character

This command determines the character recognized by the module to terminate an incoming command line. It is also generated for result codes and information text, along with character value set via **ATS4**.

ATS3 Set Command Line Termination Character

Read Command ATS3?	Response <n> OK
Write Command ATS3=<n>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<n>	Integer type. Command line termination character. Range: 0–127. Default: 13.
-----	--

2.19. ATS4 Set Response Formatting Character

This command determines the character generated by the module for result code and information text, along with the command line termination character set via **ATS3**.

ATS4 Set Response Formatting Character

Read Command ATS4?	Response <n> OK
Write Command ATS4=<n>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<n> Integer type. Response formatting character. Range: 0–127. Default: 10.

2.20. ATS5 Set Command Line Editing Character

This command determines the character value used by the module to delete the immediately preceding character from the AT command line (i.e. equates to backspace key).

ATS5 Set Command Line Editing Character

Read Command ATS5?	Response <n> OK
Write Command ATS5=<n>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .

Reference
 V.25ter

Parameter

<n> Integer type. Response editing character. Range: 0–127. Default: 8.

2.21. ATX Set CONNECT Result Code Format and Monitor Call Progress

This command determines whether the module transmits particular result codes to the TE or not. It also controls whether the module detects the presence of a dial tone when it begins dialing and the engaged tone (busy signal) or not.

ATX Set CONNECT Result Code Format and Monitor Call Progress

Execution Command ATX<value>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<value> Integer type.

- 0 Only **CONNECT** result code returned, dial tone and busy detection are both disabled.
- 1 Only **CONNECT<text>** result code returned, dial tone and busy detection are both disabled.
- 2 **CONNECT<text>** result code returned, dial tone detection is enabled, and busy detection is disabled.
- 3 **CONNECT<text>** result code returned, dial tone detection is disabled, and busy detection is enabled.
- 4 **CONNECT<text>** result code returned, and dial tone and busy detection are both enabled.

2.22. AT+CFUN Set UE Functionality

This command controls the functionality level. It can also be used to reset the UE.

AT+CFUN Set UE Functionality	
Test Command AT+CFUN=?	Response +CFUN: (list of supported <fun>s),(list of supported <rst>s) OK
Read Command AT+CFUN?	Response +CFUN: <fun> OK
Write Command AT+CFUN=<fun>[,<rst>]	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	15 s, determined by network.
Characteristics	The command takes effect immediately. The configuration will not be saved.
Reference 3GPP TS 27.007	

Parameter

<fun>	Integer type.
	0 Minimum functionality
	1 Full functionality
<rst>	4 Disable the ME from both transmitting and receiving RF signals
	Integer type.
	0 Do not reset the ME before setting it to <fun> functionality level.
<err>	1 Reset the ME. The device is fully functional after the reset. This value is available only for <fun>=1
	Error codes. For more details, please refer to Chapter 14.5 .

Example

```
AT+CFUN=0 //Switch UE to minimum functionality
OK
AT+COPS?
```

```
+COPS: 0 //No operator is registered

OK
AT+CPIN?
+CME ERROR: 13 //(U)SIM failure

AT+CFUN=1 //Switch UE to full functionality
OK

+CPIN: SIM PIN
AT+CPIN=1234
OK

+CPIN: READY

+QUSIM: 1

+QIND: PB DONE

+QIND: SMS DONE
AT+CPIN?
+CPIN: READY

OK
AT+COPS?
+COPS: 0,0,"CHINA MOBILE",7 //Operator is registered

OK
```

2.23. AT+CMEE Error Message Format

This command controls the format of error result codes: **ERROR**, error numbers or verbose messages as **+CME ERROR: <err>** and **+CMS ERROR: <err>**. This command disables or enables the use of final result code **+CME ERROR: <err>** as the indication of an error.

AT+CMEE Error Message Format

Test Command AT+CMEE=?	Response +CMEE: (range of supported <n>s) OK
Read Command AT+CMEE?	Response +CMEE: <n>

	OK
Write Command AT+CMEE=<n>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type.
0	Disable result code
<u>1</u>	Enable result code and use numeric values
2	Enable result code and use verbose values

Example

```

AT+CMEE=0                                //Disable result code
OK
AT+CPIN?
ERROR                                    //Only ERROR is displayed

AT+CMEE=1                                //Enable error result code with numeric values
OK
AT+CPIN?
+CME ERROR: 10
AT+CMEE=2                                //Enable error result code with verbose (string)
                                         values
OK
AT+CPIN?
+CME ERROR: SIM not inserted

```

2.24. AT+CSCS Select TE Character Set

This command informs the module which character set is used by the TE. This enables the UE to convert character strings correctly between TE and UE character sets.

AT+CSCS Select TE Character Set

Test Command AT+CSCS=?	Response +CSCS: (list of supported <chset>s) OK
Read Command AT+CSCS?	Response +CSCS: <chset> OK
Write Command AT+CSCS=<chset>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference 3GPP TS 27.007	

Parameter

<chset>	String type.
"GSM"	GSM default alphabet
"HEX"	Character strings consist only of hexadecimal numbers from 00 to FF.
"PCCP936"	PC character set Code Page 936.
"IRA"	International reference alphabet
"UCS2"	UCS2 alphabet

Example

AT+CSCS?	//Query the current character set
+CSCS: "GSM"	//The character set is GSM.
OK	
AT+CSCS="UCS2"	//Set the character set to "UCS2"
OK	
AT+CSCS?	
+CSCS: "UCS2"	//The character set is UCS2 after the configuration.
OK	

2.25. AT+QURCCFG Configure URC Indication Option

This commands configures the output port of URC.

AT+QURCCFG Configure URC Indication Option	
Test Command AT+QURCCFG=?	Response +QURCCFG: "urcport",(list of supported <urc_port_value>s) OK
Write Command AT+QURCCFG="urcport",[<urc_port_value>]	Response If the optional parameter is omitted, query the current configuration: +QURCCFG: "urcport",<urc_port_value> OK If the optional parameter is specified, configure the output port of URC: OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will be saved automatically.

Parameter

<urc_port_value>	String type. Set URC output port
"usbat"	USB AT port
"usbmodem"	USB modem port
"uart1"	Main UART
"uart2"	Debug UART
"uart3"	Third UART (Only valid when GPS is not supported, otherwise this port is occupied by GPS.)
"usbnmea"	USB Serial Port1
"all"	All ports

Example

```
AT+QURCCFG=?
+QURCCFG: "urcport",("usbat","usbmodem","uart1","uart2","uart3","usbnmea","all")
```

OK

AT+QURCCFG="urcport"

+QURCCFG: "urcport", "usbat"

OK

AT+QURCCFG="urcport", "usbmodem"

OK

AT+QURCCFG="urcport"

+QURCCFG: "urcport", "usbmodem"

OK

3 Serial Interface Control Commands

3.1. AT&C Set DCD Function Mode

This command controls the behavior of the UE's DCD (data carrier detection) line.

AT&C Set DCD Function Mode

Execution Command AT&C[<value>]	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<value>	Integer type. It determines how the state of circuit (DCD) relates to the detection of received line signal from the distant end.
0	DCD line is always ON
1	DCD line is ON only in the presence of data carrier

3.2. AT&D Set DTR Function Mode

This command determines how the UE responds if DTR line is changed from low to high level during data mode.

AT&D Set DTR Function Mode

Execution Command AT&D[<value>]	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately.

	The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<value>	Integer type.
0	TA ignores status on DTR
1	Low→High on DTR: Change to command mode while remaining the connected call.
2	Low→High on DTR: Disconnect data call, and change to command mode. When DTR is at high level, auto-answer function is disabled.

3.3. AT+IFC Set TE-TA Local Data Flow Control

This command determines the flow control behavior of the serial port for data mode.

AT+IFC Set TE-TA Local Data Flow Control	
Test Command AT+IFC=?	Response +IFC: (list of supported <dce_by_dte>s),(list of supported <dte_by_dce>s) OK
Read Command AT+IFC?	Response +IFC: <dce_by_dte> , <dte_by_dce> OK
Write Command AT+IFC=<dce_by_dte>,<dte_by_dce>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<dce_by_dte>	Integer type.Specifies the method that will be used by TE when receiving data from TA
0	None
2	RTS flow control

<dte_by_dce>	Integer type. Specifies the method that will be used by TA when receiving data from TE
0	None
2	CTS flow control

NOTE

Flow control is only applicable for data mode.

Example

```
AT+IFC=2,2 //Open the hardware flow control
OK

AT+IFC?
+IFC: 2,2
OK
```

3.4. AT+ICF Set TE-TA Control Character Framing

This command determines the serial interface character framing format and parity received by TA from TE.

AT+ICF Set TE-TA Control Character Framing

Test Command AT+ICF=?	Response +ICF: (list of supported <format>s),(list of supported <parity>s) OK
Read Command AT+ICF?	Response +ICF: <format> , <parity> OK
Write Command AT+ICF=[<format>],[<parity>]	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .

Reference
V.25ter

Parameter

<format>	Integer type.
1	8 data, 2 stop
2	8 data, 1 parity 1 stop
3	8 data, 1 stop
<parity>	Integer type.
0	Odd
1	Even

NOTES

1. The command is applied for command state.
2. The **<parity>** field is omitted if the **<format>** field specifies no parity.

3.5. AT+IPR Set TE-TA Fixed Local Rate

This command queries and set the baud rate of the UART.

AT+IPR Set TE-TA Fixed Local Rate

Test Command AT+IPR=?	Response +IPR: (list of supported auto detectable <rate>s),(list of supported fixed-only <rate>s) OK
Read Command AT+IPR?	Response +IPR: <rate> OK
Write Command AT+IPR=<rate>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference V.25ter	

Parameter

<rate>	String type. Baud rate per second.
	2400
	4800
	9600
	14400
	19200
	28800
	33600
	38400
	57600
	<u>115200</u>
	230400
	460800
	921600
	1000000

NOTES

1. If a fixed baud rate is set, make sure that both TE (DTE, usually external processor) and TA (DCE, Quectel module) are configured to the same rate.
2. The value of **AT+IPR** cannot be restored with **AT&F** and **ATZ**; but it is still storable with **AT&W**.
3. In multiplex mode, the baud rate cannot be changed by the Write Command **AT+IPR=<rate>**; and the setting is invalid and cannot be stored even if **AT&W** is executed after the Write Command.
4. A selected baud rate takes effect after the Write Commands are executed and acknowledged by **OK**.

Example

```

AT+IPR=115200           //Set fixed baud rate to 115200bps
OK
AT&W                   //Store current setting, that is, the serial communication
                        speed is 115200 bps after restarting module
OK
AT+IPR?
+IPR: 115200

OK
AT+IPR=115200;&W       //Set fixed baud rate to 115200bps and store current setting
OK

```


4 Status Control Commands

4.1. AT+CPAS Mobile Equipment Activity Status

This command queries the module's activity status.

AT+CPAS Mobile Equipment Activity Status	
Test Command AT+CPAS=?	Response +CPAS: (list of supported <pas>s) OK
Execution Command AT+CPAS	Response TA returns the activity status of ME: +CPAS: <pas> OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<pas>	Integer type. ME activity status. 0 Ready 3 Ringing 4 Call in progress or call hold
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```

AT+CPAS
+CPAS: 0                                //The module is idle

OK
RING
AT+CLCC
+CLCC: 1,1,4,0,0,"15695519173",161

OK
AT+CPAS
+CPAS: 3                                //The module is ringing

OK
AT+CLCC
+CLCC: 1,0,0,0,0,"10010",129

OK
AT+CPAS
+CPAS: 4                                //Call in progress

OK

```

4.2. AT+CEER Extended Error Report

This command queries an extended error and report the cause of the last failed operation, such as:

- The failure to release a call
- The failure to set up a call (both mobile originated or terminated)
- The failure to modify a call by using supplementary services
- The failure to activate, register, query, deactivate or deregister a supplementary service
- The failure to attach GPRS or the failure to activate a PDP context
- The failure to detach GPRS or the failure to deactivate a PDP context

The release cause **<text>** is a text to describe the cause information given by the network.

AT+CEER Extended Error Report

Test command	Response
AT+CEER=?	OK
Execution command	Response
AT+CEER	+CEER: <text>

	<p>OK Or ERROR</p> <p>If error is related to ME functionality: +CME ERROR: <err></p>
Maximum Response Time	300 ms
Characteristics	/

Parameter

<text>	Release cause text. Reason for the last call failure to setup or release (listed in Chapter 14.9). Both CS and PS domain call types are reported. Cause data is captured from Call Manager events and cached locally for later use by this command.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

4.3. AT+QINDCFG URC Indication Configuration

This command controls URC indication.

AT+QINDCFG URC Indication Configuration

Test command AT+QINDCFG=?	<p>Response</p> <p>+QINDCFG: "all",(list of supported <enable>s),(list of supported <save_to_nvram>s) +QINDCFG: "csq",(list of supported <enable>s),(list of supported <save_to_nvram>s) +QINDCFG: "act",(list of supported <enable>s),(list of supported <save_to_nvram>s) +QINDCFG: "smsfull",(list of supported <enable>s),(list of supported <save_to_nvram>s) +QINDCFG: "smsincoming",(list of supported <enable>s),(list of supported <save_to_nvram>s) +QINDCFG: "ring",(list of supported <enable>s),(list of supported <save_to_nvram>s)</p> <p>OK</p>
-------------------------------------	--

<p>Write command</p> <p>AT+QINDCFG=<urctype>[,<enable>[,<save_to_nvram>]]</p>	<p>Response</p> <p>If the optional parameters are omitted, query the current configuration:</p> <p>+QINDCFG: <urctype>,<enable></p> <p>OK</p> <p>If the optional parameters are specified, set the URC indication configurations:</p> <p>OK</p> <p>Or</p> <p>ERROR</p> <p>If there is any error related to ME functionality:</p> <p>+CME ERROR: <err></p>
Maximum Response Time	300 ms

Parameter

<urctype>	String type. URC type
"all"	Main switch of all URCs. Default: ON.
"csq"	Indication of signal strength and channel bit error rate change (similar to AT+CSQ). Default: OFF. If this configuration is ON, present: +QIND: "csq",<rssi>,<ber>
"smsfull"	SMS storage full indication. Default is OFF. If this configuration is ON, present: +QIND: "smsfull",<storage>
"ring"	"RING" indication. Default: ON.
"smsincoming"	Incoming message indication. Default: ON. Related URCs list: +CMTI, +CMT, +CDS
"act"	Indication of network access technology change. Default is OFF. If this configuration is ON, present: +QIND: "act",<actvalue> <actvalue> is string format. The values are as below: "GSM" "LTE" "UNKNOWN" The examples of URC are as below: +QIND: "act","LTE" +QIND: "act","UNKNOWN" The description of "act" is as below: 1. If module does not register on network, the

<actvalue> would be "UNKNOWN".

2. If this configuration is ON, the URC of "act" is reported immediately. Only when the network access technology changes, a new URC is reported.

<enable>	Integer type. URC indication is ON or OFF
	0 OFF
	1 ON
<save_to_nvram>	Integer type. Whether to save configuration into NV.
	0 Not save
	1 Save
<err>	Integer type. For details of error codes, please refer to Chapter 14.5 .

5 (U)SIM Related Commands

5.1. AT+CIMI Request International Mobile Subscriber Identity (IMSI)

This command requests the International Mobile Subscriber Identity (IMSI) which is intended to permit the TE to identify the individual SIM card or active application in the UICC (GSM or USIM) that is attached to MT.

AT+CIMI Request International Mobile Subscriber Identity (IMSI)	
Test Command AT+CIMI=?	Response OK
Execution Command AT+CIMI	Response TA returns <IMSI> for identifying the individual (U)SIM which is attached to ME. <IMSI> OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristic	/
Reference 3GPP TS 27.007	

Parameter

<IMSI>	International Mobile Subscriber Identity (string without double quotes)
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```
AT+CIMI
460023210226023           //Query IMSI number of (U)SIM which is attached to ME
```

OK

5.2. AT+CLCK Facility Lock

This command locks, unlocks or interrogates a MT or a network facility **<fac>**. It can be aborted when network facilities are being set or interrogated. The factory default password of PF, PN, PU, PP and PC lock is "12341234". For Write Command, **<passwd>** is normally needed to do such actions. When querying the status of network service (**<mode>**=2) the response line for 'not active' case (**<status>**=0) should be returned only if service is not active for any **<class>**.

AT+CLCK Facility Lock

Test Command AT+CLCK=?	Response +CLCK: (list of supported <fac> s) OK
Write Command AT+CLCK=<fac>,<mode>[,<passwd>[,<class>]]	Response If <mode> is not equal to 2 and the command is set successfully: OK If <mode> =2 and command is set successfully: +CLCK: <status>[,<class>] [+CLCK: <status>[,<class>]] [...] OK
Maximum Response Time	5 s
Characteristic	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<fac>	String type. "SC" (U)SIM (lock SIM/UICC card installed in the currently selected card slot) (SIM/UICC asks password in MT power-up and when this lock command issued). "AO" BAO (Bar All Outgoing Calls) (refer to 3GPP TS 22.088 clause 1). "OI" BOIC (Bar Outgoing International Calls) (refer to 3GPP TS 22.088 clause 1). "OX" BOIC-exHC (Bar Outgoing International Calls except to Home Country) (refer to
--------------------	--

		3GPP TS 22.088 clause 1).
	"FD"	SIM card or active application in the UICC (GSM or USIM) fixed dialing memory feature (if PIN2 authentication has not been done during the current session, PIN2 is required as <passwd>).
<mode>	Integer type. The status of network service	
	0	Unlock
	1	Lock
	2	Query status
<passwd>	String type. Password	
<class>	Integer type.	
	1	Voice
	2	Data
	4	FAX
	<u>7</u>	All telephony except SMS
	8	Short message service
	16	Data circuit synchronization
	32	Data circuit asynchronization
<status>	Integer type.	
	0	Off
	1	On

Example

```

AT+CLCK="SC",2           //Query the status of (U)SIM card.
+CLCK: 0                 //The (U)SIM card is unlocked (OFF).

OK
AT+CLCK="SC",1,"1234"    //Lock (U)SIM card, and the password is 1234.
OK
AT+CLCK="SC",2           //Query the status of (U)SIM card.
+CLCK: 1                 //The (U)SIM card is locked (ON).

OK
AT+CLCK="SC",0,"1234"    //Unlock (U)SIM card.
OK

```

5.3. AT+CPIN Enter PIN

This command enters a password or queries whether or not the module requires a password which is necessary before it can be operated. The password may be (U)SIM PIN, (U)SIM PUK, PH-SIM PIN, etc.

Read Command returns an alphanumeric string indicating whether or not some password is required.

TA stores a password, such as (U)SIM PIN, (U)SIM PUK, etc., which is necessary before it can be operated. If the PIN is to be entered twice, the TA shall automatically repeat the PIN. If no PIN request is pending, no action is taken and an error message **+CME ERROR** is returned to TE.

If the PIN required is (U)SIM PUK or (U)SIM PUK2, the second pin is required. This second pin **<new_pin>** is used to replace the old pin in the (U)SIM.

AT+CPIN Enter PIN	
Test Command AT+CPIN=?	Response OK
Read Command AT+CPIN?	Response +CPIN: <code> OK
Write Command AT+CPIN=<pin>[,<new_pin>]	Response OK
Maximum Response Time	5 s
Characteristic	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<code>	String without double quotes. The password that the module requires READY MT is not pending for any password SIM PIN MT is waiting for SIM PIN to be given SIM PUK MT is waiting for SIM PUK to be given SIM PIN2 MT is waiting for SIM PIN2 to be given SIM PUK2 MT is waiting for SIM PUK2 to be given
<pin>	String type. Password. If the requested password was a PUK, such as (U)SIM PUK1, PH-FSIM PUK or another passwords, then <pin> must be followed by <new_pin> .
<new_pin>	String type. New password required if the requested code was a PUK.

Example

```
//Enter PIN
AT+CPIN?
+CPIN: SIM PIN           //Queried PIN code is locked

OK
AT+CPIN=1234           //Enter PIN
OK
```

```

+CPIN: READY
AT+CPIN? //PIN has already been entered
+CPIN: READY

OK
//Enter PUK and PIN
AT+CPIN?
+CPIN: SIM PUK //Queried PUK code is locked

K
AT+CPIN="26601934","1234" //Enter PUK and new PIN password
OK

CPIN: READY
AT+CPIN?
+CPIN: READY //PUK has already been entered

OK

```

5.4. AT+CPWD Change Password

This command sets a new password for the facility lock function defined by **AT+CLCK**.

This Test Command returns a list of pairs which present the available facilities and the maximum length of their password.

AT+CPWD Change Password

Test Command AT+CPWD=?	Response +CPWD: ("SC",8),("P2",8) OK
Write Command AT+CPWD=<fac>,<oldpwd>,<newpwd> >	Response OK
Maximum Response Time	5 s
Characteristic	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<fac>	String type. The facility lock "SC" (U)SIM (lock SIM/UICC card) (SIM/UICC asks password in MT power-up and when this lock command is issued) "P2" (U)SIM PIN2
<pwdlength>	Integer type. Maximum length of the password.
<oldpwd>	String type. Password specified for the facility from the user interface or with command.
<newpwd>	String type. New password

Example

```

AT+CPIN?
+CPIN: READY

OK
AT+CPWD="SC","1234","4321"           //Change (U)SIM card password to "4321".
OK
//Restart the module or re-activate the SIM card.
AT+CPIN?                             //Query PIN code is locked.
+CPIN: SIM PIN

OK
AT+CPIN="4321"                       //PIN must be entered to define a new password "4321".
OK

+CPIN: READY

```

5.5. AT+CSIM Generic (U)SIM Access

This command allows a direct control of the (U)SIM that is installed in the currently selected card slot by a distant application on the TE. The TE shall then keep the processing of (U)SIM information within the frame specified by GSM/UMTS.

AT+CSIM Generic (U)SIM Access

Test Command AT+CSIM=?	Response OK
Write Command AT+CSIM=<length>,<command>	Response +CSIM: <length>,<response> OK

	Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristic	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<length>	Integer type. Length of <command> or <response> string.
<command>	Command transferred by the MT to the (U)SIM in the format as described in <i>3GPP TS 51.011</i> .
<response>	Response to the command transferred by the (U)SIM to the MT in the format as described in <i>3GPP TS 51.011</i> .
<err>	Error codes. For more details, please refer to Chapter 14.5 .

5.6. AT+CRSM Restricted (U)SIM Access

This command offers easy and limited access to the (U)SIM database. It transmits the (U)SIM command number **<command>** and its required parameters to the MT.

AT+CRSM Restricted (U)SIM Access	
Test Command AT+CRSM=?	Response OK
Write Command AT+CRSM=<command>[,<fileId>[,<P1>,<P2>,<P3>[,<data>][,<pathId>]]]	Response +CRSM: <sw1>,<sw2>[,<response>] OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristic	The command takes effect immediately. The configuration will be saved automatically.

Reference
 3GPP TS 27.007

Parameter

<command>	Integer type. (U)SIM command number 176 READ BINARY 178 READ RECORD 192 GET RESPONSE 214 UPDATE BINARY 220 UPDATE RECORD 242 STATUS
<fileId>	Integer type. Identifier for an elementary data file on (U)SIM, if used by <command> .
<P1>, <P2>, <P3>	Integer type. Parameters transferred by the MT to the (U)SIM. These parameters are mandatory for every command, except GET RESPONSE and STATUS. The values are described in <i>3GPP TS 51.011</i> .
<data>	Information which shall be written to the (U)SIM (hexadecimal character format; refer to AT+CSCS).
<pathId>	The directory path of an elementary file on a SIM/UICC in hexadecimal format.
<sw1>, <sw2>	Integer type. Information from the (U)SIM about the execution of the actual command. These parameters are delivered to the TE in both cases, on successful or failed execution of the command.
<response>	Response of a successful completion of the command previously issued (hexadecimal character format; refer to AT+CSCS). STATUS and GET RESPONSE return data, which gives information about the current elementary data field. The information includes the type of file and its size (refer to <i>3GPP TS 51.011</i>). After READ BINARY, READ RECORD or RETRIEVE DATA command, the requested data will be returned. <response> is not returned after a successful UPDATE BINARY, UPDATE RECORD or SET DATA command.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

5.7. AT+QCCID Show ICCID

This command returns the ICCID (Integrated Circuit Card Identifier) number of (U)SIM card.

AT+QCCID Show ICCID

Test Command	Response
AT+QCCID=?	OK

Execution Command AT+QCCID	Response +QCCID: <ICCID> OK Or ERROR
Maximum Response Time	300 ms
Characteristics	/

Parameter

<ICCID>	String without double quotes. ICCID (Integrated Circuit Card Identifier) number of the (U)SIM card
----------------------	--

Example

```

AT+QCCID //Query ICCID of the (U)SIM card
+QCCID: 89860025128306012474

OK

```

5.8. AT+QINISTAT Query Initialization Status of (U)SIM Card

This command queries the initialization status of (U)SIM card.

AT+QINISTAT Query Initialization Status of (U)SIM Card	
Test Command AT+QINISTAT=?	Response +QINISTAT: (range of supported <status>s) OK
Execution Command AT+QINISTAT	Response +QINISTAT: <status> OK
Maximum Response Time	300 ms
Characteristics	/

Parameter

<status>	Integer type. Initialization status of (U)SIM card. Actual value is the sum of several of the following four kinds (e.g. 7 = 1 + 2 + 4 means CPIN READY & SMS DONE & PB DONE). Default value: 7.
0	Initial state
1	CPIN READY. Operation like lock/unlock PIN is allowed
2	SMS DONE. SMS initialization completed
4	PB DONE. Phonebook initialization completed

5.9. AT+QSIMDET (U)SIM Card Detection

This command enables (U)SIM card hot-swap function. (U)SIM card is detected by GPIO interrupt. The level of (U)SIM card detection pin should also be set when (U)SIM card is inserted.

AT+QSIMDET (U)SIM Card Detection

Test Command AT+QSIMDET=?	Response +QSIMDET: (list of supported <enable>s),(list of supported <insert_level>s) OK
Read Command AT+QSIMDET?	Response +QSIMDET: <enable> , <insert_level> OK
Write Command AT+QSIMDET=<enable>,<insert_level> >	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristic	The command takes effect after rebooting. The configuration will be saved automatically.

Parameter

<enable>	Integer type. Enable or disable (U)SIM card detection. 0 Disable 1 Enable
<insert_level>	Integer type. The level of (U)SIM detection pin when a (U)SIM card is inserted. 0 Low level 1 High level

NOTES

1. Hot-swap function is invalid if the configured value of **<insert_level>** is inconsistent with that of in hardware design.
2. Hot-swap function takes effect after the module is restarted.

Example

```
AT+QSIMDET=1,0           //Set (U)SIM card detection pin level as low when (U)SIM card is inserted
OK
<Remove (U)SIM card>
+CPIN: NOT READY
<Insert (U)SIM card>
+CPIN: READY             //If PIN1 of (U)SIM card is unlocked
```

5.10. AT+QSIMSTAT (U)SIM Card Insertion Status Report

This command queries (U)SIM card insertion status or determines whether to report (U)SIM card insertion status.

AT+QSIMSTAT (U)SIM Card Insertion Status Report

Test Command AT+QSIMSTAT=?	Response +QSIMSTAT: (list of supported <enable> s) OK
Read Command AT+QSIMSTAT?	Response +QSIMSTAT: <enable> , <inserted_status> OK
Write Command AT+QSIMSTAT=<enable>	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command take effects after rebooting. The configurations will be saved automatically.

Parameter

<enable> Integer type. Enable or disable (U)SIM card insertion status report. If it is enabled,

when (U)SIM card is removed or inserted, the URC **+QSIMSTAT:** **<enable>,<inserted_status>** will be reported.

0 Disable

1 Enable

<inserted_status> Integer type. (U)SIM card is inserted or removed. This argument is not allowed to be set.

0 Removed

1 Inserted

2 Unknown, before (U)SIM initialization

Example

```

AT+QSIMSTAT?           //Query (U)SIM card insertion status
+QSIMSTAT: 0,1

OK
AT+QSIMDET=1,0
OK
AT+QSIMSTAT=1           //Enable (U)SIM card insertion status report
OK
AT+QSIMSTAT?
+QSIMSTAT: 1,1

OK
<Remove (U)SIM card>
+QSIMSTAT : 1,0           //Report of (U)SIM card insertion status: removed

CPIN: NOT READY
AT+QSIMSTAT?
+QSIMSTAT: 1,0

OK
<Insert (U)SIM card>
+QSIMSTAT: 1,1           //Report of (U)SIM card insertion status: inserted

+CPIN: READY

```

5.11. AT+CCHO Open Logical Channel

This command opens a logical channel of (U)SIM card.

AT+CCHO Open Logical Channel

Test Command AT+CCHO=?	Response OK
Write Command AT+CCHO=<dfname>	Response <sessionID> OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will not be saved.

Parameter

<dfname>	String type. All sel applications in the UICC are referenced by a DF name coded on 1 to 16 bytes.
<sessionID>	Integer type. A session ID to be used to target a specific application on the smart card using logical channels mechanism.

NOTE

The logical channel number is contained in the CLASS byte of an APDU command, thus implicitly contained in all APDU commands sent to a UICC. In this case it will be up to the MT to manage the logical channel part of the APDU CLASS byte and to ensure that the chosen logical channel is relevant to the **<sessionID>** indicated in the AT command. See *3GPP TS 31.101 [65]* for further information on logical channels in APDU commands protocol.

Example

```
AT+CCHO=? //Test command.
OK
AT+CCHO="A0000000871002FF86FFFF89FFFFFFFF" //<dfname> is made up of AID strings.
+CCHO: 1 //The session ID is 1.
OK
```

5.12. AT+CGLA UICC Logical Channel Access

This command accesses a UICC logical channel.

AT+CGLA UICC Logical Channel Access

Test Command AT+CGLA=?	Response OK
Write Command AT+CGLA=<sessionID>,<length>,<command>	Response +CGLA: <length>,<response> OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will not be saved.

Parameter

<sessionID>	Integer type. This is the identifier of the session to be used to send the APDU commands to the UICC. It is mandatory to send commands to the UICC when targeting applications on the smart card using a logical channel other than the default channel (channel "0").
<length>	Integer type. Length of the characters that are sent to TE in <command> or <response> (Twice the actual length of the command or response).
<command>	Command passed on by the MT to the UICC in the format as described in <i>3GPP TS 31.101 [65]</i> (hexadecimal character format; refer to AT+CSCS)
<response>	Response to the command passed on by the UICC to the MT in the format as described in <i>3GPP TS 31.101 [65]</i> (hexadecimal character format; refer to AT+CSCS).

Example

```
AT+CGLA=?           //Test command.
OK
AT+CGLA=1,14,"00A40804022F00" //The command is 00A40804022F00.
+CGLA: 4,"6121"      //The length is 4, the response is 6121.
OK
```

5.13. AT+CCHC Close Logical Channel

This command closes a logical channel of (U)SIM card with the given **<sessionID>**.

AT+CCHC Close Logical Channel

Test Command AT+CCHC=?	Response OK
Write Command AT+CCHC=<sessionID>	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will not be saved.

Parameter

<sessionID>	Integer type. A session ID to be used to target a specific application on the smart card using logical channels mechanism
--------------------------	---

Example

```
AT+CCHC=?           //Test command.
OK
AT+CCHC=1           //Close logical channel: 1.
OK
```

6 Network Service Commands

6.1. AT+COPS Operator Selection

This command returns the current operators and their status, and allows setting automatic or manual network selection.

This Test Command returns a set of five parameters, each representing an operator presenting in the network. Any of the formats may be unavailable and should then be an empty field. The list of operators shall be in the order of: home network, networks referenced in (U)SIM and other networks.

This Read Command returns the current mode and the currently selected operator. If no operator is selected, **<format>**, **<oper>** and **<AcT>** are omitted.

This Write Command forces an attempt to select and register the GSM/LTE network operator. If the selected operator is not available, no other operator shall be selected (except **<mode>=4**). The format of selected operator name shall apply to further Read Command (**AT+COPS?**).

AT+COPS Operator Selection

Test Command

AT+COPS=?

Response

+COPS: [list of supported (**<stat>**),long alphanumeric **<oper>**,short alphanumeric **<oper>**,numeric **<oper>**][**<AcT>**])
s][**<mode>**],(list of supported **<mode>**s),(list of supported **<format>**s)]

OK

If there is any error related to ME functionality:

+CME ERROR: <err>

Read Command

AT+COPS?

Response

+COPS: **<mode>**][**<format>**][**<oper>**][**<AcT>**]]

OK

If there is any error related to ME functionality:

+CME ERROR: <err>

Write Command AT+COPS=<mode>[,<format>[,<oper>[,<AcT>]]]	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	180 s, determined by network.
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<stat>	Integer type. 0 Unknown 1 Operator available 2 Current operator 3 Operator forbidden
<oper>	Operator in format as per <format> . <mode> determines whether <oper> is present or not.
<mode>	Integer type. 0 Automatic mode. <oper> field is omitted 1 Manual operator selection. <oper> field shall be present and <AcT> optionally 2 Manually deregister from network 3 Set only <format> (for AT+COPS? Read Command), and do not attempt registration/deregistration (<oper> and <AcT> fields are ignored). This value is invalid in the response of Read Command. 4 Manual/automatic selection. <oper> field shall be presented. If manual selection fails, automatic mode (<mode> =0) is entered
<format>	Integer type. Indicates the format of <oper> 0 Long format alphanumeric <oper> which can be up to 16 characters long 1 Short format alphanumeric <oper> 2 Numeric <oper> . GSM location area identification number
<AcT>	Integer type. Access technology selected. Values 0 and 7 are intended for the AT+COPS Write Command. 0 GSM 2 UTRAN 3 GSM W/EGPRS 4 UTRAN W/HSDPA 5 UTRAN W/HSUPA 6 UTRAN W/HSDPA and HSUPA 7 E-UTRAN
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```

AT+COPS=? //List all current network operators.
+COPS: (1,"CHN-UNICOM","UNICOM","46001",2),(1,"CHN-UNICOM","UNICOM","46001",0),(2,"CHN-UNICOM","UNICOM","46001",7),(1,"46011","46011","46011",7),(3,"CHINA MOBILE","CMCC","46000",0),(0-4),(0-2)

OK
AT+COPS? //Query the currently selected network operator.
+COPS: 0,0,"CHN-UNICOM",7

OK

```

6.2. AT+CREG Network Registration Status

This Read Command returns the status of result code presentation and an integer **<stat>** which shows whether the network has currently indicated the registration of the ME. Location information elements **<lac>** and **<ci>** are returned only when **<n>=2** and ME is registered on the network.

This Write Command controls the presentation of an unsolicited result code **+CREG: <stat>** when **<n>=1** and there is a change in the ME network registration status.

AT+CREG Network Registration Status	
Test Command AT+CREG=?	Response +CREG: (list of supported <n>s) OK
Read Command AT+CREG?	Response +CREG: <n>,<stat>[,<lac>,<ci>[,<AcT>]] OK If there is any error related to ME functionality: +CME ERROR: <err>
Write Command AT+CREG[=<n>]	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type. Whether to enable related registration network. 0 Disable network registration URC 1 Enable network registration URC +CREG: <stat> 2 Enable network registration URC with location information: +CREG: <stat>[,<lac>,<ci>[,<AcT>]]
<stat>	Integer type. Registration network status. 0 Not registered. ME is not currently searching a new operator to register to 1 Registered, home network 2 Not registered, but ME is currently searching a new operator to register to 3 Registration denied 4 Unknown 5 Registered, roaming
<lac>	String type. Two bytes location area code in hexadecimal format
<ci>	String type. 16-bit (GSM) or 28-bit (LTE) cell ID in hexadecimal format
<AcT>	Integer type. Access technology selected 0 GSM 2 UTRAN 3 GSM W/EGPRS 4 UTRAN W/HSDPA 5 UTRAN W/HSUPA 6 UTRAN W/HSDPA and HSUPA 7 E-UTRAN
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```

AT+CREG=1
OK

+CREG: 1                                //URC reports that ME has registered on network
AT+CREG=2                                //Activate extended URC mode
OK

+CREG: 1,"D509","80D413D",7             //URC reports that operator has found location area code
                                         and cell ID

```

6.3. AT+CSQ Signal Quality Report

This command indicates the received signal strength **<rssi>** and the channel bit error rate **<ber>**.

This Test Command returns values supported by the TA.

This Execution Command returns received signal strength indication **<rss>** and channel bit error rate **<ber>** from the ME.

AT+CSQ Signal Quality Report

Test Command AT+CSQ=?	Response +CSQ: (list of supported <rss>s),(list of supported <ber>s) OK
Execution Command AT+CSQ	Response +CSQ: <rss>,<ber> OK
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<rss>	Integer type. 0 -113dBm or less 1 -111dBm 2-30 -109dBm to -53dBm 31 -51dBm or greater 99 Not known or not detectable
<ber>	Integer type. Channel bit error rate (in percent). 0-7 As RxQual values in the table in 3GPP TS 45.008 subclause 8.2.4 99 Not known or not detectable

Example

```
AT+CSQ=?
+CSQ: (0-31,99),(0-7,99)

OK
AT+CSQ
+CSQ: 28,99           //The current signal strength indication is 28 and channel bit error rate is 99.

OK
```

NOTE

After using network related commands such as **AT+CCWA** and **AT+CCFC**, it is recommended to wait for 3 seconds before entering **AT+CSQ** so as to ensure that any network access required for the preceding command has been finished.

6.4. AT+CPOL Preferred Operator List

This command edits and queries the list of preferred operators.

AT+CPOL Preferred Operator List

Test Command AT+CPOL=?	Response +CPOL: (list of supported <index>s),(list of supported <format>s) OK
Read Command AT+CPOL?	Response Query the list of preferred operators: +CPOL: <index> , <format> , <oper> [, <GSM> , <GSM_compact> , <UTRAN> , <E-UTRAN>] [+CPOL: <index> , <format> , <oper> [, <GSM> , <GSM_compact> , <UTRAN> , <E-UTRAN> ...] OK
Write Command AT+CPOL=<index>[,<format>[,<oper>[<GSM>,<GSM_compact>,<UTRAN>,<E-UTRAN>]]]	Response Edit the list of preferred operators: OK Or ERROR If the <index> is given but the <oper> is left out, the entry is deleted.
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately.
Reference 3GPP TS 27.007	

Parameter

<index>	Integer type. The order number of the operator in the (U)SIM preferred operator list
<format>	Integer type. 0 Long format alphanumeric <oper> 1 Short format alphanumeric <oper> 2 Numeric <oper>
<oper>	String type. <format> indicates the format is alphanumeric or numeric (see AT+COPS)
<GSM>	Integer type. GSM access technology 0 Access technology is not selected 1 Access technology is selected
<GSM_compact>	Integer type. GSM compact access technology 0 Access technology is not selected 1 Access technology is selected
<UTRAN>	Integer type. UTRAN access technology 0 Access technology is not selected 1 Access technology is selected
<E-UTRAN>	Integer type. E-UTRAN access technology 0 Access technology is not selected 1 Access technology is selected

NOTE

The access technology selection parameters **<GSM>**, **<GSM_compact>**, **<UTRAN>** and **<E-UTRAN>** are required for SIM cards or UICC's containing PLMN selector with access technology.

6.5. AT+COPN Read Operator Names

This command returns the list of operator names from the ME. Each operator code **<numericn>** that has an alphanumeric equivalent **<alphan>** in the ME memory is returned.

AT+COPN Read Operator Names

Test Command AT+COPN=?	Response OK
Execution Command AT+COPN	Response +COPN: <numeric1>,<alpha1> [+COPN: <numeric2>,<alpha2> ...]

	OK
	If there is error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	Depends on the number of operator names.
Characteristics	/
Reference	
3GPP TS 27.007	

Parameter

<numeric>	String type. Operator in numeric format (see AT+COPS)
<alphan>	String type. Operator in long alphanumeric format (see AT+COPS)
<err>	Error codes. For more details, please refer to Chapter 14.5 .

6.6. AT+CTZU Automatic Time Zone Update

This Write Command enables and disables automatic time zone update via NITZ.

AT+CTZU Automatic Time Zone Update	
Test Command AT+CTZU=?	Response +CTZU: (list of supported <enable>s) OK
Write Command AT+CTZU=<enable>	Response OK Or ERROR
Read Command AT+CTZU?	Response +CTZU: <enable> OK
Maximum Response Time	300 ms
Characteristics	The command takes effect after rebooting. The configuration will be saved automatically.
Reference	
3GPP TS 27.007	

Parameter

<enable>	Integer type. The mode of automatic time zone update.
<u>0</u>	Disable automatic time zone update via NITZ.
1	Enable automatic time zone update via NITZ
3	Enable automatic time zone update via NITZ and update LOCAL time to RTC

Example

```

AT+CTZU?
+CTZU: 0

OK
AT+CTZU=?
+CTZU: (0,1,3)

OK
AT+CTZU=1
OK
AT+CTZU?
+CTZU: 1

OK

```

6.7. AT+CTZR Time Zone Reporting

This command controls the time zone reporting of changed event. If reporting is enabled, the MT returns the unsolicited result code **+CTZV: <tz>** or **+CTZE: <tz>,<dst>,<time>** whenever the time zone is changed.

AT+CTZR Time Zone Reporting

Test Command AT+CTZR=?	Response +CTZR: (range of supported <reporting>s) OK
Write Command AT+CTZR=<reporting>	Response OK Or ERROR
Read Command AT+CTZR?	Response +CTZR: <reporting>

	OK
Maximum Response Time	300 ms
Characteristics	The command takes effect after rebooting. The configuration will be saved automatically.
Reference	
3GPP TS 27.007	

Parameter

<reporting>	Integer type. The mode of time zone reporting 0 Disable time zone reporting of changed event 1 Enable time zone reporting of changed event by URC +CTZV: <tz> 2 Enable extended time zone reporting by URC +CTZE: <tz>,<dst>,<time>
<tz>	String type. The sum of the local time zone (difference between the local time and GMT is expressed in quarters of an hour) plus daylight saving time. The format is " $\pm zz$ ", expressed as a fixed width, two-digit integer with the range -48 to +56. To maintain a fixed width, numbers in the range -9 to +9 are expressed with a leading zero, e.g. "-09", "+00" and "+09".
<dst>	Integer type. Indicates whether <tz> includes daylight savings adjustment 0 <tz> includes no adjustment for daylight saving time 1 <tz> includes +1 hour (equals 4 quarters in <tz>) adjustment for daylight saving time 2 <tz> includes +2 hours (equals 8 quarters in <tz>) adjustment for daylight saving time
<time>	String type. The local time. The format is "YYYY/MM/DD,hh:mm:ss", expressed as integers representing year (YYYY), month (MM), date (DD), hour (hh), minute (mm) and second (ss). This parameter can be provided by the network when delivering time zone information and will be presented in the unsolicited result code of extended time zone reporting if provided by the network.

Example

```
AT+CTZR=2
OK
AT+CTZR?
+CTZR: 2

OK

+CTZE: "+32",0,"2017/11/04,06:51:13"           //<reporting> is 2
```

6.8. AT+QLTS Obtain the Latest Time Synchronized Through Network

This command obtains the latest time synchronized through network.

This Execution Command returns the latest time that has been synchronized through network.

AT+QLTS Obtain the Latest Time Synchronized Through Network

Test Command AT+QLTS=?	Response +QLTS: (range of supported <mode>s) OK
Execution Command AT+QLTS	Response +QLTS: <time>,<dst> OK
Write Command AT+QLTS=<mode>	Response +QLTS: <time>,<dst> OK Or ERROR If there is error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately.

Parameter

<mode>	Integer type. Network time obtaining mode. 0 Query the latest time that has been synchronized through network 1 Query the current GMT time calculated from the latest time that has been synchronized through network 2 Query the current LOCAL time calculated from the latest time that has been synchronized through network
<time>	String type value. Format is "YYYY/MM/dd,hh:mm:ss±zz", where characters indicate year (two last digits), month, day, hour, minutes, seconds and time zone (indicates the difference, expressed in quarters of an hour, between the local time and GMT; Range: -48 to +48). E.g. 6th of May 2004, 22:10:00 GMT+2 hours equals to "04/05/06,22:10:00+08"
<dst>	Integer type. Daylight saving time.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTE

If the time has not been synchronized through network, the command will return a null time string as **+QLTS: ""**.

Example

```

AT+QLTS=?           //Query the supported network time mode.
+QLTS: (0-2)

OK
AT+QLTS             //Query the latest time synchronized through network.
+QLTS: "2017/10/13,03:40:48+32,0"

OK
AT+QLTS=0          //Query the latest time synchronized through network. It offers the same
                    //function as Execution Command AT+QLTS.
+QLTS: "2017/10/13,03:40:48+32,0"

OK
AT+QLTS=1          //Query the current GMT time calculated from the latest time that has been
                    //synchronized through network
+QLTS: "2017/10/13,03:41:22+32,0"

OK
AT+QLTS=2          //Query the current LOCAL time calculated from the latest time that has been
                    //synchronized through network
+QLTS: "2017/01/13,11:41:23+32,0"

OK

```

6.9. AT+QNWINFO Query Network Information

This command indicates network information such as the selected access technology, the operator and the selected band.

AT+QNWINFO Query Network Information

Test Command AT+QNWINFO=?	Response OK
Execution Command AT+QNWINFO	Response +QNWINFO: <AcT>,<oper>,<band>,<channel>

	OK
Maximum Response Time	300 ms
Characteristics	/

Parameter

<AcT>	String type. The selected access technology "No Service" "GSM" "GPRS" "EDGE" "TDD LTE" "FDD LTE"
<oper>	String type. The operator in numeric format.
<band>	String type. The selected band. "GSM 850" "GSM 900" "GSM 1800" "GSM 1900" "LTE BAND 1" to "LTE BAND 43" "LTE BAND 66" "LTE BAND 71"
<channel>	Integer type. Channel ID.

Example

```
AT+QNWINFO=?
OK
AT+QNWINFO
+QNWINFO: "FDD LTE","46011","LTE BAND 3",1650
OK
```

6.10. AT+QSPN Display the Name of Registered Network

AT+QSPN Display the Name of Registered Network

Test Command	Response
AT+QSPN=?	OK

Execution Command AT+QSPN	Response +QSPN: <FNN>,<SNN>,<SPN>,<alphabet>,<RPLMN> OK
Maximum Response Time	300 ms
Characteristics	/

Parameter

<FNN>	String type. Full network name
<SNN>	String type. Short network name
<SPN>	String type. Service provider name
<alphabet>	Integer type. Alphabet of full network name and short network name 0 GSM 7-bit default alphabet 1 UCS2
<RPLMN>	String type. Registered PLMN

NOTES

1. If **<alphabet>** is 0, **<FNN>** and **<SNN>** will be shown in GSM 7-bit default alphabet string.
2. If **<alphabet>** is 1, **<FNN>** and **<SNN>** will be shown in UCS2 hexadecimal string.

Example

```
AT+QSPN //Query the EONS information of RPLMN
+QSPN: "CHN-UNICOM","UNICOM","",0,"46001"
OK
```

6.11. AT+QCSQ Query and Report Signal Strength

This command queries and reports the signal strength of the current service network. If the MT is registered with multiple networks in different service modes, you can query the signal strength of networks in each mode. No matter whether the MT is registered with a network or not, you can run this command to query the signal strength or allow the MT to unsolicitedly report the detected signal strength if the MT camps on the network. If the MT is not using any service network or the service mode is uncertain, "NOSERVICE" will be returned as the query result.

AT+QCSQ Query and Report Signal Strength

Test Command	Response
--------------	----------

AT+QCSQ=?	+QCSQ: (list of supported <sysmode>s)
	OK
Write Command AT+QCSQ=<enable>	Response OK
Read Command AT+QCSQ?	Response +QCSQ: <enable>
	OK
Execution Command AT+QCSQ	Response +QCSQ: <sysmode>,[,<value1>,<value2>[,<value3>[,<value4>]]]]
	OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will not be saved.

Parameter

<sysmode> A string type value indicating the service mode in which the MT will unsolicitedly report the signal strength.
 "NOSERVICE" NOSERVICE mode
 "GSM" GSM/GPRS/EDGE mode
 "LTE" LTE mode

<value1>, <value2>, <value3>, <value4>: the following table lists the signal strength type corresponding to each service mode.

<sysmdoe>	<value1>	<value2>	<value3>	<value4>
"NOSERVICE"	/	/	/	/
"GSM"	<gsm_rssi>	/	/	/
"LTE"	<lte_rssi>	<lte_rsrp>	<lte_sinr>	<lte_rsrq>
<gsm_rssi>,<lte_rssi> An integer indicating the received signal strength. These parameters are available for GSM and LTE mode respectively.				
<lte_rsrp> An integer indicating the reference signal received power (RSRP). This parameter is available for LTE mode.				
<lte_sinr> An integer indicating the signal to interference plus noise ratio (SINR). This parameter is available for LTE mode.				
<lte_rsrq> An integer indicating the reference signal received quality (RSRQ) in dB.				
<enable> Integer type. Whether to report URC.				

0	Disable report URC
1	Enable report URC

NOTE

URC is shown as below:

+QCSQ: <sysmode>[,<value1>[,<value2>[,<value3>[,<value4>]]]]

The URC command allows the MT to unsolicitedly report the current signal strength when the strength changes.

The write Command is used to control URC indication, Default is off (<enable>=0). If <enable>=1, then the MT can unsolicitedly report the current signal strength when the strength changes.

Example

```

AT+QCSQ                                //Query signal strength.
+QCSQ: "LTE",-52,-81,195,-10

OK
AT+QCSQ?                                //Query URC configuration.
+QCSQ: 0

OK
AT+QCSQ=?                               //List of supported <sysmode>
+QCSQ: "NOSERVICE","GSM","LTE"

OK

```

6.12. AT+QENG Switching on/off Engineering Mode

Engineering mode is designed to report the information of serving cells, neighbour cells and packet switch parameters. The command switches on/off the mode.

Engineering mode is designed to report the information of serving cells, neighbouring cells and Packet Switch parameters.

AT+QENG Switching on/off Engineering Mode

Test Command AT+QENG=?	Response +QENG: (list of supported <cell_type>s) OK
Write Command	Response

Query the information of serving cells AT+QENG="servingcell"	<p>In the case of GSM mode:</p> <p>+QENG: "servingcell",<state>,"GSM",<mcc>,<mnc>,<la c>,<cellID>,<BSIC>,<arfcn>,<band>,<rxlev>,<txp>,<rla>,< drx>,<c1>,<c2>,<gprs>,<tch>,<ts>,<ta>,<maio>,<hsn>,<r xlevsub>,<rxlevfull>,<rxqualsub>,<rxqualfull>,<voicecod ec></p> <p>OK</p> <p>In the case of LTE mode:</p> <p>+QENG: "servingcell",<state>,"LTE",<is_tdd>,<mcc>,<m nc>,<cellID>,<pcid>,<earfcn>,<freq_band_ind>,<ul_band width>,<dl_bandwidth>,<tac>,<rsrp>,<rsrq>,<rssi>,<sin r>,<srxlev></p> <p>OK</p>
Write Command Query the information of neighbour cells AT+QENG="neighbourcell"	<p>Response</p> <p>In the case of GSM mode:</p> <p>[+QENG: "neighbourcell","GSM",<mcc>,<mnc>,<lac>,<c ellID>,<BSIC>,<arfcn>,<rxlev>,<c1>,<c2>,<c31>,<c32> [...]]</p> <p>OK</p> <p>In the case of LTE mode:</p> <p>[+QENG: "neighbourcell intra","LTE",<earfcn>,<pcid>,<r srq>,<rsrp>,<rssi>,<sinr>,<srxlev>,<cell_resel_priority>,< s_non_intra_search>,<thresh_serving_low>,<s_intra_s earch> [...]]</p> <p>OK</p>
Maximum Response Time	determined by network.
Characteristics	/

Parameter

<cell_type>	String format. The information of different cells. "servingcell" The information of 2G/4G serving cells "neighbourcell" The information of 2G/4G neighbour cells
<state>	String format. UE state.

	"SEARCH"	UE is searching but could not (yet) find a suitable 2G/3G/4G cell.
	"LIMSRV"	UE is camping on a cell but has not registered on the network.
	"NOCONN"	UE is camping on a cell and has registered on the network, and it is in idle mode.
	"CONNECT"	UE is camping on a cell and has registered on the network, and a call is in progress.
<mcc>	Integer type. Mobile country code (first part of the PLMN code)	
	"_"	Invalid
<mnc>	Integer type. Mobile network code (second part of the PLMN code)	
	"_"	Invalid
<lac>	Hexadecimal format. Location area code. The parameter determines the two-byte location area code in hexadecimal format (e.g. 00C1 equals 193 in decimal) of the cell that was scanned. Range: 0–0xFFFFFFFF.	
	"_"	Invalid
<cellID>	Hexadecimal format. Cell ID. The parameter determines the 16-bit (GSM) or 28-bit (LTE) cell ID. Range: 0–0xFFFFFFFF.	
	"_"	Invalid
<BSIC>	Integer type. Base station identification code. Range: 0–63.	
<arfcn>	Integer type. The parameter determines the ARFCN of the cell that was scanned. Range: 0-1023.	
<band>	Integer type. The current band.	
	0	DCS_1800
	1	PCS_1900
	2	GSM_900
	"_"	Other bands
<rxlev>	Integer type. RX level value for base station selection in dB (see 3GPP 25.304). Range: 0-63. Subtracting 111 from the RX level value, a dBm value will be got.	
<txp>	Integer type. MS maximum TX power in CCH.	
<rla>	Integer type. Minimum access RX level.	
<drx>	Integer type. Discontinuous reception cycle length.	
<c1>	Integer type. Cell selection criterion.	
<c2>	Integer type. Cell reselection criterion.	
<gprs>	Integer type. Whether the current cell supports GPRS or not.	
	0	Not support GPRS
	1	Support GPRS
<tch>	Integer type. In hopping, displays 'h', otherwise displays the current ARFCN in a voice call.	
<ts>	Integer type. Timeslot number.	
<ta>	Integer type. Timing advance for the base station. Range: 0–63.	
<maio>	Integer type. Mobile allocation index offset.	
<hsn>	Integer type. Hopping sequence number.	
<rxqualsub>	Integer type. RX quality (sub). Range: 0–7.	
<rxqualfull>	Integer type. RX quality (full). Range: 0–7.	
<rxlevsub>	Integer type. RX level (sub). Range: 0–63.	

<rxlevfull>	Integer type. RX level (full). Range: 0–63.
<voicecodec>	String format. Channel mode during a voice call.
	"HR" Half rate
	"FR" Full rate
	"EFR" Enhanced full rate
	"AMR" Adaptive Multi-Rate
	"AMRHR" AMR half rate
	"AMRFR" AMR full rate
	"AMRWB" AMR wide band
	"_" Invalid
<is_tdd>	TDD or FDD mode.
<pcid>	Physical cell ID
<earfcn>	Integer type. E-UTRA-ARFCN of the cell that was scanned.
<freq_band_ind>	E-UTRA frequency band (see 3GPP 36.101).
<ul_bandwidth>	Integer type. UL bandwidth.
	0 1.4MHz
	1 3MHz
	2 5MHz
	3 10MHz
	4 15MHz
	5 20MHz
<dl_bandwidth>	Integer type. DL bandwidth.
	0 1.4MHz
	1 3MHz
	2 5MHz
	3 10MHz
	4 15MHz
	5 20MHz
<tac>	Tracking area code (see 3GPP 23.003 Chapter 19.4.2.3).
<rsrp>	Reference signal received power (see 3GPP 36.214 Chapter 5.1.1).
<rsrq>	Reference signal received quality (see 3GPP 36.214 Chapter 5.1.2).
<rssi>	Integer type. Received signal strength indication.
<sinr>	Integer type. Logarithmic value of SINR, and the db values is equal to the logarithmic value divided by 2 and minus 23.5. Range: 0–250, which translates to -20dB - +30dB.
<srxlev>	Integer type. Select RX level value for base station in dB (see 3GPP 25.304).
<c31>	Integer type. GPRS cell selection criterion.
<c32>	Integer type. GPRS cell reselection criterion.
<thresh_serving_low>	The threshold of <srxlev> (in dB) used by the UE on the serving cells when reselecting towards a lower priority RAT/frequency.
<cell_resel_priority>	Integer type. Cell reselection priority. Range: 0–7.
<s_non_intra_search>	Threshold to control non-intra-frequency searches.
<s_intra_search>	Cell selection parameter for the intra-frequency cell.

NOTES

1. If return “-” or -, it indicates the parameter is invalid under current condition.
2. 2G neighbour cells have already been visible in idle mode only.

Example

```
AT+QENG="servingcell"
+QENG: "servingcell","SEARCH"

OK
AT+QENG="servingcell"
+QENG: "servingcell","NOCONN","LTE","TDD",460,00,F2D4A44,206,39148,40,5,5,550B,-78,-3,-56,
118,47

OK
AT +QENG="neighbourcell"
+QENG: "neighbourcell intra","LTE",38950,201,-99,-5,-,-,26,-,-,-
+QENG: "neighbourcell intra","LTE",3590,471,-103,-16,-,-,22,-,-,-
+QENG: "neighbourcell intra","LTE",3590,121,-105,-18,-,-,20,-,-,-
+QENG: "neighbourcell intra","LTE",38400,121,-104,-9,-,-,35,-,-,-

OK
```

6.13. AT+CIND Command of Control Instructions

AT+CIND Command of Control Instructions

Test Command AT+CIND=?	Response +CIND: (<descr>,(list of supported <ind>s))[(<descr>,(list of supported <ind>s))][,...]] OK
Read Command AT+CIND?	Response +CIND: <ind>[,<ind>[,...]] OK If error is related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/

Parameter

<descr>	String type. Instructions state, see the following notes for details.
<ind>	Integer types. Instructions event, related to the value of the <descr> , see the following note for details.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTE

The values of **<descr>** and **<ind>** are described as follows:

<descr>	<ind>
"battchg"	Battery charge level. Range: 0–5.
"signal"	Signal strength indication. 0–5: According to the signal strength, it is divided into five levels from weak to strong.
"service"	Network service status indicator. 0 Not registered on the network 1 Registered to the known network
"sounder"	Sounder activity. Range: 0-1.
"message"	Message received. Range: 0-1.
"call"	Call status indication. 0 no call 1 call
"roam"	Roaming indicator. 0 Registered with the ownership or unregistered network 1 Registered to the roaming network
"smsfull"	A short message memory storage in the MT has become full ('0'), or memory locations are available ('1').

Example

AT+CIND=?

**+CIND: ("battchg",(0-5)),("signal",(0-5)),("service",(0,1)),("sounder",(0,1)),("message",(0,1)),("call",
(0,1)),("roam",(0,1)),("smsfull",(0,1))**

OK

AT+CIND?

+CIND: 0,3,1,0,0,0,1,0

OK

7 Call Related Commands

7.1. ATA Answer an Incoming Call

This command connects the module to an incoming voice or data call indicated by a **RING** URC.

ATA Answer an Incoming Call

Execution Command ATA	Response Response in case of voice call, if successfully connected: OK Response if no connection: NO CARRIER
Maximum Response Time	90 s, determined by network.
Characteristics	/
Reference V.25ter	

NOTES

- Any additional commands on the same command line are ignored.
- This command may be aborted generally by receiving a character during execution. The aborting is not possible during some states of connection establishment such as handshaking.

Example

```

RING                                     //A voice call is ringing
AT+CLCC
+CLCC: 1,0,0,1,0,"",128                 //PS call in LTE mode
+CLCC: 2,1,4,0,0,"02154450290",129     //Incoming call

OK
ATA                                     //Accept the voice call with ATA
OK

```

7.2. ATD Mobile Originated Call to Dial a Number

This command sets up outgoing voice and data calls. Supplementary services can also be controlled with this command.

ATD Mobile Originated Call to Dial a Number

Execution Command ATD<n>[<mgs>][:]	Response If a connection cannot be established: NO CARRIER If connection is successful and voice call: OK
Maximum Response Time	5 s, determined by network (AT+COLP=0).
Characteristics	/
Reference V.25ter	

Parameter

<n>	String of dialing digits and optionally V.25ter modifiers Dialing digits: 0-9, *, #, +, A, B, C Following V.25ter modifiers are ignored: ,(comma), T, P, !, W, @
<mgs>	String of GSM modifiers: I Activates CLIR (Disable presentation of own number to called party) i Deactivates CLIR (Enable presentation of own number to called party) G Activates closed user group invocation for this call only g Deactivates closed user group invocation for this call only
<;>	Only required to set up voice call, return to command mode

NOTES

- This command may be aborted generally by receiving an **ATH** command or a character during execution. The aborting is not possible during some states of connection establishment such as handshaking.
- Parameter "I" and "i" can be omitted only when there is no "*" or "#" code within the dial string.
- Responses returned after dialing with **ATD**:
For voice call, two different responses mode can be determined. TA returns **OK** immediately either after dialing was completed or after the call was established. The setting is controlled by **AT+COLP**. Factory default is **AT+COLP=0**, which causes the TA to return **OK** immediately after dialing was completed. Otherwise TA will return **OK**, **BUSY**, **NO DIAL TONE**, or **NO CARRIER**.
- Using **ATD** during an active voice call:

- When a user originates a second voice call while there is already an active voice call, the first call will be automatically put on hold.
- The current states of all calls can be easily checked at any time by using **AT+CLCC**.

Example

```
ATD10086;           //Dialing out the party's number
OK
```

7.3. ATH Disconnect Existing Connection

This command disconnects circuit switched data calls or voice calls. **AT+CHUP** is also used to disconnect the voice call.

ATH Disconnect Existing Connection

Execution Command ATH[n]	Response Disconnect existing call by local TE from command line and terminate the call. OK
Maximum Response Time	90 s, determined by network.
Characteristics	/
Reference V.25ter	

Parameter

<n>	Integer type
0	Disconnect existing call from command line and terminate the call

7.4. AT+CVHU Voice Hang up Control

This command controls whether **ATH** can be used to disconnect the voice call.

AT+CVHU Voice Hang up Control

Test Command AT+CVHU=?	Response +CVHU: (list of supported <mode>s)
----------------------------------	---

	OK
Read Command AT+CVHU?	Response +CVHU: <mode>
	OK
Write Command AT+CVHU=<mode>	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<mode>	Integer type
<u>0</u>	ATH can be used to disconnect the voice call.
1	ATH is ignored but OK response is returned.

7.5. AT+CHUP Hang up Voice Call

This command cancels all voice calls in the state of Active, Waiting and Held. For data connections, use **ATH**.

AT+CHUP Hang up Voice Call

Test Command AT+CHUP=?	Response OK
Execution Command AT+CHUP	Response OK Or ERROR
Maximum Response Time	90 s, determined by network.
Characteristics	/
Reference 3GPP 27.007	

Example

```
RING                //Incoming call

AT+CHUP             //Hang up the call
OK
```

7.6. +++ Switch from Data Mode to Command Mode

This command is only available when TA is in data mode. The "+++" character sequence causes the TA to cancel the data flow over the AT interface and switch to command mode. This allows entering AT command while maintaining the data connection with the remote server or, accordingly, the GPRS connection.

+++ Switch from Data Mode to Command Mode

Execution Command	Response
+++	OK
Maximum Response Time	300 ms
Characteristics	/
Reference	
V.25ter	

NOTES

- To prevent the +++ escape sequence from being misinterpreted as data, the following sequence should be followed:
 - Do not input any character within 1s before inputting +++.
 - Input +++ within 1s, and no other characters can be inputted during the time.
 - Do not input any character within 1s after +++ has been inputted.
 - Switch to command mode successfully; otherwise return to Step 1.
- To return back to data mode from command mode, please enter **ATO**.
- Another way to change to command mode is through DTR level change, and please refer to **AT&D** command for details.

7.7. ATO Switch from Command Mode to Data Mode

This command resumes the connection and switches back from command mode to data mode.

ATO Switch from Command Mode to Data Mode

Execution Command ATO[n]	<p>Response</p> <p>If connection is not successfully resumed: NO CARRIER</p> <p>If connection is successfully resumed, TA returns to data mode from command mode: CONNECT <text></p>
Maximum Response Time	300 ms
Characteristics	/
Reference V.25ter	

Parameter

<n>	Integer type
0	Switch from command mode to data mode

NOTE

When TA returns to data mode from command mode successfully, **CONNECT <text>** is returned. Please note that <text> outputs only when <value> is greater than 0 in **ATX<value>** parameter setting.

7.8. ATS0 Set Number of Rings before Automatically Answering

This command controls automatic answering mode for the incoming calls.

ATS0 Set Number of Rings before Automatically Answering

Read Command ATS0?	<p>Response</p> <p><n></p> <p>OK</p>
Write Command ATS0=<n>	<p>Response</p> <p>OK</p>
Maximum Response Time	300 ms
Characteristics	<p>The command takes effect immediately.</p> <p>The configuration can be saved with AT&W.</p>
Reference	

V.25ter

Parameter

<n>	Integer type. This parameter setting determines the number of rings before auto-answer.
<u>0</u>	Automatic answering is disabled
1–255	Enable automatic answering on the ring number specified

NOTE

If **<n>** is set too high, the calling party may hang up before the call is answered automatically.

Example

```

ATS0=3           //Set three rings before automatically answering a call
OK

RING             //A call is coming

RING

RING             //Automatically answering the call after three rings
  
```

7.9. ATS7 Set Time to Wait for Connection Completion

This command specifies the amount of time (unit: second) to wait for the connection completion in case of answering or originating a call. If no connection is established during the time, the module disconnects from the line.

ATS7 Set Time to Wait for Connection Completion

Read Command ATS7?	Response <n> OK
Write Command ATS7=<n>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately.

Reference
V.25ter

Parameter

<n> Integer type
0 Disabled
 1–255 Number of seconds to wait for connection completion. Unit: second.

7.10. AT+CSTA Select Type of Address

This Write Command selects the type of number for further dialing commands **ATD** according to 3GPP Specifications. Test command returns values supported a compound value.

AT+CSTA Select Type of Address

Test Command AT+CSTA=?	Response +CSTA: (list of supported <type>s)
----------------------------------	---

OK

Read Command AT+CSTA?	Response +CSTA: <type>
---------------------------------	--

OK

Write Command AT+CSTA=<type>	Response OK
--	-----------------------

Maximum Response Time	300 ms
-----------------------	--------

Characteristics	The command takes effect immediately. The configurations will not be saved.
-----------------	--

Reference 3GPP TS 27.007	
-----------------------------	--

Parameter

<type> Integer type. Current address type setting.
129 Unknown type
 145 International type (contains the character "+")
 161 National type

7.11. AT+CLCC List Current Calls of ME

This execution command returns the list of all current calls. If the command is executed successfully, but no calls existed, no information response but **OK** is sent to TE.

AT+CLCC List Current Calls of ME

Test Command AT+CLCC=?	Response OK
Execution Command AT+CLCC	Response [+CLCC : <id1>,<dir>,<stat>,<mode>,<mpty>[,<number>,<type>[,< alpha>]] [+CLCC: <id2>,<dir>,<stat>,<mode>,<mpty>[,<number>,<type>[,< alpha>]] [...] OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/

Parameter

<idx>	Integer type. Call identification number as described in <i>3GPP TS 22.030 subclause 4.5.5.1</i> . This number can be used in AT+CHLD command operation
<dir>	Integer type. 0 Mobile originated (MO) call 1 Mobile terminated (MT) call
<stat>	Integer type. State of the call 0 Active 1 Held 2 Dialing (MO call) 3 Alerting (MO call) 4 Incoming (MT call) 5 Waiting (MT call)
<mode>	Integer type. Bearer/tele service 0 Voice 1 Data

	2	FAX
<empty>	Integer type	
	0	Call is not one of multiparty (conference) call parties
	1	Call is one of multiparty (conference) call parties
<number>	Phone number in string type in format specified by <type>	
<type>	Type of address of octet in integer format (refer to 3GPP TS 24.008 <i>subclause 10.5.4.7</i> for details). Usually, it has three kinds of values:	
	129	Unknown type
	145	International type (contains the character "+")
	161	National type
<alpha>	Alphanumeric representation of <number> corresponding to the entry found in phonebook.	
<err>	Error codes. For more details, please refer to Chapter 14.5 .	

Example

```

ATD10086;                                //Establish a call
OK
AT+CLCC
+CLCC: 1,0,0,0,0,"10086",129             //Establish a call, and the call has been answered
OK

```

7.12. AT+CRRC Set Cellular Result Codes for Incoming Call Indication

This command controls whether or not to use the extended format of incoming call indication. When it is enabled, an incoming call is indicated to the TE with unsolicited result code **+CRING: <type>** instead of the normal **RING**.

AT+CRRC Set Cellular Result Codes for Incoming Call Indication

Test Command AT+CRRC=?	Response +CRRC: (list of supported <mode>s) OK
Read Command AT+CRRC?	Response +CRRC: <mode> OK
Write Command AT+CRRC=[<mode>]	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately.

	The configurations will not be saved.
Reference 3GPP TS 27.007	

Parameter

<mode>	Integer type	
	<u>0</u>	Disable extended format
	1	Enable extended format
<type>	ASYNCR	Asynchronous transparent
	SYNCR	Synchronous transparent
	RELASYNCR	Asynchronous non-transparent
	RELSYNCR	Synchronous non-transparent
	FAX	Facsimile
	VOICE	Voice

Example

```

AT+CR=1 //Enable extended format
OK

+CRING: VOICE //Indicate incoming call to the TE
ATH
OK
AT+CR=0 //Disable extended format
OK

RING //Indicate incoming call to the TE
ATH
OK

```

7.13. AT+QECCNUM Configure Emergency Call Numbers

This command queries, adds and deletes ECC (Emergency Call Codes) numbers. There are two kinds of ECC numbers: ECC numbers without (U)SIM and ECC numbers with (U)SIM. The default ECC numbers without (U)SIM is 911, 112, 00, 08, 110, 999, 118 and 119. The default ECC number with (U)SIM is 911 and 112. 911 and 112 will always be supported as ECC numbers, and cannot be deleted. ECC numbers can be saved into NV automatically. If the (U)SIM card contains ECC file, the numbers in ECC file can also be regarded as ECC numbers.

The maximal supported ECC numbers of each type is 20.

AT+QECCNUM Configure Emergency Call Numbers	
Test Command AT+QECCNUM=?	Response +QECCNUM: (range of supported <mode>s) OK
Write Command AT+QECCNUM=<mode>,<type>[,<eccnum1>[,<eccnum2>,...[,<eccnumN>]]]	Response If <mode> is equal to 0, query the ECC numbers. In this cases, <eccnumN> should be omitted: +QECCNUM: <type>,<eccnum1>,<eccnum2>[...] OK If <mode> is not equal to 0: <mode>=1 is used to add the ECC number; <mode>=2 is used to delete the ECC number. In this case, at least one ECC number <eccnumN> should be inputted, and the response is: OK Or ERROR
Read Command AT+QECCNUM?	Response +QECCNUM: 0,<eccnum1>,<eccnum2>[...] +QECCNUM: 1,<eccnum1>,<eccnum2>[...] OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved automatically.

Parameter

<mode>	Integer type. ECC number operations 0 Query ECC numbers 1 Add ECC numbers 2 Delete ECC numbers
<type>	Integer type. ECC number type 0 ECC numbers without (U)SIM 1 ECC numbers with (U)SIM
<eccnum>	String type. ECC numbers (e.g. 110, 119)

Example

AT+QECCNUM=? //Query the supported ECC number operation mode

+QECCNUM: (0-2)

OK

AT+QECCNUM? //Query the ECC numbers with or without (U)SIM

+QECCNUM: 0,"911","112","00","08","110","999","118","119"

+QECCNUM: 1,"911","112"

OK

AT+QECCNUM=0,1 //Query the ECC numbers with (U)SIM

+QECCNUM: 1,"911","112"

OK

AT+QECCNUM=1,1,"110","234" //Add "110" and "234" into the type of ECC numbers with (U)SIM

OK

AT+QECCNUM=0,1 //Query the ECC numbers with (U)SIM

+QECCNUM: 1, "911", "112", "110", "234"

OK

AT+QECCNUM=2,1,"110" //Delete "110" from the type of ECC numbers with (U)SIM

OK

AT+QECCNUM=0,1 //Query the ECC numbers with (U)SIM

+QECCNUM: 1, "911", "112", "234"

OK

7.14. AT+QHUP Hang up Call with a Specific Release Cause

This command can terminate a call or calls (including both voice call and data call) with a specific 3GPP TS 24.008 release cause specified by the host.

AT+QHUP Hang up Call with a Specific Release Cause

Test Command	Response
AT+QHUP=?	OK
Write Command	Response
AT+QHUP=<cause>[,<idx>]	OK Or ERROR
	If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	90 s, determined by network.

Characteristics

/

Parameter

<cause>	Integer type. Release cause. <i>3GPP TS 24.008</i> release cause to be indicated to the network.	
	1	Release cause "unassigned (unallocated) number"
	16	Release cause "normal call clearing"
	17	Release cause "user busy"
	18	Release cause "no user responding"
	21	Release cause "call rejected"
	27	Release cause "destination out of order"
	31	Release cause "normal, unspecified"
	88	Release cause "incompatible destination"
<idx>	Integer type. Call identification number is an optional index in the list of current calls indicated by AT+CLCC . AT+QHUP will terminate the call identified by the given call number. The default call number 0 is not assigned to any call, but signifies all calls.	
	0	Terminate all known calls. However, if circuit switches data calls and voice calls at the same time, this command only terminates the CSD calls.
	1...7	Terminate the specific call with identification number.
<err>	Error codes. For more details, please refer to Chapter 14.5 .	

Example

```

AT+QHUP=?           //Test Command
OK
ATD10010;           //Dial 10010
OK
AT+CLCC             //Query the status of calls
+CLCC: 1,0,0,0,0,"10010",129

OK
AT+QHUP=17,1        //Terminate the call whose ID is 1. Disconnect cause is "user busy"
OK
ATD10010;           //Dial 10010
OK
AT+CLCC             //Query the status of calls
+CLCC: 1,0,0,0,0,"10010",129

OK
AT+QHUP=16          //Terminate all existed calls. Disconnect cause is "normal call clearing"
OK

```

AT+CLCC

OK

7.15. AT+QCHLDIPMPTY Hang Up a Call in the VoLTE Conference

This command hangs up a call in the VoLTE conference.

AT+QCHLDIPMPTY Hang Up a Call in the VoLTE Conference

Test Command AT+QCHLDIPMPTY=?	Response +QCHLDIPMPTY: <number> OK
Write Command AT+QCHLDIPMPTY=<number>	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	/

Parameter

<number>	String of dialing digits and optionally V.25ter modifiers Dialing digits: 0-9, *, #, +, A, B, C
-----------------------	--

Example

```

AT+QCHLDIPMPTY=? //Test command
+QCHLDIPMPTY: <number>

OK
ATD13866783782; //Establish a call.
OK
AT+CLCC
+CLCC: 2,1,0,1,0,"",128
+CLCC: 1,0,0,0,0,"13866783782",129 //The second call be active.

OK
AT+CHLD=2 //Place the active call on hold and accept the waiting call as the active call.
OK
AT+CLCC //Query the status of calls.

```



```
+CLCC: 2,1,0,1,0,"",128
+CLCC: 1,0,1,0,0,"13866783782",129 //The second call on hold.

OK
ATD15155196746; //Establish a call.
OK
AT+CLCC
+CLCC: 2,1,0,1,0,"",128
+CLCC: 1,0,1,0,0,"13866783782",129 //The second call on hold.
+CLCC: 3,1,0,1,0,"",128
+CLCC: 4,0,0,0,0,"15155196746",129 //The fourth call be active.

OK
AT+CHLD=3 //Add a held call to the active calls in order to set up a conference (multiparty) call.
OK
AT+CLCC
+CLCC: 2,1,0,1,0,"",128
+CLCC: 3,1,0,1,0,"",128
+CLCC: 5,0,0,0,0,"sip:mmtel",128

OK
AT+QCHLDIPMPTY="13866783782" //Hang up a call which is activated.
OK
AT+QCHLDIPMPTY=" 15155196746" //Hang up a call which is activated.
OK
```

8 Phonebook Commands

8.1. AT+CNUM Subscriber Number

This command gets the subscribers' own number(s) from the (U)SIM.

AT+CNUM Subscriber Number	
Test Command AT+CNUM=?	Response OK
Execution Command AT+CNUM	Response [+CNUM: [<alpha>],<number>,<type>] [+CNUM: [<alpha>],<number>,<type>] OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP 27.007	

Parameter

<alpha>	Optional alphanumeric string associated with <number> . The used character set should be the one selected with AT+CSCS command
<number>	String type phone number of format specified by <type>
<type>	Type of address of octet in integer format (See <i>3GPP TS 24.008</i>). Usually, it has three kinds of values: 129 Unknown type 145 International type (contains the character "+") 161 National type
<err>	Error codes. For more details, please refer to Chapter 14.5 .

8.2. AT+CPBF Find Phonebook Entries

This command searches the phonebook entries starting with the given **<findtext>** string from the current phonebook memory storage selected with **AT+CPBS**, and return all found entries sorted in alphanumeric order.

AT+CPBF Find Phonebook Entries

Test Command AT+CPBF=?	Response +CPBF: <nlength>,<tlength> OK
Write Command AT+CPBF=<findtext>	Response [+CPBF: <index>,<number>,<type>,<text>] [...] OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	Depends on the storage of phonebook entries.
Characteristics	/
Reference 3GPP 27.007	

Parameter

<nlength>	Integer type. Indicate the maximum length of field <number>
<tlength>	Integer type. Indicate the maximum length of field <text>
<findtext>	String type. The field of maximum length <tlength> in current TE character set specified by AT+CSCS .
<number>	String type. The phone number of format specified by <type>
<index>	Integer type. In the range of location numbers of phonebook memory.
<type>	Type of address of octet in integer format (refer <i>3GPP TS 24.008</i>). Usually, it has three kinds of values: 129 Unknown type 145 International type (contains the character "+") 161 National type
<text>	String type field of maximum length <tlength> in current TE character set specified by AT+CSCS .

<err> Error codes. For more details, please refer to **Chapter 14.5**.

8.3. AT+CPBR Read Phonebook Entries

This command reads phonebook entries in location number range **<index1>... <index2>** from the current phonebook memory storage selected with **AT+CPBS**. If **<index2>** is left out, only location **<index1>** is returned.

AT+CPBR Read Phonebook Entries

Test Command AT+CPBR=?	Response +CPBR: (list of supported <index>s),<nlength>,<tlength> OK
Write Command AT+CPBR=<index1>[,<index2>]	Response +CPBR: <index1>,<number>,<type>,<text> [+CPBR: <index2>,<number>,<type>,<text> [...]] OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	Depends on the storage of phonebook entries.
Characteristics	/
Reference 3GPP 27.007	

Parameter

<index>	Integer type. Location numbers of phonebook memory.
<nlength>	Integer type. Indicate the maximum length of field <number>
<tlength>	Integer type. Indicate the maximum length of field <text>
<index1>	Integer type. The first phonebook record to read
<index2>	Integer type. The last phonebook record to read
<number>	String type. The phone number of format specified by <type>
<type>	Type of address of octet in integer format (see <i>3GPP TS 24.008</i>). Usually, it has three kinds of values: 129 Unknown type

	145	International type (contains the character "+")
	161	National type
<text>	String type. The field of maximum length <tlength> in current TE character set specified by AT+CSCS .	
<err>	Error codes. For more details, please refer to Chapter 14.5 .	

8.4. AT+CPBS Select Phonebook Memory Storage

This command selects phonebook memory storage, which is used by other phonebook commands. The Read Command returns currently selected memory, the number of used locations and the total number of locations in the memory when supported by manufacturer. The Test Command returns supported storages as compound value.

AT+CPBS Select Phonebook Memory Storage

Test Command AT+CPBS=?	<p>Response</p> <p>+CPBS: (list of supported <storage>s)</p> <p>OK</p> <p>Or</p> <p>ERROR</p> <p>If there is any error related to ME functionality: +CME ERROR: <err></p>
Read Command AT+CPBS?	<p>Response</p> <p>+CPBS: <storage>,<used>,<total></p> <p>OK</p> <p>Or</p> <p>ERROR</p> <p>If there is any error related to ME functionality: +CME ERROR: <err></p>
Write Command AT+CPBS=<storage>	<p>Response</p> <p>OK</p> <p>Or</p> <p>ERROR</p> <p>If there is any error related to ME functionality: +CME ERROR: <err></p>
Maximum Response Time	300 ms
Characteristics	/

Reference
3GPP 27.007

Parameter

<storage>	String type. Phonebook memory storage "SM" (U)SIM phonebook "FD" (U)SIM fix dialing-phonebook (AT+CPBW operation need the authority of PIN2) "LD" (U)SIM last-dialing-phonebook (AT+CPBW may not be applicable to this storage) "ME" Mobile equipment phonebook "ON" (U)SIM own numbers (MSISDNs) list
<used>	Integer type. Indicate the total number of used locations in selected memory
<total>	Integer type. Indicate the total number of locations in selected memory
<err>	Error codes. For more details, please refer to Chapter 14.5 .

8.5. AT+CPBW Write Phonebook Entry

This command writes phonebook entry in location number **<index>** in the current phonebook memory storage selected with **AT+CPBS**. It can also delete a phonebook entry in location number **<index>**.

AT+CPBW Write Phonebook Entry

Test Command AT+CPBW=?	Response +CPBW: (range of supported <index>s), <nlength> ,(list of supported <type>s), <tlength> OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Write Command AT+CPBW=[<index>][,<number>[,<type>[,<text>]]]	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/
Reference	

3GPP 27.007

Parameter

<index>	Integer type. Location numbers of phonebook memory. If <index> is not given, the first free entry will be used. If <index> is given as the only parameter, the phonebook entry specified by <index> is deleted.
<nlength>	Integer type. Indicate the maximum length of field <number> .
<tlength>	Integer type. Indicate the maximum length of field <text> .
<number>	String type phone number of format specified by <type>
<type>	Type of address of octet in integer format (See 3GPP TS 24.008). Usually, it has three kinds of values: 129 Unknown type 145 International type (contains the character "+") 161 National type
<text>	String type field of maximum length <tlength> in current TE character set specified by AT+CSCS .
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```
AT+CSCS="GSM"
OK
AT+CPBW=10,"15021012496",129,"QUECTEL"
OK                                     //Make a new phonebook entry at location 10
AT+CPBW=10                           //Delete the entry at location 10
OK
AT+CPBR=10
OK
```

9 Short Message Service Commands

9.1. AT+CSMS Select Message Service

This command selects messaging service **<service>** and returns the types of messages supported by the ME.

AT+CSMS Select Message Service	
Test Command AT+CSMS=?	Response +CSMS: (list of supported <service>s) OK
Read Command AT+CSMS?	Response +CSMS: <service> , <mt> , <mo> , <bm> OK
Write Command AT+CSMS=<service>	Response +CSMS: <mt> , <mo> , <bm> OK If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved automatically.
Reference 3GPP TS 27.005	

Parameter

<service>	Integer type. Type of message service <u>0</u> 3GPP TS 23.040 and 3GPP TS 23.041 (the syntax of SMS AT commands is compatible with 3GPP TS 27.005 Phase 2 version 4.7.0; Phase 2+ features which do not require new command syntax may be supported, e.g. correct routing of messages with new Phase 2+ data coding schemes).
------------------------	--

	1	3GPP TS 23.040 and 3GPP TS 23.041 (the syntax of SMS AT commands is compatible with 3GPP TS 27.005 Phase 2+ version; the requirement of <service> setting 1 is mentioned under corresponding command descriptions).
<mt>	Integer type. Mobile terminated messages	
	0	Type not supported
	<u>1</u>	Type supported
<mo>	Integer type. Mobile originated messages	
	0	Type not supported
	<u>1</u>	Type supported
<bm>	Integer type. Broadcast type messages	
	0	Type not supported
	<u>1</u>	Type supported
<err>	Error codes. For more details, please refer to Chapter 14.6 .	

Example

```

AT+CSMS=?                                //Test command
+CSMS: (0,1)

OK
AT+CSMS=1                                //Set type of message service to 1
+CSMS: 1,1,1

OK
AT+CSMS?                                //Read command
+CSMS: 1,1,1,1

OK

```

9.2. AT+CMGF Message Format

This command specifies the input and output format of the short messages. **<mode>** indicates the format of messages used with Test, Read, Write and Execution Commands and unsolicited result codes resulting from received messages.

The format of messages can be either PDU mode (entire TP data units used) or text mode (headers and body of the messages given as separate parameters). Text mode uses the value of parameter **<chset>** specified by **AT+CSCS** command to inform the character set to be used in the message body in the TA-TE interface.

AT+CMGF Message Format

Test Command AT+CMGF=?	Response +CMGF: (list of supported <mode>s) OK
Read Command AT+CMGF?	Response +CMGF: <mode> OK
Write Command AT+CMGF[=<mode>]	Response TA sets parameter to denote which kind of I/O format of messages is used. OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.005	

Parameter

<mode>	Integer type
0	PDU mode
1	Text mode

9.3. AT+CSCA Service Center Address

This Write Command updates the SMSC address when mobile originated SMS are transmitted. In text mode, the setting is used by Write Command. In PDU mode, setting is used by the same command, but only when the length of the SMSC address is coded into the **<pdu>** parameter which equals to zero.

AT+CSCA Service Center Address

Test Command AT+CSCA=?	Response OK
Read Command AT+CSCA?	Response +CSCA: <sca>,<tosca> OK
Write Command	Response

AT+CSCA=<sca>[,<tosca>]	OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved automatically.
Reference 3GPP TS 27.005	

Parameter

<sca>	Service center address. 3GPP TS 24.011 RP SC address Address-Value field in string format; BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see AT+CSCS command in 3GPP TS 27.007). The type of address is given by <tosca>.
<tosca>	Type of service center address. 3GPP TS 24.011 RP SC address Type-of-Address octet in integer format (see <toda>).
<err>	Error codes. For more details, please refer to Chapter 14.6 .

Example

```
AT+CSCA="+8613800210500",145 //Set SMS service center address
OK
AT+CSCA? //Query SMS service center address
+CSCA: "+8613800210500",145
OK
```

9.4. AT+CPMS Preferred Message Storage

This command selects the memory storages <mem1>, <mem2> and <mem3> to be used for reading, writing, etc.

AT+CPMS Preferred Message Storage

Test Command AT+CPMS=?	Response +CPMS: (list of supported <mem1>s),(list of supported <mem2>s),(list of supported <mem3>s) OK
---------------------------	---

Read Command AT+CPMS?	Response +CPMS: <mem1>,<used1>,<total1>,<mem2>,<used2>,<total2>,<mem3>,<used3>,<total3> OK
Write Command AT+CPMS=<mem1>[,<mem2>[,<mem3>]]	Response +CPMS: <used1>,<total1>,<used2>,<total2>,<used3>,<total3> OK If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved automatically.
Reference 3GPP TS 27.005	

Parameter

<mem1>	String type. Messages to be read and deleted from this memory storage "SM" (U)SIM message storage <u>"ME"</u> Mobile equipment message storage "MT" Same as "ME" storage
<mem2>	String type. Messages will be written and sent to this memory storage "SM" (U)SIM message storage <u>"ME"</u> Mobile equipment message storage "MT" Same as "ME" storage
<mem3>	String type. Received messages will be placed in this memory storage if routing to PC is not set (AT+CNMI) "SM" (U)SIM message storage <u>"ME"</u> Mobile equipment message storage "MT" Same as "ME" storage
<usedx>	Integer type. Number of current messages in <memx>
<totalx>	Integer type. Total number of messages which can be stored in <memx>
<err>	Error codes. For more details, please refer to Chapter 14.6 .

Example

```
AT+CPMS? //Query the current SMS message storage
+CPMS: "ME",0,255,"ME",0,255,"ME",0,255
```

```
OK
AT+CPMS="SM","SM","SM"           //Set SMS message storage as "SM"
+CPMS: 0,50,0,50,0,50

OK
AT+CPMS?                           //Query the current SMS message storage
+CPMS: "SM",0,50,"SM",0,50,"SM",0,50

OK
```

9.5. AT+CMGD Delete Message

This command deletes short messages from the preferred message storage **<mem1>** location **<index>**. If **<delflag>** is presented and not set to 0, then the ME shall ignore **<index>** and follow the rules of **<delflag>** shown as below.

AT+CMGD Delete Message

Test Command AT+CMGD=?	Response +CMGD: (range of supported <index>s),(range of supported <delflag>s) OK
Write Command AT+CMGD=<index>[,<delflag>]	Response TA deletes message from preferred message storage <mem1> location <index> . OK If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	300 ms. Note: Operation of <delflag> depends on the storage of deleted messages.
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference 3GPP TS 27.005	

Parameter

<index> Integer type. Location numbers supported by the associated memory.

<delflag>	Integer type
0	Delete the message specified in <index>
1	Delete all read messages from <mem1> storage
2	Delete all read messages from <mem1> storage and sent mobile originated messages
3	Delete all read messages from <mem1> storage, sent and unsent mobile originated messages
4	Delete all messages from <mem1> storage
<mem1>	String type. Messages to be read and deleted from this memory storage
"SM"	(U)SIM message storage
"ME"	Mobile equipment message storage
"MT"	Same as "ME" storage
<err>	Error codes. For more details, please refer to Chapter 14.6 .

Example

```

AT+CMGD=1 //Delete the message specified in <index>=1
OK
AT+CMGD=1,4 //Delete all messages from <mem1> storage
OK

```

9.6. AT+CMGL List Message

The Read Command returns messages with status value **<stat>** from preferred message storage **<mem1>** to the TE. If the status of the message is "REC UNREAD", the status in the storage changes to "REC READ". When executing command **AT+CMGL** without status value **<stat>**, it will report the list of SMS with "REC UNREAD" status.

AT+CMGL List Message

Test Command AT+CMGL=?	Response +CMGL: (list of supported <stat> s) OK
Write Command AT+CMGL[=<stat>]	Response If in text mode (AT+CMGF=1) and the command is executed successfully: For SMS-SUBMITs and/or SMS-DELIVERs: +CMGL: <index>,<stat>,<oa/da>,[<alpha>],[<scts>][,<toa/toda>,<length>]<CR><LF><data>[<CR><LF> +CMGL: <index>,<stat>,<da/oa>,[<alpha>],[<scts>][,<toa/toda>,<length>]<CR><LF><data>[...]]

	<p>For SMS-STATUS-REPORTs:</p> <p>+CMGL: <index>,<stat>,<fo>,<mr>,[<ra>],[<tora>],<sct s>,<dt>,<st>[<CR><LF> +CMGL: <index>,<stat>,<fo>,<mr>,[<ra>],[<tora>],<sct s>,<dt>,<st>[...]]</p> <p>For SMS-COMMANDs:</p> <p>+CMGL: <index>,<stat>,<fo>,<ct>[<CR><LF> +CMGL: <index>,<stat>,<fo>,<ct>[...]]</p> <p>For CBM storage:</p> <p>+CMGL: <index>,<stat>,<sn>,<mid>,<page>,<pages><C R><LF><data>[<CR><LF> +CMGL: <index>,<stat>,<sn>,<mid>,<page>,<pages><C R><LF><data>[...]]</p> <p>OK</p> <p>If in PDU mode (AT+CMGF=0) and the command is executed successfully:</p> <p>+CMGL: <index>,<stat>,[<alpha>],<length><CR><LF><p du><CR><LF> +CMGL: <index>,<stat>,[alpha],<length><CR><LF><pd u>[...]]</p> <p>OK</p> <p>If there is any error related to ME functionality:</p> <p>+CMS ERROR: <err></p>
Execution Command AT+CMGL	<p>Response</p> <p>List all messages with "REC UNREAD" status from message storage <mem1>, and then the status in the storage changes to "REC READ".</p>
Maximum Response Time	300 ms.
Characteristics	<p>The command takes effect immediately.</p> <p>The configurations will not be saved.</p>
Reference 3GPP TS 27.005	

Parameter

<stat> String type. In text mode:

"REC UNREAD"	Received unread messages
"REC READ"	Received read messages
"STO UNSENT"	Stored unsent messages
"STO SENT"	Stored sent messages
"ALL"	All messages
Integer type. In PDU mode:	
0	Received unread messages
1	Received read messages
2	Stored unsent messages
3	Stored sent messages
4	All messages
<index>	Integer type. Location numbers supported by the associated memory
<da>	Destination Address. 3GPP TS 23.040 TP-Destination-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see AT+CSCS command in 3GPP TS 27.007). The type of address is given by <tda>.
<oa>	Originating address. 3GPP TS 23.040 TP-Originating-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see AT+CSCS command in 3GPP TS 27.007). The type of address is given by <toa>.
<alpha>	String type alphanumeric representation of <da> or <oa> corresponding to the entry found in MT phonebook. Implementation of this feature is manufacturer specified. The used character set should be the one selected with AT+CSCS command (see definition of this command in 3GPP TS 27.007).
<scts>	Service center time stamp. 3GPP TS 23.040 TP-Service-Centre-Time-Stamp in time-string format (see <dt>).
<tda>	Type of recipient address. 3GPP TS 24.011 TP-Recipient-Address Type-of-Address octet in integer format.
<toa>	Type of originating address. 3GPP TS 24.011 TP-Originating-Address Type-of-Address octet in integer format (see <tda> by default).
<length>	Message length. Integer type. Indicate the length of the message body <data> (or <cdata>) in characters in the text mode (AT+CMGF=1), or the length of the actual TP data unit in octets in PDU mode (AT+CMGF=0) (i.e. the RP layer SMSC address octets are not counted in the length).
<data>	<p>In the case of SMS: 3GPP TS 23.040 TP-User-Data in text mode responses; format:</p> <ul style="list-style-type: none"> - If <dcs> (see chapter 9.7), indicates that 3GPP TS 23.038 GSM 7 bit default alphabet is used and <fo> (see chapter 9.7) indicates that 3GPP TS 23.040 TP-User-Data-Header-Indication is not set. - If TE character set other than "HEX" (refer to AT+CSCS command in 3GPP TS 27.007): ME/TA converts GSM alphabet into current TE character set according to rules of Annex A in 3GPP TS 27.007. - If TE character set is "HEX": ME/TA converts each 7-bit character of GSM 7 bit default alphabet into two IRA character long hexadecimal number (e.g. character II (GSM 7 bit default alphabet 23) is presented as 17 (IRA 49 and 55)).

- If **<dcs>**, indicates that 8-bit or UCS2 data coding scheme is used, or **<fo>** indicates that 3GPP TS 23.040 TP-User-Data-Header-Indication is set: ME/TA converts each 8-bit octet into two IRA character long hexadecimal number (e.g. octet with integer value 42 is presented to TE as two characters 2A (IRA 50 and 65)).

In the case of CBS: 3GPP TS 23.041 CBM Content of Message in text mode responses; format:

- If **<dcs>**, indicates that 3GPP TS 23.038 GSM 7 bit default alphabet is used:
- If TE character set other than "HEX" (see **AT+CSCS** in 3GPP TS27.007): ME/TA converts GSM alphabet into current TE character set according to rules of **Annex A** in 3GPP TS 27.007.
- If TE character set is "HEX": ME/TA converts each 7-bit character of the GSM 7 bit default alphabet into two IRA character long hexadecimal number.
- If **<dcs>**, indicates that 8-bit or UCS2 data coding scheme is used: ME/TA converts each 8-bit octet into two IRA character long hexadecimal number.

<pdu> In the case of SMS: 3GPP TS 24.011 SC address followed by 3GPP TS 23.040 TPDU in hexadecimal format: ME/TA converts each octet of TP data unit into two IRA character long hexadecimal number (e.g. octet with integer value 42 is presented to TE as two characters 2A (IRA 50 and 65)) 3GPP TS 27.007.

<fo> Depends on the command or result code: first octet of 3GPP TS 23.040 [3] SMS-DELIVER, SMS-SUBMIT (default 17), SMS-STATUS-REPORT, or SMS-COMMAND (default 2) in integer format.

<mr> 3GPP TS 23.040 [3] TP-Message-Reference in integer format

<ra> 3GPP TS 23.040 [3] TP-Recipient-Address Address-Value field in string format; BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see +CSCS in 3GPP TS 27.007 [9]); type of address given by **<tora>**

<tora> 3GPP TS 24.011 [6] TP-Recipient-Address Type-of-Address octet in integer format (see **<toda>** by default)

<scts> 3GPP TS 23.040 [3] TP-Service-Centre-Time-Stamp in time-string format (see **<dt>**)

<dt> 3GPP TS 23.040 [3] TP-Discharge-Time in time-string format: "yy/MM/dd,hh:mm:ss zz", where characters indicate year (two last digits), month, day, hour, minutes, seconds and time zone. E.g. 6th of May 1994, 22:10:00 GMT+2 hours equals to "94/05/06,22:10:00+08".

<st> 3GPP TS 23.040 [3] TP-Status in integer format.

<ct> 3GPP TS 23.040 [3] TP-Command-Type in integer format (default 0)

<sn> 3GPP TS 23.041 [4] CBM Serial Number in integer format.

<mid> 3GPP TS 23.041 [4] CBM Message Identifier in integer format.

<page> 3GPP TS 23.041 [4] CBM Page Parameter bits 4-7 in integer format.

<pages> 3GPP TS 23.041 [4] CBM Page Parameter bits 0-3 in integer format.

<mem1> Messages to be read and deleted from this memory storage

"SM" (U)SIM message storage

"ME" Mobile equipment message storage

"MT"	Same as "ME" storage
<err>	Integer type. For details of error codes, please refer to Chapter 14.6 .

Example

```

AT+CMGF=1 //Set SMS message format as text mode
OK
AT+CMGL="ALL" //List all messages from message storage
+CMGL: 1,"STO UNSENT","",,
<This is a test from Quectel>
+CMGL: 2,"STO UNSENT","",,
<This is a test from Quectel>
OK

```

NOTE

Operation of <stat> depends on the storage of listed messages.

9.7. AT+CMGR Read Message

This Read Command returns SMS message with location value <index> from message storage <mem1> to the TE. If status of the message is "REC UNREAD", status in the storage changes to "REC READ".

AT+CMGR Read Message	
Test Command AT+CMGR=?	Response OK
Write Command AT+CMGR=<index>	Response In Non-CDMA mode: If in text mode (AT+CMGF=1) and the command is executed successfully: For SMS-DELIVER: +CMGR: <stat>,<oa>,[<alpha>],<scts>[,<tooa>,<fo>,<pid>,<dc>,<sca>,<tosca>,<length>]<CR><LF><data> OK For SMS-SUBMIT: +CMGR: <stat>,<da>,[<alpha>][,<toda>,<fo>,<pid>,<dc>

	<p>s>,[<vp>],[<sca>,<tosca>,<length>]<CR><LF><data></p> <p>OK</p> <p>For SMS-STATUS-REPORTs:</p> <p>+CMGR: <stat>,<fo>,<mr>,[<ra>],[<tora>],[<scts>,<dt>,<st></p> <p>OK</p> <p>For SMS-COMMANDs:</p> <p>+CMGR: <stat>,<fo>,<ct>,[<pid>],[<mn>],[<da>],[<toda>],[<length><CR><LF><cdata>]</p> <p>OK</p> <p>For CBM storage:</p> <p>+CMGR: <stat>,<sn>,<mid>,<dc>,<page>,<pages><CR><LF><data></p> <p>OK</p> <p>If in PDU mode (AT+CMGF=0) and command is executed successfully:</p> <p>+CMGR: <stat>,[<alpha>],[<length><CR><LF><pdu></p> <p>OK</p> <p>In CDMA Text mode:</p> <p>+CMGR: <stat>,<oa/da>,<scts>,<alpha>,<tooa/toda>,<lang>,<fmt>,<length>,<prt>,<prv>,<type><CR><LF><data></p> <p>OK</p> <p>If there is any error related to ME functionality:</p> <p>+CMS ERROR: <err></p>
Maximum Response Time	Depends on the length of message content.
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference 3GPP TS 27.005	

Parameter

<index>	Integer type value in the range of location numbers supported by the associated
---------	---

	memory
<stat>	String type. In text mode
	"REC UNREAD" Received unread messages
	"REC READ" Received read messages
	"STO UNSENT" Stored unsent messages
	"STO SENT" Stored sent messages
	"ALL" All messages
	Integer type. In PDU mode
	0 Received unread messages
	1 Received read messages
	2 Stored unsent messages
	3 Stored sent messages
	4 All messages
<alpha>	String type alphanumeric representation of <da> or <oa> corresponding to the entry found in MT phonebook. Implementation of this feature is manufacturer specified. The used character set should be the one selected with AT+CSCS command (see definition of this command in <i>3GPP TS 27.007</i>).
<da>	Destination address. 3GPP TS 23.040 TP-Destination-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (refer to AT+CSCS command in <i>3GPP TS 27.007</i>). The type of address is given by <toda> .
<oa>	Originating address. 3GPP TS 23.040 TP-Originating-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (refer to AT+CSCS command in <i>3GPP TS 27.007</i>). The type of address is given by <tooa> .
<scts>	Service center time stamp. 3GPP TS 23.040 TP-Service-Centre-Time-Stamp in time-string format (refer to <dt>).
<fo>	First octet. Depending on the command or result code: First octet of 3GPP TS 23.040 SMS-DELIVER, SMS-SUBMIT (default 17), SMS-STATUS-REPORT, or SMS-COMMAND in integer format. If a valid value has been entered once, the parameter can be omitted.
<pid>	Protocol identifier. 3GPP TS 23.040 TP-Protocol-Identifier in integer format (default 0).
<dc>	Data coding scheme. Depending on the command or result code: 3GPP TS 23.038 SMS Data Coding Scheme (default 0), or Cell Broadcast Data Coding Scheme in integer format.
<vp>	Validity period. Depending on SMS-SUBMIT <fo> setting: 3GPP TS 23.040 TP-Validity-Period either in integer format or in time-string format (refer to <dt>).
<mn>	Message number. 3GPP TS 23.040 TP-Message-Number in integer format.
<mr>	Message reference. 3GPP TS 23.040 TP-Message-Reference in integer format.
<ra>	Recipient address. 3GPP TS 23.040 TP-Recipient-Address Address-Value field in string format. BCD numbers (or GSM default alphabet characters) are converted to characters of the currently selected TE character set (refer to AT+CSCS command). The type of address is given by <tora> .

<tora>	Type of recipient address. 3GPP TS 24.011 TP-Recipient-Address Type-of-Address octet in integer format (default refer <toda>).
<toda>	Type of recipient address. 3GPP TS 24.011 TP-Recipient-Address Type-of-Address octet in integer format.
<toa>	Type of originating address. 3GPP TS 24.011 TP-Originating-Address Type-of-Address octet in integer format (default refer to <toda>).
<sca>	Service center address. 3GPP TS 24.011 RP SC address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (refer to AT+CSCS command in 3GPP TS 27.007). The type of address is given by <tosca> .
<tosca>	Type of service center address. 3GPP TS 24.011 RP SC address Type-of-Address octet in integer format (default refer to <toda>).
<length>	Message length. Integer type. Indicating in the text mode (AT+CMGF=1) the length of the message body <data> (or <cdata>) in characters, or in PDU mode (AT+CMGF=0) the length of the actual TP data unit in octets (i.e. the RP layer SMSC address octets are not counted in the length).
<data>	The text of short message. Please refer Chapter 14.8 for details.
<pdu>	In the case of SMS: 3GPP TS 24.011 SC address followed by 3GPP TS 23.040 TPDU in hexadecimal format: ME/TA converts each octet of TP data unit into two IRA character long hexadecimal number (e.g. octet with integer value 42 is presented to TE as two characters 2A (IRA 50 and 65)).
<prt>	Priority <ul style="list-style-type: none"> 0 Normal 1 Interactive 2 Urgent 3 Emergency
<fmt>	Format <ul style="list-style-type: none"> 0 GSM 7 bit 1 ASCII 6 UNICODE
<prv>	Privacy <ul style="list-style-type: none"> 0 Normal 1 Restricted 2 Confidential 3 Secret
<lang>	Language <ul style="list-style-type: none"> 0 Unspecified 1 English 2 French 3 Spanish 4 Japanese 5 Korean 6 Chinese 7 Hebrew

<type>	0	Normal
	1	CPT
	2	Voice Mail
	3	SMS Report
<mem1>	String type. Messages to be read and deleted from this memory storage	
	"SM"	(U)SIM message storage
	"ME"	Mobile equipment message storage
	"MT"	Same as "ME" storage
<err>	Error codes. For more details, please refer to Chapter 14.6 .	

Example

```
+CMTI: "SM",3 //Indicates that new message has been received and saved
to <index>=3 of "SM"

AT+CSDH=1
OK
AT+CMGR=3 //Read message
+CMGR: "REC UNREAD","+8615021012496",,"13/12/13,15:06:37+32",145,4,0,0,"+861380021050
0",145,27

<This is a test from Quectel>

OK
```

9.8. AT+CMGS Send Message

This command sends a short message from TE to network (SMS-SUBMIT). After invoking the write command, wait for the prompt **>** and then start to write the message. After that, enter **<CTRL-Z>** to indicate the ending of PDU and begin to send the message. Sending can be cancelled by giving **<ESC>** character. Abortion is acknowledged with **OK**, though the message will not be sent. The message reference **<mr>** is returned to the TE on successful message delivery. The value can be used to identify message upon unsolicited delivery status report result code.

AT+CMGS Send Message

Test Command AT+CMGS=?	Response OK
Write Command 1) If text mode (AT+CMGF=1): AT+CMGS=<da>[,<toda>]<CR> text is entered <Ctrl+Z/ESC> ESC quits without sending	Response TA sends message from TE to the network (SMS-SUBMIT). Message reference value <mr> is returned to the TE on successful message delivery. Optionally (when AT+CSMS <service> value is 1 and network supports) <scts> is returned. Values can be used to identify message upon

2) If PDU mode (AT+CMGF=0): AT+CMGS=<length><CR> PDU is given <Ctrl+Z/ESC>	<p>unsolicited delivery status report result code.</p> <p>If in text mode (AT+CMGF=1) and sent successfully: +CMGS: <mr></p> <p>OK</p> <p>If in PDU mode (AT+CMGF=0) and sent successfully: +CMGS: <mr></p> <p>OK</p> <p>If there is any error related to ME functionality: +CMS ERROR: <err></p>
Maximum Response Time	120 s, determined by network.
Characteristics	<p>The command takes effect immediately.</p> <p>The configurations will not be saved.</p>
Reference 3GPP TS 27.005	

Parameter

<da>	Destination address. 3GPP TS 23.040 TP-Destination-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (refer to AT+CSCS command in 3GPP TS 27.007). The type of address is given by <tda>.
<tda>	Type of recipient address. 3GPP TS 24.011 TP-Recipient-Address Type-of-Address octet in integer format.
<length>	<p>Integer type. Integer type. Indicating in the text mode (AT+CMGF=1) the length of the message body <data> (or <cdata>) in characters, or in PDU mode (AT+CMGF=0), the length of the actual TP data unit in octets (i.e. the RP layer SMSC address octets are not counted in the length).</p> <p>The maximum length in text mode is 160 bytes.</p> <p>The maximum length in PDU mode is 140 bytes.</p>
<mr>	Message reference. 3GPP TS 23.040 TP-Message-Reference in integer format.
<err>	Error codes. For more details, please refer to Chapter 14.6 .

NOTES

- For concatenated messages, the maximum length will be reduced by the length of the user data header (UDH). 3GPP TS 23.040 defines two kinds of UDH length: 6 bytes and 7 bytes, so the two kinds of <uid> are 8-bit (6 bytes) and 16-bit (7 bytes). **AT+QCMGS** uses 8-bit <uid>.
 - In the case of GSM 7 bit default alphabet data coding scheme, the maximum length of each

segment of a concatenated message is $(140 \text{ octets} - 6) * 8 / 7 = 153$ characters.

- In the case of 16 bit UCS2 data coding scheme, the maximum length of each segment is $(140-6)/2=67$ characters.
- In the case of 8-bit data coding scheme, the maximum length of each segment is $140-6=134$ characters.

2. **<mr>** Message-Reference field gives an integer representation of a reference number of the SMS-SUBMIT or SMS-COMMAND submitted to the SC by the MS, and it is used to confirm whether the SMS-DELIVER has been received from SC duplicate or not.
<uid> The field of UDH. It is message identification of the concatenated SMS, which is different from **<mr>**. Each segment in a concatenated message should have the same **<uid>**, but **<mr>** must be incremented for each segment of a concatenated message.
3. **AT+QCMGS** does not support to send message in PDU mode (**AT+CMGF=0**).

Example

```
AT+CMGF=1 //Set SMS message format as text mode
OK
AT+CSCS="GSM" //Set character set as GSM which is used by the TE
OK
AT+CMGS="15021012496"
> <This is a test from Quectel> //Enter in text. Use <CTRL+Z> to send message, or
                                <ESC> quits without sending
+CMGS: 247
OK
```

9.9. AT+CMMS More Messages to Send

This command controls the continuity of the SMS relay protocol link. If the feature is enabled (and supported by the currently used network) multiple messages can be sent faster as the link is kept open.

AT+CMMS More Messages to Send

Test Command AT+CMMS=?	Response +CMMS: (range of supported <n>s) OK
Read Command AT+CMMS?	Response +CMMS: <n> OK
Write Command	Response

AT+CMMS=<n>	OK Or ERROR If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	120 s, determined by network.
Characteristics	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.005	

Parameter

<n>	Integer type
0	Feature disabled
1	Keep enabled until the time between the response of the latest message send command (AT+CMGS , AT+CMSS , etc.) and the next send command exceeds 1-5 seconds (the exact value is up to ME implementation), and then ME shall close the link and TA switches <n> back to 0 automatically
2	Feature enabled (if the time between the response of the latest message send command and the next send command exceeds 1-5 seconds (the exact value is up to ME implementation), ME shall close the link but TA will not switch <n> back to 0 automatically)
<err>	Error codes. For more details, please refer to Chapter 14.6 .

NOTE

After the execution of Read Command, a delay of 5-10 seconds is required before issuing the Write Command. Otherwise the **+CMS ERROR: 500** may appear.

9.10. AT+CMGW Write Message to Memory

This Write and Execution Commands store short messages from TE to memory storage <mem2>, and then the memory location <index> of the stored message is returned. Message status will be set to "stored unsent" by default, but parameter <stat> also allows other status values to be given. The syntax of input text is the same as the one specified in **AT+CMGS** Write Command.

AT+CMGW Write Message to Memory

Test Command	Response
--------------	----------

AT+CMGW=?	OK
Write Command 1) If text mode (AT+CMGF=1): AT+CMGW=<oa/da>[,<toa/toda>[,<stat>]]<CR> text is entered <Ctrl+Z/ESC> <ESC> quits without sending 2) If PDU mode (AT+CMGF=0): AT+CMGW=<length>[,<stat>]<CR> PDU is given <Ctrl+Z/ESC>	Response If writing is successful: +CMGW: <index> OK If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference 3GPP TS 27.005	

Parameter

<da>	Destination address. 3GPP TS 23.040 TP-Destination-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see AT+CSCS command in 3GPP TS 27.007). The type of address is given by <toda> .		
<oa>	Originating address. 3GPP TS 23.040 TP-Originating-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see AT+CSCS command in 3GPP TS 27.007). The type of address given by <toa> .		
<toa>	Type of originating address. 3GPP TS 24.011 TP-Originating-Address Type-of-Address octet in integer format (see <toda> by default).		
<stat>	PDU mode	Text mode	Explanation
	0	"REC UNREAD"	Received unread messages
	1	"REC READ"	Received read messages
	2	"STO UNSENT"	Stored unsent messages
	3	"STO SENT"	Stored sent messages
	4	"ALL"	All messages
<toda>	Type of recipient address. 3GPP TS 24.011 TP-Recipient-Address Type-of-Address octet in integer format.		
<length>	Message length. Integer type, indicating the length of the message body <data> (or <cdata>) in characters in the text mode (AT+CMGF=1), or in PDU mode (AT+CMGF=0), the length of the actual TP data unit in octets (i.e. the RP layer SMSC address octets are not counted in the length).		
<pdu>	In the case of SMS: 3GPP TS 24.011 SC address followed by 3GPP TS 23.04TPDU in		

hexadecimal format: ME/TA converts each octet of TP data unit into two IRA character long hexadecimal number (e.g. octet with integer value 42 is presented to TE as two characters 2A (IRA 50 and 65)).

<index> Index of message in selected storage **<mem2>**.
<err> Error codes. For more details, please refer to **Chapter 14.6**.

Example

```
AT+CMGF=1 //Set SMS message format as text mode
OK
AT+CSCS="GSM" //Set character set as GSM which is used by the TE
OK
AT+CMGW="15021012496"
> <This is a test from Quectel> //Enter in text. Use <CTRL+Z> to write message or
<ESC> to quit without sending.

+CMGW: 4

OK
AT+CMGF=0 //Set SMS message format as PDU mode
OK
AT+CMGW=18
> 0051FF00000008000A0500030002016D4B8BD5
+CMGW: 5

OK
```

9.11. AT+CMSS Send Message from Storage

This Write Command sends message with location value **<index>** from message storage **<mem2>** to the network (SMS-SUBMIT). If new recipient address **<da>** is given, it shall be used instead of the one stored with the message. Reference value **<mr>** is returned to the TE on successful message delivery. Values can be used to identify message upon unsolicited delivery status report result code.

AT+CMSS Send Message from Storage

Test Command AT+CMSS=?	Response OK
Write Command AT+CMSS=<index>[,<da>[,<toda>]]	Response If in text mode (AT+CMGF=1) and sent successfully: +CMSS: <mr>[,<scts>] OK

	<p>If in PDU mode (AT+CMGF=0) and sent successfully: +CMSS: <mr> [,<ackpdu>]</p> <p>OK</p> <p>If there is any error related to ME functionality: +CMS ERROR: <err></p>
Maximum Response Time	120 s, determined by network.
Characteristics	<p>The command takes effect immediately.</p> <p>The configurations will not be saved.</p>
Reference	3GPP TS 27.005

Parameter

<index>	Integer type value in the range of location numbers supported by the associated memory.
<da>	Destination Address. 3GPP TS 23.040 TP-Destination-Address Address-Value field in string format. BCD numbers (or GSM 7 bit default alphabet characters) are converted to characters of the currently selected TE character set (see AT+CSCS command in 3GPP TS 27.007). The type of address is given by <toda> .
<toda>	Type of recipient address. 3GPP TS 24.011 TP-Recipient-Address Type-of-Address octet in integer format.
<mr>	Message reference. 3GPP TS 23.040 TP-Message-Reference in integer format.
<scts>	Service center time stamp. 3GPP TS 23.040 TP-Service-Centre-Time-Stamp in time-string format (see <dt>).
<ackpdu>	The format is the same as <pdu> in case of SMS, but without 3GPP TS 24.011 SC address field and the parameter shall be bounded by double quote characters like a normal string type parameter.
<err>	Error codes. For more details, please refer to Chapter 14.6 .

Example

```

AT+CMGF=1           //Set SMS message format as text mode
OK
AT+CSCS="GSM"       //Set character set as GSM which is used by the TE
OK
AT+CMGW="15021012496"
> Hello             //Enter in text. Use <CTRL+Z> to send message or
                    //<ESC> to quit without sending.
+CMGW: 4

```

```
OK
AT+CMSS=4 //Send the message of index 4 from memory storage.
+CMSS: 54
OK
```

9.12. AT+CNMA New Message Acknowledgement to UE/TE

This Write and Execution Commands confirm successful receipt of a new message (SMS-DELIVER or SMS-STATUS-REPORT) routed directly to the TE. If the UE does not receive acknowledgement within required time (network timeout), it sends an **RP-ERROR** message to the network. The UE will automatically disable routing to the TE by setting both **<mt>** and **<ds>** values of **AT+CNMI** to 0.

AT+CNMA New Message Acknowledgement to UE/TE

Test Command AT+CNMA=?	Response +CNMA: (range of supported <n>s) OK
Execution Command AT+CNMA	Response OK Or ERROR If there is any error related to ME functionality: +CMS ERROR: <err>
Write Command AT+CNMA=<n>	Response OK Or ERROR If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.005	

Parameter

<n> Integer type. Parameter required only for PDU mode

- | | |
|---|--|
| 0 | Command operates similarly as in text mode |
| 1 | Send positive (RP-ACK) acknowledgement to the network. Accepted only in PDU mode |
| 2 | Send negative (RP-ERROR) acknowledgement to the network. Accepted only in PDU mode |

<err> Error codes. For more details, please refer to **Chapter 14.6**.

NOTE

The Execution and Write Commands shall only be used when **AT+CSMS** parameter **<service>** equals 1 (phase 2+) and an appropriate URC has been issued by the module, i.e.:

+CMT for **<mt>**=2 incoming message classes 0,1,3 and none;

+CMT for **<mt>**=3 incoming message classes 0 and 3;

+CDS for **<ds>**=1.

Example

```
AT+CSMS=1
OK
AT+CNMI=1,2,0,0,0
OK

+CMT: "+8615021012496",,"13/03/18,17:07:21+32",145,4,0,0,"+8613800551500",145,28
This is a test from Quectel.           //Short message is outputted directly when an SMS is incoming.

AT+CNMA                               //Send ACK to the network
OK
AT+CNMA
+CMS ERROR: 340                       //An error returned for the second time. It needs ACK only once.
```

9.13. AT+CNMI SMS Event Reporting Configuration

This Write Command selects the procedure on how the received new messages from the network are indicated to the TE when TE is active, e.g. DTR is at low level (ON). If TE is inactive (e.g. DTR is at high level (OFF)), message receiving should be done as specified in 3GPP TS 23.038.

AT+CNMI SMS Event Reporting Configuration

Test Command	Response
AT+CNMI=?	+CNMI: (range of supported <mode> s),(range of supported <mt> s),(list of supported <bm> s),(range of supported <ds> s),(list of supported <bfr> s)

	OK
Read Command AT+CNMI?	Response +CNMI: <mode>,<mt>,<bm>,<ds>,<bfr>
	OK
Write Command AT+CNMI[=<mode>,<mt>,<bm>,<ds>,<bfr>]]]]	Response OK Or ERROR If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved automatically.
Reference 3GPP TS 27.005	

Parameter

<mode>	Integer type
0	Buffer unsolicited result codes in the TA. If TA result code buffer is full, indications can be buffered in some other place or the oldest indications may be discarded and replaced with the new received indications.
1	Discard indication and reject new received message unsolicited result codes when TA-TE link is reserved (e.g. in on-line data mode). Otherwise forward them directly to the TE.
<u>2</u>	Buffer unsolicited result codes in the TA when TA-TE link is reserved (e.g. in data mode) and flush them to the TE after reservation. Otherwise forward them directly to the TE.
3	Forward unsolicited result codes directly to the TE. TA-TE link specific inband technique used to embed result codes and data when TA is in on-line data mode.
<mt>	Integer type. The rules for storing received SMS depend on its data coding scheme (refer to 3GPPTS 23.038) and preferred memory storage (AT+CPMS) setting, and the value is:
0	No SMS-DELIVER indications are routed to the TE.
<u>1</u>	If SMS-DELIVER is stored into ME/TA, indication of the memory location is routed to the TE by using unsolicited result code: +CMTI: <mem>,<index>
2	SMS-DELIVERs (except class 2) are routed directly to the TE using unsolicited result code: +CMT: [<i><alpha></i>],<length><CR><LF><pdu> (PDU mode enabled) or +CMT: <oa>,<alpha>,<scts>,<tooa>,<fo>,<pid>,<dcs>,<sca>,<tosca>,<length>]<CR><LF><data> (text mode enabled; about the parameters in italics, see AT+CSDH) or ^HCMT: <oa>,<scts>,<lang>,<fmt>,<length> ,

	<prt>,<prv>,<type>,<stat><CR><LF><data> (text mode for CDMA SMS). Class 2 messages result in indication as defined in <mt>=1 .
3	Class 3 SMS-DELIVERs are routed directly to TE by using unsolicited result codes defined in <mt>=2 . Messages of other classes result in indication as defined in <mt>=1 .
<bm>	Integer type. The rules for storing received CBMs depend on its data coding scheme (see 3GPP TS 23.038) and the setting of Select CBM Types (AT+CSCB), and the value is: 0 No CBM indications are routed to the TE. 2 New CBMs are routed directly to the TE using unsolicited result code: +CBM: <length><CR><LF><pdu> (PDU mode); or +CBM: <sn>,<mid>,<dcs>,<page>,<pages><CR><LF><data> (text mode)
<ds>	Integer type. 0 No SMS-STATUS-REPORTs are routed to the TE. 1 SMS-STATUS-REPORTs are routed to the TE using unsolicited result code: +CDS: <length><CR><LF><pdu> (PDU mode) +CDS: <fo>,<mr>,<ra>,<tora>,<scts>,<dt>,<st> (text mode)
<bfr>	Integer type. 0 TA buffer of unsolicited result codes defined within this command is flushed to the TE when <mode> 1 or 2 is entered (OK response shall be given before flushing the codes). 1 TA buffer of unsolicited result codes defined within this command is cleared when <mode> 1 or 2 is entered.
<err>	Error codes. For more details, please refer to Chapter 14.6 .

NOTE

Unsolicited result code:

+CMTI: <mem>,<index>	Indicates that new message has been received
+CMT: [<alpha>],<length><CR><LF><pdu>	Short message is outputted directly
+CBM: <length><CR><LF><pdu>	Cell broadcast message is outputted directly

Example

```

AT+CMGF=1           //Set SMS message format as text mode
OK
AT+CSCS="GSM"       //Set character set as GSM which is used by the TE
OK
AT+CNMI=1,2,0,1,0   //Set SMS-DELIVERs are routed directly to the TE
OK

+CMT: "+8615021012496",,"13/03/18,17:07:21+32",145,4,0,0,"+8613800551500",145,28
This is a test from Quectel.           //Short message is outputted directly when an SMS is incoming.

```


9.14. AT+CSDH Show SMS Text Mode Parameters

This Write Command controls whether detailed header information is shown in text mode result codes.

AT+CSDH Show SMS Text Mode Parameters

Test Command AT+CSDH=?	Response +CSDH: (list of supported <show>s) OK
Read Command AT+CSDH?	Response +CSDH: <show> OK
Write Command AT+CSDH[=<show>]	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.005	

Parameter

<show>	Integer type
<u>0</u>	Do not show header values defined in commands +CSCA , +CSMP (<sca>, <tosca>, <fo>, <vp>, <pid>, <dcs>) and <length>, <toda> or <tooa> in +CMT , +CMGL , +CMGR result codes for SMS-DELIVERs and SMS-SUBMITs in text mode
1	Show the values in result codes

Example

```
AT+CSDH=0
OK
AT+CMGR=2
+CMGR: "STO UNSENT", "",
<This is a test from Quectel>
OK
AT+CSDH=1
OK
```

```
AT+CMGR=2
+CMGR: "STO UNSENT", "", 128,17,0,0,143,"+8613800551500",145,18
<This is a test from Quectel>
OK
```

9.15. AT+CSMP Set SMS Text Mode Parameters

This command sets values for additional parameters needed when a short message is sent to the network or placed in a storage in text mode.

AT+CSMP Set SMS Text Mode Parameters

Test Command AT+CSMP=?	Response OK
Read Command AT+CSMP?	Response +CSMP: <fo>,<vp>,<pid>,<dc> OK
Write Command AT+CSMP=<fo>[,<vp>[,<pid>[,<dc>]]]	Response TA selects values for additional parameters needed when SM is sent to the network or placed in a storage when text mode is selected (AT+CMGF=1). It is possible to set the validity period starting from when the SM is received by the SMSC (<vp> ranges from 0 to 255) or define the absolute time of the validity period termination (<vp> is a string). OK
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.005	

Parameter

<fo>	First octet. Depending on the command or result code: First octet of 3GPP TS 23.040 SMS-DELIVER, SMS-SUBMIT (default 17), SMS-STATUS-REPORT, SMS-COMMAND in integer format. If a valid value has been entered once, parameter can be omitted.
<vp>	Validity period. Depending on SMS-SUBMIT <fo> setting: 3GPP TS 23.040 TP-Validity-Period either in integer format or in time-string format (refer to <dt>).
<pid>	Protocol identifier. 3GPP TS 23.040 TP-Protocol-Identifier in integer format (default 0).
<dc>	Data coding scheme. Depending on the command or result code: 3GPP TS 23.038

SMS Data Coding Scheme (default 0), or Cell Broadcast Data Coding Scheme in integer format.

9.16. AT+QCMGS Send Concatenated Messages

This command sends concatenated messages. Different from **AT+CMGS**, when sending a concatenated message via this command, each segment of the concatenated message must be identified by the additional parameters: **<uid>**, **<msg_seg>** and **<msg_total>**. When sending all segments of the message one by one, **AT+QCMGS** must be executed multiple times (equal to **<msg_total>**) for each segment. This command is only used in text mode (**AT+CMGF=1**).

AT+QCMGS Send Concatenated Messages

Test Command AT+QCMGS=?	Response OK
Write Command If text mode (+CMGF=1): AT+QCMGS=<da>[,<toda>],<uid>,<msg_seg>,<msg_total><CR> text is entered <Ctrl+Z/ESC>	Response If in text mode (AT+CMGF=1) and sent successfully: +QCMGS: <mr> OK Or ERROR If there is any error related to ME functionality: +CMS ERROR: <err>
Maximum Response Time	120 s, determined by network.
Characteristics	/

Parameter

<uid>	Integer type. Message identification in the user data header (UDH). Range: 0–255. This parameter is defined and inputted by the user. All segments of a same concatenated message must have the same <uid> . Different concatenated messages should have different <uid> .
<msg_seg>	Integer type. Sequence number of a concatenated message. Range: 0–7. <msg_seg>=0 means: ignore the value and regard it as a non-concatenated message.
<msg_total>	Integer type. The total number of the segments of one concatenated message. Range: 0–7. <msg_total>=0 or 1 means: ignore the value and regard it as a non-concatenated message.
<da>	Please refer to AT+CMGS .

<tda>	Please refer to AT+CMGS .
<mr>	Please refer to AT+CMGS .
<err>	Integer type. For details of error codes, please refer to Chapter 14.6 .

NOTES

- For concatenated messages, the maximum length will be reduced by the length of the user data header (UDH). 3GPP TS 23.040 defines two kinds of UDH length: 6 bytes and 7 bytes, so the two kinds of <uid> are 8-bit (6 bytes) and 16-bit (7 bytes). **AT+QCMGS** uses 8-bit <uid>.
 - In the case of GSM 7 bit default alphabet data coding scheme, the maximum length of each segment of a concatenated message is $(140 \text{ octets} - 6) * 8 / 7 = 153$ characters.
 - In the case of 16 bit UCS2 data coding scheme, the maximum length of each segment is $(140-6)/2=67$ characters.
 - In the case of 8-bit data coding scheme, the maximum length of each segment is $140-6=134$ characters.
- <mr> Message-Reference field gives an integer representation of a reference number of the SMS-SUBMIT or SMS-COMMAND submitted to the SC by the MS, and it is used to confirm whether the SMS-DELIVER has been received from SC duplicate or not.

<uid> The field of UDH. It is message identification of the concatenated SMS, which is different from <mr>. Each segment in a concatenated message should have the same <uid>, but <mr> must be incremented for each segment of a concatenated message.
- AT+QCMGS** does not support to send message in PDU mode (**AT+CMGF=0**).

Example

```

AT+CMGF=1                                //Set SMS message format as text mode
OK
AT+CSCS="GSM"                             //Set character set as GSM which is used by the TE
OK
AT+QCMGS="15056913384",120,1,2 <CR>      //Input 120 for <uid>, and send the first segment of the
                                           concatenated SMS
>ABCD<Ctrl-Z>
+QCMGS: 190

OK
AT+QCMGS="15056913384",120,2,2 <CR>      //Send the second segment of the concatenated SMS.
>EFGH<Ctrl-Z>
+QCMGS: 191

OK

```

9.17. AT+QCMGR Read Concatenated Messages

The function of this command is similar to **AT+CMGR**, except that the message to be read is a segment of concatenated messages, and parameters **<uid>**, **<msg_seg>** and **<msg_total>** would be shown in the result. Several segments should be concatenated to a whole concatenated message according to these three parameters. Similar to **AT+QCMGS**, **AT+QCMGR** is only used in text mode (**AT+CMGF=1**).

AT+QCMGR Read Concatenated Messages

Test Command AT+QCMGR=?	Response OK
Write Command AT+QCMGR=<index>	<p>Response in text mode (AT+CMGF=1) and command is executed successfully: For SMS-DELIVER: +QCMGR: <stat>,<oa>,<[alpha]>,<scts>,<tooa>,<fo>,<pid>,<dc>,<sca>,<tosca>,<length>,<[uid>,<msg_seg>,<msg_total>,<CR><LF><data></p> <p>OK For SMS-SUBMIT: +QCMGR: <stat>,<da>,<[alpha]>,<[toda>,<fo>,<pid>,<dc>,<[vp>,<sca>,<tosca>,<length>,<[uid>,<msg_seg>,<msg_total>,<CR><LF><data></p> <p>OK For SMS-STATUS-REPORTs: +QCMGR: <stat>,<fo>,<mr>,<[ra>,<[tora>,<scts>,<dt>,<st></p> <p>OK For SMS-COMMANDs: +QCMGR: <stat>,<fo>,<ct>,<[pid>,<[mn>,<[da>,<[toda>,<length>,<CR><LF><cdata></p> <p>OK Else, If there is any error related to ME functionality: +CMS ERROR: <err></p>
Maximum Response Time	Depends on the length of message content.

Characteristics

/

Parameter

<uid>	Integer type. Message identification in the user data header (UDH). Range: 0–65535 (see NOTES). All segments of a same concatenated message have same <uid> . Different concatenated messages should have different <uid> .
<msg_seg>	Integer type. Sequence number of a concatenated message. Range: 1–7.
<msg_total>	Integer type. The total number of the segments of one concatenated message. Range: 2–7.
	Other parameters please refer to AT+CMGR
<err>	Integer type. For details of error codes, please refer to Chapter 14.6 .

NOTES

1. The **<uid>** in **AT+QCMGR** is different from the **<uid>** in **AT+QCMGS**. It is possible that UE receives concatenated messages with 8-bit or 16-bit **<uid>**. So its maximal value is 255 with 8-bit and 65535 with 16-bit.
2. If the message to be read is not a concatenated message, **<uid>**, **<msg_seg>** and **<msg_total>** would not be shown in the result.

Example

```
+CMTI: "SM",3           //The first message of a concatenated message comes

+CMTI: "SM",4           //The second message of a concatenated message comes
AT+QCMGR=3              //Read the first segment of the concatenated message
+QCMGR: "REC UNREAD","+8615056913384",,"13/07/30,14:44:37+32",120,1,2
ABCD

OK

AT+QCMGR=4              //Read the second segment of the concatenated message
+QCMGR: "REC UNREAD","+8615056913384",,"13/07/30,14:44:37+32",120,2,2
EFGH

OK
```

10 Packet Domain Commands

10.1. AT+CGATT Attachment or Detachment of PS

This Write Command attaches the MT to, or detaches the MT from the Packet Domain service. After the command has been completed, the MT remains in V.25ter command state. If the MT is already in the requested state, the command will be ignored and the **OK** response will be returned. If the requested state cannot be achieved, an **ERROR** or **+CME ERROR** response is returned.

AT+CGATT Attachment or Detachment of PS	
Test Command AT+CGATT=?	Response +CGATT: (list of supported <state>s) OK
Read Command AT+CGATT?	Response +CGATT: <state> OK
Write Command AT+CGATT=<state>	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	140 s, determined by network.
Characteristics	Whether the command takes effect determined by network. The configuration will not be saved.
Reference 3GPP TS 27.007	

Parameter

<state>	Integer type. Indicates the state of PS attachment. 0 Detached 1 Attached Other values are reserved and will result in an ERROR response to the Write Command.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```

AT+CGATT=1           //Attach to PS service
OK
AT+CGATT=0           //Detach from PS service
OK
AT+CGATT?             //Query the current PS service state
+CGATT: 0
OK

```

10.2. AT+CGDCONT Define PDP Context

This command specifies PDP context parameters for a specific context **<cid>**. A special form of the Write Command (**AT+CGDCONT=<cid>**) causes the values for context **<cid>** to become undefined. It is not allowed to change the definition of an already activated context.

This Read Command returns the current settings for each defined PDP context.

AT+CGDCONT Define PDP Context	
Test Command AT+CGDCONT=?	Response +CGDCONT: (range of supported <cid> s), <PDP_type> , <APN> , <PDP_addr> ,(range of supported <data_comp> s), (range of supported <head_comp> s),(list of supported <IPv4_addr_alloc> s),(list of supported <request_type> s) OK
Read Command AT+CGDCONT?	Response +CGDCONT: <cid> , <PDP_type> , <APN> , <PDP_addr> , <data_comp> , <head_comp> , <IPv4_addr_alloc> , <request_type> [...] OK
Write Command AT+CGDCONT=<cid>[,<PDP_type>[,<APN>[,<PDP_addr>[,<data_comp>[,<head_comp>[,<IPv4_addr_alloc>[,<request_type>]]]]]]]	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately.

	The configurations will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<cid>	Integer type. PDP context identifier. A numeric parameter which specifies a particular PDP context definition. The parameter is local to the TE-MT interface and is used in other PDP context-related commands. The range of permitted values (minimum value = 1) is returned by the test form of the command.
<PDP_type>	String type. Packet data protocol type, a string parameter which specifies the type of packet data protocol. "IP" Internet Protocol (IETF STD 5) "PPP" "IPv6" "IPv4V6"
<APN>	String type. Access point name, a string parameter that is a logical name used to select the GGSN or the external packet data network. If the value is null or omitted, then the subscription value will be requested.
<PDP_addr>	String type. Identifies the MT in the address space applicable to the PDP. If the value is null or omitted, then a value may be provided by the TE during the PDP startup procedure or, failing that, a dynamic address will be requested. The allocated address may be read with AT+CGPADDR .
<data_comp>	Integer type. Controls PDP data compression (applicable for SNDCP only) (refer to 3GPP TS 44.065). 0 Off (Default if value is omitted) 1 On (Manufacturer preferred compression) 2 V.42bis
<head_comp>	Integer type. Controls PDP header compression (refer to 3GPP TS 44.065 and 3GPP TS 25.323). 0 Off (Default if value is omitted) 1 On 2 RFC1144 3 RFC2507 4 RFC3095
<IPv4_addr_alloc>	Integer type. Controls how the MT/TA requests to get the IPv4 address information. 0 IPv4 address allocation through NAS signaling 1 IPv4 address allocated through DHCP
<request_type>	Integer type. Indicate the type of PDP context activation request for the PDP context. 0 PDP context is for new PDP context establishment or for handover from

a non-3GPP access network (how the MT decides whether the PDP context is for new PDP context establishment or for handover is implementation specific).

1 PDP context is for emergency bearer services.

10.3. AT+CGQREQ Quality of Service Profile (Requested)

This command allows the TE to specify the quality of service profile that is used when the MT activates a PDP context.

The Write Command specifies a profile for the context **<cid>**. A special form of the Write Command, **AT+CGQREQ=<cid>** causes the requested profile for context number **<cid>** to become undefined. This Read Command returns the current settings for each defined context. Details can be found in *3GPP TS 23.107*.

AT+CGQREQ Quality of Service Profile (Requested)	
Test Command AT+CGQREQ=?	<p>Response</p> <p>+CGQREQ: <PDP_type>,(range of supported <precedence>s),(range of supported <delay>s),(range of supported <reliability>s),(range of supported <peak>s),(range of supported <mean>s)</p> <p>OK</p>
Read Command AT+CGQREQ?	<p>Response</p> <p>[+CGQREQ: <cid>,<precedence>,<delay>,<reliability>,<peak>,<mean>]</p> <p>[+CGQREQ: <cid>,<precedence>,<delay>,<reliability>,<peak>,<mean>]</p> <p>[...]</p> <p>OK</p>
Write Command AT+CGQREQ=<cid>[,<precedence>[,<delay>[,<reliability>[,<peak>[,<mean>]]]]]	<p>Response</p> <p>OK</p> <p>If there is any error related to ME functionality: +CME ERROR: <err></p>
Maximum Response Time	300 ms
Characteristics	<p>The command takes effect immediately.</p> <p>The configurations will be saved automatically.</p>
Reference	3GPP TS 27.007

Parameter

<cid>	Integer type. Specifies a particular PDP context definition (see AT+CGDCONT).
<PDP_type>	String type. Packet Data Protocol type. "IP" Internet Protocol (IETF STD 5) "PPP" "IPV6" "IPV4V6"
<precedence>	Integer type. Specifies the precedence class. <u>0</u> Network subscribed value 1 High Priority. Service commitments shall be maintained ahead of precedence classes 2 and 3 2 Normal priority. Service commitments shall be maintained ahead of precedence class 3 3 Low priority. Service commitments shall be maintained
<delay>	Integer type. Specifies the delay class. This parameter defines the end-to-end transfer delay incurred in the transmission of SDUs through the network. For the details, please refer to Table 5 . <u>0</u> Network subscribed value
<reliability>	Integer type. Specifies the reliability class. <u>0</u> Network subscribed value 1 Non real-time traffic, error-sensitive application that cannot cope with data loss 2 Non real-time traffic, error-sensitive application that can cope with infrequent data loss 3 Non real-time traffic, error-sensitive application that can cope with data loss, GMM/SM, and SMS 4 Real-time traffic, error-sensitive application that can cope with data loss 5 Real-time traffic, error non-sensitive application that can cope with data loss
<peak>	Integer type. Specifies the peak throughput class, in octets per second. <u>0</u> Network subscribed value 1 Up to 1 000 (8 kbit/s) 2 Up to 2 000 (16 kbit/s) 3 Up to 4 000 (32 kbit/s) 4 Up to 8 000 (64 kbit/s) 5 Up to 16 000 (128 kbit/s) 6 Up to 32 000 (256 kbit/s) 7 Up to 64 000 (512 kbit/s) 8 Up to 128 000 (1024 kbit/s) 9 Up to 256 000 (2048 kbit/s)
<mean>	A numeric parameter which specifies the mean throughput class, in octets per hour. <u>0</u> Network subscribed value 1 100 (~0.22 bit/s) 2 200 (~0.44 bit/s)

3	500 (~1.11 bit/s)
4	1 000 (~2.2 bit/s)
5	2 000 (~4.4 bit/s)
6	5 000 (~11.1 bit/s)
7	10 000 (~22 bit/s)
8	20 000 (~44 bit/s)
9	50 000 (~111 bit/s)
10	100 000 (~0.22 kbit/s)
11	200 000 (~0.44 kbit/s)
12	500 000 (~1.11 kbit/s)
13	1000 000 (~2.2 kbit/s)
14	2 000 000 (~4.4 kbit/s)
15	5 000 000 (~11.1 kbit/s)
16	10 000 000 (~22 kbit/s)
17	20 000 000 (~44 kbit/s)
18	50 000 000 (~111 kbit/s)
31	Best effort

<err> Error codes. For more details, please refer to **Chapter 14.5**.

Table 5: Delay Class

SDU Size	Delay Class	Mean Transfer Delay	95 Percentile
128 octets	1 (Predictive)	< 0.5	< 1.5
	2 (Predictive)	< 5	< 25
	3 (Predictive)	< 50	< 250
	4 (Best Effort)	Unspecified	-
1024 octets	1 (Predictive)	< 0.5	< 1.5
	2 (Predictive)	< 5	< 25
	3 (Predictive)	< 50	< 250
	4 (Best Effort)	Unspecified	-

10.4. AT+CGQMIN Quality of Service Profile (Minimum Acceptable)

This command allows the TE to specify a minimum acceptable profile which is checked by the MT against

the negotiated profile when the PDP context is activated. This Write Command specifies a profile for the context identified by the context identification parameter **<cid>**.

A special form of the Write Command, **AT+CGQMIN=<cid>** causes the minimum acceptable profile for context number **<cid>** to become undefined. In this case no check is made against the negotiated profile. This Read Command returns the current settings for each defined context. Details can be found in 3GPP TS 23.107.

AT+CGQMIN Quality of Service Profile (Minimum Acceptable)	
Test Command AT+CGQMIN=?	Response +CGQMIN: <PDP_type> , (range of supported <precedence>s), (range of supported <delay>s), (range of supported <reliability>s), (range of supported <peak>s), (range of supported <mean>s) OK
Read Command AT+CGQMIN?	Response [+CGQMIN: <cid>,<precedence>,<delay>,<reliability>,<peak>,<mean>] [+CGQMIN: <cid>,<precedence>,<delay>,<reliability>,<peak>,<mean>] [...] OK
Write Command AT+CGQMIN=<cid>[,<precedence>[,<delay>[,<reliability>[,<peak>[,<mean>]]]]]	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<cid>	Integer type. Specifies a particular PDP context definition (see AT+CGDCONT).
<PDP_type>	String type. Packet Data Protocol type. "IP" IPv4. Internet Protocol (IETF STD 5) "PPP" "IPV6"

	"IPV4V6"
<precedence>	Integer type. Specifies the precedence class.
	0 Network subscribed value
	1 High Priority. Service commitments shall be maintained ahead of precedence classes 2 and 3
	2 Normal priority. Service commitments shall be maintained ahead of precedence class 3
	3 Low priority. Service commitments shall be maintained
<delay>	Integer type. Specifies the delay class. This parameter defines the end-to-end transfer delay incurred in the transmission of SDUs through the network. For the detail please refer to Table 5
	0 Network subscribed value
<reliability>	Integer type. Specifies the reliability class.
	0 Network subscribed value
	1 Non real-time traffic, error-sensitive application that cannot cope with data loss
	2 Non real-time traffic, error-sensitive application that can cope with infrequent data loss
	3 Non real-time traffic, error-sensitive application that can cope with data loss, GMM/SM, and SMS
	4 Real-time traffic, error-sensitive application that can cope with data loss
	5 Real-time traffic, error non-sensitive application that can cope with data loss
<peak>	Integer type. Specifies the peak throughput class, in octets per second.
	0 Network subscribed value
	1 Up to 1 000 (8 kbit/s)
	2 Up to 2 000 (16 kbit/s)
	3 Up to 4 000 (32 kbit/s)
	4 Up to 8 000 (64 kbit/s)
	5 Up to 16 000 (128 kbit/s)
	6 Up to 32 000 (256 kbit/s)
	7 Up to 64 000 (512 kbit/s)
	8 Up to 128 000 (1024 kbit/s)
	9 Up to 256 000 (2048 kbit/s)
<mean>	Integer type. Specifies the mean throughput class, in octets per hour.
	0 Network subscribed value
	1 100 (~0.22 bit/s)
	2 200 (~0.44 bit/s)
	3 500 (~1.11 bit/s)
	4 1 000 (~2.2 bit/s)
	5 2 000 (~4.4 bit/s)
	6 5 000 (~11.1 bit/s)
	7 10 000 (~22 bit/s)
	8 20 000 (~44 bit/s)
	9 50 000 (~111 bit/s)

10	100 000 (~0.22 kbit/s)
11	200 000 (~0.44 kbit/s)
12	500 000 (~1.11 kbit/s)
13	1000 000 (~2.2 kbit/s)
14	2 000 000 (~4.4 kbit/s)
15	5 000 000 (~11.1 kbit/s)
16	10 000 000 (~22 kbit/s)
17	20 000 000 (~44 kbit/s)
18	50 000 000 (~111 kbit/s)
31	Best effort

<err> Error codes. For more details, please refer to **Chapter 14.5**.

10.5. AT+CGACT Activate or Deactivate PDP Context

This Write Command activates or deactivates the specified PDP context(s). After the command has completed, the MT remains in V.250 command state. If any PDP context is already in the requested state, the state for that context remains unchanged. If the MT is not PS attached when the activation form of the command is executed, the MT first performs a PS attach and then attempts to activate the specified contexts. If no **<cid>**s specify the activation/deactivation form of the command, it will activate or deactivate all defined contexts.

AT+CGACT Activate or Deactivate PDP Context	
Test Command AT+CGACT=?	Response +CGACT: (list of supported <state> s) OK
Read Command AT+CGACT?	Response +CGACT: <cid> , <state> [+CGACT: <cid> , <state> ...] OK
Write Command AT+CGACT=<state>,<cid>	Response OK Or NO CARRIER If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	150 s, determined by network.

Characteristics	Whether the command takes effect is determined by network. The configurations will not be saved.
Reference 3GPP TS 27.007	

Parameter

<state>	Integer type. Indicates the state of PDP context activation. 0 Deactivated 1 Activated Other values are reserved and will result in an ERROR response to the Write Command
<cid>	Integer type. Specifies a particular PDP context definition (see AT+CGDCONT).
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTE

If VoLTE feature is enabled, **<cid>** holds a range from 1 to 5.

Example

```
AT+CGDCONT=1,"IP","UNINET" //Define PDP context
OK
AT+CGACT=1,1                //Activated PDP
OK
AT+CGACT=0,1                //Deactivated the PDP
OK
```

10.6. AT+CGDATA Enter Data State

This Write Command causes the MT to perform whatever actions that are necessary to establish communication between the TE and the network using one or more packet domain PDP types. This may include performing a PS attach and one or more PDP context activations. Any command following the **AT+CGDATA** in the AT command line will not be processed by the MT.

If the **<L2P>** value is unacceptable to the MT, the MT shall return an **ERROR** or **+CME ERROR** response. Otherwise, the MT issues the intermediate result code **CONNECT** and enters V.250 online data state. After data transfer is completed, and the layer 2 protocol termination procedure has been completed successfully, the command state is reentered and the MT returns the final result code **OK**.

AT+CGDATA Enter Data State	
Test Command AT+CGDATA=?	Response +CGDATA: (list of supported <L2P>s) OK
Write Command AT+CGDATA=<L2P>[,<cid>[,<cid>[,...]]]	Response CONNECT Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	Whether the command takes effect is determined by network. The configurations will not be saved.
Reference 3GPP TS 27.007	

Parameter

<L2P>	String type. Indicates the layer 2 protocol to be used between the TE and MT: PPP Point to Point protocol for a PDP such as IP. Other values are not supported and will result in an ERROR response to the Execution Command
<cid>	Integer type. Specifies a particular PDP context definition (see AT+CGDCONT).
<err>	Error codes. For more details, please refer to Chapter 14.5 .

10.7. AT+CGPADDR Show PDP Address

This Write Command returns a list of PDP addresses for the specified context identifiers. If no **<cid>** is specified, the addresses for all defined contexts are returned.

AT+CGPADDR Show PDP Address	
Test Command AT+CGPADDR=?	Response +CGPADDR: (list of defined <cid>s) OK
Write Command AT+CGPADDR[=<cid>[,<cid>[,...]]]	Response +CGPADDR: <cid>,<PDP_addr>

	[+CGPADDR: <cid>,<PDP_addr> ...] OK Or ERROR
Maximum Response Time	300 ms
Characteristics	Whether the command takes effect is determined by network. The configurations will not be saved.
Reference	3GPP TS 27.007

Parameter

<cid>	Integer type. Specifies a particular PDP context definition (see AT+CGDCONT).
<PDP_addr>	String type. Identifies the MT in the address space applicable to the PDP. The address may be static or dynamic. For a static address, it will be the one set by AT+CGDCONT when the context was defined. For a dynamic address it will be the one assigned during the last PDP context activation that used the context definition referred to by <cid>. <PDP_address> is omitted if none is available.

Example

```
AT+CGDCONT=1,"IP","UNINET"      //Define PDP context
OK
AT+CGACT=1,1                      //Activated PDP
OK
AT+CGPADDR=1                      //Show PDP address
+CGPADDR: 1,"10.76.51.180"
OK
```

10.8. AT+CGCLASS GPRS Mobile Station Class

This command sets the MT to operate according to the specified mode of operation. See 3GPP TS 23.060.

AT+CGCLASS GPRS Mobile Station Class

Test Command	Response
AT+CGCLASS=?	+CGCLASS: (list of supported <class>s)

	OK
Read Command AT+CGCLASS?	Response +CGCLASS: <class>
	OK
Write Command AT+CGCLASS=<class>	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<class>	String type. Indicates the GPRS mobile class (Functionality in descending order) "B" Class-B mode of operation (A/Gb mode), or CS/PS mode of operation (lu mode) "CG" Class-C mode of operation in PS only mode (A/Gb mode), or PS mode of operation (lu mode)
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTE

<class> B means that the MT would operate PS and CS services but not simultaneously;
<class> CG means that the MT would only operate PS services;
Other values are reserved and will result in an ERROR response to the set command.

10.9. AT+CGREG Network Registration Status

This command queries the network registration status and controls the presentation of an unsolicited result code **+CGREG: <stat>** when **<n>=1** and there is a change in the MT's GPRS network registration status in GERAN/UTRAN, or unsolicited result code **+CGREG: <stat>[,<lac>],[<ci>],[<Act>]]** when **<n>=2** and there is a change of the network cell in GERAN/UTRAN.

AT+CGREG Network Registration Status	
Test Command AT+CGREG=?	Response +CGREG: (list of supported <n>s) OK
Read Command AT+CGREG?	Response +CGREG: <n>,<stat>[,<lac>,<ci>[,<AcT>]] OK
Write Command AT+CGREG[=<n>]	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type. Control the presentation of the specified URC. <ul style="list-style-type: none"> 0 Disable network registration unsolicited result code 1 Enable network registration unsolicited result code +CGREG: <stat> 2 Enable network registration and location information unsolicited result code +CGREG: <stat>[,<lac>,<ci>[,<AcT>]]
<stat>	Integer type. Network registration status. <ul style="list-style-type: none"> 0 Not registered. MT is not currently searching an operator to register to. The UE is in GMM state GMM-NUL or GMM-DEREGISTERED-INITIATED. The GPRS service is disabled, but the UE is allowed to attach for GPRS if requested by the user. 1 Registered, home network. The UE is in GMM state GMM-REGISTERED or GMM-ROUTING-AREA-UPDATING-INITIATED INITIATED on the home PLMN. 2 Not registered, but MT is currently trying to attach or searching an operator to register to. UE is in GMM state GMM-DEREGISTERED or GMM-REGISTERED-INITIATED. The GPRS service is enabled, but an allowable PLMN is currently not available. The UE will start a GPRS attach as soon as an allowable PLMN is available. 3 Registration denied. The UE is in GMM state GMM-NUL. The GPRS service is disabled, and the UE is not allowed to attach for GPRS if requested by the user. 4 Unknown 5 Registered, roaming
<lac>	String type. Two-byte location area code in hexadecimal format (e.g. "00C3" equals 195 in

	decimal)
<ci>	String type. 16 bit (GSM) or 28 bit (LTE) cell ID in hexadecimal format
<AcT>	Integer type. Access technology selected.
0	GSM
2	UTRAN
3	GSM W/EGPRS
4	UTRAN W/HSDPA
5	UTRAN W/HSUPA
6	UTRAN W/HSDPA and HSUPA
7	E-UTRAN

Example

```
AT+CGREG=2
OK
AT+CGATT=0
OK

+CGREG: 2
AT+CGATT=1
OK

+CGREG: 1,"D504","80428B5",7
```

10.10. AT+CGEREP Packet Domain Event Reporting

This Write Command enables or disables sending of unsolicited result codes **+CGEV: XXX** from MT to TE in the case of certain events occurring in the Packet Domain MT or the network. **<mode>** controls the processing of unsolicited result codes specified within this command. **<bfr>** controls the effect on buffered codes when **<mode>=1**.

AT+CGEREP Packet Domain Event Reporting	
Test Command AT+CGEREP=?	Response +CGEREP: (list of supported <mode> s),(list of supported <bfr> s) OK
Read Command AT+CGEREP?	Response +CGEREP: <mode> , <bfr> OK

Write Command AT+CGEREP=mode[,<bfr>]	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT&W .
Reference 3GPP TS 27.007	

Parameter

<mode>	Integer type. Controls the processing of unsolicited result codes specified within this command.
<u>0</u>	Buffer unsolicited result codes in the MT; if MT result code buffer is full, the oldest ones can be discarded. No codes are forwarded to the TE.
1	Discard unsolicited result codes when MT-TE link is reserved (e.g. in on-line data mode), otherwise forward them directly to the TE.
<bfr>	Integer type. Controls the effect on buffered codes
<u>0</u>	MT buffer of unsolicited result codes defined within this command is cleared when <mode>=1 is specified.
1	MT buffer of unsolicited result codes defined within this command is flushed to the TE when <mode>=1 is specified (OK response shall be given before flushing the codes).

NOTES

The unsolicited result codes and the corresponding events are defined as follows:

1. **+CGEV: REJECT <PDP_type>, <PDP_addr>**: A network request for PDP context activation occurred when the MT was unable to report it to the TE with a **+CRING** unsolicited result code and was automatically rejected.
Note: This event is not applicable for EPS.
2. **+CGEV: NW REACT <PDP_type>, <PDP_addr>,[<cid>]**: The network has requested a context reactivation. The **<cid>** used to reactivate the context is provided if known to the MT.
Note: This event is not applicable for EPS.
3. **+CGEV: NW DEACT <PDP_type>, <PDP_addr>,[<cid>]**: The network has forced a context deactivation. The **<cid>** used to activate the context is provided if known to the MT.
4. **+CGEV: ME DEACT <PDP_type>, <PDP_addr>,[<cid>]**: The mobile equipment has forced a context deactivation. The **<cid>** used to activate the context is provided if known to the MT.
5. **+CGEV: NW DETACH**: The network has forced a Packet Domain detach. This implies that all active contexts have been deactivated. These are not reported separately.
6. **+CGEV: ME DETACH**: The mobile equipment has forced a Packet Domain detach. This implies that

all active contexts have been deactivated. These are not reported separately.

7. **+CGEV: NW CLASS <class>**: The network has forced a change of MS class. The highest available class is reported (see **AT+CGCLASS**).
8. **+CGEV: ME CLASS <class>**: The mobile equipment has forced a change of MS class. The highest available class is reported (see **AT+CGCLASS**).
9. **+CGEV: PDN ACT <cid>**: Activated a context. The context represents a PDN connection in LTE or a Primary PDP context in GSM.
10. **+CGEV: PDN DEACT <cid>**: Deactivated a context. The context represents a PDN connection in LTE or a Primary PDP context in GSM.

Example

AT+CGEREP=?

+CGEREP: (0-1),(0,1)

OK

AT+CGEREP?

+CGEREP: 0,0

OK

10.11. AT+CGSMS Select Service for MO SMS Messages

This command specifies the service or service preference that the MT will use to send MO (mobile originated) SMS messages.

AT+CGSMS Select Service for MO SMS Messages	
Test Command AT+CGSMS=?	Response +CGSMS: (range of supported <service>s) OK
Read Command AT+CGSMS?	Response +CGSMS: <service> OK
Write Command AT+CGSMS=[<service>]	Response OK If there is any error related to ME functionality: +CME ERROR: <err>

Maximum Response Time	300 ms
Characteristics	
Reference	
3GPP TS 27.007	

Parameter

<service>	Integer type. indicates the service or service preference to be used
0	GPRS
1	Circuit switch
2	GPRS preferred (use circuit switched if GPRS not available)
3	Circuit switch preferred (use GPRS if circuit switched not available)
<err>	Error codes. For more details, please refer to Chapter 14.5 .

10.12. AT+CEREG EPS Network Registration Status

This command queries the network registration status and controls the presentation of an unsolicited result code **+CEREG: <stat>** when **<n>=1** and there is a change in the MT's EPS network registration status in E-UTRAN, or unsolicited result code **+CEREG: <stat>[,<tac>],[<ci>],[<AcT>]]** when **<n>=2** and there is a change of the network cell in E-UTRAN.

AT+CEREG EPS Network Registration Status	
Test Command AT+CEREG=?	Response +CEREG: (list of supported <n>s) OK
Read Command AT+CEREG?	Response +CEREG: <n>,<stat>[,<tac>,<ci>[,<AcT>]] OK
Write Command AT+CEREG[=<n>]	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations can be saved with AT+W .
Reference	
3GPP TS 27.007	

Parameter

<n>	Integer type. Controls the presentation of an unsolicited result code +CEREG: <stat> . <ul style="list-style-type: none"> 0 Disable network registration unsolicited result code 1 Enable network registration unsolicited result code +CEREG: <stat> 2 Enable network registration and location information unsolicited result code +CEREG: <stat>[,<tac>,<ci>[,<AcT>]]
<stat>	Integer type. <ul style="list-style-type: none"> 0 Not registered. MT is not currently searching an operator to register to 1 Registered, home network 2 Not registered, but MT is currently trying to attach or searching an operator to register to 3 Registration denied 4 Unknown 5 Registered, roaming
<tac>	String type. Two-byte tracking area code in hexadecimal format
<ci>	String type. 28-bit E-UTRAN cell ID in hexadecimal format
<AcT>	Integer type. Access technology selected <ul style="list-style-type: none"> 0 GSM 2 UTRAN 3 GSM W/EGPRS 4 UTRAN W/HSDPA 5 UTRAN W/HSUPA 6 UTRAN W/HSDPA and HSUPA 7 E-UTRAN

10.13. AT+QGDCNT Packet Data Counter

This command allows the application to check how much bytes are sent to or received by the module.

AT+QGDCNT Packet Data Counter	
Test Command AT+QGDCNT=?	Response +QGDCNT: (list of supported <op>s) OK
Read Command AT+QGDCNT?	Response +QGDCNT: <bytes_sent>,<bytes_rcv> OK
Write Command AT+QGDCNT=<op>	Response OK Or

	ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	Whether the command takes effect is determined by network. The configuration will not be saved.

Parameter

<op>	Integer type. The operation about data counter. 0 Reset the data counter 1 Save the results of data counter to NV If results need to be automatically saved, please refer to AT+QAUGDCNT .
<bytes_sent>	Integer type. The amount of sent bytes.
<bytes_recv>	Integer type. The amount of received bytes.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTE

When the MT is powered on, **<bytes_sent>** and **<bytes_recv>** are loaded from results of data counter in NV. The default result in NV is 0.

Example

```

AT+QGDCNT=?           //Test command
+QGDCNT: (0,1)

OK
AT+QGDCNT?           //Query the current bytes sent and received
+QGDCNT: 3832,4618

OK
AT+QGDCNT=1          //Save the results to NV
OK
AT+QGDCNT=0          //Reset the data counter
OK
  
```

10.14. AT+QAUGDCNT Auto Save Packet Data Counter

This command allows **AT+QGDCNT** to save results to NV automatically.

AT+QAUGDCNT Auto Save Packet Data Counter	
Test Command AT+QAUGDCNT=?	Response +QAUGDCNT: (list of supported <value>s) OK
Read Command AT+QAUGDCNT?	Response +QAUGDCNT: <value> OK
Write Command AT+QAUGDCNT=<value>	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	Whether the command takes effect is determined by network. The configuration will not be saved.

Parameter

<value>	Integer type. This parameter is the time-interval for AT+QGDCNT to save results to NV automatically. Range: 0, 30–65535; default: 0; unit: second. If it is set to 0, auto-save feature is disabled.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```

AT+QAUGDCNT=?           //Test command
+QAUGDCNT: (0,30-65535)

OK
AT+QGDCNT=35            //Set <value> to 35
OK
AT+QAUGDCNT?            //Query the interval of auto-save
+QAUGDCNT: 35

```

OK

10.15. AT+CGCONTRDP PDP Context Read Dynamic Parameters

AT+CGCONTRDP PDP Context Read Dynamic Parameters	
Test Command AT+CGCONTRDP=?	Response +CGCONTRDP: (list of supported <cid>s) OK
Write Command AT+CGCONTRDP[=<cid>]	Response +CGCONTRDP: <cid>,<bearer_id>,<APN>[,<local_addr and subnet_mask>[,<gw_addr>[,<DNS_prim_addr>[,<DNS_sec_addr>[,<P-CSCF_prim_addr>[,<P-CSCF_sec_addr>[,<IM_CN_Signalling_Flag>[,<LIPA_indication>[,<IPv4_MTU>[,<WLAN_Ofload>[,<Local_Addr_Ind>[,<Non-IP_MTU>[,<Serving_PLMN_rate_control_value>]]]]]]]]]] [+CGCONTRDP: <cid>,<bearer_id>,<APN>[,<local_addr and subnet_mask>[,<gw_addr>[,<DNS_prim_addr>[,<DNS_sec_addr>[,<P-CSCF_prim_addr>[,<P-CSCF_sec_addr>[,<IM_CN_Signalling_Flag>[,<LIPA_indication>[,<IPv4_MTU>[,<WLAN_Ofload>[,<Local_Addr_Ind>[,<Non-IP_MTU>[,<Serving_PLMN_rate_control_value>]]]]]]]]]] [...] OK Or ERROR
Maximum Response Time	300 ms
Characteristics	/

Parameter

<cid>	Integer type. Specifies a particular non secondary PDP context definition. The parameter is local to the TE-MT interface and is used in other PDP context-related command.
<bearer_id>	Integer type. Identifies the bearer, i.e. the EPS bearer in EPS and the NSAPI in GPRS.

	<p>1 A RmNet call is ready and MCU can get IP addresses by DHCP or QMI</p> <p>2 A RmNet call is connected</p>
<APN>	String type. A logical name that was used to select the GGSN or the external packet data network.
<local_addr and subnet_mask>	String type. Shows the IP address and subnet mask of the MT. The string is given as dot-separated numeric (0–255) parameters on the form: "a1.a2.a3.a4.m1.m2.m3.m4" for IPv4 or "a1.a2.a3.a4.a5.a6.a7.a8.a9.a10.a11.a12.a13.a14.a15.a16.m1.m2.m3.m4.m5.m6.m7.m8.m9.m10.m11.m12.m13.m14.m15.m16" for IPv6.
<gw_addr>	String type. Shows the Gateway Address of the MT. The string is given as dot-separated numeric (0–255) parameters.
<DNS_prim_addr>	String type. Shows the IP address of the primary DNS server.
<DNS_sec_addr>	String type. Shows the IP address of the secondary DNS server.
<P_CSCF_prim_addr>	String type. Shows the IP address of the primary P-CSCF server.
<P_CSCF_sec_addr>	String type. Shows the IP address of the secondary P-CSCF server.
<IM_CN_Signalling_Flag>	Integer type. Shows whether the PDP context is for IM CN subsystem-related signalling only or not. 0 PDP context is not for IM CN subsystem-related signalling only 1 PDP context is for IM CN subsystem-related signalling only
<LIPA_indication>	Integer type. Indicates that the PDP context provides connectivity using a LIPA PDN connection. This parameter cannot be set by the TE. 0 Indication not received that the PDP context provides connectivity using a LIPA PDN connection 1 Indication received that the PDP context provides connectivity using a LIPA PDN connection
<IPv4_MTU>	Integer type. Shows the IPv4 MTU size in octets.
<WLAN_Offload>	Integer type. Indicates whether traffic can be offloaded using the specified PDN connection via a WLAN or not. This refers to bits 1 and 2 of the WLAN offload acceptability IE as specified in <i>3GPP TS 24.008 [8] subclause 10.5.6.20</i> . 0 Offloading the traffic of the PDN connection via a WLAN when in S1 mode or when in lu mode is not acceptable. 1 Offloading the traffic of the PDN connection via a WLAN when in S1 mode is acceptable, but not acceptable in lu mode. 2 Offloading the traffic of the PDN connection via a WLAN when in lu mode is acceptable, but not acceptable in S1 mode. 3 Offloading the traffic of the PDN connection via a WLAN when in S1 mode or when in lu mode is acceptable.
<Local_Addr_Ind>	Integer type. Indicates whether or not the MS and the network support local IP address in TFTs (see <i>3GPP TS 24.301 [83]</i> and <i>3GPP TS 24.008 [8] subclause 10.5.6.3</i>) 0 Indicates that the MS or the network or both do not support local IP address in TFTs

	1	Indicates that the MS and the network support local IP address in TFTs
<Non-IP_MTU>		Integer type. Shows the Non-IP MTU size in octets.
<Serving_PLMN_rate_control_value>		Integer type. Indicates the maximum number of uplink messages the UE is allowed to send in a 6 minute interval. This refers to octet 3 to 4 of the Serving PLMN rate control IE as specified in <i>3GPP TS 24.301 [8] subclause 9.9.4.28</i> .

11 Supplementary Service Commands

11.1. AT+CCFC Call Forwarding Number and Conditions Control

This command allows control of the call forwarding supplementary service according to 3GPP TS 22.082. Registration, erasure, activation, deactivation and status query are supported. TA controls the call forwarding supplementary service. Registration, erasure, activation, deactivation, and status query are supported. Only **<reads>** and **<mode>** should be entered with **<mode>=0/1/2/4**.

AT+CCFC Call Forwarding Number and Conditions Control	
Test Command AT+CCFC=?	Response +CCFC: (range of supported <reads>s) OK
Write Command AT+CCFC=<reads>,<mode>[,<number>[,<type>[,<class>[,<subaddr>[,<satype>[,<time>]]]]]]]	Response If <mode> is not equal to 2 and the command is executed successfully: OK If <mode>=2 and the command is executed successfully (only in connection with <reads> 0–3): For registered call forwarding numbers: +CCFC: <status>,<class1>[,<number>,<type>[,<subaddr>,<satype>[,<time>]]]]] [+CCFC: <status>,<class1>[,<number>,<type>[,<subaddr>,<satype>[,<time>]]]]] OK If no call forwarding numbers are registered (and therefore all classes are inactive): +CCFC: <status>,<class> OK where <status>=0 and <class>=15

	If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference	
3GPP TS 27.007	

Parameter

<reads>	Integer type. Configure the forwarding conditions. 0 Unconditional 1 Mobile busy 2 No reply 3 Not reachable 4 All call forwarding (0–3) 5 All conditional call forwarding (1–3)
<mode>	Integer type. Controls the call forwarding supplementary service. 0 Disable 1 Enable 2 Query status 3 Registration 4 Erasure
<number>	Phone number in string type of forwarding address in format specified by <type> .
<type>	Integer type. Type of address. Default value: 145 when dialing string includes international access code character "+"; otherwise 129
<subaddr>	String type sub-address of format specified by <satype>
<satype>	Type of sub-address in integer
<class>	Integer type. Information class. 1 Voice 2 Data 4 FAX 7 All telephony except SMS 8 Short message service
<time>	Integer type. When "no reply" (<reads> =no reply) is enabled or queried, this gives the time in seconds to wait before call is forwarded. Range: 1–30, default: 20.
<status>	Integer type. 0 Not active 1 Active
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

AT+CCFC=0,3,"15021012496"	//Register the destination number for unconditional call forwarding (CFU)
OK	
AT+CCFC=0,2	//Query the status of CFU without specifying <class>
+CCFC: 1,1,"+8615021012496",145,,,	
OK	
AT+CCFC=0,4	//Erase the registered CFU destination number
OK	
AT+CCFC=0,2	//Query the status, no destination number
+CCFC: 0,255	
OK	

11.2. AT+CCWA Call Waiting Control

This command allows control of the call waiting supplementary service according to 3GPP TS 22.083. Activation, deactivation and status query are supported. TA controls the call waiting supplementary service with the Write Command. Activation, deactivation and status query are supported.

AT+CCWA Call Waiting Control	
Test Command AT+CCWA=?	Response +CCWA: (list of supported <n>s) OK
Read Command AT+CCWA?	Response +CCWA: <n> OK
Write Command AT+CCWA[=<n>][,<mode>][,<class>]	Response If <mode> is not equal to 2 and the command is executed successfully: OK If <mode>=2 and the command is executed successfully: +CCWA: <status>,<class1> [+CCWA:<status>,<class2> ...] OK

	If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference	3GPP TS 27.007

Parameter

<n>	Integer type. Disable or enable the presentation of an unsolicited result code. 0 Disable presentation of an unsolicited result code 1 Enable presentation of an unsolicited result code
<mode>	Integer type. When <mode> parameter is not given, network is not interrogated 0 Disable 1 Enable 2 Query status
<class>	A sum of integers, each integer represents a class of information. 1 Voice (telephony) 2 Data (bearer service) 4 FAX (facsimile)
<status>	Integer type. Disable or enable the call waiting supplementary service. 0 Disable 1 Enable
<number>	Phone number in string type of calling address in format specified by <type>
<type>	Type of address octet in integer format 129 Unknown type (ISDN format number) 145 International number type (ISDN format)
<alpha>	Optional string type alphanumeric representation of <number> corresponding to the entry found in phonebook
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTES

- <status>**=0 should be returned only if service is not active for any **<class>** i.e. **+CCWA: 0,7** will be returned in this case.
- When **<mode>**=2, all active call waiting classes will be reported. In this mode the command is aborted by pressing any key.
- Unsolicited result code:
When the presentation call waiting at the TA is enabled (and call waiting is enabled) and a terminating call set up during an established call, an unsolicited result code is returned:

+CCWA: <number>,<type>,<class>[,<alpha>]

Example

AT+CCWA=1,1	//Enable presentation of an unsolicited result code
OK	
ATD10086;	//Establish a call
OK	
+CCWA: "02154450293",129,1	//Indication of a call that has been waiting

11.3. AT+CHLD Call Related Supplementary Services

This command allows the control of the following call related services:

- A call can be temporarily disconnected from the MT but the connection is retained by the network;
- Multiparty conversation (conference calls);
- The served subscriber who has two calls (one held and the other either active or alerting) can connect the other parties and release the served subscriber's own connection.

Calls can be put on hold, recovered, released and added to a conversation, and transferred similarly as defined in *3GPP TS 22.030*.

This is based on the GSM/UMTS supplementary services HOLD (Call Hold; refer to *3GPP TS 22.083 clause 2*), MPTY (MultiParty; refer to *3GPP TS 22.084*) and ECT (Explicit Call Transfer; refer to *3GPP TS 22.091*). The interaction of this command with other commands based on other GSM/UMTS supplementary services is described in the GSM/UMTS standards. Call Hold, MultiParty and Explicit Call Transfer are only applicable to teleservice 11.

TA controls the supplementary services call hold, multiparty and explicit call transfer with the Write Command. Calls can be put on hold, recovered, released, added to conversation and transferred.

AT+CHLD Call Related Supplementary Services

Test Command AT+CHLD=?	Response +CHLD: (list of supported <n>s) OK
Write Command AT+CHLD[=<n>]	Response OK

	If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will not be saved.
Reference	
3GPP TS 27.007	

Parameter

<n>	0	Terminate all held calls or UDUB (User Determined User Busy) for a waiting call. If a call is waiting, terminate the waiting call. Otherwise, terminate all held calls (if any)
	1	Terminate all active calls (if any) and accept the other call (waiting call or held call).
	1X	Terminate the specific call number X (X=1-7)
	<u>2</u>	Place all active calls on hold (if any) and accept the other call (waiting call or held call) as the active call
	2X	Place all active calls except call X (X=1-7) on hold
	3	Add the held call to the active calls
<err>	Error codes. For more details, please refer to Chapter 14.5 .	

Example

ATD10086;	//Establish a call
OK	
+CCWA: "02154450293",129,1	//Indication of a call that has been waiting
AT+CHLD=2	//Place the active call on hold and accept the waiting call as the active call
OK	
AT+CLCC	
+CLCC: 1,0,1,0,0,"10086",129	//The first call is on hold
+CLCC: 2,1,0,0,0,"02154450293",129	//The second call is active
OK	
AT+CHLD=21	//Place the active call except call X=1 on hold
OK	
AT+CLCC	
+CLCC: 1,0,0,0,0,"10086",129	//The first call is active

```
+CLCC: 2,1,1,0,1,"02154450293",129 //The second call is on hold

OK
AT+CHLD=3 //Add a held call to the active calls in order to set up a
           conference (multiparty) call

OK
AT+CLCC
+CLCC: 1,0,0,0,1,"10086",129

+CLCC: 2,1,0,0,1,"02154450293",129

OK
```

11.4. AT+CLIP Calling Line Identification Presentation

This command refers to the GSM/UMTS supplementary service CLIP (Calling Line Identification Presentation) that enables a called subscriber to get the calling line identity (CLI) of the calling party when receiving a mobile terminated call. TA enables or disables the presentation of the calling line identity (CLI) at the TE with the Write Command. It has no effect on the execution of the supplementary service CLIP in the network.

AT+CLIP Calling Line Identification Presentation	
Test Command AT+CLIP=?	Response +CLIP: (list of supported <n>s) OK
Read Command AT+CLIP?	Response +CLIP: <n>,<m> OK
Write Command AT+CLIP=<n>	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	15 s, determined by network.
Characteristics	/
Reference	3GPP TS 27.007

Parameter

<n>	Integer type. 0 Suppress unsolicited result codes 1 Display unsolicited result codes
<m>	Integer type. 0 CLIP not provisioned 1 CLIP provisioned 2 Unknown
<number>	Phone number in string type of calling address in format specified by <type>
<subaddr>	String type sub-address of format specified by <satype>
<satype>	Type of sub-address octet in integer format (refer to 3GPP TS 24.008 [8] subclause 10.5.4.8)
<type>	Type of address octet in integer format 129 Unknown type (ISDN format) 145 International number type (ISDN format) 161 National number
<alpha>	String type alphanumeric representation of <number> corresponding to the entry found in phonebook
<CLI_validity>	Integer type. 0 CLI valid 1 CLI has been withheld by the originator 2 CLI is not available due to interworking problems or limitations of originating network
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTE

Unsolicited result code:

When the presentation of the CLIP at the TE is enabled (and calling subscriber allows), an unsolicited result code is returned after every RING (or +CRING: **<type>**) at a mobile terminating call:

+CLIP: **<number>**,**<type>**,**[subaddr]**,**[satype]**,**[<alpha>]**,**<CLI_validity>**

Example

```
AT+CPBW=1,"02151082965",129,"QUECTEL"
```

```
OK
```

```
AT+CLIP=1
```

```
OK
```

```
RING
```

```
+CLIP: "02151082965",129,,,"QUECTEL",0
```

11.5. AT+CLIR Calling Line Identification Restriction

This command refers to the CLIR supplementary service (Calling Line Identification Restriction) according to 3GPP TS 22.081 and the OIR supplementary service (Originating Identification Restriction) according to 3GPP TS 24.607 that allows a calling subscriber to enable or disable the presentation of the calling line identity (CLI) to the called party when originating a call. TA restricts or enables the presentation of the calling line identity (CLI) to the called party when originating a call with the write command.

The Write Command overrides the CLIR subscription (default is restricted or allowed) when temporary mode is provisioned as a default adjustment for all following outgoing calls. This adjustment can be revoked by using the opposite command.

AT+CLIR Calling Line Identification Restriction	
Test Command AT+CLIR=?	Response +CLIR: (range of supported <n>s) OK
Read Command AT+CLIR?	Response +CLIR: <n>,<m> OK
Write Command AT+CLIR[=<n>]	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	15 s, determined by network.
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type. Parameter sets the adjustment for outgoing calls. 0 Presentation indicator is used according to the subscription of the CLIR service 1 CLIR invocation 2 CLIR suppression
<m>	Integer type. Parameter shows the subscriber CLIR service status in the network. 0 CLIR not provisioned 1 CLIR provisioned in permanent mode 2 Unknown (e.g. no network, etc.)

	3	CLIR temporary mode presentation restricted
	4	CLIR temporary mode presentation allowed
<err>	Error codes. For more details, please refer to Chapter 14.5 .	

11.6. AT+COLP Connected Line Identification Presentation

This command refers to the GSM/UMTS supplementary service COLP (Connected Line Identification Presentation) that enables a calling subscriber to get the connected line identity (COL) of the called party after setting up a mobile originated call. The command enables or disables the presentation of the COL at the TE. It has no effect on the execution of the supplementary service COLR in the network.

Intermediate result code **OK** is returned from TA to TE before any +CR or V.25ter responses.

AT+COLP Connected Line Identification Presentation	
Test Command AT+COLP=?	Response +COLP: (list of supported <n>s) OK
Read Command AT+COLP?	Response +COLP: <n>,<m> OK
Write Command AT+COLP[=<n>]	Response OK
Maximum Response Time	15 s, determined by network.
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type. Sets/shows the result code presentation status in the TA. 0 Disable 1 Enable
<m>	Integer type. Shows the subscriber COLP service status in the network. 0 COLP not provisioned 1 COLP provisioned 2 Unknown (e.g. no network, etc.)
<number>	String type. Phone number, the format is specified by <type>

<type>	Integer type. Type of address octet in integer format 129 Unknown type (ISDN format number) 145 International number type (ISDN format)
<subaddr>	String type sub-address of format specified by <satype>
<satype>	Integer type. Type of sub-address octet (refer to 3GPP TS 24.008 subclause 10.5.4.8)
<alpha>	Optional string type alphanumeric representation of <number> corresponding to the entry found in phonebook.

NOTE

Intermediate result code:

When enabled (and called subscriber allows), an intermediate result code is returned before any +CR or V.25ter responses:

+COLP: <number>,<type>,<subaddr>,<satype>,<alpha>

Example

AT+CPBW=1,"02151082965",129,"QUECTEL"

OK

AT+COLP=1

OK

ATD02151082965;

+COLP: "02151082965",129,,,"QUECTEL"

OK

11.7. AT+CSSN Supplementary Service Notifications

This command refers to supplementary service related network initiated notifications. This Write Command enables/disables the presentation of notification result codes from TA to TE.

AT+CSSN Supplementary Service Notifications

Test Command AT+CSSN=?	Response +CSSN: (list of supported <n>s),(list of supported <m>s) OK
Read Command AT+CSSN?	Response +CSSN: <n>,<m> OK
Write Command	Response

AT+CSSN=<n>[,<m>]	OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type. Sets/shows the +CSSI intermediate result code presentation status to the TE 0 Disable 1 Enable
<m>	Integer type. Sets/shows the +CSSU unsolicited result code presentation status to the TE 0 Disable 1 Enable
<code1>	Integer type. It is manufacturer specific and supports the following codes: 0 Unconditional call forwarding is active 1 Some of the conditional call forwardings are active 2 Call has been forwarded 3 Waiting call is pending 5 Outgoing call is barred
<code2>	Integer type. It is manufacturer specific and supports the following codes: 0 The incoming call is a forwarded call 2 Call has been put on hold (during a voice call) 3 Call has been retrieved (during a voice call) 5 Held call was terminated by another party 10 Additional incoming call forwarded
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTES

- When **<n>=1** and a supplementary service notification is received after a mobile originated call setup, the **+CSSI** intermediate result code is sent to TE before any other MO call setup result codes:
+CSSI: <code1>
- When **<m>=1** and a supplementary service notification is received during a mobile terminated call setup or during a call, the **+CSSU** unsolicited result code is sent to TE:

+CSSU: <code2>

11.8. AT+CUSD Unstructured Supplementary Service Data

This command allows control of the Unstructured Supplementary Service Data (USSD) according to 3GPP TS 22.090. Both network and mobile initiated operations are supported.

<mode> is used to disable/enable the presentation of an unsolicited result code. <mode>=2 is used to cancel an ongoing USSD session. For an USSD response from the network, or a network initiated operation, the format is: **+CUSD: <status>[,<rspstr>[,<dc>]]**.

When <reqstr> is given, a mobile initiated USSD string or a response USSD string to a network initiated operation is sent to the network. The response USSD string from the network is returned in a subsequent **+CUSD** URC.

AT+CUSD Unstructured Supplementary Service Data	
Test Command AT+CUSD=?	Response +CUSD: (range of supported <mode>s) OK
Read Command AT+CUSD?	Response +CUSD: <mode> OK
Write Command AT+CUSD[=<mode>[,<reqstr>[,<dc>]]]	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	120 s, determined by network.
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference 3GPP TS 27.007	

Parameter

<mode>	Integer type. Sets/shows the result code presentation status to the TE. <u>0</u> Disable the result code presentation to the TE 1 Enable the result code presentation to the TE 2 Cancel session (not applicable to Read Command response)
<reqstr>	Unstructured Supplementary Service Data (USSD) to be sent to the network. If this parameter is not given, network is not interrogated.
<rspstr>	Unstructured Supplementary Service Data (USSD) received from the network.
<dcsc>	Integer type. 3GPP TS 23.038 Cell Broadcast Data Coding Scheme, Default value: 15.
<status>	Integer type. USSD response from the network or the network initiated operation. 0 No further user action required (network initiated USSD Notify, or no further information needed after mobile initiated operation) 1 Further user action required (network initiated USSD Request, or further information needed after mobile initiated operation) 2 USSD terminated by network 3 Another local client has responded 4 Operation not supported 5 Network time out
<err>	Error codes. For more details, please refer to Chapter 14.5 .

12 Audio Commands

12.1. AT+CLVL Loudspeaker Volume Level Selection

This command selects the volume of the internal loudspeaker of the MT.

AT+CLVL Loudspeaker Volume Level Selection

Test Command AT+CLVL=?	Response +CLVL: (range of supported <level>s) OK
Read Command AT+CLVL?	Response +CLVL: <level> OK
Write Command AT+CLVL=<level>	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will be saved.
Reference 3GPP TS 27.007	

Parameter

<level>	Integer type. Volume level with manufacturer specific range (Smallest value represents the lowest sound level). Range: 0–5; Default: 3.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

12.2. AT+QAUDLOOP Enable/Disable Audio Loop Test

This command enables/disables audio loop test.

AT+QAUDLOOP Enable/Disable Audio Loop Test

Test Command	Response +QAUDLOOP: (list of supported <enable>s) OK
Read Command AT+QAUDLOOP?	Response +QAUDLOOP: <enable> OK
Write Command AT+QAUDLOOP=<enable>	Response OK Or ERROR
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will not be saved.

Parameter

<enable>	Integer type. To enable or disable audio loop test 0 Disable audio loop test 1 Enable audio loop test
<err>	Error codes. For more details, please refer to Chapter 14.5 .

12.3. AT+VTS DTMF and Tone Generation

This command sends ASCII characters which cause MSC to transmit DTMF tones to a remote subscriber. This command can only be operated in voice call.

AT+VTS DTMF and Tone Generation

Test Command AT+VTS=?	Response +VTS: (list of supported <DTMF_string>s),(range of supported of <duration>s) OK
---------------------------------	--

Write Command AT+VTS=<DTMF_string>[,<duration>]	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	Depends on the length of <DTMF_string> and <duration> .
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<DTMF_string>	String type. ASCII characters in the set 0...9, #, *, A, B, C, D . The string should be enclosed in quotation marks ("..."). When sending multiple tones at a time, the time interval of two tones <interval> can be specified by AT+VTD . The maximal length of the string is 31.
<duration>	The duration of each tone in 1/10 seconds with tolerance. Range: 0–255. If the duration is less than the minimum time specified by the network, the actual duration will be the network specified time. If this parameter is omitted, <duration> is specified by AT+VTD .
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```

ATD12345678900;           //Dial
OK
//Call connect
AT+VTS="1"                 //The remote caller can hear the DTMF tone
OK
AT+VTS="1234567890A"       //Send multiple tones at a time
OK

```

12.4. AT+VTD Set Tone Duration

This command sets the duration of DTMF tones. It can also set time interval of two tones when sending multiple tones at a time.

AT+VTD Set Tone Duration

Test Command AT+VTD=?	Response +VTD: (range of supported <duration>s),(range of supported of <interval>s) OK
Read Command AT+VTD?	Response +VTD: <duration>,<interval> OK
Write Command AT+VTD=<duration>[,<interval>]	Response OK Or ERROR If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configurations will not be saved.
Reference 3GPP TS 27.007	

Parameter

<duration>	The duration tone in 1/10 seconds with tolerance. Range: 0–255. Default value: 3. If the duration is less than the minimum time specified by the network, the actual duration will be network specified time.
<interval>	The time interval of two tones when sending multiple tones at a time by AT+VTS . Range: 0–255. Default value: 0.
<err>	Error codes. For more details, please refer to Chapter 14.5 .

12.5. AT+QAUDRD Record Media File

This command records the uplink or downlink speech during voice call or record sound from local microphone in idle state and save it to files.

AT+QAUDRD Record Media File

Test Command	Response
--------------	----------

AT+QAUDRD=?	+QAUDRD: (list of supported of <state>s),<file_name>,(list of supported <format>),(list of supported <dlink>s) OK
Read Command AT+QAUDRD?	Response +QAUDRD: <state> OK
Write Command AT+QAUDRD=<control>[,<file_name>[,<format>[,<dlink>]]]	Response OK Or ERROR If error is related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/

Parameter

<state>	Integer type. 0 Module is not in recording 1 Module is in recording
<control>	Integer type. 0 Stop recording 1 Start recording
<file_name>	String type. Name of the recorded media file.
<format>	Integer type. Format of the file. 13 WAV_PCM16
<dlink>	Integer type. Record downlink sound. 0 Record uplink sound 1 Record downlink sound
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTES

1. <file_name> is the path usded to save the recording file, the default path is /data/ufs directory.
2. The module supports recording format of "13", suffix wav audio files.
3. If the recording file's name and format are same with that of an existing file or an unknown error occurs, the module reports URC **+QAUDRIND: 0,1**.
4. If current recording is interrupted by other audio task, the module reports URC **+QAUDRIND: 0,6**.

5. If there is no space to record, the module reports URC **+QAUDRIND: 0,3**.
6. The module supports recording uplink and downlink audio data, but not simultaneous recording.
7. This command returns error if the file format is inconsistent with the file extension.
8. Downlink record is prohibited in non-calling mode and uplink record is prohibited in calling mode.

Table 6: The Description of <code> in URC +QAUDRIND: 0,<code>

<code>	Meaning
0	Reserved
1	Unknown error
3	No space to record
6	Interrupted by other audio task

Example

```

AT+QAUDRD=1,"A.wav",13,0 //Record the uplink sound with wav format, store it in UFS.
OK
AT+QAUDRD=0 //Stop recording.
OK
AT+QAUDRD=1,"B.wav",13,1 //Record the downlink sound with wav format, store it in UFS.
OK
AT+QAUDRD=0 //Stop recording.
OK

```

12.6. AT+QPSND Play Media File

This command plays local media file.

AT+QPSND Play Media File	
Test Command AT+QPSND=?	Response +QPSND: (list of supported <control>s),<file_name>,(list of supported <repeat>s),(list of supported <ulmute>s),(list of supported <dlmute>s) OK
Read Command	Response

AT+QPSND?	+QPSND: <state>
	OK
Write Command AT+QPSND=<control>,<file_name>,<repeat>[,<ulmute>[,<dlmute>]]	Response OK Or ERROR If error is related to ME functionality: +CME ERROR: <err> After the playing is finished: +QPSND: 0
Maximum Response Time	300 ms
Characteristics	/

Parameter

<state>	Integer type. 0 Module is not playing 1 Module is playing
<control>	Integer type. 0 Stop playing 1 Start playing
<file_name>	String type. Name of the file to be played.
<repeat>	Integer type. Repeat play or not 0 Play only once 1 Repeat playing
<ulmute>	Integer type. Mute uplink or not 0 Mute 1 Not mute
<dlmute>	Integer type. Mute downlink or not 0 Mute 1 Not mute
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTES

1. <file_name> includes file path, file name and file suffix. The default play path is / data/ufs directory.
2. The module only supports 8K liner, mono wave format while playing to uplink.
3. Downlink playback is prohibited in calling mode and uplink playback is prohibited in

non-calling mode

Example

```

AT+QPSND=1,"A.wav",0           //Play a wave file which is stored in UFS.
OK

+QPSND: 0
AT+QPSND=1,"A.wav",0,1,0       //Play a wave file to far-end when a call is ongoing.
OK

+QPSND: 0
                                //Stop playing.

```

NOTE

AT+QPSND does not support both <ulmute> and <dlmute> to be 0 or 1 at the same time.

12.7. AT+QAUDPLAY Play Media File

This command plays local media file.

AT+QAUDPLAY Play Media File

Test Command AT+QAUDPLAY=?	Response +QAUDPLAY: <file_name>,(list of supported <state>s) OK
Read Command AT+QAUDPLAY?	Response +QAUDPLAY: <state> OK
Write Command AT+QAUDPLAY=<file_name>,<repeat>	Response OK Or ERROR

	<p>If error is related to ME functionality: +CME ERROR: <err></p> <p>After the playing is finished: +QAUDPLAY: 0</p>
Maximum Response Time	300 ms
Characteristics	<p>The command takes effects immediately.</p> <p>The configuration will not be saved.</p>

Parameter

<state>	<p>Integer type. Module status.</p> <p>0 Module is not in playing</p> <p>1 Module is in playing</p>
<file_name>	String type. Name of the file to play, includes file path, file name and file suffix. File path must be UFS.
<repeat>	<p>Integer type. Whether to paly the file repeatedly.</p> <p>0 Play only once</p> <p>1 Repeat</p>
<err>	Error codes. For more details, please refer to Chapter 14.5 .

NOTES

1. If there is an unknown error occurred, the module reports URC **+QAUDPIND: 0,1**.
2. If current playing is interrupted by other audio tasks, the module reports URC **+QAUDPIND: 0,6**.

12.8. AT+QAUDMOD Set Audio Mode

This command sets the audio mode required for the connected device. It will take effect at next sound activity.

AT+QAUDMOD Set Audio Mode

Test Command AT+QAUDMOD=?	<p>Response</p> <p>+QAUDMOD: (range of supported <mode>s)</p> <p>OK</p>
Read command AT+QAUDMOD?	<p>Response</p> <p>+QAUDMOD: <mode></p> <p>OK</p>

Write Command AT+QAUDMOD=<mode>	Response OK Or ERROR If error is related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect at next sound activity. The configuration will be saved automatically.

Parameter

<mode>	Integer type. Indicate the current configured audio mode. <ul style="list-style-type: none"> <u>0</u> Echo canceller, noise suppressor, digital gain and calibration parameter for Handset. 1 Echo canceller, noise suppressor, digital gain and calibration parameter for Headset. 2 Echo canceller, noise suppressor, digital gain and calibration parameter for Speaker.
---------------------	---

12.9. AT+QIIC IIC Read/Write

This command reads or writes to the IIC register from peripheral devices.

AT+QIIC IIC Read/Write	
Test Command AT+QIIC=?	Response +QIIC: (list of supported <rw>s),(range of supported <device>s),(range of supported <addr>s),(list of supported <bytes>s),(range of supported <value>s) OK
Write Command AT+QIIC=<rw>,<device>,<addr>,<bytes>[,<value>]	Response If the optional parameter is specified: OK If the optional parameter is omitted: +QIIC: <value> OK
Maximum Response Time	300 ms
Characteristics	The command takes effects after rebooting. The configuration will not be saved.

Parameter

<rw>	Integer type. 0 write command. 1 read command.
<device>	Integer type in HEX. 7-bit device address. Range: 0-0xff. Only ALC5616 device address 0x1B is supported currently.
<addr>	Integer type in HEX. Register address. Range: 0-0xff.
<bytes>	Integer type. 1 Read/write one byte 2 Read/write two bytes.
<value>	Integer type in HEX. The written value. Range: 0-0xffff.

1. This parameter is hexadecimal, please add prefix "0x" for **<device>**,**<addr>**,**<value>**.
2. **<device>** is slave device address (7bit, not include read/write bit), please find it on device datasheet, and only support ALC5616 now.

Example

AT+QIIC=0,0x1B,0x00,2,0x0000 //Write the register value. Device address: 0x1B. Register address: 0x00. Write two bytes.

OK

AT+QIIC=1,0x1B,0x00,2 //Read register value, slave address: 0x1B, register address:0x00, read two bytes.

+QIIC: 0x0000

OK

12.10. AT+QAUDSW Codec Switching

This command switches the built-in or external codec.

AT+QAUDSW Codec Switching

Test Command AT+QAUDSW=?	Response +QAUDSW:(list of supported<n>s) OK
Read Command AT+QAUDSW?	Response +QAUDSW : <n>

	OK
Write Command AT+QAUDSW =<n>	Response OK Or ERROR If error is related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect after rebooting. The configuration will be saved automatically.
Reference 3GPP TS 27.007	

Parameter

<n>	Integer type.
0	external codec
1	built-in codec

12.11. AT+QAUDPASW Audio PA Type Switching

This command switches the audio PA type.

AT+QAUDPASW Audio PA Type Switching	
Test Command AT+QAUDPASW=?	Response +QAUDSW:(list of supported<n>s) OK
Read Command AT+QAUDPASW ?	Response +QAUDPASW : <n> OK
Write Command AT+QAUDPASW =<n>	Response OK Or ERROR If error is related to ME functionality:

	+CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect after rebooting. The configuration will be saved automatically.

Parameter

<n>	Integer type. PA type
<u>0</u>	PA type is AB
1	PA type is D

13 Hardware Related Commands

13.1. AT+QPOWD Power off

This command shuts down the module. UE returns **OK** immediately when the command is executed. Then UE deactivates the network. After the deactivation is completed, UE outputs **POWERED DOWN** and enters into the shutdown state. The maximum time for unregistering network is 60 seconds. To avoid data loss, UE is not allowed to turn off the power before the module's STATUS pin is set to low or **POWERED DOWN** is outputted.

AT+QPOWD Power off	
Test Command AT+QPOWD=?	Response +QPOWD: (list of supported <n>s) OK
Execution Command AT+QPOWD[=<n>]	Response OK POWERED DOWN
Maximum Response Time	300 ms
Characteristics	/

Parameter

<n>	Integer type. Power down the module.
0	Immediately power down
1	Normal power down

13.2. AT+CCLK Clock

This command sets and queries the real time clock (RTC) of the module. The current setting is retained until the module is totally disconnected from power.

AT+CCLK Clock	
Test Command AT+CCLK=?	Response OK
Read Command AT+CCLK?	Response +CCLK: <time> OK
Write Command AT+CCLK=<time>	Response OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately. The configuration will not be saved.
Reference 3GPP TS 27.007	

Parameter

<time>	String type. The format is "yy/MM/dd,hh:mm:ss±zz", indicating year (two last digits), month, day, hour, minutes, seconds and time zone (indicates the difference, expressed in quarters of an hour, between the local time and GMT; range: -48 to +56). E.g. May 6 th , 1994, 22:10:00 GMT+2 hours equals to "94/05/06,22:10:00+08".
<err>	Error codes. For more details, please refer to Chapter 14.5 .

Example

```
AT+CCLK? //Query the local time
+CCLK: "08/01/04,00:19:43+00"
OK
```

13.3. AT+CBC Battery Charge

This command returns battery charge status **<bc>** and battery charge level **<bcl>** of the MT.

AT+CBC Battery Charge	
Test Command AT+CBC=?	Response +CBC: (range of supported <bc> s),(range of supported <bcl> s), <voltage> OK
Execution Command AT+CBC	Response +CBC: <bc> , <bcl> , <voltage> OK If there is any error related to ME functionality: +CME ERROR: <err>
Maximum Response Time	300 ms
Characteristics	/
Reference 3GPP TS 27.007	

Parameter

<bc>	Integer type. Battery charge status. 0 ME is not charging 1 ME is charging 2 Charging has been finished
<bcl>	Integer type. Battery charge level. 0–100 Battery has 0–100 percent of capacity remaining vent
<voltage>	Battery voltage (Mv).
<err>	Error codes. For more details, please refer to Chapter 14.5 .

13.4. AT+QADC Read ADC Value

This command reads the voltage value of ADC channel.

AT+QADC Read ADC Value	
Test Command AT+QADC=?	Response +QADC: (range of supported <port>s) OK
Read Command AT+QADC=<port>	Response +QADC: <port>,<value> OK
Maximum Response Time	300 ms
Characteristics	/

Parameter

<port>	Integer type. Channel number of the ADC. 0 ADC Channel 0 1 ADC Channel 1 2 ADC Channel 2
<value>	The voltage of specified ADC channel. Unit: mV.

13.5. AT+QSCLK Enable/Disable Low Power Mode

This command controls whether to enable low power mode. When low power mode is enabled, and both DTR and WAKEUP_IN are pulled up, the module can directly enter into sleep mode. If low power mode is enabled, but both DTR and WAKEUP_IN are pulled down, only after the DTR and the WAKEUP_IN are pulled up, can the module enter into low power mode.

AT+QSCLK Enable/Disable Low Power Mode	
Test Command AT+QSCLK=?	Response +QSCLK: (list of supported <n>s) OK
Read Command AT+QSCLK?	Response +QSCLK: <n>

	OK
Write Command AT+QSCLK=<n>	Response OK
Maximum Response Time	300 ms
Characteristics	The command takes effect immediately The configuration will not be saved
Reference Quectel	

Parameter

<n>	Integer type. Disable or enable low power mode. <u>0</u> Disable 1 Enable. It is controlled by DTR pin and WAKEUP_IN pin. 2 Enable. If there is no data interaction in the serial port within 5 seconds, the module will enter sleep mode and wake up when there is data interaction.
------------------	--

14 Appendix

14.1. References

Table 7: Related Documents

SN	Document Name	Description
[1]	V.25ter	Serial asynchronous automatic dialing and control
[2]	3GPP TS 27.007	Digital cellular telecommunications (Phase 2+); Universal Mobile Telecommunications System (UMTS); LTE; AT command set for User Equipment (UE)
[3]	3GPP TS 27.005	Digital cellular telecommunications (Phase 2+); Universal Mobile Telecommunications System (UMTS); LTE; Use of Data Terminal Equipment – Data Circuit terminating Equipment (DTE-DCE) interface for Short Message Service (SMS) and Cell Broadcast Service (CBS)

Table 8: Terms and Abbreviations

Abbreviation	Description
3GPP	3 rd Generation Partnership Project
ACDB	Audio Calibration Database
ACK	Acknowledge Character
ACL	Access Control List
ADC	Analog-to-Digital Converter
AMR	Adaptive Multi-Rate
APN	Access Point Name
ARFCN	Absolute Radio-Frequency Channel Number

ASCII	American Standard Code for Information Interchange
BCD	Binary-Coded Decimal
CBM	Cell Broadcast Message
CCH	Control Channel
CDMA	Code Division Multiple Access
EFS	Embedded File System
CFU	Call Forwarding Unconditional
CLI	Calling Line Identity
CLIP	Calling Line Identification Presentation
CLIR	Calling Line Identification Restriction
COL	Connected Line
COLP	Connected Line Identification Presentation
COLR	Connected Line Identification Restriction
CPT	Communication Production Technology
CS	Circuit Switching
CSD	Circuit Switch Data
DCD	Dynamic Content Delivery
DCD	Data Carrier Detection
DCE	Data Circuit-terminating Equipment
DCH	Data Channel
DCS	Data Coding Scheme
DFOTA	Delta Firmware Over-The-Air
DNS	Domain Name Server
DPCH	Dedicated Physical Channel
DRX	Discontinuous Reception

DTE	Data Terminal Equipment
DTMF	Dual Tone Multi Frequency
DTR	Data Terminal Ready
ECC	Emergency Call
ECT	Explicit Call Transfer supplementary service
EGPRS	Enhanced General Packet Radio Service
EMM	EPS Mobility Management
ENC	Encode
EONS	Enhanced Operator Name String
EPS	Evolved Packet System
ESM	EPS Session Management
E-UTRAN	Evolved UMTS Terrestrial Radio Access Network
EVDO	Evolution, Data Only
FDD	Frequency Division Duplexing
FDPCH	Fraction-Dedicated Physical Channel
FPLMN	Forbidden PLMN
FTM	Factory Test Mode
FTP(S)	File Transfer Protocol over SSL
GBK	Chinese Internal Code Specification
GERAN	GSM EDGE Radio Access Network
GGSN	Gateway GPRS Support Node
GMT	Greenwich Mean Time
GNSS	Global Navigation Satellite System
GPIO	General-Purpose Input/Output
GPRS	General Packet Radio Service

GSM	Global System for Mobile Communications
HDR	High-Dynamic Range
HSDPA	High Speed Downlink Packet Access
HSUPA	High Speed Uplink Packet Access
HTTP(S)	HyperText Transfer Protocol over SSL
ICCID	Integrated Circuit Card Identifier
IDSN	Integrated Services Digital Network
IETF	The Internet Engineering Task Force
IIC	Inter-Integrated Circuit
IMEI	International Mobile Equipment Identity
IMS	IP Multimedia Subsystem
IMSI	International Mobile Subscriber Identity
Ipv4	Internet Protocol version 4
Ipv6	Internet Protocol version 6
IRA	International Reference Alphabet
IRAT	Inter-Radio Access Technology
IWF	Interactive Website Framework
LIPA	Local IP Access
LTE	Long Term Evolution
MBN	Modem Software Configuration
MCC	Mobile Country Code
MCU	Microprogrammed Control Unit
ME	Mobile Equipment
MMS	Multimedia Messaging Service
MNC	Mobile Network Code

MO	Mobile Originated
MPTY	MultiParty
MS	Mobile Station
MSC	Mobile Services Switching Center
MSISDN	Mobile Subscriber International ISDN/PSTN number
MT	Mobile Terminal
MTU	Maximum Transmission Unit
NMEA	National Marine Electronics Association
NITZ	Network Identity and Time Zone / Network Informed Time Zone. It is a mechanism for provisioning local time and date, time zone and DST offset, as well as network provider identity information, to mobile devices via a wireless network.
NSAPI	Network Service Access Point Identifier
NV	Non-Volatile Random Access Memory
OIR	Originating Identification Restriction
PCM	Pulse Code Modulation
PDN	Public Data Network
PDP	Packet Data Protocol
PDU	Protocol Data Unit
PIN	Personal Identification Number
PLMN	Public Land Mobile Network
PPP	Point to Point Protocol
PSC	Primary Synchronization Code
PUK	Personal Identification Number Unlock Key
QCI	QoS Class Identifier
QMI	Qualcom Message Interface
QoS	Quality of Servic

RAT	Radio Access Technology
RDI	Remote Defect Indication
RI	Ring Indicator
RLP	Radio Link Protocol
RPLMN	Registered PLMN
RTC	Real Time Clock
RTS/CTS	Request To Send/Clear To Send
RSCP	Received Signal Code Power
RxQual	Receive Quality
SAP	Service Access Point
SDU	Service Data Unit
SMS	Short Message Service
SMSC	Short Message Service Center
SMTP	Simple Mail Transfer Protocol
SN	Serial Number
SNDCP	SubNetwork Dependent Convergence Protocol
SSL	Secure Sockets Layer
TA	Terminal Adapter
TCP	Transmission Control Protocol
TDD	Time Division Duplexing
TDSCDMA	Time Division-Synchronous Code Division Multiple Access
TE	Terminal Equipment
TFT	Traffic Flow Template
TTS	Text To Speech
UARFCN	UTRA Absolute Radio Frequency Channel Number

UART	Universal Asynchronous Receiver/Transmitter
UAC	USB Audio Class
UCS2	Unicode
UDH	User Data Header
UDI	Unique Device Identification
UDP	User Datagram Protocol
UDUB	User Determined User Busy
UE	User Equipment
UFS	User File System
UMTS	Universal Mobile Telecommunications System
UICC	Universal Integrated Circuit Card
URC	Unsolicited Result Code
USB	Universal Serial Bus
(U)SIM	Universal Subscriber Identity Module
USSD	Unstructured Supplementary Service Data
UTRAN	UMTS Terrestrial Radio Access Network
VoLTE	Voice (voice calls) over LTE. A standard high-speed wireless communication for mobile phones and data terminals, including Internet of things devices and wearables.
WCDMA	Wideband Code Division Multiple Access
WLAN	Wireless Local Area Network

14.2. Factory Default Settings Restorable with AT&F

Table 9: Factory Default Settings Restorable with AT&F

AT Command	Parameters	Factory Defaults
ATE	<value>	1
ATQ	<n>	0
ATS0	<n>	0
ATS3	<n>	13
ATS4	<n>	10
ATS5	<n>	8
ATS7	<n>	0
ATV	<value>	1
ATX	<value>	4
AT&C	<value>	1
AT&D	<value>	2
AT+CREG	<n>	0
AT+CGREG	<n>	0
AT+CMEE	<n>	1
AT+CSCS	<chset>	"GSM"
AT+CSTA	<type>	129
AT+CR	<mode>	0
AT+CRC	<mode>	0
AT+CSMS	<service>	0
AT+CMGF	<mode>	0
AT+CSMP	<fo>,<vp>,<pid>,<dc>	17,167,0,0

AT+CSDH	<show>	0
AT+CSCB	<mode>	0
AT+CPMS	<mem1>,<mem2>,<mem3>	"ME","ME","ME"
AT+CNMI	<mode>,<mt>,<bm>,<ds>,<bfr>	2,1,0,0,0
AT+CMMS	<n>	0
AT+CVHU	<mode>	0
AT+CLIP	<n>	0
AT+COLP	<n>	0
AT+CLIR	<n>	0
AT+CSSN	<n>	0
AT+CTZR	<reporting>	0
AT+CPBS	<storage>	"SM"
AT+CGEREP	<mode>,<brf>	0,0
AT+CEREG	<n>	0
AT+CCWA	<n>	0
AT+CUSD	<mode>	0
AT+QAUDLOOP	<enable>	0

14.3. AT Command Settings Storable with AT&W

Table 10: AT Command Settings Storable with AT&W

AT Command	Parameters	Display with AT&V
ATE	<value>	Yes
ATQ	<n>	Yes

ATS0	<n>	Yes
ATS7	<n>	Yes
ATV	<value>	Yes
ATX	<value>	Yes
AT&C	<value>	Yes
AT&D	<value>	Yes
AT+IPR	<rate>	No
AT+CREG	<n>	No
AT+CGREG	<n>	No
AT+CEREG	<n>	No

14.4. AT Command Settings Storable with ATZ

Table 11: AT Command Settings Storable with ATZ

AT Command	Parameters	Factory Defaults
ATE	<value>	1
ATQ	<n>	0
ATS0	<n>	0
ATS7	<n>	0
ATV	<value>	1
ATX	<value>	4
AT&C	<value>	1
AT&D	<value>	2
AT+CREG	<n>	0

AT+CGREG	<n>	0
AT+CEREG	<n>	0

14.5. Summary of CME ERROR Codes

Final result code **+CME ERROR: <err>** indicates an error related to mobile equipment or network. The operation is similar to **ERROR** result code. None of the following commands in the same command line is executed. Neither **ERROR** nor **OK** result code shall be returned.

<err> values are mostly used by common message commands. The following table lists most of general and GRPS related **ERROR** codes. For some GSM protocol failure cause described in GSM specifications, the corresponding **ERROR** codes are not included.

Table 12: Different Coding Schemes of +CME ERROR: <err>

Code of <err>	Meaning
0	Phone failure
1	No connection to phone
2	Phone-adaptor link reserved
3	Operation not allowed
4	Operation not supported
5	PH-SIM PIN required
6	PH-FSIM PIN required
7	PH-FSIM PUK required
10	SIM not inserted
11	SIM PIN required
12	SIM PUK required
13	SIM failure
14	SIM busy

15	SIM wrong
16	Incorrect password
17	SIM PIN2 required
18	SIM PUK2 required
20	Memory full
21	Invalid index
22	Not found
23	Memory failure
24	Text string too long
25	Invalid characters in text string
26	Dial string too long
27	Invalid characters in dial string
30	No network service
31	Network timeout
32	Network not allowed - emergency calls only
40	Network personalization PIN required
41	Network personalization PUK required
42	Network subset personalization PIN required
43	Network subset personalization PUK required
44	Service provider personalization PIN required
45	Service provider personalization PUK required
46	Corporate personalization PIN required
47	Corporate personalization PUK required
901	Audio unknown error
902	Audio invalid parameters

903	Audio operation not supported
904	Audio device busy

14.6. Summary of CMS ERROR Codes

Final result code **+CMS ERROR: <err>** indicates an error related to mobile equipment or network. The operation is similar to ERROR result code. None of the following commands in the same command line is executed. Neither **ERROR** nor **OK** result code shall be returned.

<err> values are mostly used by common message commands:

Table 13: Different Coding Schemes of +CMS ERROR: <err>

Code of <err>	Meaning
107	Other General problems
300	ME failure
301	SMS ME reserved
302	Operation not allowed
303	Operation not supported
304	Invalid PDU mode
305	Invalid text mode
310	SIM not inserted
311	SIM pin necessary
312	PH SIM pin necessary
313	SIM failure
314	SIM busy
315	SIM wrong
316	SIM PUK required

317	SIM PIN2 required
318	SIM PUK2 required
320	Memory failure
321	Invalid memory index
322	Memory full
330	SMSC address unknown
331	No network
332	Network timeout
340	No +CNMA acknowledgement expected
350	Unknown
500	Unknown
510	Message blocked

14.7. Summary of URC

Table 14: Summary of URC

Index	URC Display	Meaning	Condition
1	+CREG: <stat>	Indicate registration status of the ME	AT+CREG=1
2	+CREG: <stat>[,<lac>,<ci>[,<AcT>]]	After cell neighborhood changing shows whether the network has currently indicated the registration of the ME, with location area code	AT+CREG=2
3	+CGREG: <stat>	Indicate network registration status of the ME	AT+CGREG=1
4	+CGREG: <stat>[,<lac>,<ci>[,<AcT>]]	Indicate network registration and location information of the ME	AT+CGREG=2
5	+CTZV: <tz>	Time zone reporting	AT+CTZR=1
6	+CTZE: <tz>,<dst>,<time>	Extended time zone reporting	AT+CTZR=2

7	+CMTI: <mem>,<index>	New message is received, and saved to memory	See AT+CNMI
8	+CMT: [<alpha>],<length><CR><LF><pdu>	New short message is received and output directly to TE (PDU mode)	See AT+CNMI
9	+CMT: <oa>,<alpha>,<scts>,<tooa>,<fo>,<pid>,<dc>,<sca>,<tosc a>,<length>]<CR><LF><data>	New short message is received and output directly to TE (Text mode)	See AT+CNMI
10	^HCMT: <oa>,<scts>,<lang>,<fmt>,<length>,<prt>,<prv>,<type>,<stat><CR><LF><data>	New short message is received and output directly to TE	See AT+CNMI
11	+CBM: <length><CR><LF><pdu>	New CBM is received and output directly (PDU mode)	See AT+CNMI
12	+CBM: <sn>,<mid>,<dc>,<page>,<pages><CR><LF><data>	New CBM is received and output directly to TE (Text mode)	See AT+CNMI
13	+CDS: <length><CR><LF><pdu>	New CDS is received and output directly (PDU mode)	See AT+CNMI
14	+CDS: <fo>,<mr>,<ra>,<tora>,<scts>,<dt>,<st>	New CDS is received and output directly to TE (Text mode)	See AT+CNMI
15	+CDSI: <mem>,<index>	New message status report is received, and saved to memory	See AT+CNMI
16	^HCDS: <oa>,<scts>,<lang>,<fmt>,<length>,<prt>,<prv>,<type>,<stat><CR><LF><data>	New CDS is received and output directly to TE	See AT+CNMI
17	+COLP: <number>,<type>,<subaddr>,<satype>,<alpha>	The presentation of the COL (connected line) at the TE for a mobile originated call	AT+COLP=1
18	+CLIP: <number>,<type>,<subaddr>,<satype>,<alpha>,<CLI validity>	Mobile terminating call indication	AT+CLIP=1
19	+CRING: <type>	An incoming call is indicated to the TE with unsolicited result code instead of the normal RING	AT+CRC=1
20	+CCWA: <number>,<type>,<class>,<alpha>	Call waiting indication	AT+CCWA=1,1
21	+CSSI: <code1>	Shows the +CSSI intermediate result	AT+CSSN=1

		code presentation status to the TE	
22	+CSSU: <code2>	Shows the +CSSU unsolicited result code presentation status to the TE	AT+CSSN=<n>,1
23	+CUSD: <status>[,<rspstr>[,<dcsc>]]	USSD response from the network, or a network initiated operation	AT+CUSD=1
24	RDY	ME initialization is successful	N/A
25	+CFUN: 1	All function of the ME is available	N/A
26	+CPIN: <state>	SIM card pin state	N/A
27	+QIND: SMS DONE	SMS initialization finished	N/A
28	+QIND: PB DONE	Phonebook initialization finished	N/A
29	POWERED DOWN	Module power down	AT+QPOWD
30	+CGEV: REJECT <PDP_type>, <PDP_addr>	A network request for PDP activation, and was automatically rejected.	AT+CGEREP=2,1
31	+CGEV: NW REACT <PDP_type>, <PDP_addr>, [<cid>]	The network request PDP reactivation	AT+CGEREP=2,1
32	+CGEV: NW DEACT <PDP_type>, <PDP_addr>, [<cid>]	The network has forced a context deactivation	AT+CGEREP=2,1
33	+CGEV: ME DEACT <PDP_type>, <PDP_addr>, [<cid>]	The ME has forced a context deactivation.	AT+CGEREP=2,1
34	+CGEV: NW DETACH	The network has forced a Packet Domain detach.	AT+CGEREP=2,1
35	+CGEV: ME DETACH	The mobile equipment has forced a Packet Domain detach.	AT+CGEREP=2,1
36	+CGEV: NW CLASS <class>	The network has forced a change of MS class.	AT+CGEREP=2,1
37	+CGEV: ME CLASS <class>	The mobile equipment has forced a change of MS class.	AT+CGEREP=2,1
38	+USIM: 0	Use SIM card	N/A
39	+USIM: 1	Use USIM card	N/A

14.8. SMS Character Sets Conversions

In 3GPP TS 23.038 DCS (Data Coding Scheme) defined three kinds of alphabets in SMS, GSM 7 bit default alphabet, 8 bit data and UCS2(16 bit). **AT+CSMP** can set the DCS in text mode (**AT+CMGF=1**). In text mode, DCS (Data Coding Scheme) and **AT+CSCS** determine the way of SMS text input or output.

Table 15: The Way of SMS Text Input or Output

DCS	AT+CSCS	The Way of SMS Text Input or Output
GSM 7 bit	GSM	Input or output GSM character sets.
GSM 7 bit	IRA	Input or output IRA character sets. Input: UE will convert IRA characters to GSM characters. Output: UE will convert GSM characters to IRA characters.
GSM 7 bit	UCS2	Input or output a hex string similar to PDU mode. So only support characters 0–9 and A–F. Input: UE will convert the UCS2 hex string to GSM characters. Output: UE will convert the GSM characters to UCS2 hex string.
UCS2	-	Ignore the value of AT+CSCS, input or output a hex string similar to PDU mode. So only support characters 0–9 and A–F .
8 bit	-	Ignore the value of AT+CSCS, input or output a hex string similar to PDU mode. So only support characters 0–9 and A–F.

When DCS = GSM 7 bit, the input or output needs conversion. The detailed conversion tables are shown as below.

Table 16: The Input Conversions Table (DCS = GSM 7 bit and AT+CSCS="GSM")

	0	1	2	3	4	5	6	7
0	00	10	20	30	40	50	60	70
1	01	11	21	31	41	51	61	71
2	02	12	22	32	42	52	62	72
3	03	13	23	33	43	53	63	73
4	04	14	24	34	44	54	64	74
5	05	15	25	35	45	55	65	75

6	06	16	26	36	46	56	66	76
7	07	17	27	37	47	57	67	77
8	08	18	28	38	48	58	68	78
9	09	19	29	39	49	59	69	79
A	0A	Submit	2A	3A	4A	5A	6A	7A
B	0B	Cancel	2B	3B	4B	5B	6B	7B
C	0C	1C	2C	3C	4C	5C	6C	7C
D	0D	1A	2D	3D	4D	5D	6D	7D
E	0E	1E	2E	3E	4E	5E	6E	7E
F	0F	1F	2F	3F	4F	5F	6F	7F

Table 17: The Output Conversions Table (DCS = GSM 7 bit and AT+CSCS="GSM")

	0	1	2	3	4	5	6	7
0	00	10	20	30	40	50	60	70
1	01	11	21	31	41	51	61	71
2	02	12	22	32	42	52	62	72
3	03	13	23	33	43	53	63	73
4	04	14	24	34	44	54	64	74
5	05	15	25	35	45	55	65	75
6	06	16	26	36	46	56	66	76
7	07	17	27	37	47	57	67	77
8	08	18	28	38	48	58	68	78
9	09	19	29	39	49	59	69	79
A	0D0A		2A	3A	4A	5A	6A	7A
B	0B		2B	3B	4B	5B	6B	7B
C	0C	1C	2C	3C	4C	5C	6C	7C

D	0D	1A	2D	3D	4D	5D	6D	7D
E	0E	1E	2E	3E	4E	5E	6E	7E
F	0F	1F	2F	3F	4F	5F	6F	7F

Table 18: GSM Extended Characters

	0	1	2	3	4	5	6	7
0					1B40			
1								
2								
3								
4		1B14						
5								
6								
7								
8			1B28					
9			1B29					
A								
B								
C				1B3C				
D				1B3D				
E				1B3E				
F			1B2F					

Table 19: The Input Conversions Table (DCS = GSM 7 bit and AT+CSCS="IRA")

	0	1	2	3	4	5	6	7
0		20	20	30	00	50	20	70

1	20	20	21	31	41	51	61	71
2	20	20	22	32	42	52	62	72
3	20	20	23	33	43	53	63	73
4	20	20	02	34	44	54	64	74
5	20	20	25	35	45	55	65	75
6	20	20	26	36	46	56	66	76
7	20	20	27	37	47	57	67	77
8	backspace	20	28	38	48	58	68	78
9	20	20	29	39	49	59	69	79
A	0A	Submit	2A	3A	4A	5A	6A	7A
B	20	Cancel	2B	3B	4B	1B3C	6B	1B28
C	20	20	2C	3C	4C	1B2F	6C	1B40
D	0D	20	2D	3D	4D	1B3E	6D	1B29
E	20	20	2E	3E	4E	1B14	6E	1B3D
F	20	20	2F	3F	4F	11	6F	20

Table 20: IRA Extended Characters

	A	B	C	D	E	F
0	20	20	20	20	7F	20
1	40	20	20	5D	20	7D
2	20	20	20	20	20	08
3	01	20	20	20	20	20
4	24	20	5B	20	7B	20
5	03	20	0E	20	0F	20
6	20	20	1C	5C	1D	7C
7	5F	20	09	20	20	20

8	20	20	20	0B	04	0C
9	20	20	1F	20	05	06
A	20	20	20	20	20	20
B	20	20	20	20	20	20
C	20	20	20	5E	07	7E
D	20	20	20	20	20	20
E	20	20	20	20	20	20
F	20	60	20	1E	20	20

Table 21: The Output Conversions Table (DCS = GSM 7 bit and AT+CSCS="IRA")

	0	1	2	3	4	5	6	7
0	40	20	20	30	A1	50	BF	70
1	A3	5F	21	31	41	51	61	71
2	24	20	22	32	42	52	62	72
3	A5	20	23	33	43	53	63	73
4	E8	20	A4	34	44	54	64	74
5	E9	20	25	35	45	55	65	75
6	F9	20	26	36	46	56	66	76
7	EC	20	27	37	47	57	67	77
8	F2	20	28	38	48	58	68	78
9	C7	20	29	39	49	59	69	79
A	0D0A		2A	3A	4A	5A	6A	7A
B	D8		2B	3B	4B	C4	6B	E4
C	F8	C6	2C	3C	4C	D6	6C	F6
D	0D	E6	2D	3D	4D	D1	6D	F1
E	C5	DF	2E	3E	4E	DC	6E	FC

F	E5	C9	2F	3F	4F	A7	6F	E0
---	----	----	----	----	----	----	----	----

Table 22: GSM Extended Characters

	0	1	2	3	4	5	6	7
0					7C			
1								
2								
3								
4		5E						
5								
6								
7								
8			7B					
9			7D					
A								
B								
C				5B				
D				7E				
E				5D				
F			5C					

Because the low 8 bit of UCS2 character is the same as the IRA character:

The conversion table of DCS = GSM 7 bit and **AT+CSCS="UCS2"** is similar to **AT+CSCS="IRA"**.
 The conversion table of fmt = GSM 7 bit and **AT+CSCS="GSM"** is similar to **AT+CSCS="GSM"**.
 The conversion table of fmt = GSM 7 bit and **AT+CSCS="IRA"** is similar to **AT+CSCS="IRA"**.
 The conversion table of fmt = GSM 7 bit and **AT+CSCS="UCS2"** is similar to **AT+CSCS="IRA"**.

The difference is the way of SMS text input or output. Please refer to **Table 23** for more details.

14.9. Release Cause Text List of AT+CEER

Table 23: List of Location ID List

Location ID	Meaning
0	CS internal cause
1	CS network cause
2	CS network reject
3	PS internal cause
4	PS network cause
5	PS LTE cause
6	PS LTE local cause

Table 24: List of Cause

CS Internal Cause	Meaning
-1	No cause information available (default)
0	Phone is offline
21	No service available
25	Network release, no reason given
27	Received incoming call
29	Client ended call
34	UIM not present
35	Access attempt already in progress
36	Access failure, unknown source
38	Concur service not supported by network
39	No response received from network

45	GPS call ended for user call
46	SMS call ended for user call
47	Data call ended for emergency call
48	Rejected during redirect or handoff
100	Lower-layer ended call
101	Call origination request failed
102	Client rejected incoming call
103	Client rejected setup indication
104	Network ended call
105	No funds available
106	No service available
108	Full service not available
109	Maximum packet calls exceeded
301	Video connection lost
302	Video call setup failure
303	Video protocol closed after setup
304	Video protocol setup failure
305	Internal error
CS Network Cause	Meaning
1	Unassigned/unallocated number
3	No route to destination
6	Channel unacceptable
8	Operator determined barring
16	Normal call clearing
17	User busy

18	No user responding
19	User alerting, no answer
21	Call rejected
22	Number changed
26	Non selected user clearing
27	Destination out of order
28	Invalid/incomplete number
29	Facility rejected
30	Response to status enquiry
31	Normal, unspecified
34	No circuit/channel available
38	Network out of order
41	Temporary failure
42	Switching equipment congestion
43	Access information discarded
44	Requested circuit/channel not available
47	Resources unavailable, unspecified
49	Quality of service unavailable
50	Requested facility not subscribed
55	Incoming calls barred within the CUG
57	Bearer capability not authorized
58	Bearer capability not available
63	Service/option not available
65	Bearer service not implemented
68	ACM >= ACM max

69	Requested facility not implemented
70	Only RDI bearer is available
79	Service/option not implemented
81	Invalid transaction identifier value
87	User not member of CUG
88	Incompatible destination
91	Invalid transit network selection
95	Semantically incorrect message
96	Invalid mandatory information
97	Message non-existent/not implemented
98	Message type not compatible with state
99	IE non-existent/not implemented
100	Conditional IE error
101	Message not compatible with state
102	Recovery on timer expiry
111	Protocol error, unspecified
127	Interworking, unspecified
CS Network Reject	Meaning
2	IMSI unknown in HLR
3	Illegal MS
4	IMSI unknown in VLR
5	IMEI not accepted
6	Illegal ME
7	GPRS services not allowed
8	GPRS and non GPRS services not allowed

9	MS identity cannot be derived
10	Implicitly detached
11	PLMN not allowed
12	Location area not allowed
13	Roaming not allowed
14	GPRS services not allowed in PLMN
15	No suitable cells in location area
16	MSC temporary not reachable
17	Network failure
20	MAC failure
21	Synch failure
22	Congestion
23	GSM authentication unacceptable
32	Service option not supported
33	Requested service option not subscribed
34	Service option temporary out of order
38	Call cannot be identified
40	No PDP context activated
95	Semantically incorrect message
96	Invalid mandatory information
97	Message type non-existent
98	Message type not compatible with state
99	Information element non-existent
101	Message not compatible with state
161	RR release indication

162	RR random access failure
163	RRC release indication
164	RRC close session indication
165	RRC open session failure
166	Low level failure
167	Low level failure no redial allowed
168	Invalid SIM
169	No service
170	Timer T3230 expired
171	No cell available
172	Wrong state
173	Access class blocked
174	Abort message received
175	Other cause
176	Timer T303 expired
177	No resources
178	Release pending
179	Invalid user data
PS Internet Cause	Meaning
0	Invalid connection identifier
1	Invalid NSAPI
2	Invalid primary NSAPI
7	PDP establish timeout
3	Invalid field
4	SNDP failure

5	RAB setup failure
6	No GPRS context
8	PDP activate timeout
9	PDP modify timeout
10	PDP inactive max timeout
11	PDP lower layer error
12	PDP duplicate
13	Access technology change
14	PDP unknown reason
PS Network Cause	Meaning
25	LLC or SMDCP failure
26	Insufficient resources
27	Missing or unknown APN
28	Unknown PDP address or PDP type
29	User authentication failed
30	Activation rejected by GGSN
31	Activation rejected, unspecified
32	Service option not supported
33	Requested service option not subscribed
34	Service option temporary out of order
35	NSAPI already used (not sent)
36	Regular deactivation
37	QoS not accepted
38	Network failure
39	Reactivation required

40	Feature not supported
41	Semantic error in the TFT operation
42	Syntactical error in the TFT operation
43	Unknown PDP context
44	PDP context without TFT already activated
45	Semantic errors in packet filter
46	Syntactical errors in packet filter
81	Invalid transaction identifier
95	Semantically incorrect message
96	Invalid mandatory information
97	Message non-existent/not implemented
98	Message type not compatible with state
99	IE non-existent/not implemented
100	Conditional IE error
101	Message not compatible with state
111	Protocol error, unspecified
PS LTE Cause	Meaning
8	Operator determined barring
26	Insufficient Resources
27	Missing or unknown APN
28	Unknown PDP address or PDP type
29	User Authentication failure
30	Activation rejected by Servicing GW or PDN GW
31	Activation rejected, unspecified
32	Service option not supported

33	Requested service option not subscribed
34	Service option temporarily out of order
35	PTI already In use
36	Regular deactivation
37	QoS not accepted
38	Network failure
39	Reactivation required
40	Feature not supported
41	Semantic error in the TFT operation
42	Syntactical error in the TFT operation
43	Unknown Bearer context
44	Semantic errors in packet filter
45	Syntactical errors in packet filter
46	Bearer Context without TFT already Active
47	PTI mismatch
49	PDN disconnected ,Not allowed
50	PDN type IPV4 only Allowed
51	PDN type IPV6 only Allowed
52	Single ADR bearers only Allowed
53	ESM info not recieved
54	PDN connection does not exist
55	Multiple PDN connection for given APN not allowed
56	Collision with network init request
59	Unsupported QCI value
81	Invalid PTI value

95	Symantically invalid message
96	Invalid mandatory information
97	Message non-existent/not implemented
98	Message type not compatible with state
99	Info Element non existent
100	Conditional IE error
101	Message type not compatible with state
111	Protocol error, unspecified
112	APN restrict value incompatible with ACT context
PS LTE Local Cause	Meaning
3	Illegal UE
6	Illegal ME
7	EPS services not allowed
9	UE id can't be driven by network
10	Implicitly Detached
11	PLMN not allowed
12	Tracking area not allowed
13	Roaming not allowed in this tracking area
15	No Suitable cells in tracking area
18	CS Domain Not available
25	Not Authorized for this CSG
38	CS fallback call EST not allowed
39	CS domain temporarily not allowed
43	Unknown EPS bearer context
256	Released AT RRC

257	Signal Connection Released
258	EMM detached
259	EMM attach failed
260	EMM attach started
261	NAS service request failed
262	ESM activate dedicated bearer reactivater by network
263	Lower layer failure
264	Lower layer failure
265	Network activater dedicated bearer with ID of deffered bearer
266	BAD OTA message
267	DS rejected the call
268	Context transferred due to IRAT
269	DS explicit deactivation
270	ESM MSGR failure
271	Local Cause not available
272	Rejected due to connected state
273	NAS Service request failed, no throttle
274	ACL failure
275	NAS Service request failed , DS disallow
276	EMM T3417 expired
277	EMM T3417 ext expired
278	NAS LRRC UL data CNF failure TXN
279	NAS LRRC UL data CNF failure HO
280	NAS LRRC UL data CNF failure CONN release
281	NAS LRRC UL data CNF failure RLF

282	NAS LRRRC UL data CNF failure control Not CONN
283	NAS LRRRC connection EST success
284	NAS LRRRC connection EST failure
285	NAS LRRRC connection EST failure, aborted
286	NAS LRRRC connection EST failure, access barrer
287	NAS LRRRC connection EST failure, CELL resel
288	NAS LRRRC connection EST failure, config failure
289	NAS LRRRC connection EST failure, timer expired
290	NAS LRRRC connection EST failure, link failure
291	NAS LRRRC connection EST failure, not camped
292	NAS LRRRC connection EST failure, SI failure
293	NAS LRRRC connection EST failure, CONN reject
294	NAS LRRRC connection release normal
295	NAS LRRRC connection release RLF
296	NAS LRRRC connection release CRE failure
297	NAS LRRRC connection release QOS during CRE
298	NAS LRRRC connection release aborted
299	NAS LRRRC connection release SIB read error
300	NAS LRRRC connection release aborted IRAT success
301	NAS Reject LRRRC radio link failure
302	NAS service request failure, LTE network reject
303	NAS detach with reattach, LTE network detach
304	NAS detach without reattach, LTE network detach