

# Electromagnetic Calorimeter System Operations Manual

L.C Smith, Jefferson Laboratory

*ec\_manual.tex – v1.1*

August 23, 2016

## **Abstract**

This document provides an overview of the CLAS12 Electromagnetic Calorimeter (EC) System and serves as an Operations Manual for the detector. Instructions are provided for shift workers related to basic steps of operating and monitoring the HV controls, monitoring the detector system and responding to alarms, and knowing when to contact the on-call personnel. More complete details are also provided for EC system experts regarding the channel mapping to the readout electronics, the cable connections and routing in Hall B, higher-order high voltage system operations, and detector servicing. This document also provides references to the available EC documentation and a list of personnel authorized to perform EC system repairs and modify system settings.

# Contents

<b>1 EC Overview . . . . .</b>	<b>3</b>
<b>2 Information for Shift Workers . . . . .</b>	<b>8</b>
2.1 Shift Worker Responsibilities . . . . .	8
2.1.1 Updating the Logbook . . . . .	8
2.1.2 Contacting EC System Personnel . . . . .	8
2.1.3 Hall B Alarm Handler . . . . .	8
2.2 High Voltage Controls . . . . .	8
2.3 Detector Monitoring . . . . .	13
<b>3 Information for Subsystem Experts . . . . .</b>	<b>15</b>
3.1 Subsystem Expert Responsibilities . . . . .	15
3.1.1 Hot Checkout . . . . .	15
3.1.2 On-call Responsibilities . . . . .	15
3.1.3 HV Gain Calibrations . . . . .	15
3.2 HV System Operations . . . . .	17
3.2.1 Setting HV Channel Parameters . . . . .	17
3.2.2 HV Save and Restore . . . . .	17
3.3 Cabling Details . . . . .	19
3.3.1 Signal Cable Layout . . . . .	19
3.3.2 HV Cable Layout . . . . .	19
3.3.3 Altering Cable Maps . . . . .	26
3.3.4 Cable Connections . . . . .	26
3.4 System Failure Modes . . . . .	29
3.4.1 HV Board Replacement . . . . .	29
3.4.2 Sudden Gain Shift . . . . .	29
3.4.3 High PMT Dark Current . . . . .	30
3.4.4 Missing Anode or Dynode Signal . . . . .	30
3.4.5 Bad PMT . . . . .	31
3.4.6 Readout Electronics Issues . . . . .	31
3.4.7 IOC Issues . . . . .	31
3.5 Detector Repairs and Servicing . . . . .	31
<b>4 Documentation . . . . .</b>	<b>32</b>
<b>5 FTOF Authorized Personnel . . . . .</b>	<b>32</b>
<b>6 Appendix: Hall B Instrumentation Database . . . . .</b>	<b>33</b>

# 1 EC Overview

The CLAS12 EC package includes the legacy CLAS6 electromagnetic calorimeters (ECAL) and new pre-shower calorimeter (PCAL) modules installed just upstream of ECAL. Six sectors of EC in CLAS12 will be used primarily for identification of electrons, photons (including  $\pi^0 \rightarrow 2\gamma$  decays), and neutrons. Both PCAL and ECAL are triangular-shaped sampling calorimeters. The calorimeter design uses a lead-scintillator sandwich consisting of alternating layers of 1-cm thick scintillators and 2 mm thick lead sheets. At 11 GeV the total thickness corresponds to about 21 radiation lengths. Scintillator layers are grouped into three stereo views, called U, V, and W, which are readout using photomultiplier tubes (PMT). Specifications for each calorimeter are outlined below.




Figure 1.1: Photographs of the ECAL (left) and PCAL (right) calorimeter modules installed on the Forward Carriage in Hall B. The Forward Carriage is roughly 10 m in diameter.

Parameter	Design Value
<b>PCAL</b>	
Calorimeter type	Sampling, lead-scintillator
Number of modules	6
Module shape and dimensions	Triangle, base 394.3 cm height 385.3 cm
Total coverage area	45 m <sup>2</sup>
Distance from Target	7 m
Angular coverage	$\theta: 5^\circ \rightarrow 35^\circ, \phi: 50\% \text{ at } 5^\circ \rightarrow 85\% \text{ at } 35^\circ$
Lead sheets	2.2 mm thick (two pieces)
Number of scintillator layers	15 per module
Number of lead sheets	14 per module
Number of stereo readout views	3 (5 scintillator layers per view)
Scintillator material	Extruded polystyrene w/ 2 fiber holes
Scintillator core	Dow Styron 663 W
Scintillator cladding	Polystyrene with 12% TiO <sub>2</sub> (0.25 mm)
Scintillator strip dimensions	1 x 4.5 x 2.5-394(U)432(V,W) cm
Scintillator readout	WLS fibers (Kuraray Y-11 1mm DC)
Scintillators/module	U:84 V:77 W:77
Scintillators readout/module	U:68 V:62 W:62
Number of WLS fibers	4 fibers/strip 1428/module
Number of readout channels	192 per module
Readout PMT	Hamamatsu R6095
Light yield	11-12 photo e-/MeV

Table 1: PCAL technical design parameters.

Parameter	Design Value
<b>ECAL</b>	
Calorimeter type	Sampling, lead-scintillator
Number of modules	6
Module shape and dimensions	Triangle, base 420 cm height 388.8 cm
Total Coverage Area	49 m <sup>2</sup>
Distance from Target	7.21723 m (target center to upstream face)
Angular Coverage	$\theta: 5^\circ \rightarrow 35^\circ, \phi: 50\% \text{ at } 5^\circ \rightarrow 85\% \text{ at } 35^\circ$
Lead sheets	2.387 mm thick (single piece)
Number of scintillator layers	39 per module (15 inner, 24 outer)
Number of lead sheets	38 per module
Number of stereo readout views	3 (5 scintillator layers per view)
Scintillator material	BC-412
Scintillator cladding	None. Teflon film (0.00762 cm) between layers.
Scintillator strip dimensions	1 x 10.0 x 15-420 cm
Scintillator readout	BCF98 3mm cladded optical fiber
Scintillators/module	U:36 V:36 W:36
Number of fibers	22 fibers/PMT, 110(176) per inner(outer) view
Number of readout channels	216 per module
Readout PMTs	Phillips XP2262 and EMI 9954
Light yield	3-4 photo e-/MeV
<b>Expected Performance</b>	<b>Value</b>
Energy resolution	$10\%/\sqrt{E}$ (ECAL+PCAL)
Position resolution	0.5 cm
Time resolution	500 ps

Table 2: ECAL technical design parameters.

A block diagram of the readout electronics for the EC system is shown in Figure 1.2. Signal cables are routed from the PMT locations on the calorimeter modules to UVA 122B splitter panels located on the front of the electronics racks. The cable connections are BNC at the PMT anode and LEMO at the splitter. From the splitter, patch cables are routed to VME DSC2 leading edge discriminators (for pulse timing measurements) and JLAB 250 MHz VME Flash ADCs (FADC250) (for pulse amplitude measurements.) The TDCs are CAEN VME 1190A with 100 ps LSB resolution. The FADC250 and DSC2/TDC modules are housed in separate VXS crates. The FADC250/VXS crate contains the Virtual Trigger Processor (VTP) in a special switched slot which will be used to process energy and hit data for trigger decision making.




Figure 1.2: Schematic of signal readout electronics for ECAL system. Shown are the cable and split ratios for the ECAL PMTs. The PCAL case is similar but uses different split ratios. Not shown are HV connections. For ECAL transition patch cables were used at either end of the RG-8 signal cable, which are not shown here.

The electronics for each sector are located behind the detectors on the three levels of the Forward Carriage as follows:

- EC S1: FC Level 2 South (Beam left)
- EC S2: FC Level 3 South (Beam left)
- EC S3: FC Level 3 North (Beam right)
- EC S4: FC Level 2 North (Beam right)
- EC S5: FC Level 1 North (Beam right)
- EC S6: FC Level 1 South (Beam left)

Note that “South” refers to beam left and “North” to beam right (closer to the Pie Tower).

Figure 1.3 shows the Forward Carriage rack locations for the ECAL VME electronics and signal cable patch panels. Note the rack layout for beam left is a mirror image of the layout for beam right. Also the Level 1 rack

layout is different due to an alternate cable routing (discussed later). A photograph of the Sector 6 rack installation is shown in Figure 1.4.

The HV power supplies for all PMTs in each ECAL sector are either CAEN 1527LC mainframes or CAEN 4527 mainframes outfitted with negative polarity 24-channel A1535N cards which fit into slots at the rear of each mainframe. The HV mainframes that power the PCAL system are actually shared between the FTOF and the PCAL. The FTOF boards occupy slots 0 to 7 of each mainframe and the PCAL boards occupy slots 8 to 15 of each mainframe. These supplies are named HVFTOF $n$ ,  $n=1 \rightarrow 6$  (i.e. HVFTOF1 → HVFTOF 6). The HV mainframes for the EC modules are named HVECAL $n$  ( $n=1 \rightarrow 6$ ). Figure 1.3 shows the locations of the HV mainframes for each of the EC sectors on the Forward Carriage.




Figure 1.3: Schematic layout of the EC VME electronics, signal cable splitters, and HV power supplies in the electronics racks on each of the three levels of the Forward Carriage. The rack names on each level (c1, c2, and c3) are numbered 1 through 10.



Figure 1.4: Photograph of racks C1-6 through C1-10 (Sector 6) during cable installation. The rack with no cables installed (C1-8) houses four ECAL splitter panels (top), the FADC250 VXS crate (middle) and DSC2/TDC VXS crate (bottom). The CAEN HV mainframe *hvecal6* is at far left in rack C1-6, and the PCAL/FTOF mainframe *hvftof6* is to the right in rack C1-7.

## 2 Information for Shift Workers

### 2.1 Shift Worker Responsibilities

The shift worker in the Hall B Counting House has five responsibilities with regard to the EC system:

1. Updating the Hall B electronic logbook with records of problems or system conditions (see Section 2.1.1).
2. Contacting EC system on-called personnel for any problems that are discovered (see Section 2.1.2).
3. Responding to EC system alarms from the Hall B alarm handler (see Section 2.1.3).
4. Turning on or off the high voltage for the EC system using the HV control interface (see Section 2.2).
5. Monitoring the hit occupancy scalers for the system (see Section 2.3).

#### 2.1.1 Updating the Logbook

The electronic logbook (or e-log) [1] is set up to run on a specified terminal in the Hall B Counting House. Shift workers are responsible for keeping an up-to-date and accurate record of any problems or issues concerning the EC system. For any questions regarding the logbook, its usage, or on what is considered to be a “logbook worthy” entry, consult the assigned shift leader.

Note the shift worker should follow all posted or communicated instructions about entering ECAL scaler screens into the e-log. This is typically done once per 8-hour shift as directed on the shift checklist.

#### 2.1.2 Contacting EC System Personnel

As a general rule, shift workers should spend no more than 10 to 15 minutes attempting to solve any problem that arises with the EC system. At that point they should contact the assigned EC on-call worker to either provide advice on how to proceed or to address the problem.

This document is divided into a section for shift workers and EC system experts. However, only EC system experts (as listed in Section 5) are authorized to make changes to the EC parameter settings, to work on the hardware or electronics, or to modify the DAQ system software. This division between shift worker responsibilities and expert responsibilities is essential to maintain in order to protect and safeguard the equipment, to ensure data collection is as efficient as possible, and to minimize down time. If the shift worker has any question regarding how to proceed when an issue arises, the shift leader should be consulted.

#### 2.1.3 Hall B Alarm Handler

The BEAST alarm handler system running in the Counting House monitors the entire Hall B Slow Controls system. This include HV and LV systems, gas systems, torus and solenoid controls, subsystem environment controls (e.g. temperature, humidity), and pulser calibration systems (among several others). The system runs on a dedicated terminal in the Counting House. One of the main responsibilities of the shift worker is to respond to alarms from this system, either by taking corrective action or contacting the appropriate on-call personnel. Instructions and details on the alarm handler for Hall B are given in Ref. [2].

For the EC system, the only element of the system monitored by the alarm handler is the HV system. Any time a channel trips off an alarm will sound. The alarm handler will identify the specific channel (or channels) that have tripped. These channels can be reset either through the alarm handler or through the nominal EC HV control screens. These channels should be reset only after ensuring that whatever condition caused the trip (e.g. bad beam conditions) has been addressed.

## 2.2 High Voltage Controls

Control of the EC HV mainframes is through the Hall B CS-Studio suite, which is an Eclipse-based collection of tools used as an interface to the EPICS Slow Control system. To start the user interface on any terminal in the Hall B Counting House, enter the command `clascss`. Figure 2.1 shows the control panel that is launched.

HV controls are presented in two ways: either mapped to the physical detector (sector,layer,component) or mapped to the HV mainframe (crate,slot,channel). To access detector-based EC HV controls, click on the “ECAL” button on the Detectors list. This pops up a sub-menu of all Slow Controls subprograms for the ECAL system.




Figure 2.1: Left: The CS-Studio interface used for the Slow Controls of the CLAS12 detectors and subsystems. ECAL HV controls may be accessed through either the “ECAL” button under Detectors or the “HV” button under Subsystems. Right: Detector based ECAL HV display and control interface. For each sector the outermost triangle represents the PCAL, while ECinner and ECouter are the middle and innermost triangles respectively. Individual PMT HV channel controls are indicated by small circles. HV channel status is indicated by the colormap at lower right. An entire sector of PMTs (EC+PCAL) may be turned on and off by clicking the sector number at the apex of the triangle.

Clicking on “EC HV” will bring up the HV control panel shown in Figure 2.1 (right). This interface allows simple ON/OFF HV operations which are detailed in Figure 2.2.

For the shift worker the most common operations are turning off and on large groups of PMTs. These group operations are accessed via the pop-up menus which appear when clicking on the labels shown in Figure 2.2 and described below:

1. Turning on and off all PMTs within a single sector.
2. Turning on and off all PMTs within a single calorimeter (ECAL or PCAL).
3. Turning on and off all PMTs within a single U,V,W view of a single calorimeter.

In addition to group ON/OFF operations it may be occasionally necessary to access single PMTs in order to enable, disable, change the HV or alter various set-points for that specific PMT. This is accomplished by either clicking on the “Controls” selection in Figure 2.2 which brings up all PMTs corresponding to a (U,V,W) view, or clicking on the circular icon corresponding to the desired PMT (see Figure 2.3) to bring up just the panel for that PMT.




Figure 2.2: Detail of Fig. 2.1 which shows sector “1” has been selected, activating the pop-up option menu. Individual controls for modules are labeled “ECAL”, “PCAL” and for individual views “U,V,W” which provide similar pop-up menus as shown. Control of individual PMTs within a view is possible by clicking the circular elements.

If a single PMT is selected, a window similar to Fig. 2.3 (middle) is displayed. This window shows the monitored channel voltage and current  $V_{mon}$  (V) and  $I_{set}$  ( $\mu$ A), the channel status (OFF, ON), and the demand or set channel voltage  $V_{set}$  (V). Also shown is the maximum permissible HV divider current  $I_{set}$  ( $\mu$ A). This interface would be used by shift workers to enable or disable a PMT via the Pw button.

In the upper left corner of the window is a button marked “Expert” that brings up the window shown at the bottom of Fig. 2.3. This window allows changes to the system settings for the maximum channel current, maximum channel voltage setting, and the channel HV ramp up and ramp down rates. Clicking on the “Novice” button in




Figure 2.3: ECAL HV displays for single PMT HV controls. Hover the mouse over the PMT icons to view popup of EPICS Property Value (PV) identifier. Select the desired PMT to bring up Novice mode controls (middle) which allow only OFF/ON control via the Pw button. Click Expert button to bring up controls for voltage (Vset), maximum HV divider current (Iset), maximum HV (Vmax), HV ramp rates (Up,Down). Note these settings apply only to the PMT selected, not all PMTs.

the upper left corner toggles between the expert and novice screens. **The expert screen should only be used by the list of authorized EC personnel given in Section 5.**

The HV Control Interface screen (see Fig. 2.1) also provides a color key to indicate the channel status:

- HV off - no highlight color (channel color dark green)
- HV on - bright green
- HV ramping up or ramping down - orange
- HV trip - red
- Communication problem - yellow
- Undefined channel status - magenta

When HV controls are unresponsive or HV monitoring stripcharts appear to become static it is likely to be an EPICS communication error due to an IOC process that cannot communicate with the hardware or a server. Sometimes the hardware is at fault and has to be rebooted or power-cycled. Usually this requires an IOC reboot. Controls for monitoring IOC status and rebooting frozen IOCs are available from several menus. For the EC HV system the IOC screen can be reached from the CSS menu via the “HV” button under Subsystems (see Figure 2.4.) To reboot the IOC for a specific mainframe, click on the “Restart iochHV\*” button corresponding to the desired mainframe. PMT channels for which an IOC reboot is necessary will illuminate yellow as illustrated for the EC Sector 6 PMTs in Figure 2.1.




Figure 2.4: EPICS IOC status and controls are available from the CSS Main Menu by clicking on “HV” under “Subsystems”, then clicking on “IOC Status”. This will be necessary whenever HV Mainframes are power-cycled or otherwise interrupted, or if the HW Comms Status lights are anything but green, or the IOC “HeartBeat” is not blinking green.

## 2.3 Detector Monitoring

A number of monitoring tools to study the performance of the Forward Carriage detector systems have been prepared. A hierarchy of tools is desirable to allow quick access to detector status without the necessity of bringing up the Data Acquisition (DAQ). One of the earliest tools developed was a ROOT-based GUI called FCMON [3] to monitor and display scalers for the Forward Carriage detectors. To launch this program from any Counting House computer, type *fcmon*. This brings up the window as shown in Figure 2.5 (left). This tool enables display of the scalers from all forward carriage discriminators and FADCs for each of the six CLAS12 sectors. To use the interface for EC, click on the sector of interest in the left column, click on ECAL or PCAL in the center column, and then click on the source of the scalers in the third column. To bring up the scaler display screens, select “Scalers” under the “Monitor” drop down menu as shown in Figure 2.5 (right).




Figure 2.5: Forward Carriage scaler display program *fcmon*. (Left) Main screen. (Right) Menu selection to access scaler display window. Click on “scalers”.

The EC scalers can be monitored in one of three different ways by selecting the appropriate tab at the top of the scaler display screen (see Fig. 2.6). These three modes include:

- Slots: Scaler rate values (Hz) displayed for each VXS crate slot, channel housing the DSC2 or FADC modules.
- Rates: Scaler rate values (Hz) plotted for each physical EC detector channel.
- Stripcharts: Scaler rate values (Hz) plotted as a 2D strip chart (rate (z) vs. counter (y) vs. time (x))

As of the time of writing of this document, FCMON is the most direct tool for determining if the front-end electronics are receiving the intended signals from the PMTs. If holes show up in these plots, the first step is to determine if the HV for the affected PMT is on and if the HV divider current is non-zero. For this purpose, the HV Control GUIs already discussed can provide this information. Further steps may be taken to determine the cause of occupancy problems. A Java based CLAS12 system monitoring suite that is under development will represent another tool that the shift worker can use to quickly assess the detector status. Both FCMON and other monitoring tools will be running on dedicated terminals in the Hall B Counting House.




Figure 2.6: Display modes of FCMON Scalers GUI. Top Left: Slot/channel readout Top Right: Rates vs. PMT number and U,V,W view Bottom: 2D stripchart showing rates vs. time.

## 3 Information for Subsystem Experts

### 3.1 Subsystem Expert Responsibilities

The EC subsystem experts have several key responsibilities:

1. Complete hot checkout sign-off before the start of each run period (see Section 3.1.1).
2. Respond to calls on the on-call phone to resolve issues with the EC system that are necessary during data taking (see Section 3.1.2).
3. Take periodic HV gain calibration runs and adjust the system HV settings (see Section 3.1.3).
4. Make repairs to the hardware during maintenance periods (see Section 3.4).

#### 3.1.1 Hot Checkout

Prior to the start of each physics running period, each subsystem group leader is responsible to review the components of their systems to be sure that they are fully operational. This review is referred to as “hot checkout”. The hot checkout is an online checklist for each system that includes a sign-off for all hardware elements of the system (e.g. HV, LV, detectors, gas, pulser). For the EC system, the hot checkout includes verification that all detectors are operational and that all signals are present as seen through the scaler displays. Fig. 3.1 shows screenshots of the hot checkout interface from a development version of the system. Under the heading “Hall B CLAS12 Detector”, open the list for the EC system. All entries for EC must be verified as ready. Note that often as part of the system checkout before the start of a run period, an initial HV gain calibration is completed (see Section 3.1.3). Reminders to complete the system hot checkout will be sent out shortly before the start of a given run period with the required deadline for completing the work.

#### 3.1.2 On-call Responsibilities

Each subsystem will organize a list of on-call experts who will take responsibility for carrying a cell phone to allow 24 hour access to experts who can address any problems that arise during the physics running period. The phone numbers of all subsystem experts are posted on the run page. Any problems that cannot be quickly solved by the shift workers, where quickly amounts to 10 to 15 minutes, should result in a call to the relevant expert cell phone.

The on-call experts can often diagnose problems over the telephone, but there are times where they will have to go to the Counting House to more fully address the issues. One of the important responsibilities of the on-call experts is to make practical decisions regarding which problems require access to Hall B for immediate attention and when they can be delayed to periods when the accelerator is down or other work is scheduled in the hall. For the EC system, usually problems with a single channel are not important enough to stop the data acquisition. The normal mode of operation after initial investigation of a bad channel, is to turn off the HV for that channel until access can be made for a more detailed investigation. This work should be coordinated with the Run Coordinator.

Note: It is the responsibility of the EC on-call expert to review all issues that they cannot resolve with the EC subsystem Group Leader as soon as is reasonable.

#### 3.1.3 HV Gain Calibrations

The HV gain calibrations for the EC system are typically completed before the start of each run period, as well as several times during the run period when there is opportunity. The HV gain calibration procedure employs a cosmic ray trigger defined either ECAL or PCAL. The ADC spectra for each counter are fit to ensure that the minimum ionizing particle peak appears at a specific location in the ADC range corresponding to a specific gain. The end result of the gain calibration amounts to adjusting the system HV settings to position the ADC peaks at their assigned locations.

The calibration suite for the EC system includes both an online and an offline component. The online component is used to calibrate the PMT gains and the output is a table of PMT HV settings that are downloaded into the HV power supplies. The offline component is used to determine the parameters to optimize the absolute energy calibration and resolution of the system. Full documentation on using EC calibration, including tutorials for using the code, are included on the EC web page. [4].




Figure 3.1: Screenshots of the development version of the Hall B hot checkout screens. The EC system will appear under the “Hall B CLAS12 Detector” heading. All entries for EC have been to verified as functional and all items listed as “Not Ready” must be changed over to “Ready”.

## 3.2 HV System Operations

### 3.2.1 Setting HV Channel Parameters

The CS-Studio program is used to monitor the HV settings of the EC system and to toggle the HV off and on for individual or multiple channels in the system. As discussed in Section, there is also the option to adjust settings channel-by-channel using the HV “expert” screen shown in Fig. 2.3. Here the parameters,  $V_{set}$ ,  $I_{set}$ ,  $V_{max}$ , and the HV ramp up and ramp down rates, can be entered directly into the parameter fields. This “expert” screen should most properly be used only for viewing the channel parameter set values. Finally there are control scripts available in the event nominal settings need to be restored. From the computers in the Hall B Counting House, the scripts are located in the sector subdirectories located in the path: `/home/clasrun/ecal/hv/sn`, and `/home/clasrun/pcal/hv/sn` where  $sn$  corresponds to  $s1$  to  $s6$  for  $S1 \rightarrow S6$ . There are five scripts available for setting these HV channel parameters:

- `loadhvmax-sn`: Maximum HV limits for each supply channel (units = V)
- `loadi0-sn`: Maximum current limits for each supply channel (units =  $\mu$ A)
- `loadrup-sn`: Voltage ramp up rates for each supply channel (units = V/s)
- `loadrdn-sn`: Voltage ramp down rates for each supply channel (units = V/s)
- `loadtrip-sn`: Maximum time duration for an overcurrent condition before the channel trips (units = s)

The nominal settings for the HV channel parameters are as follows:


- HV values (PCAL): Typically in the range from -800 V to -950 V
- HV values (ECAL): Typically in the range from -1500 V to -2000 V
- HV values (PCAL): Typically in the range from -800 V to -950 V
- $HV_{max}$  values: PCAL: -1000 V, ECAL: -2500 V
- $i_{max}$  values: 500  $\mu$ A
- HV ramp up rate: 50 V/s
- HV ramp down rate: 100 V/s
- Overcurrent duration before trip: 1 s

Individual HV values and the enable/disable status of each PMT are created by the monitoring and calibration programs and these values are stored in a separate database. There are no backup scripts for setting these values since they are time-dependent and have to be carefully managed. Nevertheless save and restore values can be archived from the EC HV control screen (see Section 3.2.2).

### 3.2.2 HV Save and Restore

The EC HV interface allows all system channel settings to be saved into a file or loaded from an archived file by clicking on the “ECAL” or “PCAL” button in the upper right corner of the main HV screen (see Fig. 2.1). The files created are referred to as “BURT” backup files, where BURT is an acronym for “Backup and Restore Tool”. BURT is a utility for saving the HV system settings into an ascii file readable by the EPICS Slow Control system.

After clicking on the detector button, a sub-menu appears as shown in Fig. 3.2 to select “Save Settings” or “Restore Settings”. Clicking on “Save Settings” brings up a window “CREATE HV BACKUP” as shown at bottom, displaying the save file path and the selected file name that contains the system name along with the date and time. If the “Restore Settings” option is chosen, the window shown in Fig. 3.3 comes up showing the saved ECAL or PCAL HV restore files available to select from. Selecting a file and clicking on “OK” at the bottom of the window loads all channel parameters for the full HV system. Note that a new backup file should be created whenever any HV settings have changed, including HV values, channel parameter settings, and channel on/off settings.



<det>\_HV-<year>\_<month>\_<date> - <hour>\_<min>\_<sec>.snp

Figure 3.2: Top: Choose the appropriate detector (ECAL or PCAL) for saving HV settings. The pop-up menu will allow you to select “Save Settings” or “Restore Settings”. Bottom: If “Save Settings” is chosen, a pop-up confirmation dialog will display the path and name of the BURT snapshot file, using the timestamp format shown at bottom. This name can be edited if desired.




Figure 3.3: If “Restore Settings” is chosen, use the pop-up file chooser to select the snapshot file for restoring HV settings.

### 3.3 Cabling Details

#### 3.3.1 Signal Cable Layout

The U,V,W PMTs for the ECAL modules are located at the rear (downstream) face of each triangle-shaped module (see Figure 3.4) and are distributed uniformly along its perimeter. There are two layers of PMTs: the top layer reads out the inner calorimeter (closest to the target) and the bottom layer reads out the outer calorimeter. The PMTs are also oriented parallel to the U,V,W strips within each module. HV and RG-8 signal cables are fastened to and routed along steel gratings running parallel to the calorimeter sides. RG-58 patch cables (16 ns delay) run from the PMT anode connector to the thicker and less flexible RG-8 cable. At the other end of the RG-8, a second connection is made to RG-58 patch cables (16 ns delay) connected to LEMO inputs at the rear of the UVA 122B splitter panels. These patch connections are illustrated by the photos in Figure 3.5.



Figure 3.4: Placement of ECAL U,V,W PMTs at rear (downstream) side of Sector 2 module. Gratings are used to route HV and RG-8 signal cables.

The U,V,W PMTs for the PCAL modules are mounted along the sides of each module (see Figures 3.6 and 3.7). Due to geometry constraints the V,W PMTs for PCAL are located together on the same side (corresponding to V PMT side of the ECAL.) For PCAL only the U PMTs and cable connections are accessible from the Forward Carriage decks. Figure 3.8 shows a view of the PCAL U cable routing within the gap between adjacent ECAL modules, and Figure 3.9 shows the V,W cable routing for Sector 6.

#### 3.3.2 HV Cable Layout

HV cable connections to the rear of the mainframes are made using a JLAB built transition/distribution box with 48 SHV input connectors and two output cables each terminated with a 24-pin connector designed to mate with the receptacle on the A1535N cards (see Figure 3.13).

Both signal and HV cables from the EC system pass under the floor gratings on Levels 2 and 3 and for Level 1 cables are routed through openings in the ceiling. For ECAL RG-8 signal cables the connection to BNC-Lemo transition cables are made under the grating near the racks containing the ECAL splitter panels (Figure 3.13.)

The high voltage cables for each PMT run from the voltage divider to a local disconnect HV distribution box located behind the panel-2 arrays in each sector next to the signal cable local disconnect patch panels. Note that there are four HV distribution boxes for each sector, two for the left PMTs and two for the right PMTs of each sector. Fig. 3.14 shows the layout of the two HV distribution boxes for the left and right PMT HV connections. The



Figure 3.5: For ECAL two RG-58 16 ns patch cable connections are made to the RG-8 signal cable: at the PMT end and near the UVA 122B splitter panels at the electronic racks. Left: Connections made along the rail grating next to the PMTs. Middle: Connection made beneath the floor gratings on Levels 2 and 3 of the Forward Carriage. Right: Connections made within the electronics racks on Level 1.



Figure 3.6: Placement of PCAL U PMTs (left) and V,W PMTs (right). Photo taken in EEL Building.



Figure 3.7: Orientation of PCAL U and V,W PMTs relative to ECAL. Photo taken in Hall B during installation of PCAL in Sector 5 of the Forward Carriage.




Figure 3.8: Routing of HV and RG-58 signal cables from U PMTs of PCAL. Cables pass through the gap in between adjacent ECAL modules (seen above and below in the photo.)




Figure 3.9: Routing of HV and RG-58 signal cables from V,W PMTs of PCAL. Cables are routed directly to cable trays mounted parallel to the V,W readout side for all modules. Only Sector 5 and Sector 6 (seen here) V,W PMTs are accessible from floor level with ladders. Other sectors require a man-lift for access. Also visible at left are the V PMTs for ECAL.

Figure 3.10: Electronics map for the input connections to the FTOF VME FADCs.

Figure 3.11: Electronics map for the input connections to the FTOF VME discriminators.

Figure 3.12: Electronics map for the input connections to the FTOF VME TDCs .




Figure 3.13: Left: Rear of CAEN HV mainframe (top) showing installed HV cards. At bottom are transition boxes with SHV input connectors and red output cables which mate with the HV cards. Right: Photographs of ECAL HV/signal cable bundles underneath floor gratings (which are removed here). Removal of floor gratings gives access to RG-8/RG-58 BNC/BNC connections visible at top. Also visible are HV cable connections to the HV distribution box (right).

output of each HV distribution box is a pair of 35-ft-long multi-conductor cables, each containing 24-channels, with a Radiall connector to mate with the HV A1535N board input connector. See Figs. 3.16 and 3.17 in Section 3.3.4 for schematics of the cable and connector types for each segment of the HV connections from the voltage divider to the HV power supplies for the counters in FTOF panel-1a, panel-1b, and panel-2. The HV power supply channel assignments for each sector are nominally given as shown in Fig. 3.15.

### 3.3.3 Altering Cable Maps

The nominal procedure if there is a problem with a VME electronics board is to replace the board with a spare unit. However, for testing purposes, it might be necessary to change a signal input at the FADC, discriminator, or TDC to an unused channel. This work must always be done in coordination with the DAQ system expert in order to update the channel map used as input to the translation table. This operation is not something that is normally done and should not be attempted by shift workers or FTOF experts as it could lead to problems decoding the data.

Problems with channels within the HV system are more common issues as channels on the HV distribution box or on an A1535N card are reasonably common. The standard procedure when there is a problem with a CAEN HV board is to swap out the board (see Section 3.4.1). If there is a problem on the HV distribution box on either the left or right side of a sector, there are six spare HV channels that are available. These are detailed in Section 3.3.2. If one of these spare channels is to be used, the first step before disconnecting any system HV cables is to be sure that the channel HV is turned off for the channel to be moved. The SHV cable can then be moved to one of the open connectors on the HV distribution box shown in Fig. 3.14. In order to update the HV channels map, contact the Slow Controls expert.

### 3.3.4 Cable Connections

In order to better understand the signal and high voltage cabling scheme for the FTOF system, Figs. 3.16 and 3.17 show for panel-1a, panel-1b, and panel-2 the cable and connection types from the counter PMTs to the Forward Carriage electronics and power supplies.

Figure 3.14: Mapping of the HV channel connections to the HV distribution boxes for each sector. Each sector is connected to four HV distribution boxes, two for the left side PMTs and two for the right side PMTs. Note: The box beam that supports the panel-2 arrays and the patch panels themselves is located under the second box.

Figure 3.15: HV mainframe FTOF channel assignments for each sector.

Figure 3.16: FTOF panel-1a and panel-2 HV and signal cable connections.

Figure 3.17: FTOF panel-1b HV and signal cable connections.

## 3.4 System Failure Modes

For the FTOF detector, there are a number of usual “failure” modes with which the system expert should be familiar. These include the following:

- Replacing a HV board (see Section 3.4.1).
- Sudden ADC gain shift (see Section 3.4.2).
- High PMT dark current (see Section 3.4.3).
- Missing anode or dynode signal (see Section 3.4.4).
- Bad PMT (see Section 3.4.5).
- Readout electronics issues (see Section 3.4.6).
- IOC issues (see Section 3.4.7).

### 3.4.1 HV Board Replacement

The evidence for a bad HV board (A1535N) is either that the 24 channels associated with a single board won’t ramp up to full voltage before tripping off or bad voltage regulation. For the case of bad voltage regulation, the channels ramp up to full voltage but then fluctuate about the demand voltage setting by up to several hundred volts. Before deciding whether a HV board is bad, some investigation should be completed to ensure that a single HV channel is not causing the problems with the board, which could point to a problem with the PMT or voltage divider. If a board is deemed bad and needs to be replaced, the following steps are necessary:

1. Take a spare A1535N board from the storage area on the second level of the Pie Tower in Hall B.
2. Turn the front panel key on the HV supply to the “off” position and toggle the main power switch to “off” on the back of the HV supply.
3. On the back of the supply, remove the Radiall connector on the bad board.
4. Pull out the bad board, being careful of the Radiall connectors on the neighboring boards.
5. Install the new board and reconnect the Radiall connector.
6. Toggle the main power switch to “on” and turn the HV power supply on using the key on the front panel, putting the key in the “local” position.
7. Run all parameter scripts for the HV power supply to load all channel parameters. See instructions in Section 3.2.1.
8. Enter information on the new board and the old bad board into the Hall B equipment database (see the Appendix).
9. Leave the bad board on the RadCon Survey table in Hall B.

### 3.4.2 Sudden Gain Shift

Sometimes a sudden gain shift can appear in the ADC spectra for a given counter. There are a number of possible causes for such a condition.

- Problematic PMT - sometimes gain shifts can be attributed to a problem with a PMT that requires adjustment of the HV settings. Of course, PMT gain issues typically lead to a reduced gain that requires an increase of the HV.
- DAQ Problems - the most common cause for an apparent gain shift in the ADC spectra for a counter is due to problems with the FADC settings. Such problems can typically be diagnosed from pedestal shifts or widened pedestals. The pedestals can be checked by taking FADC data in “raw mode”. Note that as the panel-1a and panel-1b dynode signal used for the FADC inputs are bipolar pulses (see Section ??), issues with shifts in the signal summing region can have a dramatic impact on the FADC spectra.

- Bad Inverters - the panel-1b dynode signals, which are used for the input to the FADCs, are nominally positive polarity pulses that are sent through an inline inverter attached to the Forward Carriage patch panel (see Section 3.3.1). These inverters occasionally go bad and can be diagnosed comparing the signal on either side of the inverter. Bad inverters should be replaced with new spare inverters contained in the FTOF storage cabinets on the upper level of the Pie Tower.
- Light Leak - it is possible that a gain shift can be due to hardware damage or a light leak on the counter. Note that issues with hardware damage are less likely for the panel-1a and panel-1b counters as they are buried between the LTCC/RICH detectors and the calorimeters. Of course, the panel-2 counters are more exposed and hardware issues can either be explored by looking at signals or measuring dark currents at the voltage dividers, the local disconnect patch panels, or the electronics patch panels. The panel-2 detectors themselves can be explored using access with manlifts as necessary, coordinating work through the Hall B Work Coordinator.

### 3.4.3 High PMT Dark Current

High PMT dark currents can be seen in the channel scaler displays. The dark currents can be measured at either the local disconnect or the electronics patch panels. There are three likely causes for high PMT dark currents:

1. Bad PMT - At times when a PMT goes bad, its dark current can increase. Typical FTOF PMT dark currents are at the level of 50 nA or less. If a bad PMT has been identified, it can only be worked on during designated FTOF servicing periods. However, the usual procedure is to leave the PMT energized and live with the increased dark current unless the higher currents cause the HV supply channel to trip. If the channel HV needs to be turned off, the logbook should be updated and the HV setting configuration with the channel off should be saved as the nominal setting.
2. Light Leak - A light leak in the counter wrapping will also lead to higher dark currents. The issue of light leaks is not expected to be an issue for the panel-1a and panel-1b counters as they are buried within the detectors on the Forward Carriage and ambient light levels are very low. For the panel-2 counters, they are more exposed. Light leaks can be repaired during opportunities when the Forward Carriage is moved away from the torus magnet.
3. Reflective Layer Wrapping Problems (panel-1b only) - There is an issue with the wrapping of the reflective layer on some of the panel-1b counters that has been seen to lead to “super-hot” PMTs, with dark currents up to 100  $\mu$ A. There are several PMTs that have a history of showing such high currents, but occasionally a PMT that had been operating without issue, can suddenly show very large currents. Sometimes the current draw will monotonically reduce over the period of several hours. These PMTs will remain at low currents as long as the HV is not turned off. Sometimes, the currents remain high regardless of how long they are energized. In such cases, judgment should be exercised as to whether to leave the channel on or off. If the channel is turned off, the HV setting configuration should be updated and saved.

### 3.4.4 Missing Anode or Dynode Signal

Occasionally a signal will disappear from FTOF monitoring plots. In such a situation, further investigation will be necessary.

- If both anode and dynode signals are missing, this could be due either to a problem with the HV, the VME crate (which would affect an entire board or entire sector), or the PMT itself. If the problem is with the HV board, it should be replaced as detailed in Section 3.4.1. PMT problems are typically apparent as the nominal PMT signal (see Fig. ??) is absent, severely distorted, or replaced by high frequency noise.
- If one signal is present and the other is missing, this could be a bad cable connection anywhere from the voltage divider to the input to the electronics. The way to diagnose is to use an oscilloscope to look at the signal at each accessible junction point. If the signal is missing from the monitoring data but is seen to be good at the input to the FADC and TDC, contact the DAQ expert for help.
- If the dynode signal is missing from panel-1b, this is likely caused by a bad signal inverter (see Section 3.4.2).

- If either the anode or dynode signal is missing from a panel-1a or panel-2 PMT and the cabling checks out, the problem is likely due to a bad component on the voltage divider. In such a case the channel must be turned off (with HV channel parameters updated - see Section 3.2.2). Repairs can only be made during a designated FTOF repair cycle.

#### **3.4.5 Bad PMT**

One of the most common failure modes of a PMT is a gradual loss of gain over the period of several years. This can be compensated by adjusting the HV to maintain the gain setting. The PMTs used in the FTOF system have maximum voltage ratings of -2500 V for the PMTs in panel-1a and panel-2, and -2000 V for the PMTs in panel-1b. Once the PMT HV is set to its maximum value and the gain falls below the nominal setting, the PMT should be flagged for replacement during the next servicing opportunity.

#### **3.4.6 Readout Electronics Issues**

Readout electronics issues, typically associated with all channels associated with a given discriminator board, TDC board, or FADC board, once diagnosed should be brought to the attention of the DAQ system expert for further diagnosis and attention.

#### **3.4.7 IOC Issues**

Loss of communication between the IOC and the HV mainframe is seen by a yellow color status for all HV channels in a given sector. The IOC should be reset following the instructions given in Section 2.2. If resetting the IOC does not solve the problems, contact the Slow Controls system expert.

### **3.5 Detector Repairs and Servicing**

Repairs and servicing on the FTOF detectors themselves, specifically panel-1a and panel-1b, are highly involved and inherent risky operations. As the counters themselves are structurally robust, no mechanical problems are expected with them during the lifetime of CLAS12. However, PMTs do occasionally go bad due to gain reductions as a function of time and need to be replaced. In addition, voltage dividers can also sometimes go bad due to failed components. In order to replace a PMT or a voltage divider on either panel-1b or panel-1a, the entire panels have to be removed from the Forward Carriage and placed on the floor of Hall B. This involves removal of the associated LTCC and either one or both FTOF arrays depending on which array needs servicing. Such an operation would never be done to repair a single bad element due to the effort and the risk involved. Of course, PMT and/or divider replacement for the panel-2 counters can be performed in situ using a ladder or a manlift (depending on the PMT location). This work will be carried out either by the FTOF Group Leader or the Hall B technicians during a scheduled hall access. As for panel-1b and panel-1a, mechanical problems with the scintillation counters themselves in panel-2 are not expected to be necessary during the lifetime of CLAS12.

All FTOF detector repairs will be organized through the FTOF Group Leader in conjunction with the Hall B Work Coordinator to be scheduled during a planned major down time for Hall B.

## 4 Documentation

All current documentation for the FTOF system is located on the official FTOF web page [?]. A number of basic subsystem documents can be found there including:

- FTOF System Operations Manual (this document)
- FTOF Geometry Document
- FTOF Calibration Constants
- FTOF Monte Carlo Simulation Details
- FTOF Reconstruction Document
- Assorted photographs of the detector hardware

## 5 FTOF Authorized Personnel

Beyond turning on/off the EC system HV and monitoring the system scalers, all other operations and repairs are only to be carried out by the list of authorized personnel shown in Table 3. The list of authorized personnel for FTOF can only be modified by FTOF Group Leader.

Name	Telephone	email	Area
Stepan Stepanyan	757-269-7196	stepanya@jlab.org	EC Group Leader
Cole Smith	434-249-4307	lcsmith@jlab.org	Hardware
Daniel Carman	757-269-5586	carman@jlab.org	Hardware
Sergey Boyarinov	757-269-5795	boyarinov@jlab.org	DAQ
Nathan Baltzell	757-269-5902	baltzell@jlab.org	Slow Controls

Table 3: EC detector authorized personnel.

## 6 Appendix: Hall B Instrumentation Database

When electronics modules or HV modules are removed from Hall B and replaced during servicing with new boards, the information regarding both the old board and the new board need to be entered into the Hall B Instrumentation Database. This database is accessed online at <http://clonwiki0.jlab.org> by clicking on the “Hall B Inventory” link. This brings up the access screen shown in Fig. 6.1. To enter information for the old component, search for it in the database using its property tag information. When the item shows up, click on the “Action” button for “Modify this item”. Be sure to change the location of the item to “Hall B Underground/RadCon Table” and change the status of the item to “Action needed/Broken”, as well as to leave the item on the RadCon survey table in Hall B. By entering this information, email will be sent to the property custodian to pick up the item for servicing. For the new component, be sure to also change the location as appropriate using the same approach.

Figure 6.1: Hall B equipment database web page.

## References

- [1] Hall B Electronic Logbook: <https://logbooks.jlab.org/book/hblog>
- [2] Hall B BEAST alarm handler:  
[https://clasweb.jlab.org/wiki/index.php/Slow\\_Control\\_Alarms](https://clasweb.jlab.org/wiki/index.php/Slow_Control_Alarms)
- [3] FCMON:  
<https://github.com/forcar/fc/wiki/FCMON>
- [4] EC web page:  
[https://clasweb.jlab.org/wiki/index.php/CLAS12\\_Forward\\_Electromagnetic\\_Calorimeter](https://clasweb.jlab.org/wiki/index.php/CLAS12_Forward_Electromagnetic_Calorimeter)