Kontrol Sistemleri

Final çalışması – Çözüm 1

Original notes: Solution-1.pdf

UYARI Bu belge, el yazısı ders notlarından Claude (Anthropic) yardımıyla dijitale aktarılmıştır. Yardımcı kaynak olarak hazırlanmıştır; hata veya eksik içerebilir. Lütfen orijinal notları ve ders kaynaklarını esas alın.


NOTICE *This document was transcribed from handwritten lecture notes with the help of Claude (Anthropic). It is meant as a supplementary resource and may contain errors or omissions. Always check against the original notes and official course material.*

orig. p. 1

Q1

20% 5% per item

a) Not always. when an entire row in Routh table becomes zero, it means that at least two poles are on the imaginary axis OR real axis OR complex poles symmetric with respect to the origin



b) Steady state error is due to the type of the system as well as the input signal. For example a type 1 system can follow an step input while inputs like ramp or parabolic signals are not followed accurately.

c) No, stability is a characteristic of the system itself and does not depend on the input signal.

d) Pole placement: reduces stability, increases accuracy
increases the settling time (slow response)
Zero placement: Increases stability, faster responses will appear (decreasing the settling time), can lead to noise augmentation
In terms of performance, when poles are added, max. overshoot is reduced but for zero placement, M_p% increases.

orig. p. 2

Q2

$$\begin{cases} C(s) = \big(E(s)\,G_1(s) + D(s)\big)\,G_2(s) \\ E(s) = R(s) - C(s) \end{cases}$$

$$\Rightarrow \quad R(s) - E(s) = \big(E(s)\,G_1(s) + D(s)\big)\,G_2(s)$$

$$\Rightarrow \quad E(s) = \frac{R(s)}{1 + G_1(s)G_2(s)} - \frac{G_2(s)\,D(s)}{1 + G_1(s)G_2(s)}$$

The steady state error is 10%

$$e(\infty) = e_{ss} = \lim_{s\to 0} sE(s)$$
$$= \lim_{s\to 0}\left[\frac{sR(s)}{1 + G_1(s)G_2(s)} - \frac{sG_2(s)D(s)}{1 + G_1(s)G_2(s)}\right]$$

a) steady-state error due to $D(s) = \frac{1}{s}$, $R(s) = 0$ is -0.00001

$$-0.00001 = \lim_{s\to 0} -\frac{G_2(s)}{1 + G_1(s)G_2(s)}$$
$$= \lim_{s\to 0} -\frac{\dfrac{k_2}{s(s+4)}}{1 + \dfrac{k_2}{s(s+4)}\dfrac{k_1(s+2)}{s+3}}$$

$$\Rightarrow \quad 0.00001 = \lim_{s\to 0} \frac{k_2(s+3)}{s(s+3)(s+4) + k_1k_2(s+2)}$$
$$= \frac{3k_2}{2k_1k_2} = \frac{3}{2k_1} \qquad 5\%$$

$$\Rightarrow \quad \boxed{k_1 = 150{,}000}$$

b) steady-state error due to $R(s) = \frac{1}{s}$, $D(s) = 0$ is 0.002

$$0.002 = \lim_{s\to 0} \frac{1}{1 + G_1(s)G_2(s)}$$
$$= \lim_{s\to 0} \frac{s(s+3)(s+4)}{s(s+3)(s+4) + k_1k_2(s+2)} \neq 0 \qquad 5\%$$

So the second condition may not be satisfied, and for any value of k_2, the system tracks unit step input!

orig. p. 3

Q3

$$1 + kG(s) = 0$$

$$\rightarrow\ s(s+0.7)(s+1.2)(s^2 + 0.8s + 6) + k(s+6) = 0$$

(characteristic equation)

$$\Rightarrow (s^2 + 0.7s)(s^3 + 0.8s^2 + 6s + 1.2s^2 + 0.96s + 7.2) + ks + 6k = 0$$
$$\Rightarrow (s^2 + 0.7s)(s^3 + 2s^2 + 6.96s + 7.2) + ks + 6k = 0$$
$$\Rightarrow s^5 + 2s^4 + 6.96s^3 + 7.2s^2 + 0.7s^4 + 1.4s^3 + 4.872s^2 + 5.04s + ks + 6k = 0$$
$$\Rightarrow s^5 + 2.7s^4 + 8.36s^3 + 12.072s^2 + (k + 5.04)s + 6k = 0 \qquad 5\%$$

s^5	1	8.36	$k + 5.04$
s^4	2.7	12.072	$6k$
s^3	3.89	$\frac{-3.3k + 13.608}{2.7}$	
s^2	$\frac{33.35 + 3.3k}{3.89}$	$6k$	
s^1	$\frac{k^2 + 28.37k - 41.53}{-8.24 - 0.82k}$	0	
s^0	$6k$		

10%

So in order to have no change in sign, all components of the first column must be positive, which gives the following conditions,

1) $k > 0$
2) $33.35 + 3.3k > 0 \rightarrow k > -10.1$

orig. p. 4

from the above two conditions we find out that k must be positive (greater than zero).

Now let's check the last condition.

$$\frac{k^2 + 28.37k - 41.53}{-8.24 - 0.82k} > 0 \Rightarrow \underbrace{k^2 + 28.37k - 41.53}_{eq.} < 0$$

roots of this 2nd order equation are $k_1 = 1.395$, $k_2 = -29.76$

$k < -29.76$	$\rightarrow eq > 0$	×
$-29.76 < k < 1.395$	$\rightarrow eq < 0$	✓
$k > 1.395$	$\rightarrow eq > 0$	×

So in total the acceptable range is $\boxed{0 < k < 1.395}$ 5%

orig. p. 5

Q4

$$\text{Open loop T.F.:} \quad G(s) = \frac{k(s+1)}{s(s-1)(s^2 + 6s + 30)}$$

Zero: $Z = -1$

Poles: $P_1 = 0$, $P_2 = 1$, $P_{3,4} = -3 \pm j\sqrt{21}$ 5%

unmatched branches : $n - m = 3 \Rightarrow$ 3 asymptotes

$$\Phi_k = \frac{2k+1}{n-m} \cdot 180 \rightarrow \begin{cases} \Phi_0 = 60^\circ \\ \Phi_1 = 180^\circ \\ \Phi_2 = 300^\circ = -60^\circ \end{cases}$$ 5%

So asymptote angles are $\pm 60^\circ$ and 180°.

the centroid of asymptotes may be determined as

$$S = \frac{\sum \text{real part of poles} - \sum \text{real part of zeroes}}{n - m} = -\frac{4}{3} = -1.33$$ 5%

Now, let's calculate the breaking points by using the characteristic equation

$$s(s-1)(s^2+6s+30)+k(s+1)=0 \Rightarrow k=-\frac{s(s-1)(s^2+6s+30)}{s+1}$$

$$\frac{dk}{ds}=0 \Rightarrow \frac{(s-1)(s^2+6s+30)+s(s^2+6s+30)+s(s-1)(2s+6)}{s+1} \quad 5\%$$

$$=\frac{s(s-1)(s^2+6s+30)}{(s+1)^2}$$

$$\Rightarrow 3s^4+14s^3+39s^2+48s-30=0 \rightarrow \begin{cases} s_1 = +0.44 & \checkmark \\ s_2 = -2.601 & \checkmark \\ s_{3,4} = -1.25 \pm 2.67j & \times \end{cases}$$

orig. p. 6

The first two roots are on the root locus, so they are accepted as break out and break in points.

Figure: Root locus sketch in the s-plane (Re axis to the right, jω axis up). Real-axis marks −3, −2, −1, +1. Poles (×) at 0 and +1; zero (o) at −1; complex poles P_3 (upper left, above −3) and P_4 (lower left, below −3), each joined to the jω axis by a dashed horizontal line. Red root-locus segments on the real axis: from −∞ (red arrow to the left labeled "∞ asymptote") up to the zero at −1, with "Break in" marked between −3 and −2 (about −2.6); and between 0 and +1, with a double-headed arrow labeled "break out" (about +0.44). Green dashed asymptote lines leave the centroid (labeled "Centroid", between −2 and −1, about −1.33) at 60° and −60° (angles marked 60° and −60°); the upper one is labeled "asymptote".
(in the original notes, p. 6)

Now let's determine the angles of leaving from the complex poles,

∗ leaving angle: $180^\circ - \sum$ angles of other poles w.r.t this pole
from P_3 $+ \sum$ angles of other zeros

$$= 180^\circ - (90^\circ) - \left(180 - \tan^{-1}\left(\frac{\sqrt{21}}{3}\right)\right) - \left(180 - \tan^{-1}\frac{\sqrt{21}}{4}\right) \quad 5\%$$

$$+ \left(180 - \tan^{-1}\frac{\sqrt{21}}{2}\right)$$

$$= 180^\circ - 90^\circ - 123.21^\circ - 131.12^\circ + 113.58^\circ = -50.75^\circ$$

for pole 'P_4' the leaving angle will be +50.75°.

orig. p. 7

we can also determine the intersection of the root locus with the imaginary axis by using the Routh table as,

$$s(s-1)(s^2+6s+30)+k(s+1)=0$$

$$\rightarrow s^4+5s^3+ks+24s^2+k-30s=0 \quad 5\%$$

$$\rightarrow s^4+5s^3+24s^2+(k-30)s+k=0$$

s^4	1	24	k
s^3	5	$k-30$	
s^2	$30-\frac{k}{5}$	k	
s^1	$\frac{k^2-155k+4500}{k-150}$		
s^0	k		

① $k > 0$

② $30-\frac{k}{5} > 0 \rightarrow k < 150$

③ $\frac{k^2-155k+4500}{k-150} > 0$

In order to be stable, all the above conditions must hold. So $k^2 - 155k + 4500 < 0$ then $38.68 < k < 116.31$ to make it happen and finally all the three conditions are satisfied for $38.68 < k < 116.31$. 10%

There are two cases where we can construct a full zero row, in the s^1 row. For $k = 38.68$ and $k = 116.31$ this row becomes zero, the auxiliary equation for these two cases are

orig. p. 8


$$\left(30-\frac{k}{5}\right)s^2 + k = 0$$

$$@\ k = 38.68 \ : \ 22.26\,s^2 + 38.68 = 0$$
$$@\ k = 116.31 \ : \ 6.74\,s^2 + 116.31 = 0$$

So the jω-crossings are 5%

$$s_{1,2} = \pm j1.32$$
$$s_{3,4} = \pm j4.15$$

According to the current data, we can plot the root locus to a high degree of accuracy, but if we want explicit and analytical definition for various branches we should check the phase condition by substituting $s = \sigma + j\omega$ in the open-loop transfer function.




original drawing, p. 8

10%

orig. p. 9

for positive feedback, the root locus plot is



original drawing, p. 9

5%