Event day: set up the scouting server

Laminate it and tape it to the Pi's case. First-time setup: SETUP_GUIDE.md. Network detail: PI_NETWORK.md. SSD and backups: PI_STORAGE.md.

[PHOTO: the Pi, the switch and every cable plugged in correctly, each cable labelled]

Kit: Pi (SSD attached) · official 27 W Pi supply · unmanaged switch and its power · one flat Ethernet cable per Chromebook · USB-C-to-Ethernet adapters · gaff tape · USB stick. **No Wi-Fi hotspot, router, mesh, cellular tether or any radio network for event data, ever.**

Set up (about 10 minutes)

1. **Cable before power.** Pi `eth0` → switch. Each Chromebook → switch (adapter only where needed). Tape every cable run flat.
2. **Power on in order:** switch first, then the Pi. Wait about a minute for the green light to settle.
3. **The server starts by itself.** `systemctl status tealteam` should say `active (running)`. If not: `sudo systemctl restart tealteam`; `journalctl -u tealteam -n 50` says why.
4. **Check:** in the TealTeam folder, `deploy/pi/network/status.sh`. Every line `ok`; a `FAIL` names the fix. `no uplink` is fine.
5. **No phone tether at the event.** The Pi runs without an uplink; rankings use the latest local snapshot.
6. **From a Chromebook:** open **http://tealteam.local** (else **http://tealteam** or **http://10.101.0.1**).
7. **Lead scout:** sign in, pick the event, check the rankings age. Scouting and lead work happen on the wired Chromebooks; phones only view.
8. **Schedule posted:** on the Pi, `deploy/event/prep-event.sh deploy/profiles/ftc-qual-4robot.env --roster roster.csv --csv athens.csv`. Check every match against the printed schedule. If it changes, run it again: observations are kept.

Between match blocks: back up to the stick

Plug in the stick, then `sudo /opt/tealteam/tt-web backup /media/$USER/STICK`. Wait for "**It is on the disk.**", check the observation count looks right, eject, then pull it. (The server also snapshots to the SSD every 10 minutes; the stick is the copy that leaves the building.)

If something is wrong

Symptom	Do this
Chromebook can't open the page	Cable and adapter seated? Switch powered? Wi-Fi off? Try `http://10.101.0.1`. Run `status.sh`.
`status.sh`: eth0 FAIL	Switch unpowered or the Pi's cable is loose.
`status.sh`: app FAIL	`sudo systemctl restart tealteam`; still failing → is the SSD plugged in?
Rankings stale (amber)	No uplink by design. Use the local snapshot; note when upstream data was last updated.
Pi lost power	Check the Pi's clock (`date`) once it is back up: it has no clock battery.
App down for more than a match	Switch to the paper sheets. Write the time on the paper-switch log.
FTA asks about wireless	There is none. Offer to unplug the phone; nothing else changes.

Tear down

1. Last backup to the stick, and eject it.
2. `sudo poweroff` and wait for the green light to stop.
3. Unplug the Pi, then the switch. Count the cables, adapters and the stick.