

12/24/02 ; Re-build for 12x12 package (GZG289) based on 16x16 (GHK288)
12/26/02 : Changed group of VSSA and VSS3V from Power to GND

PIN #	CSP BALL#	Pin Name	Group	Type	During reset		Pin Function										Pull up/down
					Nrml	Ehost											
1	H7	DSP_BDX0	Audio I/F	O	Z	Z	DSP Serial-port Transmit 00										-
2	J8	DSP_BCLKX0	Audio I/F	I/O	I	I	DSP Transmit Clock 0KX0										-
3	B1	DSP_BFSX0	Audio I/F	I/O	I	I	DSP Frame Sync Pulse Transmit 0X0										-
4	C2	DSP_BDR0	Audio I/F	I/O	I	I	DSP Serial Data Receive 00										-
5	D3	DSP_BCLKR0	Audio I/F	I/O	I	I	DSP Receive Clock 0KR0										-
6	C1	DSP_BFSR0	Audio I/F	I/O	I	I	DSP Frame Sync Pulse Receive 0R0										-
7	E4	DVDD1	Power	-	-	-	VDD for I/O										-
8	D2	DSP_CLKS0	Audio I/F	I	I	I	DSP Serial Clock 0S0										-
9	F4	DGND1	GND	-	-	-	GND for I/O										-
10	E3	RXD0	Communication I/F	I	I	I	UART RXD 0 / AIMSIF Data in										-
11	E2	TXD0	Communication I/F	O	H	H	UART TXD 0 / AIMSIF Data out										-
12	J7	SDEN0	Communication I/F	I/O	I	I	Serial Data Enable 0 / AIMSIF Enable										-
13	E1	SCLK0	Communication I/F	I/O	I	I	Serial Clock 0 / AIMSIF Clock										-
14	F3	SDI0	Communication I/F	I	I	I	Serial Data Input 0										-
15	F2	SDO0	Communication I/F	O	L	L	Serial Data Output 0										-
16	G4	GIO33	General I/O	I/O	I	I	GIO	EXT_LINE_ID	I	NTSC/PAL Encoder				-			
17	G3	GIO32	General I/O	I/O	I	I	GIO	SDA	I	I2C Data				-			
18	G2	GIO31	General I/O	I/O	I	I	GIO	SCL	O	I2C Clock				-			
19	K8	GIO30	General I/O	I/O	I	I	GIO	PWM1	O	Pulse Width Modulation				-			
20	H4	GIO29	General I/O	I/O	I	I	GIO	PWM0	O	Pulse Width Modulation				-			
21	G1	CVDD1	Power	-	-	-	VDD for core										-
22	H2	CGND1	GND	-	-	-	GND for core										-
23	H3	GIO28	General I/O	I/O	I	I	GIO	FIELD	O	Field (NTSC/PAL Enc.)				-			
24	K7	GIO27	General I/O	I/O	I	I	GIO	CCDC_SHUT	O	CCD CCDC SHUT				-			
25	J2	GIO26	General I/O	I/O	I	I	GIO	C_WEN	I	CCD In Write Enable				-			
26	J4	GIO25	General I/O	I/O	I	I	GIO	MIRQ	O	IRQ Monitor	MRST	O	Master Reset from WDT	-			
27	J3	GIO24	General I/O	I/O	I	I	GIO	TXD1	O	UART TXD 1				-			
28	J1	GIO23	General I/O	I/O	I	I	GIO	RXD1	I	UART RXD 1				-			
29	K2	GIO22	General I/O	I/O	I	I	GIO	SDEN1	I/O	Serial Data Enable 1				-			
30	L8	GIO21	General I/O	I/O	I	I	GIO	SCLK1	I/O	Serial Clock 1				-			
31	K4	GIO20	General I/O	I/O	I	I	GIO	SDI1	I	Serial Data input 1				-			
32	K3	GIO19	General I/O	I/O	I	I	GIO	SDO1	O	Serial Data Output 1				-			
33	L7	GIO18	General I/O	I/O	I	I	GIO	CLKOUT2	O	General Clock Out 2				-			
34	L4	GIO17	General I/O	I/O	I	I	GIO	CLKOUT1	O	General Clock Out 1				-			
35	L3	GIO16	General I/O	I/O	I	I	GIO	CLKOUT0	O	General Clock Out 0				-			
36	L1	GIO15	General I/O	I/O	I	I	GIO	INT15	I	External Interrupt	DSP_XF	O	DSP External Flag	-			
37	M8	DVDD2	Power	-	-	-	VDD for I/O										-
38	M7	GIO14	General I/O	I/O	I	I	GIO	INT14	I	External Interrupt	DSP_CLKS1	I	DSP Serial Clock 1	-			
39	M3	DGND2	Power	-	-	-	GND for I/O										-
40	M4	GIO13	General I/O	I/O	I	I	GIO	INT13	I	External Interrupt	DSP_BDX1	O	DSP Serial-port Transmit 1	-			
41	N8	GIO12	General I/O	I/O	I	I	GIO	INT12	I	External Interrupt	DSP_BCLKX1	I/O	DSP Transmit Clock 1	-			
42	M2	GIO11	General I/O	I/O	I	I	GIO	INT11	I	External Interrupt	DSP_BFSX1	I/O	DSP Frame Sync Pulse Transmit 1	-			
43	N3	GIO10	General I/O	I/O	I	I	GIO	INT10	I	External Interrupt	DSP_BDR1	I/O	DSP Serial Data Receive 1	-			
44	N1	GIO9	General I/O	I/O	I	I	GIO	INT9	I	External Interrupt	DSP_BCLKR1	I/O	DSP Receive Clock 1	-			
45	N4	GIO8	General I/O	I/O	I	I	GIO	INT8	I	External Interrupt	DSP_BFSR1	I/O	DSP Frame Sync Pulse Receive 1	-			
46	N2	GIO7	General I/O	I/O	I	I	GIO	INT7	I	External Interrupt				-			
47	N7	GIO6	General I/O	I/O	I	I	GIO	INT6	I	External Interrupt				-			
48	P3	GIO5	General I/O	I/O	I	I	GIO	INT5	I	External Interrupt				-			
49	P2	GIO4	General I/O	I/O	I	I	GIO	INT4	I	External Interrupt				-			
50	P4	GIO3	General I/O	I/O	I	I	GIO	INT3	I	External Interrupt				-			
51	P7	GIO2	General I/O	I/O	I	I	GIO	INT2	I	External Interrupt				-			
52	R1	GIO1	General I/O	I/O	I	I	GIO	INT1	I	External Interrupt				-			
53	R2	GIO0	General I/O	I/O	I	I	GIO	INT0	I	External Interrupt				-			
54	R3	CVDD2	Power	-	-	-	VDD for core										-
55	R4	RSN	Misc.	I	I	I	Reset for Main Land										-
56	T2	PWDWN	Sleep Controller	I	I	I	Power Down Mode										Dn
57	T3	CGND2	GND	-	-	-	GND for core										-
58	P8	TCK	Misc.	I	I	I	JTAG Clock										Up
59	U1	TDI	Misc.	I	I	I	JTAG Data Input										Up
60	U2	TMS	Misc.	I	I	I	JTAG Test Mode Select										Up
61	U3	TRST	Misc.	I	I	I	JTAG Test Reset										Dn
62	T4	TEST0	Misc.	I	I	I	Test Input0										Dn
63	V2	TEST1	Misc.	I	I	I	Test Input1										Dn
64	V3	TEST2	Misc.	I	I	I	Test Input2										Dn
65	U4	TEST3	Misc.	I	I	I	Test Input3										Dn
66	W1	SCANEN	Misc.	I	I	I	Test Scan Enable										Dn
67	W2	TDO	Misc.	O	Z	Z	JTAG Data Output										-
68	V4	VCLK	Video Output	O	L	L	Video Out Clock										-
69	Y1	HSYNC	Video Output	O	L	L	H-Sync for RGB output										-
70	W3	VSYNC	Video Output	O	L	L	V-Sync/Composite-Sync output										-
71	Y2	YOUT7	Video Output	I/O	L	L	Y OUT Signal										-
72	AA1	YOUT6	Video Output	I/O	L	L	Y OUT Signal										-
73	R8	YOUT5	Video Output	I/O	L	L	Y OUT Signal										-
74	P9	YOUT4	Video Output	I/O	L	L	Y OUT Signal										-
75	AA2	YOUT3	Video Output	I/O	L	L	Y OUT Signal										-
76	Y3	YOUT2	Video Output	I/O	L	L	Y OUT Signal										-
77	W4	YOUT1	Video Output	I/O	L	L	Y OUT Signal										-
78	AA3	YOUT0	Video Output	I/O	L	L	Y OUT Signal										-
79	V5	DVDD3	Power	-	-	-	VDD for I/O										-
80	Y4	DGND3	GND	-	-	-	GND for I/O										-
81	V6	COUT7	Video Output	I/O	L	L	C OUT Signal										-
82	W5	COUT6	Video Output	I/O	L	L	C OUT Signal										-
83	Y5	COUT5	Video Output	I/O	L	L	C OUT Signal										-
84	R9	COUT4	Video Output	I/O	L	L	C OUT Signal										-
85	AA5	COUT3	Video Output	I/O	L	L	C OUT Signal										-
86	W6	COUT2	Video Output	I/O	L	L	C OUT Signal										-
87	Y6	COUT1	Video Output	I/O	L	L	C OUT Signal										-
88	V7	COUT0	Video Output	I/O	L	L	C OUT Signal										-
89	W7	CVDD3	Power	-	-	-	VDD for core										-
90	Y7	CGND3	GND	-	-	-	GND for core										-
91	P10	YI7	Video Input	I	I	I	Y IN Signal										Dn
92	V8	YI6	Video Input	I	I	I	Y IN Signal										Dn
93	AA7	YI5	Video Input	I	I	I	Y IN Signal										Dn
94	Y8	YI4	Video Input	I	I	I	Y IN Signal										Dn
95	W8	YI3	Video Input	I	I	I	Y IN Signal										Dn
96	R10	YI2	Video Input	I	I	I	Y IN Signal										Dn
97	Y9	YI1	Video Input	I	I	I	Y IN Signal										Dn
98	V9	YI0	Video Input	I	I	I	Y IN Signal										Dn
99	W9	DGND4	GND	-	-	-	GND for I/O										-
100	AA9	PCLK	Video Input	I	I	I	Pixel Clock										-
101	Y10	DVDD4	Power	-	-	-	VDD for I/O										-
102	P11	HD	Video Input	I/O	I	I	H-Sync										-
103	V10	VD	Video Input	I/O	I	I	V-Sync										-
104	W10	FID	Video Input	I/O	I	I	Field Indicator										-

105	R11	Ci7	Video Input	I	I	I	C IN Signal	Dn
106	V11	Ci6	Video Input	I	I	I	C IN Signal	Dn
107	W11	Ci5	Video Input	I	I	I	C IN Signal	Dn
108	AA11	Ci4	Video Input	I	I	I	C IN Signal	Dn
109	P12	Ci3	Video Input	I	I	I	C IN Signal	Dn
110	R12	Ci2	Video Input	I	I	I	C IN Signal	Dn
111	W12	Ci1	Video Input	I	I	I	C IN Signal	Dn
112	V12	Ci0	Video Input	I	I	I	C IN Signal	Dn
113	R13	PLLVD01	Power	-	-	-	VDD for PLL	-
114	Y12	PLLGND1	GND	-	-	-	GND for PLL	-
115	W13	CGND4	GND	-	-	-	GND for core	-
116	V13	M48X0	Misc.	O	-	-	48MHz X'tal output	-
117	AA13	M48XI	Misc.	I/O	I	I	48MHz X'tal Input	-
118	Y13	CVDD4	Power	-	-	-	VDD for core	-
119	P13	DGND5	GND	-	-	-	GND for I/O	-
120	W14	SYCLK	Misc.	I	I	I	External Clock Input	-
121	Y14	DVDD5	Power	-	-	-	VDD for I/O	-
122	R14	BTSEL	Misc.	I	I	I	ARM Boot Selector	-
123	V14	FLSHSEL	Misc.	I	I	I	Flash ROM Bus Selector	-
124	AA15	EXTHOST	Misc.	I	I	I	EMIF/EHIF Selector	-
125	Y15	IREF	Video DAC	I	I	I	DAC Current Control	-
126	W15	DAOUT	Video DAC	O	O	O	DAC Composite Output	-
127	V16	VSSA	GND	-	-	-	analog GND for DAC	-
128	Y16	VDDA	Power	-	-	-	analog VDD for DAC	-
129	V15	BIAS	Video DAC	I	I	I	DAC Bias with Compensation Capacitor	-
130	W16	VREFIN	Video DAC	I	I	I	DAC Reference Voltage	-
131	AA17	VSS3V	GND	-	-	-	digital GND for DAC	-
132	Y17	VDD3V	Power	-	-	-	digital VDD for DAC	-
133	V17	USB_VDD	Power	-	-	-	VDD for USB	-
134	W17	USB_DP	Communication I/F	I/O	I	I	USB Data Plus	-
135	Y18	USB_DM	Communication I/F	I/O	I	I	USB Data Minus	-
136	P14	CVDD5	Power	-	-	-	VDD for core	-
137	W18	CGND5	GND	-	-	-	GND for core	-
138	AA19	SDR_A14	SDRAM I/F	O	L	L	SDRAM Bank 0	-
139	Y19	SDR_A13	SDRAM I/F	O	L	L	SDRAM Bank 1	-
140	V18	SDR_A12	SDRAM I/F	O	L	L	SDRAM Address(MSB)	-
141	AA20	SDR_A11	SDRAM I/F	O	L	L	SDRAM Address	-
142	W19	SDR_A10	SDRAM I/F	O	L	L	SDRAM Address	-
143	Y20	SDR_A9	SDRAM I/F	O	L	L	SDRAM Address	-
144	AA21	SDR_A8	SDRAM I/F	O	L	L	SDRAM Address	-
145	P15	SDR_A7	SDRAM I/F	O	L	L	SDRAM Address	-
146	N14	SDR_A6	SDRAM I/F	O	L	L	SDRAM Address	-
147	Y21	SDR_A5	SDRAM I/F	O	L	L	SDRAM Address	-
148	W20	SDR_A4	SDRAM I/F	O	L	L	SDRAM Address	-
149	W21	DVDDSD1	Power	-	-	-	VDD for SDRAM I/O	-
150	V19	DGNDSD1	GND	-	-	-	GND for SDRAM I/O	-
151	U18	SDR_A3	SDRAM I/F	O	L	L	SDRAM Address	-
152	V20	SDR_A2	SDRAM I/F	O	L	L	SDRAM Address	-
153	T18	SDR_A1	SDRAM I/F	O	L	L	SDRAM Address	-
154	U19	SDR_A0	SDRAM I/F	O	L	L	SDRAM Address(LSB)	-
155	U20	SDR_DQ31	SDRAM I/F	I/O	I	I	SDRAM Data (MSB)	Dn
156	N15	SDR_DQ30	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
157	U21	SDR_DQ29	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
158	T19	SDR_DQ28	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
159	T20	SDR_DQ27	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
160	R18	SDR_DQ26	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
161	R19	SDR_DQ25	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
162	R20	SDR_DQ24	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
163	M14	CVDD6	Power	-	-	-	VDD for core	-
164	P18	CGND6	GND	-	-	-	GND for core	-
165	R21	SDR_DQ23	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
166	P20	SDR_DQ22	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
167	P19	SDR_DQ21	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
168	M15	SDR_DQ20	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
169	N20	SDR_DQ19	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
170	N18	SDR_DQ18	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
171	N19	SDR_DQ17	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
172	N21	SDR_DQ16	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
173	M20	SDR_DQ15	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
174	L14	SDR_DQ14	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
175	M18	SDR_DQ13	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
176	M19	SDR_DQ12	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
177	L15	DVDDSD2	Power	-	-	-	VDD for SDRAM I/O	-
178	L18	DGNDSD2	GND	-	-	-	GND for SDRAM I/O	-
179	L19	SDR_DQ11	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
180	L21	SDR_DQ10	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
181	K14	SDR_DQ9	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
182	K15	SDR_DQ8	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
183	K19	SDR_DQ7	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
184	K18	SDR_DQ6	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
185	J14	SDR_DQ5	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
186	K20	SDR_DQ4	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
187	J19	SDR_DQ3	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
188	J21	SDR_DQ2	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
189	J18	SDR_DQ1	SDRAM I/F	I/O	I	I	SDRAM Data	Dn
190	J20	SDR_DQ0	SDRAM I/F	I/O	I	I	SDRAM Data (LSB)	Dn
191	J15	CVDD7	Power	-	-	-	VDD for core	-
192	H19	CGND7	GND	-	-	-	GND for core	-
193	H20	SDR_RAS	SDRAM I/F	O	H	H	SDRAM RAS Strobe	-
194	H18	SDR_CAS	SDRAM I/F	O	H	H	SDRAM CAS Strobe	-
195	H15	SDR_WE	SDRAM I/F	O	H	H	SDRAM WE	-
196	G21	SDR_CLK	SDRAM I/F	I/O	L	L	SDRAM I/F	-
197	G20	SDR_CS	SDRAM I/F	O	H	H	SDRAM CS	-
198	G19	SDR_CKE	SDRAM I/F	O	H	H	SDRAM CKE	-
199	G18	SDR_DQMHH	SDRAM I/F	O	H	H	DQMH for SDR_DQ[31:24]	-
200	F20	SDR_DQMLH	SDRAM I/F	O	H	H	DQMH for SDR_DQ[23:16]	-
201	F19	SDR_DQMLH	SDRAM I/F	O	H	H	DQMH for SDR_DQ[15:8]	-
202	H14	SDR_DQMLL	SDRAM I/F	O	H	H	DQMH for SDR_DQ[7:0]	-
203	E21	CFOE	External Memory I/F	O	H	H	CFC Output Enable	-
204	E20	CFE1	External Memory I/F	O	H	H	CFC Enable 1	-
205	E19	CFE2	External Memory I/F	O	H	H	CFC Enable 2	-
206	F18	CFWAIT	External Memory I/F	I	I	I	CFC Wait Signal Input	Up
207	D20	CFRDY	External Memory I/F	I	I	I	CFC Ready	Up
208	D19	IOIS16	External Memory I/F	I	I	I	CFC I/O Select	Up
209	E18	CFIORD	External Memory I/F	O	H	H	CFC I/O Read Strobe	-
210	C21	CFIOWR	External Memory I/F	O	H	H	CFC I/O Write Strobe	-
211	C20	DVDD6	Power	-	-	-	VDD for I/O	-
212	D18	DGND6	GND	-	-	-	GND for I/O	-
213	B21	SD_DATA1	SD/MS Card I/F	I/O	I	I	SD Data 1	-
214	C19	SD_DATA0	SD/MS Card I/F	I/O	I	I	SD Data 0	-
215	B20	SD_CLK	SD/MS Card I/F	O	L	L	SD Clock	-

216	A21	SD_CMD	SD/MS Card I/F	I/O	I	I	SD Command	-
217	G14	SD_DATA3	SD/MS Card I/F	I/O	I	I	SD Data 3	-
218	H13	SD_DATA2	SD/MS Card I/F	I/O	I	I	SD Data 2	-
219	A20	CVDD8	Power	-	-	-	VDD for core	-
220	B19	CGND8	GND	-	-	-	GND for core	-
221	C18	EM_WE	External Memory I/F	I/O	H	I	External Memory Write Enable	-
222	A19	EM_OE	External Memory I/F	I/O	H	I	External Memory Output Enable	-
223	D17	EM_WAIT	External Memory I/F	I/O	I	I	External Memory Wait	-
224	B18	EM_BEL	External Memory I/F	O	H	H	External Memory Byte Enable Low	-
225	D16	EM_BEH	External Memory I/F	O	H	H	External Memory Byte Enable High	-
226	C17	EM_CEO	External Memory I/F	I/O	H	I	External Memory Chip Enable #1	-
227	B17	EM_CEO	External Memory I/F	O	H	H	External Memory Chip Enable #2	-
228	G13	EM_RDWR	External Memory I/F	O	H	H	External Memory Read/Write	-
229	A17	DVDD7	Power	-	-	-	VDD for I/O	-
230	C16	MXO	Misc.	O	-	-	X'tal Output	-
231	B16	MXI	Misc.	I/O	-	-	X'tal Input	-
232	D15	DGND7	GND	-	-	-	GND for I/O	-
233	C15	PLLVDD2	Power	-	-	-	VDD for PLL	-
234	B15	PLLGND2	GND	-	-	-	GND for PLL	-
235	H12	TEST4	Misc.	I	I	I	Test Input4 (INITZ)	Up
236	D14	FLSH_CE	External Memory I/F	O	H	H	Flash ROM Chip Enable	-
237	A15	BUSWIDTH	External Memory I/F	I	I	I	8/16 bit select for FLSH_CEH	-
238	B14	CVDD9	Power	-	-	-	VDD for core	-
239	C14	CGND9	GND	-	-	-	GND for core	-
240	G12	ARM_D15	External Memory I/F	I/O	I	I	External Memory Data (MSB)	-
241	B13	ARM_D14	External Memory I/F	I/O	I	I	External Memory Data	-
242	D13	ARM_D13	External Memory I/F	I/O	I	I	External Memory Data	-
243	C13	ARM_D12	External Memory I/F	I/O	I	I	External Memory Data	-
244	A13	ARM_D11	External Memory I/F	I/O	I	I	External Memory Data	-
245	B12	ARM_D10	External Memory I/F	I/O	I	I	External Memory Data	-
246	H11	ARM_D9	External Memory I/F	I/O	I	I	External Memory Data	-
247	D12	ARM_D8	External Memory I/F	I/O	I	I	External Memory Data	-
248	C12	ARM_D7	External Memory I/F	I/O	I	I	External Memory Data	-
249	G11	DVDD8	Power	-	-	-	VDD for I/O	-
250	D11	DGND8	GND	-	-	-	GND for I/O	-
251	C11	ARM_D6	External Memory I/F	I/O	I	I	External Memory Data	-
252	A11	ARM_D5	External Memory I/F	I/O	I	I	External Memory Data	-
253	H10	ARM_D4	External Memory I/F	I/O	I	I	External Memory Data	-
254	G10	ARM_D3	External Memory I/F	I/O	I	I	External Memory Data	-
255	C10	ARM_D2	External Memory I/F	I/O	I	I	External Memory Data	-
256	D10	ARM_D1	External Memory I/F	I/O	I	I	External Memory Data	-
257	H9	ARM_D0	External Memory I/F	I/O	I	I	External Memory Data (LSB)	-
258	B10	CVDD10	Power	-	-	-	VDD for core	-
259	C9	CGND10	GND	-	-	-	GND for core	-
260	A9	ARM_A22	External Memory I/F	I/O	L	I	External Memory Address (MSB)	-
261	D9	ARM_A21	External Memory I/F	I/O	L	I	External Memory Address	-
262	B9	ARM_A20	External Memory I/F	I/O	L	I	External Memory Address	-
263	G9	ARM_A19	External Memory I/F	I/O	L	I	External Memory Address	-
264	C8	ARM_A18	External Memory I/F	I/O	L	I	External Memory Address	-
265	B8	ARM_A17	External Memory I/F	I/O	L	I	External Memory Address	-
266	D8	ARM_A16	External Memory I/F	I/O	L	I	External Memory Address	-
267	G8	ARM_A15	External Memory I/F	I/O	L	I	External Memory Address	-
268	A7	ARM_A14	External Memory I/F	I/O	L	I	External Memory Address	-
269	B7	DVDD9	Power	-	-	-	VDD for I/O	-
270	C7	DGND9	GND	-	-	-	GND for I/O	-
271	D7	ARM_A13	External Memory I/F	I/O	L	I	External Memory Address	-
272	B6	ARM_A12	External Memory I/F	I/O	L	I	External Memory Address	-
273	C6	ARM_A11	External Memory I/F	I/O	L	I	External Memory Address	-
274	H8	ARM_A10	External Memory I/F	I/O	L	I	External Memory Address	-
275	A5	ARM_A9	External Memory I/F	I/O	L	I	External Memory Address	-
276	B5	ARM_A8	External Memory I/F	I/O	L	I	External Memory Address	-
277	C5	ARM_A7	External Memory I/F	I/O	L	I	External Memory Address	-
278	D6	ARM_A6	External Memory I/F	I/O	L	I	External Memory Address	-
279	B4	CVDD11	Power	-	-	-	VDD for core	-
280	C4	CGND11	GND	-	-	-	GND for core	-
281	D5	ARM_A5	External Memory I/F	I/O	L	I	External Memory Address	-
282	A3	ARM_A4	External Memory I/F	I/O	L	I	External Memory Address	-
283	B3	ARM_A3	External Memory I/F	I/O	L	I	External Memory Address	-
284	D4	ARM_A2	External Memory I/F	I/O	L	I	External Memory Address	-
285	A2	ARM_A1	External Memory I/F	I/O	L	I	External Memory Address	-
286	C3	ARM_A0	External Memory I/F	I/O	L	I	External Memory Address (LSB)	-
287	B2	EMU0	Misc.	I/O	I	I	Emulator Interrupt0	-
288	A1	EMU1	Misc.	I/O	I	I	Emulator Interrupt1	-

Dn	Pulled down during reset.
DGNDx/CGNDx	Common GND in substrate
DGNDx	
SDRAM I/F	