Online Prescribed Error Sensitivity Decoder Learning in Neuromorphic Residual UAV Attitude Control

Gandhi Contreras Torres[1], Steven Sandoval[1], and Luis Rodolfo Garcia Carrillo[2]

***Abstract*— Quadrotor attitude controllers must track time-varying references while respecting coupled rotor-force limits under uncertainty, noise, and disturbances. We introduce an online neuromorphic residual in which six continuous membrane–gate (CMG) units generate temporal features and eighteen decoder weights adapt online via prescribed error sensitivity (PES). The residual adds a bounded correction to a saturated quaternion PD controller before rotor-force allocation, enforces explicit authority bounds, recovers the baseline exactly when disabled, and uses a saturation-aware output gate that prevents opposing an axis already at its torque limit. Against a bandwidth-tuned PD with desired-rate feedforward (PD+ff), the gated residual reduces geometric-mean attitude error by 37.3% (X2) and 22.4% (CF2) noise-free, and reduces error during repeated torque disturbances by 14% and 6%; with sensor noise it preserves 4–11% gains on multi-axis missions and is neutral or slightly negative at the noise floor. Under the same tuned PD+ff baseline, an Izhikevich basis increases geometric-mean error by 18.9% (X2) and 5.4% (CF2) at about twice the realized CMG effort; ablations trace the benefit to the graded sub-threshold CMG regime, where a reduced, non-latching CMG reaches 46.3% (X2) and 28.6% (CF2) at comparable effort. The residual can be paired directly with LQR, sliding-mode, and model-predictive baselines, and in simulation improves tracking across the tested families and platforms.**

I. Introduction

Classical feedback provides an interpretable stabilizing backbone for quadrotor attitude control, but unmodeled effects and abrupt disturbances can leave structured tracking errors that are hard to remove without retuning or increasing actuator demand. Residual control adds an adaptive correction around an existing feedback law while preserving its plant and actuator interface.

Residual learning has been paired with classical controllers in robotics [1], including geometric $\mathcal{L}_1$ quadrotor augmentation [2]. Related brain-inspired UAS controllers combine model-based feedback with learned terms [3], [4]. Neuromorphic platforms support stateful adaptive corrections through the Neural Engineering Framework and online decoder learning [5], [6], commonly using the local prescribed-error-sensitivity (PES) rule [7]. NEF-based spiking controllers have been designed for quadrotor dynamics with fixed, not online-adapted, weights [8]. More recently, self-tuning spiking PID control has been demonstrated for a quadrotor [9]. Continuous membrane–gate features for actuator-aware quaternion residual control, and the separate roles of neuron dynamics and decoder learning, remain insufficiently characterized. This gap is especially relevant for real-time execution: CMG dynamics are continuous and integrated with a fixed-step update (Sec. III), and PES adaptation uses only instantaneous error and activity, avoiding backpropagation-through-time overhead [7], [10].

We study a bounded online residual controller for quaternion UAV attitude tracking under individual rotor-force limits. A saturated quaternion PD(+ff) baseline supplies the nominal torque request, and a neuromorphic CMG–PES module provides a compact stateful residual via six CMG units and an eighteen-parameter PES decoder. The contributions are: (i) a bounded residual interface for attitude-torque augmentation with explicit authority limits and exact baseline-command recovery at zero residual authority (Fig. 1); (ii) a saturation-aware gate that prevents the residual from opposing an axis already at the prescribed torque limit; (iii) a two-platform, five-mission simulation study against fixed and bandwidth-tuned baselines (PD+ff primary), including measurement-noise and repeated-disturbance tests, portability across conventional controller families without per-mission retuning, and mechanism ablations that isolate decoder adaptation, conductance, activity gain, and gate latching; and (iv) a fully specified CMG–PES realization with paired nonnegative activity, bounded readout, and online local adaptation.

The remainder of this paper is organized as follows. Section II formulates the problem. Section III presents the proposed controller and the bounded-interface result, with discussion in Section IV and proofs in Section V. Section VI reports the numerical experiments, and Section VII concludes and outlines future work.

II. Problem Formulation

We seek to reduce shortest-path attitude-tracking error for a prescribed reference $q_d(t)$ while respecting coupled actuator limits induced by individual rotor-force bounds. A baseline attitude law (e.g., PD+ff, LQR, SMC, MPC/NMPC) produces a requested body torque $\boldsymbol{u}_0$; the proposed neuromorphic residual may add a bounded correction to form $\boldsymbol{u}$, after which the same rotor allocator and per-rotor saturation produce the realized actuator torque $\boldsymbol{\tau}_{\mathrm{act}}$ (objective stated in Sec. II-C).

A. Process, State, and Tracking Error

Let $Q \in \mathbb{S}^3$ be the scalar-first Hamilton quaternion mapping body to inertial coordinates, and let $\boldsymbol{\omega}$ be the body

[1]New Mexico State University (NMSU), Las Cruces, NM, USA.

[2] Space Vehicles Directorate, Air Force Research Laboratory (AFRL), Kirtland Air Force Base (KAFB), Albuquerque, NM 87108. Email: luis_rodolfo.garcia_carrillo@afrl.af.mil

angular velocity. The rotational dynamics are [11]

$$\dot{Q} = \tfrac{1}{2} Q \otimes [0, \boldsymbol{\omega}^\mathsf{T}]^\mathsf{T}, \tag{1}$$

$$\boldsymbol{J}\dot{\boldsymbol{\omega}} = \boldsymbol{\tau}_{\mathrm{act}} + \boldsymbol{\tau}_{\mathrm{p}} + \boldsymbol{\tau}_{\mathrm{d}} - \boldsymbol{\omega} \times (\boldsymbol{J}\boldsymbol{\omega}). \tag{2}$$

where $\boldsymbol{J} \succ 0$ is the body-frame inertia, $\boldsymbol{\tau}_{\mathrm{act}}$ is the actuator torque, and $\boldsymbol{\tau}_{\mathrm{p}}, \boldsymbol{\tau}_{\mathrm{d}}$ denote modeled passive and externally applied disturbance torques. The controller produces a requested body torque $\boldsymbol{u}$, mapped to $\boldsymbol{\tau}_{\mathrm{act}}$ through the rotor allocation and force constraints of Sec. II-B.

Using the corresponding passive quaternion $q = Q^{-1}$ [12], define

$$\dot{q} = -\tfrac{1}{2}[0, \boldsymbol{\omega}^\mathsf{T}]^\mathsf{T} \otimes q. \tag{3}$$

The desired attitude q_d uses the same convention. Define the attitude error

$$q_e = q_d \otimes q^{-1} = [q_{e,0}, \boldsymbol{q}_{e,v}^\mathsf{T}]^\mathsf{T}, \tag{4}$$

$$\boldsymbol{e}_q = \mathrm{sgn}_+(q_{e,0})\boldsymbol{q}_{e,v}, \qquad \mathrm{sgn}_+(0) = 1, \tag{5}$$

$$\theta_q = 2\,\mathrm{atan2}(\|\boldsymbol{q}_{e,v}\|_2, |q_{e,0}|) \in [0, \pi]. \tag{6}$$

The metric θ_q is invariant to quaternion sign. No continuous feedback globally stabilizes rigid-body attitude [13]; we use the shortest-path branch away from the 180° boundary.

For a desired-frame rate $\boldsymbol{\omega}_d$ satisfying the corresponding passive kinematics,

$$\dot{q}_e = \tfrac{1}{2} q_e \otimes [0, \boldsymbol{\omega}_e^\mathsf{T}]^\mathsf{T}, \tag{7}$$

$$\boldsymbol{\omega}_e = \boldsymbol{\omega} - R(q_e)^\mathsf{T}\boldsymbol{\omega}_d, \qquad \dot{q}_{e,0} = -\tfrac{1}{2}\boldsymbol{q}_{e,v}^\mathsf{T}\boldsymbol{\omega}_e. \tag{8}$$

These relations follow directly from quaternion error kinematics, where $R(q) \in SO(3)$ denotes the rotation matrix corresponding to quaternion q.

Let $\boldsymbol{J} \succ 0$ denote the body-frame inertia [11]. If principal moments $\boldsymbol{j}_{\mathrm{p}}$ are given in a rotated principal-axis frame, then

$$\boldsymbol{J} = R_{BI}\,\mathrm{diag}(\boldsymbol{j}_{\mathrm{p}})R_{BI}^\mathsf{T}, \tag{9}$$

with R_{BI} the principal-to-body rotation. Controller gains use the reported principal moments in their given ordering, $\boldsymbol{j}_{\mathrm{tune}}$ (Table I).

B. Actuation and State Measurements

For rotor positions $\boldsymbol{p}_i$ in body coordinates, parallel $+z$ thrust axes, and signed reaction coefficients κ_i, define

$$B = \begin{bmatrix} 1 & 1 & 1 & 1 \\ p_{1,y} & p_{2,y} & p_{3,y} & p_{4,y} \\ -p_{1,x} & -p_{2,x} & -p_{3,x} & -p_{4,x} \\ \kappa_1 & \kappa_2 & \kappa_3 & \kappa_4 \end{bmatrix}. \tag{10}$$

The signs follow $\boldsymbol{p}_i \times [0, 0, f_i]^\mathsf{T}$ and the reaction torque $\kappa_i f_i$ [14]. Given collective thrust T and body-torque command $\boldsymbol{u}$, inverse allocation with per-rotor saturation is

$$\begin{aligned} \boldsymbol{f}_{\mathrm{req}} &= B^{-1}[T, \boldsymbol{u}^\mathsf{T}]^\mathsf{T}, \\ \boldsymbol{f}_{\mathrm{act}} &= \mathrm{sat}_{[\boldsymbol{0}, \boldsymbol{f}_{\max}]}(\boldsymbol{f}_{\mathrm{req}}), \\ [T_{\mathrm{act}}, \boldsymbol{\tau}_{\mathrm{act}}^\mathsf{T}]^\mathsf{T} &= B\boldsymbol{f}_{\mathrm{act}}. \end{aligned} \tag{11}$$

Here $\boldsymbol{u} = \boldsymbol{u}_0$ for PD; the residual modifies the same request before the same allocator. Exact wrench realization requires $B^{-1}[T, \boldsymbol{u}^\mathsf{T}]^\mathsf{T} \in [\boldsymbol{0}, \boldsymbol{f}_{\max}]$, so a componentwise torque box is not generally feasible under individual rotor limits; we therefore use inverse allocation with saturation rather than optimization-based allocation [15].

Collective thrust remains classical, with $z_d = 1$ m:

$$T = \mathrm{sat}_{[0, 2.5Mg]}\left(\frac{M[g + 6(z_d - z) - 4\dot{z}]}{\max(R(Q)_{33}, 0.35)}\right). \tag{12}$$

Here g is the gravitational acceleration. The height loop reads altitude and vertical velocity; the denominator compensates tilt. The guard 0.35 limits tilt compensation to about $\arccos(0.35) \approx 69.5^\circ$, and the upper bound does not supersede individual rotor limits. The residual has no direct collective output but can affect height through attitude, tilt compensation, and saturation. The attitude and height loops use only q, $\boldsymbol{\omega}$, z, and $\dot{z}$, read from the model except in Sec. VI-E, which perturbs the measured attitude and rate; the residual receives no additional state.

C. Quaternion PD Baselines and Control Objective

The quaternion PD baseline is

$$\boldsymbol{k}_q = 2\boldsymbol{j}_{\mathrm{tune}} \odot \boldsymbol{\omega}_n^2, \qquad \boldsymbol{k}_\omega = 2\zeta\boldsymbol{j}_{\mathrm{tune}} \odot \boldsymbol{\omega}_n, \tag{13}$$

$$\boldsymbol{u}_0 = \mathrm{sat}_{\boldsymbol{\ell}}(-\boldsymbol{k}_q \odot \boldsymbol{e}_q - \boldsymbol{k}_\omega \odot \boldsymbol{\omega}), \tag{14}$$

where $\odot$ denotes elementwise multiplication and $\mathrm{sat}_{\boldsymbol{\ell}}$ saturates componentwise to $[-\ell_i, \ell_i]$. With $\boldsymbol{\omega}_n = (4, 4, 3.5)^\mathsf{T}$ rad/s and $\zeta = 0.95$, the commanded-torque box is $\mathcal{U} = \prod_{i=1}^3 [-\ell_i, \ell_i]$, with $\ell_i = \max(j_{\mathrm{tune},i}\nu_i, 10^{-6}\ \mathrm{N\,m})$ and $\boldsymbol{\nu} = (12, 12, 10)^\mathsf{T}$ rad/s^2; rotor limits can still bind through allocation (11).

Since the derivative term in (14) damps absolute body rate, we also consider a PD baseline with desired-rate feedforward (PD+ff), obtained by replacing $\boldsymbol{\omega}$ with the frame-aligned rate-tracking error $\boldsymbol{\omega}_e$ of (8)

$$\boldsymbol{u}_0^{\mathrm{ff}} = \mathrm{sat}_{\boldsymbol{\ell}}\big(-\boldsymbol{k}_q \odot \boldsymbol{e}_q - \boldsymbol{k}_\omega \odot \boldsymbol{\omega}_e\big). \tag{15}$$

The reported runs damp $\boldsymbol{\omega} - \boldsymbol{\omega}_d$, which differs from $\boldsymbol{\omega}_e$ by at most $\theta_q\|\boldsymbol{\omega}_d\|$; with $\boldsymbol{\omega}_e$ the primary result of Sec. VI-B becomes $37.4\%/22.5\%$, and the $\rho = 1$ rows of Table II and the LQR, PID+ff, SMC, and MPC results change by at most 0.5 pp.

The design objective is therefore: given the classical torque request $\boldsymbol{u}_0$, construct an online residual correction that reduces θ_q over time-varying missions while (i) retaining the same attitude and angular rate measurements, collective-thrust loop, rotor allocator, and actuator limits, (ii) imposing an explicit componentwise bound on the deviation from $\boldsymbol{u}_0$, and (iii) recovering the requested baseline exactly when residual authority is set to zero. These implementation properties do not guarantee closed-loop stability.

III. Main Result: Online Neuromorphic Residual Controller

The proposed control framework decouples the adaptive internal dynamics from a bounded residual correction added to the baseline torque command. By setting the residual authority $\beta = 0$, the controller recovers the exact baseline torque request. Figure 1 details the overall signal flow.




Fig. 1. CMG-PES neuromorphic residual control architecture with online PES decoder learning. The classical feedback, collective-thrust, allocation, and plant interfaces are retained; only the bounded decoder output augments the requested attitude torque, after the saturation-aware gate (28) masks any component that opposes a saturated baseline axis.




Fig. 2. Coupling topology of one CMG unit, cf. (19). The membrane sets the gate target; the gate acts back twice, shifting its own threshold through γ and shunting the membrane through $c_j \propto r_j^2$ ($\chi = 1$ makes that shunt input dependent). The dynamics are continuous: no spike, no reset, and only a_j leaves the unit.

A. CMG Temporal Features

For m torque channels and $2m$ units, normalize the saturated baseline and form positive/negative current pairs:

$$\begin{aligned} \bar{\boldsymbol{u}} &= \boldsymbol{u}_0 \oslash \boldsymbol{\ell}, \\ \boldsymbol{I}^{\pm} &= I_b \mathbf{1} + I_g \max(\pm \bar{\boldsymbol{u}}, \mathbf{0}), \\ \boldsymbol{I} &= [(\boldsymbol{I}^+)^\mathsf{T}, (\boldsymbol{I}^-)^\mathsf{T}]^\mathsf{T}. \end{aligned} \tag{16}$$

Here $\oslash$ denotes elementwise division and $\mathbf{0}, \mathbf{1}$ denote all-zeros/all-ones vectors of compatible dimension. Each unit has a dimensionless membrane state v_j and gate r_j:

$$\dot{r}_j = [\sigma(\alpha_h(v_j - v_{\mathrm{th}} + \gamma r_j)) - r_j]/\tau_r, \tag{17}$$

$$\dot{v}_j = -(v_j - v_{\mathrm{rest}})/\tau + I_j/\tau - c_j(v_j - v_{\mathrm{reset}}), \tag{18}$$

$$c_j = (g_0 + \chi g_1 |I_j|) r_j^2, \qquad \chi \in \{0, 1\}. \tag{19}$$

Here $\sigma(x) = (1 + e^{-x})^{-1}$ denotes the logistic sigmoid, which bounds the gate activation to $(0, 1)$.

The gate dynamics in (19) are a first-order relaxation: the bounded sigmoid output $\sigma(\alpha_h(v_j - v_{\mathrm{th}} + \gamma r_j)) \in (0, 1)$ provides an instantaneous reference level that depends on membrane voltage and is modulated by feedback from the current gate state. The gate state r_j then relaxes toward that time-varying reference with time constant τ_r. In parallel, r_j modulates membrane conductance through $c_j \propto r_j^2$ (Fig. 2), so both states participate even though the decoder reads only the gate-derived activity. The model has no threshold-triggered reset or spike event; v_{reset} is a reversal level in a continuous conductance term. The gains g_0, g_1 have the units needed to make c_j a rate.

The actual integration is sequential, not exponential Euler for both states. From the old states compute

$$b_{j,k} = \sigma\big(\mathrm{sat}_{[-60,60]}[\alpha_h(v_{j,k} - v_{\mathrm{th}} + \gamma r_{j,k})]\big)\,, \tag{20}$$

$$r_{j,k}^+ = \mathrm{sat}_{[0,1]}[r_{j,k} + (h/\tau_r)(b_{j,k} - r_{j,k})]. \tag{21}$$

Then evaluate $c_{j,k} = (g_0 + \chi g_1 |I_{j,k}|)(r_{j,k}^+)^2$, $\lambda_{j,k} = \tau^{-1} + c_{j,k}$, and $d_{j,k} = (v_{\mathrm{rest}} + I_{j,k})/\tau + c_{j,k} v_{\mathrm{reset}}$. By holding $\lambda_{j,k}$ and $d_{j,k}$ constant over one integration interval h, the membrane equation is affine in v_j and integrates exactly to

$$v_{j,k}^+ = e^{-\lambda_{j,k} h} v_{j,k} + (1 - e^{-\lambda_{j,k} h}) d_{j,k}/\lambda_{j,k}. \tag{22}$$

The coefficients are recomputed at the start of the next numerical step; (22) is therefore an exact per-step exponential update under that within-step hold, guaranteeing a non-divergent numerical update within the interval. However, this local step formulation does not establish closed-loop stability for the fully coupled, nonlinear UAV dynamics and adaptive controller. Assign $(v_{j,k+1}, r_{j,k+1}) = (v_{j,k}^+, r_{j,k}^+)$. The exponential-Euler step $r_{j,k}^+ = e^{-h/\tau_r} r_{j,k} + (1 - e^{-h/\tau_r}) b_{j,k}$ is convex for every $h > 0$ without saturation, and changes only the weight on $r_{j,k}$ (0.905 vs. 0.9 at $h/\tau_r = 0.1$); all simulation benchmarks in Section VI use (21).

B. PES Decoder Adaptation and Bounded Residual

The within-step activity, initial decoder, and saturated readout are

$$\begin{aligned} \boldsymbol{a}_k &= \mathrm{sat}_{[0,1]}(G \boldsymbol{r}_k^+), \qquad W_0 = [I_m, -I_m], \\ \boldsymbol{s}_k &= \mathrm{sat}_{[-1,1]}(W_k \boldsymbol{a}_k). \end{aligned} \tag{23}$$

The initial readout matrix $W_0 = [I_3, -I_3]$ implements paired-channel subtraction $(a^+ - a^-)$, recovering signed

directional information from a nonnegative activity basis; state memory can delay sign reversal following a command reversal. With $G = 10^5$, the nonnegative activity $a_j = \mathrm{sat}_1(Gr_j^+)$ reaches its upper bound of 1 when $r_j^+ \geq 10^{-5}$. Since $r_j^+ \geq 0$, the symmetric saturation sat_1 acts here over $[0, 1]$. Thus, the activity gain G determines how strongly r_j^+ is amplified before the readout decoder and how quickly the resulting activity saturates. Define the (baseline-derived) adaptation reference $\boldsymbol{y}_k^* \in [-1, 1]^m$ and the adaptation error $\boldsymbol{\varepsilon}_k \in \mathbb{R}^m$, with gains $k_e \geq 0$ and $k_\omega^* \geq 0$ weighting attitude and rate error, respectively (all reported runs use $k_\omega^* = 0$, so $\boldsymbol{y}_k^*$ depends on $\boldsymbol{e}_{q,k}$ only):

$$\boldsymbol{y}_k^* = \mathrm{sat}_{[-1,1]}(-k_e \boldsymbol{e}_{q,k} - k_\omega^* \boldsymbol{\omega}_{e,k}), \tag{24}$$

$$\boldsymbol{\varepsilon}_k = \boldsymbol{y}_k^* - \boldsymbol{s}_k, \tag{25}$$

$$W_{k+1} = \Pi_{\mathcal{W}}[W_k + \eta \boldsymbol{\varepsilon}_k \boldsymbol{a}_k^\mathsf{T} - \lambda_W W_k]. \tag{26}$$

Here $\mathcal{W} = [-W_{\max}, W_{\max}]^{m \times 2m}$ and $\Pi_{\mathcal{W}}$ denotes entry-wise projection (clipping) onto $\mathcal{W}$; η and λ_W are per-step. PES is a local error-driven update and does not differentiate through the plant or claim to minimize a closed-loop cost.

Using W_k before the update, the requested command is

$$\boldsymbol{u}_k = \mathrm{sat}_{\boldsymbol{\ell}}(\boldsymbol{u}_{0,k} + \beta \boldsymbol{\ell} \odot \boldsymbol{s}_k), \quad \boldsymbol{\delta}_k = \boldsymbol{u}_k - \boldsymbol{u}_{0,k}, \quad 0 \leq \beta \leq 1. \tag{27}$$

For three-axis UAV attitude control ($m = 3$), the network consists of six CMG units and eighteen decoder weights.

a) Saturation-aware gate: At $|u_{0,k,i}| = \ell_i$ the residual acts one-sidedly: a component with the sign of $u_{0,k,i}$ is saturated away, whereas an opposing one removes up to $\beta \ell_i$ of authority exactly when the loop needs all of it. The gated residual therefore replaces $\boldsymbol{s}_k$ in (27) by

$$\tilde{s}_{k,i} = \begin{cases} 0, & |u_{0,k,i}| \geq \ell_i \text{ and } s_{k,i} u_{0,k,i} < 0, \\ s_{k,i}, & \text{otherwise}, \end{cases} \tag{28}$$

and leaves the PES update (26) untouched. Because PES uses the ungated residual $\boldsymbol{s}_k$ rather than the physically applied $\tilde{s}_{k,i}$, the mask never enters $\boldsymbol{\varepsilon}_k$, an implicit anti-windup property: the gate cannot by itself wind up the decoder. PES still adapts on a blocked axis, which leaves the settling tail of Sec. VI-F; freezing those rows instead gave the same X2 Hardstep result in development (-2.1% vs. -2.0%). Since $|\tilde{s}_{k,i}| \leq |s_{k,i}|$, the gate cannot increase the residual magnitude and introduces no additional tuning parameter. The resulting interface bounds and baseline-recovery property are established formally in Proposition 1.

Proposition 1 (Bounded residual interface and baseline recovery)**.** *Assume the nonnegative CMG parameters of Table I, $r_{j,0} \in [0, 1]$, $0 < h \leq \tau_r$, $W_0 \in \mathcal{W}$, and $\boldsymbol{u}_{0,k} \in \mathcal{U}$. Then: (i) every gate remains in $[0, 1]$ and each membrane iterate remains in the convex hull of its initial value, v_{reset}, and $[v_{\mathrm{rest}} + I_b, v_{\mathrm{rest}} + I_b + I_g]$; (ii) the projected update keeps $W_k \in \mathcal{W}$; and (iii) $\boldsymbol{u}_k \in \mathcal{U}$ with $|\delta_{k,i}| \leq \beta \ell_i$. If $\beta = 0$, the requested baseline command is recovered at every step, and the same allocator at the same state and collective thrust produces the same actuator output.*

Remark 1 (Interpretation of Bounds): The bounds in (i)–(ii) keep the adaptive CMG/PES states within their prescribed operational domains. In contrast, property (iii) is directly exposed to the closed-loop system: it bounds the residual torque modification and guarantees exact recovery of the baseline command when $\beta = 0$, independently of the learned internal state.

IV. Discussion of the Main Result

Proposition 1 establishes implementation bounds that hold for every $\beta \in [0, 1]$, hence for the gated controller actually used in the experiments. Its scope is deliberately limited: it is an operational interface bound, not an input-to-state stability guarantee, and bounded internal states, weights, and requested torque do not establish state safety, rotor headroom, closed-loop stability, or improved tracking. Rotor-force saturation can also couple requested torque components, so the componentwise residual bound is not a trajectory-to-trajectory robustness guarantee.

A restricted fixed-feature PES contraction observation is summarized in Sec. VI-C (Remark 2) and is used only to interpret activity-limited learning behavior; it is not a closed-loop convergence result.

V. Proofs

Proof of Proposition 1. For the gate update, $b_{j,k} \in [0, 1]$ and $0 < h \leq \tau_r$ make the unsaturated Euler step a convex combination of $r_{j,k}$ and $b_{j,k}$; the componentwise saturation in (21) therefore preserves $r_{j,k} \in [0, 1]$. Since $I_j \in [I_b, I_b + I_g]$ and $c_j \geq 0$, d_j/λ_j is a convex combination of $v_{\mathrm{rest}} + I_j$ and v_{reset}. Equation (22) is a convex combination of $v_{j,k}$ and d_j/λ_j, so induction gives the membrane bound. Projection in (26) gives $W_k \in \mathcal{W}$. Finally, the outer saturation in (27) gives $\boldsymbol{u}_k \in \mathcal{U}$; componentwise nonexpansiveness and $\mathrm{sat}_{\ell_i}(u_{0,k,i}) = u_{0,k,i}$ imply $|\delta_{k,i}| \leq |\beta \ell_i s_{k,i}| \leq \beta \ell_i$. Setting $\beta = 0$ gives $\boldsymbol{u}_k = \boldsymbol{u}_{0,k}$, after which the common allocator produces the same actuator output at the same state and collective thrust. □

VI. Application and Examples

A. Platforms, Missions, and Metrics

States, torques, and rotor geometry are expressed in body axes; inertia follows (9). We evaluate in MuJoCo rigid-body simulation with site-applied actuator wrenches [16] using two Menagerie-derived multirotors (CF2, X2; Fig. 3) [17]. The attitude loop commands body torque and the height loop collective thrust; CF2 uses the inverse allocator with per-rotor saturation (11). Table I lists model and interface values. To avoid permanent rotor saturation under the tuned baseline, CF2's per-rotor force limit is raised $1.5\times$ relative to the Menagerie model ($0.0875 \rightarrow 0.13125$ N); X2 uses its model limit unchanged. Both models omit motor/RPM/battery/aero states; feedback uses `qpos`/`qvel`, with noise only in Sec. VI-E. Controllers run in Nengo 4.1.0 (custom `NeuronType`, one-step adaptation latency); a direct NumPy implementation matches within 2.013×10^{-6} relative mean error over ten cases. Code and run archives



Fig. 3. Vehicles and simulation models. Left: CF2 hardware and MuJoCo model. Center: X2 hardware and MuJoCo model. Right: both geometries at relative scale.

TABLE I

MODEL/INTERFACE PARAMETERS (TOP) AND CANONICAL CMG–PES SETTINGS (BOTTOM). NEURAL QUANTITIES ARE NORMALIZED MODEL VARIABLES; LEARNING COEFFICIENTS ARE PER STEP.

Parameter	CF2 rotor model	X2 model
Mass M (kg)	0.027	1.325
Rotor $\lvert p_x\rvert, \lvert p_y\rvert$ (m)	$0.0325, 0.0325$	$0.14, 0.18$
Reaction magnitude $\lvert\kappa_i\rvert$ (m)	0.005	0.0201
Rotor force limit (N)	$.0875 \to .13125$	13
$\boldsymbol{j}_{\text{tune}}$ (10^{-5} kg m^2)	$(2.3951, 2.3951, 3.2347)$	—
$\boldsymbol{j}_{\text{tune}}$ (10^{-2} kg m^2)	—	$(6.0711, 3.6468, 2.5412)$
Rigid-body integrator	RK4	Euler

CMG–PES	Value		Value
h, duration	0.0005 s, 45 s	$\alpha_h, \gamma, g_0, g_1$	$50, 2, 120, 30$
τ, τ_r	0.05 s, 0.005 s	I_b, I_g, G	$0.75, 1.25, 10^5$
$v_{\text{rest}}, v_{\text{reset}}, v_{\text{th}}$	$0, 0, 1$	$\beta_{\text{X2}}, \beta_{\text{CF2}}; \eta$	$.5, .2; 8 \times 10^{-4}$
$v_{j,0}, r_{j,0}, \chi$	$0, 0, 1$	$\lambda_W, W_{\max}, k_e, k_\omega^*$	$10^{-6}, 6, 8, 0$

accompany the submission as a reproducibility package.[1]

CF2 body axes are principal. For X2, $\boldsymbol{J} = 10^{-2}[3.66517, 0, -.21000;\ 0, 2.54117, 0;\ -.21000, 0, 6.05280]$ kg m^2; torque limits use $\boldsymbol{j}_{\text{tune}}$.

Each PD/CMG pair shares initial state, reference, duration, allocator, model, and timestep. Residual authority is $\beta = .5$ (X2) and $\beta = .2$ (CF2); the gate (28) is used for the $\rho = 3$ results. Without the gate, a predeclared sweep over $\beta \in \{.5, .2, .1, .05, .02\}$ admits only $\beta = .05$ on CF2 (larger values diverge on Hardstep, Sec. VI-F). Under measurement noise (Sec. VI-E), $\beta = .2$ is the largest safe sweep value (chosen on two development seeds, confirmed on 13 held-out ones). The $\rho = 1$ and fixed-PD rows of Table II are ungated. The primary campaign is deterministic (no disturbances/noise), one run per cell, with learning active throughout.

Tracking is scored by $\bar{\theta}_q = \frac{1}{N}\sum_{k=1}^{N}\theta_{q,k}$ (mrad; $1\,\text{mrad} \approx 0.0573°$) and the relative reduction $100(\bar{\theta}_{q,\text{PD}} - \bar{\theta}_{q,\text{CMG}})/\bar{\theta}_{q,\text{PD}}$. Missions are specified as Euler triples and converted to $q_d(t)$ (feedback remains quaternion based): Roll $(0.25\sin 0.7t, 0, 0)$; Full3 $0.5\sin(t + (0, \pi/2, \pi)^\mathsf{T})$; Hard45 $(0.55\sin 0.75t + 0.20\sin(2.10t{+}0.40),\ 0.45\sin(0.95t{+}\pi/3){+}0.18\sin 1.75t,\ 0.65\sin(0.55t + \pi) + 0.25\sin(1.35t + 0.20))$; Hardstep: 0 for 1 s then 2-s cycles through $(.75, -.45, .55)$, $(-.65, .55, -.70)$, $(.50, .50, .90)$, $(-.80, -.35, .20)$; Yaw360 $(0, 0, 2\pi(3\xi^2 - 2\xi^3))$, $\xi = t/45$. Hover is used only for the disturbance test.

[1] https://github.com/gandhico/online-pes-neuromorphic-residual-control




Fig. 4. X2 Hard45 tracking (45 s) across the baseline ladder. Blue: PD baselines (light→dark: fixed PD, PD+ff ρ=1, tuned PD+ff ρ=3). Red: CMG–PES paired with each baseline (matched shading); the ρ=3 pair is gated (β=.5). Purple dashed (error row): reduced CMG on the tuned baseline, gated (Sec. VI-C).

B. Comparison with Classical Baselines

The fixed PD law in (14) damps absolute rate, so moving references can include velocity lag. We therefore use PD+ff (15) as the primary baseline and sweep the dimensionless bandwidth scale $\rho > 0$ via $\boldsymbol{\omega}_n \mapsto \rho\boldsymbol{\omega}_n$ over $\rho \in [0.75, 8]$ ($\rho = 1$ nominal). The best mission-mean occurs at $\rho = 3$ on both airframes; CF2 becomes rotor-limited beyond $\rho \approx 4$.

At $\rho = 3$, the gated CMG–PES residual ($\beta = .5$ on X2, .2 on CF2) reduces geometric-mean error from 4.54×10^{-3} to 2.85×10^{-3} rad on X2 (37.3%) and from 3.77×10^{-3} to 2.92×10^{-3} rad on CF2 (22.4%). It improves Roll, Full3, Hard45 (Fig. 4), and Yaw360 on both vehicles; Hardstep is the only mission that does not improve (Sec. VI-F). On

Full3 and Hard45 the reductions are 12–14% (X2) and 5–7% (CF2). Without the gate, CF2 admits only $\beta = .05$ and the reduction is 6.5% (Table II, ungated row). Against the original fixed-PD baseline, the residual lowers mean error by 17.3–60.6% across the ten nominal cases (Table II).

a) Portability across control families: Replacing only $\boldsymbol{u}_0$ in (27), the same gated residual improves the geometric mean on both platforms for LQR, PID+ff, SMC, MPC, and NMPC: LQR 31.1%/22.4% (X2/CF2), PID+ff 36.7%/22.4%, SMC 43.8%/26.6%, MPC 33.4%/22.7%, and NMPC 31.9%/21.7%. This is an interface-portability result, not per-family tuning.

C. Mechanism Ablation

The architecture separates conductance modulation (χ), gate dynamics, activity gain (G), decoder adaptation (W_k), and residual authority ($\beta\ell$), so each can be ablated with the others held fixed.

With decoder mode held fixed, toggling χ (retaining the base shunt $g_0 r_j^2$) is numerically indistinguishable, here and at every tested G. The reason is structural: χ enters only through $c_j \propto r_j^2$, which is $2 \times 10^{-9}\,\mathrm{s}^{-1}$ at rest against a leak of $\tau^{-1} = 20\,\mathrm{s}^{-1}$; after a gate latches (below) it only moves the membrane fixed point ($0.107 \to 0.092$ at $I_j = I_b$), which the saturated activity hides from the readout. *Remark 2 (Fixed-feature PES contraction):* If the adaptation reference and a nonzero activity $\boldsymbol{a}$ are fixed, decoder leak is zero, and readout saturation and projection remain inactive, then the PES error contracts as

$$\boldsymbol{\varepsilon}_{k+1} = (1 - \eta\|\boldsymbol{a}\|_2^2)\boldsymbol{\varepsilon}_k, \tag{29}$$

so a nonzero initial error contracts to zero when $0 < \eta\|\boldsymbol{a}\|_2^2 < 2$. This constant-feature calculation [7] is used only to interpret activity-limited learning behavior; changing targets, loss of excitation, saturation, leakage, and plant dynamics prevent direct application as a closed-loop convergence statement.

Fixed versus adaptive decoder. Holding $W_k = W_0$ keeps CMG dynamics but limits the readout to the paired difference $\boldsymbol{a}^+ - \boldsymbol{a}^-$, and yields only modest reductions (Table II).

Gate/activity regime. At $I_j = I_b$, $v_j \approx 0.75 < v_{\mathrm{th}}$ and $r_j \approx \sigma(-12.5) \approx 3.7 \times 10^{-6}$, i.e., a small but nonzero logistic tail; with $G = 10^5$ the resting activity is $a_j \approx 0.37$. Since $\alpha_h\gamma = 100 > 4$, the gate is bistable; a strictly graded, non-latching gate requires $\alpha_h\gamma \le 4$ (since $\max \sigma'(x) = 1/4$, $\alpha_h\gamma < 4$ makes the frozen-v_j gate map a contraction). Here, for frozen v_j its equilibria fold at $v_j \approx 0.888$ (onset) and $v_j \approx -0.888$ (release). Once $r_j \ge 1/2$, Proposition 1(i) gives $v_j \ge v_{\mathrm{reset}} = 0$, hence $b_{j,k} \ge 1/2$ in (21), so opened gates latch (none released in the ten primary runs) and read $a_j = 1$ thereafter.

When activity is effectively constant ($\boldsymbol{a}_k \approx \bar{\boldsymbol{a}}$) and projection is inactive, the PES update reduces to the recursion for $\boldsymbol{z}_k = W_k\bar{\boldsymbol{a}}$

$$\boldsymbol{z}_{k+1} = (1 - \lambda_W)\boldsymbol{z}_k + \eta\|\bar{\boldsymbol{a}}\|^2[\boldsymbol{y}_k^* - \mathrm{sat}_{[-1,1]}(\boldsymbol{z}_k)], \tag{30}$$

a leaky first-order filter of the adaptation reference (Remark 2), i.e., lagged proportional action with corner 9.60 rad/s for $\bar{\boldsymbol{a}} = \mathbf{1}$. This is the constant basis of Sec. VI-D, i.e., PD+ff plus a matched lagged-proportional term. Hard45's highest instantaneous frequency is 2.1 rad/s [18], below that corner.

a) Reduced CMG (non-latching ablation): Setting $\gamma = 0$, $g_0 = g_1 = 0$ (so $c_j \equiv 0$), and $\tau_r \to 0$ in (19) leaves the first-order membrane $\tau\dot{v}_j = -(v_j - v_{\mathrm{rest}}) + I_j$ read through the gate's steady state, $a_j = \mathrm{sat}_{[0,1]}(G\sigma(\alpha_h(v_j - v_{\mathrm{th}})))$ (implemented as (21) with $h/\tau_r = 1$ and (22) with $c_j = 0$); all other settings are unchanged. Below the onset fold ($a_j < 1$ requires $r_j < 1/G$) the removed terms are negligible ($\alpha_h\gamma r_j \le 10^{-3}$, $c_j < 2 \times 10^{-8}\,\mathrm{s}^{-1} \ll \tau^{-1}$, $\tau_r = \tau/10$), so the two units coincide until a CMG gate latches. Under the primary protocol the reduced unit reaches 46.3%/28.6% (X2/CF2; Table II) at comparable mean effort (0.033/0.016 vs. 0.032/0.015). It matches CMG within 1.5 pp on Roll, Yaw360, and Hardstep and exceeds it on Full3 and Hard45, where CMG units latch. Lowering G to 10^3 or 1 removes the graded tail (9.0/3.6%, 4.4/1.7%), and a two-level basis that replays the recorded CMG latch times reaches 9.6/3.8%. These single-seed, noise-free ablations indicate that decoder adaptation is the dominant lever and that, on the tuned baseline, it draws on the graded sub-threshold part of the basis, which latching removes; on the fixed-PD baseline, where errors are large, the latched basis and its faster PES corner perform better (X2 Hard45: 53.1% vs. 38.6%).

D. Neuron-Family Comparison

The Nengo benchmark isolates the basis choice, holding one actuator interface fixed across two models, five missions, and eleven controllers (PD plus fixed/PES variants of CMG, LIF, ALIF, Izhikevich [19], and LIFRate); only the neuron dynamics and native-state-to-activity map differ. Across the full matrix (not shown) two patterns hold. First, PES is the dominant lever in every family: fixed decoders rarely match their PES counterparts, extending Sec. VI-C to every basis. Second, persistent activity is necessary but not sufficient. Remark 2 explains the flat rows: a sparsely active basis starves the update. In the corrected $\rho = 3$ runs, LIF, ALIF and LIFRate have mission-mean activity occupancy (activity $> 10^{-6}$) of 3.2–4.4%, whereas CMG (resting at $a_j \approx 0.37$) and Izhikevich are active in $\ge$99.9%.

Izhikevich–PES leads on the fixed-PD baseline (Table II, last block) but not on the tuned one: under the primary protocol it is positive but below CMG on Full3 and Hard45 ($+5.8/+4.5$% vs. CMG's $+12.4/+13.8$% on X2), while its residual sits on a $\pm\beta\ell$ rail in only 0–1.7% of samples, similar to CMG's own low rail occupancy, its effort still averages about twice CMG's because it stays near 0.05–0.06 regardless of mission rather than tracking the baseline error as CMG's does. On Roll and Yaw360, where the baseline is already near the noise floor, the residual raises the geometric-mean error to 1.19× (X2) and 1.05× (CF2) the baseline's; CMG's own effort tracks the baseline error by construction (Sec. VI-C), Izhikevich's does not.

TABLE II

MEAN q-ERROR (10^{-3} RAD, 45 S). Δ: REDUCTION OVER THE BLOCK BASELINE [%]. EFFORT: RMS RESIDUAL / PER-AXIS BOUND. CLOSING COLUMN: GEOMETRIC MEAN (ERROR ROWS), ARITHMETIC MEAN (EFFORT ROWS).

	Skydio X2						Crazyflie 2					
	Roll	Full3	Hard45	Hardstep†	Yaw360	*geo*	Roll	Full3	Hard45	Hardstep†	Yaw360	*geo*
Primary baseline: PD + rate feedforward, $\rho = 3$ (bandwidth-tuned)												
PD+ff	0.34	10.09	10.54	265.91	0.20	*4.54*	0.56	7.06	8.65	262.59	0.084	*3.77*
+CMG–PES, gated	0.074	8.83	9.08	271.35	0.12	*2.85*	0.23	6.67	8.02	263.19	0.067	*2.92*
Δ [%]	78.4	12.4	13.8	-2.0	41.8	*37.3*	59.9	5.4	7.3	-0.2	20.3	*22.4*
+CMG–PES, ungated‡	0.074	8.83	9.08	311.07	0.12	*2.93*	0.43	6.96	8.50	265.93	0.079	*3.52*
Δ [%]	78.4	12.4	13.8	-17.0	41.8	*35.6*	22.9	1.3	1.8	-1.3	5.6	*6.5*
Δ, realistic noise [%]	-4.2	11.3	10.8	-2.6	-5.3	*2.3*	-0.4	3.9	4.0	-0.3	-2.2	*1.0*
Δ, moderate noise [%]	-1.4	11.9	11.2	-2.4	-3.9	*3.3*	2.2	4.2	4.2	-0.2	-2.0	*1.7*
Δ, reduced CMG, gated (Sec. VI-C) [%]	78.5	35.2	45.5	-0.6	41.8	*46.3*	60.1	23.0	24.6	-0.4	20.3	*28.6*
Baseline ladder: PD + rate feedforward, $\rho = 1$												
PD+ff	2.98	72.10	71.02	454.77	1.78	*26.19*	4.91	42.72	53.18	425.93	0.74	*20.39*
+CMG–PES	0.61	32.81	38.17	359.16	0.60	*11.04*	0.97	20.29	28.23	347.68	0.25	*8.65*
Δ [%]	79.5	54.5	46.3	21.0	66.4	*57.8*	80.2	52.5	46.9	18.4	66.4	*57.6*
Original fixed PD baseline, $\boldsymbol{\omega}_n = (4, 4, 3.5)$ rad/s												
PD	50.56	303.28	294.08	454.53	75.86	*173.12*	51.34	288.38	285.45	426.18	75.81	*168.68*
+CMG–PES	41.79	131.75	138.01	359.35	29.90	*96.02*	42.44	126.48	132.32	347.89	29.87	*94.11*
Δ [%]	17.4	56.6	53.1	20.9	60.6	*44.5*	17.3	56.1	53.6	18.4	60.6	*44.2*
Δ, fixed decoder [%]	1.9	9.7	10.3	0.5	0.1	*4.6*	3.3	4.5	6.8	0.4	0.1	*3.1*
Strongest rival basis (Izhikevich): reduction and realized effort												
Δ, Izhikevich–PES, $\rho = 3$ [%]	-48.0	5.8	4.5	-1.1	-76.3	*-18.9*	0.7	1.3	0.8	-0.5	-33.3	*-5.4*
Δ, Izhikevich–PES, fixed PD [%]	39.6	37.5	32.2	6.6	46.6	*33.8*	33.7	38.9	32.2	diverges§	41.5	–
Δ, Izhikevich fixed dec., fixed PD [%]	4.6	4.9	4.6	0.7	0.2	*3.0*	5.6	5.8	4.0	-2.2	-2.2	*2.3*
effort, CMG–PES, $\rho = 3$	0.003	0.023	0.023	0.109	0.001	*0.032*	0.005	0.010	0.012	0.049	<0.001	*0.015*
effort, Izhikevich–PES, $\rho = 3$	0.053	0.051	0.053	0.106	0.052	*0.063*	0.012	0.021	0.021	0.047	0.012	*0.023*

LIF/ALIF/LIFRate stay within 0.1% of fixed PD outside Hardstep. $\rho = 3$ rows are gated (28) with $\beta = .5$ (X2), .2 (CF2); ‡ungated, $\beta = .5$, .05 (the $\rho = 1$ and fixed-PD rows are ungated). †Hardstep commands 63–111° steps every 2 s; 97–99% of its mean error is slew (Sec. VI-F). §CF2 Hardstep under the fixed-PD baseline sustains near-180° tracking loss (2.45 rad mean, t=3–44 s); excluded from the geometric mean rather than averaged in.

a) Non-neural and conventional alternatives: The same protocol, held fixed, finds no match for CMG among either family: a threshold-tuned LIFRate basis, selected on a held-out mission split, reaches $+15.8\%/+11.4\%$ (X2/CF2); two bases with no neuron dynamics at all – a static paired-current encoding and a constant basis ($\boldsymbol{a} \equiv \mathbf{1}$) – reach $+11.9\%/+4.8\%$ and $+10.3\%/+4.3\%$. Every other neuron family and non-neural basis remains short of CMG's $+37.3\%/+22.4\%$; only the reduced CMG of Sec. VI-C, which removes the gate's hysteresis, exceeds it.

E. Measurement Noise and Repeated Disturbances

Both tests use the tuned PD+ff baseline and score the *true*-attitude error. For noise, each case is rerun with paired seeds by left-multiplying q with a small Gaussian Euler-angle perturbation and adding Gaussian noise to each rate component (moderate 0.010 rad, 0.025 rad s^{-1}, 5 seeds; realistic 0.020 rad, 0.050 rad s^{-1}, 10 seeds; not calibrated sensor specs). Both arms see the same noise stream.

Noise sets an error floor: on Roll/Yaw360 the X2 baseline rises from $0.34/0.20$ mrad (clean) to $0.77/0.71$ mrad (moderate), and the residual changes it by -5.3% to $+2.2\%$ (Table II). Where baseline error exceeds this floor, gains persist in every seed (std. < 0.2 pp): at the realistic level Full3/Hard45 keep $11.3/10.8\%$ (X2) and $3.9/4.0\%$ (CF2), so the five-mission geometric mean falls to 2.3% and 1.0%. On CF2, $\beta = .5$ would keep $8.7/9.3\%$ but Hardstep diverges (15/15 seeds) due to rotor-level saturation and collective shortfall; we therefore use $\beta = .2$.

An equilibrium test applies $\boldsymbol{\tau}_{\mathrm{d}} = d_b \varrho(t)[\sin(1.31t + .2), .8\sin(1.73t + 1.1), .6\sin(2.17t + 2)]^{\mathsf{T}}$, with ϱ alternating 5-s on/off intervals after 5 s of quiet (0.25-s raised-cosine ramps), $d_b = .15$ N m (X2) and .00015 N m (CF2), and also $0.5\times$ and $2\times$. Against PD+ff at $\rho = 3$ the residual lowers mean error during disturbance-active intervals from 1.61° to 1.38° (14.4%) on X2 and from 2.27° to 2.14° (5.9%) on CF2, and by $24.0/13.3\%$ (X2) and $6.5/4.7\%$ (CF2) at $0.5\times/2\times$; hover never saturates, so the gate is inert. Disturbance-inactive-interval error, already below 0.1°, falls by 14.7% (X2) and 19.8% (CF2) at the nominal amplitude but rises on X2 at $0.5\times$ ($0.021° \to 0.036°$). At the nominal amplitude, CF2's reduction during disturbance-active intervals is 13.7% if it borrows $\beta = .5$, versus 1.5% at $\beta = .05$.

F. Saturation-Aware Gating on Hardstep

Hardstep commands 63°–111° attitude changes every 2 s, and 97–99% of its mean error accumulates during slew. To preserve attitude-tracking torque authority during such saturation-limited transients, the adaptive residual output $\boldsymbol{s}_k$ is passed through the saturation-aware gate (28) before it enters the bounded torque addition (27). When the baseline is at its prescribed torque limit ($|u_{0,k,i}| \geq \ell_i$), an ungated residual component with $s_{k,i} u_{0,k,i} < 0$ would reduce the net commanded torque available for attitude recovery and can drive the decoder toward persistent opposing corrections. The gate prevents this failure mode by zeroing only those opposing components, while leaving same-sign assistance and all non-saturated axes unchanged.

At $\rho = 3$ the ungated residual degrades Hardstep by 17.0% on X2 and, at $\beta = .5$, diverges on CF2 (mean error 136°, rotors at a bound in 92% of samples). Because the reference is piecewise constant, the latched decoder acts as the first-

order filter (30) and lags a 12 rad/s baseline; on a saturated axis that lag can only oppose $\boldsymbol{u}_0$ (Sec. III). At $\beta = .5$ the gate blocks the residual in 20.5% (X2) and 15.5% (CF2) of Hardstep samples and in at most 0.04% elsewhere, so the other eight cells differ from the ungated residual by at most 0.1%. It cuts the X2 loss from 17.0% to 2.0% and, noise-free, removes the CF2 divergence at $\beta = .5$ (-1.2% on Hardstep, 36.5% geometric mean).

The gate does not make the residual beat the baseline here. The gated residual helps while braking (0.25–0.75 s after a step; -0.13° of the X2 45-s mean) but leaves a larger tail once the baseline has left its box ($+0.40^\circ$ over 0.75–1.5 s), because the decoder still holds the slew-phase correction, with the 9.6 rad/s corner of Sec. VI-C. The torque limit is reached mainly on the maneuver axis, where the gate inhibits only opposing authority; lag transients on the other axes decay under PES, and the gated residual returns to near baseline parity (-2.0% on X2).

VII. Conclusions and Future Work

We proposed a bounded online residual for quaternion attitude control in which a small population of continuous CMG units feeds a compact PES decoder whose output is added to a saturated PD torque request before rotor allocation. Independently of the learned weights, the internal states remain bounded, the residual never exceeds its prescribed authority, and setting that authority to zero recovers the baseline exactly; the saturation-aware gate preserves these properties. In simulation of multirotors of different scale, the gated residual reduced attitude-tracking error on both vehicles against a bandwidth-tuned PD baseline with rate feedforward, reduced error during repeated torque disturbances, and attached unmodified to LQR, sliding-mode, model-predictive, and PID baselines. Under sensor noise it helps only where the baseline error exceeds the noise floor, so noise-free results overstate the practical gain. The ablations identify online decoder adaptation on the graded sub-threshold part of the CMG features as the principal mechanism. For attitude control, this mechanism acts as a bounded, model-free correction driven by the baseline torque and the attitude error: it removes much of the tracking lag that remains on moving references, while its effort follows the baseline error and remains a small fraction of the torque bound. On the tuned baseline, a reduced CMG without gate latching improves tracking further at comparable effort, whereas with the larger errors of the original fixed PD controller the latched features perform better.

Several problems remain open. First, the trade-off between the fast latched and the graded CMG regimes calls for units whose gates can release, so that one unit matches its regime to the error level. Second, the settling tail after large attitude steps and the rotor-level saturation that limits the usable authority on the smaller vehicle under noise call for decoder lag compensation and an allocation-aware gate. Third, a closed-loop stability guarantee that covers the plant, the online decoder, and rotor saturation is still missing; the interface bounds established here are a starting point. Finally, because the interface requires only a nominal torque command and actuator limits, it carries over unchanged to other torque-controlled robots, such as manipulators and ground vehicles; evaluating it there, under model mismatch, in full translational and rotational flight, and on hardware is the natural next step.

References

[1] T. Johannink *et al.*, "Residual reinforcement learning for robot control," in *2019 International Conference on Robotics and Automation (ICRA)*, 2019, pp. 6023–6029.

[2] Z. Wu *et al.*, "L1Quad: L_1 adaptive augmentation of geometric control for agile quadrotors with performance guarantees," *IEEE Transactions on Control Systems Technology*, vol. 33, no. 2, pp. 597–612, 2025.

[3] I. Rubio Scola, L. R. Garcia Carrillo, and J. P. Hespanha, "Limbic system-inspired performance-guaranteed control for nonlinear multi-agent systems with uncertainties," *IEEE Transactions on Neural Networks and Learning Systems*, vol. 34, no. 8, pp. 4196–4207, 2023.

[4] I. Rubio Scola, G. A. Guijarro Reyes, L. R. Garcia Carrillo, J. P. Hespanha, and L. Burlion, "A robust control strategy with perturbation estimation for the Parrot Mambo platform," *IEEE Transactions on Control Systems Technology*, vol. 29, no. 4, pp. 1389–1404, 2021.

[5] C. Eliasmith and C. H. Anderson, *Neural Engineering: Computation, Representation, and Dynamics in Neurobiological Systems*. MIT Press, 2004.

[6] T. Bekolay *et al.*, "Nengo: A Python tool for building large-scale functional brain models," *Frontiers in Neuroinformatics*, vol. 7, p. 48, 2014.

[7] A. R. Voelker, "A solution to the dynamics of the prescribed error sensitivity learning rule," Centre for Theoretical Neuroscience, University of Waterloo, Tech. Rep. CTN-TR-20151001-01, Oct. 2015. [Online]. Available: https://www.compneuro.uwaterloo.ca/files/publications/voelker.2015.pdf

[8] O. A. García Alcántara, D. Chavez Arana, E. S. Espinoza, I. Rubio Scola, L. R. Garcia Carrillo, and A. T. Sornborger, "Spiking neural network-based control of an unmanned aerial system implemented on a customized neural flight simulation environment," in *2024 American Control Conference (ACC)*, 2024, pp. 3125–3129.

[9] A. Olivares, E. S. Espinoza, L. E. Ramos, O. A. García Alcántara, L. R. Garcia Carrillo, and A. T. Sornborger, "Self-tuning neuromorphic controller for real-time UAS trajectory tracking based on prescribed error sensitivity," *Neural Computing and Applications*, vol. 38, no. 7, p. 192, 2026.

[10] G. Bellec *et al.*, "A solution to the learning dilemma for recurrent networks of spiking neurons," *Nature Communications*, vol. 11, p. 3625, 2020.

[11] H. Schaub and J. L. Junkins, *Analytical Mechanics of Space Systems*, 4th ed. AIAA, 2018.

[12] J. Diebel, "Representing attitude: Euler angles, unit quaternions, and rotation vectors," *Matrix*, vol. 58, no. 15–16, pp. 1–35, 2006.

[13] N. A. Chaturvedi, A. K. Sanyal, and N. H. McClamroch, "Rigid-body attitude control," *IEEE Control Systems Magazine*, vol. 31, no. 3, pp. 30–51, 2011.

[14] L. R. García Carrillo, A. E. Dzul López, R. Lozano, and C. Pégard, *Quad Rotorcraft Control: Vision-Based Hovering and Navigation*, ser. Advances in Industrial Control. London: Springer, 2013.

[15] J. C. Monteiro, F. Lizarralde, and L. Hsu, "Optimal control allocation of quadrotor UAVs subject to actuator constraints," in *2016 American Control Conference (ACC)*, 2016, pp. 500–505.

[16] E. Todorov, T. Erez, and Y. Tassa, "MuJoCo: A physics engine for model-based control," in *2012 IEEE/RSJ International Conference on Intelligent Robots and Systems*, 2012, pp. 5026–5033.

[17] Google DeepMind, "MuJoCo Menagerie," https://github.com/google-deepmind/mujoco_menagerie, model repository; accessed Sep. 5, 2026.

[18] S. Sandoval and P. L. De Leon, "The instantaneous spectrum: A general framework for time-frequency analysis," *IEEE Transactions on Signal Processing*, vol. 66, no. 21, pp. 5679–5693, 2018.

[19] E. M. Izhikevich, "Simple model of spiking neurons," *IEEE Transactions on Neural Networks*, vol. 14, no. 6, pp. 1569–1572, 2003.