Pi4GPU (PiG)

TOP VIEW



PCB Project:	Pi4GPU (PiG)
Version:	V1
Revision:	R1
Project State:	Released (2022-11-29)
Variant:	STD_PRO
Print date:	03.12.2022

Page	Index
01	Cover page
02	Block diagram
03	Top schematic
04	CM4 module - part #1
05	CM4 module - part #2
06	USB C interface
07	USB Hub
08	PCIe x4 slot
09	HDMI
10	100/1000M Ethernet
11	MicroSD card
12	MISC
13	Power supply #1
14	Power supply #2
15	Sensors
16	PCB marking and mechnics
17	Hardware changelog

[02]Block_diagram.SchDoc

[03]Top.SchDoc

PCB
PCB BARE BOARD

mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A3
Title: Pi4GPU (PiG)			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: -	
Designer: M.Folejewski		Sheet: 1 / 15	
File Name: [01]Cover_page.SchDoc		Printed: 03.12.2022	


MicroSD slot
Only for CM4 Lite
J450
SDIO/eMMC
3V3_SD
U450 Load switch 1A limited
3V3
Q450/Q451 PWR Switch
R452
SD_PWR_ON
HDMI #0 (Type A)
Video
J350
5V_HDMI
U352 Load Switch
5V
HDMI
RJ45 (GbE)
Ethernet
J400
MDI
PCIe x4 Edge Connector
PCIe x4
J300
PCIe x1 Gen2
12V_PCIE
3V3_PCIE
MOD100
CM4 / CM4 Lite
SDIO/eMMC
HDMI #0
GbE
PCIe
GPIO
PMIC_5V0_IN
PMIC_3V3_OUT
PMIC_1V8_OUT
5V
3V3
1V8
nPWR
nActivity
nPWR
nACT
Q100/Q101 Buffer
LED100/101 SYS LED Green/Red
nRSTEXT
R/C Filter
SYS_RST
USB 2.0
USB-D
U200 USB MUX
USB 2.0
USB-H
3V3
OTG ID
USB OTG
SW200
RPI_BOOT
Q200 BOOT Mode
USB-C
5V_USBC
J200
USB 2.0
Only for Flashing
USB #1/#2
2x USB 2.0
J250
USB1
USB2
5V_VBUS
HUB_RST
U251 2-port USB HUB
EN
FLT
U250 Load switch 2A limited
5V_HUB
U804 U/I Sensor
I2C1
GPIO22
GPIO27
LED500/501 STATUS LED Green/Red
40-pin GPIO HAT
GPIO
5V
3V3
J100
GPIO12
Q500 FAN CTRL #1
Fan #1 Socket
J500
Fan #2 Socket
J501
U500 FAN CTRL #2
TACH/PWM
12V_SYS
J502 PWR Switch
FAN_PWR
J700 (Barrel Jack)
12VDC
J700
12V_IN1
Q700 Ideal Diode
Q701/Q702 Disable Circuit
J701 (Molex)
12VDC
J700
12V_IN2
Q703 Ideal Diode
U803 U/I Sensor
U801 U/I Sensor
12V_PCIE
12V_SYS
3.3V (For PCIE)
U750 Buck converter 3.3V/3A
U750 Buck converter 5V/3A
5V (For CM4)
3V3_PCIE
U802 U/I Sensor
U800 U/I Sensor
mirko electronics
Mirko Electronics
Smoka Wawelskiego 1
30-535 Kraków, Poland
Size
A4
Title
Block diagram
Version
V1
Project: Pi4GPU (PiG)
Revision
R1
Variant: STD_PRO
RefDes: 1-99
Designer: M. Folejewski
Sheet: 2 / 15
File Name: [02] Block_diagram.SchDoc
Printed: 03.12.2022



mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland	Size A4
Title Top schematic		Version V1
Project: Pi4GPU (PiG) Variant: STD_PRO Designer: M. Folejewski File Name: [03] TOP.SchDoc	RefDes: 1-99 Sheet: 3 / 15 Printed: 03.12.2022	Revision R1

CM4 MODULE (PART #1)



SCH:
I2C0 Interface: SCL0 pin (GPIO45) and SDA0 pin (GPIO44) typically are used for Camera and Displays and have Internal 1.8k pull up to CM4_3.3V.
ID Interface (ID_SD/ID_SC): CM4 datasheet does not mention about pull-up resistors on ID_SD and ID_SC pins.

I2C1 (GPIO2/GPIO3) have 1.8k pull-up resistors added on CM 4 module.

SCH:
I2C0 (SDA0/SCL0): This internal I2C bus is normally allocated to the CSI1 and DSI1 as these devices are controlled by the firmware.

SCH:
nRPIBOOT: A low on this pin force booting from an RPI server. If not used leave floating. Internally pulled via 10K to +3.3V.

SCH:
I2C (ID_SD/ID_SC): This I2C bus is normally used for identifying HATs (HAT ID EEPROM) and controlling CSI0 and DSI0 devices.

At boot time this I2C interface will beinterrogated to look for an EEPROM that identifies the attached board andallows automagic setup of the GPIOs (and optionally, Linux drivers).

DO NOT USE these pins for anything other than attaching an I2C ID EEPROM. Leave unconnected if ID EEPROM not required.

SCH:
EEPROM_nWP pin: Leaving floating NB internally pulled up to CM4_3.3V via 100k (VIL <0.8V) but can be grounded to prevent writing to the on board EEPROM which stores the bootcode.

SCH:
1.8V and 3.3V Outputs +/-2.5%. Power Output max 300mA per pin for a total of 600mA. This will be powered down during power off or GLOBAL_EN being set low.

SCH:
GLOBAL_EN: Drive low to power off CM4. Internally pulled up with a 100K to +5V.

40-PIN GPIO HEADER



TESTPOINTS (DEBUG)





Used GPIOs:

GPIO2 - I2C1 SDA
GPIO3 - I2C1 SCL

GPIO12 - GPIO/PWM (FAN #1)
GPIO22 - GPIO (USER LED1 Green)
GPIO27 - GPIO (USER LED2 Red)

Raspberry Pi Pinout

3v3 Power	1	2	5v Power	
GPIO 2 (I2C1 SDA)	3	4	5v Power	
GPIO 3 (I2C1 SCL)	5	6	Ground	
GPIO 4 (GPCLK0)	7	8	GPIO 14 (UART TX)	
Ground	9	10	GPIO 15 (UART RX)	
GPIO 17	11	12	GPIO 18 (PCM CLK)	
GPIO 27	13	14	Ground	
GPIO 22	15	16	GPIO 23	
3v3 Power	17	18	GPIO 24	
GPIO 10 (SPI0 MOSI)	19	20	Ground	
GPIO 9 (SPI0 MISO)	21	22	GPIO 25	
GPIO 11 (SPI0 SCLK)	23	24	GPIO 8 (SPI0 CE0)	
Ground	25	26	GPIO 7 (SPI0 CE1)	
GPIO 0 (EEPROM SDA)	27	28	GPIO 1 (EEPROM SCL)	
GPIO 5	29	30	Ground	
GPIO 6	31	32	GPIO 12 (PWM0)	
GPIO 13 (PWM1)	33	34	Ground	
GPIO 19 (PCM FS)	35	36	GPIO 16	
GPIO 26	37	38	GPIO 20 (PCM DIN)	
Ground	39	40	GPIO 21 (PCM DOUT)	

GLOBAL RESET



SCH:
nEXTRST: Driven low during reset. Driven high (3.3V) once CM4 CPU has started to boot.

ID I2C



SYS LEDs

3V3 LOAD



SCH:
Extra load on the 3V3 power rail to fix the HDMI issue with 5V LED.



components - display 4 parameters: val/tol/pwr rating/package

mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland	Size	A3
Title: Compute Module 4 (Part #1)		Version	V1
Project: Pi4GPU (PiG)		Revision	R1
Variant: STD_PRO	RefDes: 100-199		
Designer: M.Folejewski	Sheet: 4 / 15		
File Name: [04] CM4_PART1.SchDoc	Printed: 03.12.2022		

CM4 MODULE (PART #2)



SCH:

USB_OTG_ID: Input (3.3V signal) USB OTG Pin. Internal pulled up. The USB_OTG pin is used to select between USB host and device that is typically wired to the ID pin of a Micro usb connector. To use this functionality it must be enabled in the OS that is used. If using either as a fixed slave or fixed master, please tie the USB OTGID pin to ground.

LAYOUT:

Route MIPI signals as matched length 100 Ohm differential pairs, each signal within a pair should ideally be matched to better than 0.15mm.

Route USB signals as matched length 90 Ohm differential pairs. The P N signals should ideally be matched to 0.15mm.

Route HDMI signals as matched length 100 Ohm differential pairs, each signal within a pair should ideally be matched to better than 0.15mm. Pairs don't typically need any extra matching as they only have to be matched to 25mm.

LAYOUT:

Route Ethernet signals as matched length 100 Ohm differential pairs with suitable clearances. Length matching between pairs should be better than 50mm, so in the typical case no length matching is required. However the signals within a pair need to be length matched, ideally to better than 0.15mm.

Route PCIe signals as matched length 90 Ohm differential pairs with suitable clearances. There is no need to match the lengths between pairs, only the signals within a pair need to be length matched ideally to better than 0.1mm.

LAYOUT:

Impedance matching:
90 Ohm -> PCIe, USB
100 Ohm -> HDMI, Ethernet, MIPI (CSI, DSI)

MEZZANINE CONNECTORS

J101 — CONNECTOR — Mezzanine, 100pin, 3.0mm

J102 — CONNECTOR — Mezzanine, 100pin, 3.0mm



mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size: B
Title: Compute Module 4 (Part #2)			Version: V1
Project: Pi4GPU (PiG)			Revision: R1
Variant: STD_PRO		RefDes: 100-199	
Designer: M. Folejewski		Sheet: 5 / 15	
File Name: [05] CM4_PART2.SchDoc		Printed: 03.12.2022	



TESTPOINTS (DEBUG)





BOM:
USB 3.1 Type C:
Use XKB Connectivity, MPN = U262-161N-4BVC11.
Description: vertical connector, 16 pins, USB 2.0 only, SMD version.

LAYOUT:
Route USB signals as matched length 90 Ohm differential pairs. The P N signals should ideally be matched to 0.15mm.

mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland	Size	A4
Title: USB-C interface and USB switch		Version	V1
Project: Pi4GPU (PiG)		Revision	R1
Variant: STD_PRO	RefDes: 200-249		
Designer: M. Folejewski	Sheet: 6 / 15		
File Name: [06] USB_C.SchDoc	Printed: 03.12.2022		



Mirko Electronics	Size: A4
Smoka Wawelskiego 1, 30-535 Kraków, Poland	
Title: 2-port USB 2.0 hub	Version: V1
Project: Pi4GPU (PiG)	Revision: R1
Variant: STD_PRO	RefDes: 250-299
Designer: M. Folejewski	Sheet: 7 / 15
File Name: [07] USB_HUB.SchDoc	Printed: 03.12.2022

PCI Express x4 Edge Connector



SCH:

TX and RX diff pairs have PN swaps to improve PCB layout

LAYOUT:

Route PCIe signals as matched length 90 Ohm differential pairs with suitable clearances. There is no need to match the lengths between pairs, only the signals within a pair need to be length matched ideally to better than 0.1mm.

TESTPOINTS (DEBUG)







mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title M.2 PCIe x1 Socket			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: 300-399	
Designer: M. Folejewski		Sheet: 8 / 15	
File Name: [08] PCIe.SchDoc		Printed: 03.12.2022	

ESD PROTECTION



LAYOUT:

Place the TVS array diodes as close as possible to the HDMI connector.

LAYOUT:

connect the IO1A - IO4A on the connector side.

HDMI #0 (TYPE A)



BOM:

HDMI #0 connector:
Wurth Elektronik, MPN = 685 119 134 923
BOOMELE, MPN = HDMI-001
Description: Type A (Standard), 19 pins, 0.50mm pitch, horizontal, SMD.

LAYOUT:

Route HDMI signals as matched length 100 Ohm differential pairs, each signal within a pair should ideally be matched to better than 0.15mm. Pairs don't typically need any extra matching as they only have to be matched to 25mm.

TESTPOINTS (DEBUG)



5V POWER SWITCH





mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland	Size	A4
Title: HDMI Interface		Version	V1
Project: Pi4GPU (PiG)		Revision	R1
Variant: STD_PRO	RefDes: 400-449		
Designer: M. Folejewski	Sheet: 9 / 15		
File Name: [09] HDMI.SchDoc	Printed: 03.12.2022		

ESD PROTECTION



LAYOUT:

connect IO1A - IO4A on the connector side.

LAYOUT:

Place TVS array diodes as close as possible to RJ45 connector.

100/1000M ETHERNET



add 4 parameters R/C

LAYOUT:

Route Ethernet signals as matched length 100 Ohm differential pairs with suitable clearances. Length matching between pairs should be better than 50mm, so in the typical case no length matching is required. However the signals within a pair need to be length matched, ideally to better than 0.15mm.

BOM:

RJ45 -> compatible connectors:
HanRun, MPN = HR911130A (HY911130A)
Link-PP, MPN = LPJG0806FBNL
Description: 100/1000M RJ45, Tab-down, G/Y LEDs

TESTPOINTS (DEBUG)





mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title 100/1000M Ethernet interface			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: 500-599	
Designer: M. Folejewski		Sheet: 10 / 15	
File Name: [10] Ethernet.SchDoc		Printed: 03.12.2022	

MICRO SD CARD



SCH:

Used MicroSD card slot: Hmax = 2.00 mm

USER:

SD Card only for CM4 Lite module with no on-board Flash memory chip (eMMC).

BOM:

MicroSD slot -> compatible components:
GCT, MPN = MEM2055-00-190-01-A
SOFNG, MPN = TF-015
HOAUC, MPN = HYC77-TF09-200
XUNPU, MPN = TF-115

PWR SWITCH



BOM:

Texas Instruments, MPN = TPS25221DBV
Diodes, MPN = AP2553W6-7
Diodes, MPN = AP22653W6-7

SCH:

ILIM resistor = 24k => current limit set to 1.05A

TESTPOINTS (DEBUG)





mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title MicroSD slot			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: 600-699	
Designer: M. Folejewski		Sheet: 11 / 15	
File Name: [11] SD.SchDoc		Printed: 03.12.2022	

USER LEDs



FAN1 (5V, ON/OFF)



USER:

FAN1 can be controlled by FAN1_CTRL line (by static GPIO level or by using PWM mode). FAN1 control can be disabled (always on) by assembly R802 jumper.

FAN2 (5V/12V PWM CTRL IC)



BOM:

4-pin connector (2.54mm pitch):
Molex, MPN = 47053-1000.
PINREX, MPN = 744-81-04TW30.



mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title MISC			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: 800-899	
Designer: M. Folejewski		Sheet: 12 / 15	
File Name: [12] MISC.SchDoc		Printed: 03.12.2022	



Table 1. INA219 Address Pins and Slave Addresses

A1	A0	SLAVE ADDRESS
GND	GND	1000000
GND	V_{S+}	1000001
GND	SDA	1000010
GND	SCL	1000011
V_{S+}	GND	1000100
V_{S+}	V_{S+}	1000101
V_{S+}	SDA	1000110
V_{S+}	SCL	1000111
SDA	GND	1001000
SDA	V_{S+}	1001001
SDA	SDA	1001010
SDA	SCL	1001011
SCL	GND	1001100
SCL	V_{S+}	1001101
SCL	SDA	1001110
SCL	SCL	1001111



mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland	Size	A4
Title: Measurement sensors		Version	V1
Project: Pi4GPU (PiG)		Revision	R1
Variant: STD_PRO	RefDes: 900-949		
Designer: M. Folejewski	Sheet: 13 / 15		
File Name: [15] Sensors.SchDoc	Printed: 03.12.2022		


+3.3V @3A POWER SUPPLY (FOR PCIE ONLY)
7.5V - 28V INPUT
PP12000H_SYS
C751 10uF/35V
C752 10uF/35V
C753 10uF/35V
C761 10uF/35V
C762 10uF/35V
C763 10uF/35V
U750
VIN
EN
SS
EP GND
BST
SW
FB
COMP
AP64501SP-13
C760 100nF
C750 100nF
R750 10R
PP3300_PCIE_SW
PP3300_PCIE_FB
L750
3.3uH
R752 47k
C754 DNP
R754 15k
R753 12k
C764 DNP
C765 1.2nF
C755 10uF/10V
C756 10uF/10V
C757 10uF/10V
C758 10uF/10V
C759 100uF/10V
PP3300_PCIE_R
PP3300_PCIE
Shunt
R751 15k
LED750 Green
LAYOUT:
Place decoupling capacitors as close as possible to the Buck converter.
BOM:
3.3uH -> compatible components (7.3x6.6x2.4mm):
Changjiang Microelectronics Tech, MPN = FXL0624-3R3-M
Sumida, MPN = 0624CDMCCDS-3R3MC
AVX, MPN = LMLP07B7M3R3DTAS
+5V @3A POWER SUPPLY
7.5V - 28V INPUT
PP12000H_SYS
C767 10uF/35V
C768 10uF/35V
C769 10uF/35V
C777 10uF/35V
C778 10uF/35V
C779 10uF/35V
U751
VIN
EN
SS
EP GND
BST
SW
FB
COMP
AP64501SP-13
C776 100nF
C766 100nF
R755 10R
PP5000_SW
PP5000_FB
L751
3.3uH
R757 12k
C770 DNP
R760 2k26
R759 20k
C780 DNP
C781 1.2nF
C771 10uF/10V
C772 10uF/10V
C773 10uF/10V
C774 10uF/10V
C775 100uF/10V
PP5000_R
PP5000
Shunt
R756 15k
R758 15k
LED751 Green
LAYOUT:
Place decoupling capacitors as close as possible to the Buck converter.
BOM:
3.3uH -> compatible components (7.3x6.6x2.4mm):
Changjiang Microelectronics Tech, MPN = FXL0624-3R3-M
Sumida, MPN = 0624CDMCCDS-3R3MC
AVX, MPN = LMLP07B7M3R3DTAS
PP5000
PP5000
PP3300_PCIE
PP3300_PCIE
TP750
TP751
TP752
TP754
TP753
TP755
GND
mirko electronics
Mirko Electronics
Smoka Wawelskiego 1
30-535 Kraków, Poland
Size
A4
Title
Power supply
Version
V1
Project: Pi4GPU (PiG)
Variant: STD_PRO
Designer: M. Folejewski
File Name: [14] PWR2.SchDoc
RefDes: 900-949
Sheet: 13 / 15
Printed: 03.12.2022
Revision
R1

7.5V - 12V INPUT
12V NOMINAL

PP12000H_IN1

J700
1
2
SH
8A, 2.0mm

GND

PP12000H_IN2

J701
4 1
5 2
6 3
039-30-1060

GND
SENSE0
GND
+12V
+12V
+12V

GND

IDEAL DIODE

SCH:
Ideal diode to prevent reverse polarity at the input

PP12000H_IN1

FUS700
10A/125VDC

Q700
PMOS
SI7149ADP-T1-GE3

D701
SMAJ12A

D700
12V

R702
100k

C700
100nF/50V

R703
15k

R704
5k1

Q701
DTC143ZE

R705
0R
DNP

Q702
DTC143ZE

R708
5k1

PP12000H_SYS_R

Shunt

PP12000H_SYS

C701
220uF/25V

GND

LEDs

PP12000H_SYS

R700
100k

LED700
Green

PP12000H_PCIE

R701
100k

LED701
Green

PP12000H_IN1

R706
100k

LED702
Green

PP12000H_IN2

R707
100k

LED703
Green

GND

TESTPOINTS

TP700
TP701
TP702
TP703

GND

7.5V - 12V INPUT
12V NOMINAL

IDEAL DIODE

BOM:
Fuse: 10A/125V
Bel Fuse, MPN = 0679L9100-01
KOA Speer, MPN = CCF1F10TTE
Bourns, MPN = SF-2410FP1000T-2
Littelfuse, MPN = 0453010.NR

PP12000H_IN2

FUS701
10A/125VDC

Q703
PMOS
SI7149ADP-T1-GE3

D703
SMAJ12A

D702
12V

C702
100nF/50V

R709
15k

C704
220uF/25V

C703
10uF/35V

FUS702
10A/125VDC

PP12000H_PCIE_R

Shunt

PP12000H_PCIE

C705
220uF/25V

GND

PP12000H_IN1 TP704
PP12000H_IN1 TP705
PP12000H_IN2 TP706
PP12000H_IN2 TP707
PP12000H_SYS TP708
PP12000H_SYS TP709
PP12000H_PCIE TP710
PP12000H_PCIE TP711

12V PCIe POWER RAIL: ±8% (75W)
12V ±8% = 11.04V - 12.96V

PCIe Gen3 power requirement: 75W
12V -> 5.5A (66W)
3.3V -> 3A (9.9W)

mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title Power supply			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: 900-949	
Designer: M. Folejewski		Sheet: 13 / 15	
File Name: [13] PWR1.SchDoc		Printed: 03.12.2022	

CM4 MOUNTING HOLES

MH900 H270_C600
MH901 H270_C600
MH902 H270_C600
MH903 H270_C600

PCB MOUNTING HOLES

MH904 H320_C700 GND
MH905 H320_C700 GND
MH906 H320_C700 GND
MH907 H320_C700 GND

M2.5 STEEL SPACERS

MECH900 M2.5, L = 3.0mm
MECH901 M2.5, L = 3.0mm
MECH902 M2.5, L = 3.0mm
MECH903 M2.5, L = 3.0mm
SCR900 M2.5
SCR901 M2.5
SCR902 M2.5
SCR903 M2.5

BOM:

SMT Steel Spacer with internal Thread M2.5, L = 3.0mm:
Use Wurth Elektronik, MPN = 977 403 015 1.

PCB MARKING

FID900 Fiducial
FID901 Fiducial
FID902 Fiducial
FID903 Fiducial
FID904 Fiducial
FID905 Fiducial
PCB900 LAYER INDICATOR PCB_LAYER_STACKUP

ASSEMBLY VARIANT INDICATOR

R900 0R — LITE VARIANT
R901 0R — STD/PRO VARIANT

mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title: PCB marking & mechanical parts			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: 950-999	
Designer: M. Folejewski		Sheet: 14 / 15	
File Name: [16] PCB_Mech.SchDoc		Printed: 03.12.2022	

Hardware changelog

2022.10.27:
- project has started;
- imported schematics from existing designs;

2022.10.29:
- schematic update, minor changes;

2022.10.31:
- PCB shape according to PCIe standard;
- initial component placement of the front connectors;
- minor changes;

2022.11.02:
- added DC barrel jack;
- schematic: power supply update;

2022.11.03:
- component placement of the front connectors;
- microsd card: updated PCB edge;
- RefDes updated;

2022.11.09:
- power supply circuit created;
- added EC schematic page;
- minor changes;

2022.11.10:
- minor changes;
- RefDes updated;
- power supply circuit updated;

2022.11.14:
- Sensors: schematic circuit designed;

2022.11.15:
- PCB layout and component placement;

2022.11.16:
- PCB layout and component placement;

2022.11.17:
- PCB layout and component placement;

2022.11.18:
- PCB layout and component placement;

2022.11.21:
- PCB layout;

2022.11.22:
- PCB layout;

2022.11.23:
- PCB layout;

2022.11.24:
- PCB layout;

2022.11.25:
- PCB layout;

2022.11.26:
- PCB layout;

2022.11.27:
- PCB layout;

2022.11.29:
- Project released (V1/R1);

2022.12.03:
- Block diagram updated;

mirko electronics	Mirko Electronics Smoka Wawelskiego 1 30-535 Kraków, Poland		Size A4
Title Hardware changelog			Version V1
Project: Pi4GPU (PiG)			Revision R1
Variant: STD_PRO		RefDes: -	
Designer: M. Folejewski		Sheet: 15 / 15	
File Name: [17] Changelog.SchDoc		Printed: 03.12.2022	