

## DOCUMENTATION

Project Name: **Automation v3**

Description: Control 8-channel USB relay board from raspberry PI

### Hardware Requirements

1. Denkovi 8-Channel USB Relay <http://denkovi.com/usb-relay-boards>
2. Raspberry Pi 3 or recent model <https://www.raspberrypi.org/products/>

### Software Requirements

1. Raspbian <https://www.raspbian.org/>
2. Java 8 or latest <https://www.java.com/en/download/>
3. Termux <https://play.google.com/store/apps/details?id=com.termux&hl=en>

### Install Instruction

1. Click this [link](#) to download the installer
2. Open terminal
3. Ensure that you have connected your raspberry PI on the network, you can then check the IP address assigned to the device  
command: **ifconfig -a | grep 192.168**  
=> Router IP configuration have common starting IP of 192.168
4. Copy the downloaded file but make sure you know the IP assigned to the device  
command: **scp automation\_v3.zip pi@192.168.1.109:/home/pi**  
=> enter the password
5. Connect to your raspberry device  
command: **ssh pi@192.168.1.109**  
=> enter the password
6. Extract the installer zip file  
command: **unzip -P password automation\_v3.zip -d /home/pi/installation**  
**=> To request for password, I have included contact information below.**
7. Navigate to installation folder  
command: **cd /home/pi/installation/scripts**
8. Login as root:  
command: **sudo su**  
=> ensure that you are in scripts folder
9. Execute the script file  
command: **bash starter.sh**  
=> It will check for existing java on your machine and previous installation  
=> It should display "Installation complete" once the process is complete
10. Navigate to desktop directory of the user you specified and locate the folder automation  
command: **cd /home/pi/desktop/automation**  
=> Once you are in directory, notice that there are two files namely: **configuration.txt** and **masterlist.txt**, those are the files that you can edit to schedule timer on relay board.  
=> Follow this pattern for masterlist configuration. **RELAY\_POSITION=TIME:TIME-TIME**

=> Default mode for **configuration.txt** is **HOURLY** but you can change it to **MINUTES**  
=> Check the file `/docs/conversion.pdf` for proper time input


### Mobile Access (Android)

1. Open PlayStore
2. Install termux
3. Open termux application on your phone
4. Install SSH client, by executing the commands below:  
command: **sudo apt-get update**  
command: **sudo apt-get upgrade**  
command: **sudo apt-get install openssh**
4. Find the IPv4 address of your raspberry device (*ignore this step, if you already know the IP of your device*)  
command: **ifconfig -a | grep 192.168**  
=> You can also verify the IPv4 assigned from your router by comparing the mac address
5. Connect to your raspberry device  
command: **ssh pi@192.168.1.109**  
=> If your device and your phone is connected on same network you can access it.  
=> If you want to connect to the actual IP assigned by your ISP (*usually for remote access*), you must enable forwarding on your router and link your raspbebrry device.


### Wiring Instruction – **WARNING!! LIVE WIRE IS DEADLY REFER TO PROFESSIONALS**

1. The relay board consist of SPDT switch, meaning if there is power on the switch it will activate circuit 1 or activate circuit 2  
=> Normally Open (NO), Common, and Normally Closed (NC)
2. Connect the first wire to common then the second wire either NO or NC  
=> If you want to connect high load appliance like air conditioner, you must use solid state relay (SSR) for additional protection of your board. This is due to the fact that high load appliance generates more heat.

### Wiring Diagram 1



## Wiring Diagram 2 – with SSR (for high load appliance)



### Additional Information

Project URL: <https://mtagab.me/automation>

Systems Developer: Mark Tagab

Hometown: Iligan City, Philippines

LinkedIn: <https://www.linkedin.com/in/mtagab/>

Facebook: <https://www.facebook.com/mtagab007>

Contact

=> Email: [proxyshadow@gmail.com](mailto:proxyshadow@gmail.com)

=> Phone: +639155140113

Support

=> PayPal: <http://paypal.me/mtagab>

=> Cloud Referral: [DigitalOcean](#)