

# The Method of Moments for Antenna Simulation

Gijs Lagerweij

December 21, 2024

## Contents

<b>1</b>	<b>Introduction</b>	<b>2</b>
<b>2</b>	<b>Electromagnetic Theory</b>	<b>2</b>
2.1	Maxwell's Equations . . . . .	2
2.2	Green's Functions . . . . .	2
2.2.1	Electrostatic Green's Function . . . . .	2
2.2.2	Electrodynamic Green's Function . . . . .	3
2.3	Electric Field Integral Equation (EFIE) . . . . .	4
<b>3</b>	<b>Method of Moments</b>	<b>5</b>
3.1	Discretization . . . . .	5
3.2	Practical Matrix Assembly per Element . . . . .	6
3.3	Boundary Conditions . . . . .	6
3.4	Post-processing . . . . .	6
3.4.1	Antenna impedance . . . . .	6
3.4.2	Far-field radiation . . . . .	6

# 1 Introduction

## 2 Electromagnetic Theory

### 2.1 Maxwell's Equations

$$\nabla \times \mathbf{E} = -j\omega\mu\mathbf{H} \quad (1)$$

$$\nabla \times \mathbf{H} = j\omega\epsilon\mathbf{E} + \mathbf{J}_0 \quad (2)$$

$$\nabla \cdot \mathbf{D} = q_e \quad (3)$$

$$\nabla \cdot \mathbf{B} = 0 \quad (4)$$

### 2.2 Green's Functions

#### 2.2.1 Electrostatic Green's Function

Consider the electrostatic Poisson equation

$$\nabla^2 \phi = -\frac{\rho}{\epsilon}, \quad (5)$$

where  $\rho$  is the charge density. To find the electric potential due to an arbitrary charge configuration, we can apply the method using the electrostatic Green's function as outlined above. First, we find the impulse response  $G(r)$  such that

$$\nabla^2 G(\mathbf{r}) = -\frac{\delta(\mathbf{r})}{\epsilon}. \quad (6)$$

Expanding the Laplace operator in spherical coordinates, we find

$$\nabla^2 G = \frac{1}{r^2} \frac{\partial}{\partial r} \left[ r^2 \frac{\partial G}{\partial r} \right] = \frac{\partial^2 G}{\partial r^2} + \frac{2}{r} \frac{\partial G}{\partial r} = \frac{\partial^2 (rG)}{\partial r^2}$$

Outside of the point  $r = 0$ , the Dirac delta function is zero, such that

$$\frac{\partial^2 (rG)}{\partial r^2} = 0 \quad r > 0 \quad (7)$$

Integrating this differential equation twice gives us the general solution  $G(r) = a + \frac{b}{r}$ . We must have  $G \rightarrow 0$  as  $r \rightarrow \infty$ , so the coefficient  $a = 0$ . To find

coefficient  $b$ , we integrate the differential equation over a sphere of radius  $R$ :

$$\begin{aligned} b \iiint_V \nabla^2 \left( \frac{1}{r} \right) dV &= - \iiint_V \frac{\delta(r)}{\varepsilon} dV = -\frac{1}{\varepsilon} \\ \oiint_{\partial V} \nabla \left( \frac{1}{r} \right) \cdot \hat{\mathbf{r}} ds &= -\frac{1}{\varepsilon b} \\ \oiint_{\partial V} \frac{1}{r^2} ds &= \frac{1}{\varepsilon b} \\ 4\pi &= \frac{1}{\varepsilon b} \end{aligned}$$

Therefore, the electrostatic Green's function becomes

$$G(\mathbf{r}, \mathbf{r}') = \frac{1}{4\pi\varepsilon r}, \quad r = |\mathbf{r} - \mathbf{r}'|. \quad (8)$$

Then, the electric potential due to an arbitrary charge distribution  $\rho(\mathbf{r})$  is given by

$$\phi(\mathbf{r}) = \iiint G(\mathbf{r}, \mathbf{r}') \rho(\mathbf{r}') d\mathbf{r}' = \frac{1}{4\pi\varepsilon} \iiint \frac{\rho(\mathbf{r}')}{|\mathbf{r} - \mathbf{r}'|} d\mathbf{r}' \quad (9)$$

### 2.2.2 Electrodynamic Green's Function

Similarly, we can derive a Green's function which satisfies the scalar Helmholtz equation. It will be shown later that the electrodynamic equations resemble the (vector) Helmholtz equation. Consider

$$\nabla^2 G(\mathbf{r}, \mathbf{r}') + k^2 G(\mathbf{r}, \mathbf{r}') = -\delta(\mathbf{r}, \mathbf{r}') \quad (10)$$

Using the same derivation as before, we can equate the left-hand side to zero for  $r > 0$ .

$$\frac{\partial^2(rG)}{\partial r^2} + k^2(rG) = 0 \quad r > 0 \quad (11)$$

The solution to this differential equation is

$$G(r) = \frac{ae^{-jkr}}{r} + \frac{be^{+jkr}}{r}.$$

By requiring that  $G \rightarrow 0$  as  $r \rightarrow \infty$ , we find that  $b = 0$ . To find coefficient  $a$ , we again integrate over a sphere of radius  $R$ .

$$a \iiint_V \nabla^2 \left( \frac{e^{-jkr}}{r} \right) + k^2 \left( \frac{e^{-jkr}}{r} \right) dV = -1$$

The first part of the integral can be tackled by applying the divergence theorem:

$$\iiint_V \nabla^2 \left( \frac{e^{-jkr}}{r} \right) dV = \oint_{\partial V} \nabla \left( \frac{e^{-jkr}}{r} \right) \cdot \hat{\mathbf{r}} ds = 4\pi a^2 \left[ \frac{\partial}{\partial r} \left( \frac{e^{-jkr}}{r} \right) \right]_{r=R}$$

$$\lim_{R \rightarrow 0} 4\pi a^2 \left[ \frac{\partial}{\partial r} \left( \frac{e^{-jkr}}{r} \right) \right]_{r=R} = -4\pi$$

The second part of the integral is calculated by inspection:

$$\iiint_V k^2 \left( \frac{e^{-jkr}}{r} \right) dV = 4\pi k^2 R^2 \int_0^R \frac{e^{-jkr}}{r} dr$$

$$\lim_{R \rightarrow 0} 4\pi k^2 R^2 \int_0^R \frac{e^{-jkr}}{r} dr = 0$$

Therefore, we find that the coefficient  $a = \frac{1}{4\pi}$  and the electrodynamic Green's function is

$$G(\mathbf{r}, \mathbf{r}') = \frac{e^{-jkr}}{4\pi r}, \quad r = |\mathbf{r} - \mathbf{r}'|. \quad (12)$$

## 2.3 Electric Field Integral Equation (EFIE)

$$\nabla \times \nabla \times \mathbf{E} = -j\omega\mu(j\omega\varepsilon\mathbf{E} + \mathbf{J}) = \nabla(\nabla \cdot \mathbf{E}) - \nabla^2 \mathbf{E}$$

Gathering the unknown  $\mathbf{E}$  on the left-hand side, and the source terms involving  $\mathbf{J}$  on the right:

$$\nabla^2 \mathbf{E} + k^2 \mathbf{E} = j\omega\mu\mathbf{J} - \frac{\nabla(\nabla \cdot \mathbf{J})}{j\omega\varepsilon} \quad (13)$$

This equation has the vector Helmholtz form with wavenumber  $k = \omega/c = \omega\sqrt{\mu\varepsilon}$ . Using the electrodynamic Green's function derived above, we get an integral equation for the electric field.

$$\mathbf{E}(\mathbf{r}) = -j\omega\mu \iiint G(\mathbf{r}, \mathbf{r}') \left[ 1 + \frac{\nabla' \cdot \nabla'}{k^2} \right] \mathbf{J}(\mathbf{r}') d\mathbf{r}' \quad (14)$$

Equation (14) is called the *electric field integral equation* (EFIE) and can also be written more compactly in terms of the operator  $\mathcal{L}$ .

$$\mathbf{E}(\mathbf{r}) = -j\omega\mu(\mathcal{L}\mathbf{J})(\mathbf{r}), \quad (15)$$

where

$$(\mathcal{L}\mathbf{X})(\mathbf{r}) = \iiint G(\mathbf{r}, \mathbf{r}') \left[ 1 + \frac{\nabla' \cdot \nabla'}{k^2} \right] \mathbf{X}(\mathbf{r}') d\mathbf{r}' \quad (16)$$

## 3 Method of Moments

### 3.1 Discretization

Starting from the EFIE, we expand the unknown current distribution  $\mathbf{J}(\mathbf{r})$  into a series of basis functions:

$$\mathbf{J}(\mathbf{r}) = \sum_{n=1}^N I_n \mathbf{f}_n(\mathbf{r}), \quad (17)$$

where  $I_n$  are the unknown coefficients representing the current, and  $\mathbf{f}_n(\mathbf{r})$  are the vector basis functions. Many choices of basis are possible, but we will use the triangular basis functions shown in Figure 1. The orientation of the basis vectors is further discussed in Section 3.3.

Figure 1: Triangular basis function

Substituting (17) into the EFIE, the  $\mathcal{L}$  operator now operates on the (known) basis functions.

$$\mathbf{E}(\mathbf{r}) = j\omega\mu \sum_{n=1}^N I_n (\mathcal{L}\mathbf{f}_n)(\mathbf{r}) \quad (18)$$

Next, we can test (18) with the same basis functions  $\mathbf{f}_m(\mathbf{r})$  with  $m = 1, \dots, N$ .

$$\langle \mathbf{f}_m, \mathbf{E} \rangle = j\omega\mu \sum_{n=1}^N I_n \langle \mathbf{f}_m, \mathcal{L}\mathbf{f}_n \rangle \quad m = 1, \dots, N \quad (19)$$

This results in a square  $N \times N$  system of equations.

$$\{V\} = [Z] \{I\}, \quad (20)$$

with

$$\begin{aligned} V_m &= \int_{f_m} \mathbf{f}_m(\mathbf{r}) \cdot \mathbf{E}(\mathbf{r}) d\mathbf{r} \\ Z_{mn} &= j\omega\mu \int_{f_m} \int_{f_n} \mathbf{f}_m(\mathbf{r}) \cdot \mathbf{f}_n(\mathbf{r}') G_k(\mathbf{r}, \mathbf{r}') d\mathbf{r}' d\mathbf{r} \\ &\quad - \frac{1}{j\omega} \int_{f_m} \int_{f_n} \nabla \cdot \mathbf{f}_m(\mathbf{r}) \nabla' \cdot \mathbf{f}_n(\mathbf{r}') G_k(\mathbf{r}, \mathbf{r}') d\mathbf{r}' d\mathbf{r} \end{aligned}$$

For ease of notation and to clarify the physical role each integral term plays, we redefine the impedance contribution in terms of the vector potential  $\mathbf{A}$  and the scalar potential  $\Phi$ .

$$Z_{mn} = j\omega\mu A_{mn} - \frac{j}{\omega\epsilon} \Phi_{mn} = jk\eta_0 \left( A_{mn} - \frac{1}{k^2} \Phi_{mn} \right), \quad (21)$$

where

$$A_{mn} = \int_{f_m} \int_{f_n} \mathbf{f}_m(\mathbf{r}) \cdot \mathbf{f}_n(\mathbf{r}') G_k(\mathbf{r}, \mathbf{r}') d\mathbf{r}' d\mathbf{r} \quad (22)$$

$$\Phi_{mn} = \int_{f_m} \int_{f_n} \nabla \cdot \mathbf{f}_m(\mathbf{r}) \nabla' \cdot \mathbf{f}_n(\mathbf{r}') G_k(\mathbf{r}, \mathbf{r}') d\mathbf{r}' d\mathbf{r} \quad (23)$$

### 3.2 Practical Matrix Assembly per Element

### 3.3 Boundary Conditions

Two boundary conditions arise from the equation of charge conservation:

1. The basis vectors  $\mathbf{a}_n$  should be oriented such that (24) holds at every node.
2. A condition  $I = 0$  must be imposed on the end-points of every segment, as this is the only way to enforce (24).

$$\nabla \cdot \mathbf{J} = 0 \quad (24)$$

### 3.4 Post-processing

#### 3.4.1 Antenna impedance

To calculate the impedance seen by a source embedded in segment  $e$ , with nodes  $n_1, n_2$ , we make use of the current coefficient vector  $\{I\}$ . The impedance is defined as

$$Z = \frac{V_{src}}{I_{src}}, \quad (25)$$

where  $V_{src}$  is the known source voltage and  $I_{src}$  is the solved current averaged over segment  $e$ :

$$I_{src} = \frac{1}{2} (I[n_1] + I[n_2])$$

#### 3.4.2 Far-field radiation

The far-field radiation pattern can also be derived from the solved current vector. The EFIE can be simplified by assuming that the  $1/r$  are dominant, and that higher order terms have negligible amplitude in the far field.

$$\mathbf{E}(\mathbf{r}) = -j\omega\mu \int \mathbf{J}(\mathbf{r}') G_k(\mathbf{r}, \mathbf{r}') d\mathbf{r}' \quad (26)$$

This expression can be further simplified by considering that  $\mathbf{r} \gg \mathbf{r}'$ , such that

$$|\mathbf{r} - \mathbf{r}'| = \begin{cases} r & \text{for amplitude variations} \\ r - \mathbf{r}' \cdot \hat{\mathbf{r}} & \text{for phase variations} \end{cases} \quad (27)$$

Applying (27) to (26) yields

$$\mathbf{E}(\mathbf{r}) = j\omega\mu \frac{e^{-jk r}}{4\pi r} \int ((\hat{\mathbf{r}} \cdot \mathbf{J}(\mathbf{r}'))\hat{\mathbf{r}} - \mathbf{J}(\mathbf{r}')) e^{jk\mathbf{r}' \cdot \hat{\mathbf{r}}} d\mathbf{r}' \quad (28)$$

Applying the same discretization procedure,

$$\mathbf{E}(\mathbf{r}) = j\omega\mu \frac{e^{-jk r}}{4\pi r} \sum_{n=1}^N I_n \int_{f_n} ((\hat{\mathbf{r}} \cdot \hat{\mathbf{a}}_n)\hat{\mathbf{r}} - \hat{\mathbf{a}}_n) f_n(\mathbf{r}') e^{jk\mathbf{r}' \cdot \hat{\mathbf{r}}} d\mathbf{r}' \quad (29)$$

The integral can be tackled using quadrature and all the terms are known.