POWERMATIC 1200

Wire installation guide

Device labeling and connector preparation, followed by the complete 131-row installation checklist.

Preparation and sequence

Use pages 2-5 for device labels, connector identification, and bin placement. The checklist on pages 6-8 contains 129 native wires plus two supplemental pendant jumpers. Rows 1-82 and 120-123 are bench work. Rows 83-119 and 124-131 require the backpanel and off-panel devices to be installed. Defer each complete external connection until installation.

Pendant jumpers

Rows 104 and 105 add S2_1T to S2_3T and S2_3T to S2_5T. Row 111 is S2_2B to S2_4B. All three remain pending in the saved installation record. Use 16 AWG blue wire and RA rings at both ends; strip 9.5 mm. The two supplemental rows must be restored when rebuilding a checklist from the native 129-row schedule.

Keeping the checklist current

Project Review Refresh updates Wire_schedule.csv and Wire_length_totals.csv. It does not rebuild this PDF. Reconcile and rebuild the printable checklist after changing the native wiring. The installation groups, terminal cross-reference, and supplemental-jumper record are preserved in WIRING_STANDARD.md.

Page guide

PDF pages	Contents
2	Device and terminal labeling prerequisites
3	Connector inventory and preparation reference
4	Retained connector case and identification
5	32-compartment connector-bin placement and strip settings
6-8	Wire installation checklist, rows 1-131

Consolidated 9 November 2026. Original sheets retain their dimensions and content. Use PDF bookmarks to select a section.

Apply device labels; add terminal labels only where unmarked

	Device	Terminal labels	Locations
☐	Terminal blocks	top, bottom	Existing module-letter device labels
☐	G1-G6	top, bottom	top: pin 1; bottom: pin 2
☐	F4	top, bottom	top: source / pin 1; bottom: load / pin 2
☐	FH1	P1A, P1B, P2A, P2B, P3A, P3B	Left to right: P1, P2, P3; A top; B bottom
☐	K1	31NC, 32NC, 43NO, 44NO, A1_top, A2_top, A1_bottom, A2_bottom, R/1/L1, S/3/L2, T/5/L3, U/2/T1, V/4/T2, W/6/T3	Suppressor at both top clamps. Both field coil wires use bottom.
☐	K2	31NC, 32NC, 43NO, 44NO, A1_top, A2_top, A1_bottom, A2_bottom, R/1/L1, S/3/L2, T/5/L3, U/2/T1, V/4/T2, W/6/T3	Suppressor at both top clamps. Both field coil wires use bottom.
☐	K3	13, 14, 23, 24, 31, 32, 41, 42, A1+, A2	
☐	K4	31NC, 32NC, 43NO, 44NO, A1_top, A2_top, A1_bottom, A2_bottom, R/1/L1, S/3/L2, T/5/L3, U/2/T1, V/4/T2, W/6/T3	Suppressor at both top clamps. Both field coil wires use bottom.
☐	K5	31NC, 32NC, 43NO, 44NO, A1_top, A2_top, A1_bottom, A2_bottom, R/1/L1, S/3/L2, T/5/L3, U/2/T1, V/4/T2, W/6/T3	Suppressor at both top clamps. Both field coil wires use bottom.
☐	K6	31NC, 32NC, 43NO, 44NO, A1_top, A2_top, A1_bottom, A2_bottom, R/1/L1, S/3/L2, T/5/L3, U/2/T1, V/4/T2, W/6/T3	Suppressor at both top clamps. Both field coil wires use bottom.
☐	KA1	51NC, 52NC, 63NO, 64NO	
☐	OL4	2T1, 4T2, 6T3, 95NC, 96NC, 97NO, 98NO	
☐	OL6	2T1, 4T2, 6T3, 95NC, 96NC, 97NO, 98NO	
☐	PS1	+V, -V, L, N, ⏚	-V: first output screw; +V: third output screw
☐	Q1	1, 2, 3, 4	
☐	TD1	15, 16, 18, A1, A2, A3(+), B1(+)	
☐	TD2	15, 16, 18, A1, A2, A3(+), B1(+)	
☐	GL1	PE	Use existing earth mark; otherwise label PE
☐	GL2	PE	Use existing earth mark; otherwise label PE
☐	GS1	PE1, PE2, PE3	One WB splice: PE1 to GL1; PE2 to GL2; PE3 to G2
☐	H1	X1, X2	
☐	H2	X1, X2	
☐	J1	1, 2, 3, 4	
☐	J2	BLK, GRN, RED, WHT	Unmarked ends: apply labels matching wire colors
☐	J5	PE	Use existing earth mark; otherwise label PE
☐	J7	PE	Use existing earth mark; otherwise label PE
☐	J8	PE	Use existing earth mark; otherwise label PE
☐	M1	PE1, PE2, PE3, T1, T2, T3, T4, T5, T6	T1-T6: six WA splices; one WB splice: PE1 to G1; PE2 to J5; PE3 to J7; T1-T6 tags confirmed by owner
☐	S2	1B, 1T, 2B, 2T, 3B, 3T, 4B, 4T, 5T, 6T	Unmarked: apply these terminal labels before wiring
☐	S3	1T-8T; 1B-8B	T top; B bottom. Left: 1,3,5,7; right: 2,4,6,8
☐	SW1	1/L1, 2T1, 3/L2, 4/T2, 5/L3, 6/T3	Rear view: top 5/L3, 3/L2, 1/L1; bottom 6/T3, 4/T2, 2T1

Connector types - inventory codes, 2026-11-03

Bin	Color	Type	AWG	Area mm2	Barrel mm	Stud	Tab mm	Width mm	Ports	Supplier	SPN
FA	GRY	Ferrule	22-20	0.75	10					MCMC	7950K16
FB	RED	Ferrule	18	1	6					MCMC	7950K71
FC	RED	Ferrule	18	1	10					MCMC	7950K73
FD	BLK	Ferrule	16	1.5	10					MCMC	7950K24
FE	BLU	Ferrule	14	2.5	10					DK	3202533
FF	GRY	Ferrule	12	4	10					MCMC	7950K31
FG	WHT	Ferrule	22	0.5	8					AE	1181050
FH	GRY	Ferrule	20	0.75	8					AE	1181075
FI	RED	Ferrule	18	1	8					AE	1181010
FJ	BLK	Ferrule	16	1.5	8					AE	1181015
FK	BLU	Ferrule	14	2.5	8					AE	1181025
RA	BLU	Ring	16-14			#8		8.4		MCMC	7113K49
RB	BLU	Ring	16-14			#10		8.4		MCMC	7113K24
RC	YEL	Ring	12-10			M5		9.5		MCMC	8429T62
RD	YEL	Ring	16-12			5/16 in		15.5		MCMC	9388K35
RE	RED	Ring	22-18			#6		6.4		MCMC	7113K35
RF	BLU	Ring	16-14			#6		6.4		MCMC	7113K23
RG	BLU	Ring	16-14			1/4 in		11.9		MCMC	7113K25
RH	YEL	Ring	12-10			#10		9.7		MCMC	7113K29
RI	YEL	Ring	12-10			3/8 in		15		MCMC	7113K32
RJ	BLU	Ring nylon	16-14			#8		8.4		3M	12-8-NB
SA	RED	Fork	22-18			#6		8.6		MCMC	69145K211
SB	BLU	Fork	16-14			#6		8.6		MCMC	69145K214
SC	BLU	Fork	16-14			#10		8.6		MCMC	69145K216
SD	YEL	Fork	12-10			#10		9.7		MCMC	69145K218
SE	BLU/TURQ	Blade female	16-14				6.35			MCMC	7243K21
SF	BLU/TURQ	Blade male	16-14				6.35			MCMC	7243K22
SG	YEL	Fork lock	12-10			1/4 in		12.2		3M	SS-33-14-NB
WA	CLR/ORG	Splice	20-10	0.5-6					2	AD	221-612
WB	CLR/ORG	Splice	20-10	0.5-6					3	AD	221-613

AE = American Electrical. FG-FK: 8 mm single-wire ferrules from kit 1617050.
RJ: 3M nylon ring with insulation grip; distinct from the existing vinyl ring RA.
SG: 3M locking fork. Width includes the locking ears (12.2 mm maximum).
SE/SF: fully insulated female/male blades, 6.35 x 0.81 mm mating tab.
The retained kit types match the chart by position, shape and wire-color class.
FA wire range is 22-20 AWG, confirmed by the owner on 2026-11-03.

Retained connector case - label placement

View with the hinge at the top; the two labeled additions are in the right column.

The lid chart is vertically mirrored relative to the tray. Empty cells remain empty.

HINGE

Empty	Empty	Empty	RE Ring 22-18 AWG Stud #6 7113K35	RF Ring 16-14 AWG Stud #6 7113K23	RJ Ring nylon 16-14 AWG Stud #8 12-8-NB
RB Ring 16-14 AWG Stud #10 7113K24	RG Ring 16-14 AWG Stud 1/4 in 7113K25	RH Ring 12-10 AWG Stud #10 7113K29	RI Ring 12-10 AWG Stud 3/8 in 7113K32	SA Fork 22-18 AWG Stud #6 69145K211	RJ label Label only
SB Fork 16-14 AWG Stud #6 69145K214	SC Fork 16-14 AWG Stud #10 69145K216	SD Fork 12-10 AWG Stud #10 69145K218	Empty	Empty	SG Fork lock 12-10 AWG Stud 1/4 in SS-33-14-NB
Empty	Empty	SE Blade female 16-14 AWG Tab 6.35 mm 7243K21	SF Blade male 16-14 AWG Tab 6.35 mm 7243K22	Empty	SG Fork lock 12-10 AWG Stud 1/4 in SS-33-14-NB

RJ: blue 3M 12-8-NB ring, 16-14 AWG, #8 stud.

SG: yellow 3M SS-33-14-NB locking fork, 12-10 AWG, 1/4-inch stud.

Both yellow-fork cells at the right belong to SG; the paper label is in the lower cell.

Sort the stray yellow fork pieces out of RJ and the stray blue blade pieces out of SG.

RB already identifies the retained blue #10 ring (McMaster 7113K24).

BLU/TURQ records the blue gauge class and turquoise appearance of SE/SF.

Stud sizes follow the chart; loose-piece markings and dimensions are not measured here.

FA 10 mm Ferrule 22-20 AWG MC 7950K16 strip 10mm	**FB** 6 mm Ferrule 18 AWG MC 7950K71 strip 6mm	**FC** 10 mm Ferrule 18 AWG MC 7950K73 strip 10mm	**FD** 10 mm Ferrule 16 AWG MC 7950K24 strip 12mm	**FE** 10 mm Ferrule 14 AWG PX 3202533 strip 13mm	**FF** 10 mm Ferrule 12 AWG MC 7950K31 strip 12mm	**FG** 8 mm Ferrule 22 AWG AE 1181050 strip 8mm	**FH** 8 mm Ferrule 20 AWG AE 1181075 strip 8mm
FI 8 mm Ferrule 18 AWG AE 1181010 strip 8mm	**FJ** 8 mm Ferrule 16 AWG AE 1181015 strip 8mm	**FK** 8 mm Ferrule 14 AWG AE 1181025 strip 8mm	**RA** #8 Ring 16-14 AWG MC 7113K49 strip 9.5mm	**RB** #10 Ring 16-14 AWG MC 7113K24 strip 9.5mm	**RC** M5 Ring 12-10 AWG MC 8429T62 strip 8mm	**RD** 5/16" Ring 16-12 AWG MC 9388K35 strip 9.5mm	**RE** #6 Ring 22-18 AWG MC 7113K35 strip 9.5mm
RF #6 Ring 16-14 AWG MC 7113K23 strip 9.5mm	**RG** 1/4" Ring 16-14 AWG MC 7113K25 strip 9.5mm	**RH** #10 Ring 12-10 AWG MC 7113K29 strip 9.5mm	**RI** 3/8" Ring 12-10 AWG MC 7113K32 strip 9.5mm	**RJ** #8 Nylon Ring 16-14 AWG 3M 12-8-NB strip 9.5mm	**SA** #6 Fork 22-18 AWG MC 69145K211 strip 9.5mm	**SB** #6 Fork 16-14 AWG MC 69145K214 strip 9.5mm	**SC** #10 Fork 16-14 AWG MC 69145K216 strip 9.5mm
SD #10 Fork 12-10 AWG MC 69145K218 strip 9.5mm	**SE** 1/4" Female Spade 16-14 AWG MC 7243K21 strip 9.5mm	**SF** 1/4" Male Spade 16-14 AWG MC 7243K22 strip 9.5mm	**SG** 1/4" Locking Fork 12-10 AWG 3M SS-33-14-NB strip 9.5mm	**WA** 2-Port WAGO 20-10 AWG WAGO 221-612 strip 13mm	**WB** 3-Port WAGO 20-10 AWG WAGO 221-613 strip 13mm	Spare	Spare

Wire installation checklist

	No.	Wire	From	To	Connector	Connector
☐	1	14AWG BLK	K1_R/1/L1	K2_R/1/L1	FE	FE
☐	2	14AWG BLK	K1_S/3/L2	K2_S/3/L2	FE	FE
☐	3	14AWG BLK	K1_T/5/L3	K2_T/5/L3	FE	FE
☐	4	14AWG BLK	K1_U/2/T1	K2_W/6/T3	FE	FE
☐	5	14AWG BLK	K1_V/4/T2	K2_V/4/T2	FE	FE
☐	6	14AWG BLK	K1_W/6/T3	K2_U/2/T1	FE	FE
☐	7	14AWG BLK	5A_top	K2_R/1/L1	FE	FE
☐	8	14AWG BLK	5C_top	K1_S/3/L2	FE	FE
☐	9	14AWG BLK	5B_bottom	Q1_1	FE	12mm bare
☐	10	14AWG BLK	5D_bottom	Q1_3	FE	12mm bare
☐	11	14AWG BLK	PS1_L	Q1_2	5mm bare	12mm bare
☐	12	14AWG BLK	PS1_N	Q1_4	5mm bare	12mm bare
☐	13	14AWG BLK	5E_bottom	K1_U/2/T1	FE	FE
☐	14	14AWG BLK	5E_top	K6_R/1/L1	FE	10mm bare
☐	15	14AWG BLK	5F_bottom	K4_R/1/L1	FE	10mm bare
☐	16	14AWG BLK	5G_bottom	K1_V/4/T2	FE	FE
☐	17	14AWG BLK	5G_top	K6_S/3/L2	FE	10mm bare
☐	18	14AWG BLK	5H_bottom	K4_S/3/L2	FE	10mm bare
☐	19	14AWG BLK	5J_bottom	K1_W/6/T3	FE	FE
☐	20	14AWG BLK	5J_top	K6_T/5/L3	FE	10mm bare
☐	21	14AWG BLK	5K_bottom	K4_T/5/L3	FE	10mm bare
☐	22	14AWG BLK	1A_bottom	OL4_2T1	FE	10mm bare
☐	23	14AWG BLK	1C_bottom	OL4_4T2	FE	10mm bare
☐	24	14AWG BLK	1E_bottom	OL4_6T3	FE	10mm bare
☐	25	14AWG BLK	1B_bottom	K5_U/2/T1	FE	10mm bare
☐	26	14AWG BLK	1D_bottom	K5_V/4/T2	FE	10mm bare
☐	27	14AWG BLK	1F_bottom	K5_W/6/T3	FE	10mm bare
☐	28	14AWG BLK	1G_bottom	OL6_2T1	FE	10mm bare
☐	29	14AWG BLK	1H_bottom	OL6_4T2	FE	10mm bare
☐	30	14AWG BLK	1J_bottom	OL6_6T3	FE	10mm bare
☐	31	14AWG BLK	K5_R/1/L1	K5_S/3/L2	10mm bare	10mm bare
☐	32	14AWG BLK	K5_S/3/L2	K5_T/5/L3	10mm bare	10mm bare
☐	33	18AWG BLU	2C_bottom	PS1_-V	FC	5mm bare
☐	34	18AWG BLU	2A_bottom	K3_A2	FC	8mm bare
☐	35	18AWG BLU	2A_top	K4_A2_bottom	FC	8mm bare
☐	36	18AWG BLU	2C_top	K1_A2_bottom	FC	8mm bare
☐	37	18AWG BLU	2D_top	K2_A2_bottom	FC	8mm bare
☐	38	18AWG BLU	2E_bottom	K6_A2_bottom	FC	8mm bare
☐	39	18AWG BLU	2E_top	K5_A2_bottom	FC	8mm bare
☐	40	18AWG BLU	2D_bottom	TD1_A2	FC	7mm bare
☐	41	18AWG BLU	2F_top	TD2_A2	FC	7mm bare
☐	42	18AWG BLU	F4_top	PS1_+V	FC	5mm bare
☐	43	18AWG BLU	4D_bottom	F4_bottom	FC	FC
☐	44	18AWG BLU	4C_top	K3_13	FC	8mm bare

Wire installation checklist

	No.	Wire	From	To	Connector	Connector
☐	45	18AWG BLU	4C_bottom	K3_31	FC	8mm bare
☐	46	18AWG BLU	K3_14	K3_23	8mm bare	8mm bare
☐	47	18AWG BLU	K3_24	OL4_95NC	8mm bare	8mm bare
☐	48	18AWG BLU	OL4_96NC	OL6_95NC	8mm bare	8mm bare
☐	49	18AWG BLU	K1_32NC	K2_A1_bottom	8mm bare	8mm bare
☐	50	18AWG BLU	K1_A1_bottom	K2_32NC	8mm bare	8mm bare
☐	51	18AWG BLU	K4_A1_bottom	K6_32NC	8mm bare	8mm bare
☐	52	18AWG BLU	K5_32NC	KA1_51NC	8mm bare	8mm bare
☐	53	18AWG BLU	K5_44NO	K6_A1_bottom	8mm bare	8mm bare
☐	54	18AWG BLU	K5_A1_bottom	TD1_18	8mm bare	7mm bare
☐	55	18AWG BLU	3B_top	K4_31NC	FC	8mm bare
☐	56	18AWG BLU	3D_top	K4_32NC	FC	8mm bare
☐	57	18AWG BLU	1S_bottom	3A_top	FC	FC
☐	58	18AWG BLU	3A_bottom	K1_43NO	FC	8mm bare
☐	59	18AWG BLU	3B_bottom	K2_43NO	FC	8mm bare
☐	60	18AWG BLU	1N_bottom	K2_31NC	FC	8mm bare
☐	61	18AWG BLU	1Q_bottom	K1_31NC	FC	8mm bare
☐	62	18AWG BLU	1P_bottom	K1_44NO	FC	8mm bare
☐	63	18AWG BLU	1R_bottom	K2_44NO	FC	8mm bare
☐	64	18AWG BLU	1K_bottom	K4_44NO	FC	8mm bare
☐	65	18AWG BLU	1L_bottom	K6_44NO	FC	8mm bare
☐	66	18AWG BLU	1Y_bottom	3E_top	FC	FC
☐	67	18AWG BLU	1Z_bottom	3H_top	FC	FC
☐	68	18AWG BLU	3C_bottom	K5_31NC	FC	8mm bare
☐	69	18AWG BLU	3C_top	K4_43NO	FC	8mm bare
☐	70	18AWG BLU	1T_bottom	K6_43NO	FC	8mm bare
☐	71	16AWG BLU	1U_bottom	K5_43NO	FD	8mm bare
☐	72	16AWG BLU	1V_bottom	K6_31NC	FD	8mm bare
☐	73	16AWG BLU	1W_bottom	OL6_96NC	FD	8mm bare
☐	74	18AWG BLU	1X_bottom	TD2_18	FC	7mm bare
☐	75	18AWG BLU	3D_bottom	TD1_A3(+)	FC	7mm bare
☐	76	18AWG BLU	3E_bottom	TD1_15	FC	7mm bare
☐	77	18AWG BLU	3F_bottom	KA1_63NO	FC	8mm bare
☐	78	18AWG BLU	3G_bottom	KA1_64NO	FC	8mm bare
☐	79	18AWG BLU	3G_top	TD1_B1(+)	FC	7mm bare
☐	80	18AWG BLU	3J_bottom	TD2_A3(+)	FC	7mm bare
☐	81	18AWG BLU	3J_top	KA1_52NC	FC	8mm bare
☐	82	18AWG BLU	3K_bottom	TD2_15	FC	7mm bare
☐	83	12AWG WHT	FH1_P3B	J2_WHT	RC	bare
☐	84	12AWG RED	FH1_P2B	J2_RED	RC	bare
☐	85	12AWG BLK	FH1_P1B	J2_BLK	RC	bare
☐	86	14AWG BLK	FH1_P3A	SW1_5/L3	RB	12mm bare
☐	87	14AWG BLK	FH1_P2A	SW1_3/L2	RB	12mm bare
☐	88	14AWG BLK	FH1_P1A	SW1_1/L1	RB	12mm bare

Wire installation checklist

	No.	Wire	From	To	Connector	Connector
☐	89	14AWG BLK	5A_bottom	SW1_2T1	FE	12mm bare
☐	90	14AWG BLK	5C_bottom	SW1_4/T2	FE	12mm bare
☐	91	14AWG BLK	K1_T/5/L3	SW1_6/T3	FE	12mm bare
☐	92	14AWG BLK	1A_top	M1_T1	FE	WA
☐	93	14AWG BLK	1C_top	M1_T2	FE	WA
☐	94	14AWG BLK	1E_top	M1_T3	FE	WA
☐	95	14AWG BLK	1G_top	M1_T4	FE	WA
☐	96	14AWG BLK	1H_top	M1_T5	FE	WA
☐	97	14AWG BLK	1J_top	M1_T6	FE	WA
☐	98	18AWG BLU	2B_bottom	H1_X2	FC	FB
☐	99	18AWG BLU	2B_top	H2_X2	FC	FB
☐	100	22AWG BLU	4A_bottom	J1_3	FA	na
☐	101	22AWG WHT	4A_top	J1_2	FA	na
☐	102	22AWG BRN	4B_bottom	J1_1	FA	na
☐	103	22AWG BLK	J1_4	K3_A1+	na	8mm bare
☐	104	16AWG BLU	S2_1T	S2_3T	RA	RA
☐	105	16AWG BLU	S2_3T	S2_5T	RA	RA
☐	106	16AWG BLU	1M_top	S2_2B	FD	RA
☐	107	16AWG BLU	1N_top	S2_1B	FD	RA
☐	108	16AWG BLU	1Q_top	S2_3B	FD	RA
☐	109	16AWG BLU	1S_top	S2_6T	FD	RA
☐	110	16AWG BLU	1W_top	S2_5T	FD	RA
☐	111	16AWG BLU	S2_2B	S2_4B	RA	RA
☐	112	16AWG BLU	1T_top	S3_2B	FD	RA
☐	113	16AWG BLU	1U_top	S3_2T	FD	RA
☐	114	16AWG BLU	1V_top	S3_1T	FD	RA
☐	115	16AWG BLU	1X_top	S3_1B	FD	RA
☐	116	16AWG BLU	1Y_top	S3_3B	FD	RA
☐	117	16AWG BLU	1Z_top	S3_3T	FD	RA
☐	118	18AWG BLU	4D_top	H1_X1	FC	FB
☐	119	18AWG BLU	H2_X1	K3_32	FB	8mm bare
☐	120	12AWG GRN/YEL	G4_top	G5_top	FF	FF
☐	121	12AWG GRN/YEL	G1_bottom	G5_bottom	FF	FF
☐	122	12AWG GRN/YEL	G2_bottom	G3_top	FF	FF
☐	123	14AWG GRN/YEL	G6_bottom	PS1_⏚	FE	5mm bare
☐	124	12AWG GRN	G4_bottom	J2_GRN	FF	bare
☐	125	12AWG GRN/YEL	G6_top	J8_PE	FF	RD
☐	126	14AWG GRN/YEL	GL1_PE	GS1_PE1	10mm bare	WB
☐	127	14AWG GRN/YEL	GL2_PE	GS1_PE2	10mm bare	WB
☐	128	14AWG GRN/YEL	G2_top	GS1_PE3	FE	WB
☐	129	12AWG GRN/YEL	G1_top	M1_PE1	FF	WB
☐	130	10AWG GRN/YEL	J5_PE	M1_PE2	na	WB
☐	131	10AWG GRN/YEL	J7_PE	M1_PE3	na	WB