

Controlled Shop Pack

At-machine working set - controlled braking followed by delayed STO and line isolation

Implementation documents

- Wire Schedule Rev K is the point-to-point build authority. Ferrule number equals wire number.
- Ladder Logic Rev K is the CLICK PLUS programming authority.
- This Shop Pack supplies the one-line, safety loop, VFD card, and validation sequence.
- The owner-maintained BOM Rev K is the sourcing authority.
- The SCCR Worksheet Rev K records personal-shop SCCR due diligence and field verification.

Rev K safety and hardware decisions

- Dold BH5928-92-61-24-1: 24 V, fixed screw terminals, 0.1-1.0 s adjustable release delay.
- Instantaneous safety contacts independently open Run-FWD and Run-REV. The GS20 performs a controlled ramp stop.
- Three Phoenix Contact 2966265 modules: CR-S1 asserts safety DI4, CR-S2 sources X013, and CR-DB asserts thermal DI4.
- Three BH5928 delayed contacts independently open the TD-DB/Contactor A path, STO1, and STO2. X011 proves KA status.
- TD-DB 2910140 delays thermal KA dropout after CR-DB immediately commands DI4. Hardware recovery is automatic; motion requires a fresh command.
- No BH5928 delayed output remains spare and Rev K includes no mechanical brake.
- Initial drive deceleration is 0.50 s; commission the relay at 1.00 s. Final delay is provisional until measured.

Fuse map

Position	Protects	Holder	Element	Rating
Branch (3x)	VFD input branch	LFT300603C, 3-pole	TJN35 x3	35 A Class T
PSU-FU	208 V PSU tap	DN-F10MN x2	GMC3 x2	3 A time-delay
KB-FU	Contactor-B tap	DN-F10MN x2	GMC3 x2	3 A time-delay
24V-FU	+24 V main bus	DN-F10MN	GMC5	5 A time-delay
SR-FU	Safety-relay feed	DN-F10MN	GMC3	3 A time-delay
DB-FU	DB thermal control	DN-F10MN	GMC1	1 A time-delay

POWER-CIRCUIT PROCUREMENT CHECK PASSED

The LC1D18BD is rated 100 kA with fuses through 40 A. The GS20 manual specifies TJN35 Class T protection for GS23-22P0 and rates GS20 drives for circuits up to 100 kA. For this personal-shop retrofit, the worksheet is due diligence and a field record, not a product-certification gate.

STOP-TIME LIMITATION

At 2,000 RPM a linear 0.50 s stop represents about 8.3 spindle revolutions; 0.25 s represents about 4.2. This design materially improves coast-down but is not contact-triggered SawStop behavior.

DWG 01 - Power One-Line

208/240 V 3PH - permanent high-speed motor connection - VFD braking resistor

Main power path

Stage	Device	Build requirement
1. Supply	Rear line-entry j-box	3PH plus PE; remove the front AH7810 switch and line-voltage operator loop.
2. Disconnect	ABB OT30F3	UL 98, 3-pole, 30 A, non-fused. External handle and shaft selected with enclosure. Padlockable OFF.
3. Branch protection	LFT300603C + 3 x TJN35	35 A Class T. Install one LFT30060FBC cover per pole.
4. Contactor A	Schneider LC1D18BD	3 poles, 18 A AC-3 / 32 A AC-1, 24 VDC coil. Coil path is BH5928 47-48 in series with TD-DB 11-14. 21-22 mirror N.C. is EDM; 13-14 N.O. is X011.
5. VFD	GS23-22P0	2 HP, 230 V class, 3PH input. DB resistor on + / BR. Separate delayed STO1 and STO2.
6. Motor	Existing 1.5 HP motor	Permanent high-speed lead connection. Shielded U/V/W plus dedicated PE.

Auxiliary power and braking

Function	Device / wiring	Notes
24 VDC control	Owner NDR-240-24	PSU-FU: 2 x GMC3 on the line tap; 24V-FU GMC5; SR-FU GMC3; DB-FU GMC1.
Contactor B theater	Vintage Furnas through CR-B 52102	Both line tap legs fused at origin. Main contacts switch no load. Y004 supplies 300 ms chunk.
Dynamic braking	BR-N1-280W50, 50 ohm / 280 W	Thermal N.C. drives X012, CR-DB, and TD-DB B1. CR-DB asserts DI4 immediately; TD-DB later drops KA. Mount high; internal stirring fan.
PE and shield	Dedicated PE and 360-degree motor-cable clamp	Bond enclosure, panel, door, disconnect, KA, KB, rails, VFD, motor, and machine frame. Target PE continuity below 0.1 ohm.

ORDER OF DEVICES

Line -> OT30F3 -> LFT300603C/TJN35 -> LC1D18BD -> GS23-22P0 -> motor. Disconnect line-side terminals remain live with the switch OFF.

SCCR FIELD RECORD

The selected contactor, fuse, disconnect, and VFD conditions pass the 10 kA target. Confirm available fault current for the personal-shop record; formal certification/listing would be a separate future product step.

DWG 02 - Stop Category 1 Safety Loop

Dual-channel E-stop - monitored reset/EDM - controlled braking - delayed independent safe state

Dold BH5928-92-61-24-1

Circuit	Terminals	Function
E-stop channel 1	S11 -> NC1 -> S12	Positive-opening N.C. contact
E-stop channel 2	S31 -> NC2 -> S32	Positive-opening N.C. contact; cross-fault monitoring configured
Configuration	S21-S22; Y39-Y40	Cross-fault/timing jumpers per exact relay instructions; seal delay after validation
Manual reset / EDM	S34 -> SAFETY RESET -> KA 21-22 -> S33	KA base-device mirror N.C.; welded KA blocks reset

Output allocation

Timing	Contact	Destination	Role
Instant	13-14 N.O.	Y001 to DI1	Open Run-FWD
Instant	23-24 N.O.	Y002 to DI2	Open Run-REV
Instant monitor	31-32 N.C.	CR-S1 A1+ and CR-S2 A1+	Close on trip; two 9 mA polarized coils
Delayed	47-48 N.O.	TD-DB 11-14 -> LC1D18BD A1+	Open Contactor A after safety or thermal delay
Delayed	57-58 N.O.	VFD STO1	Independent torque-removal channel
Delayed	67-68 N.O.	VFD STO2	Independent torque-removal channel

Signal relays and thermal timer

Relay	Coil	Contact path	Result
CR-S1 - Phoenix 2966265	A1+ from SR32; A2- to 0 V	VFD DCM -> 11-14 -> DI4	GS20 function 18 Force to Stop
CR-S2 - Phoenix 2966265	A1+ from SR32; A2- to 0 V	+24 V -> 11-14 -> PLC X013	Immediate advisory trip indication
CR-DB - Phoenix 2966265	A1+ from DB thermal OK; A2- to 0 V	VFD DCM -> 11-12 N.C. -> DI4	Immediate thermal Force to Stop
TD-DB - Phoenix 2910140	A1/A2 continuous; B1 from DB thermal OK	SR48 -> 11-14 N.O. -> KA A1+	Release-delayed KA dropout

POLARITY AND TIMER

All three 2966265 modules contain input protection and flywheel diodes; observe A1+/A2-. CR-S contacts 12 are unused. Set TD-DB to Rs, 0.1-10 s range, nominal 1.00 s, then measure actual dropout.

Sequence on E-stop

- Instant contacts open DI1 and DI2. Contact 31-32 energizes CR-S1/CR-S2, asserting DI4 and X013.
- GS20 ramps according to P07.20=2 and P01.15 while KA and both STO channels remain enabled.
- At the validated delay, KA, STO1, and STO2 open independently; KA 13-14 drops X011.
- Reset is blocked until delay completion and healthy EDM. Reset cannot restart the spindle.
- DB thermal trip is equipment protection: CR-DB asserts DI4 immediately; TD-DB opens KA after its measured delay. Recovery is automatic without restart.

VFD Parameter Card - GS23-22P0

Enter with motor uncoupled if practical - parameter numbers per current GS20 manual

Function	Setting	Why
Motor current	6.42 A	Electronic thermal overload
Motor base	60 Hz / measured supply voltage	Use the verified machine supply and motor base point
Command source	External terminals	PLC brokers operational commands
Main / preset 1	60 Hz / 30 Hz	High and low ranges
DI1 / DI2 / DI3	FWD / REV / preset 1	DI1 and DI2 pass through separate instant safety contacts
DI4	Function 18 - Force to Stop	Asserted by CR-S1 on safety trip or CR-DB on thermal trip
P00.22	0 - ramp to stop	Never coast on loss of run command
P01.13	0.50 s initial	Normal/fallback deceleration
P01.15	0.50 s initial	Emergency deceleration time 2
P01.26 / P01.27	0.00 s / 0.00 s	Remove deceleration S-curve timing addition
P07.20	2	Force-to-stop uses deceleration time 2
DI function 28	UNUSED	It disables output and free-runs/coasts
DB chopper	Enabled; resistor on + / BR	Absorbs stop and reversal energy
STO1 / STO2	Separate delayed contacts	Independent torque-removal paths
DI mode	NPN/sink - internal power	DCM bonded to CLICK 0 V; never apply +24 V to DCM

Control-wiring checks

- Leave the GS20 input selector at factory NPN/sink. CLICK Y001/Y002/Y003 and dry safety contacts pull inputs to DCM.
- Wire 81 bonds CLICK 0 V to DCM. DCM and STO common share potential; never land external +24 V on DCM.
- Y001 -> 13-14 -> DI1; Y002 -> 23-24 -> DI2. CR-S1 11-14 and de-energized CR-DB 11-12 independently connect DCM to DI4; CR-S2 sources +24 V to X013.
- Set P01.26=P01.27=0.00 s. Factory 0.20 s S-curve values add about 0.20 s to nominal 0.50 s deceleration.
- Initial relay delay is 1.00 s. Reduce only after worst-case measured stop time is <=0.50 s and margin remains.
- A 0.25 s target is aspirational and may be rejected by overvoltage, overcurrent, belt/CVT dynamics, chuck retention, or resistor temperature.

Commissioning - Before Power and VFD Setup

Check in order - LOTO before wiring work - begin motor uncoupled where practical

SCCR FIELD RECORD

LC1D18BD and GS23-22P0 are verified with the selected 35 A TJN35 Class T protection. Confirm available fault current for the personal-shop field record; formal product certification would be separate.

Before first power-up

- Continuity and insulation check complete; no line voltage reaches operator controls or machine-front lamps.
- Power order verified: line -> OT30F3 -> LFT300603C/TJN35 -> KA -> VFD. Disconnect line terminals front-protected; three fuse pole covers installed.
- PE continuity below 0.1 ohm including dedicated machine-frame bond, door braid, rails, contactors, VFD, and motor.
- BH5928 inputs wired S11-S12 and S31-S32; S21-S22 and Y39-Y40 jumpers fitted; manual reset/EDM proven by continuity.
- Instant paths: Y001 through 13-14 to DI1 and Y002 through 23-24 to DI2. No bypass around either contact.
- Delayed paths: 47-48 through TD-DB 11-14 to KA, 57-58 to STO1, 67-68 to STO2. STO factory jumper removed.
- +24 V -> SR31-32 -> CR-S1/CR-S2 A1+; each A2- -> 0 V. CR-S1 11-14 closes DCM to DI4; CR-S2 11-14 sources +24 V to X013.
- LC1D18BD 21-22 N.C. is in EDM; 13-14 N.O. supplies X011; built-in coil suppressor used with correct polarity.
- DB-FU is GMC1 1 A. TD-DB A1/A2 is continuously powered; DB thermal OK feeds X012, CR-DB A1, and TD-DB B1.
- Machine and panel red pilots are in parallel on Y006 and labeled FAULT / NOT READY; black button is SAFETY RESET; white pilot is CONTROL POWER.

Mechanical checks

- Depth-rod metal stop takes bottom load; neither limit-switch lever is used as a mechanical stop.
- Bottom and top limit tags set slightly before the physical stops.
- Carlo Gavazzi ICF12 target is clean and ferrous; SIO mode selected; X010=1 only with lever confirmed OFF.
- Chuck, arbor, belts, CVT sheaves, guards, and tool retention inspected before any rapid-stop test.

VFD setup - staged

- Measure supply voltage; enter 6.42 A, 60 Hz, and the verified motor base voltage; enable electronic thermal protection.
- Set P00.22=0, P01.13=0.50 s, P01.15=0.50 s, P01.26=P01.27=0.00 s, P07.20=2, and DI4 function 18. Confirm function 28 is unused.
- Enable braking chopper. Force the DB thermostat path open: DI4 must assert immediately and KA must drop only after the measured TD-DB delay.
- At low speed with light tooling, verify FWD/REV directions and that E-stop commands a ramp rather than coast.
- Increase speed and inertia in stages; stop immediately if the drive trips, belt/CVT shifts, chuck loosens, or resistor overheats.

Commissioning - Safety and Sequences

Do not release for use until every required test passes and results are recorded

Safety sequence and timing

- Set BH5928 delay to 1.00 s. With spindle running, E-stop picks CR-S1/CR-S2 and X013, opens DI1/DI2, and starts a controlled ramp.
- During braking, KA and both STO inputs remain enabled. At delay expiry KA, STO1, and STO2 open independently; X011 falls with KA.
- Measure stop time at minimum and maximum CVT settings, FWD and REV, and maximum expected chuck/tool inertia. Record each result.
- Reduce delay to about 0.75 s only after worst-case stop time is ≤ 0.50 s and at least 0.20-0.25 s margin remains.
- EDM test: prevent KA 21-22 from proving open and confirm reset is refused. Remove the test condition before proceeding.
- After reset, spindle remains stopped and a fresh FWD command is required. E-stop during TAP returns state to IDLE.
- Thermal test: open the DB thermostat path while running; verify immediate DI4 ramp, delayed KA dropout, X012=0, and blinking red on both pilots.
- Restore the thermostat; verify automatic hardware recovery, 10 s healthy cooldown, and no spindle restart without a fresh command.

PLC indication and sequence

- Immediate trip: X013=1, C20/C60 clear, green turns off, red turns solid even while X011 remains high during braking.
- Safety final state: X011=0 after KA opens and red remains solid. Thermal KA dropout keeps red blinking because C11 explains X011=0.
- DRILL: FWD and REV latch separately; opposite button stops first; second press starts opposite direction; no plug reversal.
- TAP: lever-OFF proof required; bottom reverses; top stops; lever engagement mid-cycle faults and stops.
- JOG: 5 s FWD hold only arms mode; the held entry press never moves the spindle. Drum OFF inhibits motion but does not exit jog. Any STOP press exits jog.

Acceptance boundary

- SCCR worksheet completed as a personal-shop field record; certification/listing deferred unless this becomes a product.
- No nuisance drive faults, DC-bus overvoltage, or contactor opening before the spindle reaches zero.
- No belt/CVT upset, chuck/arbor release, abnormal motor noise, or repeated DB-resistor thermal trip over the planned stop frequency.
- If ≤ 0.50 s cannot be demonstrated with margin, do not claim the target. Increase delay and revisit braking hardware/drive architecture.
- This is not contact detection and cannot guarantee stopping within one revolution at 2,000 RPM.

Recorded item	Result
Available fault current / SCCR field note	_____
Worst-case measured stop time	_____
Final BH5928 delay setting	_____
Final TD-DB measured dropout	_____
Maximum validated chuck/tool inertia	_____
Reviewed by / date	_____