JUPITER

Jupiter Io

Route your program feed to multiple Zoom rooms.

One central distribution point for your live program.
Independent picture and audio controls for every destination.

How it works

Send your approved program into Io. Each satellite joins a destination Zoom meeting and delivers that same program as a camera or screen share, with audio controlled separately.



A satellite is a destination participant

It is not another source feed. A saved satellite profile holds the destination meeting, passcode, display name, and output mode. Hosts still control admission and sharing permissions.

Open Io: app.jupiter.events/admin/jupiter-io

01 / SOURCE SETUP

Bring your program into Io

Start with a clean picture and a working audio feed in your encoder.

1

Prepare the source

For a hardware production: ATEM or another switcher → capture device → OBS or Telescope. Check the complete program picture and sound before sending.

2

Allow the encoder and copy destination

Open **Manage ingest** on the encoder computer. Choose **Use this computer's public IP**, then **Allow encoder IP** and confirm. Mac/Windows lookup commands are below the field. Choose **Copy connection**; keep its secret URL private.

3

Configure the encoder

In OBS: **Settings → Stream → Custom**. Paste the copied URL into **Server** and leave **Stream Key** blank. Follow Io's saved **Encoder setup** guidance. In Telescope, use the URL as the send destination.

4

Start receiving, then send

Choose **Start receiving** in Io. Then start streaming in OBS or sending in Telescope. Stop the old encoder before switching computers. Repeat the IP step on the new computer.

5

Confirm incoming media

Check Io's video and audio indicators. **Take snapshot** checks the incoming program only; the audio meter indicates program input levels. Confirm final playback in the destination Zoom meeting.

Using a Zoom meeting as the source?

The alternate Zoom-source path requires the source host to admit Io Source and grant SDK recording permission for raw media access. The HDMI/SRT path does not require that source-meeting permission.

02 / SATELLITE SETUP

Send to your Zoom rooms

Create a destination profile, join the meeting, then enable the program output.

1

Create or edit a profile

Click **Add satellite** for one new profile. Use **Quantity to add** for several. Save a name, Zoom meeting ID, passcode, and output mode. **Edit satellite** changes an existing profile.

2

Choose the right picture path

New profiles use **Screen share + Full HD (up to 1080p) + Widescreen (16:9)**. Recommended for program feeds, slides, and graphics; the host must allow sharing. Use **Camera** for participant tiles, pinning, or spotlighting; Zoom may limit camera resolution.

3

Connect and check admission

Click **Connect**. A satellite may wait for the meeting host or for admission from a waiting room. Confirm the actual state before treating it as connected.

4

Enable picture and audio independently

Turn on **Share** or **Camera**, then unmute program audio. New satellites start with picture and audio off. Reconnecting retains saved controls. **Original Sound** does not unmute audio.

5

Verify in the destination meeting

Check picture, framing, sharing permission, and sound in Zoom. A successful Io connection or input snapshot alone does not prove what attendees see or hear.

Editing and cleanup

Disconnect before changing meeting details, output mode, quality, or aspect ratio. Connected satellites can still be renamed. A blank existing passcode keeps the saved one. **Delete satellite** is available after stopping and asks for confirmation.

03 / LIVE OPERATION

See the route. Check the room.

Use the matrix for selection and the destination meeting for final confidence.



Example routing

Matrix controls

Green + solid link:
connected

Dim red + dashed link:
not connected

Cyan outline:
selected for an action

Expand satellite view opens the orbital map. Click a satellite, drag a connector from Io, or drag on empty space to lasso several. Then click **Connect selected** or **Disconnect selected**. Dragging alone does not change connections.

If something is not working

Waiting for host	Start the destination meeting, or check its join-before-host and waiting-room settings.
Connected, no picture	Check source video, Share/Camera state, and the destination host's sharing permissions.
No sound	Check encoder audio, program input levels, and the satellite microphone. The current relay is mono.
Failed or stale	Open Failure report for the reported reason and last update. Disconnect before retrying; repeated failures need controller investigation.

Finish safely: Disconnect destination satellites, stop the encoder, then stop receiving in Io. Up to 50 profiles can be configured; practical concurrent capacity depends on the deployment. Zoom permissions and delivered quality still apply.