

## cmpr\_2\_2.xbe

### Attributes

```
xbe name=cmpr_2_2 evaluate=yes limit_tstep=yes save_history=yes
# if x1 > x2, y1 = high, else low
# (reverse if flag_inverting=1)
# y2 = not(y1)
Jacobian: variable
input_vars: x1 x2
output_vars: y1 y2
aux_vars:
iparms:
+ flag_invert=0
+ flag_quad=0
sparms:
rparms:
+ y_low=0
+ y_high=1
+ x1_1=0
+ x1_2=0
+ x2_1=0
+ x2_2=0
+ t_1=0
+ t_2=0
+ epsl=1.0e-6
+ delt_min=1.0e-6
+ delt_nrml=0.001
stparms:
igparms:
outparms: x1 x2 y1 y2
```

### Description

cmpr\_2\_2.xbe is a comparator with the following behaviour.

- (a)  $\text{flag\_invert} = 0$ :  
 $y1 = y_{\text{high}}$  if  $x1 > x2$ ,  
 $= y_{\text{low}}$  if  $x1 < x2$ .
- (b)  $\text{flag\_invert} = 1$ :  
 $y1 = y_{\text{high}}$  if  $x1 < x2$ ,  
 $= y_{\text{low}}$  if  $x1 > x2$ .

The other output  $y2$  is the complement of  $y1$ .

The parameters `delt_min`, `delt_nrml`, and `epsl` are used for controlling the simulator time steps. Additional time points are forced, depending on the values of `delt_min` and `delt_nrml`, when  $x1$  and  $x2$  are within `epsl` of each other. This feature allows accurate simulation without having to make the average time step very small. Generally, `delt_nrml` should be made equal to the typical simulator time step while `delt_min` should be made much smaller (say, by a factor of 100).

`flag_quad` decides the type of interpolation used to estimate the cross-over time (when  $x_1 - x_2$  changes sign). If `flag_quad` is 0, linear interpolation is used; if it is 1, quadratic interpolation is used. For more details, see Ref. [1].

### References

1. M.B. Patil, R.D. Korgaonkar, K. Appaiah, "GSEIM: A General-purpose Simulator with Explicit and Implicit Methods," submitted to *Sādhana*, also available at <https://arxiv.org/abs/2104.06621>