The PetPiano v.1.0 - BOM							
NO.	**Qty**	**NAME**	**Link**	**Category**	**Material**	**Type**	**Notes**
1	1	Right		Enclosure	MDF	Custom	
2	1	Left		Enclosure	MDF	Custom	
3	1	Back		Enclosure	MDF	Custom	
4	1	Bottom		Enclosure	MDF	Custom	
5	1	Front Bottom		Enclosure	MDF	Custom	
6	1	Keyboard Support		Enclosure	MDF	Custom	
7	1	Front		Enclosure	MDF	Custom	
8	1	Front Up		Enclosure	MDF	Custom	
9	1	Top		Enclosure	MDF	Custom	
10	1	Right Filler		Enclosure	MDF	Custom	
11	1	Left Filler		Enclosure	MDF	Custom	
12	1	Hinge Holder		Enclosure	MDF	Custom	
13	2	Hinge 25/15mm		Enclosure	Metal	Stock	
14	8	Wood screw 2.5/8mm		Enclosure	Metal	Stock	
15	1	Impeller-base		Dispenser	PETG/ABS	Custom	
16	1	Impeller		Dispenser	PETG/ABS	Custom	
17	1	Conteiner		Dispenser	PETG/ABS	Custom	
18	1	Impeller Enclosure		Dispenser	PETG/ABS	Custom	
19	1	Base		Dispenser	PETG/ABS	Custom	
20	2	Brush		Dispenser	TPU	Custom	
21	1	DC Motor - FT-49OGM500-530K	LINK	Dispenser	Electronic	Stock	
22	1	Bolt M3/15mm (flat head)		Dispenser	Metal	Stock	To attach the Impeller-base to the motor shaft.
23	4	Bolt M3/8mm (conical head)		Dispenser	Metal	Stock	To mount the motor onto the Base.
24	4	Wood screw 3.5/10mm		Dispenser	Metal	Stock	To mount the Base to the wooden foundation.
25	1	Wires with crimp connector: JST ZH1.5-3P	LINK	Dispenser	Wire	Stock/Custom	
26	1	Rotation sensor		Dispenser	PCB	Custom	
27	1	Frame		Keyboard	PETG/ABS	Custom	
28	1	White Keys		Keyboard	PETG/ABS	Custom	
29	1	Black Keys		Keyboard	PETG/ABS	Custom	
30	1	Main PCB		Keyboard	PCB	Custom	
31	5	Bolt M3/25mm (conical head)		Keyboard	Metal	Stock	To attach the white and black keys to the Frame.
32	2	Wood screw 3.5/25mm (conical head)		Keyboard	Metal	Stock	To attach the keyboard to the casing.
33	1	Speaker 3W/8Ohm 78/78mm	LINK	Speaker	Electronic	Stock	
34	1	Wires with crimp connector: JST XH2.54-2P	LINK	Speaker	Wire	Stock/Custom	
35	4	Bolt M3/15mm (flat head)		Speaker	Metal	Stock	To attach the speaker to the casing.
36	1	AD-DC Adapter 9VDC		Power Supply	Electronic	Stock	
37	1	Battery Compartment 6xAA	LINK	Power Supply	PETG/ABS	Stock	
38	1	DPST Rocker Switch	LINK	Power Supply	Electronic	Stock	
39	1	5.5MM x 2.5MM Female DC Power Jack	LINK	Power Supply	Electronic	Stock	
40	5	Bolt M3/15mm (flat head)		Dispenser/Speaker	Metal	Stock	To attach the Impeller-base to the motor shaft, and for the Speaker
41	8	Nut M3		Dispenser/Speaker	Metal	Stock	To mount the motor to the base, and for the Speaker
42	7	Magnet 5/2mm	LINK	Dispenser/Enclosure	Magnet	Stock	For the Impeller and the Lid
43	5	Wires with crimp connector: JST XH2.54-2P	LINK	Dispenser/Power Supply	Wire	Stock/Custom	For the motor, and for the power supply