

Input-to-state stabilization of linear systems under data-rate constraints

Mahmoud Zamani and Guosong Yang*

Abstract

We study feedback stabilization of linear systems under finite data rate in the presence of completely unknown disturbances. A communication and control strategy is proposed based on sampled and quantized state measurements, where the quantization range is dynamically adjusted using reachable-set approximations and a disturbance estimate derived from quantization parameters. An additional quantization symbol is introduced to ensure robustness near the equilibrium. Under a data-rate condition, the proposed strategy guarantees input-to-state stability (ISS) with respect to the disturbance. A simulation example illustrates the effectiveness of the method.

1 Introduction

Feedback control under data-rate constraints has been an active research area for decades, as surveyed in, e.g., [1–3]. Such constraints arise naturally in networked control systems due to communication costs, bandwidth limitations, and security considerations. Beyond these practical motivations, a fundamental question is how much information is required to achieve a given control objective.

A widely used framework for achieving finite data rate is to generate the control input from sampled and quantized state measurements taking values in a finite set. Beginning with [4–10], various quantization schemes have been developed for stabilizing linear systems. In particular, asymptotic stabilization under finite data rate requires dynamic adjustment of the size of the quantization range (zooming) [6–10], while the required data rate can be reduced by dynamically adjusting its center as well (moving-center quantization) [8–10]. These ideas have subsequently been extended to nonlinear systems [7, 11, 12] and switched systems [13, 14].

We consider feedback stabilization under finite data rate in the presence of unknown disturbances. In [8, 10], disturbances are assumed to be bounded, and the minimum data rate required for asymptotic stabilization is characterized. Without such bounds, the problem becomes significantly more challenging, as disturbances may drive the state outside the quantization range after capture. In this setting, [15] established input-to-state stability (ISS) [16] through dynamic quantization with alternating zooming-out and zooming-in stages. Similar ISS results were obtained in [17] using logarithmic quantization in polar coordinates, and in [18] using moving-center quantization with improved data-rate efficiency. However, the fixed-center quantization schemes in [15, 17] lead to implicit and generally conservative data-rate bounds, whereas the moving-center scheme in [18] relies on additional mechanisms such as dedicated escape-detection stages

*The authors are with the Department of Electrical and Computer Engineering, Rutgers University–New Brunswick, Piscataway, NJ 08854 USA (e-mails: {mahmoud.zamani, guosong.yang}@rutgers.edu).

and quantizer resets. More recently, [14] proposed a Lyapunov-based disturbance-estimation framework for switched linear systems that avoids these complexities, but achieves only the weaker property of practical ISS [19].

This paper develops a communication and control strategy for linear systems with completely unknown disturbances. Building on the disturbance-estimation idea of [14], the proposed approach combines the data-rate efficiency of moving-center quantization with Lyapunov analysis and eliminates the need for dedicated escape-detection stages and quantizer resets. Our results provide an explicit characterization of the admissible data rate and establish ISS rather than practical ISS. To achieve this, we design a disturbance estimate derived from quantization parameters to replace the estimate based on an increasing sequence of constants in [14], and introduce an additional quantization symbol for establishing ISS near the equilibrium. These features distinguish the proposed approach from [14, 15, 17, 18] and constitute the main methodological contribution of the paper.

The remainder of the paper is organized as follows. Section 2 introduces the system model and the information structure. The main result is presented in Section 3. Section 4 explains the communication and control strategy, with reachable-set approximations derived in Section 5. Section 6 presents the stability analysis, with key intermediate results summarized as technical lemmas. Section 7 provides a simulation example.

Notations: The ∞ -norm of a vector $v = (v_1, \dots, v_n) \in \mathbb{R}^n$ is denoted by $|v| := |v|_\infty = \max_{1 \leq i \leq n} |v_i|$. The induced ∞ -norm of a matrix $M = [a_{ij}] \in \mathbb{R}^{n \times n}$ is denoted by $\|M\| := \|M\|_\infty = \max_{1 \leq i \leq n} \sum_{j=1}^n |a_{ij}|$. The largest and smallest eigenvalues of a symmetric matrix $M \in \mathbb{R}^{n \times n}$ are denoted by $\bar{\lambda}(M)$ and $\underline{\lambda}(M)$, respectively. A continuous function $\gamma : \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{\geq 0}$ is of class $\mathcal{K}_\infty$, denoted by $\gamma \in \mathcal{K}_\infty$, if it is strictly increasing, unbounded, and satisfies $\gamma(0) = 0$. The left limit of a piecewise continuous function $z(\cdot)$ at t is denoted by $z(t^-) := \lim_{s \nearrow t} z(s)$.

2 Problem formulation

2.1 System definition

Consider a continuous-time linear system

$$\dot{x} = Ax + Bu + Dd, \quad x(0) = x_0, \quad (1)$$

where $x \in \mathbb{R}^{n_x}$ is the state, $u \in \mathbb{R}^{n_u}$ is the control input, and $d \in \mathbb{R}^{n_d}$ is an unknown disturbance. The disturbance $d(\cdot)$ is assumed to be Lebesgue measurable and locally essentially bounded. The essential supremum ∞ -norm of $d(\cdot)$ over an interval J is denoted by $\|d\|_J := \text{ess sup}_{t \in J} |d(t)|$; the subscript is omitted when $J = \mathbb{R}_{\geq 0}$.

Our first basic assumption is that the system (1) is stabilizable.

Assumption 1 (Stabilizability). The pair (A, B) is stabilizable, that is, there exists a state feedback gain matrix K such that $A + BK$ is Hurwitz (all eigenvalues have negative real parts).

In what follows, we assume that such a matrix K has been selected and fixed.

2.2 Information structure

We aim to generate stabilizing control input $u(\cdot)$ based on limited information about the state $x(\cdot)$. As shown




Figure 1: Information structure.

in Fig. 1, the feedback loop includes a sensor with an encoder and a controller with a decoder. The sensor samples the state at times $t_k = k\tau_s$, $k \in \mathbb{Z}_{\geq 0}$, where $\tau_s > 0$ is a fixed *sampling period*. Each sample $x(t_k)$ is encoded as an integer $i_k \in \{0, 1, \dots, N^{n_x} + 1\}$, where $N > 0$ is a fixed integer, and then transmitted to the controller. The resulting data transmission rate is

$$\frac{\log_2(N^{n_x} + 2)}{\tau_s} \quad (2)$$

bits per unit time. This information structure enables a separation of sensing and control tasks, since the controller does not require access to the exact state. Details of the communication and control strategy are presented in Section 4.

Our second basic assumption concerns the data rate.

Assumption 2 (Data rate). The sampling period τ_s and the integer N satisfy

$$\Lambda := \|e^{A\tau_s}\| < N. \quad (3)$$

The inequality in (3) requires N to be sufficiently large relative to τ_s , thereby imposing a lower bound on the admissible data rate. Similar conditions were shown to be sufficient for stabilizing linear systems [9, 18] and switched linear systems [13, 14].¹ These conditions, including (3), are generally conservative compared to the minimal data rate required for stabilization characterized in [8, 10]. However, the gap can be made arbitrarily small by tailoring the quantization scheme to the structure of the system matrix A ; see, e.g., [18, Sec. V]. Furthermore, the results in [8, 10] assume known disturbance bounds, whereas the disturbance is completely unknown in [14, 18] and in the present work.

3 Main result

The control objective is to stabilize the system defined in Section 2.1 under the information structure described in Section 2.2 in a robust sense. Specifically, we aim to achieve *input-to-state stability* (ISS) introduced in [16]. The theorem below adopts an equivalent characterization from [19].

Theorem 1. *Consider the linear system (1). Suppose that Assumptions 1 and 2 hold. Then there exists a communication and control strategy that renders the closed-loop system ISS, that is, there exist functions $\gamma_1, \gamma_2, \gamma_3 \in \mathcal{K}_\infty$ such that, for any initial condition $x_0 \in \mathbb{R}^{n_x}$ and any disturbance $d(\cdot)$, the solution satisfies*

$$|x(t)| \leq \gamma_1(|x_0|) + \gamma_2(\|d\|) \quad \forall t \geq 0 \quad (4)$$

¹Compared with [9, 18] and with [13, 14] specialized to the nonswitched case, the proposed approach uses one additional quantization symbol, corresponding to $N^{n_x} + 2$ rather than $N^{n_x} + 1$ symbols in (2). This additional symbol is essential for establishing ISS near the equilibrium and also removes the requirement that N be odd; see Section 4.1.

and

$$\limsup_{t \rightarrow \infty} |x(t)| \leq \gamma_3 \left(\limsup_{t \rightarrow \infty} |d(t)| \right). \quad (5)$$

The communication and control strategy is presented in Section 4. The corresponding closed-loop dynamics are derived in Section 5; see (15) and (27). The gain functions γ_1 , γ_2 , and γ_3 are derived in the proof of Theorem 1 in Section 6.3; see (46) and (47).

4 Communication and control strategy

In this section, we present the communication and control strategy used to establish Theorem 1, assuming that suitable approximations of the reachable sets of the state are available at all sampling times (these approximations are derived in Section 5).

The initial state $x(0) = x_0$ is unknown. At $t_0 = 0$, both the sensor and the controller are initialized with $x_0^* = 0$ and an arbitrary design parameter $E_0 > 0$. At each sampling time $t_k \geq 0$, the sensor checks whether

$$|x(t_k) - x_k^*| \leq E_k, \quad (6)$$

that is, whether the state $x(t_k)$ lies inside the hypercube

$$\mathcal{R}_k := \{v \in \mathbb{R}^{n_x} : |v - x_k^*| \leq E_k\}.$$

The set $\mathcal{R}_k$ approximates the reachable set at t_k and serves as the quantization range. If (6) holds, then the state is *visible* and the system is in a *stabilizing stage* (Section 4.1); otherwise, the state is *lost* and the system is in a *searching stage* (Section 4.2).

If the state is visible at t_k , then the system remains in a stabilizing stage until the first sampling time $t_j > t_k$ such that $x(t_j) \notin \mathcal{R}_j$, at which point the state *escapes*. Conversely, if the state is lost at t_k , then the system remains in a searching stage until the first sampling time $t_i > t_k$ such that $x(t_i) \in \mathcal{R}_i$, at which point the state is *(re)captured*. Due to the unknown disturbance, the system may switch between stages finitely or infinitely many times.

4.1 Stabilizing stages

At each sampling time t_k in a stabilizing stage, the sensor first checks whether

$$|x(t_k)| \leq \frac{E_k}{N}. \quad (7)$$

If so, it transmits $i_k = 1$ to the controller. Otherwise, it partitions the range $\mathcal{R}_k$ into N^{n_x} equal hypercubic cells of radius E_k/N in the ∞ -norm (N per dimension), assigns each cell a unique index from $\{2, \dots, N^{n_x} + 1\}$, and transmits the index i_k of the cell containing $x(t_k)$.

Upon receiving an $i_k \in \{1, \dots, N^{n_x} + 1\}$, the controller infers that (6) holds and reconstructs the corresponding cell center c_k using the same indexing protocol. If $i_k \geq 2$, then

$$|x(t_k) - c_k| \leq \frac{E_k}{N} \quad (8)$$

and

$$|c_k - x_k^*| \leq \frac{N-1}{N} E_k. \quad (9)$$

If $i_k = 1$, then $c_k = 0$ and (8) still holds.

The controller then sets the control input as

$$u(t) = K\hat{x}(t), \quad t \in [t_k, t_{k+1}), \quad (10)$$

where K is the stabilizing gain matrix from Assumption 1, and $\hat{x}$ evolves according to the auxiliary system

$$\dot{\hat{x}} = A\hat{x} + Bu \quad (11)$$

with the boundary condition

$$\hat{x}(t_k) = c_k. \quad (12)$$

Hence $\hat{x}$ is updated to c_k at each sampling time t_k in a stabilizing stage and is thus only right-continuous in general. As a result, the controller dynamics are hybrid, with both continuous flows and discrete jumps.

Finally, both the sensor and the controller update the quantization range by computing

$$\begin{aligned} x_{k+1}^* &:= F(c_k), \\ E_{k+1} &:= G(E_k, x_k^*) \end{aligned} \quad (13)$$

without further communication, where the functions F and G are derived in Section 5.1.

In contrast to the quantization schemes in [9, 13, 14, 18], we introduce an additional quantization cell centered at the origin, defined by (7). This design ensures that the control input vanishes whenever the state is sufficiently close to the origin, which is essential for establishing ISS near the equilibrium. Moreover, it preserves the equilibrium at the origin without requiring the integer N to be odd.

4.2 Searching stages

At each sampling time t_k in a searching stage, the sensor transmits the “overflow symbol” $i_k = 0$. Upon receiving $i_k = 0$, the controller infers that the state is lost and sets the control input to zero on $[t_k, t_{k+1})$. Finally, both the sensor and the controller update the quantization range by computing

$$\begin{aligned} x_{k+1}^* &:= \hat{F}(x_k^*), \\ E_{k+1} &:= \hat{G}((1 + \varepsilon)E_k, \delta) \end{aligned} \quad (14)$$

without further communication, where the functions $\hat{F}$ and $\hat{G}$ are derived in Section 5.2, and $\varepsilon, \delta > 0$ are arbitrary design parameters. At an escape time t_j , which corresponds to the start of a searching stage, the update of E_{j+1} is modified as described in Section 5.2.

5 Approximation of reachable sets

In this section, we derive the recursive formulas needed to implement the proposed communication and control strategy. Section 5.1 derives the functions F and G in (13) for stabilizing stages. Section 5.2 derives the functions $\hat{F}$ and $\hat{G}$ in (14) for searching stages.

5.1 Stabilizing stages

Consider a sampling time t_k in a stabilizing stage. Define the error $e := x - \hat{x}$. On $[t_k, t_{k+1})$, combining (1), (10), and (11) yields the closed-loop system

$$\begin{aligned}\dot{x} &= Ax + BK\hat{x} + Dd, \\ \dot{\hat{x}} &= (A + BK)\hat{x},\end{aligned}\tag{15}$$

and thus the error dynamics

$$\dot{e} = Ae + Dd, \quad |e(t_k)| = |x(t_k) - c_k| \leq \frac{E_k}{N},\tag{16}$$

where the boundary condition follows from (8) and (12). Hence

$$\begin{aligned}|e(t_{k+1}^-)| &= \left| e^{A\tau_s} e(t_k) + \int_{t_k}^{t_{k+1}} e^{A(t_{k+1}-\tau)} Dd(\tau) d\tau \right| \\ &\leq \|e^{A\tau_s}\| |e(t_k)| + \left(\int_0^{\tau_s} \|e^{As} D\| ds \right) \|d\|_{[t_k, t_{k+1}]} \\ &\leq \frac{\Lambda}{N} E_k + \Phi \|d\|_{[t_k, t_{k+1}]},\end{aligned}\tag{17}$$

where $\Lambda = \|e^{A\tau_s}\|$ as in (3) and

$$\Phi := \int_0^{\tau_s} \|e^{As} D\| ds.\tag{18}$$

We define the update formulas by

$$x_{k+1}^* = F(c_k) := \hat{x}(t_{k+1}^-) = Sc_k,\tag{19}$$

where $S := e^{(A+BK)\tau_s}$, and

$$E_{k+1} = G(E_k, x_k^*) := \frac{\Lambda}{N} E_k + \phi \sqrt{V_k}\tag{20}$$

with

$$V_k := V(x_k^*, E_k) := (x_k^*)^\top P x_k^* + \rho E_k^2,\tag{21}$$

where $\phi, \rho > 0$ are design parameters selected below. The functions F and G are designed such that, if the disturbance $\|d\|_{[t_k, t_{k+1}]} = 0$, then $|x(t_{k+1}) - x_{k+1}^*| \leq E_{k+1}$, so the state cannot escape at the next sampling time t_{k+1} . The term $\phi \sqrt{V_k}$ in (20) ensures that, if the state does escape at t_{k+1} , then V_k can be bounded in terms of $\|d\|_{[t_k, t_{k+1}]}$.

We now select three design parameters $\psi, \rho, \phi > 0$ sequentially so that the Lyapunov-type function V_k decreases exponentially during stabilizing stages. Since $A + BK$ is Hurwitz, there exist positive definite symmetric matrices $P, Q \in \mathbb{R}^{n_x \times n_x}$ such that

$$S^\top P S - P = -Q < 0.\tag{22}$$

Define

$$\chi := \frac{2n_x^2 \|S^\top P S\|^2}{\underline{\lambda}(Q)} + n_x \|S^\top P S\|.\tag{23}$$

Since $\Lambda < N$ by Assumption 2, there exists a sufficiently small $\psi > 0$ such that

$$(1 + \psi) \frac{\Lambda^2}{N^2} < 1. \quad (24)$$

Then there exists a sufficiently large $\rho > 0$ such that

$$\frac{(N-1)^2}{N^2} \frac{\chi}{\rho} + (1 + \psi) \frac{\Lambda^2}{N^2} < 1. \quad (25)$$

Finally, there exists a sufficiently small $\phi > 0$ such that

$$\begin{aligned} \nu := \max & \left\{ 1 - \frac{\lambda(Q)}{2\bar{\lambda}(P)}, \frac{(N-1)^2}{N^2} \frac{\chi}{\rho} + (1 + \psi) \frac{\Lambda^2}{N^2} \right\} \\ & + \left(1 + \frac{1}{\psi} \right) \phi^2 \rho \end{aligned} \quad (26)$$

satisfies $\nu < 1$.

5.2 Searching stages

Consider a sampling time t_k in a searching stage. On $[t_k, t_{k+1})$, combining (1) and (11) with $u \equiv 0$ and $\hat{x}(t_k) = x_k^*$ yields the closed-loop system

$$\begin{aligned} \dot{x} &= Ax + Dd, \\ \dot{\hat{x}} &= A\hat{x}, \end{aligned} \quad (27)$$

and thus the error dynamics

$$\dot{e} = Ae + Dd, \quad e(t_k) = x(t_k) - x_k^*. \quad (28)$$

Hence

$$\begin{aligned} |e(t_{k+1}^-)| &= \left| e^{A\tau_s} e(t_k) + \int_{t_k}^{t_{k+1}} e^{A(t_{k+1}-\tau)} Dd(\tau) d\tau \right| \\ &\leq \|e^{A\tau_s}\| |e(t_k)| + \left(\int_0^{\tau_s} \|e^{As} D\| ds \right) \|d\|_{[t_k, t_{k+1}]} \\ &\leq \Lambda |e(t_k)| + \Phi \|d\|_{[t_k, t_{k+1}]}, \end{aligned} \quad (29)$$

where Λ and Φ are defined in (3) and (18), respectively.

We define the update formulas by

$$x_{k+1}^* = \hat{F}(x_k^*) := \hat{x}(t_{k+1}^-) = \hat{S}x_k^*, \quad (30)$$

where $\hat{S} := e^{A\tau_s}$, and

$$E_{k+1} = \hat{G}((1 + \varepsilon)E_k, \delta) := (1 + \varepsilon)\Lambda E_k + \Phi\delta, \quad (31)$$

where $\varepsilon, \delta > 0$ are arbitrary design parameters introduced in Section 4.2. The functions $\hat{F}$ and $\hat{G}$ are designed such that

$$|x(t_{k+1}) - x_{k+1}^*| \leq \hat{G}(|x(t_k) - x_k^*|, \|d\|_{[t_k, t_{k+1}]}).$$

Consequently, the factor $1 + \varepsilon$ in (31) ensures that the growth rate of E_k dominates that of $|x(t_k) - x_k^*|$, which guarantees finite-time (re)capture of the state.

The parameter δ serves as a constant disturbance estimate used only during searching stages. In contrast, [14] employs an increasing sequence of constants to estimate the disturbance during both stabilizing and searching stages, yielding only practical ISS. This distinction is one of the key ingredients for establishing ISS in the present paper.

At an escape time t_j , which corresponds to the start of a searching stage, the update of E_{j+1} is modified. Instead of using $E_j = G(E_{j-1}, x_{j-1}^*)$ in (31), we define

$$E_{j+1} := \hat{G}((1 + \varepsilon)\hat{E}_j, \delta), \quad (32)$$

where

$$\hat{E}_j := \frac{\Lambda}{N} E_{j-1} + \Phi \delta.$$

This modification ensures that the state is recaptured at t_{j+1} whenever $\|d\|_{[t_{j-1}, t_{j+1}]} \leq \delta$, a property that is later used to derive a bound on the recapture time in terms of the disturbance.

6 Stability analysis

In this section, we establish Theorem 1 based on the communication and control strategy presented in Section 4. We first summarize several key intermediate results as technical lemmas in Sections 6.1 and 6.2. Section 6.3 then completes the proof of Theorem 1.

Throughout the analysis, we assume that the essential supremum norm $\|d\|$ is finite, since otherwise the ISS bounds (4) and (5) hold vacuously. We also assume that $\Lambda > 1$.²

6.1 Stabilizing stages

We first establish that the Lyapunov-type function $V_k := V(x_k^*, E_k)$ defined in (21) decreases exponentially.

Lemma 1. *For any sampling time t_k in a stabilizing stage,*

$$V_{k+1} \leq \nu V_k, \quad (33)$$

where $\nu \in (0, 1)$ is defined in (26).

Proof. See Appendix A.1. □

We next relate V_k to $|x(t_k)|$, $|x(t_{k+1})|$, and E_k .

Lemma 2. *There exist constants $C_1, C_2, C_3 > 0$ such that, for any sampling time t_k in a stabilizing stage,*

$$\sqrt{V_k} \leq C_1(|x(t_k)| + E_k), \quad (34)$$

$$|x(t_k)| \leq C_2 \sqrt{V_k}, \quad (35)$$

$$|x(t_{k+1})| \leq C_3 \sqrt{V_k} + \Phi \|d\|_{[t_k, t_{k+1}]}, \quad (36)$$

²Note that $\Lambda = \|e^{A\tau_s}\| \geq 1$, and equality holds only if all eigenvalues of A have nonpositive real parts. The case $\Lambda = 1$ can be addressed by replacing Λ with $\max\{\|e^{A\tau_s}\|, 1 + \epsilon_\Lambda\}$ for an arbitrarily small $\epsilon_\Lambda > 0$.

Proof. See Appendix A.2. $\square$

The next two lemmas provide an exponentially decaying state bound and a state bound with suitable monotonicity and $\mathcal{K}_\infty$ properties.

Lemma 3. *There exist constants $C, \lambda > 0$ such that, for any two sampling times $t_k > t_l$ from the same stabilizing stage,*

$$|x(t_k)| \leq C e^{-\lambda(k-l)} (|x(t_l)| + E_l) + \Phi \|d\|_{[t_{k-1}, t_k]}. \quad (37)$$

Proof. See Appendix A.3. $\square$

Lemma 4. *There exist continuous functions $\chi^x, \chi^d : \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{\geq 0}$ such that, a) for each fixed $s > 0$, $\chi^x(\cdot, s)$ and $\chi^d(\cdot, s)$ are nondecreasing, b) for each fixed $E > 0$, $\chi^x(E, \cdot), \chi^d(E, \cdot) \in \mathcal{K}_\infty$, and c) for any two sampling times $t_k \geq t_l$ from the same stabilizing stage,*

$$|x(t_k)| \leq \chi^x(E_l, |x(t_l)|) + \chi^d(E_l, \|d\|_{[t_l, t_k]}). \quad (38)$$

Proof. See Appendix A.4. $\square$

Finally, we bound the state and the quantization radius at escape times in terms of the disturbance over the preceding sampling interval, independently of the initial state.

Lemma 5. *There exists a constant $\Gamma > 0$ such that, for any sampling time t_j at which the state escapes,*

$$|x(t_j)| \leq \Gamma \|d\|_{[t_{j-1}, t_j]}, \quad E_{j-1} \leq \Gamma \|d\|_{[t_{j-1}, t_j]}. \quad (39)$$

Proof. See Appendix A.5. $\square$

6.2 Searching stages

We first show that if the state is lost at $t_0 = 0$, then it is guaranteed to be captured in finite time.

Lemma 6. *If the state is lost at $t_0 = 0$, then it is captured at some sampling time t_{i_0} satisfying*

$$i_0 \leq \max \left\{ \eta_x \left(\frac{|x_0|}{E_0} \right), \eta_d \left(\frac{\|d\|_{[0, t_{i_0}]}}{\delta} \right) \right\}, \quad (40)$$

where

$$\eta_x(s) := \begin{cases} \lceil \log_{1+\varepsilon} s \rceil, & s > 1, \\ 0, & 0 \leq s \leq 1, \end{cases}$$

$$\eta_d(s) := \begin{cases} \lceil \log_{1+\varepsilon}(r_\varepsilon s) \rceil, & s > 1, \\ 0, & 0 \leq s \leq 1, \end{cases}$$

with

$$r_\varepsilon := \frac{\hat{\Lambda} - 1}{\Lambda - 1}, \quad \hat{\Lambda} := (1 + \varepsilon)\Lambda.$$

Proof. See Appendix A.6. □

The next lemma provides bounds on the state before the first capture and on the quantization radius at the first capture.

Lemma 7. *There exist functions $\hat{\gamma}_0^x, \hat{\gamma}_0^d \in \mathcal{K}_\infty$ such that, if the state is first captured at t_{i_0} , then for any sampling time $t_k \leq t_{i_0}$,*

$$|x(t_k)| \leq \hat{\gamma}_0^x(|x_0|) + \hat{\gamma}_0^d(\|d\|_{[0, t_{i_0}]}) . \quad (41)$$

Moreover, there exists a continuous function $\hat{\chi}_0^E : \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0} \times \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{>0}$ such that, a) for each fixed $E, s > 0$, $\hat{\chi}_0^E(E, s, \cdot)$ and $\hat{\chi}_0^E(E, \cdot, s)$ are nondecreasing, and b) at the capture time t_{i_0} ,

$$E_{i_0} \leq \hat{\chi}_0^E(E_0, |x_0|, \|d\|_{[0, t_{i_0}]}) . \quad (42)$$

Proof. See Appendix A.7. □

We now show that if the state escapes, then it is guaranteed to be recaptured in finite time.

Lemma 8. *If the state escapes at $t_j > 0$, then it is recaptured at some sampling time $t_i > t_j$ satisfying*

$$i \leq j + \max \left\{ \eta_d \left(\frac{\|d\|_{[t_{j-1}, t_i]}}{\delta} \right), 1 \right\} , \quad (43)$$

where η_d is defined in Lemma 6.

Proof. See Appendix A.8. □

The final lemma provides bounds on the state and the quantization radius at recapture.

Lemma 9. *There exist $\hat{\gamma}^x, \hat{\gamma}^d \in \mathcal{K}_\infty$ such that, if the state escapes at t_j and is recaptured at t_i , then for any sampling time t_k between t_j and t_i ,*

$$|x(t_k)| \leq \hat{\gamma}^x(|x(t_j)|) + \hat{\gamma}^d(\|d\|_{[t_{j-1}, t_i]}) . \quad (44)$$

Moreover, there exists a continuous function $\hat{\chi}^E : \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{>0}$ such that a) for each fixed $E > 0$, $\hat{\chi}^E(E, \cdot)$ is nondecreasing, and b) at the recapture time t_i ,

$$E_i \leq \hat{\chi}^E(E_{j-1}, \|d\|_{[t_{j-1}, t_i]}) . \quad (45)$$

Proof. See Appendix A.9. □

6.3 Proof of Theorem 1

The proof proceeds by analyzing alternating searching and stabilizing stages separately. During stabilizing stages, Lemmas 3 and 4 provide state bounds with exponentially decaying and $\mathcal{K}_\infty$ properties, respectively. At escape times, Lemma 5 bounds the state and the quantization radius in terms of the disturbance. During searching stages, Lemmas 6 and 8 ensure finite-time (re)capture, while Lemmas 7 and 9 provide bounds on the state and the quantization radius. Combining these bounds yields the ISS bounds (4) and (5).

We index the alternating searching and stabilizing stages as follows. Let $0 \leq i_0 < j_1 < i_1 < \dots$ be such that the state is first captured at t_{i_0} , escapes at t_{j_1} , and is recaptured at t_{i_l} for $l \geq 1$. By Lemma 6, we have $i_0 < \infty$. If the state never escapes after some t_{i_l} , we set $j_{l+1} = \infty$. By Lemma 8, if $j_l < \infty$ then $i_l < \infty$.

First, we establish the bound (4) at sampling times by constructing the functions $\gamma_1, \gamma_2 \in \mathcal{K}_\infty$.

First searching stage $[0, t_{i_0})$ By Lemma 7, the bound (41) holds for all $t_k \leq t_{i_0}$, including the case $i_0 = 0$ (i.e., when the state is visible at $t_0 = 0$).

First stabilizing stage $[t_{i_0}, t_{j_1})$ At t_{i_0} , Lemma 7 yields

$$|x(t_{i_0})| \leq \hat{\gamma}_0^x(|x_0|) + \hat{\gamma}_0^d(\|d\|_{[0, t_{i_0}]})$$

and

$$E_{i_0} \leq \hat{\chi}_0^E(E_0, |x_0|, \|d\|_{[0, t_{i_0}]})$$

From Lemma 4, for any $t_{i_0} \leq t_k < t_{j_1}$,

$$\begin{aligned} |x(t_k)| &\leq \chi^x(E_{i_0}, |x(t_{i_0})|) + \chi^d(E_{i_0}, \|d\|_{[t_{i_0}, t_k]}) \\ &\leq \chi^x\left(\hat{\chi}_0^E(E_0, |x_0|, \|d\|_{[0, t_{i_0}]})\right) + \hat{\gamma}_0^x(|x_0|) + \hat{\gamma}_0^d(\|d\|_{[0, t_{i_0}]}) \\ &\quad + \chi^d\left(\hat{\chi}_0^E(E_0, |x_0|, \|d\|_{[0, t_{i_0}]})\right) + \chi^d(\|d\|_{[t_{i_0}, t_k]}) \end{aligned}$$

Using the above bounds, a standard comparison-function argument yields continuous functions $\bar{\chi}_1, \bar{\chi}_2 : \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{\geq 0}$ such that a) for each fixed $s > 0$, $\bar{\chi}_1(\cdot, s), \bar{\chi}_2(\cdot, s)$ are nondecreasing, b) for each fixed $E > 0$, $\bar{\chi}_1(E, \cdot), \bar{\chi}_2(E, \cdot) \in \mathcal{K}_\infty$, and c)

$$\begin{aligned} &\chi_1(E_0, |x_0|) + \bar{\chi}_2(E_0, \|d\|_{[0, t_k]}) \\ &\geq \chi^x\left(\hat{\chi}_0^E(E_0, |x_0|, \|d\|_{[0, t_k]})\right) + \hat{\gamma}_0^x(|x_0|) + \hat{\gamma}_0^d(\|d\|_{[0, t_k]}) \\ &\quad + \chi^d\left(\hat{\chi}_0^E(E_0, |x_0|, \|d\|_{[0, t_k]})\right) + \chi^d(\|d\|_{[0, t_k]}) \end{aligned}$$

which implies

$$|x(t_k)| \leq \bar{\chi}_1(E_0, |x_0|) + \bar{\chi}_2(E_0, \|d\|_{[0, t_k]}).$$

If $t_{j_1} = \infty$, then the proof of (4) is complete. Otherwise, consider an arbitrary escape time $t_{j_l} < \infty$.

Searching stage $[t_{j_l}, t_{i_l})$ At t_{j_l} , Lemma 5 yields

$$|x(t_{j_l})| \leq \Gamma \|d\|_{[t_{j_l-1}, t_{j_l}]}, \quad E_{j_l-1} \leq \Gamma \|d\|_{[t_{j_l-1}, t_{j_l}]}$$

From Lemma 9, for any $t_{j_l} \leq t_k \leq t_{i_l}$,

$$\begin{aligned} |x(t_k)| &\leq \hat{\gamma}^x(|x(t_{j_l})|) + \hat{\gamma}^d(\|d\|_{[t_{j_l-1}, t_{i_l}]}) \\ &\leq \hat{\gamma}^x(\Gamma \|d\|_{[t_{j_l-1}, t_{j_l}]}) + \hat{\gamma}^d(\|d\|_{[t_{j_l-1}, t_{i_l}]}) \\ &\leq \hat{\gamma}(\|d\|_{[t_{j_l-1}, t_{i_l}]}) \end{aligned}$$

where $\hat{\gamma}(s) := \hat{\gamma}^x(\Gamma s) + \hat{\gamma}^d(s) \in \mathcal{K}_\infty$.

Stabilizing stage $[t_{i_l}, t_{j_{l+1}})$ At the recapture time t_{i_l} ,

$$|x(t_{i_l})| \leq \hat{\gamma}(\|d\|_{[t_{j_l-1}, t_{i_l}]}) ,$$

and Lemma 9 yields

$$\begin{aligned} E_{i_l} &\leq \hat{\chi}^E(E_{j_l-1}, \|d\|_{[t_{j_l-1}, t_{i_l}]}) \\ &\leq \hat{\chi}^E(\Gamma\|d\|_{[t_{j_l-1}, t_{j_l}]}, \|d\|_{[t_{j_l-1}, t_{i_l}]}). \end{aligned}$$

From Lemma 4, for any $t_{i_l} \leq t_k < t_{j_{l+1}}$,

$$\begin{aligned} |x(t_k)| &\leq \chi^x(E_{i_l}, |x(t_{i_l})|) + \chi^d(E_{i_l}, \|d\|_{[t_{i_l}, t_k]}) \\ &\leq \chi^x\left(\hat{\chi}^E(\Gamma\|d\|_{[t_{j_l-1}, t_{j_l}]}, \|d\|_{[t_{j_l-1}, t_{i_l}]}), \hat{\gamma}(\|d\|_{[t_{j_l-1}, t_{i_l}]})\right) \\ &\quad + \chi^d\left(\hat{\chi}^E(\Gamma\|d\|_{[t_{j_l-1}, t_{j_l}]}, \|d\|_{[t_{j_l-1}, t_{i_l}]}), \|d\|_{[t_{i_l}, t_k]}\right) \\ &\leq \bar{\gamma}(\|d\|_{[t_{j_l-1}, t_k]}), \end{aligned}$$

where $\bar{\gamma}(s) := \chi^x(\hat{\chi}^E(\Gamma s, s), \hat{\gamma}(s)) + \chi^d(\hat{\chi}^E(\Gamma s, s), s) \in \mathcal{K}_\infty$.

Combining the above cases yields the bound (4) for all sampling times with the $\mathcal{K}_\infty$ functions

$$\begin{aligned} \gamma_1(s) &:= \max\{\hat{\gamma}_0^x(s), \bar{\chi}_1(E_0, s)\}, \\ \gamma_2(s) &:= \max\{\hat{\gamma}_0^d(s), \bar{\chi}_2(E_0, s), \hat{\gamma}(s), \bar{\gamma}(s)\}. \end{aligned} \tag{46}$$

Next, we establish the bound (5) at sampling times by constructing the function $\gamma_3 \in \mathcal{K}_\infty$. If only finitely many searching stages occur, then the system eventually remains in a stabilizing stage, and Lemma 3 implies

$$\limsup_{k \rightarrow \infty} |x(t_k)| \leq \Phi \limsup_{t \rightarrow \infty} |d(t)|.$$

If infinitely many searching stages occur, then the bounds established in the derivation of (4) imply that, between escape times t_{j_l} and $t_{j_{l+1}}$,

$$\begin{aligned} |x(t_k)| &\leq \hat{\gamma}(\|d\|_{[t_{j_l-1}, t_{i_l}]}) & \forall j_l \leq k \leq i_l, \\ |x(t_k)| &\leq \bar{\gamma}(\|d\|_{[t_{j_l-1}, t_k]}) & \forall i_l \leq k < j_{l+1}. \end{aligned}$$

Therefore,

$$\limsup_{k \rightarrow \infty} |x(t_k)| \leq \gamma_3\left(\limsup_{t \rightarrow \infty} |d(t)|\right)$$

with the $\mathcal{K}_\infty$ function

$$\gamma_3(s) := \max\{\Phi s, \hat{\gamma}(s), \bar{\gamma}(s)\}. \tag{47}$$

The extension of (4) and (5) from sampling times to all $t \geq 0$ follows from standard arguments. Specifically, for any $t \geq 0$, let k be such that $t \in [t_k, t_{k+1})$. We first consider the case that the system is in a

stabilizing stage at t_k and $c_k \neq 0$. From (15) and (16),

$$\begin{aligned} |x(t)| &\leq |\hat{x}(t)| + |e(t)| \\ &\leq \|e^{(A+BK)(t-t_k)}\| \|c_k\| \\ &\quad + \|e^{A(t-t_k)}\| \|e(t_k)\| + \left(\int_0^t \|e^{As} D\| ds \right) \|d\|_{[t_k, t]} \\ &\leq \bar{\Lambda} |c_k| + \frac{\tilde{\Lambda}}{N} E_k + \Phi \|d\|_{[t_k, t]}, \end{aligned}$$

where

$$\bar{\Lambda} := \max_{0 \leq s \leq \tau_s} \|e^{(A+BK)s}\|, \quad \tilde{\Lambda} := \max_{0 \leq s \leq \tau_s} \|e^{As}\|.$$

By (8),

$$|c_k| \leq |x(t_k)| + |x(t_k) - c_k| \leq |x(t_k)| + \frac{E_k}{N},$$

and since (7) fails at t_k ,

$$|x(t_k)| > \frac{E_k}{N}.$$

Hence

$$|x(t)| \leq \tilde{H} |x(t_k)| + \Phi \|d\|_{[t_k, t]}, \quad (48)$$

where

$$\tilde{H} := 2\bar{\Lambda} + \tilde{\Lambda}.$$

If the system is in a stabilizing stage at t_k and $c_k = 0$, or the system is in a searching stage at t_k , then $u \equiv 0$ on $[t_k, t_{k+1})$, and

$$\begin{aligned} |x(t)| &\leq \|e^{A(t-t_k)}\| |x(t_k)| + \left(\int_0^{\tau_s} \|e^{As} D\| ds \right) \|d\|_{[t_k, t]} \\ &\leq \tilde{\Lambda} |x(t_k)| + \Phi \|d\|_{[t_k, t]}, \end{aligned}$$

so (48) still holds.

Since the bound (4) holds for all sampling times with $\gamma_1, \gamma_2 \in \mathcal{K}_\infty$ defined in (46), by (48), it holds for all $t \geq 0$ with the $\mathcal{K}_\infty$ functions

$$\begin{aligned} \gamma_1(s) &:= \tilde{H} \max\{\hat{\gamma}_0^x(s), \bar{\chi}_1(E_0, s)\}, \\ \gamma_2(s) &:= \tilde{H} \max\{\hat{\gamma}_0^d(s), \bar{\chi}_2(E_0, s), \hat{\gamma}(s), \bar{\gamma}(s)\} + \Phi s. \end{aligned}$$

Since

$$\limsup_{k \rightarrow \infty} |x(t_k)| \leq \gamma_3 \left(\limsup_{t \rightarrow \infty} |d(t)| \right)$$

with $\gamma_3 \in \mathcal{K}_\infty$ defined in (47), by (48),

$$\begin{aligned} \limsup_{t \rightarrow \infty} |x(t)| &\leq \limsup_{k \rightarrow \infty} \tilde{H} |x(t_k)| + \Phi \|d\|_{[t_k, t_{k+1}]} \\ &\leq \limsup_{k \rightarrow \infty} \tilde{H} |x(t_k)| + \Phi \limsup_{t \rightarrow \infty} |d(t)|, \end{aligned}$$

which implies the bound (5) with the $\mathcal{K}_\infty$ function

$$\gamma_3(s) := \tilde{H} \max\{\Phi s, \hat{\gamma}(s), \bar{\gamma}(s)\} + \Phi s.$$

7 Simulation example

We illustrate the proposed communication and control strategy on the linear system (1) with

$$A = \begin{bmatrix} 1 & 0 \\ 0 & -1.5 \end{bmatrix}, B = \begin{bmatrix} 1 \\ 0.5 \end{bmatrix}, D = \begin{bmatrix} 1 \\ 0 \end{bmatrix}, K = \begin{bmatrix} -3.5 & 0 \end{bmatrix},$$

sampling period $\tau_s = 0.1$ s, and integer $N = 5$, which satisfy Assumptions 1 and 2. The design parameters are chosen according to the conditions in Sections 5:

$$E_0 = 0.5, \varepsilon = 0.2, \delta = 0.1, \psi = 0.2, \rho = 0.1, \phi = 0.01.$$

The simulation starts from the initial state $x_0 = \begin{bmatrix} 1 & 1 \end{bmatrix}^\top$, which lies outside the initial quantization range. To induce escape and recapture events, disturbance pulses of magnitude 1.5 and duration 0.2 s are applied at $t = 3$ s, 9.5 s, and 11.2 s; otherwise, $d(t) = 0$.




Figure 2: (a) Error $|e(t)| = |x(t) - \hat{x}(t)|$ (blue) and quantization radius E_k (red). (b) State $x_1(t)$ (blue) and auxiliary state $\hat{x}_1(t)$ (red). Black vertical lines indicate disturbance onsets. Shaded regions indicate searching stages. The zoomed-in plots highlight the first escape and the subsequent searching stage and recapture.

Figure 2(a) shows the error $|e(t)| = |x(t) - \hat{x}(t)|$ and the quantization radius E_k . During stabilizing stages, $|e(t_k)|$ and E_k decrease rapidly at sampling times; between sampling times, $|e(t)|$ may increase due to error propagation, while E_k is plotted as a step function. Disturbance pulses cause sharp increases in $|e(t)|$, leading to escapes. During searching stages, the growth rate of E_k dominates that of $|e(t_k)|$, ensuring finite-time (re)capture.

Figure 2(b) shows the state $x_1(t)$ and the auxiliary state $\hat{x}_1(t)$. During stabilizing stages, the control input is $u(t) = -3.5\hat{x}_1(t)$; $x_1(t)$ is driven toward zero, while $\hat{x}_1(t)$ decreases continuously between sampling times and is updated upon receiving new quantized measurements. During searching stages, the control input is set to zero; both $x_1(t)$ and $\hat{x}_1(t)$ grow, although the latter is difficult to discern due to its small magnitude. These behaviors are consistent with the ISS properties established in Theorem 1.

A Proofs of technical lemmas

We first recall several basic facts from linear algebra used throughout the proofs. For any $v, w \in \mathbb{R}^n$, the ∞ -norm satisfies

$$|v|^2 \leq v^\top v, \quad v^\top w \leq n|v||w|. \quad (49)$$

For any symmetric matrix $M \in \mathbb{R}^{n \times n}$ and any $v \in \mathbb{R}^n$,

$$\underline{\lambda}(M) v^\top v \leq v^\top M v \leq \bar{\lambda}(M) v^\top v, \quad (50)$$

which yields

$$\underline{\lambda}(M)|v|^2 \leq v^\top M v \leq n \bar{\lambda}(M)|v|^2. \quad (51)$$

A.1 Proof of Lemma 1

We first consider the case $c_k \neq 0$. From the update formula (19),

$$x_{k+1}^* = S c_k = S(x_k^* + \Delta_k), \quad \Delta_k := c_k - x_k^*,$$

where

$$|\Delta_k| \leq \frac{N-1}{N} E_k$$

by (9). Then

$$\begin{aligned} & (x_{k+1}^*)^\top P x_{k+1}^* \\ &= (x_k^* + \Delta_k)^\top S^\top P S (x_k^* + \Delta_k) \\ &= (x_k^*)^\top S^\top P S x_k^* + 2(x_k^*)^\top S^\top P S \Delta_k + \Delta_k^\top S^\top P S \Delta_k. \end{aligned}$$

Using the Lyapunov equation (22) and bounds (50) and (51), we obtain

$$\begin{aligned} (x_k^*)^\top S^\top P S x_k^* &= (x_k^*)^\top (P - Q) x_k^* \\ &= (x_k^*)^\top P x_k^* - \frac{1}{2} (x_k^*)^\top Q x_k^* - \frac{1}{2} (x_k^*)^\top Q x_k^* \\ &\leq \left(1 - \frac{\underline{\lambda}(Q)}{2\bar{\lambda}(P)}\right) (x_k^*)^\top P x_k^* - \frac{1}{2} \underline{\lambda}(Q) |x_k^*|^2. \end{aligned}$$

Moreover, by (49),

$$\begin{aligned} 2(x_k^*)^\top S^\top P S \Delta_k &\leq 2n_x |x_k^*| \|S^\top P S\| |\Delta_k|, \\ \Delta_k^\top S^\top P S \Delta_k &\leq n_x \|S^\top P S\| |\Delta_k|^2. \end{aligned}$$

Combining the bounds and completing the square yields

$$\begin{aligned}
& (x_{k+1}^*)^\top P x_{k+1}^* \\
& \leq \left(1 - \frac{\lambda(Q)}{2\bar{\lambda}(P)}\right) (x_k^*)^\top P x_k^* - \frac{1}{2} \lambda(Q) |x_k^*|^2 \\
& \quad + 2n_x |x_k^*| \|S^\top P S\| |\Delta_k| + n_x \|S^\top P S\| |\Delta_k|^2 \\
& \leq \left(1 - \frac{\lambda(Q)}{2\bar{\lambda}(P)}\right) (x_k^*)^\top P x_k^* + \chi |\Delta_k|^2 \\
& \quad - \left(\sqrt{\frac{1}{2} \lambda(Q)} |x_k^*| - \frac{\sqrt{2} n_x \|S^\top P S\|}{\sqrt{\lambda(Q)}} |\Delta_k|\right)^2 \\
& \leq \left(1 - \frac{\lambda(Q)}{2\bar{\lambda}(P)}\right) (x_k^*)^\top P x_k^* + \frac{(N-1)^2}{N^2} \chi E_k^2,
\end{aligned}$$

where χ is defined in (23).

Next, from the update formula (20) and Young's inequality,

$$\begin{aligned}
E_{k+1}^2 &= \left(\frac{\Lambda}{N} E_k + \sqrt{\phi} V_k\right)^2 \\
&\leq (1 + \psi) \frac{\Lambda^2}{N^2} E_k^2 + \left(1 + \frac{1}{\psi}\right) \phi V_k
\end{aligned}$$

where $\psi > 0$ is chosen according to (24).

Finally, combining both bounds in $V_{k+1} = (x_{k+1}^*)^\top P x_{k+1}^* + \rho E_{k+1}^2$ yields

$$V_{k+1} \leq \nu V_k,$$

where ν is defined in (26).

If $c_k = 0$, then $x_{k+1}^* = S c_k = 0$, and

$$V_{k+1} = \rho E_{k+1}^2 \leq \left((1 + \psi) \frac{\Lambda^2}{N^2} + \left(1 + \frac{1}{\psi}\right) \phi \rho\right) V_k,$$

so (33) still holds.

A.2 Proof of Lemma 2

We first prove (34). Since $V_k = (x_k^*)^\top P x_k^* + \rho E_k^2$, the upper bound in (51) yields

$$\sqrt{V_k} \leq \sqrt{n_x \bar{\lambda}(P)} |x_k^*| + \sqrt{\rho} E_k,$$

where we used $\sqrt{a+b} \leq \sqrt{a} + \sqrt{b}$. Moreover, by (6),

$$|x_k^*| \leq |x(t_k)| + |x(t_k) - x_k^*| \leq |x(t_k)| + E_k.$$

Hence (34) holds with

$$C_1 := \sqrt{n_x \bar{\lambda}(P)} + \sqrt{\rho}.$$

Next, we establish (35). From (6),

$$|x(t_k)| \leq |x_k^*| + |x(t_k) - x_k^*| \leq |x_k^*| + E_k.$$

Using the lower bound in (51), we obtain

$$|x_k^*| \leq \sqrt{\frac{V_k}{\underline{\lambda}(P)}}, \quad E_k \leq \sqrt{\frac{V_k}{\rho}}$$

which yields (35) with

$$C_2 := \frac{1}{\sqrt{\underline{\lambda}(P)}} + \frac{1}{\sqrt{\rho}}.$$

Finally, we prove (36). From the error estimate (17) and update formula (19),

$$\begin{aligned} |x(t_{k+1})| &\leq |\hat{x}(t_{k+1}^-)| + |e(t_{k+1}^-)| \\ &\leq \|S\| |c_k| + \frac{\Lambda}{N} E_k + \Phi \|d\|_{[t_k, t_{k+1}]}. \end{aligned}$$

We first consider the case $c_k \neq 0$. By (9) and the lower bound in (51),

$$|c_k| \leq |x_k^*| + |c_k - x_k^*| \leq |x_k^*| + \frac{N-1}{N} E_k.$$

Hence

$$|x(t_{k+1})| \leq \|S\| |x_k^*| + \frac{(N-1)\|S\| + \Lambda}{N} E_k + \Phi \|d\|_{[t_k, t_{k+1}]}. \quad (36)$$

Bounding $|x_k^*|$ and E_k in terms of V_k yields (36) with

$$C_3 := \frac{\|S\|}{\sqrt{\underline{\lambda}(P)}} + \frac{(N-1)\|S\| + \Lambda}{N\sqrt{\rho}}.$$

If $c_k = 0$, then $\hat{x}(t_{k+1}^-) = Sc_k = 0$, and

$$|x(t_{k+1})| = |e(t_{k+1}^-)| \leq \frac{\Lambda}{N} E_k + \Phi \|d\|_{[t_k, t_{k+1}]},$$

so (36) still holds.

A.3 Proof of Lemma 3

By iterating Lemma 1, we obtain

$$V_{k-1} \leq \nu^{k-1-l} V_l,$$

where $\nu \in (0, 1)$. Applying (34) at t_l and (36) at t_{k-1} yields

$$\begin{aligned} |x(t_k)| &\leq C_3 \sqrt{V_{k-1}} + \Phi \|d\|_{[t_{k-1}, t_k]} \\ &\leq C_3 \nu^{(k-l-1)/2} \sqrt{V_l} + \Phi \|d\|_{[t_{k-1}, t_k]} \\ &\leq C_1 C_3 \nu^{(k-l-1)/2} (|x(t_l)| + E_l) + \Phi \|d\|_{[t_{k-1}, t_k]}. \end{aligned}$$

Hence (37) holds with

$$C := C_1 C_3 \nu^{-1/2}, \quad \lambda := -\frac{1}{2} \ln \nu > 0.$$

A.4 Proof of Lemma 4

We consider two cases depending on whether the initial state dominates the disturbance.

Case 1: $|x(t_l)| > \Phi \|d\|_{[t_l, t_k]}$. Let

$$H := 2\|S\| + \Lambda > 1.$$

Then $\log_\nu H < 0$ since $\nu \in (0, 1)$. Fix any $\kappa \in (0, -1/\log_\nu H)$, and define

$$l_x := \max\{\lceil \kappa \log_\nu |x(t_l)| \rceil, 0\}.$$

Then $\nu^{l_x} \leq |x(t_l)|^\kappa$ for all $|x(t_l)| > 0$. We distinguish between the “long-time” regime $k \geq l + l_x$ and the “short-time” regime $k < l + l_x$.

If $k \geq l + l_x$, iterating Lemma 1 yields

$$V_k \leq \nu^{k-l} V_l \leq \nu^{l_x} V_l \leq |x(t_l)|^\kappa V_l.$$

Applying (34) at t_l and (35) at t_k , we obtain

$$\begin{aligned} |x(t_k)| &\leq C_2 \sqrt{V_k} \\ &\leq C_2 |x(t_l)|^{\kappa/2} \sqrt{V_l} \\ &\leq C_1 C_2 |x(t_l)|^{\kappa/2} (|x(t_l)| + E_l) =: \chi_1^x(E_l, |x(t_l)|), \end{aligned}$$

where $\chi_1^x(\cdot, s)$ is nondecreasing for each fixed $s > 0$ and $\chi_1^x(E, \cdot) \in \mathcal{K}_\infty$ for each fixed $E > 0$.

If $l \leq k < l + l_x$, we first consider the case $c_k \neq 0$. From the error estimate (17) and update formula (19),

$$\begin{aligned} |x(t_{k+1})| &\leq |\hat{x}(t_{k+1}^-)| + |e(t_{k+1}^-)| \\ &\leq \|S\| |c_k| + \frac{\Lambda}{N} E_k + \Phi \|d\|_{[t_k, t_{k+1}]}. \end{aligned}$$

By (8),

$$|c_k| \leq |x(t_k)| + |x(t_k) - c_k| \leq |x(t_k)| + \frac{E_k}{N},$$

and since (7) fails at t_k ,

$$|x(t_k)| > \frac{E_k}{N}.$$

Hence

$$|x(t_{k+1})| \leq H |x(t_k)| + \Phi \|d\|_{[t_k, t_{k+1}]}. \quad (52)$$

If $c_k = 0$, then $u \equiv 0$ on $[t_k, t_{k+1})$, and

$$\begin{aligned} |x(t_{k+1})| &\leq \|e^{A\tau_s}\| |x(t_k)| + \left(\int_0^{\tau_s} \|e^{As} D\| ds \right) \|d\|_{[t_k, t_{k+1}]} \\ &\leq \Lambda |x(t_k)| + \Phi \|d\|_{[t_k, t_{k+1}]}, \end{aligned}$$

so (52) still holds. Since (52) holds for all sampling times between t_l and t_k , iterating it yields

$$\begin{aligned} |x(t_k)| &\leq H^{k-l}|x(t_l)| + \frac{H^{k-l} - 1}{H - 1} \Phi \|d\|_{[t_l, t_k]} \\ &\leq \frac{H^{k-l+1} - 1}{H - 1} |x(t_l)| \\ &\leq \frac{H^{l_x} - 1}{H - 1} |x(t_l)| =: \chi_2^x(|x(t_l)|). \end{aligned}$$

If $|x(t_l)| = s < 1$, then $l_x < \kappa \log_\nu s + 1$, and

$$\chi_2^x(s) < \frac{H^{\kappa \log_\nu s + 1}}{H - 1} s = \frac{H}{H - 1} s^{\kappa \log_\nu H + 1} =: \chi_3^x(s).$$

where $\chi_3^x \in \mathcal{K}_\infty$ since $\kappa \log_\nu H + 1 > 0$. If $|x(t_l)| = s \geq 1$, then $l_x = 0$, and $\chi_2^x(s) = 0 < \chi_3^x(s)$.

Finally,

$$\begin{aligned} |x(t_k)| &\leq \max\{\chi_1^x(E_l, |x(t_l)|), \chi_3^x(|x(t_l)|)\} \\ &=: \chi^x(E_l, |x(t_l)|), \end{aligned}$$

which satisfies the stated monotonicity and $\mathcal{K}_\infty$ properties.

Case 2: $|x(t_l)| \leq \Phi \|d\|_{[t_l, t_k]}$. The proof follows the same steps as in Case 1 and is omitted for brevity. It yields analogous functions χ_1^d and χ_3^d such that

$$\begin{aligned} |x(t_k)| &\leq \max\{\chi_1^d(E_l, \|d\|_{[t_l, t_k]}), \chi_3^d(\|d\|_{[t_l, t_k]})\} \\ &=: \chi^d(E_l, \|d\|_{[t_l, t_k]}), \end{aligned}$$

which satisfies the stated monotonicity and $\mathcal{K}_\infty$ properties.

Combining the two cases yields (38).

A.5 Proof of Lemma 5

Since (6) holds at t_{j-1} but fails at t_j ,

$$|e(t_j)| = |x(t_j) - x_j^*| > E_j.$$

Applying the error estimate (17) and update formula (20) at t_{j-1} , we obtain

$$\frac{\Lambda}{N} E_{j-1} + \Phi \|d\|_{[t_{j-1}, t_j]} > \frac{\Lambda}{N} E_{j-1} + \sqrt{\phi V_{j-1}},$$

that is,

$$\sqrt{\phi V_{j-1}} < \Phi \|d\|_{[t_{j-1}, t_j]}.$$

Therefore,

$$E_{j-1} \leq \sqrt{\frac{V_{j-1}}{\rho}} < \frac{1}{\sqrt{\rho\phi}} \Phi \|d\|_{[t_{j-1}, t_j]}.$$

Next, applying (36) at t_{j-1} yields

$$\begin{aligned} |x(t_j)| &\leq C_3 \sqrt{V_{j-1}} + \Phi \|d\|_{[t_{j-1}, t_j]} \\ &< \left(\frac{C_3}{\sqrt{\phi}} + 1 \right) \Phi \|d\|_{[t_{j-1}, t_j]}. \end{aligned}$$

Combining the two bounds, we obtain (39) with

$$\Gamma := \max \left\{ \frac{1}{\sqrt{\rho\phi}}, \frac{C_3}{\sqrt{\phi}} + 1 \right\} \Phi > 0,$$

where $C_3 > 0$ is from Lemma 2.

A.6 Proof of Lemma 6

Let $t_k > 0$ be a sampling time such that the state has not yet been captured by t_k . Then the system remains in a searching stage on $[0, t_k)$, and iterating the error estimate (29) and update formulas (30) and (31) from 0 to t_k with $x_0^* = 0$ yields

$$\begin{aligned} |e(t_k^-)| &\leq \Lambda^k |x_0| + \frac{\Lambda^k - 1}{\Lambda - 1} \Phi \|d\|_{[0, t_k]}, \\ E_k &= \hat{\Lambda}^k E_0 + \frac{\hat{\Lambda}^k - 1}{\hat{\Lambda} - 1} \Phi \delta. \end{aligned}$$

Let i_0^* be the smallest positive integer such that

$$i_0^* \geq \max \left\{ \eta_x \left(\frac{|x_0|}{E_0} \right), \eta_d \left(\frac{\|d\|_{[0, t_{i_0^*}^*]}}{\delta} \right) \right\}.$$

Such an integer exists if $\|d\|$ is finite. We show that the state is captured no later than $t_{i_0^*}$.

First, since $i_0^* \geq \eta_x(|x_0|/E_0)$,

$$\begin{aligned} \hat{\Lambda}^{i_0^*} E_0 &= \Lambda^{i_0^*} (1 + \varepsilon)^{i_0^*} E_0 \\ &\geq \Lambda^{i_0^*} (1 + \varepsilon)^{\eta_x(|x_0|/E_0)} E_0 \geq \Lambda^{i_0^*} |x_0|. \end{aligned}$$

Second, if $\delta < \|d\|_{[0, t_{i_0^*}^*]}$, then

$$i_0^* \geq \eta_d \left(\frac{\|d\|_{[0, t_{i_0^*}^*]}}{\delta} \right) \geq \log_{1+\varepsilon} \left(\frac{r_\varepsilon \|d\|_{[0, t_{i_0^*}^*]}}{\delta} \right),$$

and

$$\begin{aligned} \frac{\hat{\Lambda}^{i_0^*} - 1}{\hat{\Lambda} - 1} \delta &> \frac{\Lambda^{i_0^*} - 1}{\hat{\Lambda} - 1} (1 + \varepsilon)^{i_0^*} \delta \\ &= \frac{\Lambda^{i_0^*} - 1}{\Lambda - 1} \frac{(1 + \varepsilon)^{i_0^*}}{r_\varepsilon} \delta \geq \frac{\Lambda^{i_0^*} - 1}{\Lambda - 1} \|d\|_{[0, t_{i_0^*}^*]}. \end{aligned}$$

Otherwise, $\delta \geq \|d\|_{[0, t_{i_0}^*]}$, and since $\hat{\Lambda} > \Lambda$,

$$\frac{\hat{\Lambda}^{i_0^*} - 1}{\hat{\Lambda} - 1} \delta \geq \frac{\Lambda^{i_0^*} - 1}{\Lambda - 1} \|d\|_{[0, t_{i_0}^*]}.$$

Combining these bounds yields

$$E_{i_0^*} \geq |e(t_{i_0^*})|.$$

Hence the state is captured at some sampling time $t_{i_0} \leq t_{i_0^*}$. If $i_0 < i_0^*$, then (40) follows immediately. If $i_0 = i_0^*$, then

$$i_0 - 1 < \max \left\{ \eta_x \left(\frac{|x_0|}{E_0} \right), \eta_d \left(\frac{\|d\|_{[0, t_{i_0-1}]}}{\delta} \right) \right\},$$

and since both sides are integers, (40) still holds.

A.7 Proof of Lemma 7

Consider any $t_k \leq t_{i_0}$. Since the state is first captured at t_{i_0} , the system remains in a searching stage on $[0, t_{i_0})$.

First, iterating the error estimate (29) and update formula (30) from 0 to t_k with $x_0^* = 0$ yields

$$\begin{aligned} |x(t_k)| &\leq \Lambda^k |x_0| + \frac{\Lambda^k - 1}{\Lambda - 1} \Phi \|d\|_{[0, t_k]} \\ &\leq \Lambda^{i_0} |x_0| + \frac{\Lambda^{i_0} - 1}{\Lambda - 1} \Phi \|d\|_{[0, t_{i_0}]}. \end{aligned}$$

Substituting the bound on i_0 from (40) into the right-hand side, we obtain a bound on $|x(t_k)|$ that is nondecreasing in $|x_0|$ and $\|d\|_{[0, t_{i_0}]}$ and vanishes when $|x_0| = \|d\|_{[0, t_{i_0}]} = 0$. Therefore, it can be dominated by $\mathcal{K}_\infty$ functions $\hat{\gamma}_0^x(|x_0|) + \hat{\gamma}_0^d(\|d\|_{[0, t_{i_0}]})$ using a standard comparison-function construction, which proves (41).

Second, iterating the update formula (31) from 0 to t_{i_0} yields

$$E_{i_0} = \hat{\Lambda}^{i_0} E_0 + \frac{\hat{\Lambda}^{i_0} - 1}{\hat{\Lambda} - 1} \Phi \delta.$$

Substituting again the bound on i_0 from (40) into the right-hand side, we obtain a bound on E_{i_0} that, for each fixed $E_0 > 0$, is nondecreasing in $|x_0|$ and $\|d\|_{[0, t_{i_0}]}$. Therefore, by another standard comparison-function construction, there exists a continuous function $\hat{\chi}_0^E : \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0} \times \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{>0}$ with the stated monotonicity property such that (42) holds.

A.8 Proof of Lemma 8

If the state is recaptured at t_{j+1} , then $i = j + 1$ and (43) holds. In the remainder of the proof, we assume that the state is not recaptured at t_{j+1} .

The system remains in a searching stage on $[t_j, t_i)$. Applying the same argument as in the proof of Lemma 6, with the adjustment at t_j according to (32), we obtain

$$i \leq j + \max \left\{ \eta_x \left(\frac{|e(t_j)|}{\hat{E}_j} \right), \eta_d \left(\frac{\|d\|_{[t_j, t_i]}}{\delta} \right), 1 \right\}, \quad (53)$$

where η_x, η_d are defined in Lemma 6 and satisfy $\eta_x(s) \leq \eta_d(s)$ for all $s \geq 0$.

Next, applying the searching-stage error estimate (29) at t_j and the stabilizing-stage error estimate (17) at t_{j-1} yields

$$\begin{aligned} |e(t_{j+1})| &\leq \Lambda |e(t_j)| + \Phi \|d\|_{[t_j, t_{j+1}]} \\ &\leq \frac{\Lambda^2}{N} |e(t_{j-1})| + (\Lambda + 1) \Phi \|d\|_{[t_{j-1}, t_{j+1}]}. \end{aligned}$$

Moreover, from the adjusted update formula (32),

$$E_{j+1} = \hat{\Lambda} \hat{E}_j + \Phi \delta = \frac{\hat{\Lambda} \Lambda}{N} E_{j-1} + (\hat{\Lambda} + 1) \Phi \delta,$$

where $\hat{\Lambda} = (1 + \varepsilon) \Lambda$.

Since the state escapes at t_j and is not recaptured at t_{j+1} ,

$$|e(t_{j-1})| \leq E_{j-1}, \quad |e(t_{j+1})| > E_{j+1},$$

and the above bound on $|e(t_{j+1})|$ and formula of E_{j+1} imply

$$\delta < \|d\|_{[t_{j-1}, t_{j+1}]}. \quad (54)$$

Consequently,

$$\frac{|e(t_j)|}{\hat{E}_j} \leq \frac{\frac{\Lambda}{N} |e(t_{j-1})| + \Phi \|d\|_{[t_{j-1}, t_{j+1}]}}{\frac{\Lambda}{N} E_{j-1} + \Phi \delta} < \frac{\|d\|_{[t_{j-1}, t_{j+1}]}}{\delta},$$

and thus

$$\eta_x \left(\frac{|e(t_j)|}{\hat{E}_j} \right) \leq \eta_x \left(\frac{\|d\|_{[t_{j-1}, t_{j+1}]}}{\delta} \right) \leq \eta_d \left(\frac{\|d\|_{[t_{j-1}, t_{j+1}]}}{\delta} \right).$$

Substituting this bound into (53) yields (43).

A.9 Proof of Lemma 9

Since the state escapes at t_j and is recaptured at t_i , the system remains in a searching stage on $[t_j, t_i)$. Consider any sampling time $t_k \in [t_j, t_i)$.

First, since $u \equiv 0$ on $[t_j, t_i)$, the state satisfies

$$\dot{x} = Ax + Dd,$$

and thus

$$|x(t_{k+1})| \leq \Lambda |x(t_k)| + \Phi \|d\|_{[t_k, t_{k+1}]}$$

Iterating this bound from t_j to t_k yields

$$\begin{aligned} |x(t_k)| &\leq \Lambda^{k-j} |x(t_j)| + \frac{\Lambda^{k-j} - 1}{\Lambda - 1} \Phi \|d\|_{[t_j, t_k]} \\ &\leq \Lambda^{i-j} |x(t_j)| + \frac{\Lambda^{i-j} - 1}{\Lambda - 1} \Phi \|d\|_{[t_j, t_i]}. \end{aligned}$$

Substituting the bound on i from (43) into the right-hand side, we obtain a bound on $|x(t_k)|$ that is nondecreasing in $|x(t_j)|$ and $\|d\|_{[t_{j-1}, t_i]}$ and vanishes when $|x(t_j)| = \|d\|_{[t_{j-1}, t_i]} = 0$. Therefore, it can be dominated by $\mathcal{K}_\infty$ functions $\hat{\gamma}^x(|x(t_j)|) + \hat{\gamma}^d(\|d\|_{[t_{j-1}, t_i]})$ using a standard comparison-function construction, which proves (44).

Second, iterating the update formula (31) from t_j to t_i , with the adjustment at t_j according to (32), yields

$$\begin{aligned} E_i &= \hat{\Lambda}^{i-j} \hat{E}_j + \frac{\hat{\Lambda}^{i-j} - 1}{\hat{\Lambda} - 1} \Phi \delta \\ &= \frac{\hat{\Lambda}^{i-j} \Lambda}{N} E_{j-1} + \frac{\hat{\Lambda}^{i-j+1} - 1}{\hat{\Lambda} - 1} \Phi \delta. \end{aligned}$$

Substituting again the bound on i from (43) into the right-hand side, we obtain a bound on E_i that, for each fixed $E_{j-1} > 0$, is nondecreasing in $\|d\|_{[t_{j-1}, t_i]}$. Therefore, by another standard comparison-function construction, there exists a continuous function $\hat{\chi}^E : \mathbb{R}_{>0} \times \mathbb{R}_{\geq 0} \rightarrow \mathbb{R}_{>0}$ with the stated monotonicity property such that (45) holds.

References

- [1] G. N. Nair, F. Fagnani, S. Zampieri, and R. J. Evans, “Feedback control under data rate constraints: An overview,” *Proc. IEEE*, vol. 95, no. 1, pp. 108–137, Jan. 2007.
- [2] Z.-P. Jiang and T. Liu, “Quantized nonlinear control — A survey,” *Acta Autom. Sin.*, vol. 39, no. 11, pp. 1820–1830, Nov. 2013.
- [3] P. Park, S. C. Ergen, C. Fischione, C. Lu, and K. H. Johansson, “Wireless network design for control systems: A survey,” *IEEE Communications Surveys & Tutorials*, vol. 20, no. 2, pp. 978–1013, 2018.
- [4] D. F. Delchamps, “Stabilizing a linear system with quantized state feedback,” *IEEE Transactions on Automatic Control*, vol. 35, no. 8, pp. 916–924, 1990.
- [5] N. Elia and S. K. Mitter, “Stabilization of linear systems with limited information,” *IEEE Transactions on Automatic Control*, vol. 46, no. 9, pp. 1384–1400, Sep. 2001.
- [6] R. W. Brockett and D. Liberzon, “Quantized feedback stabilization of linear systems,” *IEEE Transactions on Automatic Control*, vol. 45, no. 7, pp. 1279–1289, Jul. 2000.
- [7] D. Liberzon, “Hybrid feedback stabilization of systems with quantized signals,” *Automatica*, vol. 39, no. 9, pp. 1543–1554, Sep. 2003.

- [8] J. P. Hespanha, A. Ortega, and L. Vasudevan, “Towards the control of linear systems with minimum bit-rate,” in *15th Int. Symp. Math. Theory Networks Syst.*, 2002, 15 pages.
- [9] D. Liberzon, “On stabilization of linear systems with limited information,” *IEEE Trans. Automat. Contr.*, vol. 48, no. 2, pp. 304–307, Feb. 2003.
- [10] S. Tatikonda and S. Mitter, “Control under communication constraints,” *IEEE Trans. Automat. Contr.*, vol. 49, no. 7, pp. 1056–1068, Jul. 2004.
- [11] D. Liberzon and J. P. Hespanha, “Stabilization of nonlinear systems with limited information feedback,” *IEEE Trans. Automat. Contr.*, vol. 50, no. 6, pp. 910–915, Jun. 2005.
- [12] M. D. Ferdinando, B. Castillo-Toledo, S. D. Gennaro, and P. Pepe, “Robust quantized sampled-data stabilization for a class of Lipschitz nonlinear systems with time-varying uncertainties,” *IEEE Control Syst. Lett.*, vol. 6, pp. 1256–1261, 2022.
- [13] D. Liberzon, “Finite data-rate feedback stabilization of switched and hybrid linear systems,” *Automatica*, vol. 50, no. 2, pp. 409–420, Feb. 2014.
- [14] G. Yang and D. Liberzon, “Feedback stabilization of switched linear systems with unknown disturbances under data-rate constraints,” *IEEE Trans. Automat. Contr.*, vol. 63, no. 7, pp. 2107–2122, Jul. 2018.
- [15] D. Liberzon and D. Nešić, “Input-to-state stabilization of linear systems with quantized state measurements,” *IEEE Trans. Automat. Contr.*, vol. 52, no. 5, pp. 767–781, May 2007.
- [16] E. D. Sontag, “Smooth stabilization implies coprime factorization,” *IEEE Trans. Automat. Contr.*, vol. 34, no. 4, pp. 435–443, Apr. 1989.
- [17] J. Wang, “A necessary and sufficient condition for input-to-state stability of quantised feedback systems,” *Int. J. Control*, vol. 90, no. 9, pp. 1846–1860, 2017.
- [18] Y. Sharon and D. Liberzon, “Input to state stabilizing controller for systems with coarse quantization,” *IEEE Trans. Automat. Contr.*, vol. 57, no. 4, pp. 830–844, Apr. 2012.
- [19] E. D. Sontag and Y. Wang, “New characterizations of input-to-state stability,” *IEEE Trans. Automat. Contr.*, vol. 41, no. 9, pp. 1283–1294, Sep. 1996.