

- a) **Describe all the pins of PIC16f877A. After that, your colleagues would have enough information once they need to interface the PIC16f877A with other hardware.**

## **ANSWER:**

1. MCLR/ VPP: This is the Master Clear/ Voltage Programming Pin. It is an active-low input pin that is used to reset the microcontroller. It can also be used for programming the device during production.
2. RA0/AN0: This is a general-purpose input/output (GPIO) pin that can be used for both analog and digital signals.
3. RA1/AN1: This is also a GPIO pin that can be used for both analog and digital signals.
4. RA2/AN2: This is a GPIO pin that can be used for both analog and digital signals.
5. RA3/AN3/VREF-: This is a GPIO pin that can be used for both analog and digital signals. It can also be used as an analog input for the ADC and as a reference voltage for the ADC.
6. RA4/T0CKI: This is a GPIO pin that can be used as a timer input or as a counter input.
7. RA5/AN4/SS: This is a GPIO pin that can be used for both analog and digital signals. It is also used as the Slave Select pin in SPI communication mode.
8. RE0/RD/AN5: This is a GPIO pin that can be used for both analog and digital signals. It is also used as a read signal in external memory interfacing.
9. RE1/WR/AN6: This is a GPIO pin that can be used for both analog and digital signals. It is also used as a write signal in external memory interfacing.
10. RE2/CS/AN7: This is a GPIO pin that can be used for both analog and digital signals. It is also used as a chip select signal in external memory interfacing.
11. VSS: This is the ground pin of the microcontroller.
12. VDD: This is the power supply pin of the microcontroller.
13. OSC1/CLKIN: This pin is connected to an external oscillator or crystal to provide a clock signal to the microcontroller.

- 14.OSC2/CLKOUT: This pin is connected to an external oscillator or crystal for providing a clock signal to the microcontroller. It can also be used as a clock output for other devices.
- 15.RC0/T1OSO/T13CKI: This is a GPIO pin that can be used as a timer output or as a clock input.
- 16.RC1/T1OSI/CCP2: This is a GPIO pin that can be used as a timer input or as a capture/compare/PWM (CCP) module 2 input.
- 17.RC2/CCP1: This is a GPIO pin that can be used as a CCP module 1 input.
- 18.RC3/SCK/SCL: This is a GPIO pin that is used as the Serial Clock pin in SPI or I2C communication mode.
- 19.RC4/SDI/SDA: This is a GPIO pin that is used as the Serial Data Input pin in SPI or I2C communication mode.
- 20.RC5/SDO: This is a GPIO pin that is used as the Serial Data Output pin in SPI communication mode.
- 21.RC6/TX/CK: This is a GPIO pin that is used as the Transmit pin in UART communication mode. It can also be used as a clock output for other devices.
- 22.RC7/RX/DT: This is a GPIO pin that is used as the Receive pin in UART communication mode. It can also be used as a data input for other devices.
- 23.RD0/PSP0: This is a GPIO pin that can be used as a Parallel Slave Port (PSP) data pin.
- 24.RD1/PSP1: This is a GPIO pin that can be used as a PSP data pin.
- 25.RD2/PSP2: This is a GPIO pin that can be used as a PSP data pin.
- 26.RD3/PSP3: This is a GPIO pin that can be used as a PSP data pin.
- 27.RD4/PSP4: This is a GPIO pin that can be used as a PSP data pin.
- 28.RD5/PSP5: This is a GPIO pin that can be used as a PSP data pin.
- 29.RD6/PSP6: This is a GPIO pin that can be used as a PSP data pin.
- 30.RD7/PSP7: This is a GPIO pin that can be used as a PSP data pin.
- 31.PGD: This is the Programming Data pin used for In-Circuit Serial Programming (ICSP).
- 32.PGC: This is the Programming Clock pin used for ICSP.
- 33.VSS: This is the ground pin of the microcontroller.
- 34.VDD: This is the power supply pin of the microcontroller.
- 35.RB0/INT: This is a GPIO pin that can be used as an external interrupt input.

- 36.RB1/SDO/SDA: This is a GPIO pin that can be used as the Serial Data Output pin in SPI communication mode or as the Serial Data Input pin in I2C communication mode.
- 37.RB2/INT2/CCP1: This is a GPIO pin that can be used as an external interrupt input or as a CCP module 1 input.
- 38.RB3/CCP2/INT3: This is a GPIO pin that can be used as a CCP module 2 input or as an external interrupt input.
- 39.RB4/AN11: This is a GPIO pin that can be used for both analog and digital signals.
- 40.RB5/AN12: This is a GPIO pin that can be used for both analog and digital signals.
- b) Explain to your colleagues the functions of the main blocks in PIC16f877A : ALU, Status and Control, Program Counter, Flash Program Memory, Instruction Register, Instruction Decoder.**

## ANSWER:

1. ALU (Arithmetic Logic Unit): The ALU is responsible for performing arithmetic and logical operations on data. It can perform operations such as addition, subtraction, AND, OR, and XOR. The ALU receives data from the working registers and performs the specified operation, and then stores the result in the working registers.
2. Status and Control: The Status and Control block contains several registers that are used to control the operation of the microcontroller and provide status information. These registers include the Program Status Register (PSR), which contains flags that indicate the status of the last operation performed by the ALU, and the Control Register (CR), which contains bits that control the operation of the microcontroller, such as interrupt enable/disable bits.
3. Program Counter: The Program Counter (PC) keeps track of the address of the next instruction to be executed. When an instruction is executed, the PC is incremented to point to the next instruction in memory.
4. Flash Program Memory: The Flash Program Memory is where the program code is stored. The PIC16F877A has 14KB of Flash Program Memory, which can be programmed and reprogrammed in-circuit. The program code is stored in memory as a series of instructions that the microcontroller executes in order.

5. Instruction Register: The Instruction Register (IR) is a temporary register that holds the current instruction being executed. When an instruction is fetched from memory, it is loaded into the IR, and then decoded and executed.
  6. Instruction Decoder: The Instruction Decoder decodes the instruction in the IR and determines which operation needs to be performed. The decoder reads the opcode (operation code) of the instruction and determines which instruction is being executed, and then sends the appropriate signals to the ALU and other blocks to carry out the operation.
- c) **Examine the reasons why a led, which is connected to RA4 for flashing prepose not working probably.**

## ANSWER:

If a LED connected to RA4 of the PIC16F877A is not flashing properly, there could be several reasons for this issue. Here are some possible reasons:

1. Incorrect I/O configuration: The most common reason why a LED is not flashing is due to incorrect I/O configuration. Ensure that the RA4 pin is configured as an output pin and that the TRISA4 bit is cleared to allow output. Also, check that the pin is not configured for any other alternate functions that could interfere with its operation as a GPIO.
2. Incorrect power supply: Check that the microcontroller is being powered correctly and that the voltage is within the operating range of the PIC16F877A. The LED may not be flashing if the power supply voltage is too low or too high.
3. Incorrect LED polarity: Ensure that the LED is connected correctly with the correct polarity. If the LED is connected in reverse, it will not light up.
4. Insufficient current: The LED may not be flashing because it is not receiving enough current. Ensure that the LED current-limiting resistor is properly sized and that the value is appropriate for the LED. If the resistor value is too high, the LED may not light up, and if it is too low, it may burn out.
5. Software issues: Check the software code to ensure that the LED is being toggled correctly. Verify that the correct register is being written to toggle the LED state. Also, ensure that there are no errors in the code

that could be causing the LED to malfunction, such as an infinite loop or an incorrect conditional statement.

6. Hardware issues: Check the physical connections of the LED and the microcontroller to ensure that there are no loose connections or damaged pins. Also, check that there are no short circuits or other hardware issues that could be interfering with the operation of the LED.

**d) ATmega328P [2] is also an 8-bit but AVR microcontroller. Evaluate the characteristics of ATmega328P versus PIC16f877A, by comparing the memory size, the power consumption, pin count... of those two MCUs. Give 2 examples of embedded systems where ATmega328P is a better choice than PIC16f877A.**

## ANSWER:

Here is a comparison of the characteristics of the ATmega328P and the PIC16F877A microcontrollers:

1. Memory size: The ATmega328P has 32KB of Flash program memory and 2KB of SRAM, whereas the PIC16F877A has 14KB of Flash program memory and 368 bytes of RAM. Therefore, the ATmega328P has more program memory and RAM compared to the PIC16F877A, which makes it suitable for more complex applications.
2. Power consumption: The ATmega328P has a lower power consumption than the PIC16F877A. The ATmega328P can operate at a voltage range of 1.8V to 5.5V and has a typical current consumption of 1.5mA at 1MHz and 1.8V, whereas the PIC16F877A operates at a voltage range of 2.0V to 5.5V and has a typical current consumption of 15mA at 1MHz and 5V. Therefore, the ATmega328P is more suitable for low-power applications.
3. Pin count: The ATmega328P has 28 pins, while the PIC16F877A has 40 pins. The lower pin count of the ATmega328P makes it suitable for applications that require a smaller form factor and fewer I/O pins.

Based on these characteristics, the ATmega328P is a better choice than the PIC16F877A for embedded systems that require more program memory, lower power consumption, and a smaller form factor.