Health watch — main board

Sơ đồ phân cấp: mỗi ô là một trang con. Nhãn toàn cục (global label) nối tín hiệu giữa các trang; ký hiệu nguồn nối theo tên.

Ref 101–199. Sinh tự động bởi tools/gen_sch.py từ tools/design.py.

Power: USB-C, AXP2101 PMIC, battery, current shunts

File: health_watch_main_power.kicad_sch

ESP32-S3R8 + 16 MB flash + RF

File: health_watch_main_mcu.kicad_sch

Display FPC, IMU, RTC, LED boost, sensor-board FPC

File: health_watch_main_periph.kicad_sch

Motor, buzzer, SOS button, status LED

File: health_watch_main_ui.kicad_sch

Generated by tools/gen_sch.py from tools/design.py — edit the design file, not this sheet

harisama1 — đồ án đồng hồ sức khỏe

Sheet: /
File: health_watch_main.kicad_sch


Title: Health watch — main board — root

Size: A4	Date: 2026-11-05	**Rev: 1.3**
KiCad E.D.A. 10.0.8		Id: 1/5


Power: USB-C, AXP2101 PMIC, battery, current shunts

USB-C → ESD → AXP2101 (sạc LiPo + DCDC1 3.3 V). Shunt + test point để đo dòng: pin (R111) và 3V3 (R112).

USB-C + ESD



PMIC AXP2101 + pin + shunt đo dòng



Generated by tools/gen_sch.py from tools/design.py — edit the design file, not this sheet

harisama1 — đồ án đồng hồ sức khỏe

Sheet: /Power: USB-C, AXP2101 PMIC, battery, current shunts/
File: health_watch_main_power.kicad_sch


Title: Health watch — main board — Power: USB-C, AXP2101 PMIC, battery,

Size: A3	Date: 2026-11-05	**Rev: 1.3**
KiCad E.D.A. 10.0.8		Id: 2/5


ESP32-S3R8 + 16 MB flash + RF

ESP32-S3R8: decoupling theo HDG Fig.1 p.5, thạch anh 40 MHz, flash QSPI 16 MB, mạch phối hợp RF + ăng-ten gốm, UART0.

ESP32-S3R8 + flash + thạch anh + RF + UART0



Reset (CHIP_PU) + Boot (GPIO0)



Generated by tools/gen_sch.py from tools/design.py — edit the design file, not this sheet

harisama1 — đồ án đồng hồ sức khỏe

Sheet: /ESP32-S3R8 + 16 MB flash + RF/

File: health_watch_main_mcu.kicad_sch


Title: Health watch — main board — ESP32-S3R8 + 16 MB flash + RF

Size: A3	Date: 2026-11-05	**Rev: 1.3**
KiCad E.D.A. 10.0.8		Id: 3/5

Display FPC, IMU, RTC, LED boost, sensor-board FPC


Màn hình AMOLED (FPC 31P như Waveshare 1.75C), IMU BMI270, RTC PCF85063A, boost 5 V cho LED PPG, FPC 16P sang bo cảm biến.

FPC màn hình AMOLED + cảm ứng




QSPI + I2C chung


IMU BMI270 + RTC PCF85063A



I2C 0x68: CSB = VDDIO, SDO = GND




Boost 5 V cho LED PPG (TPS61240)




EN = GPIO3, kéo xuống 1 MΩ: giữ bằng RTC hold khi ngủ. I_LED = V(TP108−TP109) / 0.1 Ω

FPC 16P sang bo cảm biến



Cáp đảo đưa 5 V vào chân tín hiệu: đo thông mạch trước khi cấp nguồn

Điểm đo bus (bring-up)



Generated by tools/gen_sch.py from tools/design.py — edit the design file, not this sheet

harisama1 — đồ án đồng hồ sức khỏe

Sheet: /Display FPC, IMU, RTC, LED boost, sensor-board FPC/
File: health_watch_main_periph.kicad_sch


Title: Health watch — main board — Display FPC, IMU, RTC, LED boost, senso

Size: A3	Date: 2026-11-05	**Rev: 1.3**
KiCad E.D.A. 10.0.8		Id: 4/5


Motor, buzzer, SOS button, status LED

Motor rung + còi từ: MOSFET phía thấp, diode dập, cổng kéo xuống (GPIO45/46 là chân strapping). Nút SOS, LED trạng thái.


Motor rung (GPIO46)




Còi từ (GPIO45, PWM ~2.7 kHz)



Nút SOS (GPIO8, đánh thức deep-sleep)



LED trạng thái (GPIO18)



Generated by tools/gen_sch.py from tools/design.py — edit the design file, not this sheet

harisama1 — đồ án đồng hồ sức khỏe

Sheet: /Motor, buzzer, SOS button, status LED/
File: health_watch_main_ui.kicad_sch

Title: Health watch — main board — Motor, buzzer, SOS button, status LED

Size: A4	Date: 2026-11-05	**Rev: 1.3**
KiCad E.D.A. 10.0.8		Id: 5/5