

Fourier Series

Harry Xi

January 28, 2022

Defining the Fourier Series on $[-\pi, \pi]$

Given some function $f(x)$ defined from $-\pi$ to π , we can represent it as the infinite sum of sines and cosines:

$$f(x) = \frac{A_0}{2} + \sum_{k=1}^{\infty} (A_k \cos(kx) + B_k \sin(kx))$$

where

$$A_k = \frac{1}{\pi} \int_{-\pi}^{\pi} f(x) \cos(kx) dx$$

$$B_k = \frac{1}{\pi} \int_{-\pi}^{\pi} f(x) \sin(kx) dx$$

Recalling the inner product of functions will give some much needed context to these equations.

$$\langle f(x), g(x) \rangle = \int_a^b f(x) \overline{g(x)} dx$$

But for real-valued functions, the conjugate operator does nothing.

$$\langle f(x), g(x) \rangle = \int_a^b f(x) g(x) dx$$

We see that our coefficients A_k and B_k can be reinterpreted.

$$A_k = \frac{1}{\|\cos(kx)\|^2} \langle f(x), \cos(kx) \rangle$$

$$B_k = \frac{1}{\|\sin(kx)\|^2} \langle f(x), \sin(kx) \rangle$$

The component of $f(x)$ in the direction of $\cos(kx)$ and $\sin(kx)$ respectively. Now let's check one more inner product, remembering that k is an integer.

$$\langle \sin(kx), \cos(kx) \rangle = \int_{-\pi}^{\pi} \sin(kx) \cos(kx) dx = 0$$

So they are orthogonal to each other. Which gives us some intuition as to how $f(x)$ is formed by an infinite sum of sines and cosines with increasing frequency. We can also check that other sines and cosines of different frequencies will be orthogonal to each other, so that all of these sines and cosines form a basis of the function space.

We can also approximate $f(x)$ with

$$f(x) \approx \frac{A_0}{2} + \sum_{k=1}^N (A_k \cos(kx) + B_k \sin(kx)), \quad N \in \mathbb{N}$$

Defining the Fourier Series on $[0, L]$

These infinite sums actually give periodic functions, so for each move in the x direction equal to the length of the interval we gave, the function will repeat. We now extend our definitions to a period of $[0, L]$.

$$f(x) = \frac{A_0}{2} + \sum_{k=1}^{\infty} \left(A_k \cos\left(\frac{2\pi kx}{L}\right) + B_k \sin\left(\frac{2\pi kx}{L}\right) \right)$$

$$A_k = \frac{2}{L} \int_0^L f(x) \cos\left(\frac{2\pi kx}{L}\right) dx$$

$$B_k = \frac{2}{L} \int_0^L f(x) \sin\left(\frac{2\pi kx}{L}\right) dx$$

Complex Fourier Series

Since now, we have taken $f(x)$ as a real-valued function. But what if we wanted to take $f(x)$ as a complex-valued function? We apply a slightly different, albeit simpler Fourier series. We restrict it for functions $[-\pi, \pi]$ to simplify notation.

$$f(x) = \sum_{k=-\infty}^{\infty} c_k e^{ikx} = \sum_{k=-\infty}^{\infty} (\alpha_k + i\beta_k)(\cos(kx) + i\sin(kx))$$

Noting that $c_k = \overline{c_{-k}}$ if $f(x)$ is real. Now we want to show that these functions of the form e^{ikx} are orthogonal to each other, and will produce a basis for our function space. First define,

$$e^{ikx} = \psi_k$$

Now computing:

$$\begin{aligned} \langle \psi_j, \psi_k \rangle &= \int_{-\pi}^{\pi} e^{ijx} e^{-ikx} dx = \int_{-\pi}^{\pi} e^{i(j-k)x} dx = \frac{1}{i(j-k)} \left[e^{i(j-k)x} \right]_{-\pi}^{\pi} \\ &= \begin{cases} 0, & \text{for } j \neq k \\ 2\pi, & \text{for } j = k \end{cases} \end{aligned}$$

So we see that taking k from $-\infty$ to ∞ will provide us with an infinite basis for the function space in terms of $e^{ikx} = \psi_k$. Now we define the Fourier Series in a more full way, involving both complex functions and a domain of $-L$ to L .

$$f(x) = \sum_{k=-\infty}^{\infty} c_k e^{ik\pi x/L} \quad c_k = \frac{1}{2L} \langle f(x), e^{ik\pi x/L} \rangle = \frac{1}{2L} \int_{-L}^L f(x) e^{-ik\pi x/L} dx$$

The Fourier Transform

While the Fourier series gives a representation of $f(x)$ that's $2L$ periodic, meaning repeating everytime we move $2L$ in any direction, the Fourier transform, keeps the tails of our function the same. So recalling our definition from above, we want to move L to infinity. We first define;

$$\omega_k = \frac{k\pi}{L} = k\Delta\omega, \quad \Delta\omega = \frac{\pi}{L}$$

So as $L \rightarrow \infty$, $\Delta\omega \rightarrow 0$ which we can use to determine $f(x)$ as $L \rightarrow \infty$.

$$\begin{aligned} f(x) &= \lim_{\Delta\omega \rightarrow 0} \sum_{-\infty}^{\infty} \frac{\Delta\omega}{2\pi} \int_{-\pi/\Delta\omega}^{\pi/\Delta\omega} f(\xi) e^{-ik\Delta\omega\xi} d\xi e^{ik\Delta\omega x} \\ &= \lim_{\Delta\omega \rightarrow 0} \sum_{-\infty}^{\infty} \frac{1}{2\pi} \int_{-\pi/\Delta\omega}^{\pi/\Delta\omega} f(\xi) e^{-ik\Delta\omega\xi} d\xi e^{ik\Delta\omega x} \Delta\omega \\ &= \int_{-\infty}^{\infty} \frac{1}{2\pi} \int_{-\infty}^{\infty} f(\xi) e^{-i\omega\xi} d\xi e^{i\omega x} d\omega \end{aligned}$$

From here, our actual Fourier transform pair is...

$$\hat{f}(\omega) = \mathcal{F}(f(x)) = \int_{-\infty}^{\infty} f(x) e^{-i\omega x} dx$$

$$f(x) = \mathcal{F}^{-1}(\hat{f}(\omega)) = \frac{1}{2\pi} \int_{-\infty}^{\infty} \hat{f}(\omega) e^{i\omega x} d\omega$$

In Fourier space, it is easier to compute derivatives so they are useful in solving differential equations! Also, the operator \mathcal{F} is unitary!!