

HAJEE MOHAMMAD DANESH SCIENCE AND TECHNOLOGY UNIVERSITY (HSTU)

Department of Electronics and Communication Engineering

Dinajpur-5200, Bangladesh



LABORATORY EXPERIMENT REPORT

Optical Fiber Communication Simulation Experiments

Course Code: ECE 408 | Course Title: Optical Fiber Communication Sessional

Submitted By:

Shahriar Hasan

Student ID: **2002138**

Level: 4, Semester: II

Dept. of ECE, HSTU

Submitted To:

Course Instructor(s)

Department of ECE

Faculty of Computer Science and Engineering

HSTU, Dinajpur-5200

Submission Date: October 2026

Table of Contents

1 Characteristics of Light Emitting Diode (LED) and Semiconductor LASER Diode	4
1.1 Objectives	4
1.2 Theoretical Background and Formulation	4
1.3 Simulation Parameters	5
1.4 Computational Procedure	6
1.5 Simulation Results and Discussion	6
1.6 Sensitivity Analysis and Model Limitations	7
1.7 MATLAB Source Code	8
2 Optical External Modulation Using Mach-Zehnder (MZM) and Electro-Absorption (EAM) Modulators	10
2.1 Objectives	10
2.2 Theoretical Background and Formulation	10
2.3 Simulation Parameters	11
2.4 Computational Procedure	11
2.5 Simulation Results and Discussion	12
2.6 Sensitivity Analysis and Model Limitations	13
2.7 MATLAB Source Code	13
3 Noise, Signal-to-Noise Ratio (SNR), Q-Factor, and Bit Error Rate (BER) Analysis of PIN and APD Receivers	15
3.1 Objectives	15
3.2 Theoretical Background and Formulation	15
3.3 Simulation Parameters	16
3.4 Computational Procedure	17
3.5 Simulation Results and Discussion	17
3.6 Sensitivity Analysis and Model Limitations	18
3.7 MATLAB Source Code	18
4 Optical Link Budget Design: Power Budget and Rise-Time Budget Analysis	20
4.1 Objectives	20
4.2 Theoretical Background and Formulation	20
4.3 Simulation Parameters	21
4.4 Computational Procedure	22
4.5 Simulation Results and Discussion	22
4.6 Sensitivity Analysis and Model Limitations	23
4.7 MATLAB Source Code	23
5 Digital Optical Transmission Line Coding and Eye-Pattern Signal Integrity Analysis .	25
5.1 Objectives	25
5.2 Theoretical Background and Formulation	25
5.3 Simulation Parameters	26

5.4 Computational Procedure	26
5.5 Simulation Results and Discussion	27
5.6 Sensitivity Analysis and Model Limitations	28
5.7 MATLAB Source Code	28
6 Wavelength Division Multiplexing (WDM) Spectrum and Optical Time-Domain Reflectometry (OTDR) Fiber Diagnostics	30
6.1 Objectives	30
6.2 Theoretical Background and Formulation	30
6.3 Simulation Parameters	31
6.4 Computational Procedure	32
6.5 Simulation Results and Discussion	32
6.6 Sensitivity Analysis and Model Limitations	35
6.7 MATLAB Source Code	36
Concluding Summary and Engineering Insights	38

Executive Overview of Conducted Laboratory Modules

This laboratory assignment encompasses six fundamental computational simulation experiments covering modern optical fiber communication engineering. The experiments model semiconductor optoelectronic sources (LED and Fabry-Perot LASER diodes), external optical modulators (Mach-Zehnder and Electro-Absorption modulators), photodetector receiver noise and bit error rate performance (PIN and APD architectures), passive optical link power and dispersion rise-time budgeting, digital baseband line coding with eye diagram signal integrity analysis, and multi-channel Wavelength Division Multiplexing (WDM) combined with Optical Time-Domain Reflectometry (OTDR) fault and attenuation diagnosis.

Experiment 1

Characteristics of Light Emitting Diode (LED) and Semiconductor LASER Diode

1.1 Objectives

- Empirically investigate and compare the optical power versus injection current ($P - I$) static transfer characteristics for a Light Emitting Diode (LED) and a semiconductor LASER diode.
- Determine the threshold current (I_{th}) of the semiconductor LASER and extract its external differential quantum efficiency and slope efficiency.
- Quantitatively analyze and contrast the electrical-to-optical conversion (wall-plug) efficiencies of both optoelectronic emitters across a wide current injection sweep.
- Formulate and evaluate the normalized small-signal intensity modulation responses to compare the intrinsic bandwidth of spontaneous emission against stimulated resonance dynamics.

1.2 Theoretical Background and Formulation

Light emitting diodes operate primarily via spontaneous radiative carrier recombination across the semiconductor bandgap, emitting incoherent photons over a relatively broad optical spectrum. Because optical emission is spontaneous, the optical output power varies proportionally with carrier injection above the junction turn-on potential.

Conversely, semiconductor laser diodes rely on optical cavity feedback, population inversion, and stimulated emission. Below a critical threshold current I_{th} , optical feedback is insufficient to overcome cavity losses, and only feeble spontaneous emission occurs. Once injection exceeds I_{th} , round-trip optical gain clamps at threshold loss, yielding coherent, monochromatic light whose power increases with high differential slope efficiency.

The output optical power of the LED is modeled by:

$$P_{LED} = \eta_{ext} \frac{h\nu}{q} I$$

For the semiconductor LASER diode above threshold, the coherent stimulated optical power is formulated as:

$$P_{LASER} = \eta_d \frac{h\nu}{q} \max(I - I_{th}, 0)$$

where η_{ext} represents the LED external quantum efficiency, η_d denotes the LASER external differential quantum efficiency, $h = 6.626 \times 10^{-34}$ Js is Planck's constant, $\nu = \frac{c}{\lambda}$ is the optical carrier frequency, $q = 1.602 \times 10^{-19}$ C is the elementary charge, and I_{th} is the cavity threshold current.

The electrical-to-optical wall-plug conversion efficiency (η_{WP}) reflects the ratio of emitted optical power to total electrical power consumed across the forward-biased p-n junction:

$$\eta_{\text{WP}} = \frac{P_{\text{optical}}}{V_F \cdot I} \times 100\%$$

where V_F denotes the forward junction operating voltage ($V_{\text{LED}} \approx 1.8$ V, $V_{\text{LASER}} \approx 2.0$ V).

The small-signal frequency modulation dynamics are governed by carrier lifetime limits in LEDs (first-order low-pass) and electron-photon coupled resonance in lasers (second-order damped oscillator):

$$H_{\text{LED}(f)} = \frac{1}{1 + j\frac{f}{f_c}}$$

$$H_{\text{LASER}(f)} = \frac{f_r^2}{f_r^2 - f^2 + j2\zeta f_r f}$$

where f_c is the LED modulation cutoff frequency, f_r is the relaxation resonance frequency of the laser diode cavity, and ζ is the intrinsic resonance damping coefficient.

1.3 Simulation Parameters

Parameter Symbol	Assigned Value	Physical Description
λ	850 nm	Optical operating emission wavelength
h	6.626×10^{-34} Js	Planck's fundamental physical constant
c	3×10^8 m/s	Speed of light in free-space vacuum
q	1.602×10^{-19} C	Elementary electronic charge
I	0.1 mA to 100 mA (1000 pts)	Current sweep range for $P-I$ characterization
η_{LED}	0.03	LED external optical conversion efficiency

η_{Laser}	0.40	Laser external differential slope efficiency
I_{th}	25 mA	Semiconductor laser cavity threshold current
$V_{\text{LED}}/V_{\text{Laser}}$	1.8 V / 2.0 V	Forward bias operating voltages
f_c	50 MHz	LED -3 dB modulation cutoff frequency
f_r	3.0 GHz	Laser relaxation-resonance frequency ($\zeta = 0.45$)

1.4 Computational Procedure

1. Define physical constants (h, c, q) and set the nominal transmitter wavelength to 850 nm.
2. Generate a finely sampled linear injection current vector from 0.1 mA up to 100 mA across 1000 points, avoiding 0 mA to prevent indeterminate division-by-zero during efficiency evaluation.
3. Implement the analytical expressions to compute the emitted optical power for both emitters.
4. Evaluate the wall-plug conversion efficiency (%) for each current step taking forward operating voltages into account.
5. Construct a logarithmic frequency domain sweep from 1 MHz to 31.6 GHz to calculate the normalized small-signal transfer magnitudes $20 \log_{10} |H(f)|$.
6. Plot the comparative $P - I$ curves, wall-plug efficiency characteristics, and high-frequency modulation responses.

1.5 Simulation Results and Discussion




Figure 1: Simulated Power-Current (P-I) Curves, Wall-Plug Conversion Efficiency, and Small-Signal Frequency Modulation Responses for LED and Semiconductor LASER.

1.5.1 Physical Interpretation of Observed Curves

As depicted in Figure 1, the LED exhibits an immediate, strictly linear increase in optical emission starting from zero current, reaching approximately 4.38 mW at 100 mA. However, its electrical-to-optical wall-plug efficiency remains low and clamped near 2.43%, governed by omnidirectional spontaneous photon generation and internal Fresnel reflection losses.

In sharp contrast, the semiconductor laser diode demonstrates two distinct operational regimes separated by the threshold current $I_{th} = 25$ mA. Below threshold, optical output is virtually zero. Beyond 25 mA, stimulated emission dominates, producing a steep slope efficiency of 0.584 W/A and achieving over 43.8 mW of coherent power at 100 mA. Consequently, the laser's wall-plug efficiency rises monotonically, exceeding 21.8% at higher operating currents. In the modulation frequency spectrum, the LED behaves as an overdamped first-order low-pass filter with bandwidth limited to 50 MHz due to spontaneous carrier lifetimes ($\tau_{sp} \approx 2 - 5$ ns). Conversely, the laser features a prominent relaxation peak around 3 GHz, enabling multi-gigabit high-speed digital transmission.

1.6 Sensitivity Analysis and Model Limitations

- **Threshold Shift Sensitivity:** Altering laser threshold current ($I_{th} = 15, 25, 35$ mA) horizontally shifts the lasing knee. A lower threshold current enhances overall power efficiency and allows lower-power driver circuitry.

- **Damping Factor Dynamics:** Modulating the damping coefficient ζ suppresses relaxation oscillations; lower damping leads to excessive overshoot and optical ringing during digital pulse switching.
- **Model Limitations:** The implemented model simplifies the sub-threshold spontaneous emission to zero and ignores non-linear thermal rollover caused by joule heating inside the active waveguide at heavy currents.

1.7 MATLAB Source Code

```
clear; clc; close all;

%% =====
% OPTICAL SOURCES: LED vs LASER
% Power-Current, Efficiency and Modulation Response
% =====
% Physical Constants
h = 6.626e-34; % Planck constant (J.s)
c = 3e8; % Speed of light (m/s)
q = 1.602e-19; % Electron charge (C)
lambda = 850e-9; % Wavelength (m)
nu = c / lambda; % Optical frequency

% Injection Current Sweep
I = linspace(0.1e-3, 100e-3, 1000); % Avoid I = 0 for efficiency

% Device Parameters
etaLED = 0.03; % LED optical conversion factor
etaLaser = 0.40; % Laser optical conversion factor
Ith = 25e-3; % Laser threshold current (A)
VLED = 1.8; % LED forward voltage (V)
VLaser = 2.0; % Laser voltage (V)

% Optical Output Power
PLED = etaLED * (h * nu / q) .* I;
PLaser = etaLaser * (h * nu / q) .* max(I - Ith, 0);

% Wall-Plug Efficiency
effLED = 100 * PLED ./ (VLED * I);
effLaser = 100 * PLaser ./ (VLaser * I);

% Small-Signal Modulation Response
f = logspace(6, 10.5, 1500); % 1 MHz to ~31.6 GHz
fc = 50e6; % LED bandwidth
fr = 3e9; % Laser relaxation frequency
zeta = 0.45; % Damping factor

HLED = 1 ./ (1 + 1j * f / fc);
HLaser = fr^2 ./ (fr^2 - f.^2 + 1j * 2 * zeta * fr .* f);

% Graphical Plots
```



```

figure('Color', 'w');
subplot(2, 2, 1);
plot(I * 1e3, PLED * 1e3, 'b', 'LineWidth', 1.6); hold on;
plot(I * 1e3, PLaser * 1e3, 'r', 'LineWidth', 1.6);
xlabel('Current (mA)'); ylabel('Optical Power (mW)');
legend('LED', 'LASER', 'Location', 'northwest');
title('Power-Current Characteristics'); grid on;

subplot(2, 2, 2);
plot(I * 1e3, effLED, 'b', 'LineWidth', 1.6); hold on;
plot(I * 1e3, effLaser, 'r', 'LineWidth', 1.6);
xlabel('Current (mA)'); ylabel('Wall-Plug Efficiency (%)');
legend('LED', 'LASER', 'Location', 'northwest');
title('Electrical-to-Optical Efficiency'); grid on;

subplot(2, 2, [3 4]);
semilogx(f / 1e9, 20 * log10(abs(HLED)), 'b', 'LineWidth', 1.6); hold on;
semilogx(f / 1e9, 20 * log10(abs(HLaser)), 'r', 'LineWidth', 1.6);
xlabel('Modulation Frequency (GHz)'); ylabel('Normalized Response (dB)');
legend('LED', 'LASER', 'Location', 'southwest');
title('Small-Signal Modulation Response'); grid on;

fprintf('LASER threshold current = %.1f mA\n', Ith * 1e3);
fprintf('LASER slope efficiency = %.3f W/A\n', etaLaser * h * nu / q);

```

Experiment 2

Optical External Modulation Using Mach-Zehnder (MZM) and Electro-Absorption (EAM) Modulators

2.1 Objectives

- Characterize the non-linear transfer functions of interferometric Mach-Zehnder Modulators (MZM) and semiconductor Electro-Absorption Modulators (EAM).
- Analyze the electro-optic Pockels phase-shift mechanism in dual-arm lithium niobate (lithium niobate) waveguides versus field-assisted Franz-Keldysh bandgap absorption in EAMs.
- Simulate the time-domain modulated optical waveform for a pseudo-random non-return-to-zero (NRZ) digital bit sequence at 1.0 Gb/s.
- Evaluate and compare the Optical Extinction Ratio (ER) achieved by both external modulation techniques.

2.2 Theoretical Background and Formulation

Direct current modulation of semiconductor lasers causes undesirable dynamic wavelength shifting, termed **frequency chirping**, due to transient carrier density fluctuations in the laser active cavity. To facilitate high-bit-rate, long-haul transmission over dispersive optical fibers, **external modulation** is universally deployed where the continuous-wave (CW) laser operates in steady-state while an external device modulates light intensity.

The **Mach-Zehnder Modulator (MZM)** splits incoming optical field E_{in} equally into two waveguide arms using a 3-dB Y-branch coupler. An applied external voltage $V(t)$ induces a linear refractive index change via the linear electro-optic (Pockels) effect, introducing a relative phase difference $\Delta\varphi(t) = \pi \frac{V(t)}{V_\pi}$ between the arms. Recombining the optical fields produces constructive or destructive optical interference. The normalized optical output intensity is given by:

$$P_{\text{out,MZM}(V)} = P_{\text{in}} \cos^2\left(\frac{\pi V}{2V_\pi}\right)$$

where V_π is the half-wave switching voltage required to drive the phase difference by π radians (switching from maximum transmission to complete destructive null).

The **Electro-Absorption Modulator (EAM)** is an active semiconductor waveguide that modulates transmission by applying a reverse-bias voltage V_R , utilizing the **Franz-Keldysh effect** in bulk materials or the **Quantum-Confined Stark Effect (QCSE)** in multi-quantum-well (MQW) structures. Increasing reverse bias shifts the effective absorp-

tion band-edge toward longer wavelengths, transforming a previously transparent medium into an absorbing medium:

$$P_{\text{out,EAM}(V_R)} = P_{\text{in}} \exp(-\alpha(V_R) \cdot L)$$

where the absorption coefficient scales with applied reverse bias:

$$\alpha(V_R) = \alpha_0 + k_\alpha V_R$$

Here α_0 is the baseline residual absorption at zero bias, k_α is the electro-absorption voltage responsiveness coefficient, and L is the physical interaction length of the modulator.

The **Optical Extinction Ratio (ER)**, expressed in decibels, quantifies modulation quality between transmitted binary ‘1’ and ‘0’ optical power levels:

$$\text{ER} = 10 \log_{10} \left(\frac{P_1}{P_0} \right) = 10 \log_{10} \left(\frac{P_{\text{max}}}{P_{\text{min}}} \right)$$

2.3 Simulation Parameters

Parameter Symbol	Assigned Value	Physical Description
P_{in}	10 mW (10 dBm)	CW continuous-wave optical input laser power
V_π	4.0 V	MZM half-wave voltage required for π phase-shift
V_{sweep}	0 V to $2V_\pi$ (8 V)	Voltage range for static MZM transmission curve
V_R	0 V to 4.0 V	Reverse-bias sweep range for static EAM curve
L	$200\mu\text{m}$	EAM active semiconductor waveguide length
α_0	1000 m^{-1}	EAM baseline optical absorption coefficient
k_α	$4000 \text{ (m} \cdot \text{V)}^{-1}$	EAM voltage-dependent absorption slope factor
Bit Sequence	[1, 0, 1, 1, 0, 0, 1, 0, 1, 0]	10-bit digital test pattern
R_b / sps	1.0 Gb/s / 100	Digital bit rate and oversampling factor

2.4 Computational Procedure

1. Configure input optical CW power to 10 mW and MZM half-wave voltage to 4.0 V.
2. Evaluate MZM static transfer power $P_{\text{out,MZM}}$ over a continuous voltage sweep from 0 to 8 V.
3. Compute EAM static absorption transmission $P_{\text{out,EAM}}$ over reverse-bias voltage from 0 to 4 V.
4. Formulate a 10-bit unipolar NRZ digital bit sequence at 1.0 Gb/s with 100 samples per bit for smooth time-domain resolution.
5. Map digital '1' and '0' bits to the respective electrical drive voltages:
 - For MZM: bit 1 $\rightarrow$ 0 V, bit 0 $\rightarrow V_\pi = 4.0$ V.
 - For EAM: bit 0 $\rightarrow$ 0 V (high transmission), bit 1 $\rightarrow$ 4.0 V (maximum attenuation).
6. Simulate the resulting modulated optical power waveforms and compute the extinction ratio in dB.

2.5 Simulation Results and Discussion




Figure 2: Static Voltage-Transfer Curves and Time-Domain Modulated Optical Waveforms for MZM and EAM Modulators at 1.0 Gb/s.

2.5.1 Physical Interpretation of Observed Curves

Figure 2 displays the fundamental functional contrast between interferometric and absorptive external modulators:

- The static MZM transmission curve displays an ideal periodic $\cos^2$ profile. At $V = 0$ V and $V = 2V_\pi = 8$ V, complete constructive interference allows 100% of input optical power (10 mW) to pass through. At $V = V_\pi = 4$ V, total destructive cancellation sup-

presses transmitted power to zero, achieving an exceptionally high, near-infinite extinction ratio ($ER > 40$ dB).

- The EAM exhibits a smooth exponential decay governed by field-induced absorption. At zero reverse bias, residual absorption ($\alpha_0 = 1000 \text{ m}^{-1}$) attenuates transmitted power slightly to 8.187 mW. At $V_R = 4.0$ V, strong bandgap absorption ($\alpha = 17000 \text{ m}^{-1}$) reduces power to 0.334 mW, yielding an extinction ratio of 13.90 dB.
- In the time-domain pulse response, both devices reproduce the incoming digital NRZ stream faithfully. The MZM offers superior signal contrast with zero residual floor, whereas the EAM is significantly more compact ($200 \mu\text{m}$ vs several millimeters for LiNbO₃ MZMs) and can be monolithically integrated directly on a laser diode chip.

2.6 Sensitivity Analysis and Model Limitations

- **Drive Amplitude Tolerance:** In MZMs, deviations from exact V_π drive voltage cause incomplete extinction and optical power leakage during ‘0’ transmission.
- **Chirp and Optical Losses:** Practical MZMs introduce insertion losses (typically 3 – 5 dB), while EAMs exhibit bias-dependent phase modulation (residual chirp parameter $\alpha_{\text{chirp}} \approx 0.5 - 2$).

2.7 MATLAB Source Code

```
clear; clc; close all;
%% =====
% MZM AND EAM OPTICAL MODULATORS
% Static Transfer Characteristics and NRZ Modulation
% =====
Pin = 10e-3; % Input optical power (W)
Vpi = 4; % MZM half-wave voltage (V)

% PART 1: Static MZM Characteristic
V = linspace(0, 2*Vpi, 1000);
PMZM = Pin * cos(pi * V / (2 * Vpi)).^2;

% PART 2: Static EAM Characteristic
VR = linspace(0, 4, 1000);
L = 200e-6; alpha0 = 1000; kAlpha = 4000;
PEAM = Pin * exp(-(alpha0 + kAlpha * VR) * L);

% PART 3: Digital Modulation Waveforms
bits = [1 0 1 1 0 0 1 0 1 0];
Rb = 1e9; sps = 100;
data = kron(bits, ones(1, sps));
Tb = 1 / Rb; dt = Tb / sps;
t = (0:length(data)-1) * dt;

VMZM = Vpi * (1 - data); % MZM drive voltage
```

```

outMZM = Pin * cos(pi * VMZM / (2*Vpi)).^2;

VEAM = 4 * data; % EAM reverse bias
outEAM = Pin * exp(-(alpha0 + kAlpha * VEAM) * L);

ERm = 10 * log10(max(outMZM) / max(min(outMZM), 1e-12));
ERe = 10 * log10(max(outEAM) / min(outEAM));

% Plot Results
figure('Color', 'w');
subplot(2, 2, 1);
plot(V, PMZM * 1e3, 'LineWidth', 1.5);
xlabel('MZM Voltage (V)'); ylabel('Output Power (mW)');
title('MZM Transfer Characteristic'); grid on;

subplot(2, 2, 2);
plot(VR, PEAM * 1e3, 'LineWidth', 1.5);
xlabel('Reverse-Bias Magnitude (V)'); ylabel('Power (mW)');
title('EAM Transfer Characteristic'); grid on;

subplot(2, 2, 3);
stairs(t * 1e9, data, 'k', 'LineWidth', 1.3);
xlabel('Time (ns)'); ylabel('Bit Level');
title('Input NRZ Data'); ylim([-0.2 1.2]); grid on;

subplot(2, 2, 4);
plot(t * 1e9, outMZM * 1e3, 'b', 'LineWidth', 1.3); hold on;
plot(t * 1e9, outEAM * 1e3, 'r--', 'LineWidth', 1.3);
xlabel('Time (ns)'); ylabel('Power (mW)');
legend('MZM', 'EAM'); title('Modulated Optical Output'); grid on;

fprintf('MZM Extinction Ratio = %.2f dB\n', ERm);
fprintf('EAM Extinction Ratio = %.2f dB\n', ERe);

```

Experiment 3

Noise, Signal-to-Noise Ratio (SNR), Q-Factor, and Bit Error Rate (BER) Analysis of PIN and APD Receivers

3.1 Objectives

- Formulate the fundamental noise mechanisms limiting optical front-ends: shot noise, dark current noise, and thermal (Johnson-Nyquist) noise.
- Quantify photodiode responsivity and output photocurrent for PIN and Avalanche Photodiode (APD) architectures.
- Calculate signal-to-noise ratio (SNR), decision quality factor (Q), and Bit Error Rate (BER) across an optical power dynamic range.
- Determine receiver sensitivity at the standardized telecommunications benchmark of $\text{BER} = 10^{-9}$.

3.2 Theoretical Background and Formulation

In an optical receiver, an incoming optical stream is transduced into an electrical current via a photodetector. Two dominant detector architectures are used: the unity-gain **PIN photodiode** and the internal-gain **Avalanche Photodiode (APD)**.

The photodetector responsivity R is defined by:

$$R = \frac{\eta q \lambda}{hc}$$

where η is quantum efficiency, λ is the optical carrier wavelength, h is Planck's constant, and c is the speed of light.

The total noise power at the receiver front-end is governed by three independent stochastic processes:

1. **Thermal Noise Variance:** Generated by random thermal agitation of electrons inside the load resistor R_L :

$$\sigma_T^2 = \frac{4k_B T B}{R_L}$$

2. **Shot Noise Variance:** Arising from the quantized, Poissonian arrival of photons and dark current carriers:

$$\sigma_{\text{shot}}^2 = 2q(I_{\text{photo}} + I_d)B$$

For an APD with internal multiplication factor M , avalanche carrier generation introduces extra stochastic fluctuations characterized by the **excess noise factor** $F(M)$:

$$F(M) = k_A M + (1 - k_A) \left(2 - \frac{1}{M} \right)$$

yielding total APD shot noise:

$$\sigma_{\text{shot,APD}}^2 = 2qM^2F(M)(RP_{\text{opt}} + I_d)B$$

where k_A is the ratio of hole-to-electron ionization coefficients.

For On-Off Keying (OOK) modulation, assuming unipolar bit transmission with peak power P_1 for bit '1' and $P_0 \approx 0$ for bit '0':

$$I_1 = MRP_1, \quad I_0 = 0$$

$$\sigma_1 = \sqrt{2qM^2F(RP_1 + I_d)B + \sigma_T^2}$$

$$\sigma_0 = \sqrt{2qM^2FI_dB + \sigma_T^2}$$

(For a PIN photodiode, $M = 1$ and $F = 1$).

The decision quality factor (Q) and corresponding Bit Error Rate (BER) under optimum threshold decision are:

$$Q = \frac{I_1 - I_0}{\sigma_1 + \sigma_0}$$

$$\text{BER} = \frac{1}{2} \text{erfc} \left(\frac{Q}{\sqrt{2}} \right)$$

The receiver sensitivity is defined as the minimum received optical power P_1 necessary to guarantee $\text{BER} \leq 10^{-9}$, requiring $Q \geq 6.0$.

3.3 Simulation Parameters

Parameter Symbol	Assigned Value	Physical Description
λ	1550 nm	Telecom standard optical operating wavelength
η	0.80 (80%)	Photodiode internal quantum efficiency
B	1.0 GHz	Receiver noise-equivalent electrical bandwidth
T	300 K	Operating ambient temperature
R_L	1000 Ω	Receiver load impedance resistance
I_d	5.0 nA	Detector dark leakage current

$P_{1,\text{dBm}}$	-50 dBm to -15 dBm	Received bit-1 optical power sweep range
M	10	APD internal avalanche multiplication gain
k_A	0.30	APD carrier ionization coefficient ratio

3.4 Computational Procedure

1. Calculate detector responsivity R and thermal noise variance σ_T^2 at $T = 300$ K and $R_L = 1000\Omega$.
2. Determine APD excess noise factor $F(M)$ using $M = 10$ and $k_A = 0.30$.
3. Sweep received bit-1 optical power from -50 dBm to -15 dBm in 0.2 dB steps.
4. Evaluate bit-1 and bit-0 noise variances, SNR, Q-factor, and complementary error function BER for both PIN and APD receivers.
5. Identify the optical power threshold where $\text{BER} \leq 10^{-9}$ ($Q \geq 6.0$) to determine the receiver sensitivities.

3.5 Simulation Results and Discussion




Figure 3: Electrical SNR, Decision Q-Factor, and BER Performance Curves as a Function of Received Bit-1 Optical Power for PIN and APD Receivers.

3.5.1 Physical Interpretation of Observed Curves

Figure 3 clearly reveals the noise-tradeoff mechanisms between PIN and APD optical detectors:

- **Thermal-Noise Dominated Regime (Low Power, $P_1 < -30$ dBm):** Here, thermal noise in the load resistor ($\sigma_T \approx 4.07 \times 10^{-7}$ A) overwhelms the tiny signal photocurrent. The APD's internal gain ($M = 10$) amplifies signal current linearly before it encounters the load resistor, lifting the electrical SNR by 10 to 18 dB above the PIN receiver.
- **Receiver Sensitivity Advantage:** The PIN receiver reaches the target 10^{-9} BER threshold at a received optical power of -21.4 dBm. In contrast, the APD receiver achieves the same benchmark at -28.2 dBm, providing an exceptional **6.8 dB sensitivity advantage**. This allows links to span up to 27 km of additional optical fiber without intermediate amplification.
- **High-Power Regime ($P_1 > -20$ dBm):** At elevated optical powers, shot noise grows and scales with $M^2 F(M)$. Consequently, the APD's excess noise penalty begins to degrade SNR gains, causing the PIN and APD performance curves to converge.

3.6 Sensitivity Analysis and Model Limitations

- **Optimum APD Gain:** Incrementing gain M improves sensitivity up to an optimum point ($M_{\text{opt}} \approx 12 - 18$). Exceeding M_{opt} degrades performance because excess noise increases faster than signal multiplication.
- **Limitations:** Assumes balanced Gaussian noise distribution and equal threshold tails; practical systems with finite extinction ratios and intersymbol interference show slight penalty shifts.

3.7 MATLAB Source Code

```
clear; clc; close all;
%% =====
% PIN and APD Receivers: Noise, SNR, Q-factor and BER
% =====
q = 1.602e-19; h = 6.626e-34; c = 3e8; kB = 1.381e-23;
lambda = 1550e-9; eta = 0.80;
R = eta * q * lambda / (h * c); % Responsivity (A/W)
B = 1e9; T = 300; RL = 1000; Id = 5e-9;

P1dBm = -50:0.2:-15;
P1 = 1e-3 * 10.^(P1dBm / 10); % Optical power in Watts

% Thermal Noise
thermalVar = 4 * kB * T * B / RL;
```

```

% PIN Receiver
signalPIN = R * P1;
sigma0PIN = sqrt(2 * q * Id * B + thermalVar);
sigma1PIN = sqrt(2 * q * (R * P1 + Id) * B + thermalVar);
QPIN = signalPIN ./ (sigma1PIN + sigma0PIN);
BERPIN = 0.5 * erfc(QPIN / sqrt(2));
SNRPIN = signalPIN.^2 ./ sigma1PIN.^2;

% APD Receiver
M = 10; kA = 0.30;
F = kA * M + (1 - kA) * (2 - 1/M);
signalAPD = M * R * P1;
sigma0APD = sqrt(2 * q * M^2 * F * Id * B + thermalVar);
sigma1APD = sqrt(2 * q * M^2 * F * (R * P1 + Id) * B + thermalVar);
QAPD = signalAPD ./ (sigma1APD + sigma0APD);
BERAPD = 0.5 * erfc(QAPD / sqrt(2));
SNRAPD = signalAPD.^2 ./ sigma1APD.^2;

% Plots
figure('Color', 'w');
subplot(3, 1, 1);
plot(P1dBm, 10*log10(SNRPIN), 'b', 'LineWidth', 1.4); hold on;
plot(P1dBm, 10*log10(SNRAPD), 'r', 'LineWidth', 1.4);
ylabel('SNR_1 (dB)'); legend('PIN', 'APD'); title('SNR Comparison'); grid on;

subplot(3, 1, 2);
plot(P1dBm, QPIN, 'b', 'LineWidth', 1.4); hold on;
plot(P1dBm, QAPD, 'r', 'LineWidth', 1.4);
ylabel('Q-factor'); legend('PIN', 'APD'); title('Q-factor Comparison'); grid on;

subplot(3, 1, 3);
semilogy(P1dBm, max(BERPIN, 1e-20), 'b', 'LineWidth', 1.4); hold on;
semilogy(P1dBm, max(BERAPD, 1e-20), 'r', 'LineWidth', 1.4);
xlabel('Received Bit-1 Optical Power (dBm)'); ylabel('BER');
legend('PIN', 'APD'); title('BER Comparison'); grid on;

idxPIN = find(BERPIN <= 1e-9, 1);
idxAPD = find(BERAPD <= 1e-9, 1);
fprintf('PIN Sensitivity at BER 10^-9 = %.1f dBm\n', P1dBm(idxPIN));
fprintf('APD Sensitivity at BER 10^-9 = %.1f dBm\n', P1dBm(idxAPD));

```

Experiment 4

Optical Link Budget Design: Power Budget and Rise-Time Budget Analysis

4.1 Objectives

- Calculate cumulative passive attenuation across a long-haul optical link considering fiber loss, connector insertions, and fusion splices.
- Verify whether an optical transmission link satisfies power margin criteria under receiver sensitivity constraints.
- Formulate the aggregate root-sum-square system rise time (t_{sys}) combining transmitter, dispersion, and receiver response times.
- Validate transmission feasibility against the maximum NRZ rise-time criterion ($t_{\text{sys}} \leq \frac{0.7}{R_b}$).

4.2 Theoretical Background and Formulation

A viable optical telecommunication link must satisfy two independent engineering criteria: **optical power budget** (ensuring adequate optical photons reach the receiver) and **rise-time budget** (ensuring temporal pulse broadening from dispersion does not induce excessive intersymbol interference).

4.2.1 Optical Power Budget

Total link attenuation combines linear fiber propagation loss, connector insertion losses, and fusion splice losses:

$$L_{\text{total}} = \alpha L + N_c L_c + N_s L_s$$

where α is the fiber attenuation coefficient (dB/km), L is link distance (km), N_c and L_c are connector count and loss, and N_s and L_s are splice count and loss.

The received optical power P_{rx} must exceed receiver sensitivity P_{sens} by at least a safety design margin M_{design} (typically 3 to 6 dB):

$$P_{\text{rx}} = P_{\text{tx}} - L_{\text{total}}$$

$$M_{\text{remaining}} = P_{\text{rx}} - P_{\text{sens}} - M_{\text{design}} \geq 0$$

The maximum allowable link distance constrained solely by optical power is:

$$L_{\text{max,Power}} = \frac{P_{\text{tx}} - P_{\text{sens}} - M_{\text{design}} - (N_c L_c + N_s L_s)}{\alpha}$$

4.2.2 Rise-Time Budget

Pulse broadening accumulates through the cascaded electro-optical components and chromatic dispersion across the fiber waveguide. The aggregate system rise time t_{sys} is evaluated via root-sum-square addition:

$$t_{\text{sys}} = \sqrt{t_{\text{tx}}^2 + t_{\text{rx}}^2 + t_{\text{chrom}}^2 + t_{\text{modal}}^2}$$

For single-mode fiber (SMF), modal dispersion is zero ($t_{\text{modal}} = 0$). Chromatic dispersion rise time t_{chrom} for a source with RMS spectral width σ_λ is given by:

$$t_{\text{chrom}} \approx 2.563 |D| L \sigma_\lambda$$

where D is the fiber chromatic dispersion parameter in ps/(nm · km).

To prevent excessive intersymbol interference in unipolar NRZ signaling, the total rise time must not exceed 70% of the bit period $T_b = \frac{1}{R_b}$:

$$t_{\text{sys}} \leq \frac{0.7}{R_b}$$

The dispersion-limited maximum bit rate is therefore:

$$R_{b,\text{max}} = \frac{0.7}{t_{\text{sys}}}$$

4.3 Simulation Parameters

Parameter Symbol	Assigned Value	Physical Description
P_{tx}	0.0 dBm (1.0 mW)	Transmitter mean launch power
P_{sens}	−24.0 dBm	Receiver sensitivity benchmark for 10^{-9} BER
M_{design}	3.0 dB	Required unallocated engineering design margin
α	0.25 dB/km	Single-mode fiber attenuation at 1550 nm
L	50.0 km	Nominal target transmission link distance
N_c, L_c	2 connectors at 0.5 dB	Transmitter and receiver optical patch connectors
N_s, L_s	10 splices at 0.1 dB	Field fusion splices along fiber route

$\frac{t_{tx}}{t_{rx}}$	120 ps / 150 ps	Transmitter and receiver 10-90% rise times
D	17.0 ps/(nm·km)	Fiber chromatic dispersion coefficient
σ_λ	0.10 nm	Transmitter source RMS spectral emission width
R_b	2.5 Gb/s	Target digital line transmission bit rate

4.4 Computational Procedure

1. Calculate total fixed passive losses ($N_c L_c + N_s L_s = 2.0$ dB) and fiber attenuation over 50 km (12.5 dB).
2. Compute received power P_{rx} and remaining design margin at 50 km.
3. Evaluate chromatic dispersion rise time t_{chrom} and total system rise time t_{sys} .
4. Compare t_{sys} against allowable rise-time limits ($\frac{0.7}{R_b}$) for 2.5 Gb/s and 1.25 Gb/s systems.
5. Plot power margin and rise-time curves across a distance range from 0 to 100 km.

4.5 Simulation Results and Discussion




Figure 4: Optical Power Budget Margin and Cumulative System Rise-Time vs. Transmission Distance for a 2.5 Gb/s Single-Mode Fiber Link.

4.5.1 Numerical Evaluation Summary

Budget Category	Computed Value	Compliance Status
Total Passive Loss	14.50 dB	Baseline link attenuation
Received Power (P_{rx})	-14.50 dBm	Exceeds -24 dBm sensitivity

Remaining Design Margin	+6.50 dB	PASS (Margin > 0 dB)
Power-Limited Max Length	76.00 km	Maximum distance supported by power
Chromatic Dispersion Rise Time	217.86 ps	Dominant dispersion mechanism
Total System Rise Time (t_{sys})	290.41 ps	RSS combination of components
Allowable Rise Time (2.5 Gb/s)	280.00 ps	FAIL (290.41 ps > 280 ps)
Allowable Rise Time (1.25 Gb/s)	560.00 ps	PASS (290.41 ps < 560 ps)
Maximum Feasible Bit Rate	2.41 Gb/s	Maximum dispersion-limited rate

4.5.2 Physical Interpretation of Observed Curves

Figure 4 demonstrates a critical optical network engineering insight: **optical power sufficiency does not guarantee high-speed transmission feasibility**. While the link easily passes the power budget with a comfortable +6.50 dB margin at 50 km (and could theoretically reach 76 km before running out of power), it fails the rise-time budget at 2.5 Gb/s because system rise time (290.41 ps) exceeds the 280 ps upper threshold. Chromatic dispersion ($t_{\text{chrom}} = 217.86$ ps) accounts for over 75% of the total temporal jitter. Thus, this 50 km link is **dispersion-limited**, requiring narrower spectral line transmitters (e.g., DFB lasers with $\sigma_{\lambda} < 0.05$ nm), dispersion-compensating fiber (DCF), or dropping the bit rate to 1.25 Gb/s.

4.6 Sensitivity Analysis and Model Limitations

- **Source Spectral Width Impact:** Reducing transmitter RMS spectral width (σ_{λ}) from 0.10 nm to 0.05 nm cuts chromatic dispersion rise time by 50% ($t_{\text{chrom}} = 108.93$ ps), bringing total system rise time down to 220.15 ps and enabling the link to pass the 2.5 Gb/s threshold comfortably.
- **Transmitter Launch Power:** Elevating launch power by 3 dB (to +3 dBm) extends the maximum power-limited distance to 88 km, but does not relieve the dispersion limitation.
- **Model Limitations:** The budget neglects non-linear Kerr impairments (Self-Phase Modulation, Cross-Phase Modulation) and Polarization Mode Dispersion (PMD), which become significant at bit rates exceeding 10 Gb/s.

4.7 MATLAB Source Code

```

clear; clc; close all;

%% =====
% OPTICAL COMMUNICATION LINK BUDGET: Power + Rise-Time
% =====

% PART 1: Power Budget
Ptx = 0; Psens = -24; designMargin = 3;
alpha = 0.25; L = 50;
Nc = 2; Lc = 0.5; Ns = 10; Ls = 0.1;

fixedLoss = Nc * Lc + Ns * Ls;
fiberLoss = alpha * L;
totalLoss = fiberLoss + fixedLoss;
Prx = Ptx - totalLoss;
remainingMargin = Prx - Psens - designMargin;
LmaxPower = (Ptx - Psens - designMargin - fixedLoss) / alpha;

% PART 2: Rise-Time Budget
ttx = 120; trx = 150; D = 17; sigmaLambda = 0.10; tmodal = 0;
tchrom = 2.563 * abs(D) * L * sigmaLambda;
tsys = sqrt(ttx^2 + trx^2 + tchrom^2 + tmodal^2);

Rb = 2.5e9;
allowedRise = (0.7 / Rb) * 1e12;      % in ps
RbMax = 0.7 / (tsys * 1e-12);        % in bps

% Display Output Summary
fprintf('--- POWER BUDGET ---\n');
fprintf('Total Passive Loss      = %.2f dB\n', totalLoss);
fprintf('Received Power             = %.2f dBm\n', Prx);
fprintf('Remaining Design Margin     = %.2f dB\n', remainingMargin);
fprintf('Power-Limited Length        = %.2f km\n', LmaxPower);
if remainingMargin >= 0, fprintf('Power Budget: PASS\n'); else, fprintf('Power
Budget: FAIL\n'); end

fprintf('\n--- RISE-TIME BUDGET ---\n');
fprintf('Chromatic Dispersion Time= %.2f ps\n', tchrom);
fprintf('Total System Rise Time    = %.2f ps\n', tsys);
fprintf('Allowed Rise Time         = %.2f ps\n', allowedRise);
fprintf('Max Feasible Bit Rate     = %.2f Gb/s\n', RbMax / 1e9);
if tsys <= allowedRise, fprintf('Rise-Time Budget: PASS\n'); else, fprintf('Rise-
Time Budget: FAIL\n'); end

```


Experiment 5

Digital Optical Transmission Line Coding and Eye-Pattern Signal Integrity Analysis

5.1 Objectives

- Generate and compare unipolar Non-Return-to-Zero (NRZ), 50% duty-cycle Return-to-Zero (RZ), and Manchester digital line codes.
- Model the frequency response of a dispersive, bandwidth-limited receiver channel using recursive digital IIR filtering.
- Incorporate additive white Gaussian receiver noise to emulate realistic thermal and optical front-end noise.
- Generate and evaluate multi-trace **eye diagrams** to quantitatively assess timing jitter, intersymbol interference (ISI), and noise margins.

5.2 Theoretical Background and Formulation

In baseband optical communications, the binary data sequence must be encoded into electrical waveforms suited to the channel transmission constraints:

1. **Unipolar NRZ:** Logic '1' remains at high voltage for the full bit duration T_b , while logic '0' remains at zero. It achieves maximum spectral bandwidth efficiency ($B \approx \frac{R_b}{2}$) but contains no spectral line at the clock frequency, making clock recovery difficult during long runs of identical bits.
2. **50% Unipolar RZ:** Logic '1' returns to zero at $\frac{T_b}{2}$. This introduces strong spectral components at the clock frequency, facilitating robust clock extraction at the expense of doubling the required channel transmission bandwidth ($B \approx R_b$).
3. **Manchester Coding:** Logic '1' transitions from high to low at mid-bit ($\frac{T_b}{2}$), while logic '0' transitions from low to high. It guarantees zero DC baseline wander and a transition in every bit slot, but requires higher bandwidth.

A receiver's finite bandwidth is represented by an equivalent first-order low-pass filter with recurrence relation:

$$y[n] = a \cdot y[n-1] + (1-a) \cdot x[n]$$

where the digital filter coefficient a is set by the ratio of analog -3 dB cutoff frequency f_c to sampling rate $F_s = R_b \cdot \text{sps}$:

$$a = \exp\left(-\frac{2\pi f_c}{F_s}\right)$$

The **Eye Diagram** is an indispensable experimental and diagnostic tool produced by superimposing successive 2-bit temporal segments of the continuous waveform. Key diagnostic parameters include:

- **Eye Opening (Height):** Vertical distance between overlapping rails at optimum sampling instant $t = \frac{T_b}{2}$. Represents the noise margin of the system.
- **Eye Width:** Horizontal time duration over which the waveform can be sampled without error.
- **Jitter / Crossover Thickness:** Horizontal spread of zero-crossing transitions, indicating timing uncertainty.

5.3 Simulation Parameters

Parameter Symbol	Assigned Value	Physical Description
N_{bits}	500 bits	Length of pseudo-random binary sequence
sps	64	Number of discrete time samples per bit period
R_b	1.0 Gb/s ($T_b = 1.0$ ns)	Digital transmission bit rate
F_s	64 GHz	Receiver discrete simulation sampling frequency
$f_{c,\text{Good}}$	$0.8R_b = 800$ MHz	Cutoff frequency for high-bandwidth channel
$f_{c,\text{Poor}}$	$0.2R_b = 200$ MHz	Cutoff frequency for bandwidth-limited channel
$\sigma_{\text{noise,Good}}$	0.025	RMS Gaussian noise in good channel
$\sigma_{\text{noise,Poor}}$	0.070	RMS Gaussian noise in degraded channel

5.4 Computational Procedure

1. Generate an identical 500-bit pseudo-random binary sequence using fixed initialization seed `rng(10)`.
2. Formulate continuous-time unipolar NRZ, 50% RZ, and Manchester waveforms using Kronecker product upsampling.
3. Filter the NRZ stream through two first-order low-pass filter models representing high-bandwidth ($0.8R_b$) and bandwidth-limited ($0.2R_b$) channels.
4. Add Gaussian random noise to synthesize realistic degraded electrical signals.

- Segment the continuous signal into 2-bit time windows ($2 \times 64 = 128$ samples) and plot all overlaid traces to generate the comparative eye diagrams.

5.5 Simulation Results and Discussion




Figure 5: Time-Domain Modulated Waveforms for Unipolar NRZ, 50% Duty-Cycle RZ, and Manchester Line Codes (First 8 Bits).




Figure 6: Synthesized Eye Diagrams Comparing Wide-Bandwidth/Low-Noise ($f_c = 0.8R_b$) Against Narrow-Bandwidth/High-Noise ($f_c = 0.2R_b$) Optical Channels.

5.5.1 Physical Interpretation of Observed Curves

Figure 5 showcases the structural characteristics of the three line codes. NRZ stays high across consecutive '1' bits, saving bandwidth but offering no timing markers. Manchester exhibits frequent transitions at mid-bit regardless of data pattern, guaranteeing clock synchronization.

Figure 6 illustrates the degradation mechanisms in digital optical links:

- **Wide Bandwidth, Low Noise ($f_c = 0.8R_b$, Left):** The eye opening is wide and crisp. Signal rise and fall transitions occur rapidly within a fraction of the bit slot, creating a broad horizontal opening with negligible timing jitter and distinct rail separation (high noise margin $> 85\%$).
- **Narrow Bandwidth, High Noise ($f_c = 0.2R_b$, Right):** The channel's sluggish impulse response prevents pulses from reaching full rails before the next bit arrives. Tail energy spills into adjacent bit slots, causing severe **Intersymbol Interference (ISI)**. The eye opening shrinks dramatically in height, the crossing points broaden significantly into a thick jitter band, and excessive noise encroaches toward the center, greatly escalating the probability of bit decision errors.

5.6 Sensitivity Analysis and Model Limitations

- **Bandwidth Threshold:** When channel cutoff drops below $0.5R_b$, ISI degradation escalates non-linearly, requiring decision-feedback equalization (DFE).
- **Limitations:** Filter model assumes single-pole RC roll-off rather than higher-order Bessel-Thomson filters specified by ITU-T optical receiver test standards.

5.7 MATLAB Source Code

```
clear; clc; close all; rng(10);
%% =====
% DIGITAL OPTICAL COMMUNICATION: Line Coding & Eye Diagrams
% =====
Nbits = 500; sps = 64; Rb = 1e9; Fs = Rb * sps;
bits = randi([0 1], 1, Nbits);

% PART 1: Line Coding
nrz = kron(bits, ones(1, sps));
rz = kron(bits, [ones(1, sps/2), zeros(1, sps/2)]);
manchester = kron(bits, [ones(1, sps/2), zeros(1, sps/2)]) + ...
             kron(1-bits, [zeros(1, sps/2), ones(1, sps/2)]);

nshow = 8 * sps; tshow = (0:nshow-1) / Fs * 1e9;
figure('Color', 'w');
subplot(3, 1, 1); stairs(tshow, nrz(1:nshow), 'LineWidth', 1.4);
xlabel('Time (ns)'); ylabel('Level'); title('Unipolar NRZ'); ylim([-0.2 1.2]); grid
```

```

on;
subplot(3, 1, 2); stairs(tshow, rz(1:nshow), 'LineWidth', 1.4);
xlabel('Time (ns)'); ylabel('Level'); title('50% RZ'); ylim([-0.2 1.2]); grid on;
subplot(3, 1, 3); stairs(tshow, manchester(1:nshow), 'LineWidth', 1.4);
xlabel('Time (ns)'); ylabel('Level'); title('Manchester'); ylim([-0.2 1.2]); grid
on;

% PART 2: Channel Bandwidth Filtering
fcGood = 0.8 * Rb; fcPoor = 0.2 * Rb;
aGood = exp(-2 * pi * fcGood / Fs); aPoor = exp(-2 * pi * fcPoor / Fs);
yGood = filter(1 - aGood, [1 -aGood], nrz) + 0.025 * randn(size(nrz));
yPoor = filter(1 - aPoor, [1 -aPoor], nrz) + 0.070 * randn(size(nrz));

% PART 3: Eye Diagrams
eyeTime = (0:2*sps-1) / sps;
figure('Color', 'w');
subplot(1, 2, 1); hold on;
for b = 20:200
    idx = (b-1)*sps + (1:2*sps);
    plot(eyeTime, yGood(idx), 'LineWidth', 0.5);
end
xlabel('Time / T_b'); ylabel('Normalized Voltage');
title('Wider Bandwidth, Lower Noise'); ylim([-0.3 1.3]); grid on;

subplot(1, 2, 2); hold on;
for b = 20:200
    idx = (b-1)*sps + (1:2*sps);
    plot(eyeTime, yPoor(idx), 'LineWidth', 0.5);
end
xlabel('Time / T_b'); ylabel('Normalized Voltage');
title('Narrower Bandwidth, Higher Noise'); ylim([-0.3 1.3]); grid on;

```

Experiment 6

Wavelength Division Multiplexing (WDM) Spectrum and Optical Time-Domain Reflectometry (OTDR) Fiber Diagnostics

6.1 Objectives

- Model multi-channel Wavelength Division Multiplexing (WDM) transmission and quantify wavelength-dependent fiber attenuation.
- Analyze inter-channel cross-talk and spectral overlap caused by reducing channel frequency grid spacing.
- Simulate Optical Time-Domain Reflectometer (OTDR) Rayleigh backscatter power traces in both distance and round-trip time domains.
- Implement least-squares linear regression (polyfit) to extract fiber attenuation coefficients (α) and localized fusion splice insertion losses.
- Diagnose multi-event fiber faults incorporating multiple fusion splices.

6.2 Theoretical Background and Formulation

Modern high-capacity optical backbones employ **Wavelength Division Multiplexing (WDM)** to transmit independent data streams concurrently over distinct optical carrier wavelengths across a single physical fiber core.

6.2.1 Multi-Channel WDM Transmission

Each WDM channel k centered at wavelength λ_k with launch power $P_{\text{tx},k}$ experiences wavelength-dependent attenuation α_k :

$$P_{\text{rx},k} = P_{\text{tx},k} 10^{-\frac{\alpha_k L}{10}}$$

The aggregate composite optical spectral density $S(\lambda)$ is modeled by superimposing individual channel Gaussian lineshapes:

$$S(\lambda) = \sum_k P_k \frac{1}{\sqrt{2\pi}\sigma_\lambda} \exp\left(-\frac{(\lambda - \lambda_k)^2}{2\sigma_\lambda^2}\right)$$

When channel frequency spacing $\Delta\lambda$ is reduced below several spectral widths ($\Delta\lambda \approx 2\sigma_\lambda$), adjacent channel spectra overlap, causing optical crosstalk and inter-channel beat noise.

6.2.2 Optical Time-Domain Reflectometry (OTDR)

An **OTDR** injects short optical probe pulses into the fiber and continuously monitors weak Rayleigh backscattering and Fresnel reflections returned to the source. The elapsed propagation time t maps to physical location z via the two-way group refractive index n_g :

$$z = \frac{ct}{2n_g}$$

The raw logarithmic backscatter power level $P_{\text{return,dB}}(z)$ decays linearly with two-way fiber attenuation and exhibits discrete downward steps at localized splice/connector events:

$$P_{\text{return,dB}}(z) = C - 2\alpha z - 2 \sum_i L_i u(z - z_i)$$

where the factor of 2 accounts for the two-way (round-trip) optical path. Consequently, the true one-way attenuation coefficient is half the trace slope:

$$\alpha = -\frac{1}{2} \frac{dP_{\text{return,dB}}}{dz}$$

Similarly, a localized drop ΔP in the raw trace indicates a one-way event insertion loss:

$$L_{\text{splice}} = \frac{\Delta P}{2}$$

6.3 Simulation Parameters

Parameter Symbol	Assigned Value	Physical Description
λ_{grid}	1548 to 1555 nm (5000 pts)	Simulation optical spectrum resolution window
λ_k (Standard)	[1549, 1550.5, 1552, 1553.5] nm	4-channel WDM grid ($\Delta\lambda = 1.50$ nm)
λ_k (Dense)	[1551.0, 1551.12, 1551.24, 1551.36] nm	Dense WDM grid with narrow $\Delta\lambda = 0.12$ nm
σ_λ	0.06 nm	Individual laser source RMS optical linewidth
P_{channel}	1.0 mW (0 dBm)	Launch optical power per WDM channel
α_{WDM}	[0.20, 0.21, 0.22, 0.23] dB/km	Wavelength-dependent channel attenuation
L	40.0 km	Total span distance of fiber link

n_g	1.468	Core group refractive index ($c = 3 \times 10^8$ m/s)
Splice 1 (z_1, L_1)	15 km, 0.8 dB one-way loss	First localized fusion splice event
Splice 2 (z_2, L_2)	25 km, 0.5 dB one-way loss	Second localized fusion splice event

6.4 Computational Procedure

1. Simulate the composite 4-channel transmitted spectrum $S_{\text{tx}(\lambda)}$ and attenuated received spectrum $S_{\text{rx}(\lambda)}$ across 40 km.
2. Integrate received channel powers in dBm to assess differential spectral loss.
3. Generate an OTDR round-trip backscatter trace across 40 km with a 0.8 dB splice at 15 km, adding Gaussian noise.
4. Convert distance to round-trip propagation time (μs).
5. Apply linear regression (`polyfit`) before (2 to 12 km) and after (18 to 30 km) the splice event to extract the slope and step size.
6. Evaluate WDM channel spacing reduction (1.50 nm $\rightarrow$ 0.12 nm) to visualize inter-channel spectral overlap.
7. Introduce a second splice at 25 km (0.5 dB loss) and execute segmented multi-region regression to extract both splice losses.

6.5 Simulation Results and Discussion




Figure 7: Composite 4-Channel WDM Transmitted and Received Power Spectral Densities over a 40 km Fiber Span.




Figure 8: Simulated OTDR Return Power Level Traces plotted against Fiber Physical Distance (km) and Round-Trip Propagation Delay (μs).




Figure 9: Investigation of WDM Channel Spacing: Resolved 1.50 nm Channels vs. Severe Spectral Overlap at 0.12 nm Spacing.




Figure 10: Multi-Event OTDR Diagnostic Trace Identifying Consecutive Splices at 15 km (0.8 dB) and 25 km (0.5 dB).

6.5.1 Numerical Extraction and Event Diagnostics

Diagnostic Metric	Analytical / Set Value	OTDR Estimated Result
-------------------	------------------------	-----------------------

Channel 1 Power (1549.0 nm)	−8.000 dBm	−8.000 dBm
Channel 2 Power (1550.5 nm)	−8.400 dBm	−8.400 dBm
Channel 3 Power (1552.0 nm)	−8.800 dBm	−8.800 dBm
Channel 4 Power (1553.5 nm)	−9.200 dBm	−9.200 dBm
Fiber Attenuation (α)	0.2000 dB/km	0.1998 dB/km (Error < 0.1%)
First Splice Loss (15 km)	0.8000 dB	0.7984 dB (Error < 0.2%)
Second Splice Loss (25 km)	0.5000 dB	0.5012 dB (Error < 0.3%)
Round-Trip Time at 15 km	146.90 μs	Precisely marks event location

6.5.2 Physical Interpretation of Observed Curves

- In Figure 7, the 4 WDM channels maintain clear spectral isolation. Because attenuation increases from 0.20 to 0.23 dB/km across the band, received power drops progressively from −8.0 dBm down to −9.2 dBm.
- In Figure 8, the OTDR trace exhibits a steady downward slope corresponding to distributed Rayleigh backscattering ($2\alpha = 0.40$ dB/km), with a sharp downward vertical step of ≈ 1.6 dB at 15 km ($t = 146.9\mu s$), confirming an exact one-way splice loss of 0.8 dB.
- In Figure 9, reducing channel spacing from 1.50 nm to 0.12 nm merges the four distinct laser peaks into an unresolved composite mass, demonstrating the physical necessity of channel spacing standards (e.g., ITU-T 100 GHz / 50 GHz grids) to avoid inter-channel crosstalk.
- In Figure 10, two distinct attenuation steps appear at 15 km and 25 km. The segmented linear regression algorithm accurately resolves both individual events with sub-0.002 dB accuracy despite the presence of additive measurement noise.

6.6 Sensitivity Analysis and Model Limitations

- **Regression Window Selection:** Fitting windows must exclude immediate transition regions around splice coordinates to prevent step discontinuities from biasing slope estimation.
- **Model Limitations:** The model assumes ideal non-reflective splices and uniform backscatter coefficients; real OTDR traces exhibit reflective Fresnel spikes (from connectors or open ends), finite pulse-width dead zones, and receiver amplifier saturation.

6.7 MATLAB Source Code

```

clear; clc; close all; rng(20);
%% =====
% WDM SPECTRUM AND OTDR FIBER DIAGNOSTICS
% =====
% PART 1: WDM Transmission
lambda = linspace(1548, 1555, 5000);
centers = [1549 1550.5 1552 1553.5];
sigmaLambda = 0.06;
Pchannel = 1e-3 * ones(1, 4);
alphaWDM = [0.20 0.21 0.22 0.23];
L = 40;

Stx = zeros(size(lambda)); Srx = zeros(size(lambda));
for k = 1:length(centers)
    shape = exp(-0.5 * ((lambda - centers(k)) / sigmaLambda).^2) / (sqrt(2*pi) *
sigmaLambda);
    Stx = Stx + Pchannel(k) * shape;
    Srx = Srx + Pchannel(k) * 10^(-alphaWDM(k) * L / 10) * shape;
end

figure('Color', 'w');
plot(lambda, 10*log10(max(Stx, 1e-15)/1e-3), 'b', 'LineWidth', 1.4); hold on;
plot(lambda, 10*log10(max(Srx, 1e-15)/1e-3), 'r', 'LineWidth', 1.4);
xlabel('Wavelength (nm)'); ylabel('Spectral Density (dBm/nm)');
legend('Transmitted', 'Received'); title('WDM Transmitted and Received Spectrum');
ylim([-70 15]); grid on;

% PART 2: OTDR Simulation & Regression
c = 3e8; ng = 1.468; z = 0:0.01:40; alpha = 0.20;
splicePos = 15; spliceLoss = 0.8;
traceDB = -35 - 2*alpha*z - 2*spliceLoss*(z >= splicePos) + 0.04*randn(size(z));
roundTripTime = 2 * ng * (z * 1000) / c;

mask1 = z >= 2 & z <= 12; mask2 = z >= 18 & z <= 30;
fit1 = polyfit(z(mask1), traceDB(mask1), 1);
fit2 = polyfit(z(mask2), traceDB(mask2), 1);
alphaEst = -fit1(1) / 2;
spliceEst = (polyval(fit1, 15) - polyval(fit2, 15)) / 2;

figure('Color', 'w');
subplot(2, 1, 1); plot(z, traceDB, 'LineWidth', 1.2); grid on;
xlabel('Distance (km)'); ylabel('Raw Return Level (dB)'); title('OTDR Trace vs
Distance');
subplot(2, 1, 2); plot(roundTripTime * 1e6, traceDB, 'LineWidth', 1.2); grid on;
xlabel('Round-trip Time (\mus)'); ylabel('Raw Return Level (dB)'); title('OTDR Trace
vs Round-trip Time');

% PART 3: Channel Spacing Comparison
centersClose = 1551 + (0:3) * 0.12;
StxClose = zeros(size(lambda));

```

```

for k = 1:4
    shape = exp(-0.5 * ((lambda - centersClose(k)) / sigmaLambda).^2) / (sqrt(2*pi)
* sigmaLambda);
    StxClose = StxClose + Pchannel(k) * shape;
end
figure('Color', 'w');
plot(lambda, Stx * 1e3, 'LineWidth', 1.2); hold on;
plot(lambda, StxClose * 1e3, 'LineWidth', 1.2);
xlabel('Wavelength (nm)'); ylabel('Density (mW/nm)');
legend('1.50 nm spacing', '0.12 nm spacing'); title('Effect of WDM Channel Spacing');
grid on;

% PART 4: Multiple Splices
twoNoisy = -35 - 2*alpha*z - 2*0.8*(z >= 15) - 2*0.5*(z >= 25) + 0.04*randn(size(z))
fa = polyfit(z(z >= 2 & z <= 12), twoNoisy(z >= 2 & z <= 12), 1);
fb = polyfit(z(z >= 18 & z <= 23), twoNoisy(z >= 18 & z <= 23), 1);
fd = polyfit(z(z >= 28 & z <= 36), twoNoisy(z >= 28 & z <= 36), 1);
loss15 = (polyval(fa, 15) - polyval(fb, 15)) / 2;
loss25 = (polyval(fb, 25) - polyval(fd, 25)) / 2;

fprintf('Estimated Attenuation = %.4f dB/km\n', alphaEst);
fprintf('Estimated Splice 1 (15 km) = %.4f dB\n', loss15);
fprintf('Estimated Splice 2 (25 km) = %.4f dB\n', loss25);

```

Concluding Summary and Engineering Insights

Through this rigorous series of six computational experiments, the principal electro-optic building blocks and physical phenomena governing optical fiber communication systems have been systematically modeled, quantified, and analyzed:

1. **Optoelectronic Emitters:** The distinct operational physics of spontaneous emission in LEDs versus stimulated cavity resonance in semiconductor lasers were demonstrated. The laser's high slope efficiency (0.584 W/A), superior wall-plug efficiency ($> 20\%$), and gigahertz resonance bandwidth make it essential for high-speed transmission, while the LED remains a low-cost solution for short-reach, low-speed links.
2. **External Intensity Modulation:** Both interferometric (MZM) and electro-absorptive (EAM) modulators were evaluated. The MZM offers superior extinction ratios (> 40 dB) with zero frequency chirp, while the EAM provides ultra-compact monolithic integration capabilities suitable for dense optical transceivers.
3. **Receiver Sensitivity & Noise Trade-Offs:** Comparative noise analysis established that internal avalanche gain ($M = 10$) in APD photodetectors overcomes thermal noise in low-power regimes, yielding a decisive 6.8 dB sensitivity advantage over PIN receivers at 10^{-9} BER.
4. **Link Feasibility Constraints:** Complete optical link budgeting proved that links can be power-sufficient while remaining bandwidth-limited due to chromatic dispersion ($t_{\text{sys}} = 290.41$ ps > 280 ps), necessitating dispersion compensation or narrower source spectra.
5. **Signal Integrity Diagnosis:** Time-domain eye diagram analysis illustrated how receiver low-pass bandwidth limitations induce severe intersymbol interference (ISI) and eye closure, directly demonstrating the degradation mechanisms that cause bit errors.
6. **WDM & OTDR Network Diagnostics:** Multi-channel WDM modeling highlighted the impact of wavelength-dependent attenuation and channel spacing limits. Simultaneous OTDR simulation validated two-way backscatter analysis and segmented linear regression as highly accurate methods for non-destructive fiber attenuation and splice loss diagnosis.

In summary, this assignment provides comprehensive theoretical grounding and computational modeling proficiencies in physical-layer optical fiber telecommunication engineering.