

	1	2	3	4	5	6
	IR BLASTER V1 — GPIO25 low-side switched 12-channel IR emitter					
	ELECTRICAL NETLIST (PCB is authoritative)					
A	+5V -> R1 100R -> D1 anode; D1 cathode -> LED_DRAIN					A
	+5V -> R2 100R -> D2 anode; D2 cathode -> LED_DRAIN					
	+5V -> R3 100R -> D3 anode; D3 cathode -> LED_DRAIN					
	+5V -> R4 100R -> D4 anode; D4 cathode -> LED_DRAIN					
	+5V -> R5 100R -> D5 anode; D5 cathode -> LED_DRAIN					
	+5V -> R6 100R -> D6 anode; D6 cathode -> LED_DRAIN					
B	+5V -> R7 100R -> D7 anode; D7 cathode -> LED_DRAIN					B
	+5V -> R8 100R -> D8 anode; D8 cathode -> LED_DRAIN					
	+5V -> R9 100R -> D9 anode; D9 cathode -> LED_DRAIN					
	+5V -> R10 100R -> D10 anode; D10 cathode -> LED_DRAIN					
	+5V -> R11 100R -> D11 anode; D11 cathode -> LED_DRAIN					
	+5V -> R12 100R -> D12 anode; D12 cathode -> LED_DRAIN					
	LED_DRAIN -> Q1 pin 2 DRAIN; Q1 pin 1 SOURCE -> GND					
C	GPIO25 / IR_TX -> RG 220R -> Q1 pin 3 GATE					C
	RPD 10k: GATE -> GND					
	Cbulk 1000uF + Cdec 100nF: +5V -> GND					
	D1,D4,D7,D10 = OSISLA7WA1B wide 100°; remaining LEDs = OSISLA5A33A-B narrow 30°					
	Confirmed mapping: both LED types pin 1=A, pin 2=K; Q1 pin 1=S, pin 2=D, pin 3=G					
D						D
	Sheet: / File: ir_blaster_v1.kicad_sch					
	Title:					
	Size: A4		Date:		Rev:	
	KiCad E.D.A. 9.0.6				Id: 1/1	
	1	2	3	4	5	6