数字证书柜 JS 交互接口文档

目录

一、 接口通用说明 2
二、 接口详情 2
1、 批量下发用户 2
2、 查询用户 4
3、 绑定/解绑用户 4
4、 初始化证书柜 5
5、 查询证书柜信息 6
6、 查询证书柜状态 7
7、 初始化系统配置 7
8、 显示系统配置 9
9、 修改证书柜管理员密码 9
10、 管理员登录 10
11、 上报标签状态 10
12、 上报门锁状态 11
13、 根据用户身份证号码更新用户信息 11
14、 人脸采集功能 12
15、 人脸识别功能 12
16、 人脸预览控制功能 13
17、 停止预览请求示例 13
18、 批量插入操作日志 13

一、接口通用说明

本文档定义数字证书柜 Web 页面与底层能力的交互接口，统一遵循「构建请求 JSON 对象 + 调用 invokeAndroid 方法发起请求 + 异步回调函数接收返回结果」的调用规范，所有接口的动作标识通过 action 字段指定。

二、接口详情

1、批量下发用户

接口说明
批量将人员信息同步至证书柜系统，完成人员基础信息的批量新增操作。
请求示例

```
var doInsertUserPo = function () {
  var action = "doInsertUserPo";
  var userJsonArrayStr = [{
        userName: "zhangsan",
        idNoUnique: "123",
        plsNoUnique: "A123",
        deptId: "9001",
        deptName: "行政"
  }, {
        userName: "lisi",
        idNoUnique: "456",
        plsNoUnique: "A456",
        deptId: "9001",
        deptName: "行政"
  }, {
        userName: "wangwu",
        idNoUnique: "789",
        plsNoUnique: "A789",
        deptId: "9001",
        deptName: "行政"
  }];
  var json = {
        "action": action,
        "userJsonArrayStr": userJsonArrayStr
  };
  invokeAndroid(json);
};
```

回调方法 doInsertUserPoCallback 返回数据示例

```
{
"code": 0,
```

```
    "msg": "新增用户成功",
    "failCnt": 0,
    "successCnt": 3,
    "userPoListJsonStr":
"[{\"cabinetCode\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"deptId\":\"9001\",
\"deptName\":\"                    行                    政
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"123\",\"plsNoUnique\":\"A123\",\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotP
ositions\":\"\",\"thirdFingerFeature\":\"\",\"userName\":\"zhangsan\"},{\"cabinetCode\":\"
cabinetCode\",\"cabinetName\":\"cabinetName\",\"deptId\":\"9001\",\"deptName\":\"  行
政
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"456\",\"plsNoUnique\":\"A456\",\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotP
ositions\":\"\",\"thirdFingerFeature\":\"\",\"userName\":\"lisi\"},{\"cabinetCode\":\"cabinet
Code\",\"cabinetName\":\"cabinetName\",\"deptId\":\"9001\",\"deptName\":\"   行   政
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"789\",\"plsNoUnique\":\"A789\",\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotP
ositions\":\"\",\"thirdFingerFeature\":\"\",\"userName\":\"wangwu\"}]"
    }
```

2、查询用户

接口说明

获取系统内所有已录入的人员全量信息。

请求示例

```
var doQueryUserPoList = function () {
  var action = "doQueryUserPoList";
  var json = {
        "action": action
  };
  invokeAndroid(json);
};
```

回调方法 doQueryUserPoListCallback 返回数据示例


```
{
"code": 0,
"msg": "人员信息查询成功:idNoUnique;//身份证号码;plsNoUnique;//警号",
"userPoListJsonStr":
"[{\"cabinetCode\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"deptId\":\"9001\",
\"deptName\":\" 行 政
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"123\",\"plsNoUnique\":\"A123\",\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotP
ositions\":\"1_1,2_1\",\"thirdFingerFeature\":\"\",\"userName\":\"zhangsan\"},{\"cabinetCo
de\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"deptId\":\"9001\",\"deptName\
":\" 行 政
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"456\",\"plsNoUnique\":\"A456\",\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotP
ositions\":\"1_2\",\"thirdFingerFeature\":\"\",\"userName\":\"lisi\"},{\"cabinetCode\":\"cab
inetCode\",\"cabinetName\":\"cabinetName\",\"deptId\":\"9001\",\"deptName\":\" 行 政
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"789\",\"plsNoUnique\":\"A789\",\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotP
ositions\":\"\",\"thirdFingerFeature\":\"\",\"userName\":\"wangwu\"}]",
"total": 3,
"bindCnt": 2,
"unBindCnt": 1
}
```


3、绑定/解绑用户

接口说明

实现人员与证书柜插槽的绑定关联，传入空 bindNo 即可解除对应插槽的绑定关系。

请求参数说明

slotNoUnique：插槽编号，格式示例 1_1、1_2

bindNo：绑定人员的身份证号，传入空字符串则为解绑操作

请求示例

```
var doUpdateDevicePoBindNoBySlotNoUnique = function () {
   var action = "doUpdateDevicePoBindNoBySlotNoUnique";
```

```
    var deviceJsonArrayStr = [{
        bindNo: "123",
        slotNoUnique: "1_1"
    }, {
        bindNo: "123",
        slotNoUnique: "2_1"
    }, {
        bindNo: "456",
        slotNoUnique: "1_2"
    }, {
        bindNo: "",
        slotNoUnique: "1_3"
    }];
    var json = {
        "action": action,
        "deviceJsonArrayStr": deviceJsonArrayStr
    };
    invokeAndroid(json);
};
```

回调方法 doUpdateDevicePoBindNoBySlotNoUniqueCallback 返回字段补充说明

useStatus：插槽使用状态 0-空闲 1-使用中 2-脱机

status：插槽设备状态 0-正常，1-禁用，2-异常

返回数据示例

```
{
"code": 0,
"msg": "绑定/解绑用户成功",
"devicePoListJsonStr":
"[{\"bindNo\":\"123\",\"remark\":\"\",\"slotNoUnique\":\"1_1\",\"status\":\"0\",\"uid\":\"\
",\"useStatus\":\"0\"},{\"bindNo\":\"456\",\"remark\":\"\",\"slotNoUnique\":\"1_2\",\"stat
us\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique
\":\"1_3\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"123\",\"remark\":
\"\",\"slotNoUnique\":\"2_1\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"}]"
}
```

4、初始化证书柜

接口说明

根据预先配置的行、列参数初始化证书柜所有插槽，仅首次部署时执行一次即可，重复执行会重置所有插槽状态。

请求示例

```
var doInitDevicePo = function () {
  var action = "doInitDevicePo";
  var json = {
```

```
        "action": action
    };
    invokeAndroid(json);
};
```

回调方法 doInitDevicePoCallback 返回数据示例


```
{
"code": 0,
"msg": "初始化证书柜成功",
"devicePoListJsonStr":
"[{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_1\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_2\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_3\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_4\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_5\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_1\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_2\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_3\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_4\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_5\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"}]"
}
```


5、查询证书柜信息

接口说明

获取所有证书柜插槽的全量状态数据。

请求示例

```
var doQueryDevicePoList = function () {
  var action = "doQueryDevicePoList";
  var json = {
        "action": action
  };
  invokeAndroid(json);
};
```

回调方法 doQueryDevicePoListCallback 返回数据示例


```
{
"code": 0,
"msg": "设备信息查询成功:slotNoUnique;//插槽编号 1_1、1_2;bindNo;//绑定人员的编号;useStatus;//使用状态 0-空闲 1-使用中 2:脱机;status;//设备状态 0-正常，1-禁用，2-异常;uid;//标签编号.",
"devicePoListJsonStr":
"[{\"bindNo\":\"123\",\"remark\":\"\",\"slotNoUnique\":\"1_1\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"456\",\"remark\":\"\",\"slotNoUnique\":\"1_2\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_3\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",
```

\"slotNoUnique\":\"1_4\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"1_5\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"123\",\"remark\":\"\",\"slotNoUnique\":\"2_1\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_2\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_3\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_4\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"},{\"bindNo\":\"\",\"remark\":\"\",\"slotNoUnique\":\"2_5\",\"status\":\"0\",\"uid\":\"\",\"useStatus\":\"0\"}]",
"total": 10,
"bindCnt": 3,
"freeCnt": 10,
"busyCnt": 0,
"abnormalityCnt": 0
}

6、查询证书柜状态

接口说明

获取当前证书柜的柜门开关状态。

请求示例

```
var doShowCabinetDoorStatus = function () {
  let action = "doShowCabinetDoorStatus";
  let json = {
        "action": action
  };
  invokeAndroid(json);
};
```

回调方法 doConfigCallback（通过返回的 action 字段区分当前接口回调）

返回数据示例

{
"code": 0,
"msg": "证书柜状态查询成功 0-关闭；1-开启",
"jsonStr": "{\"cabinetDoorStatus\":\"0\"}",
"action": "doShowCabinetDoorStatus"
}

7、初始化系统配置

接口说明

配置证书柜核心系统参数，仅传入的非空字段会执行更新，建议仅在首次部署时修改一次参数。

请求参数说明

字段名	字段说明
cabinetCode	证书柜编号
cabinetName	证书柜名称

mgrLoginName	管理员登录名
mgrPwd	管理员密码
baiduLicenceCode	百度离线人识别授权码
frontOrBackCamera	摄像头选择，front 为启用前置摄像头
lockCabinetPath	锁控设备串口路径，默认/dev/ttyS3
rows	证书柜行数
columns	证书柜列数

请求示例

```
var doInitConfig = function () {
    var action = "doInitConfig";
    var cabinetCode = "cabinetCode";
    var cabinetName = "cabinetName";
    var mgrLoginName = "admin";
    var mgrPwd = "123456";
    var baiduLicenceCode = $("baiduLicenceCode").val();
    var frontOrBackCamera = "front";
    var lockCabinetPath = "/dev/ttyS3";
    var rows = "2";
    var columns = "5";
    var configJsonStr = {
        cabinetCode: cabinetCode,
        cabinetName: cabinetName,
        mgrLoginName: mgrLoginName,
        mgrPwd: mgrPwd,
        baiduLicenceCode: baiduLicenceCode,
        frontOrBackCamera: frontOrBackCamera,
        lockCabinetPath: lockCabinetPath,
        rows: rows,
        columns: columns
    };
    var json = {
        "action": action,
        "configJsonStr": configJsonStr
    };
    invokeAndroid(json);
};
```

回调方法

doConfigCallback

返回数据示例

```
{
   "code": 0,
   "msg": "doInitConfig  初始化配置成功",
```

"jsonStr":
"{\"lockCabinetPath\":\"\\/dev\\/ttyS3\",\"cabinetName\":\"cabinetName\",\"mgrPwd\":\"123456\",\"columns\":\"5\",\"cabinetCode\":\"cabinetCode\",\"mgrLoginName\":\"admin\",\"rows\":\"2\",\"frontOrBackCamera\":\"front\"}",
"action": "doInitConfig"
}

8、显示系统配置

接口说明
查询当前系统所有已保存的全量配置参数。
请求示例

```
var doShowConfig = function () {
  let action = "doShowConfig";
  let json = {
        "action": action
  };
  invokeAndroid(json);
};
```

回调方法 doConfigCallback 返回数据示例

{
"code": 0,
"msg": "配置数据查询成功",
"jsonStr":
"{\"lockCabinetPath\":\"\\/dev\\/ttyS3\",\"cabinetName\":\"cabinetName\",\"cabinetDoorStatus\":\"0\",\"mgrPwd\":\"123456\",\"columns\":\"5\",\"cabinetCode\":\"cabinetCode\",\"baiduLicenceCode\":\"EAQE-FAL8-WXJS-T9NF\",\"mgrLoginName\":\"admin\",\"rows\":\"2\",\"frontOrBackCamera\":\"front\"}",
"action": "doShowConfig"
}

9、修改证书柜管理员密码

接口说明
更新管理员账号的登录密码。
请求示例

```
var doModifyMgrPwdInitConfig = function () {
  var action = "doInitConfig";
  var mgrLoginName = "admin";
  var mgrPwd = "123456";
  var configJsonStr = {
        mgrLoginName: mgrLoginName,
        mgrPwd: mgrPwd
  };
  var json = {
```

```
        "action": action,
        "configJsonStr": configJsonStr
    };
    invokeAndroid(json);
};
```

返回数据示例

{"code":0,"msg":"doInitConfig 初始化配置成功","jsonStr":"{\"mgrPwd\":\"123456\",\"mgrLoginName\":\"admin\"}","action":"doInitConfig"}

10、管理员登录

接口说明

校验管理员账号密码合法性，完成系统管理员身份鉴权。

请求示例

```
var doMgrLogin = function () {
    var action = "doMgrLogin";
    let mgrLoginName = "admin";
    let mgrPwd = "123456";
    var json = {
        "action": action,
        "mgrLoginName": mgrLoginName,
        "mgrPwd": mgrPwd
    };
    invokeAndroid(json);
};
```

回调方法 doMgrLoginCallback 返回状态码说明

0：登录成功

-1：管理员用户名不正确

-2：密码不正确

返回数据示例

{
"code" : 0,
"msg" : "管理员 admin 登录成功",
"action" : "doMgrLogin"
}

11、上报标签状态

接口说明

控制板自动检测到电机锁标签状态变化后主动触发的通知事件，通知前端调用「查询证书柜信息」接口同步更新插槽显示状态。

事件触发参数

layer：插槽所属层数

numb：插槽在当前层的序号

uid：标签 ID

12、上报门锁状态

接口说明

控制板自动监测到门锁开关状态变化后主动触发的通知事件，通知前端调用「查询证书柜状态」接口同步更新门禁显示状态。

事件触发参数

- doorLockState：0x01 表示门开启，0x00 表示门关闭

13、根据用户身份证号码更新用户信息

接口说明

通过身份证号作为唯一标识，更新指定人员的部门信息、人脸信息、指纹信息等用户扩展属性。

请求示例

```
var doUpdateUserPoByIdNo = function () {
var action = "doUpdateUserPoByIdNo";
let idNoUnique = "123";
let deptId = "90003";
let deptName = "财务部";
let faceFeature = "";
let faceBase64_image = "";
let firstFingerFeature = "";
let userName = "wutian";
let userPoJsonStr = {
    idNoUnique: idNoUnique,
    deptId: deptId,
    deptName: deptName,
    faceFeature: faceFeature,
    faceBase64_image: faceBase64_image,
    firstFingerFeature: firstFingerFeature,
    userName: userName
};
var json = {
    "action": action,
    "userPoJsonStr": userPoJsonStr
};
invokeAndroid(json);
};
```

回调方法 doUpdateUserPoByIdNoCallback 返回数据示例

```
{
"code": 0,
"msg":
"{\"cabinetCode\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"deptId\":\"90003\",
\"deptName\":\" 财 务 部
\",\"faceBase64_image\":\"\",\"faceFeature\":\"\",\"firstFingerFeature\":\"\",\"idNoUnique
\":\"123\",\"plsNoUnique\":null,\"remark\":\"\",\"secondeFingerFeature\":\"\",\"slotPositio
ns\":\"\",\"thirdFingerFeature\":\"\",\"userName\":\"wutian\"}数据更新成功"
}
```

14、人脸采集功能

接口说明

为指定身份证号的人员采集人脸数据，存储人脸特征和人脸图片。

请求示例

```
var doFaceCollect = function () {
var action = "doFaceCollect";
let idNoUnique = "456";
var json = {
    "action": action,
    "idNoUnique": idNoUnique
};
invokeAndroid(json);
};
```

回调方法 termFaceCallback（通过返回的 action 字段区分回调类型）返回数据示例

```
{
"action": "doFaceCollect",
"code": "0",
"msg": "456  人脸采集成功",
"termFaceFeature": "",
"termFaceImageBase64Str": ""
}
```

15、人脸识别功能

接口说明

核验指定身份证号人员的人脸身份，返回识别到的人脸特征和人脸图片。

请求示例

```
var doFaceDetect = function () {
var action = "doFaceDetect";
let idNoUnique = "123";
var json = {
    "action": action,
    "idNoUnique": idNoUnique
```

```
};
invokeAndroid(json);
};
```

回调方法 termFaceCallback 返回数据示例


```
{
"action": "doFaceDetect",
"idNoUnique": "123",
"code": "0",
"msg": "123  人脸识别成功",
"termFaceFeature":
"22356391fc2f1b94f8ad3019324d311d8be5e0805ceaf584fa134b09922a150cdd9",
"termFaceImageBase64Str":
"\\/9j\\/4AAQSkZJRgABAQAAAQABAAD\\/4gHYSUNDX1BST0ZJTEUAAQEAAAHIAAAAAAQwA
ABtbnRyUkdCIFhZWiAH4AABAAEAAAAAAABhY3NwAAA"
}
```


16、人脸预览控制功能

接口说明

控制摄像头人脸预览的启动和停止。

启动预览请求示例

```
var startCameraPreview = function () {
var action = "startCameraPreview";
var json = {
    "action": action
};
invokeAndroid(json);
};
```

17、停止预览请求示例

```
var stopCameraPreview = function () {
var action = "stopCameraPreview";
var json = {
    "action": action
};
invokeAndroid(json);
};
```

通用回调方法

termFaceCallback

18、批量插入操作日志

接口说明

支持单条或批量新增证书柜存取操作日志，记录人员存取证书的完整操作轨迹。

请求示例

```
var doInsertOperateLogPo = function () {
var action = "doInsertOperateLogPo";
var operateLogJsonArrayStr = [{
        userName: "zhangsan",
        idNo: "123",
        plsNo: "A123",
        layer: "1",
        numb: "1",
        operateType: "0",
        remark: "备注 01"
}, {
        userName: "lisi",
        idNo: "456",
        plsNo: "A456",
        layer: "1",
        numb: "2",
        operateType: "1",
        remark: "备注 02"
}, {
        userName: "wangwu",
        idNo: "789",
        plsNo: "A789",
        layer: "2",
        numb: "1",
        operateType: "0",
        remark: "备注 03"
}];
var json = {
        "action": action,
        "operateLogJsonArrayStr": operateLogJsonArrayStr
};
invokeAndroid(json);
};
```

回调方法 doInsertOperateLogPoCallback 返回数据示例

```
{
"code" : 0,
"msg" : "日志新增成功",
"failCnt" : 0,
"successCnt" : 3
}
```

查询操作日志

接口说明

获取证书柜所有历史操作日志数据，统计存取操作数量。

请求示例

```
var doQueryOperateLogPoList = function () {
var action = "doQueryOperateLogPoList";
var json = {
    "action": action
};
invokeAndroid(json);
};
```

回调方法 doQueryOperateLogPoListCallback 返回数据示例


```
{
"code" : 0,
"msg" : "日志查询成功  operateType（0-存  1-取）",
"operateLogPoListJsonStr" : "[{\"cabinetCode\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"idNo\":\"123\",\"layer\":\"1\",\"numb\":\"1\",\"operateTime\":\"2026-07-19 16:42:49\",\"operateType\":\"0\",\"plsNo\":\"A123\",\"remark\":\"备注01\",\"slotPosition\":\"1_1\",\"userName\":\"zhangsan\"},{\"cabinetCode\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"idNo\":\"456\",\"layer\":\"1\",\"numb\":\"2\",\"operateTime\":\"2026-07-19 16:42:49\",\"operateType\":\"1\",\"plsNo\":\"A456\",\"remark\":\"备注02\",\"slotPosition\":\"1_2\",\"userName\":\"lisi\"},{\"cabinetCode\":\"cabinetCode\",\"cabinetName\":\"cabinetName\",\"idNo\":\"789\",\"layer\":\"2\",\"numb\":\"1\",\"operateTime\":\"2026-07-19  16:42:49\",\"operateType\":\"0\",\"plsNo\":\"A789\",\"remark\":\"备注03\",\"slotPosition\":\"2_1\",\"userName\":\"wangwu\"}]",
"total" : 3,
"inCnt" : 2,
"outCnt" : 1
}
```