

Cairo University
Faculty of Engineering
Electronics & Communication Department

Assignment 2


Consider the following communication system.



- **The output of the binary source is a series of random 0's and 1's.**
- **The pulse shape $g(t)$ is given below, where '1' is represented by $g(t)$ and '0' by 0**



- **The channel is ideal (i.e. its impulse response is $\delta(t)$).**
- **The noise is an AWGN with zero mean and variance $No/2$.**
- **Consider the three following cases:**
  - **a) The receive filter $h(t)$ is a matched filter with unit energy**
  - **b) The receive filter $h(t)$ is not existent (i.e. $h(t) = \delta(t)$)**
  - **c) The receive filter $h(t)$ has the following impulse response**



Requirements:

1. **Derive the probability of error in the three mentioned cases.**
2. **Write a Matlab code that generates random bits, simulates the above communication system, and calculates the probability of error for the three mentioned cases.**
3. **Plot the output of the receive filter for the three mentioned cases**
4. **On the same figure, plot the theoretical and simulated Bit Error Rate (BER) Vs E/No (where E is the average symbol energy) for the three mentioned cases. Take E/No to be in the range -10 dB: 20:dB. (Use a semilogy plot)**
5. **Is the BER an increasing or a decreasing function of E/No? Why?**
6. **Which case has the lowest BER? Why?**

Deliverables:

- **Please deliver a single report that contains the solution to part I and part II.**
- **The solution of Part II should contain the theoretical derivation, the Matlab code, the required figures, and your comments to 5 and 6.**