

DAY-5

1.A user reports their laptop won't power on even when plugged in. List 5 troubleshooting steps you would take to diagnose the cause, and for each step, explain what you are checking for.

- **Check the power socket** – make sure the wall socket is working by plugging in another device.
- **Check the charger** – check if the charger cable or adapter is damaged or loose.
- **Check the charging port** – look for damage in the laptop's charging port.
- **Check the charging light** – see if the charging LED turns on when the charger is connected.
- **Test with another charger** – If available, try a compatible charger to check if the original charger is faulty.
- **Check the battery** – If the battery is removable, I would remove and reinsert it properly.

**2.You receive a helpdesk ticket: 'My monitor is showing a blank screen, but the CPU seems to be running.' Write a step-by-step troubleshooting flow you would follow to identify and resolve the issue.

Hint: Consider checking both hardware connections and basic display settings.**

- **Check if the monitor is turned on** – Make sure the monitor power light is on.
- **Check the monitor cable** – Ensure the HDMI/DisplayPort cable is connected securely at both ends.

- **Check the monitor input source** –select the correct input (HDMI, or DisplayPort) from the monitor menu.
- **Restart the computer** –restart the PC to see if the display appears.
- **Check the graphics card** –make sure the monitor cable is connected to the correct graphics port and that the GPU is properly seated.
- **Test with another monitor or cable** –try a different monitor or display cable to identify whether the monitor or cable is faulty.
- **Check the RAM** – If there is still no display, I would reseal the RAM and restart the computer.
- **Confirm the fix** – If the display appears normally, the issue has been resolved.

3.A user complains that their wireless mouse is unresponsive, but the keyboard works fine. Describe how you would isolate whether the issue is with the mouse, the USB port, or the system settings.

- **Check the mouse battery** – Replace the battery or charge the mouse to make sure it has power.
- **Check the USB receiver** – Make sure the wireless USB receiver is plugged in properly.
- **Try another USB port** –Plug the receiver into a different USB port to check if the original port is faulty.
- **Test the mouse on another computer** –Connect the mouse to another PC to see if the mouse itself is working.
- **Check system settings** – Open Device Manager and Mouse Settings to ensure the mouse is detected and the driver is working correctly.
- **Restart the computer** – Restart the system and test the mouse again.

4. Imagine you are working on a helpdesk team for a gaming cafe. One system is overheating and shutting down during use. List 3 possible hardware causes and describe how you would check each one.

Hint: Think about fans, dust, and thermal paste.

- **Dust in the CPU or GPU fan** – I would open the computer and check for dust blocking the fans. I would clean the dust using compressed air or a soft brush.
- **Faulty or slow cooling fan** – I would check if the CPU and case fans are spinning properly. If a fan is not working, I would replace it.
- **Dry or old thermal paste** – I would remove the CPU cooler and check the thermal paste. If it is dry or cracked, I would clean it and apply new thermal paste.