

Vcc, GND, Tx, Rx. GT-511C3

You need to make the following connections.

- 1 Transmit needs to be connected to pin 10 (GPIO 15, RXD)
- 2 Receive needs to be connected to pin 8 (GPIO 14, TXD)
- 3 GND needs to be connected to a Pi ground pin (pin 6 or 9 or any other ground pin)
- 4 Vcc need to be connected to a Pi 5V pin (pin 2 or pin 4)



***Abb. 9–7** Anschluss des Fingerabdruckscanners an den Raspberry Pi*

Raspberry Pi2 GPIO Header

Pin#	NAME		NAME	Pin#
01	3.3v DC Power		DC Power 5v	02
03	GPIO02 (SDA1 , I²C)		DC Power 5v	04
05	GPIO03 (SCL1 , I²C)		Ground	06
07	GPIO04 (GPIO_GCLK)		(TXD0) GPIO14	08
09	Ground		(RXD0) GPIO15	10
11	GPIO17 (GPIO_GEN0)		(GPIO_GEN1) GPIO18	12
13	GPIO27 (GPIO_GEN2)		Ground	14
15	GPIO22 (GPIO_GEN3)		(GPIO_GEN4) GPIO23	16
17	3.3v DC Power		(GPIO_GEN5) GPIO24	18
19	GPIO10 (SPI_MOSI)		Ground	20
21	GPIO09 (SPI_MISO)		(GPIO_GEN6) GPIO25	22
23	GPIO11 (SPI_CLK)		(SPI_CE0_N) GPIO08	24
25	Ground		(SPI_CE1_N) GPIO07	26
27	ID_SD (I²C ID EEPROM)		(I²C ID EEPROM) ID_SC	28
29	GPIO05		Ground	30
31	GPIO06		GPIO12	32
33	GPIO13		Ground	34
35	GPIO19		GPIO16	36
37	GPIO26		GPIO20	38
39	Ground		GPIO21	40

Rev. 1
26/01/2014

http://www.element14.com

-