



H5SDK User Manual

step 1: Unzip file named as H5SDK_PRO_1.0.0

Name	Type	Size
H5SDK_Pro_1.0.0	File folder	
H5SDK_Pro_1.0.0	WinRAR ZIP archive	4,980 KB

After unzipping, you will find two main folders:

Name	Type	Size
dist	File folder	
doc	File folder	

dist Folder: Contains the code and supportive files to run SDK.

doc Folder: Includes all the System Requirements Specifications (SRS), flowcharts, and algorithms.

step 2: Running the SDK Locally

i18n	js	alarm.g711a
canvasWorker	cloud	connector
decoder_def	decoder-pro	decoder-pro.wasm
decoder-pro-audio	decoder-pro-audio.wasm	decoder-pro-hard
decoder-pro-simd	decoder-pro-simd.wasm	g711a_al
glutils	hevcdec	index
index	index	index_alarm
index_test	indexEN	jadecoder
jadecoder.wasm	jadecoder.wasm.map	jessibuca-pro
logo_bg	md5	nalu2mp4
nalu2mp4.wasm	play	remoteConfig
userApi		

Open the dist folder, where you will find the index.html file.

To run the file locally or on a server, you can use the Live Server extension in Visual Studio Code (VS Code). Right-click on the dist folder and select "Open with VS Code."

Open the index.html file within the dist folder.

In the VS Code text editor, right-click on the code and choose "Open with Live Server."

The file will open in your default web browser. Simply copy the link from the browser's address bar and hit Enter. The file will display directly in the browser.

If you haven't installed VS Code and the Live Server extension, follow these instructions

Install VS Code: Download and install Visual Studio Code.

Install Live Server: In VS Code, go to the Extensions view by clicking on the Extensions icon in the Activity Bar on the side of the window. Search for "Live Server" and click "Install."

step 3: Viewing the SDK in the Browser

Copy the link generated by Live Server.

Paste the link into your browser's address bar.

Press Enter, and the index.html file should display as expected in your browser.

pic.below

version: 1.0.0 (543b64ed1d 2024/8/6 17:52:35)

语言/Language: English

DeviceId: Username: admin Password: SubStream channel1 search SN Restart Device

Preview

Connect Device Disconnect startRecord endRecord Open Stream Switch Stream Close Stream Screenshot Open Audio Close Audio Alarm Close Alarm

H.264 Set MainStream H.264 The substream is set to H264 Get Encoding Format Current Decoding Mode: wasm

Main stream parameters resolution Bit rate type Bit rate Frame rate

Sub stream parameters resolution Bit rate type Bit rate Frame rate

Obtain video encoding parameters Set video encoding parameters

Start Recording Stop Recording

☐ Flipping the image up and down ☐ Flip the image left and right Get Set

Please confirm in advance whether the device supports the following functions

PTZ Control

PTZ Up PTZ Down PTZ Left PTZ Right PTZ Nearly PTZ Far Zoom in Zoom out Focus in Focus out Pan tilt calibration Preset Position:

1 Set Preset Position Call Preset Position Clear Preset Position

Talk

Open Talk Start Talk Stop Talk Close Talk

step 4: Connect Device to SDK

Before connecting the camera, ensure you have the device ID and password required for the connection.

Username: admin (This is the default username; do not change it.)

Open the browser's developer console by right-clicking on the page and selecting "Inspect," then navigating to the "Console" tab.

Click on the "Connect Device" button located below the preview area in the SDK interface.

The console will display the device ID twice, followed by an error code indicating the connection status.

```
6444730999连接成功 play.js:315
0 play.js:330
6444730999登录成功 play.js:333
```

Note :

When connecting a device to the SDK, you may encounter various error codes. Here's what they mean:

Error 0: Success

The operation was successful. The device is connected and functioning properly.

Error -2: Timeout

The operation timed out. Please check your connection and try again.

Error -10: Local Connection Closed

The local connection to the device was closed. Reconnect the device and retry.

Error -11: Remote Connection Closed

The remote connection to the device was closed. This might require checking the device or network settings.

Error -12: Addressing Failed

Addressing to the device failed. Ensure the device ID is correct and that the device is reachable.

Error -13: Connection Failed (Device Offline)

The device is currently offline. Ensure the device is powered on and connected to the network.

Error -15: Network Delay

There is a delay in the network. You may need to refresh the page or check for issues on the camera side of the network.

Error -20: Wrong Password

step 5: Performing Operations After Successful Connection

Once the device is successfully connected to the SDK, you can perform various operations using the available buttons in the interface. Below is a guide on how to execute these operations:

5.1. Video Streaming Operations

Open Stream: Click on the "Open Stream" button to start video streaming from the connected device.

Switch Stream: Use the "Switch Stream" button to toggle between different video streams (e.g., MainStream, SubStream).

Close Stream: To stop the video stream, click on the "Close Stream" button.

Screenshot: Capture a snapshot of the current video stream by clicking "Screenshot."

Open/Close Audio: Toggle audio on or off during the video stream by clicking "Open Audio" or "Close Audio."

5.2. Recording Operations

Start Recording: Begin recording the video stream by clicking "Start Record."

Stop Recording: Click "Stop Record" to end the recording session.

Set MainStream/SubStream Parameters: Configure video settings like resolution, bit rate, and frame rate for both MainStream and SubStream.

Flipping Image: Use the "Flip the image up and down" or "Flipv the image left and right" buttons to adjust the video orientation.

5.3. PTZ Control (If Supported)

PTZ Up/Down/Left/Right: Control the Pan-Tilt-Zoom (PTZ) of the camera using the corresponding directional buttons.

Zoom In/Out: Adjust the zoom level with the "Zoom in" and "Zoom out" buttons.

Focus In/Out: Fine-tune the focus using "Focus in" or "Focus out."

Preset Position: Set and recall preset positions using the "Set Preset Position" and "Call Preset Position" buttons.

5.4. Talk Operations

Open Talk: Click "Open Talk" to enable the talk feature.

Start Talk: Begin speaking through the device using the "Start Talk" button.

Stop Talk: End the talk session by clicking "Stop Talk."

Close Talk: Click "Close Talk" to disable the talk feature.

5.5. Playback Operations

Search Record: Use the "Search Record" button to search for video recordings within a specified time range.

Play Video: After searching, use the "Display Video List" to select and play recordings.

Playback Controls: Control video playback using the "Play," "Pause," "Continue Playback," "Download Video," and "Stop Playback" buttons.

5.6. Remote Settings

Volume Settings: Adjust the input, output, and alarm volumes using the corresponding buttons.

Night Vision Mode: Toggle between Infrared, Full Color, and Intelligent Night Vision modes.

RTMP Settings: Enable or configure RTMP settings for video streaming.

TF Card Status: Check the status of the TF card, including total and available storage.

Motion Tracking: Enable or configure motion tracking features.

5.7. FTP Operations

FTP Configuration: Set up and test FTP settings for uploading video recordings and images.

FTP Synchronization: Enable and configure FTP synchronization schedules and parameters.

5.8. Device and Firmware Information

Device Info: Retrieve device details, including SIM card information and firmware version.

Firmware Update: Check for new firmware and update the device if available.

5.9 Cloud Playback

After successfully connecting to the SDK and understanding potential errors, you can use the Cloud Playback feature to access and view recordings stored in the cloud.

5.9.1. Logging into Cloud Playback

Step 1: Enter your cloud account credentials in the provided fields:

Account: Enter your cloud account name.

Password: Enter your cloud account password.

Step 2: Click on the **“TrueCloud login”** button to log in and access your cloud storage.

5.9.2. Searching for Cloud Records

Step 1: In the cloud playback interface, select the date for which you want to search for video records:

Search Date: Enter or select the desired date, for example, 8/10/2024., MM/DD/YYYY.

Step 2: Click on the **“Search Record”** button to retrieve the video recordings stored in the cloud for the specified date.

Step 3: Once the search results are displayed, you can select and play the recordings directly from the cloud.

step 6: SDK Screenshots

The screenshot displays the SDK web interface with the following sections:

- Header:** Browser address bar shows 127.0.0.1:8000. Navigation icons and a search bar are present.
- Version:** version: 1.0.0 (543b64ed1d 2024/8/6 17:52:35)
- Language:** 语言/Language: English
- Device Info:** DeviceId: 6444730999, Username: admin, Password: [input], SubStream: [dropdown], channel: [dropdown], search SN, Restart Device
- Preview:**
 - Buttons: Connect Device, Disconnect, startRecord, endRecord, Open Stream, Switch Stream, Close Stream, Screenshot, Open Audio, Close Audio, Alarm, Close Alarm, H.264
 - Stream Info: Set MainStream, H.264, The substream is set to H264, Get Encoding Format, Current Decoding Mode: wasm
 - Parameters: Main stream parameters resolution, Bit rate type, Bit rate, Frame rate, Sub stream parameters resolution, Bit rate type, Bit rate, Frame rate
 - Encoding: Obtain video encoding parameters, Set video encoding parameters
 - Recording: Start Recording, Stop Recording
 - Flipping: ☐ Flipping the image up and down, ☐ Flip the image left and right, Get, Set
- PTZ Control:**
 - Buttons: PTZ Up, PTZ Down, PTZ Left, PTZ Right, PTZ Nearly, PTZ Far, Zoom in, Zoom out, Focus in, Focus out, Pan tilt calibration, Preset Position: 1
 - Position: Set Preset Position, Call Preset Position, Clear Preset Position
- Talk:**
 - Buttons: Open Talk, Start Talk, Stop Talk, Close Talk
- Playback:**
 - Buttons: Search Record, Display Video List, playback First Video, playback Next Video, playback Last Video, Pause Playback, Continue Playback, Download Video
 - Time: Start Time: 8/10/2024 00:00:00, End Time: 8/10/2024 23:59:59, Specified Time Playback, Stop Playback
 - Search: Search all dates with videos, Play the selected date, Download Video
- Remote setting:**
 - Buttons: Get Remote Settings Parameters, Volume setting, Get Volume
 - Input/Output: Input Volume: 0, Output Volume: 0, Alarm Volume: 0, Set the input/output volume, Set AlarmVolume
 - Card Type: Signal
 - Modes: ☐ Infrared Night Vision Mode, ☐ Full Color Night Vision Mode, ☐ Intelligent Mode
 - Alarms: ☐ Loudspeaker Alarm Switch, ☐ Light switch
 - RTMP: ☐ Is RTMP setting enabled, RTMP push address: [input], MainStream, SubStream, RTMP status: Get, Set
 - TF Card: TF Status: [input], TF Card Total Size: [input], TF Card Leave Size: [input], Get TF Card Status, Format TF Card
 - FTP: Get FTP, Set FTP, Test FTP, FTP Switch, FTP Schedule Switch, Select Schedule, FTP Synchronization Switch
 - FTP Details: FTP Port: [input], FTP UploadWay: Alarm, FTP synchronization type: Sync recording by time (days), FTP custom synchronization time: [input], FTP user name: [input], FTP Password: [input], FTP server IP (domain name): [input], FTP upload directory: [input], FTP upload picture path: [input], FTP upload video path: [input], FTP upload time interval(Seconds): [input], FTP upload content: Upload Picture

Video Setting
Get
Time Record Duration(2-30)minute:
Set
Recording Resolution: SubStream
Set

timeZone Setting
Get
Set

Get Device Password
Set Device Password

SIM card details
Get
ICCID:
IMSI:

Current Firmware Version: - Is there a new firmware available: No
Get Device Info
Check for New Firmware
Update Firmware

When running the SDK on a server, the screen color can help diagnose connection issues.

6.1. Screen Color Indications

Black Screen: The SDK is connected to the server and operating normally. This is the expected behavior when everything is functioning correctly.

Green Screen: The SDK is not connected to the server. This indicates a connection problem that needs to be addressed.

6.2. Steps to Troubleshoot a Green Screen

- Step 1:** Verify that the server is running and accessible. Ensure that the server hosting the SDK is operational and that there are no network issues.
- Step 2:** Check the device connection. Make sure the device is properly connected to the SDK with the correct device ID and password.
- Step 3:** Review console logs. Open the browser's developer console (usually by pressing F12 or right-clicking and selecting "Inspect") and check for any error messages related to the SDK connection.
- Step 4:** Reconnect the SDK. If the screen remains green, try reconnecting the SDK by refreshing the browser or restarting the server.


cloud playback

Account:
Password:
True Cloud Login

Search Date 8/10/2024
search

Start time
Duration (seconds)
Video Type
Download video
Playback





Stop Playing 

Before accessing the cloud features, ensure your device is connected to the SDK.

6.1. Connect Your Device

Step 1: Ensure the device is powered on and properly connected to the SDK.

Step 2: Follow the connection steps outlined earlier in the manual to successfully connect your device.

6.2. Log into TrueCloud

Step 1: Once the device is connected, navigate to the TrueCloud login section.

Step 2: Enter your registered mobile number in the designated field.

Step 3: If you have purchased cloud storage, proceed by clicking the “Truecloud” (TrueCloud Login) button to access your cloud account and features.

Player Initialization for Multi-Channel Streaming

To set up a player for viewing multiple channels simultaneously, you need to initialize the player with an array of canvas elements.

6.10.1. Initializing the Player

Step 1: Prepare your HTML file with four <canvas> elements, which will serve as the display windows for each channel.

html

```
<canvas id="canvas1"></canvas>
<canvas id="canvas2"></canvas>
<canvas id="canvas3"></canvas>
<canvas id="canvas4"></canvas>
```

Step 2: In your JavaScript code, create an array containing the four canvas elements:

javascript

```
const canvasElements = [
  document.getElementById('canvas1'),
  document.getElementById('canvas2'),
  document.getElementById('canvas3'),
  document.getElementById('canvas4')
];
```

Step 3: Initialize the player by passing the array of canvas elements to the player initialization function:

javascript

```
initializePlayer(canvasElements);
```

Step 4: Ensure that the initializePlayer function is defined to handle the setup for displaying video streams on the provided canvas elements.

step 7: Precautions

To ensure optimal performance and a smooth user experience while using the SDK, please adhere to the following precautions:

1. Background Image Requirements:

The player background image must be named logo_bg.png and placed in the same directory as the HTML file for the interface. Ensure that the application runs on a web server to properly load the background image.

2. Browser Decoding Limitations:

Be aware that browser decoding performance is limited. To avoid performance issues, do not play video streams on more than 4 screens simultaneously.

3. Default Login Credentials:

The default username for the device is admin, and the password is empty by default. If you successfully connect the device but cannot log in, the password may be incorrect. In such cases, try resetting the device and attempt to log in again.

4. Canvas Element Sizing:

The <canvas> tag of the player must specify both the width and height. Setting the value to 100% may cause the screen to render blurry. If the interface requires adaptive design, ensure that the width and height are reset after any changes.



If you need further assistance, please do not hesitate to contact our support team.

Contact no: +91 75074 07111

Mail id: support@trueview.co.in