Fast and High-Fidelity Quantum Logic Gates for Parametrically Coupled Transmons

Hyeongjin Kim, Professor Frederick W. Strauch
Department of Physics, Williams College

INTRODUCTION

There have been significant advancements in realizing quantum computers composed of quantum bits (=qubits). However, a key challenge is the decoherence, which limits how long information can be stored in each qubit. Thus, we explore fast and high-fidelity quantum logic gates in parametrically driven transmons.

BACKGROUND

Qubits are mathematical representations of quantum states:

$$|0\rangle = \begin{pmatrix}1\\0\\0\end{pmatrix}, \quad |1\rangle = \begin{pmatrix}0\\1\\0\end{pmatrix}, \quad |2\rangle = \begin{pmatrix}0\\0\\1\end{pmatrix}$$

A transmon is a type of superconducting charge qubit. Consider a transmon with anharmonicity δ:

Energy Diagram for System A



Hamiltonian for System A

$$\mathcal{H}_A = \hbar \begin{pmatrix} 0 & 0 & 0 \\ 0 & \omega_A & 0 \\ 0 & 0 & 2\omega_A - \delta_A \end{pmatrix}$$

SYSTEM OF TWO TRANSMONS

We consider the system of two coupled transmons, labelled A and B, that is parametrically driven by a pulse.



Hamiltonian for System

$$\mathcal{H} = \mathcal{H}_0 + \mathcal{H}_{\text{pulse}}(t)$$

$$\mathcal{H}_0 = \mathcal{H}_A \otimes I + I \otimes \mathcal{H}_B$$

$$\mathcal{H}_{\text{pulse}}(t) = g(t)\, \mathbb{X} \otimes \mathbb{X}$$

Coupling Operator

$$\mathbb{X} = \begin{pmatrix} 0 & 1 & 0 \\ 1 & 0 & \sqrt{2} \\ 0 & \sqrt{2} & 0 \end{pmatrix}$$

$g(t)$ is the driving pulse.

METHODOLOGY

We parametrically drive the system with a time-varying pulse, $g(t)$, for the time of T_{pulse}, activating the coupling operator:

$$g(t) = \frac{A}{2}\left(1 - \cos\left(\frac{2\pi t}{T_{\text{pulse}}}\right)\right)\cos(\omega_d t) + B \sin\left(\frac{2\pi t}{T_{\text{pulse}}}\right)\sin(\omega_d t)$$

Both the one-quadrature approach ($B = 0$) and the two-quadrature approach ($B \neq 0$) are considered. We explore pulses with drive frequencies ω_d near $\omega_A - \omega_B$. By solving the Schrödinger equation, we note that the evolution operator, U, causes the transitions between **01** and **10**. Further, we observe that the operator is locally equivalent to $\sqrt{\varphi\text{-SWAP}}$.

Schrödinger equation

$$i\hbar \frac{d|\psi(t)\rangle}{dt} = \mathcal{H}|\psi(t)\rangle$$

$$\downarrow$$

$$|\psi(T_{\text{pulse}})\rangle = U|\psi(0)\rangle$$

$$U \to U_{\text{local}} \sim \sqrt{\varphi\text{-SWAP}}$$

$$\sqrt{\varphi\text{-SWAP}} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & \frac{1}{\sqrt{2}} & \frac{-i}{\sqrt{2}} & 0 \\ 0 & \frac{-i}{\sqrt{2}} & \frac{1}{\sqrt{2}} & 0 \\ 0 & 0 & 0 & e^{-i\varphi} \end{pmatrix}$$

RESULTS

The optimized parameters of the pulses are for one- and two-quadrature pulses (fixed frequency is at $\omega_d = \omega_A - \omega_B$):







Using the optimized parameters, we simulate the evolution operator of the Hamiltonian from RFT without RWA, and then calculate the error.

RFT with RWA: Optimize $1 - \frac{1}{4}\left|\text{trace}(\tilde{U}_{\text{local}}\sqrt{\varphi\text{-SWAP}})\right|$

Obtain optimal parameters: A, B, ω_d

$\downarrow$

RFT without RWA: Simulate using optimized A, B, ω_d

Calculate error



MODELING AND OPTIMIZATION

We impose the rotating frame transformation (RFT) and rotating wave approximation (RWA) on the Hamiltonian:

$$\mathcal{H} \sim \tilde{\mathcal{H}} = \mathcal{H}_1 + g_1(t)\mathcal{H}_2 + g_2(t)\mathcal{H}_3$$

$$g_1(t) = \frac{A}{2}\left(1 - \cos\left(\frac{2\pi t}{T_{\text{pulse}}}\right)\right), \quad g_2(t) = B \sin\left(\frac{2\pi t}{T_{\text{pulse}}}\right)$$

The evolution operator from $\tilde{\mathcal{H}}$ was numerically approximated to the second-order with small timesteps dt:

$$U \sim \tilde{U} = \prod_{t=0,dt,2dt,\ldots}^{T_{\text{pulse}}} e^{-i\mathcal{H}_1 dt/2\hbar} e^{-i(g_1(t)\mathcal{H}_2 + g_2(t)\mathcal{H}_3)dt/\hbar} e^{-i\mathcal{H}_1 dt/2\hbar}$$

After local operations, $\tilde{U} \to \tilde{U}_{\text{local}}$, we optimize the parameters of the pulse to minimize the error between $\tilde{U}_{\text{local}}$ and $\sqrt{\varphi\text{-SWAP}}$ for various values of T_{pulse}:

$$\text{ERROR} = 1 - \frac{1}{4}\left|\text{trace}(\tilde{U}_{\text{local}}\sqrt{\varphi\text{-SWAP}})\right|$$

$$\text{FIDELITY} = 1 - \text{ERROR}$$

DISCUSSION

- Using optimized parameters for two-quadrature, non-fixed drive frequency pulses, we achieve errors between 10^{-4} and 10^{-6} for T_{pulse}'s between 5 ns and 10 ns.
- The probabilities that **11** state transitions to the **02** and **20** states, $|\langle 02|U|11\rangle|^2$ and $|\langle 20|U|11\rangle|^2$, contribute to the gate errors. For example, at $T_{\text{pulse}} = 6$ ns, two-quadrature pulses with non-fixed frequency lead to lower error **and** $|\langle 20|U|11\rangle|^2$ than with fixed frequency:



- Two applications of the $\sqrt{\varphi\text{-SWAP}}$ gates can be used to create a CNOT gate, up to a global phase shift:

Redacted

- CNOT gates are important in the development of quantum computers, for any unitary gate can be implemented to arbitrary accuracy using CNOT and single-qubit gates.
- In conclusion, by using fast and high-fidelity $\sqrt{\varphi\text{-SWAP}}$ gates, one can achieve fast and high-fidelity CNOT gates and thus improve the accuracy of any gate.

FUTURE OUTLOOK

- Use the Derivative Removal by Adiabatic Gate (DRAG) formalism to theoretically predict optimal parameters of the pulses as analytical functions of T_{pulse}.
- Investigate locally different quantum logic gates by considering different drive frequency regions.
- Numerically model an open quantum system to explore the effects of decoherence and dephasing.
- Investigate the first-principles analysis of multi-transmon circuits.