combination frame

Offset	Length	Type	Data	Details
0	1	Data Length	0x02	Data length of the AD structure
1	1	Flag Data Type	0x01	The AD type is Flags
2	1	Flag Data	0x06	The flags are "LE (Low Energy) Regular Discoverable Mode" and "BR/EDR not supported
3	1	Data Length	0x0E	Data length of the AD structure = 14
4	1	AD Type	0xFF	The AD type is vendor - defined data
5	2	CompanyID	0x3906	LE,Manufacturer ID,Ox0639 = Minew Technologies Co., Ltd
7	1	Frame Type	0xCA	Minew Connect V3
8	1	Frame Version	0x03	Broadcast frame type
9	x	**Block #1**	-	Broadcast frame type, Door sensor
...	...	Block #N		(no more block for now)
14	2	Salt	-	BE，Random number
16	2	Digital Signature	-	Digital signature

door sensor block information

Offset	Length	Type	Data	Details
9	1	block ID	0x1F	block ID = 31
10	1	**Door sensor Current Status**	-	-
11	1	The door opening serial number	-	Every time the door is opened，the serial number automatically adds 1. After reaching 255, it jumps to 0 and loops
12	1	The door closing serial number	-	Every time the door is closed, the serial number automatically adds 1. After reaching 255, it jumps to 0 and loops
13	1	Anti disassembly alarm serial number	-	Every time the anti disassembly alarm，the serial number automatically adds 1, up to 255 jump to 0, cycle

Door Sensor Current Status description

bit offset	bit Length	Details
0	1	Door sensor alarm status (close =0/ open =1)
1	1	Anti disassembly alarm status (press =0/ release =1)
2	1	Trigger alarm state, any trigger will turn it from 0 to 1 for one times.
3	5	reserved

Note

bit offset 0	bit offset 1	bit offset 2	bit offset 3~7	Broadcast	Meaning
0	0	0	00000	0x00	Door close Disassembly key press
1	0	1	00000	0xA0	Door open Disassembly key release First frame after triggered

info frame

Offset	Length	Type	Data	Details
0	1	Data Length	0x02	Data length of the AD structure
1	1	Flag Data Type	0x01	The AD type is Flags
2	1	Flag Data	0x06	The flags are "LE (Low Energy) Regular Discoverable Mode" and "BR/EDR not supported
3	1	Data Length	0x1B	Data length of the AD structure= 27
4	1	AD Type	0xFF	The AD type is vendor - defined data
5	2	CompanyID	0x3906	LE,Manufacturer ID,Ox0639 = Minew Technologies Co., Ltd
7	1	Frame Type	0xCA	Minew Connect V3
8	1	Frame Version	0x00	@ref [ESL device type](ESL Branch Vers.md)
9	6	Mac Address	0x01653322 11AC	LE,0x0165332211AC = AC:11:22:33:65:01
15	1	Battery Level	0x64	Percentage of battery capacity, 0x64 = 100%
16	2	Firmware Version	0x2187	BE, 0x2187 = 1.3.7 (16 bites: 3b maior 6b minor 7b build
18	8	Peripheral Support	-	@ref peripherals support description
26	1	TBD	-	Not yet defined
27	2	Salt	-	BE，Random number
29	2	Digital Signature	-	Digital signature

Serial number specification

1. The device will keep broadcasting at a 1s broadcast interval.
2. In addition to broadcasting the current status, The number of times the doors are opened and closed will also be broadcast.
3. The HUB compares the two serial number data received to know how many times the door was opened or closed during this period.

For example:

No.1

020106 0EFF 3906 CA03 ***1F 00020301*** *xxxx xxxx* (byte offset start from 0)

The first time the hub received the 9~13 byte offset was： 0x1F**00020301**

020106 0EFF 3906 CA03 ***1F 00060702*** *xxxx xxxx*

The second time the hub received the 9~13 bytes offset was：0x1F**00060702**

Then during this period, The door was opened four times and closed four times. Anti disassembly alarm one time.

No.2

020106 0EFF 3906 CA03 ***1F 0002030E*** *xxxx xxxx*(byte offset start from 0)

The first time the hub received the 9~12 byte offset wass：0x1F**0002030E**

020106 0EFF 3906 CA03 ***1F 8006060E*** *xxxx xxxx*

The second time the hub received the 9~12 byte offset was：0x1F**8006060E**

Then during this period, The door was opened four times and closed three times,.The door is now open. No anti disassembly alarm.

* The preceding broadcast format is for reference and subject to subsequent official delivery.