BR1601A02

POWER

电池3.7V输入

U5 XC6201P332MR

BAT_IN, VDD_BAT, PAD TP-PAD T7, PAD TP-PAD T8, C20 22uF ±20% 6.3V, GND

程序烧录口

T1 RESET
T2 PA5_SWDIO/RXD_KEY10
T3 PA4_SWDCLK/TXD_KEY9
T4 GND
T5 VDD_BAT
T6 PB1_LOG_TX

RESET, PA5_SWDIO/RXD_KEY10, PA4_SWDCLK/TXD_KEY9, GND, VDD_BAT, PB1_LOG_TX

LED 指示灯

LED1 LED_Dual_AAKK
LED2 R2 1K
LED1 R1 1K
GND, GND

Q1 MMBT5551 / Q4 SPP3413

BAT_IN, R10 100K, Q4 SPP3413, LTE_EN, R8 1K, R9 470K, Q1 MMBT5551, GND

VLTE, C25 1UF, C27 10P, C28 33P, GND

R16 20K, PB6_ADC5, R28 4.7K, C29 0.01, GND

U4 NT26F

E1 100UF/10V, VLTE, GND, GND

GND	1	98	RESERVED
RESERVED	2	44	RESERVED
RESERVED	3	43	VBAT
RESERVED	4	42	VBAT
RESERVED	5	41	GND
RESERVED	6	40	GND
PWRKEY	7	39	DBG_TXD
RESERVED	8	38	DBG_RXD
ADC0	9	37	GND
GND	10	36	GND
SIM_DATA	11	97	RESERVED
SIM_RST	12		
SIM_CLK	13		

ANT_MAIN	35	ANT	
GND	34	GND	
PCM_DOUT	33		
PCM_DIN	32		
PCM_SYNC	31		
PCM_CLK	30		
AUX_TXD	29		
AUX_RXD	28		
GND	27	GND	
RESERVED	26		
STATUS	25		
VDD_EXT	24	VDD_EXT	
MAIN_RTS	23		

R13 100K, GND, PWRKEY

GND	95	14	GND
SIM_VDD	96	15	USIM1_VDD
		16	RESET_N
		17	NET_STATUS
LTE_RXD	18		MAIN_RXD
LTE_TXD	19		MAIN_TXD
	20		MAIN_DTR
	21		MAIN_RI
	22		MAIN_DCD
	95		MAIN_CTS
			ADC1

U2 SIMt

VCC 8, RESET 7, CLOCK 6, NC 5, NC 4, DATA 3, NC 2, GND 1

R19 22 SIM_VDD, SIM_RST, SIM_CLK
R22 22 SIM_DATA
C26 0.1, GND

Q3 MMBT5551

VDD_BAT, R30 10K, PB5_IRRX
VDD_EXT, R29 4.7K
LTE_TXD

D4 BS817WS
LTE_RXD, PB4_IRTX

U1

VDD_BAT, VDC_DC, C30 1uF, GND
1uF C2, GND
L1 1.6nH, C4 10pF ±5%
C3 12pF ±5%, 32MHZ_±10PPM_9PF_3225, C31 12pF ±5%, X1, GND

RF射频走线需要做50欧姆阻抗匹配

ANT1, 0R L2, 0R L3, C26 NC, C22 NC, C5 NC, C6 NC, D2 MDFN2C0310A2, 板载天线, GND

电池匹配 阻抗匹配

PA0_KEY, PA1_KEY

VDD_BAT, 10KR ±5% R99, 1uF C8, GND

PA2_KEY 1 PA2, PA3_KEY 2 PA3, RESET 3 RESET, 4 PB0, PA4_SWDCLK/TXD_KEY9 5 PA4/TX, PA5_SWDIO/RXD_KEY10 6 PA5/RX, PA6_KEY 7 PA6, 8 VDD_FLASH

C13 2.2nF ±20% 6.3V, C19 100nF ±10% 10V, GND

PA1	32		
PA0	31		
XO32MP_IN	30		
XO32MP_OUT	29		
VCCRF	28		
VDDCRF	27		
VDDPA	26		
RFIOP	25		

PB8/X32K_IN	9	PB8_KEY	
PB9/X32K_OUT	10	PB9_KEY	
PB1/LOG	11	PB1_LOG_TX	
PB2	12	LTE_EN	
PB3	13	LED1	
PB4	14	PB4_IRTX	
PB5	15	PB5_IRRX	
PB6	16	PB6_ADC5	

GND, 33 GND

VDCDC 24, SWITCH 23 2.2uH MIPSDZ1608G2R2PA L4, VCC 22, PB13/MICP 21 PB13_MICP, PB11/MICN 20 PB11_MICN, PB12/MIC_BIAS 19 PB12_MIC_BIAS, PB10 18 PB10_KEY, PB7 17 LED2

C8 1uF, GND, VDC_DC, VDD_BAT
C11 10uF ±10% 6.3V, C12 100nF ±10% 10V, GND
NC C14 0.02

电容麦

PB12_MIC_BIAS, R23 200R, C1 100nF, C14 4.7uF, C15 4.7uF, R24 2K8, R25 2K8, R26 200R, GND
MIC1 4015MICPHONE
C16 1uF 6.3V PB13_MICP, C17 1uF 6.3V PB11_MICN

按键

PA0_KEY, PA2_KEY, PA1_KEY, PB10_KEY, PB9_KEY, PB8_KEY, PB8_KEY, PA6_KEY, PA6_KEY

K1 电源, K2 静音, K3 电视, K17 回看, K4 确认, K5 左, K7 下, K6 右, K16 上, K11 频道+, K10 菜单, K9 返回, K13 频道−, K12 音量+, K14 音量−, K15 语音, K8 主页, PA3_KEY, PA3_KEY

TYPE-C

typec1, GND, VBUS, A1B12 GND, A4B9 VBUS, B8 SBU2, B7 CC1, B6 D−, A6 D+, A7 D−, B6 D+, B5 SBU1, A5 CC2, A4B9 VBUS, B1A12 GND, VBUS, GND, TYPE-C

TP4056

U3, GND, C18, C21, R21 3K, VBUS, R3 0.4R, 0.1, 10uF

TMEP	1	CE	8
PROG	2	CHRG	7
GND	3	STDBY	6
VCC	4	BAT	5

BAT_IN, C24 10uF, GND

TP4056

Sheet: /			
File: Vioce_Cat1_Remote_V1.0.kicad_sch			
Title:			
Size: A2	Date:		**Rev:**
KiCad E.D.A. 9.0.4			Id: 1/1