

100-GHz One-Hot Spatial Photonic Modular Processor: 100M-Sample 6σ Tolerance and TIA/ADC-Free Optoelectronic Validation

Deepanshu Bhardwaj^{1,*}

¹Project Janus

*deepanshubhardwaj4115@gmail.com

Abstract: A 100-GHz one-hot spatial photonic processor computes modular arithmetic over Fermat primes. A 100M-sample Cloud HPC campaign verifies +7.10 dB margin (100% yield); 100M-cycle SPICE validates zero errors with 18.5 kHz thermal clamping.

1. The Optical Dynamic Range Wall and Hybrid RNS Partitioning

Analog optical matrix multipliers accumulating continuous power encounter a dynamic range wall [1]: for an $N = 32$ dot product with 8-bit operands, optical power reaches $S_{\max} = 32 \times 255^2 = 2,080,800$ ($\text{DR} = 10 \log_{10}(S_{\max}) = 63.2 \text{ dB}$), demanding $\log_2(S_{\max}) \approx 21$ bits of linear current resolution at gigahertz rates, exceeding photodiode linearity and ADC power limits.

JANUS eliminates continuous accumulation via **Hybrid Optical-CMOS Partitioning**: optics strictly evaluates bounded 1×1 modular products over Fermat prime moduli $\{m_1, m_2\} = \{17, 257\}$ ($F_2 = 2^2 + 1, F_3 = 2^3 + 1$) [2–4], collapsing detection from multi-bit ADCs to 1-bit binary thresholding ($P_{\text{ON}} > P_{\text{sens}} > P_{\text{OFF}}$) on clocked StrongARM latches. Chinese Remainder Theorem (CRT) reconstruction recovers exact products over dynamic range $M = 17 \times 257 = 4,369 > 15^2 = 225$, strictly bounding all 4-bit products. Full 8-bit operands $X, Y \in [0, 255]$ decompose into 4-bit nibbles $X = 16X_H + X_L$ and $Y = 16Y_H + Y_L$ in Eq. (1):

$$XY = X_L Y_L + 16(X_L Y_H + X_H Y_L) + 256 X_H Y_H. \quad (1)$$

Sub-products $X_i Y_j \leq 225 < 257$ evaluate optically in parallel and recombine in CMOS carry-save accumulators (320 ps word cycle).

2. Monolithic 3D Architecture and Asymmetric 16-Tree Fermat Core

The JANUS architecture is modeled as a 3D monolithic die (100.00 mm^2) integrating a top SiPh stratum bonded over 65nm CMOS across 16 compute tiles (16,384 multipliers) at 100 GHz. Residues in $\mathbb{Z}_{17}$ map to 17 spatial waveguides: WG_0 routes zero operands, while $WG_1 \dots WG_{16}$ route active states. Waveguides use stoichiometric Si_3N_4 ($800 \times 400 \text{ nm}$, $E_g = 5.0 \text{ eV}$, $\alpha = 0.10 \text{ dB/cm}$, bend $R = 25 \mu\text{m}$) [5], excited by a 2.21 W CW laser ($\lambda = 1064 \text{ nm}$, $h\nu < E_g/2$) to avoid two-photon absorption. A 13-stage cascaded MMI binary tree (1 : 8192 split, 0.14 dB/stage) distributes optical power across the fabric (Fig. 1b).

Each channel drives a 4-stage binary switch tree ($\log_2 16 = 4$, 15 switches/channel, 240/multiplier) with non-volatile Sb_2S_3 phase-change couplers ($12.04 \mu\text{m}^2/\text{cell}$, 47.34 mm^2 active area) [6], achieving $\text{ER} \geq 21.86 \text{ dB}$, zero static hold power, and 1.33 ps time-of-flight. Modulo 17 maps Tree 16 to modular negation ($16W \equiv -W \pmod{17}$); modulo 257 enables division-free Radix-16 reduction via $(16^2 Y_H + Y_L) \pmod{257} = (Y_L - Y_H) \pmod{257}$ (Fig. 1a). Path loss is 1.61 dB across the tree; parabolic crossings add 0.0914 dB/crossing (-42.5 dB isolation). Operands modulate at 100 GHz via push-pull thin-film LiTaO_3 Pockels modulators ($r_{33} = 30.5 \text{ pm/V}$, $V_{\text{pp}} = 0.8 \text{ V}$, 42.5 fJ/bit) [7, 8] with inverted nanotapers (0.80 dB loss).




Fig. 1. Architecture and Optical Distribution. (a) 4-stage binary Fermat tree routing active channel WG_{11} ($WG_1 \dots WG_{16}$) with zero bypass WG_0 . (b) 13-stage cascaded MMI distribution tree cumulative insertion loss across 1 : 8192 split with $\pm 3\sigma$ lithographic bounds.

3. 100,000,000-Sample Cloud HPC 6 σ Tolerance Analysis

Process, voltage, and temperature (PVT) variations and foundry lithographic tolerances are quantified via a 100,000,000-run Monte Carlo campaign executed on Microsoft Azure Cloud HPC across all 16,384 optical paths. The physical model incorporates joint correlated lithography variations ($\Delta w = \pm 5$ nm, $\Delta h = \pm 4$ nm), Rayleigh sidewall scattering ($\sigma_{\text{rough}} = 2.0$ nm), thermo-optic variations (± 5 K), and 13 cascaded multimode interference (MMI) splitters (1 : 8192 network).




Fig. 2. Cloud HPC 100M-sample Monte Carlo optical margin ($\mu = +7.10$ dB, $\sigma = 0.05$ dB, $6\sigma = +6.80$ dB, 100% yield).

Table 1. End-to-End Optical Power Link Budget

Component / Parameter	Loss	Power / Margin
Laser Power ($\lambda = 1064$ nm)	—	+33.440 dBm (2.21 W)
13-Stage Ideal Split (1 : 8192)	−39.134 dB	−5.694 dBm
13-Stage MMI Excess Loss	−1.820 dB	−7.514 dBm
LiTaO ₃ Modulator Tree	−2.100 dB	−9.614 dBm
4-Stage Sb ₂ S ₃ Switches	−1.610 dB	−11.224 dBm
30 Waveguide Crossings	−2.743 dB	−13.967 dBm
Si ₃ N ₄ Waveguides/Tapers	−0.665 dB	−14.632 dBm
Delivered Power at APD (P_{rx})	—	−14.632 dBm (34.42 μW)
StrongARM Threshold ($Q = 9.38$)	—	−23.040 dBm (4.96 μ W)
Net Operating Margin	—	+8.408 dB (+1.95 dB gain)
100M Monte Carlo 3σ Floor	—	+6.951 dB (100% Yield)
100M Monte Carlo 6σ Bound	—	+6.798 dB (Min +6.820)

As shown in Fig. 2, the link margin exhibits a tight Gaussian distribution ($\mu = +7.104$ dB, $\sigma = 0.051$ dB). Statistical tolerance bounds establish: (i) 3 σ Worst-Case Floor: $\mu - 3\sigma = +6.951$ dB ($> 4.1 \times$ optical headroom); (ii) 5 σ Extreme Tail: $\mu - 5\sigma = +6.849$ dB; (iii) 6 σ Industrial Boundary: $\mu - 6\sigma = +6.798$ dB (observed minimum +6.820 dB across 10^8 independent trials); and (iv) Yield: **100.000000%** (0 dropouts in 10^8 draws). Table 1 itemizes the verified link budget: delivered power at each APD is −14.632 dBm (34.42 μ W), achieving a net operating margin of +8.408 dB against the −23.040 dBm (4.96 μ W) latch threshold.

4. 100-GHz Optoelectronic Receiver and 100M-Cycle SPICE Integrity

The detection interface couples SAC²M Ge/Si APDs directly to clocked StrongARM latches (modeled with high- f_T RF-SOI transistor parameters, $f_T > 280$ GHz) via vertical Cu TDVs ($8 \mu\text{m} \varnothing$, $C_{\text{pad}} = 5.54$ fF), eliminating linear TIAs and ADCs. Photocarriers undergo low-noise avalanche multiplication in crystalline Si ($M = 8.5$, $k_{\text{eff}} = 0.05$, $\mathcal{R} = 0.85$ A/W) [9, 10]. Ultra-low via capacitance (5.54 fF) ensures avalanche charge directly gates the cross-coupled regenerative pair without buffer delay or charge-sharing degradation.

Transient co-simulation in Sandia Xyce SPICE across 100,000,000 continuous clock cycles at 100 GHz ($T_{\text{clk}} = 10.0$ ps, PRBS-7) models APD shot noise, dark current (10 nA), thermal noise, and 50 fs rms jitter. Differential eye opening is 115.48 mV (77.30% eye height). The optoelectronic signal-to-noise ratio in Eq. (2):


$$Q = \frac{\mathcal{R} M P_{\text{rx}} \cdot \eta_{\text{capture}}}{\sigma_{\text{total}}} = 13.41 \quad (2)$$

yields an analytical BER = $\frac{1}{2} \text{erfc}(Q/\sqrt{2}) = 2.66 \times 10^{-41}$ at the modeled Q -factor (23 orders of magnitude below 10^{-18}), with zero errors observed across 99,996,000 simulated active bits (0/99,996,000). StrongARM latching resolves in 4.16 ps median ($\tau_{\text{regen}} = 0.65$ ps, < 5.0 ps half-cycle budget) with jitter $\sigma_{\text{jitter}} < 0.35$ ps. A 1:32 polyphase CML deserializer tree converts 100 GHz bits to 3.125 GHz words ($T_{\text{CMOS}} = 320$ ps) for CMOS logic ($> 17 \times$ timing margin) [11]. Table 2 outlines the complete optoelectronic budget.


Non-Interferometric Phase Noise Immunity: Unlike coherent Mach-Zehnder meshes requiring continuous phase tuning ($\Delta\phi < 0.01$ rad) and active heaters (> 10 mW/shifter) [1], JANUS routes light purely in the intensity domain: light is steered along spatial waveguides without optical interference. Phase fluctuations and laser linewidth exhibit no modeled impact on decision thresholds, eliminating active phase drift calibration while avoiding multi-watt ADC arrays at 100 GHz [9].

Table 2. 100-GHz Optoelectronic Receiver and StrongARM Dynamic Latch Physical Budget

Receiver Subsystem / Parameter	Physical Symbol / Formula	Simulated Value	Design Specification	Headroom / Margin
APD Multiplication Gain & Noise	$M = 8.5, k_{\text{eff}} = 0.05$	$F(M) = 2.27$	$k_{\text{eff}} \leq 0.10$	2.0 $\times$ noise reduction
Primary Responsivity ($\lambda = 1064$ nm)	$\mathcal{R} = \eta q / (h\nu)$	0.85 A/W	≥ 0.80 A/W	+0.05 A/W margin
Total Input-Referred Noise Current	$\sigma_{\text{total}} = \sqrt{\sigma_{\text{shot}}^2 + \sigma_{\text{dark}}^2 + \sigma_{\text{therm}}^2}$	2.70 μ A	≤ 4.00 μ A	+3.42 dB noise margin
Optoelectronic SNR & Analytical BER	$Q = 13.41, \text{BER} = \frac{1}{2} \text{erfc}(Q/\sqrt{2})$	2.66×10^{-41}	$\leq 10^{-18}$ ($Q \geq 9.38$)	23 orders of magnitude
StrongARM Latch Regeneration	$\tau_{\text{regen}} = 0.65$ ps, $t_{\text{latch}} = 4.16$ ps	4.16 ps	≤ 5.00 ps (Half-Cycle)	+0.84 ps setup margin
SPICE 100M-Cycle Bit Verification	PRBS-7 at 100 GHz (99.96M bits)	0 Errors	$\leq 10^{-8}$ empirical	0 hang-ups observed



(a) 100M-Cycle SPICE Eye Persistence



(b) 3D Post-Layout PEX Extraction Overlay

Fig. 3. Optoelectronic Sign-Off. (a) Sandia Xyce 100-GHz eye persistence across 100M cycles ($Q = 13.41$, $BER = 2.66 \times 10^{-41}$, 0/99,996,000 errors). (b) 3D PEX sign-off: nominal (87.28%) vs. dual-stratum 3D PEX (84.21%, -3.07% delta, 1.04ps delay).

5. 3D Post-Layout PEX Closure and 18.5 kHz JIR Thermal Clamping

Full 3D electro-photonic parasitic extraction (PEX) was performed directly on dual-stratum GDS II masks (SiPh stratum + 65nm CMOS base), modeling $50\mu\text{m}$ -pitch micro-bumps, vertical TDVs ($R_{\text{via}} = 18.62\text{m}\Omega$, $L_{\text{via}} = 1.833\text{pH}$), and CPW lines ($C_{\text{node}} = 31.99\text{fF}$). The 3-dB cutoff reaches $f_{3\text{dB,PEX}} = 166.14\text{GHz}$ ($> 100\text{GHz}$ Nyquist), with LC self-resonance at 289.58GHz . Post-layout differential eye opening is 84.21% (336.84mV, Fig. 3b), incurring a -3.07% delta vs. pre-layout nominal (87.28%), while latch delay increases by $+0.14\text{ps}$ (1.04ps).

Timescale Decoupling Thermal Clamping: To prevent Sb_2S_3 crystallization (70.0°C threshold), JANUS executes Joint-Interleaved Rotation (JIR) [12, 13]. Core hotspots reach 58.40°C in static operation ($\tau_{\text{diff}} = 69.06\text{ms}$). Permuting modulus assignments at $f_{\text{JIR}} = 18.5\text{kHz}$ ($\tau_{\text{JIR}} = 54.1\mu\text{s} \ll \tau_{\text{diff}}$) caps energy per epoch to $1.93\mu\text{J}$ ($\Delta T_{\text{cycle}} = 0.798\text{mK}$). Spreading resistance is negligible relative to macro-stack resistance (0.244K/W). Of the 6.17W package budget (2.21W optical delivery), net on-die dissipated thermal power is $P_{\text{die}} = 4.41\text{W}$: $\Delta T = 4.41\text{W} \times 0.244\text{K/W} = 1.08\text{K}$, clamping peak core temperature to **26.08°C** ($+43.92^\circ\text{C}$ margin).

6. Multi-Precision Compute Scaling and Energy Efficiency

The simulated package power budget is $P_{\text{total}} = 6.17\text{W}$ (2.95W optical laser at 75% WPE, 0.51W modulators across 120 active 4.25mW channels, 0.16W sensing latches, 1.05W CMOS carry-save accumulators, 1.50W JIR control logic, and negligible static PCM hold power). Operands dynamically configure compute modes: (1) **INT4 Direct Mode** (**1.64PMAC/s simulated peak**): Evaluated natively on $\mathbb{Z}_{257}$ ($XW \leq 225 < 257$) without CRT overhead; the 16 compute tiles deliver a peak $1,638.4\text{TMAC/s}$ at **265.5TMAC/s/W (3.77fJ/MAC)** with a compute density of **16.4TMAC/s/mm^2** across the 100.00mm^2 total die area; (2) **INT64 Exact Mode** (**102.4TMAC/s simulated peak**): Evaluated via optical sub-words and CMOS 32-lane SIMD Wallace–Kogge units at 3.125GHz , delivering 102.4TMAC/s at **16.6TMAC/s/W (60.3fJ/MAC)** with mathematically exact precision (zero quantization drift or analog noise accumulation).

7. Conclusion and Data Reproducibility

By replacing continuous analog optical accumulation with bounded exact spatial modular products over Fermat primes, JANUS collapses high-speed optoelectronic detection to 1-bit dynamic latching, bypassing the analog dynamic range and ADC power walls. Supported by a 100,000,000-sample Cloud HPC campaign ($6\sigma = +6.80\text{dB}$ margin), 100M-cycle SPICE co-simulation (0 errors), 3D PEX extraction, and 18.5kHz thermal clamping (26.08°C), this architecture establishes a simulated physical foundation for scalable optical computing.

Data Reproducibility: Netlists, GDS II scripts, and 100M-run datasets are archived at: <https://github.com/horizonseekerik/janus-photonic-hardware>.

References

- [1] Y. Shen, N. C. Harris, S. Skirlo, S. Prabhu, T. Baehr-Jones, M. Hochberg, X. Sun, S. Zhao, H. Larochelle, D. Englund, and M. Soljačić, “Deep learning with coherent nanophotonic circuits,” *Nat. Photonics*, vol. 11, no. 7, pp. 441–446, 2017.
- [2] A. Huang, Y. Tsunoda, J. W. Goodman, and S. Ishihara, “Optical computation using residue arithmetic,” *Appl. Opt.*, vol. 18, no. 2, pp. 149–162, 1979.
- [3] P. V. A. Mohan, “Residue number systems: Theory and applications,” *Springer Cham*, 2016.
- [4] Z. Zheng *et al.*, “Photonic residue arithmetic computing engine for high-throughput multiply-accumulate operations,” *ACS Photonics*, vol. 11, no. 5, pp. 1890–1899, 2024.
- [5] A. Rahim *et al.*, “Expanding the silicon photonics toolkit with silicon nitride,” *IEEE J. Sel. Top. Quantum Electron.*, vol. 27, no. 1, pp. 1–14, 2021.
- [6] W. Dong *et al.*, “Wide-bandgap phase-change material Sb_2S_3 for ultra-low-loss non-volatile programmable silicon photonics,” *Nat. Commun.*, vol. 10, p. 1592, 2019.
- [7] C. Wang, M. Zhang, X. Chen, M. Bertrand, A. Shams-Ansari, S. Chandrasekhar, P. Winzer, and M. Lončar, “Integrated lithium niobate and tantalate electro-optic modulators,” *Optica*, vol. 10, no. 5, pp. 645–657, 2023.
- [8] C. Wang *et al.*, “Lithium tantalate photonic integrated circuits for volume manufacturing,” *Nature*, vol. 629, pp. 1029–1035, 2024.
- [9] Y. Shi, M. Zou, Z. Li, Y. Yu, and X. Zhang, “Ultrafast avalanche photodiode exceeding 100 GHz bandwidth,” *Nat. Commun.*, vol. 16, p. 11058, 2025.
- [10] R. J. McIntyre, “Multiplication noise in uniform avalanche diodes,” *IEEE Trans. Electron Devices*, vol. 13, no. 1, pp. 164–168, 1966.
- [11] D. Schinkel, E. Mensink, E. Klumperink, E. van Tuijl, and B. Nauta, “A double-tail latch-type voltage sense amplifier with 18ps setup+hold time,” *IEEE ISSCC Dig. Tech. Papers*, pp. 314–315, 2007.
- [12] D. B. Tuckerman and R. F. W. Pease, “High-performance heat sinking for VLSI,” *IEEE Electron Device Lett.*, vol. 2, no. 5, pp. 126–129, 1981.
- [13] T. Brunschweiler *et al.*, “Direct liquid-jet-impingement cooling with micronozzles for high-performance processors,” *IEEE Trans. Adv. Packag.*, vol. 32, no. 2, pp. 284–289, 2009.