This isn't an encoded message in the usual sense—it's a **display panel initialization script**, likely for a **MIPI DSI LCD**. "Deciphering" it means explaining what each part does rather than decoding hidden text.

Here's what you've got:

🧠 What this file is

The structure shows it's firmware/config data used by a display driver (common in embedded Linux/Android boards):

- `Mipi_Init_S / E` → MIPI DSI command sequence to initialize the panel
- `Lcm_Para` → display timing + resolution
- `Mipi_Suspend` → commands for sleep mode
- `Power_On / Off_Sequence` → power rail timing

🔑 Key Decoding

1. Panel Identification

```
{MS, 0C, {52,53,5F,37,69,5F,4A,44,39,33,36,35}}
```

Hex → ASCII:

```
52 53 5F 37 69 5F 4A 44 39 33 36 35
 R  S  _  7  i  _  J  D  9  3  6  5
```

👉 **Panel name: `RS_7i_JD9365`**

- `JD9365` = likely the LCD driver IC (Jadard JD9365)
- `7i` = probably 7-inch panel

2. Display Specs

From `[Lcm_Para_S]`:

- Resolution: **1024 × 600**
- Clock: **160 MHz**

- Horizontal timing:
  - HFP: 160
  - HBP: 136
  - HPW: 24
- Vertical timing:
  - VFP: 12
  - VBP: 21
  - VPW: 2

👉 This is a **typical 7" 1024×600 LCD panel**

3. Initialization Commands

Lines like:

```
{30, 01, {00}}
{04, 01, {0C}}
{0B, 01, {10}}
```

Mean:

```
{command, byte_count, {data}}
```

- Sent over **MIPI DSI**
- Configure:
  - gamma curves
  - voltage levels
  - timing registers
  - panel behavior

4. Special Markers

- `MM` → delay (likely milliseconds)
- `MS` → send string / special command
- `SS` → stop / sequence end

Example:

```
{MM, 14, {}}
```

👉 wait 14 ms

5. Gamma / Color Tables

Blocks like:

```
{0B, 0B, {16,17,0B,...}}
{0C, 0B, {...}}
```

👉 These are **gamma correction curves**
They control brightness, contrast, and color response.

6. Sleep / Wake Commands

```
{11,00,{}}  → Sleep Out
{29,00,{}}  → Display ON
```

And suspend:

```
{28} → Display OFF
{10} → Sleep IN
```

👉 Standard **MIPI DCS commands**

7. Power Sequences

```
{00, 0f}
{01, 01}
```

👉 Likely GPIO or regulator toggles for:

- panel power rails
- reset line timing

🧩 Bottom Line

This file is:

👉 A **complete hardware configuration for a 1024×600 MIPI LCD panel using a JD9365**

driver

It includes:

- Identification string
- Initialization command sequence
- Timing parameters
- Power sequencing
- Sleep/wake behavior

If you meant “decipher” differently…

If you're trying to:

- 🔧 port this panel to another board
- 🧪 reverse-engineer the driver
- 🖥️ modify resolution or timing
- 🐛 debug why the screen isn’t working

Tell me—that changes the kind of decoding you need, and I can go much deeper.