Y8960

APPLICATION MANUAL

(MSX-MUSIC/AUDIO/SCC/SSG/OPM)

Y8960 APPLICATION MANUAL

2026.10

Contents

Item	Page
Chapter 1 Introduction	3
Chapter 2 Hardware Organization	7
Chapter 3 I/O Map and Memory Map	10
Chapter 4 SSG	21
Chapter 5 OPLL-EX	27
Chapter 6 OPL2 + ADPCM	32
Chapter 7 SCC	41
Chapter 8 OPM	47
Chapter 9 Digital Mixer	53
Chapter 10 System Functions	56
Index	66

Chapter 1 Introduction

1.1 About This Manual

This manual is the programmer's manual for the **Y8960 Cartridge**, a sound cartridge for the MSX. The Y8960 is a sound source module developed as the successor to the Y8950 (MSX-AUDIO), which was widely used as a sound source for the MSX, and the Y8960 Cartridge is a development cartridge for using that Y8960 in an MSX cartridge slot.

This manual is intended for software developers who develop applications and drivers that produce music and sound effects using the Y8960, and focuses on hardware-oriented information such as register specifications and memory maps.

The supported models are MSX, MSX2, MSX2+, and MSX turbo R.

1.2 Notation

This manual uses the following notation.

- Hexadecimal notation for addresses and numeric values is indicated by a trailing `h` (for example, `7FF0h`). Binary numbers may be indicated by a trailing `b`.
- A division of the memory space in 8KB units is called a **BANK**, and the corresponding 8KB entity on the SerialSRAM side is called **BANK#n** (n is the bank number).
- Register read/write access is indicated in the R/W column by `RO` (read-only), `WO` (write-only), and `RW` (read/write).
- "SSG1" and "SSG2" are the names used to distinguish the two built-in SSG cores. SSG1 corresponds to register numbers 00h–0Fh, and SSG2 corresponds to 10h–1Fh.

1.3 Overview of the Y8960

The Y8960 is a sound source in a combo-cartridge configuration that integrates circuits equivalent to multiple sound source chips that have been used on the MSX into a single unit. As the successor to the Y8950, it inherits the conventional MSX-AUDIO compatible functions, while adding more sound sources

and making all of the sound sources stereo.

Stereo support is provided in a form that allows the stereo positioning (pan) to be specified for each channel of every sound source. The output of each sound source is mixed by the digital mixer and output in stereo.

1.4 Block Configuration

The finalized configuration of the Y8960 is as follows.

Block	Count	Description
SSG (YM2149 equivalent)	2	A PSG with 3 tone channels + noise + envelope. With pan for each channel. The two groups can be used independently, for example by separating them for music and for sound effects
OPLL-EX (YM2413 equivalent)	1	9-channel FM + rhythm. With extensions for preset instrument bank switching and pan for each channel
OPL2 (YM3812 equivalent)	1	9-channel FM + rhythm. Two built-in timers and an interrupt. With an extension for pan for each channel
ADPCM (ADPCM-B equivalent)	1	An ADPCM playback circuit controlled through the same register map as the OPL2 (Y8950 compatible). Uses 256KB of dedicated memory
OPM (YM2151 equivalent)	1	8-channel FM. Has L/R output selection for each channel
SCC	1	Waveform memory sound source, 5 channels (A–E). Also handles MegaROM bank control. With an extension for pan for each channel
Digital mixer	1	Mixes the stereo inputs of the five groups above (SSG / OPLL / OPL2+ADPCM / SCC / OPM) and outputs them via I2S
MSX-TIMER	4 core	Timers using an index/value method. With interrupts

Block	Count	Description
	s	
System Controller	1	A management circuit that provides cartridge identification and access to the Config ROM (I/O 40h–4Fh, device ID = 02h)
SerialSRAM	1	512KB. 256KB for program/data and 256KB dedicated to ADPCM
SPI ROM (Config ROM)	1	Part of its contents are copied to SerialSRAM at power-on

1.5 Main Features

- **Two SSG groups built in**: They can be used separately without interfering with each other, for example by separating them for music and for sound effects.
- **Preset instrument bank switching for OPLL-EX**: Four types of instrument ROMs are built in as the preset instruments of the OPLL — OPLL (YM2413) / OPLL-X (YM2423) / OPLL-P (YMF281) / VRC7 — and a bank can be selected for each channel. [TBC] It has not been confirmed whether the VRC7 bank can actually be selected via the bank register (in the RTL, switching is designed to be performed on the bank register side, but whether the VRC7 bank can be selected has not been verified).
- **OPL2+ADPCM is controlled with a Y8950 (MSX-AUDIO) compatible register map**: Existing assets for MSX-AUDIO can be used.
- **All sound sources support stereo**: SSG, OPLL, OPL2, ADPCM, and SCC have pan specification for each channel, and OPM has YM2151-compatible L/R output specification. In the mixer, the volume of each group and the master volume can be adjusted.
- **Control by Memory Mapped I/O**: The normal I/O ports are disabled immediately after power-on, and are enabled for each block through the Memory Mapped I/O procedure (a mechanism based on the same concept as that of the FM-PAC, which also makes it possible to control multiple cartridges individually).
- **Four built-in MSX-TIMER cores**: Equipped with timers with interrupts, which can be used for purposes such as tempo management of music.

For details of each block, see Chapters 4 to 8; for the mixer, see Chapter 9.

Chapter 2 Hardware Organization

2.1 Cartridge Configuration

The Y8960 Cartridge is an MSX cartridge that implements all of the Y8960 circuitry in an FPGA (TangPrimer25K). Internally, it consists broadly of the following elements.

- **Sound source blocks**: SSG×2, OPLL-EX, OPL2, ADPCM, OPM, SCC (see the block configuration table in Chapter 1)
- **Digital mixer**: A time-division mixer that mixes the stereo outputs of the five groups
- **Slot interface**: Conversion between the MSX slot signals and the internal bus, address decoding, and management of the I/O enable
- **SerialSRAM and its peripherals**: 512KB of serial SRAM, an arbiter that arbitrates among the three parties — the CPU (SCC bank) / ADPCM / initialization sequencer — and SCC bank control
- **SPI ROM (Config ROM)**: SPI flash that holds power-on data
- **System Controller**: A management circuit for cartridge identification and Config ROM access
- **I2S output**: A digital audio output that sends the mixer output to the outside
- **Clock generation**: Generates the internal operating clocks using a PLL and divider circuits

2.2 SerialSRAM Organization

The installed memory is SerialSRAM of 512KB. If it is divided into 8KB units and numbered BANK#0–BANK#63, their roles are as follows.

BANK#	Capacity	Role
#0–#15	128KB	BIOS ROM (copied from the Config ROM at power-on)
#16–#31	128KB	RAM (for program/data)
#32–#63	256KB	RAM dedicated to ADPCM

The SerialSRAM address space is divided into two by the most significant bit (A18): A18 = 0 is the 256KB visible from the CPU (BANK#0–BANK#31), and A18 = 1 is the 256KB dedicated to ADPCM. From the CPU,

only the range BANK#0–BANK#31 is visible, through the SCC bank control (Chapter 3). The contents of the ADPCM memory are read and written through the register control of the ADPCM (Chapter 6).

Note that BANK#32–BANK#62 appear from CPU space as mirrors of BANK#0–BANK#30, and BANK#63 becomes the SCC register bank depending on conditions (Chapter 3, Section 3.5). BANK#64 and beyond are not connected.

2.3 Behavior at Power-On

At power-on (startup), the System Controller executes an initialization sequence.

1. It copies the **128KB located at 7E0000h–7FFFFFh of the Config ROM (SPI flash) to SerialSRAM starting at address 00000h**. This becomes the contents of the BIOS ROM in BANK#0–BANK#15.
2. While the copy is in progress, the other modules are stopped, and the MSX itself is also stopped by the /WAIT signal.
3. When the copy ends, the cartridge enters normal operation.

Also, immediately after power-on and immediately after reset, **all of the normal I/O ports of the sound source blocks are disabled**, and the cartridge does not respond to the bus. For the procedure to enable them, see Chapter 3, Section 3.3. Details of the state at reset and the recommended initialization sequence are covered in Chapter 10.

2.4 Audio Output

The output of each sound source is mixed by the digital mixer and output in I2S format, after **24-bit saturation processing**. The I2S configuration is 32-bit slots × 2 channels.

The sampling frequency of I2S is approximately 94.4kHz (obtained by dividing the I2S clock of approximately 24.16MHz generated by the PLL; MCLK is unused). For details, see Chapter 9, Section 9.4.

For the specifications of the mixer's group volume, pan, and master volume, see Chapter 9.

2.5 Clock and Reset

The internal clocks are generated by a PLL (in the implementation, a 171.8MHz system and an approximately 24.16MHz system are generated from an input clock of 28.63636MHz, and a 42.95MHz

system is made by frequency division). The sound source cores are driven by generating enable signals from these clocks so that they operate at timing equivalent to that of the original chips.

When a reset is applied, all of the I/O enables return to disabled (the same state as immediately after power-on).

Chapter 3 I/O Map and Memory Map

3.1 Overview of Access Methods

There are three routes for accessing the Y8960 Cartridge.

1. **Ordinary I/O ports**: A method that uses the I/O addresses assigned to each sound source block. However, immediately after power-on, all of them are disabled, and they cannot be used until they have been enabled by the Memory Mapped I/O procedure (Section 3.3).
2. **Memory Mapped I/O (MMIO)**: A window placed at memory addresses 7FF0h–7FFFh. It provides direct access to the sound source registers, enabling of the I/O ports, and mixer volume settings (Section 3.4).
3. **Memory space**: The SCC also serves as a MegaROM controller, providing bank switching for 4000h–BFFFh and access to the SCC registers (Section 3.5).

3.2 I/O Port Map

I/O address	R / W	Contents
40h–4Fh	R W	System Controller (Section 3.2.4)
7Ch	W O	OPLL register address (MSX-MUSIC compatible)
7Dh	W O	OPLL register data
7Eh	W O	OPM register address
7Fh	R	OPM register data / status

I/O address	R / W	Contents
	W	
A0h	WO	SSG register address (latch)
A1h	WO	SSG register data write (a read returns FFh)
A2h	RO	SSG register data read
A3h	—	[TBC] The formal handling has not been confirmed. In the RTL, a read returns FFh and a write has no effect
B0h	RW	MSX-TIMER: index (bits 3–2 = core selection, bits 1–0 = register selection)
B1h	RW	MSX-TIMER: value of the register pointed to by the index
B2h	RW	MSX-TIMER: interrupt flags (cleared by read / write)
B3h	RW	MSX-TIMER: counter read (a write selects the target core)
C0h	WO	OPL2 register address (MSX-AUDIO compatible)
C1h	RW	OPL2 register data / status

The ADPCM has no independent I/O ports; it is controlled from the OPL2 ports (C0h / C1h) using a register map compatible with the Y8950 (MSX-AUDIO). The SCC likewise has no I/O ports and appears

only in the memory space.

3.2.1 Accessing the SSG

The SSG is accessed using an address latch method.

1. Write the register number to A0h.
2. Write data to A1h, or read data from A2h.

The correspondence between register numbers and target cores is as follows; the two cores share a single address latch.

Register number	Target
00h–0Fh	SSG1 registers (YM2149-compatible registers)
10h–1Fh	SSG2 registers (same as above)
20h–22h / 24h–26h	Gain adjustment registers (SSG1 / SSG2)
28h–2Ah / 2Ch–2Eh	Pan registers (SSG1 / SSG2)

For details of the registers, see Section 4.3 in Chapter 4.

3.2.2 Accessing the OPLL / OPL2 / OPM

All of these use a two-port method: write the register number to the address port, and read or write the value at the data port.

- OPLL: 7Ch (address) / 7Dh (data). The same ports as MSX-MUSIC.
- OPL2: C0h (address) / C1h (data). The same ports as MSX-AUDIO; the status is also read from C1h. The ADPCM registers are also included in this map.
- OPM: 7Eh (address) / 7Fh (data).

3.2.3 Accessing the MSX-TIMER

The MSX-TIMER has four cores, all accessed through the single set of ports B0h–B3h. Write an index to B0h (bits 3–2 select the core, bits 1–0 select the register within the core), and read or write the value of

that register at B1h. B2h holds the interrupt flags for the four cores (cleared by read / write), and B3h reads the counter value of the currently selected core. For the timer specifications and interrupts, see Section 10.2 in Chapter 10.

3.2.4 System Controller

The System Controller is a management circuit connected to I/O 40h–4Fh, and provides identification of the cartridge and reads and writes to the Config ROM. Independently of the sound sources, it can be accessed from immediately after power-on.

I/O address	Contents
40h	Enabler. Writing 80h enables it. After it has been enabled, a read returns 7Fh (all bits of 80h inverted), and the program recognizes the presence of the System Controller by this. Until it is enabled, reads of 40h–4Fh are not responded to
41h	Device Select. Write the device ID. The ID of the Y8960 Cartridge is **02h**. Only when its own ID has been written does it return the inverted value (FDh) on read. For other IDs it does not respond (to avoid bus contention with other devices)
42h	Function Select. 01h = Config ROM Reader/Writer. When read in the correctly selected state, FEh is returned
43h–45h	Config ROM address (lower / middle / upper 8 bits)
46h	Command (00h = read, 01h = write, 02h = sector erase (in 64KB units), 03h = chip erase, 04h = status read. A read returns FFh)
47h	Data. Read / status results are read from this port after the command has completed. Bit 0 of the status is BUSY
48h–4Fh	Reserved. Does not respond to reads or writes

While a command is executing (a few µs), I/O accesses to the System Controller cannot be accepted (no WAIT is issued). After writing a command to 46h, repeat reads until 40h returns 7Fh before performing the next access.


3.3 State at Power-On and Enabling the I/O Ports


Immediately after power-on and immediately after a reset, **all of the ordinary I/O ports of the sound source blocks are disabled**, and the cartridge does not respond to those addresses. This is a specification to avoid conflicts with other sound devices, and is based on the same approach as the Panasonic FM-PAC.

Enabling is performed block by block by writing to Memory Mapped I/O **I/O Enabler1 (7FF6h)** and **I/O Enabler2 (7FFFh)**.

Address	Bit	Block enabled
7FF6h (Enabler1)	b0	OPLL
7FFFh (Enabler2)	b0	OPL2 (+ADPCM)
	b1	SSG
	b2	OPM
	b7	MSX-TIMER

Writing 1 to a bit enables it; writing 0 returns it to disabled. Enabler2 can also be read, so the current settings can be read back.





Note that MMIO itself is an access to the cartridge's memory space, so even when multiple Y8960 Cartridges are installed, each cartridge can be enabled and controlled individually (the I/O ports of a cartridge that has not been enabled remain disabled, so there is no conflict in the I/O space either).

3.4 Memory-Mapped I/O (7FF0h–7FFFh)

MMIO is a 16-byte window at memory addresses 7FF0h–7FFFh. Except for 7FFFh, it is write-only. This window can be used only **when RAM mode = 0, or when a ROM bank (BANK#0–#15) is mapped into BANK1** (Section 3.5).

Address	R/W	Contents
7FF0h	WO	SSG register address
7FF1h	WO	SSG register data write
7FF2h	WO	OPL2 register address
7FF3h	WO	OPL2 register data
7FF4h	WO	OPLL register address
7FF5h	WO	OPLL register data
7FF6h	WO	I/O Enabler1 (b0 = OPLL)
7FF7h	WO	SSG volume

Address	R/W	Contents
7FF8h	WO	OPLL volume
7FF9h	WO	OPL2 volume
7FFAh	WO	SCC volume
7FFBh	WO	OPM register address
7FFCh	WO	OPM register data
7FFDh	WO	OPM volume
7FFEh	WO	Master volume
7FFFh	RW	I/O Enabler2 (b7 = TIMER, b2 = OPM, b1 = SSG, b0 = OPL2)

All volumes are 8-bit values: 0 = OFF, 128 = MAX. For details of the mixer, see Chapter 9.

Register accesses via MMIO can be used at any time, regardless of whether the ordinary I/O ports are enabled or disabled. This is convenient when you want to initialize the sound sources before enabling the I/O ports, such as during driver initialization.

3.5 Memory Map and Bank Control

3.5.1 Bank Organization

The CPU memory space 4000h–BFFFh is divided into four banks of 8KB each.

CPU address	Bank name
4000h–5FFFh	BANK0
6000h–7FFFh	BANK1

CPU address	Bank name
8000h–9FFFh	BANK2
A000h–BFFFh	BANK3

Each bank has a bank register; writing a value n maps SerialSRAM BANK#n into that bank. The contents of BANK#n are as described in Section 2.2 in Chapter 2 (#0–#15 = ROM, #16–#31 = RAM), and the upper bank numbers are handled as follows.

Bank number	Handling
#32–#62	Mirrors of BANK#0–#30
#63	The SCC register bank when the conditions are met (Section 3.5.3). Otherwise, a mirror of BANK#31
#64–#255	Not connected

Reading a bank register address returns the currently selected bank number.

BANK0 is read-only. Even if a RAM bank (#16–#31) is mapped in, writes to BANK0 do not reach the SRAM (except for writes to the RAM mode register, described below).

3.5.2 RAM Mode and Bank Register Layout

The placement of the bank registers changes depending on the RAM mode (compatible mode / RAM mode). At power-on, RAM mode = 0 (compatible mode).

Bank registers for RAM mode = 0 (compatible mode):

Address	Contents
5000h–57FFh	BANK0 bank register
7000h–77FFh	BANK1 bank register

Address	Contents
9000h–97FFh	BANK2 bank register
B000h–B7FFh	BANK3 bank register

Switching to **RAM mode = 1** is done by writing 1 to **b0 of address 4XFBh (X = 8–F)**. In RAM mode, the layout changes as follows.

Address	Contents
4XFBh	BANK mode register (b0: 0 = compatible mode, 1 = RAM mode). Always present
4XFCh	BANK0 bank register
4XFDh	BANK1 bank register
4XFEh	BANK2 bank register
4XFFh	BANK3 bank register

In RAM mode, writes to BANK1–BANK3 reach the SRAM, and the SCC register bank can also be mapped into BANK1. Note that writes to the RAM mode register and to the bank registers themselves are not written into the contents of the currently mapped BANK#.

3.5.3 SCC Register Bank

When BANK#63 is mapped in, that bank becomes the SCC register bank. The location where it appears differs depending on the RAM mode.

Condition	Address where the SCC registers appear
RAM mode = 0, BANK#63 in BANK2	9800h–9FFFh (addresses shown as 9xxxh)
RAM mode = 1, BANK#63 in BANK1	7800h–7FFFh (addresses shown as 7xxxh)

Overview of the register layout (for 9xxxh; for 7xxxh, the top digit becomes 7):

Address	R/W	Contents
9800h–981Fh	RW	Ch.A waveform memory (32 bytes)
9820h–983Fh	RW	Ch.B waveform memory
9840h–985Fh	RW	Ch.C waveform memory
9860h–987Fh	RW	Ch.D/E waveform memory
9880h–9889h	WO	Frequency registers for each channel
988Ah–988Eh	WO	Volume registers for each channel
988Fh	WO	Output switch
9890h–989Fh	WO	Mirrors of 9880h–988Fh
98E0h–98FFh	WO	Mode register (implemented as a single byte)
9900h–9904h	WO	Stereo positioning (pan) for Ch.A–E. 1 = leftmost, 128 = center, 255 = rightmost. Default 128
9905h–9FFFh	—	Unused (access prohibited; reserved for future use)

For write-only registers such as the frequency and volume registers, there is no guarantee that a value

will be returned when they are read. For details of the SCC registers, see Section 7.3 in Chapter 7.

Chapter 4 SSG

4.1 Overview

The Y8960 contains **two** SSG cores equivalent to the YM2149 (AY-3-8910 compatible). In this manual, the first core is called **SSG1** and the second **SSG2**. Each core has three tone channels (A / B / C), one noise generator group, and one envelope generator group, and its register configuration and basic operation are compatible with the YM2149.

The two cores operate simultaneously at all times, and their outputs are summed and sent to the SSG input of the mixer. The two-core arrangement is intended for uses such as assigning one core to music and the other to sound effects. Which core is assigned to which purpose is up to the software, and there is no distinction in hardware. Note, however, that as described below, registers can be read only on the SSG2 side.

The Y8960 extensions are the following two points.

- **Per-channel stereo positioning (pan)**: An 8-bit pan can be specified for each of channels A / B / C, so the left/right positioning can be varied per channel (Section 4.6).
- **Per-channel gain**: The output level of each channel can be adjusted with 8 bits (Section 4.6).

4.2 Access Methods

4.2.1 I/O Ports

The SSG is accessed through I/O ports A0h–A3h. The two cores share a single register address space (Section 4.3), and the roles of the ports are as follows.

Port	R/W	Function
A0h	W	Specifies the register address
A1h	W	Writes to a register (reads return FFh)
A2h	R	Reads from a register

Port	R/W	Function
A3h	—	Reserved. Accessing it has no effect (reads return FFh)

To write, write the register address to A0h, then write the data to A1h. To read, write the register address to A0h, then read A2h.

Note that immediately after power-on, the SSG I/O ports are disabled. To use them, the I/O enable (the SSG bit of MMIO 7FFFh) must be set to 1 to enable them (see Chapter 3).

4.2.2 Memory-Mapped I/O (Mirror)

The same register access can also be performed through memory-mapped I/O 7FF0h / 7FF1h.

Address	R/W	Function
7FF0h	W	Specifies the register address (same as A0h)
7FF1h	W	Writes to a register (same as A1h)

The mirror side is write-only and cannot be read. For the memory-state conditions under which the mirror is available, see Chapter 3.

4.3 Register Map

The register address is 6 bits, and the basic registers and extended registers of SSG1 / SSG2 are arranged in a single space.

Address	Target	Contents
00h–0Fh	SSG1	Basic registers (Table 4.2)
10h–1Fh	SSG2	Basic registers (same configuration as Table 4.2)
20h–22h	SSG1	Per-channel gain A / B / C (Section 4.6)

Address	Target	Contents
23h	—	Not connected
24h–26h	SSG2	Per-channel gain A / B / C (Section 4.6)
27h	—	Not connected
28h–2Ah	SSG1	Per-channel pan A / B / C (Section 4.6)
2Bh	—	Not connected
2Ch–2Eh	SSG2	Per-channel pan A / B / C (Section 4.6)
2Fh	—	Not connected
30h–EFh	—	Not connected

Read availability: Reading (via A2h) is possible only for **the SSG2-side registers (10h–1Fh, 24h–26h, 2Ch–2Eh)**; all SSG1-side registers are write-only. Specifying an SSG1-side address and reading returns FFh.

Table 4.2 Basic registers (SSG1 uses offset +00h, SSG2 uses offset +10h)

Offset	Contents	Bit configuration
00h	Ch.A tone divider, low	Divider [7:0]
01h	Ch.A tone divider, high	Divider [11:8]
02h	Ch.B tone divider, low	Divider [7:0]
03h	Ch.B tone divider, high	Divider [11:8]
04h	Ch.C tone divider, low	Divider [7:0]
05h	Ch.C tone divider, high	Divider [11:8]

Offset	Contents	Bit configuration
06h	Noise divider	Divider [4:0]
07h	Mixer / I/O control (/ENABLE)	b7: IOB, b6: IOA, b5: NC, b4: NB, b3: NA, b2: TC, b1: TB, b0: TA
08h	Ch.A volume	b4: M (envelope select), b3–b0: volume
09h	Ch.B volume	b4: M, b3–b0: volume
0Ah	Ch.C volume	b4: M, b3–b0: volume
0Bh	Envelope period, low	Period [7:0]
0Ch	Envelope period, high	Period [15:8]
0Dh	Envelope shape	b3: CONT, b2: ATT, b1: ALT, b0: HOLD
0Eh	I/O port A	GPIO (Section 4.5)
0Fh	I/O port B	GPIO (Section 4.5)

4.4 Functions of the Basic Registers

The basic registers operate in the same way as on the YM2149. Only the key points are given here.

- **Tone divider (00h–05h)**: Specifies the period of each channel's square wave with 12 bits. The larger the value, the lower the pitch.
- **Noise divider (06h)**: Specifies the noise period with 5 bits. The noise is shared by the three channels.
- **Mixer / I/O control (07h)**: TA / TB / TC enable the tone output of each channel, and NA / NB / NC enable the noise output to each channel; in both cases, **0 enables and 1 disables** (negative logic). IOA / IOB specify the direction of I/O ports A / B: 0 is input and 1 is output.
- **Volume (08h–0Ah)**: The lower 4 bits specify the volume in 16 steps. When the M bit is 1, that

channel's volume follows the output of the envelope generator.

- **Envelope period (0Bh, 0Ch)**: Specifies the envelope period with 16 bits.
- **Envelope shape (0Dh)**: The combination of CONT / ATT / ALT / HOLD selects the shape. Writing to this register restarts the envelope from the beginning.

4.5 I/O Ports (GPIO)

Registers 0Eh / 0Fh of each core are general-purpose I/O ports A / B. Their connections on the cartridge are as follows.

Core	Port A (0Eh / 1Eh)	Port B (0Fh / 1Fh)
SSG1	Not connected	Not connected
SSG2	Input: the cartridge DIP switches (lower 2 bits; the upper bits are 0)	Not connected (the output is not connected)

By reading SSG2 port A, the setting state of the DIP switches can be obtained. Keep the IOA bit of 07h / 17h at 0 (input).

4.6 Y8960 Extended Registers

4.6.1 Per-Channel Gain (20h–26h)

These registers adjust the final output level of each channel with 8 bits (SSG1: A = 20h, B = 21h, C = 22h; SSG2: A = 24h, B = 25h, C = 26h).

- The value range is 0–128, with **128 being the maximum** (unity gain); 0 produces silence.
- The default is 128.
- Because this gain acts on the output stage of the core, it also affects channels for which the envelope is selected in the volume register. It can be used to fine-tune, per channel, the balance of a sound created with the 4-bit volume (plus envelope).

On the mixer side there is also a volume for the SSG group as a whole (MMIO 7FF7h, 0 = OFF to 128 =

MAX). The roles are divided as follows: the per-channel gain adjusts each channel, and the mixer volume adjusts the SSG group as a whole (see the chapter on the digital mixer).

4.6.2 Per-Channel Pan (28h–2Eh)

These registers specify the stereo positioning of each channel with 8 bits (SSG1: A = 28h, B = 29h, C = 2Ah; SSG2: A = 2Ch, B = 2Dh, C = 2Eh).

- **1 is the far left, 128 is center, and 255 is the far right.**
- The default is 128 (center).
- Noise and the envelope are constituent elements of a channel, and the pan and gain set for that channel apply to them as they are.

Since earlier SSG sound sources were monaural, playing existing music data as it is reproduces all channels positioned at center. By panning each channel, playback with a stereo image becomes possible.

Chapter 5 OPLL-EX

5.1 Overview

OPLL-EX is an FM sound source equivalent to the YM2413 (OPLL). It is configured either as 9 melody channels, or as 6 melody channels + 5 rhythm sounds (bass drum, snare drum, tom-tom, top cymbal, and hi-hat). Its register configuration and basic operation are compatible with the YM2413, so the software assets of MSX-MUSIC can be used as they are.

The Y8960 extensions are the following two points, and this extended version is called OPLL-EX.

- **Addition of preset instrument banks**: In addition to the genuine YM2413 preset instruments, it contains the preset instrument sets of the OPLL-X (YM2423), the OPLL-P (YMF281), and the VRC7, which can be switched per channel (Section 5.4).
- **Per-channel stereo positioning (pan)**: An 8-bit pan can be specified for each of the 9 channels (Section 5.6). Since the YM2413 had monaural output, this is an extension unique to the Y8960.

5.2 Access Methods

5.2.1 I/O Ports

Port	R/W	Function
7Ch	W	Specifies the register address
7Dh	W	Writes to a register

The OPLL registers cannot be read. To write, write the register address to 7Ch, then write the data to 7Dh.

Immediately after power-on, the OPLL I/O ports are disabled. To use them, I/O Enabler 1 (the OPLL bit of MMIO 7FF6h) must be set to 1 to enable them (see Chapter 3).

5.2.2 Memory-Mapped I/O (Mirror)

Address	R/W	Function
7FF4h	W	Specifies the register address (same as 7Ch)
7FF5h	W	Writes to a register (same as 7Dh)

For the memory-state conditions under which the mirror is available, see Chapter 3.

[TBC] The specified values for the wait required when writing to a register (the waiting time after writing the address and after writing the data). The original chip, the YM2413, has specified values, but whether the same wait is required in the Y8960 implementation has not been confirmed.

5.3 Register Map

All registers are write-only. 00h–38h is the YM2413-compatible part, and 40h–48h and 50h–58h are registers newly added in the Y8960.

Address	Contents	Main bit configuration
00h	User instrument: modulator characteristics	AM, VIB, EGT, KSR, MULTI [3:0]
01h	User instrument: carrier characteristics	AM, VIB, EGT, KSR, MULTI [3:0]
02h	User instrument: modulator output level	KSL [7:6], TL [5:0]
03h	User instrument: modulation depth / feedback	KSL [7:6], DC, DM, FB [2:0]
04h	User instrument: modulator EG	AR [7:4], DR [3:0]
05h	User instrument: carrier EG	AR [7:4], DR [3:0]

Address	Contents	Main bit configuration
06h	User instrument: modulator EG	SL [7:4], RR [3:0]
07h	User instrument: carrier EG	SL [7:4], RR [3:0]
08h–0Dh	Unused	—
0Eh	Rhythm control	b5: R (rhythm mode), b4: BD, b3: SD, b2: TOM, b1: TC, b0: HH (key-on for each rhythm sound)
0Fh	Test	Always write 0
10h–18h	Ch.1–9 F-number, low	F# [7:0]
19h–1Fh	Unused	—
20h–28h	Ch.1–9 control	SUS [5], KEY [4], BLOCK [3:1], F# [0] (most significant bit)
29h–2Fh	Unused	—
30h–38h	Ch.1–9 instrument / volume	INST [7:4] (instrument number), VOL [3:0] (volume)
39h–3Fh	Unused	—
40h–48h	**Ch.1–9 preset instrument bank (new)**	BANK [1:0] (Section 5.4)

Address	Contents	Main bit configuration
49h–4Fh	Unused	—
50h–58h	**Ch.1–9 pan (new)**	PAN [7:0] (Section 5.6)
59h–FFh	Unused	—

The meaning of each register is the same as on the YM2413. For details of the instrument parameters and the relationship between the F-number and pitch, refer to the YM2413 documentation. Note that for VOL in 30h–38h, the smaller the value, the larger the volume (0 is the maximum).

5.4 Preset Instrument Banks

The preset instruments of the YM2413 family differ in content from chip to chip. The OPLL-EX contains the following four kinds of preset instrument sets (banks).

Bank	Contents
OPLL	The preset instruments of the YM2413
OPLL-X	The preset instruments of the YM2423
OPLL-P	The preset instruments of the YMF281
VRC7	The preset instruments of the VRC7

For each channel, the **BANK (lower 2 bits)** of the additional registers 40h–48h (40h for Ch.1, ⋯, 48h for Ch.9) selects the bank that the channel uses. INST (the instrument number) in 30h–38h points to a preset instrument within the selected bank. The user instrument with INST = 0 (the instrument defined in 00h–07h) is common regardless of the bank.



Select the preset instrument bank used for each channel

Because the bank can be changed per channel, mixed use is possible, for example using VRC7 instruments for the melody and YM2413 instruments for the accompaniment.

[TBC] The correspondence between the BANK values (0–3) and the four kinds of bank (OPLL / OPLL-X / OPLL-P / VRC7). It has been confirmed that, in the implementation, switching of the preset instrument ROM is designed to be performed by the BANK register, but the correspondence table between values and bank names has not been finalized. It has also not been confirmed whether the VRC7 bank can actually be selected via the BANK register (the ALTPATCH_EN pin of IKAOPLL is fixed to the disabled side, and switching via the pin is not used).

5.5 Rhythm Mode

Setting the R bit of register 0Eh to 1 enters rhythm mode, and melody Ch.7–9 are replaced by rhythm sounds (BD / SD / TOM / TC / HH). Sound generation for each rhythm sound is performed with the corresponding bit of 0Eh, and the instrument and volume follow the INST / VOL specification of the corresponding channel (Ch.7–9). Operation is the same as on the YM2413.

5.6 Stereo Positioning (Pan)

The additional registers 50h–58h (50h for Ch.1, ⋯, 58h for Ch.9) specify the stereo positioning for each channel.

- **1 is the far left, 128 is center, and 255 is the far right.**
- The default is 128 (center).

On the mixer side there is also a volume for the OPLL group as a whole (MMIO 7FF8h, 0 = OFF to 128 = MAX) (see the chapter on the digital mixer).

[TBC] In rhythm mode, which registers the pan of the five rhythm sounds follows (whether they share the pan of Ch.7–9, 56h–58h) has not been confirmed.

Chapter 6 OPL2 + ADPCM

6.1 Overview

This block combines an FM sound source equivalent to the YM3812 (OPL2) with an ADPCM playback section equivalent to ADPCM-B. Its register map is configured to be **compatible with the MSX-AUDIO (Y8950)**, so existing software written for the MSX-AUDIO can be used.

- **FM section**: 2-operator FM, 9 channels. In rhythm mode, 6 melody channels + 5 rhythm sounds. It contains two timers (Timer 1 / Timer 2) and can generate interrupts. The Y8960 implementation uses a stereo-output core, and per-channel panning has been added as an extension (Section 6.7).
- **ADPCM section**: Sample playback using the ADPCM-B method. It has a dedicated 256KB memory, and plays back waveform data stored in memory using delta modulation. The data port for recording and for memory read/write is also located at the same addresses as on the Y8950.

The outputs of the FM section and the ADPCM section are summed and saturated within the block, and are combined into a single group as the mixer's "OPL2" input. The mixer volume and pan are therefore common to the FM section and the ADPCM section (panning per channel can be set individually in each section).

The functions that existed on the Y8950 but were abolished on the Y8960 (keyboard I/O, the prescaler, direct DAC output, and so on) are listed in Section 6.5.

6.2 Access Methods

6.2.1 I/O Ports

Port	R/W	Function
C0h	W	Specifies the register address
C0h	R	Reads the status register (Section 6.3)

Port	R/W	Function
C1h	W	Writes to a register

To write, write the register address to C0h, then write the data to C1h. The register values themselves cannot be read back.

Immediately after power-on, the OPL2 I/O ports are disabled. To use them, set the OPL2 bit of I/O Enabler 2 (MMIO 7FFFh) to 1 to enable them (see Chapter 3).

6.2.2 Memory-Mapped I/O (Mirror)

Address	R/W	Function
7FF2h	W	Specifies the register address (same as C0h)
7FF3h	W	Writes to a register (same as C1h)

The mirror side is write-only, and the status cannot be read from it. For the memory-state conditions under which the mirror can be used, see Chapter 3.

[TBC] The specified wait times required when writing registers (the wait after writing an address and after writing data). The original chips, the YM3812 / Y8950, have specified values, but whether the same waits are required in the Y8960 implementation has not been confirmed.

6.3 Status Register

Reading C0h returns the status register. It is used to check interrupt sources.

Bit	Name	Meaning
b7	INT	An interrupt has occurred (one of the flags is set and interrupts are enabled)
b6	T1	Timer 1 flag
b5	T2	Timer 2 flag

Bit	Name	Meaning
b4	EOS	The ADPCM has reached the stop address
b3	BUF_RDY	Buffer ready (the ADPCM data register can be accessed)
b2–b1	—	Fixed at 1
b0	PCM_BSY	1 while playing (while START of Control 1 is set)

Flags are masked and cleared using register 04h (flag control) (Section 6.4). For the handling of interrupts as a whole, see the chapter on interrupts.

The ADPCM-related flags behave as follows.

- Immediately after reset, the EOS / BUF_RDY flags are both masked, and the status reads 06h (no interrupt is raised by the ADPCM either). The masks are released with register 04h.
- EOS is set when playback reaches the stop address. In repeat playback, it is also set at the end of each loop.
- When non-repeat playback ends, START and the other bits of Control 1 are cleared automatically, and PCM_BSY also returns to 0.
- BUF_RDY stays 1 while idle and in memory transfer modes. During reads and writes through the data register, it is 0 until the access to the SRAM completes.

6.4 FM Section Registers

All registers are write-only. The address layout of the FM section is the same as that of the YM3812; for the meaning of each parameter, refer to the YM3812 documentation. This section shows the layout on the Y8960 and the timer/flag-related registers.

Address	Contents	Main bit composition
01h	Test	Test register. Normally write 0
02h	Timer 1	Counter value (8 bits)

Address	Contents	Main bit composition
03h	Timer 2	Counter value (8 bits)
04h	Flag control	b7: IRQRST (flag reset), b6: T1MSK, b5: T2MSK, b4: MSKEDS (EOS mask), b3: MSKBR (BUF mask), b1: ST2 (start Timer 2), b0: ST1 (start Timer 1)
08h	CSM / note select	b7: CSM (composite sine wave mode), b6: NSEL. Shared with ADPCM Control 2 (Section 6.5)
20h–35h	Operator characteristics 1	AM, VIB, EGT, KSR, MULTI [3:0]
40h–55h	Operator characteristics 2	KSL [7:6], TL [5:0]
60h–75h	Operator EG 1	AR [7:4], DR [3:0]
80h–95h	Operator EG 2	SL [7:4], RR [3:0]
A0h–A8h	Ch.1–9 F-number low byte	F# [7:0]
B0h–B8h	Ch.1–9 control	KON [5], BLOCK [4:2], F# [1:0]
BDh	Rhythm / AM/VIB depth	AM depth [7], VIB depth [6], R (rhythm mode) [5], BD [4], SD [3], TOM [2], TC [1], HH [0]
C0h–C8h	Ch.1–9 connection	FB [3:1], C (algorithm) [0]
E0h–	Operator	WS [1:0] (selects from 4 waveforms)

Address	Contents	Main bit composition
F5h	waveform select	


In rhythm mode (the R bit of BDh = 1), melody Ch.7–9 are replaced by rhythm sounds. The operation is the same as on the YM3812.

6.5 ADPCM Section Registers

The registers of the ADPCM section are laid out at the same addresses as on the Y8950.

Address	R/W	Contents	Bit composition / description
07h	W	Control 1	b7: START (starts memory playback), b6: REC (for recording, but recording is not supported on the Y8960; used to select the memory write mode), b5: MEMD (data source select: 1 = memory, 0 = data register), b4: REPT (repeat playback), b3: SPOFF (1 stops the ADPCM output), b0: RST (resets the flags and counters)
08h	W	Control 2	b1: 64K, b0: ROM (memory type specification; see the text for their effects). SMPL / DA/AD have no effect. Shares its address with the FM section's CSM / NSEL
09h	W	Start address low byte	Address [7:0]
0Ah	W	Start address high byte	Address [15:8] (Section 6.6)
0Bh	W	Stop address low byte	Address [7:0]
0Ch	W	Stop	Address [15:8] (Section 6.6)

Address	R / W	Contents	Bit composition / description
		address high byte	
0Fh	R W	ADPCM data	Data port used to read and write the ADPCM memory (Section 6.6)
10h	W	DELTA-N low byte	Playback rate [7:0]
11h	W	DELTA-N high byte	Playback rate [15:8]
12h	W	EG control	Envelope control of the playback level



Abolished registers

The following Y8950 functions do not exist on the Y8960. Writing to them has no effect.

Address	Function on the Y8950	Notes
05h / 06h	Keyboard input/output	Abolished

Address	Function on the Y8950	Notes
0Dh / 0Eh	Prescaler	Abolished (the playback rate is set directly with DELTA-N)
15h / 16h	DAC data	Abolished
17h	Shift register	Abolished
18h / 19h / 1Ah	I/O control, I/O data, PCM data	Abolished

The memory type specification of register 08h is effective on the Y8960 as well. When **64K** is set, memory access addresses are masked to the lower 16 bits and wrap around within a 64KB range. When **ROM** is set, memory reads return 0 and writes are ignored (emulating a ROM bank). The SMPL / DA/AD bits have no effect, and playback that supplies samples directly through the data register (CPU direct synthesis) is not supported.

Recording (REC) is not supported. Setting START and REC does not record anything, and there is no analog input path. The REC bit is used only to select the memory write mode (Section 6.6).

6.6 ADPCM Memory

The ADPCM section has a **dedicated 256KB memory** within the SerialSRAM. This area is separate from the CPU bank area (BANK#0–31), and its size and configuration cannot be switched (fixed).

- **Address specification**: The start address (09h / 0Ah) and the stop address (0Bh / 0Ch) are specified in **units of 4 bytes**. The 16-bit value written to the registers × 4 gives the byte address, so the entire 256KB can be addressed. Playback and transfers cover the range from start address × 4 to stop address × 4 + 3; the stop side includes its last 4 bytes.
- **Playback**: When START is set (MEMD = 1, REC = 0), data is read out in sequence from the start address to the stop address and played back. When REPT is set, playback returns to the start address after reaching the stop address and repeats. When the stop address is reached, the EOS flag in the status is set. Playback is from memory only; direct playback through the data register is not supported.
- **Reading and writing from the CPU**: Performed through register 0Fh (ADPCM data). In write

mode (START = 0, REC = 1, MEMD = 1), each write to 0Fh automatically advances the internal address; when the end of the stop address is reached, the EOS flag is set and the pointer returns to the start address (writes beyond the end are ignored). In read mode (START = 0, REC = 0, MEMD = 1), the first two reads after setting Control 1 are dummy reads, and the prefetched data is returned from the third read on. Reading past the stop address returns 0 and sets the EOS flag. Before starting a read or write, set the start/stop addresses and MEMD and the other bits of Control 1. The BUF_RDY flag in the status indicates whether data transfer is possible.

- **Playback rate**: Set with DELTA-N (10h / 11h, 16 bits). The larger the value, the faster the playback (the higher the sampling rate).
- Memory access from the CPU is possible even during playback; accesses to the SRAM are arbitrated internally.

6.7 Pan and Volume

6.7.1 Per-Channel Pan (New)

These registers are new on the Y8960 and specify the stereo positioning for each channel.

Address	Contents
F6h–FEh	Pan of FM Ch.1–9
FFh	Pan of the ADPCM

- **1 is the far left, 128 is the center, and 255 is the far right**.
- The default is 128 (center).

6.7.2 Group Volume

On the mixer side there is a volume for the OPL2 group (the sum of the FM section + the ADPCM section) (MMIO 7FF9h, 0 = OFF – 128 = MAX) (see the chapter on the digital mixer). The division of roles is that the volume of each channel is adjusted with the FM section's TL or the ADPCM's EG control, and the volume of the group as a whole is adjusted with the mixer volume.

6.8 Interrupts

This block has, as interrupt sources, the timeouts of Timer 1 / Timer 2 and the ADPCM's EOS and BUF. Each flag can be masked with register 04h, and when a flag is set and an unmasked source exists, the interrupt signal is asserted. For details, see the chapter on interrupts.

Chapter 7 SCC

This chapter describes the SCC (waveform memory sound source) built into the Y8960 and its registers. The SCC is a block dedicated to memory-mapped I/O, and it also handles the bank control of the MegaROM. The bank control mechanism itself was described in Chapter 3, "3.5 Memory Map and Bank Control". This chapter mainly covers the registers as a sound source, and touches on bank control only within the scope related to the sound source.

7.1 Overview

The SCC of the Y8960 is based on IKASCC (a reproduction core of the Konami SCC). Its main specifications are as follows.

- Waveform memory sound source with 5 channels (Ch.A–Ch.E)
- Each channel has 32 bytes of waveform memory and produces sound by repeatedly reading out its contents. However, Ch.D and Ch.E share a single waveform memory (the same configuration as the original SCC)
- A frequency (12-bit period value) and a volume (4 bits) can be set for each channel
- As an extension unique to the Y8960, stereo positioning (pan) can be specified for each channel (Section 7.7)
- It also handles MegaROM bank control (the SCC banks), and has the role of making the cartridge's SerialSRAM appear in the MSX memory space

No I/O ports are assigned to the SCC. All registers are accessed by making the SCC register bank appear in the memory space.

7.2 How the SCC Register Bank Appears

The SCC registers appear within the bank in which BANK#63 has been made to appear (see Chapter 3, Section 3.5.3).

Condition	Where it appears	Base address of the registers
BANK#63 made to appear in BANK2 with RAM mode = 0	8000h–9FFFh	9800h–9FFFh
BANK#63 made to appear in BANK1 with RAM mode = 1	6000h–7FFFh	7800h–7FFFh

In the following description, the addresses for the case where it is made to appear in BANK2 (98xxh) are mainly used; for BANK1, read them as 78xxh.

7.3 Register Map

The arrangement of the registers within the SCC register bank is as follows. Addresses are given in the order: when appearing in BANK2 / when appearing in BANK1.

Address	R/W	Contents
9800h–981Fh / 7800h–781Fh	R/W	Ch.A waveform memory (32 bytes)
9820h–983Fh / 7820h–783Fh	R/W	Ch.B waveform memory (32 bytes)
9840h–985Fh / 7840h–785Fh	R/W	Ch.C waveform memory (32 bytes)
9860h–987Fh / 7860h–787Fh	R/W	Ch.D/Ch.E waveform memory (32 bytes, shared)
9880h–9881h / 7880h–7881h	W	Ch.A frequency register
9882h–9883h / 7882h–7883h	W	Ch.B frequency register
9884h–9885h / 7884h–7885h	W	Ch.C frequency register
9886h–9887h / 7886h–7887h	W	Ch.D frequency register
9888h–9889h / 7888h–7889h	W	Ch.E frequency register
988Ah / 788Ah	W	Ch.A volume

Address	R/W	Contents
988Bh / 788Bh	W	Ch.B volume
988Ch / 788Ch	W	Ch.C volume
988Dh / 788Dh	W	Ch.D volume
988Eh / 788Eh	W	Ch.E volume
988Fh / 788Fh	W	Output switch
9890h–989Fh / 7890h–789Fh	W	Mirror of 9880h–988Fh
98A0h–98BFh / 78A0h–78BFh	—	Unused (do not access)
98C0h–98DFh / 78C0h–78DFh	—	Unused (do not access)
98E0h–98FFh / 78E0h–78FFh	W	Mode register (a single byte in substance)
9900h / 7900h	W	Ch.A stereo positioning (pan)
9901h / 7901h	W	Ch.B stereo positioning (pan)
9902h / 7902h	W	Ch.C stereo positioning (pan)
9903h / 7903h	W	Ch.D stereo positioning (pan)
9904h / 7904h	W	Ch.E stereo positioning (pan)
9905h–9FFFh / 7905h–7FEFh	—	Unused (do not access. Reserved for the future)

Registers other than the waveform memory are write-only. The result of reading them is undefined. Do not read from or write to the regions marked "do not access".

7.4 Waveform Memory

The waveform memory of each channel is 32 bytes and stores signed waveform data of 8 bits per sample. While sound is being generated, the channel repeatedly reads out the waveform memory from the beginning and outputs it as a waveform of 32 samples per period.

- The waveform memory can be read and written. If it is rewritten during sound generation, the waveform changes from that point on
- Ch.D and Ch.E share the waveform memory. Writing to 9860h–987Fh changes the instrument of both channels at the same time. To give them independent waveforms, some contrivance is needed, such as using only one of the channels

7.5 Frequency Registers and Volume

The frequency register is 2 bytes per channel: the lower 8 bits of the period value are written to the lower address, and the upper 4 bits to the upper address (a 12-bit value).

The sound generation frequency is determined by the following formula, as on the original SCC.

$$\text{Sound generation frequency} = 3.579545\ \text{MHz} \div (32 \times (\text{period value} + 1))$$

The larger the period value, the lower the sound.


The volume register is 1 byte per channel, of which the lower 4 bits are valid (0 = silence, 15 = maximum).

7.6 Output Switch

The output switch at 988Fh controls the output on/off of each channel.

Bit	Target	Meaning
bit0	Ch.A	1 = output on, 0 = output off
bit1	Ch.B	Same as above
bit2	Ch.C	Same as above

Bit	Target	Meaning
bit3	Ch.D	Same as above
bit4	Ch.E	Same as above
bit7–5	—	Not used



The value at reset is all bits 0, with all channels' output off. Setting only the frequency and volume does not produce sound. Set the bit of the channel to be sounded to 1.

7.7 Stereo Positioning (Pan)

9900h–9904h are per-channel stereo positioning registers added in the Y8960. The positioning is specified with 8 bits for each channel.

- 1 = far left
- 128 = center (the initial value at reset)
- 255 = far right

They are write-only (the read result is undefined). At reset, all channels return to 128 (center).

7.8 Mode Register

98E0h–98FFh is the mode register. The substance is a single byte for the entire region, and writing to any address within the range updates the same register. This corresponds to the test-related registers of the original SCC, and a normal performance program does not need to rewrite it (use it with the reset value of 00h as it is).

- [TBC] The function definition of each bit of the mode register is not given in the current specification documents. Details will be added to this section as they become known.

7.9 Relationship to Bank Control

The SCC core is a sound source and, at the same time, is responsible for the memory bank control of the entire cartridge. Only the programming points are listed here. For details, see Chapter 3, Section 3.5.

- There are four banks, 4000h–5FFFh (BANK0), 6000h–7FFFh (BANK1), 8000h–9FFFh (BANK2), and A000h–BFFFh (BANK3), each 8 KB
- The arrangement of the bank registers changes with RAM mode. With RAM mode = 0, writing is to addresses within each bank (5000h–57FFh, 7000h–77FFh, 9000h–97FFh, B000h–B7FFh); with RAM mode = 1, writing is to 4XFCh–4XFFh. The mode register (RAM mode specification) is at 4XFBh and appears at all times
- BANK#0–#15 are treated as ROM banks, and BANK#16–#31 as RAM banks. Writing to a RAM bank is valid only when RAM mode = 1
- BANK#63 is dedicated to the SCC register bank (Section 7.2). Even if it is made to appear in another bank, it does not function as registers
- At reset, BANK#0–#3 appear in BANK0–BANK3 in order, and RAM mode = 0

7.10 Procedure for Producing Sound

1. Make BANK#63 appear in BANK2 (or, with RAM mode = 1, in BANK1)
2. Write waveform data into the waveform memory
3. Set the frequency register and volume
4. If necessary, set the stereo positioning (9900h–9904h)
5. Set the bit of the channel to be sounded to 1 with the output switch (988Fh)

Chapter 8 OPM

This chapter describes the OPM (equivalent to the YM2151) FM sound source built into the Y8960. The OPM was added to the Y8960's sound source blocks later, and was not described in the earlier draft documentation. This chapter is the official description in this manual.

8.1 Overview

The Y8960's OPM is based on IKAOPM (a reproduction core of the YM2151). Its main specifications are as follows.

- 4-operator FM sound source, 8 channels
- The algorithm (connection form) and feedback can be set for each channel
- Stereo output. For each channel, whether it is output to the left and right (the RL bits) can be specified
- Equipped with an LFO (for vibrato/tremolo) and a noise generator
- Contains Timer A / Timer B and can generate interrupts

The register configuration is compatible with the YM2151. The meanings of the registers described in the YM2151 documentation apply as-is to the Y8960's OPM. This chapter focuses on the access methods and the Y8960-specific implementation (the write queue and so on), and gives an overview of the register map.

8.2 Access Methods

The OPM has two access methods: I/O ports and memory-mapped I/O.

Destination	Address register	Data register	Notes
I/O port	7Eh	7Fh	The status can be obtained by reading the data side
Memory-mapped I/O	7FFBh	7FFCh	Write-only

The procedure for writing to a register is as follows.

1. Write the number of the OPM register to be written to the address register
2. Write the value to the data register

When using the I/O ports (7Eh / 7Fh), the I/O ports must be enabled in advance (the OPM bit of I/O Enabler2; see Chapter 3, Section 3.3). They are disabled immediately after power-on. Memory-mapped I/O can be used while the window of Chapter 3, Section 3.4 is open.

8.3 Write Queue and /WAIT

The YM2151 has the property that "if the next write arrives before the processing of the previous write has finished, that write is dropped," and on the actual chip it was necessary to write while watching the BUSY bit in the status.

In the Y8960's OPM, this restriction is absorbed on the hardware side.

- Writes from the CPU are stored in sequence in an internal queue (16 entries)
- Writes are taken from the queue one at a time, in step with the YM2151's processing timing, and written to the core (the hold times required for the address write and the data write respectively are ensured)
- When the queue becomes full, the CPU is made to wait by the slot's /WAIT signal. No write is ever dropped

A program can therefore write continuously at the pace of ordinary OUT instructions, without strictly monitoring BUSY. Note, however, that the queue depth is limited, so rewriting a large number of registers in a short time causes waits due to /WAIT, which lengthens the CPU processing time.

The BUSY bit of the status register (Section 8.4) is 1 while unprocessed writes remain in the queue or while the core is processing. To confirm that "all writes have been applied to the core," wait until BUSY becomes 0.

8.4 Status Register

Reading I/O port 7Fh returns the status register (it cannot be read from the memory-mapped I/O side).

Bit	Name	Meaning
bit7	BUSY	1 = write processing in progress (writes remain in the queue, or the core is processing)
bit1	FBT	Timer B overflow flag
bit0	FTA	Timer A overflow flag
Others	—	0

For how to clear the timer flags, see Section 8.7.

8.5 Register Map (Overview)

The OPM's registers are laid out at the same addresses as on the YM2151. The main ones are excerpted below. For the detailed meaning of each parameter, refer to the YM2151 documentation.

Register	Contents
01h	Test register (normally left at 00h)
08h	Key on / key off (specifies the channel and operators)
0Fh	Noise control (NE: noise enable, NFRQ: noise frequency)
10h	Timer A counter (upper 8 bits)
11h	Timer A counter (lower 2 bits)
12h	Timer B counter
14h	Timer control (CSM, flag reset, interrupt enable, load)
18h	LFO frequency

Register	Contents
19h	LFO amplitude modulation depth (AMD) / phase modulation depth (PMD). bit7 selects the target, and the value is written in two separate writes
1Bh	LFO waveform select
20h–27h	Channel control (RL: left/right output, FL: feedback amount, CON: algorithm)
28h–2Fh	Key code (KC) for each channel
30h–37h	Key fraction (KF) for each channel
38h–3Fh	PMS (phase modulation sensitivity) / AMS (amplitude modulation sensitivity) for each channel
40h–5Fh	Operator DT1 (detune 1) / MUL (frequency multiplier)
60h–7Fh	Operator TL (total level)
80h–9Fh	Operator KS (key scaling) / AR (attack rate)
A0h–BFh	Operator AME (AM enable) / D1R (first decay rate)
C0h–DFh	Operator DT2 (detune 2) / D2R (second decay rate)
E0h–FFh	Operator D1L (first decay level) / RR (release rate)

In the per-channel registers (20h–3Fh), the lower 3 bits of the address select the channel; in the per-operator registers (40h–FFh), the lower 5 bits of the address select the channel and the operator (the same rules as the YM2151).

8.6 Stereo Output (RL Bits)

Using the RL bits of registers 20h–27h, you can specify, for each channel, whether it is sent to the left output, the right output, or both.

bit7 (R)	bit6 (L)	Output
0	0	Output to neither left nor right
0	1	Left only
1	0	Right only
1	1	Both left and right (center)

The OPM's stereo positioning consists entirely of these RL bits; there is no fine per-channel pan setting on the mixer side (for the mixer, see Chapter 9). If fine positioning is required, one approach is to assign the same instrument to two channels and vary the TL of the left and right channels to reproduce it.

8.7 Timers and Interrupts

The OPM contains Timer A and Timer B.

- Timer A has a 10-bit counter value and Timer B an 8-bit counter value; they are set with registers 10h–12h
- Register 14h controls the loading (count start) of each timer, interrupt enable, and flag reset
- When a counter overflows, the corresponding flag (FTA / FBT) in the status register (Section 8.4) is set. If interrupts are enabled, the cartridge's interrupt output also becomes active (see Chapter 10, Section 10.4)
- Flags are cleared with the flag reset bits of register 14h. Until cleared, a flag remains set and the interrupt continues

In addition to using the timers as a timing source for periodic processing, the CSM mode (a function that performs key-on in synchronization with a Timer A overflow) can also be used, as on the YM2151.

Chapter 9 Digital Mixer

This chapter describes the digital mixer that combines the outputs of all of the Y8960's sound sources, and the I2S output in the final stage.

9.1 Overview

All of the Y8960's sound source blocks support stereo, and their outputs are summed by a digital mixer inside the FPGA and sent via an I2S interface to a DAC (PCM5102A). No mixing is performed in the analog stage.

The mixer inputs are the following five groups.

Group	Contents	Stereo method	Details
SSG	The sum of the outputs of the SSG × 2 cores	Pan for each channel	Chapter 4
OPLL	OPLL-EX	Pan for each channel	Chapter 5
OPL2	OPL2 and ADPCM summed internally	Pan for each channel (including ADPCM)	Chapter 6
SCC	SCC 5 channels	Pan for each channel	Chapter 7
OPM	OPM 8 channels	RL bits for each channel (left/right output specification)	Chapter 8

The pan (stereo positioning) settings are made on the side of each sound source block. The role of the mixer is volume adjustment and summation for each group, and applying the master volume.

Note that ADPCM has no independent group volume. The ADPCM volume follows the volume of the OPL2 group (Section 9.2).

9.2 Per-Group Volumes and the Master Volume

The volume registers are memory-mapped I/O (they can be written when the window of Chapter 3, Section 3.4 is open). All of them are write-only.

Address	Contents
7FF7h	SSG Volume
7FF8h	OPLL Volume
7FF9h	OPL2 Volume (including ADPCM)
7FFAh	SCC Volume
7FFDh	OPM Volume
7FFEh	Master Volume

Each register is 8 bits, and the meanings of the values are as follows.

- 0 = OFF (that group becomes silent)
- 1–128 = volume. 128 is the maximum
- If a value of 129–255 is written, it is treated the same as 128 (the maximum)

The initial value at reset is 128 (the maximum) for all registers.

The processing inside the mixer is performed in the following order.

1. Multiply the input of each group by the volume of that group
2. Sum the five groups, with 24-bit saturation
3. Multiply the summed result by the master volume and output it

9.3 Saturation and Clipping

The summation is 24-bit saturation processing. Values that exceed the range are clamped to the maximum value / minimum value (clip), so no abnormal sound is produced by wraparound, but the

waveform is flattened and becomes distorted.

No attenuation is applied after the summation. Even a single group playing a 16-bit full-scale source at group volume 128 (×1) reaches −6dBFS at the output, so playing multiple groups simultaneously at high volumes clips easily.

If all groups are played simultaneously at high volumes, clipping is more likely to occur. If distortion is a concern, lowering the group volumes while taking the balance on the group volume side, rather than with the master volume, makes it easier to preserve the relative balance of each sound source.

9.4 I2S Output

The mixer output (24-bit stereo) is sent to the DAC via the I2S interface.

Item	Specification
Format	I2S (MSB first)
Slot configuration	32 bits × 2 channels. The valid data is 24 bits
BCLK	Approx. 6.04 MHz
LRCLK (sampling frequency)	Approx. 94.4 kHz (obtained by dividing the I2S clock of approx. 24.16 MHz)
MCLK	Not output (the DAC is configured to operate without MCLK)

Programs normally do not need to be aware of I2S. The settings related to volume and pan are made with the registers in Section 9.2 and the registers of each sound source block.

Chapter 10 System Functions

This chapter describes the system functions other than the sound source blocks — the System Controller and the MSX-TIMER — and also summarizes the reset operation, the overall picture of interrupts, and notes on use.

10.1 System Controller

The System Controller is a block that provides identification of the cartridge and access to the built-in Config ROM (SPI flash). It uses I/O ports 40h–4Fh. This port range is outside the scope of the sound source blocks' I/O enablers (Chapter 3, Section 3.3), and the System Controller has its own enabling procedure.

10.1.1 Enabling and Device Identification

At power-on, the System Controller is in the disabled state and does not respond to reads of 40h–4Fh. The procedure for enabling and identification is as follows.

1. Writing 80h to I/O 40h enables the System Controller
2. In the enabled state, reading I/O 40h returns 7Fh (all bits of 80h inverted). A program can confirm the presence of the System Controller from this value
3. Write a device ID to I/O 41h (device select). Only the device whose own ID matches responds to a read of 41h with "all bits of the ID inverted" (because another device may respond, a device that does not match is designed not to respond)
4. The ID of the Y8960 Cartridge is 02h. After writing 02h to 41h, if reading 41h returns FDh, the Y8960's System Controller has been selected

The assignment of device IDs is as follows.

ID	Device
00h	N/A
01h	V9968 Cartridge

ID	Device
02h	Y8960 Cartridge (this cartridge)
03h	FPGA MSXtR CPU Board
04h	FPGA MSXtR VDP Board
05h	FPGA MSXtR SND Board
06h–FEh	Reserved
FFh	N/A

10.1.2 Function Select

I/O 42h is the function select. It functions when the System Controller is enabled and 02h (the device itself) is selected in 41h.

Value written to 42h	Function
01h	Config ROM Reader/Writer
Others	N/A

After writing 01h, reading 42h returns FEh. If a value other than 01h is written, FFh is returned. While the System Controller is disabled, or while another device is selected, there is no response to reads of 42h.

10.1.3 Config ROM Reader/Writer

When function 01h is selected, I/O 43h–47h are assigned as follows.

I/O	Meaning
43h	Lowest 8 bits of the address

I/O	Meaning
44h	Middle 8 bits of the address
45h	Highest 8 bits of the address
46h	Command (reading returns FFh)
47h	Data
48h–4Fh	Reserved (no response to reads or writes)

Set the Config ROM address (24 bits) in 43h–45h, then write a command to 46h to operate it.

Command	Operation
00h	Read. After completion, the data can be read from 47h
01h	Write
02h	Sector erase (in units of 64KB. The lower 16 bits of the address are ignored)
03h	Chip erase
04h	Status read. After completion, status register 1 of the Config ROM can be read from 47h (bit0 = BUSY)
05h–FFh	Reserved (ignored)

For a write, a sector erase, and a chip erase, issuing the command is all that is done. Confirm completion by repeatedly reading the status until BUSY = 0.

Note that while a command is executing (a few µs), the System Controller does not accept I/O accesses (no /WAIT is asserted during this time). After writing a command to 46h, keep reading 40h and perform the next access only after 7Fh is returned.

- [TBC] A version display register, a function for setting the boot mode, and a write-protect function for the Config ROM could not be confirmed in the current specification documents or

RTL. Whether they exist is being checked.

10.1.4 Boot Copy at Power-On

At power-on, the System Controller automatically copies 7E0000h–7FFFFFh (128KB) of the Config ROM to 00000h–1FFFFh of the SerialSRAM. During the copy, the other modules are stopped, and the MSX itself is also stopped by the slot's /WAIT signal. Therefore, by the time a program on the MSX side starts running, the copy has already completed, and there is no need to wait on the program side.

With this mechanism, the cartridge's programs/data are placed in the SerialSRAM from immediately after power-on, and can be executed and referenced via the SCC banks (Chapter 3, Section 3.5).

10.2 MSX-TIMER

The MSX-TIMER is a block that contains four independent timer cores. It can be used to generate periodic interrupts and to measure elapsed time.


10.2.1 Ports and Access Methods


It uses I/O ports B0h–B3h. It is disabled at power-on, so enable it in advance by setting the TIMER bit (bit7) of I/O Enabler2 to 1 (see Chapter 3, Section 3.3).

Port	Read	Write
B0h	Index (current value)	Sets the index
B1h	The value of the register pointed to by the index	Sets the value of the register pointed to by the index
B2h	Interrupt flags (bit3–0 correspond to cores 3–0; the upper 4 bits are 0)	Flag clear (writing 1 to bit3–0 clears the flag of the corresponding core)
B3h	The current count value of the selected core	Selects the core whose counter is to be read (value 0–3)

The format of the index is as follows.

Bit	Meaning
bit3–2	Core number (0–3)
bit1–0	Register number within the core (0–2; next section)





If a value other than 0–3 (a value in which any of bit7–2 is 1) is written as the core selection of B3h, reading B3h returns FFh.


Reading a register (B1h) takes a few cycles for internal processing, during which the hardware inserts a wait. No special wait processing is required on the program side.

10.2.2 Registers Within a Core

Each timer core has the following registers.

Register number	Name	Contents
0	Mode register	bit7: interrupt enable, bit6–4: resolution (RESO), bit0: repeat
1	Count register	Count value until time-up (8 bits)

Register number	Name	Contents
2	Control register	bit0: count enable, bit1: counter clear (writing 1 returns the counter to 0)
3	—	Not implemented (reads return 00h)



The mode register, the count register, and the control register can all be read back.

10.2.3 Operation

- Setting bit0 of the control register to 1 starts counting
- RESO selects the prescaler and determines the unit time of one count. The counter has a wide bit width internally, and the range used for comparison switches according to RESO, so the unit time becomes 4 times longer each time RESO increases by 1
- When the count value reaches the value of the count register, time-up occurs and the interrupt flag is set
- If repeat (mode register bit0) is 0, the timer is one-shot, and counting stops at the same time as time-up. If it is 1, the counter automatically returns to 0 and counting repeats
- The interrupt flag is set regardless of whether interrupts are enabled. The flag is held until it is explicitly cleared by a write to B2h. While interrupt enable is 1, if there is a core whose flag is set, the cartridge's interrupt output becomes active (Section 10.4)

- The current count value can be read with B3h (see Section 10.2.1)

The unit time is 2^(10 + 2×RESO) ÷ f, where f is the core's clock. The time until time-up is approximately (count value + 1) × unit time. The table below gives reference values calculated with f = 42.95454 MHz.

RESO	Unit time (reference)	Period at count value 255 (reference)
0	Approx. 23.8 µs	Approx. 6.1 ms
1	Approx. 95.4 µs	Approx. 24 ms
2	Approx. 382 µs	Approx. 98 ms
3	Approx. 1.53 ms	Approx. 391 ms
4	Approx. 6.10 ms	Approx. 1.56 s
5	Approx. 24.4 ms	Approx. 6.25 s
6	Approx. 97.7 ms	Approx. 25 s
7	Approx. 391 ms	Approx. 100 s

- [TBC] The actual clock of the timer cores is being confirmed. At the top level, 42.95454 MHz is connected, but the design documents for the timer core side describe 85.90908 MHz, so the actual periods may be twice as fast as those in the table above.

10.2.4 Example Usage Procedure

The following is the flow for using core 0 as a periodic timer.

1. Enable the TIMER bit of I/O Enabler2
2. Write 00h (core 0, mode register) to B0h, and write the mode (interrupt enable, RESO, repeat) to B1h
3. Write 01h (core 0, count register) to B0h, and write the count value to B1h
4. Write 02h (core 0, control register) to B0h, and write 03h (counter clear + count enable) to B1h
5. In the interrupt handler, read B2h to check the flags, and write 1 to the bit of the core that was

handled to clear its flag

10.3 Reset Behavior

The state of each block at power-on and at reset is as follows.

Item	State at reset
I/O ports of the sound source blocks (SSG / OPLL / OPL2 / OPM / MSX-TIMER)	All disabled (I/O Enabler1/2 are all 0). No response even if accessed
Mixer volumes (per group and master)	All 128 (maximum)
SCC bank registers	BANK#0–#3 in BANK0–BANK3, RAM mode = 0
SCC stereo positioning	All channels 128 (center)
SCC output switches	All channels off
OPM write queue	Empty (BUSY eventually becomes 0)
MSX-TIMER	All cores stopped, interrupt flags cleared, interrupt enable 0
System Controller	Disabled (enable it with the procedure of Section 10.1.1 when using it)
Config ROM → SerialSRAM boot copy	Executed at power-on (see Section 10.1.4)

While the I/O ports are disabled, the sound source chips cannot be accessed, so effectively no sound is produced. The recommended initialization flow is as follows.

1. Enable the I/O ports of the sound sources to be used with I/O Enabler1/2
2. Initialize the registers of each sound source chip, and set the instruments and volumes
3. As necessary, set the mixer's per-group volumes and the pan of each channel
4. If timers or interrupts are used, set and enable them last

- [TBC] Whether the boot copy is executed again when the MSX itself is reset, and what happens to

the enabled state of the System Controller, is being confirmed.

10.4 Interrupts

The Y8960 activates the cartridge's interrupt output (/INT) for the following three groups of sources.

Source	Occurrence condition	Checking and clearing the flag
MSX-TIMER	One of the cores reaches time-up and interrupts are enabled	Check with B2h, and clear by writing to B2h (Section 10.2)
OPL2 built-in timers	Overflow of Timer A / Timer B (when interrupts are enabled)	Check with the OPL2 status register, and clear with the reset bit (Chapter 6)
OPM built-in timers	Overflow of Timer A / Timer B (when interrupts are enabled)	Check with the status register (read of 7Fh), and clear with register 14h (Chapter 8)

The interrupt outputs of the three groups are combined internally and go out to the slot's /INT. /INT remains active as long as even one source remains. In the interrupt handler, check the flags of all three groups, clear all of them that have occurred, and then return. If a source is left uncleared, an interrupt will occur again immediately after returning.

The SSG, OPLL, and SCC have no interrupt output.

10.5 Notes on Use

- **I/O address conflicts**: The Y8960's sound source ports are all disabled at power-on. This is a specification intended to avoid conflicts even if the addresses overlap with devices of other cartridges or the MSX itself. Enable only the ports you use. Note in particular that A0h–A3h of the SSG are in the same address range as the MSX's built-in PSG, and enabling them causes writes to be made to the built-in PSG at the same time (see Chapter 4)
- **Enabling conditions for memory-mapped I/O**: Depending on the state of the RAM mode and BANK1, the window for memory-mapped I/O such as the volumes and the I/O enablers (7FF0h–7FFFh) may be closed and access may not be possible (see Chapter 3, Section 3.4). If settings are not reflected, check the state of the window
- **Consecutive writes to the OPM**: The OPM prevents dropped writes with its write queue and

/WAIT, but rewriting a large number of registers in a short time makes the CPU wait, which may delay playback processing and the like (see Chapter 8, Section 8.3)

- **Rewriting the Config ROM**: The Config ROM Reader/Writer is a function for maintenance and updating of the cartridge. Do not use it from ordinary playback programs. Erasure is performed in units of 64KB sectors or for the whole chip, and an incorrect operation will lose data required for the cartridge to boot
- **Access-prohibited areas of the SCC**: The unused areas within the SCC register bank (98A0h–98DFh, 9905h–9FFFh, etc.) are prohibited from access (see Chapter 7, Section 7.3)
- **Fast consecutive accesses**: Consecutive accesses in a fast loop may occupy the bus and cause sound dropouts. It is recommended to keep register rewrites to the minimum necessary

Index

An index of the important terms used in this manual and the pages that mainly describe them. The page numbers are links: selecting one takes you to the corresponding passage.

Term	Page
ADPCM	36, 38
Bank register	17
Bank switching	16
Boot copy	59, 8
Config ROM	57
Device ID	56
Digital mixer	53
Enabler1	14
Enabler2	14
Function select	57
Gain	25
GPIO	25
Group volume	39, 54
I2S	55
Interrupts	64

Term	Page
Master volume	54
Memory map	16
Memory-mapped I/O	15
MMIO	15
Mode register (SCC)	45
MSX-TIMER	59
OPL2	32
OPLL-EX	27
OPM	47
Output switch	44
Pan	26, 31
Preset instrument bank	30
Register bank (SCC)	18, 41
Reset behavior	63
Rhythm mode	31
Saturation and clipping	54
SCC	41
SerialSRAM	7

Term	Page
SPI ROM	57
SSG	21
Stereo output (RL bits)	51
System Controller	13, 56
Waveform memory	44
Write queue	48

Y8960 APPLICATION MANUAL

October 31, 2026

Written by Takayuki Hara (HRA!)