




SAMPLING · DETECTION · MODULATION · CODING

# Digital Communications

*Lecture Notes*



Hüseyin Uğur Yıldız

IEEE Senior Member

Associate Professor of Electrical and Electronics Engineering

TED University, Ankara, Türkiye

# Contents

|          |                                                                                                                                                                                                                                                                                                                                                         |           |
|----------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------|
|          | <b>List of Figures</b>                                                                                                                                                                                                                                                                                                                                  | <b>5</b>  |
|          | <b>List of Tables</b>                                                                                                                                                                                                                                                                                                                                   | <b>8</b>  |
| <b>1</b> | <b>The transition from analog to digital</b> PS CH7.1–7.7                                                                                                                                                                                                                                                                                               | <b>9</b>  |
|          | Impulse-train sampling and the replication of the spectrum. The sampling theorem. Reconstruction and sinc interpolation. Uniform quantization, overload, the error it makes, and the signal-to-quantization-noise ratio. Dither. Companding. Encoding, line codes and pulse code modulation. DPCM and delta modulation. Speech, audio and image coding. |           |
| 1.1      | Impulse-train sampling                                                                                                                                                                                                                                                                                                                                  | 9         |
| 1.2      | The sampling theorem and reconstruction                                                                                                                                                                                                                                                                                                                 | 10        |
| 1.3      | Quantization                                                                                                                                                                                                                                                                                                                                            | 13        |
| 1.4      | Quantization noise and the signal-to-noise ratio                                                                                                                                                                                                                                                                                                        | 14        |
| 1.5      | Non-uniform quantization                                                                                                                                                                                                                                                                                                                                | 17        |
| 1.6      | PCM, DPCM and delta modulation                                                                                                                                                                                                                                                                                                                          | 18        |
| 1.7      | Vector quantization                                                                                                                                                                                                                                                                                                                                     | 20        |
| 1.8      | Speech, audio and image coding                                                                                                                                                                                                                                                                                                                          | 22        |
| 1.9      | Summary                                                                                                                                                                                                                                                                                                                                                 | 23        |
| <b>2</b> | <b>Baseband transmission of digital signals</b> PS CH8.2–8.3, PS CH10.1, PS CH10.3                                                                                                                                                                                                                                                                      | <b>24</b> |
|          | Matched filtering. Correlator and matched-filter demodulators. The decision statistic, optimal threshold, and bit error probability. Intersymbol interference and the eye pattern. Nyquist's criterion and the raised cosine.                                                                                                                           |           |
| 2.1      | The matched filter                                                                                                                                                                                                                                                                                                                                      | 24        |
| 2.2      | From waveform to number                                                                                                                                                                                                                                                                                                                                 | 26        |
| 2.3      | The decision and its error probability                                                                                                                                                                                                                                                                                                                  | 27        |
| 2.4      | Intersymbol interference                                                                                                                                                                                                                                                                                                                                | 31        |
| 2.5      | Nyquist's criterion and the raised cosine                                                                                                                                                                                                                                                                                                               | 32        |
| 2.6      | Summary                                                                                                                                                                                                                                                                                                                                                 | 35        |
| <b>3</b> | <b>Geometric representation of signal waveforms</b> PS CH8.1                                                                                                                                                                                                                                                                                            | <b>36</b> |
|          | Signals as vectors. Orthonormal bases, coordinates, energy and distance. The constellation diagram. The Gram–Schmidt procedure.                                                                                                                                                                                                                         |           |
| 3.1      | Signals as vectors                                                                                                                                                                                                                                                                                                                                      | 36        |
| 3.2      | Constellations                                                                                                                                                                                                                                                                                                                                          | 40        |
| 3.3      | The Gram–Schmidt procedure                                                                                                                                                                                                                                                                                                                              | 45        |
| 3.4      | Summary                                                                                                                                                                                                                                                                                                                                                 | 50        |
| <b>4</b> | <b>The optimal receiver in additive white Gaussian noise</b> PS CH8.3–8.4                                                                                                                                                                                                                                                                               | <b>51</b> |

Correlator banks. The MAP and ML rules. Minimum-distance detection. Decision regions. The union bound and the nearest-neighbour approximation.

|     |                               |    |
|-----|-------------------------------|----|
| 4.1 | What the receiver keeps ..... | 51 |
| 4.2 | The decision rule .....       | 52 |
| 4.3 | Decision regions .....        | 52 |
| 4.4 | The union bound .....         | 53 |
| 4.5 | Summary .....                 | 56 |

## 5 Digital modulation methods PS CH8.5–8.7, PS CH9.5 57

Binary modulation and its energy costs. M-ary phase-shift keying, amplitude-shift keying, quadrature amplitude modulation, and frequency-shift keying.

|     |                                                     |    |
|-----|-----------------------------------------------------|----|
| 5.1 | Putting bits on a carrier .....                     | 57 |
| 5.2 | Phase-shift keying .....                            | 59 |
| 5.3 | Amplitude and quadrature .....                      | 62 |
| 5.4 | Frequency-shift keying and orthogonal signals ..... | 65 |
| 5.5 | Bandwidth and the choice of scheme .....            | 66 |
| 5.6 | Summary .....                                       | 70 |

## 6 An introduction to information theory PS CH12.1–12.3 72

Self-information and entropy. Extended sources. Average codeword length and coding efficiency. Uniquely decodable and prefix codes, the Kraft inequality, and how close to the entropy a code can get. Huffman coding, its ties and its variance.

|      |                                                          |    |
|------|----------------------------------------------------------|----|
| 6.1  | The information in one symbol .....                      | 72 |
| 6.2  | Entropy .....                                            | 72 |
| 6.3  | Extended sources .....                                   | 73 |
| 6.4  | What a code costs .....                                  | 74 |
| 6.5  | Codes that can be read back .....                        | 75 |
| 6.6  | The Kraft inequality, and how close a code can get ..... | 75 |
| 6.7  | Huffman coding .....                                     | 76 |
| 6.8  | Lempel–Ziv coding .....                                  | 77 |
| 6.9  | The discrete memoryless channel .....                    | 78 |
| 6.10 | Mutual information .....                                 | 79 |
| 6.11 | Channel capacity .....                                   | 80 |
| 6.12 | The bandlimited channel .....                            | 82 |
| 6.13 | Summary .....                                            | 83 |

## A Summary of formulas – 84

The main formulas in course order, without derivations.

|     |                                                 |    |
|-----|-------------------------------------------------|----|
| A.1 | From an analog signal to bits — Chapter 1 ..... | 84 |
| A.2 | Baseband transmission — Chapter 2 .....         | 85 |

|     |                                        |    |
|-----|----------------------------------------|----|
| A.3 | Signal space — Chapter 3 .....         | 85 |
| A.4 | The optimal receiver — Chapter 4 ..... | 86 |
| A.5 | Digital modulation — Chapter 5 .....   | 86 |
| A.6 | Information theory — Chapter 6 .....   | 87 |

## B The laboratories — 88

Four laboratories on quantization, matched filtering, quadrature amplitude modulation, and Huffman coding.

|     |                                                                    |    |
|-----|--------------------------------------------------------------------|----|
| B.1 | Quantization, the signal-to-quantization-noise ratio and PCM ..... | 88 |
| B.2 | The matched filter and the bit error rate .....                    | 90 |
| B.3 | Sixteen-point QAM and the union bound .....                        | 92 |
| B.4 | Huffman coding and how much it compresses .....                    | 94 |

### Course conventions

These notes are written for undergraduates. They assume Fourier analysis, probability and random processes. Read the plain explanation before the mathematics. Worked examples use five headings: Given, Find, Method, Solution, and Check.

Noise is white and Gaussian with **two-sided** power spectral density  $N_0/2$  watts per hertz. The Gaussian tail is  $Q(x) = \frac{1}{\sqrt{2\pi}} \int_x^\infty e^{-t^2/2} dt = \frac{1}{2} \operatorname{erfc}(x/\sqrt{2})$ . Energy and power use  $R = 1 \Omega$ .

A **PS** marker points to the related section of Proakis and Salehi, *Fundamentals of Communication Systems*, second edition. The textbook chapter numbers differ from the course chapter numbers.

# List of Figures

## CHAPTER 1 · THE TRANSITION FROM ANALOG TO DIGITAL

|      |                                                                   |    |
|------|-------------------------------------------------------------------|----|
| 1.1  | $f_s > 2W$ : a gap between the replicas.                          | 10 |
| 1.2  | $f_s = 2W$ : they touch and do not overlap.                       | 10 |
| 1.3  | $f_s < 2W$ : they overlap, and the overlap cannot be undone.      | 10 |
| 1.4  | Each sample contributes one shifted sinc scaled by its own value. | 12 |
| 1.5  | Mid-rise, $L = 8$ , $\Delta = 1$ .                                | 13 |
| 1.6  | Mid-tread, $L = 8$ , $\Delta = 1$ .                               | 13 |
| 1.7  | The identity line shows the result without companding.            | 17 |
| 1.8  | Unipolar NRZ.                                                     | 18 |
| 1.9  | Polar NRZ, carrying the same eight bits 01101001.                 | 18 |
| 1.10 | A signal with one steep rise and the delta-modulation staircase.  | 20 |
| 1.11 | A scalar quantizer represents all 256 pairs.                      | 21 |
| 1.12 | The coarse quantizer changes a smooth gradient into flat steps.   | 21 |

## CHAPTER 2 · BASEBAND TRANSMISSION OF DIGITAL SIGNALS

|     |                                                                                                                   |    |
|-----|-------------------------------------------------------------------------------------------------------------------|----|
| 2.1 | A rectangular pulse and the output of the filter matched to it.                                                   | 25 |
| 2.2 | Three pulses of the same energy.                                                                                  | 25 |
| 2.3 | Equal priors: the threshold sits midway and the shaded decision regions are symmetric.                            | 28 |
| 2.4 | $P(s_0) = 0.7$ : the more likely symbol's curve is taller and the crossing has moved towards the less likely one. | 28 |
| 2.5 | Bit error probability against $E_b/N_0$ .                                                                         | 29 |
| 2.6 | A wide-open eye: a pulse that decays quickly.                                                                     | 31 |
| 2.7 | A slowly decaying pulse.                                                                                          | 31 |
| 2.8 | The spectrum at $\alpha = 0, 0.5$ and 1.                                                                          | 34 |
| 2.9 | Their pulses.                                                                                                     | 34 |

## CHAPTER 3 · GEOMETRIC REPRESENTATION OF SIGNAL WAVEFORMS

|      |                                                                                             |    |
|------|---------------------------------------------------------------------------------------------|----|
| 3.1  | $s_0(t)$                                                                                    | 37 |
| 3.2  | $s_1(t)$                                                                                    | 37 |
| 3.3  | Their product: +1 on two quarters and -1 on two.                                            | 37 |
| 3.4  | The four signals of Example 3.1 as a constellation.                                         | 41 |
| 3.5  | Antipodal: one axis.                                                                        | 42 |
| 3.6  | Orthogonal: two axes.                                                                       | 42 |
| 3.7  | On-off: one point at the origin.                                                            | 42 |
| 3.8  | The two axes with $T = 1$ and $f_c T = 3$ : $\psi_1$ solid and $\psi_2$ dashed.             | 42 |
| 3.9  | Example 3.2 as QPSK: four points on the circle of radius $\sqrt{2}$ , with $d_{\min} = 2$ . | 45 |
| 3.10 | 8-PSK at $E = 1$ : eight points on the unit circle.                                         | 45 |
| 3.11 | $s_1$                                                                                       | 46 |
| 3.12 | $s_2$                                                                                       | 46 |
| 3.13 | $s_3 = s_1 + s_2$                                                                           | 46 |
| 3.14 | Two axes carry three signals.                                                               | 47 |
| 3.15 | Four signals need three axes.                                                               | 49 |

---

**CHAPTER 4 · THE OPTIMAL RECEIVER IN ADDITIVE WHITE GAUSSIAN NOISE**

|     |                                                                                                                    |    |
|-----|--------------------------------------------------------------------------------------------------------------------|----|
| 4.1 | Two points, equal priors: the boundary is halfway. ....                                                            | 53 |
| 4.2 | The left symbol four times more likely: its region has grown. ....                                                 | 53 |
| 4.3 | Four points, four boundaries, each perpendicular to the pair it separates. ....                                    | 53 |
| 4.4 | The constellation, its four regions, and the observations the receiver sees when the top-right point is sent. .... | 55 |

---

**CHAPTER 5 · DIGITAL MODULATION METHODS**

|      |                                                                                         |    |
|------|-----------------------------------------------------------------------------------------|----|
| 5.1  | The correlation of two BFSK tones against their spacing. ....                           | 58 |
| 5.2  | Bit error of BPSK (solid) and of BFSK and BASK (dashed). ....                           | 59 |
| 5.3  | QPSK with Gray labels. ....                                                             | 60 |
| 5.4  | 8-PSK with Gray labels. ....                                                            | 60 |
| 5.5  | 16-PSK: the wedges narrow. ....                                                         | 60 |
| 5.6  | Symbol error of M-PSK from the nearest-neighbour form, exact for $M = 2$ . ....         | 61 |
| 5.7  | 4-ASK on one axis. ....                                                                 | 62 |
| 5.8  | 16-QAM and its decision regions. ....                                                   | 64 |
| 5.9  | Exact symbol error of square QAM for $M = 4, 16$ and $64$ . ....                        | 64 |
| 5.10 | From left: coherent BPSK (solid), binary DPSK, coherent BFSK and noncoherent BFSK. .... | 66 |
| 5.11 | Spectra of offset QPSK (dashed) and MSK (solid). ....                                   | 67 |
| 5.12 | The link budget of Example 5.5 against distance. ....                                   | 69 |

---

**CHAPTER 6 · AN INTRODUCTION TO INFORMATION THEORY**

|     |                                                                                                   |    |
|-----|---------------------------------------------------------------------------------------------------|----|
| 6.1 | The entropy of a binary source. ....                                                              | 73 |
| 6.2 | The standard example. ....                                                                        | 73 |
| 6.3 | <b>Code II.</b> Every symbol is at a leaf, so no path to one passes through another. ....         | 75 |
| 6.4 | <b>Code III.</b> Every symbol sits on one path, each hanging off the node before it. ....         | 75 |
| 6.5 | <b>Merged symbol placed high.</b> Lengths 2, 2, 2, 3, 3, average 2.2, variance 0.16. ....         | 77 |
| 6.6 | <b>Merged symbol placed low.</b> Lengths 1, 2, 3, 4, 4, the same average 2.2, variance 1.36. .... | 77 |
| 6.7 | Capacity of the binary symmetric channel. ....                                                    | 81 |
| 6.8 | The Z-channel of Example 6.6. ....                                                                | 81 |
| 6.9 | Bandwidth efficiency against energy per bit. ....                                                 | 83 |

---

**APPENDIX B · THE LABORATORIES**

|      |                                                                                                                              |    |
|------|------------------------------------------------------------------------------------------------------------------------------|----|
| B.1  | The first second of the run. ....                                                                                            | 89 |
| B.2  | The quantizer itself, drawn by feeding it a thousand values across its range. ....                                           | 89 |
| B.3  | The first four samples encoded and sent. ....                                                                                | 89 |
| B.4  | Measured against modelled, for one to six bits a sample, both computed from the seventeen samples the laboratory takes. .... | 90 |
| B.5  | Sixteen bits at $E_b/N_0 = 2$ dB. ....                                                                                       | 91 |
| B.6  | The matched-filter output for the same sixteen bits, read once at the end of every bit interval. ....                        | 91 |
| B.7  | Measured bit error rate against the formula, five thousand bits a point. ....                                                | 92 |
| B.8  | $E_b/N_0 = 6$ dB. ....                                                                                                       | 93 |
| B.9  | $E_b/N_0 = 11$ dB. ....                                                                                                      | 93 |
| B.10 | Measured symbol error rate against the nearest-neighbour approximation. ....                                                 | 94 |
| B.11 | The source statistics $p_i$ over the ten-digit alphabet. ....                                                                | 95 |
| B.12 | The code the algorithm builds. ....                                                                                          | 95 |
| B.13 | $\rho = 0.01$ . ....                                                                                                         | 96 |

B.14  $\rho = 0.99$ .

---

96

# List of Tables

---



---

## CHAPTER 1 · THE TRANSITION FROM ANALOG TO DIGITAL

|     |                                                           |    |
|-----|-----------------------------------------------------------|----|
| 1.1 | Summary of Chapter 1: from an analog signal to bits. .... | 23 |
|-----|-----------------------------------------------------------|----|

---

## CHAPTER 2 · BASEBAND TRANSMISSION OF DIGITAL SIGNALS

|     |                                                                          |    |
|-----|--------------------------------------------------------------------------|----|
| 2.1 | Summary of Chapter 2: baseband transmission and the matched filter. .... | 35 |
|-----|--------------------------------------------------------------------------|----|

---

## CHAPTER 3 · GEOMETRIC REPRESENTATION OF SIGNAL WAVEFORMS

|     |                                                                              |    |
|-----|------------------------------------------------------------------------------|----|
| 3.1 | Summary of Chapter 3: the geometric representation of signal waveforms. .... | 50 |
|-----|------------------------------------------------------------------------------|----|

---

## CHAPTER 4 · THE OPTIMAL RECEIVER IN ADDITIVE WHITE GAUSSIAN NOISE

|     |                                                                                   |    |
|-----|-----------------------------------------------------------------------------------|----|
| 4.1 | Summary of Chapter 4: the optimal receiver in additive white Gaussian noise. .... | 56 |
|-----|-----------------------------------------------------------------------------------|----|

---

## CHAPTER 5 · DIGITAL MODULATION METHODS

|     |                                                                                         |    |
|-----|-----------------------------------------------------------------------------------------|----|
| 5.1 | Each family on the bandwidth–power plane at $M = 16$ and $P_e = 10^{-5}$ . ....         | 67 |
| 5.2 | The signal-to-noise ratio each set of an adaptive link needs for $P_b = 10^{-5}$ . .... | 67 |
| 5.3 | Summary of Chapter 5: digital modulation methods. ....                                  | 70 |

---

## CHAPTER 6 · AN INTRODUCTION TO INFORMATION THEORY

|     |                                                                    |    |
|-----|--------------------------------------------------------------------|----|
| 6.1 | Three codes for the same four symbols. ....                        | 75 |
| 6.2 | Summary of Chapter 6: information, entropy and source coding. .... | 83 |

---

## APPENDIX A · SUMMARY OF FORMULAS

|     |                                                                                 |    |
|-----|---------------------------------------------------------------------------------|----|
| A.1 | Companding and the PCM bit rate. ....                                           | 84 |
| A.2 | Minimum squared distance and number of nearest neighbours for each scheme. .... | 86 |

---

## APPENDIX B · THE LABORATORIES

|     |                                                                                          |    |
|-----|------------------------------------------------------------------------------------------|----|
| B.1 | Entropy, average codeword length, efficiency and compression for the three sources. .... | 96 |
|-----|------------------------------------------------------------------------------------------|----|



## CHAPTER

## 1

# The transition from analog to digital

*A continuous waveform becomes a bit stream in three steps. Sampling makes time discrete. Quantization makes amplitude discrete. Encoding replaces each quantized amplitude with bits. Sampling can be reversed. Quantization cannot.*

## 1.1 Impulse-train sampling

Sampling every  $T_s$  seconds is multiplication by a train of impulses. Write  $f_s = 1/T_s$  for the sampling frequency.

### THE IDEAL SAMPLED SIGNAL

$$p(t) = \sum_{n=-\infty}^{\infty} \delta(t - nT_s)$$

$$g_\delta(t) = g(t)p(t) = \sum_{n=-\infty}^{\infty} g(nT_s)\delta(t - nT_s)$$

The second line uses the sampling property  $g(t)\delta(t - t_0) = g(t_0)\delta(t - t_0)$ , which turns the product under the sum into a number.

The signal  $g_\delta$  is continuous in time, not a sequence of numbers. Therefore, it has a Fourier transform. A product in time becomes a convolution in frequency:

$$P(f) = \frac{1}{T_s} \sum_{n=-\infty}^{\infty} \delta(f - nf_s) = f_s \sum_{n=-\infty}^{\infty} \delta(f - nf_s)$$

The Fourier-series coefficient of  $p(t)$  is the same for every harmonic:  $a_k = \frac{1}{T_s} \int_{-T_s/2}^{T_s/2} \delta(t) e^{-j2\pi k f_0 t} dt = \frac{1}{T_s}$ . Now convolve  $G$  with the impulse train:

$$G_\delta(f) = G(f) * P(f) = \frac{1}{T_s} \sum_{n=-\infty}^{\infty} G(f) * \delta(f - nf_s)$$

A shifted impulse shifts the function during convolution. Write the convolution integral and use the even property  $\delta(-u) = \delta(u)$ :


$$\begin{aligned}
 G(f) * \delta(f - nf_s) &= \int G(\theta) \delta(f - nf_s - \theta) d\theta \\
 &= \int G(\theta) \delta(-[\theta - (f - nf_s)]) d\theta \\
 &= \int G(\theta) \delta(\theta - (f - nf_s)) d\theta \\
 &= G(f - nf_s)
 \end{aligned}$$

The last line uses the sifting property. Each impulse in  $P(f)$  places one copy of  $G$  at a multiple of  $f_s$ .


#### SAMPLING REPLICATES THE SPECTRUM

$$G_\delta(f) = f_s \sum_{n=-\infty}^{\infty} G(f - nf_s)$$


Sampling copies the spectrum to every multiple of  $f_s$  and scales it by  $f_s$ . Nothing is lost provided the copies do not overlap.



**FIGURE 1.1**  $f_s > 2W$ : a gap between the replicas.



**FIGURE 1.2**  $f_s = 2W$ : they touch and do not overlap.



**FIGURE 1.3**  $f_s < 2W$ : they overlap, and the overlap cannot be undone.

#### ⚠ ALIASING

When the replicas overlap, a high message frequency combines with a low frequency from a replica. No filter can separate these components. The samples no longer determine the original signal. A real signal is not strictly bandlimited, so a **guard band**  $f_g$  separates the message and the first replica. Then  $f_s = 2W + f_g$ . An anti-aliasing filter removes frequencies above  $W$  before sampling.

A camera samples in space. An image  $N$  pixels wide holds at most  $N/2$  cycles across its width without aliasing, two pixels a cycle. A finer pattern, such as a striped shirt, folds back into a coarser false pattern called **moiré**. Many cameras put a slight blur in front of the sensor for the same reason an anti-aliasing filter precedes a sampler.

## 1.2 The sampling theorem and reconstruction

### ① SAMPLING THEOREM

If  $G(f) = 0$  for  $|f| \geq W$  and  $f_s \geq 2W$ , then  $g(t)$  is determined completely by its samples  $g(nT_s)$  and can be recovered from them exactly. If  $f_s < 2W$ , aliasing occurs and the recovery fails. The rate  $2W$  is the **Nyquist rate** and  $T_s = 1/(2W)$  the **Nyquist interval**.

An ideal lowpass filter keeps the copy at the origin and rejects the other copies. At  $f_s = 2W$ :

#### THE RECONSTRUCTION FILTER AND ITS IMPULSE RESPONSE

$$H_{\text{LPF}}(f) = \begin{cases} \frac{1}{2W}, & |f| \leq W \\ 0, & \text{otherwise} \end{cases}$$

$$h_{\text{LPF}}(t) = \int_{-W}^W \frac{1}{2W} e^{j2\pi ft} df = \frac{\sin(2\pi Wt)}{2\pi Wt} = \text{sinc}(2Wt)$$

The course uses  $\text{sinc}(x) = \sin(\pi x)/(\pi x)$ . This function is one at zero and zero at every other integer.

#### △ RECONSTRUCTION-FILTER GAIN

Sampling scales the spectrum by  $f_s = 2W$ . The filter must remove this scale factor. A unit-gain filter returns a signal that is  $2W$  times too large.

Filtering in frequency is convolution in time. Therefore, convolve the impulse train with  $h_{\text{LPF}}$ . Use  $\tau$  as the integration variable:

#### THE CONVOLUTION INTEGRAL, AND THE SIFTING STEP


$$\begin{aligned} g_r(t) &= \int_{-\infty}^{\infty} \overbrace{\sum_{n=-\infty}^{\infty} g(nT_s) \delta(\tau - nT_s)}^{= g_s(\tau)} \text{sinc}(2W(t - \tau)) d\tau \\ g_r(t) &= \sum_{n=-\infty}^{\infty} g(nT_s) \underbrace{\int_{-\infty}^{\infty} \text{sinc}(2W(t - \tau)) \delta(\tau - nT_s) d\tau}_{= \text{sinc}(2W(t - nT_s))} \end{aligned}$$

The sum does not depend on  $\tau$ , so it moves outside the integral. The sifting property then replaces  $\tau$  with  $nT_s$ .

#### INTERPOLATION

$$\begin{aligned} g_r(t) &= \sum_{n=-\infty}^{\infty} g(nT_s) \text{sinc}(2W(t - nT_s)) \\ g_r(t) &= \sum_{n=-\infty}^{\infty} g\left(\frac{n}{2W}\right) \text{sinc}(2Wt - n) \quad \text{at } f_s = 2W \end{aligned}$$

At  $t = kT_s$ , every term is zero except the term with  $n = k$ . Therefore,  $g_r(kT_s) = g(kT_s)$ . The same sum reconstructs the signal between the sample times.



**FIGURE 1.4** Each sample contributes one shifted sinc scaled by its own value. Their sum, drawn heavy, passes through every sample because each sinc is zero at all the other sampling instants.

### EXAMPLE 1.1 – THREE SAMPLING RATES

- GIVEN** A signal  $x(t)$  bandlimited to  $W = 40$  kHz.
- FIND** Find (a) the Nyquist rate, (b) the rate with a 10 kHz guard band, and (c) the Nyquist rate of  $y(t) = x(t) \cos(80000\pi t)$ .
- METHOD** Read (a) and (b) off the geometry of the replicas. For (c) find the bandwidth of  $y$  first: the rate follows from that, not from the bandwidth of  $x$ .
- SOLUTION** (a)  $f_s = 2W = 80$  kHz. (b)  $f_s = 2W + f_g = 90$  kHz. (c) The carrier is at  $f_c = 40$  kHz, and multiplication shifts the spectrum both ways and halves it:  $Y(f) = \frac{1}{2}X(f - 40k) + \frac{1}{2}X(f + 40k)$ . The result occupies  $|f| < 80$  kHz, so  $f_s = 160$  kHz.
- CHECK** The highest frequency of  $y$  is  $f_c + W = 80$  kHz. Therefore, its Nyquist rate is 160 kHz. The rate follows the highest frequency, not the message bandwidth.


#### COMMON ERROR IN PART (C)

The rate 80 kHz applies to  $x$ , not to  $y$ . Modulation moves the highest frequency to 80 kHz. Therefore,  $y$  needs a sampling rate of 160 kHz.


### 1.3 Quantization

Quantization replaces a sample amplitude with one of  $L$  **representation levels**. A **uniform** quantizer uses the same spacing  $\Delta$  between consecutive levels.

A **mid-rise** quantizer has a decision boundary at zero, so it has no zero output level. A **mid-tread** quantizer has an output level at zero. Thus, a mid-tread quantizer reproduces a small input as zero.



**FIGURE 1.5** Mid-rise,  $L = 8$ ,  $\Delta = 1$ . A boundary at the origin.



**FIGURE 1.6** Mid-tread,  $L = 8$ ,  $\Delta = 1$ . A level at the origin.

A quantizer divides the input range into  $L$  regions  $\mathcal{J}_k$ . Each region has one output value  $v_k$ . Two conditions define an optimal quantizer:

1. Each boundary is the **midpoint** of its two adjacent levels:  $m_k = \frac{1}{2}(v_{k-1} + v_k)$ . This sends each input to the nearer level.
2. Each level is the **centroid** of its region:  $v_k = E[M \mid M \in \mathcal{J}_k]$ . This minimizes the mean-square error in that region.

The two conditions depend on each other, so apply them in turn. A uniform quantizer satisfies both conditions for a uniform input.

A quantizer spanning  $[-m_{\max}, m_{\max}]$  makes two kinds of error. An input beyond  $\pm m_{\max}$  is clipped to the outer level, and its error has no bound. This is **overload**. Inside the range the error stays within  $\pm\Delta/2$ . This is **granular noise**.

A wider range reduces overload but makes  $\Delta$  and the granular noise larger. For a Gaussian input and 3 bits, the SQNR is largest at  $m_{\max} = 2.34\sigma$ , with 14.27 dB. At  $m_{\max} = \sigma$  it falls to 6.97 dB, because about 32% of the samples are clipped.

#### ⊗ COMMON ERROR

Set  $m_{\max}$  from the rare peaks of the signal, not from its typical size. A range equal to one standard deviation clips a third of a Gaussian signal.

## 1.4 Quantization noise and the signal-to-noise ratio

The quantization error is  $Q = M - \mathbb{Q}(M)$ . Nearest-level quantization keeps this error between  $-\Delta/2$  and  $\Delta/2$ .

If  $\Delta$  is small, the density of  $M$  is nearly constant across one region. The error can then be modeled as uniform.

### THE UNIFORM ERROR MODEL

$$f_Q(q) = \frac{1}{\Delta}, \quad -\frac{\Delta}{2} \leq q \leq \frac{\Delta}{2}$$

$$E[Q^2] = \int_{-\Delta/2}^{\Delta/2} q^2 \frac{1}{\Delta} dq = \frac{\Delta^2}{12}$$

For a zero-mean error, this mean-square value is also the variance and the quantization-noise power.

Substitute  $\Delta = 2m_{\max}/L$  and  $L = 2^R$ . Then divide the signal power by the error power to obtain the SQNR.

### SIGNAL-TO-QUANTIZATION-NOISE RATIO

$$E[Q^2] = \frac{1}{12} \left( \frac{2m_{\max}}{L} \right)^2 = \frac{m_{\max}^2}{3 \cdot 2^{2R}}$$

$$\text{SQNR} = \frac{P_M}{E[Q^2]} = \frac{3P_M}{m_{\max}^2} 2^{2R}$$

$$\text{SQNR [dB]} = \underbrace{10 \log_{10} \frac{3P_M}{m_{\max}^2}}_{\alpha} + 6.02R$$

Each extra bit adds  $20 \log_{10} 2 = 6.02$  dB. Doubling the level count halves the step size and divides the error power by four.

### ⚠ INPUT-RANGE USE

The term  $\alpha$  depends on the signal power and peak amplitude. A full-scale sinusoid gives  $\alpha \approx 1.76$  dB. A sinusoid that reaches one quarter of the range loses 12.04 dB.

### EXAMPLE 1.2 – A FULL-SCALE SINUSOID

- GIVEN**  $m(t) = 5 \cos t$  through a uniform quantizer spanning its full range.
- FIND** The step size and the SQNR at  $R = 3$  and  $R = 4$  bits per sample.
- METHOD** Average power from Parseval, step size from  $\Delta = 2m_{\max}/L$ , then  $\alpha + 6.02R$ .
- SOLUTION** The coefficients are  $a_{\pm 1} = 5/2$ , so  $P_M = 2(5/2)^2 = 12.5$  and  $m_{\max} = 5$ . At  $R = 3$ :  $\Delta = 2(5)/8 = 1.25$  V and SQNR =  $1.76 + 18.06 = 19.82$  dB. At  $R = 4$ :  $\Delta = 0.625$  V and SQNR =  $1.76 + 24.08 = 25.84$  dB.
- CHECK** The two differ by 6.02 dB, one bit. Independently,  $E[Q^2] = \Delta^2/12 = 0.1302$  and  $10 \log_{10}(12.5/0.1302) = 19.82$  dB.

#### MODEL LIMIT

The measured results are 19.09 dB and 25.31 dB. They are below the model by 0.7 dB and 0.5 dB. A sinusoid does not produce a uniform error at low resolution. The gap decreases as  $R$  increases.

### EXAMPLE 1.3 – WHEN THE MODEL BREAKS

- GIVEN** A zero-mean stationary Gaussian source has  $S_X(f) = 2$  for  $|f| < 100$  Hz. Its samples enter a five-level quantizer with outputs  $-30, -10, 0, 10, 30$  and boundaries at  $-40, -20, 20, 40$ .
- FIND** The SQNR of the scheme.
- METHOD** The signal power is the area under the spectral density. The noise power must be integrated region by region, because this quantizer is neither uniform nor fine.
- SOLUTION**  $P_X = \int_{-100}^{100} 2 df = 400$ , and since the mean is zero this is also  $\sigma_X^2$ . Splitting  $P_Q = \int (x - Q(x))^2 f_X(x) dx$  at the four boundaries gives five contributions of about 7.98, 46.36, 79.50, 46.36 and 7.98, which add to  $P_Q = 188.17$ , so SQNR =  $10 \log_{10}(400/188.17) = 3.28$  dB.
- CHECK** The central region alone contributes 79.50, and it holds the 68% of the mass with  $|X| < 20$  and an error of up to 20. That is where a five-level quantizer spends its error, and it is why the answer is a few decibels rather than a few tens.

#### MODEL LIMIT

This quantizer is coarse, and its outer regions are unbounded. A sample at  $x = 120$  has an error of 90. The formula  $\Delta^2/12$  predicts 10.8 dB, but direct integration gives 3.28 dB.

Every source gains 6.02 dB a bit. The source sets only the intercept  $\alpha = 10 \log_{10}(3P_M/m_{\max}^2)$ :

$$\begin{aligned} \text{sinusoid: } 10 \log_{10} \frac{3(A^2/2)}{A^2} &= 1.76 \text{ dB} \\ \text{uniform on } [-1, 1]: 10 \log_{10} \frac{3(1/3)}{1} &= 0 \text{ dB} \\ \text{Gaussian, } m_{\max} = 4\sigma: 10 \log_{10} \frac{3\sigma^2}{16\sigma^2} &= -7.27 \text{ dB} \end{aligned}$$

At equal  $R$  the Gaussian source sits  $1.76 - (-7.27) = 9.03$  dB below the sinusoid. Its rare large peaks force a wide range, so typical samples use few of the levels.

At a few bits the error follows the signal. On speech it sounds like distortion, not like hiss, and the uniform error model no longer holds. **Dither** is a small random signal, about one step wide, added before the quantizer. Each output still sits on a level, but the error no longer follows the signal. Averaged over time, or by the eye over neighbouring pixels, the output follows the input between the levels.

For example, let an input sit  $0.3\Delta$  above a level, with dither uniform on  $[-\Delta/2, \Delta/2]$ . The next boundary is  $0.5\Delta$  up, so the level above is chosen when the dither exceeds  $0.2\Delta$ . That happens 30% of the time, and the average output is  $0.3\Delta$  above the level. Dither adds noise power. It trades a pattern that the ear or eye notices for a hiss or grain that it ignores.



## 1.5 Non-uniform quantization

Speech contains small amplitudes more often than large amplitudes. A uniform quantizer gives every amplitude the same step size. Thus, its relative error is larger for small amplitudes.

A non-uniform quantizer uses narrow regions where the probability density is high. It uses wide regions where the density is low. This arrangement reduces distortion without adding levels.


A **compander** first compresses the signal with a memoryless nonlinearity. It then uses a uniform quantizer. The receiver applies the inverse expansion.

### THE TWO STANDARD COMPRESSORS

$$y = \frac{\ln(1 + \mu|x|)}{\ln(1 + \mu)} \operatorname{sgn}(x), \quad |x| \leq 1$$

$$y = \begin{cases} \frac{A|x|}{1 + \ln A} \operatorname{sgn}(x), & 0 \leq |x| \leq 1/A \\ \frac{1 + \ln(A|x|)}{1 + \ln A} \operatorname{sgn}(x), & 1/A < |x| \leq 1 \end{cases}$$

Both laws map  $x = \pm 1$  to  $y = \pm 1$ . The standard parameters are  $\mu = 255$  and  $A = 87.6$ . For the same speech and eight-bit quantizer, their SQNR values differ by less than 0.01 dB.



**FIGURE 1.7** The identity line shows the result without companding. Both compressors use much of the output range for small input amplitudes.

With a uniform quantizer the noise power  $\Delta^2/12$  does not depend on the signal. When a talker drops 20 dB below full scale, the SQNR drops by 20 dB. The  $\mu$ -law steps shrink with the signal, so its SQNR hardly

changes over a wide range of levels.

## 1.6 PCM, DPCM and delta modulation

With  $L = 2^R$  levels, each sample needs  $R$  bits. At  $f_s$  samples per second, the bit rate is  $R_b = Rf_s$ .

**Natural binary coding** assigns increasing binary values to the levels. Adjacent **Gray** words differ by one bit. Thus, a small level error changes only one Gray-coded bit.

A **line code** converts the bits into a waveform. Unipolar NRZ has a DC component that causes droop in an AC-coupled stage. Balanced polar NRZ has no DC component.

A long run of equal NRZ bits has no transitions for clock recovery. Manchester coding adds a transition to every bit but uses twice the bandwidth.




FIGURE 1.8 Unipolar NRZ.




FIGURE 1.9 Polar NRZ, carrying the same eight bits 01101001.

### EXAMPLE 1.4 – A COMPLETE PCM STREAM

- GIVEN**  $m(t) = 8|\text{sinc}(t - 2)|$ , so  $0 \leq m(t) \leq 8$ , sampled every  $T_s = 0.6$  s and quantized by an eight-level uniform quantizer covering  $[0, 8]$ .
- FIND** The step size, the levels, the code words for  $t = 0, 0.6, \dots, 3.6$ , and the bit rate.
- METHOD** Calculate  $\Delta$  from the range and level count. Evaluate each sample. Select the word from the quantization region.
- SOLUTION**  $\Delta = 8/8 = 1$  V and the levels sit at  $0.5, 1.5, \dots, 7.5$ . The samples are 0, 1.73, 1.87, 7.48, 6.05, 0, 1.51, giving the words 000 001 001 111 110 000 001. With  $R = 3$  and  $f_s = 1/0.6 = 1.667$ ,  $R_b = 5$  bit/s and  $T_b = T_s/3 = 0.2$  s.
- CHECK** At  $t = 3$ , the sample is  $8|\text{sinc}(1)| = 0$ . The sinc function is zero at every nonzero integer. The interpolation formula uses the same property.

### The bandwidth of PCM

A binary stream of  $R_b$  bits a second needs a bandwidth of at least  $R_b/2$  hertz. Chapter 2 shows why.

## LEAST BANDWIDTH OF PCM

$$B_T \geq \frac{R_b}{2} = \frac{R f_s}{2}$$

$$B_T \geq RW \quad \text{at } f_s = 2W$$

Each extra bit adds 6.02 dB of SQNR and  $W$  hertz of bandwidth. Telephone PCM at  $f_s = 8$  kHz and  $R = 8$  bits sends 64 kb/s and needs at least 32 kHz, eight times the 4 kHz of the voice.

**Bit errors**

A channel error flips one bit of a code word. With natural binary coding, bit  $b$  counted from 0 at the right moves the decoded value by  $2^b \Delta$ . A wrong first bit,  $b = R - 1$ , moves the sample by  $2^{R-1} \Delta = m_{\max}$ , half the range. For  $R = 8$  and  $\Delta = 1/128$  V that is 1 V. On speech it sounds as a click, far louder than the quantization noise.

**Differential PCM**

Neighbouring samples of speech are close. **DPCM** quantizes the difference between a sample and its prediction, which has a much smaller range than the sample.

## DPCM WITH THE LAST DECODED VALUE AS PREDICTION

$$e[n] = x[n] - \hat{x}[n-1]$$

$$\hat{x}[n] = \hat{x}[n-1] + \mathbb{Q}(e[n])$$


The encoder predicts from  $\hat{x}[n-1]$ , which the decoder also has. So  $x[n] - \hat{x}[n] = e[n] - \mathbb{Q}(e[n])$ , and quantization errors do not pile up.

For speech at 8 kHz, DPCM with 4 bits a sample matches PCM with 8. That is 32 kb/s in place of 64 kb/s.

**Delta modulation**

**Delta modulation** is DPCM with a two-level quantizer. Each bit moves a staircase up or down by  $\Delta$ . The staircase climbs at most  $\Delta$  every  $T_s$ , so it follows the signal only while

$$\left| \frac{dx}{dt} \right| \leq \frac{\Delta}{T_s} = \Delta f_s$$



**FIGURE 1.10** A signal with one steep rise and the delta-modulation staircase. On the rise the staircase falls behind (slope overload). Where the signal is flat it hunts by  $\pm\Delta$  (granular noise).

#### EXAMPLE 1.5 – THE STEP OF A DELTA MODULATOR

**GIVEN**  $x(t) = \sin(2\pi 1000 t)$ , sampled at  $f_s = 64$  kHz by a delta modulator.

**FIND** The smallest step  $\Delta$  that avoids slope overload.

**METHOD** Find the largest slope of  $x$ , then apply  $|dx/dt| \leq \Delta f_s$ .

**SOLUTION**  $dx/dt = 2\pi(1000) \cos(2\pi 1000 t)$ , whose largest value is  $2\pi(1000) = 6283$  per second. So  $\Delta \geq 6283/64\,000 = 0.098$ .

**CHECK** A larger  $\Delta$  avoids overload but raises the granular noise, which grows with  $\Delta$ .

#### ⊗ COMMON ERROR

Use the largest slope of the signal,  $2\pi f_0 A$ , not its peak value  $A$ . The staircase fails where the signal changes fastest.


## 1.7 Vector quantization

**Scalar quantization** processes one sample at a time. It does not use the dependence between neighboring samples.


**Vector quantization** treats  $n$  samples as one point in  $n$  dimensions. A **codebook** contains the allowed output points. The quantizer selects the nearest codebook point.

### EXAMPLE 1.6 – PAIRS OF NEIGHBOURING SAMPLES

- GIVEN**  $L = 16$  levels, and a signal smooth enough that a sample never moves more than one step from the one before it.
- FIND** What a pair costs, quantized separately and quantized together.
- METHOD** Count the pairs each scheme has to be able to name, and take the base-two logarithm.
- SOLUTION** Separately, every combination is allowed:  $L^2 = 256$  pairs,  $\log_2 256 = 8$  bits a pair, or 4 bits a sample. Together, only the pairs with  $|i - j| \leq 1$  can occur, and there are  $3L - 2 = 46$  of them:  $\lceil \log_2 46 \rceil = 6$  bits a pair, or 3 bits a sample.
- CHECK** The cell size and rounding error do not change. The code omits 210 pairs that the signal model cannot produce. The rate decreases from four to three bits per sample.



**FIGURE 1.11** A scalar quantizer represents all 256 pairs. Under the smooth-signal assumption, only the 46 shaded pairs can occur.



**FIGURE 1.12** The coarse quantizer changes a smooth gradient into flat steps. Each step boundary appears as a false line.

### △ SOURCE DEPENDENCE

Most of the rate reduction comes from dependence between neighboring samples. Better cell shapes can give a smaller gain for independent samples. This course does not develop that case.

### EXAMPLE 1.7 – QUANTIZING AN IMAGE

- GIVEN** A  $512 \times 512$  grayscale image at 8 bits a pixel, so  $L = 256$  levels.
- FIND** The size of the file, and the size and the cost at  $L = 32$ .
- SOLUTION**  $512^2(8) = 2\,097\,152$  bits, which is 256 KiB. At  $L = 32$  the rate is  $R = \log_2 32 = 5$  bits a pixel, so 1 310 720 bits or 160 KiB — 37.5% smaller.
- COST**  $\Delta\text{SQNR} = 6.02(8 - 5) = 18.06$  dB. A smooth gradient becomes flat bands with false edges.
- CHECK** The decoder cannot recover the position of a pixel inside its quantization interval. Therefore, this compression is **lossy**. JPEG also quantizes transformed image blocks.

## 1.8 Speech, audio and image coding

The same three steps, sampling, quantization and encoding, sit under the coders in everyday use. This section shows four of them briefly.

### Linear predictive coding

LPC does not send the waveform. Every 20 ms, that is 160 samples at 8 kHz, it sends a model of the voice. The receiver runs the model to make the speech again.

#### THE ALL-POLE MODEL OF SPEECH

$$x_n = \sum_{i=1}^p a_i x_{n-i} + G w_n$$

$w_n$  is a pulse train for a voiced sound and white noise for an unvoiced one. The coefficients  $a_i$  describe the shape of the vocal tract, and the peaks of the filter are the formants.

Each frame sends the  $a_i$ , the gain  $G$ , the pitch and one voiced bit. A coder with 48 bits a 20 ms frame runs at  $48(50) = 2400$  b/s, against 64 kb/s for PCM.

### Time-division multiplexing

Many PCM calls share one line by taking turns. Each call gets one slot in every frame, and a frame lasts one sampling interval,  $125 \mu\text{s}$  at 8 kHz.

#### THE T1 FRAME

$$24(8) + 1 = 193 \text{ bits a frame}$$

$$193(8000) = 1.544 \text{ Mb/s}$$

The extra bit marks the start of each frame. The 24 calls alone need  $24(64) = 1.536$  Mb/s. Four T1 lines make a 6.312 Mb/s line, and seven of those a 44.736 Mb/s line. Europe and Türkiye use E1: 32 slots of 64 kb/s, 2.048 Mb/s.

### Oversampling and sigma-delta conversion

At a rate far above  $2W$ , neighbouring samples are nearly equal, and one bit a sample can carry the change. A sigma-delta converter integrates the error between the input and its one-bit output:

$$\begin{aligned} v[n] &= v[n-1] + x[n] - y[n-1] \\ y[n] &= \text{sgn}(v[n]) \end{aligned}$$

The running average of the bits  $y$  stays on the input. A lowpass filter removes the fast swings of the bits and returns the signal. A CD player that oversamples 44.1 kHz audio by  $U = 256$  runs its one-bit converter at  $256(44.1 \text{ kHz}) = 11.2896 \text{ MHz}$ .

### Transform coding and JPEG

JPEG cuts a picture into  $8 \times 8$  blocks and takes the discrete cosine transform of each. Most of the energy of a block lands in a few low-frequency coefficients.

Each coefficient has its own uniform step, larger at high frequencies. Most high-frequency coefficients round to zero and cost almost nothing to send. At a coarse step each block keeps little more than its average, and the picture breaks into visible  $8 \times 8$  squares.

A  $512 \times 512$  picture coded at 0.5 bit a pixel takes  $512^2(0.5)/8 = 16\,384$  bytes, or 16 KiB. That is sixteen times less than at 8 bits a pixel.

## 1.9 Summary

**TABLE 1.1** Summary of Chapter 1: from an analog signal to bits.

| RESULT              | STATEMENT                                                             | ANCHOR          |
|---------------------|-----------------------------------------------------------------------|-----------------|
| Replication         | $G_\delta(f) = f_s \sum_n G(f - n f_s)$                               | PS CH7.1.1      |
| Sampling theorem    | $f_s \geq 2W$ for a message bandlimited to $W$                        | PS CH7.1.1      |
| Reconstruction      | $g_r(t) = \sum_n g(nT_s) \text{sinc}(2Wt - n)$ , filter gain $1/(2W)$ | PS CH7.1.1      |
| Step size           | $\Delta = 2m_{\max}/L$ , $L = 2^R$                                    | PS CH7.2.1      |
| Error power         | $E[Q^2] = \Delta^2/12$ , when the step is small                       | PS CH7.2.1      |
| Signal-to-noise     | $\text{SQNR [dB]} = \alpha + 6.02R$                                   | PS CH7.2.1      |
| Bit rate            | $R_b = R f_s$                                                         | PS CH7.3, 7.4.1 |
| PCM bandwidth       | $B_T \geq R_b/2 = RW$ at $f_s = 2W$                                   | PS CH7.4.1      |
| DPCM                | quantize $e[n] = x[n] - \hat{x}[n-1]$                                 | PS CH7.4.2      |
| Delta modulation    | no slope overload while $ dx/dt  \leq \Delta f_s$                     | PS CH7.4.3      |
| T1 line             | 193 bits every $125 \mu\text{s}$ , 1.544 Mb/s                         | PS CH7.6.1      |
| Vector quantization | round $n$ samples together and use a codebook                         | PS CH7.2.2      |

Sampling is reversible and quantization is not. Everything after this chapter takes the bit stream as given and asks what the channel does to it.

## CHAPTER

## 2

# Baseband transmission of digital signals

Chapter 1 produced a stream of bits. Each bit now becomes a waveform, and the channel adds noise. The receiver must identify the transmitted waveform. This chapter selects the receiver filter and decision threshold. It also studies pulse overlap in a bandlimited channel.

## 2.1 The matched filter

Over one bit interval the receiver sees  $x(t) = g(t) + w(t)$ , the waveform plus white Gaussian noise of two-sided density  $N_0/2$ . It passes this through a filter and takes one sample at the end of the interval. Because the filter is linear, its output splits the same way, into a signal part  $g_0(t) = g * h$  and a noise part  $n(t) = w * h$ .

The quantity worth maximising is the signal at the sampling instant against the noise power that accompanies it. Call this ratio  $\eta$ .

### THE PEAK PULSE SIGNAL-TO-NOISE RATIO

$$\eta = \frac{|g_0(T)|^2}{E[n^2(T)]} = \frac{\left| \int_{-\infty}^{\infty} G(f)H(f)e^{j2\pi fT} df \right|^2}{\frac{N_0}{2} \int_{-\infty}^{\infty} |H(f)|^2 df}$$

Scaling  $H$  up multiplies the top and the bottom by the same factor, so the answer cannot be "make  $H$  large". What is being chosen is the shape of  $H$ .

Schwarz's inequality says that  $\left| \int \phi_1 \phi_2 \right|^2 \leq \int |\phi_1|^2 \int |\phi_2|^2$ , with equality only when  $\phi_1 = k\phi_2^*$ . Taking  $\phi_1 = H(f)$  and  $\phi_2 = G(f)e^{j2\pi fT}$ , the factor  $\int |H|^2$  cancels between the top and the bottom and a bound appears that contains no  $H$  at all.

### THE BOUND, AND THE FILTER THAT REACHES IT

$$\eta \leq \frac{2}{N_0} \int |G(f)|^2 df = \frac{2E}{N_0}$$

$$H(f) = k G^*(f) e^{-j2\pi fT} \iff h_{\text{opt}}(t) = k g(T - t)$$

The optimum filter is the transmitted waveform reversed in time and shifted into the interval. It is called the **matched filter**.



### ✓ TWO THINGS THIS SAYS


The best achievable ratio is  $\eta_{\max} = 2E/N_0$ . It depends on the **energy** of the pulse and on the noise density, and on nothing else about the pulse. Two completely different waveforms of the same energy perform identically. The constant  $k$  cancels. Therefore, the filter is fixed only up to a gain.

The matched-filter output can be found directly, without going through frequency. Write it as a convolution and substitute  $h(t) = g(T - t)$ .


### THE MATCHED-FILTER OUTPUT AS A SLIDING OVERLAP

$$y(t) = \int_{-\infty}^{\infty} g(\tau) h(t - \tau) d\tau = \int_{-\infty}^{\infty} g(\tau) g(T - t + \tau) d\tau$$

At  $t = T$  the two copies of  $g$  line up exactly, so  $y(T) = \int g^2(\tau) d\tau = E$ . The peak of the matched-filter output is always the pulse energy, whatever the pulse shape.



**FIGURE 2.1** A rectangular pulse and the output of the filter matched to it. The output peaks at exactly  $t = T$ , and its peak is the energy of the pulse.



**FIGURE 2.2** Three pulses of the same energy. Against white Gaussian noise a matched-filter receiver performs identically on all three.

### ✂ EXAMPLE 2.1 – MATCHED FILTER OF A RECTANGULAR PULSE

**GIVEN**  $s(t) = A$  on  $[0, T]$ , with  $A = 2$  V,  $T = 0.5$  ms and  $N_0/2 = 10^{-4}$  W/Hz.

**FIND** The matched filter  $h(t)$ , the output  $y(t)$  and the largest peak SNR  $\eta_{\max}$ .

**METHOD** Reverse and shift the pulse to get  $h(t)$ . Slide it across  $s(t)$  to get  $y(t)$ . Then use  $\eta_{\max} = 2E/N_0$ .

**SOLUTION**  $h(t) = s(T - t) = A$  on  $[0, T]$ . Sliding the overlap gives  $y(t) = A^2 t$  for  $0 \leq t \leq T$  and  $y(t) = A^2(2T - t)$  for  $T \leq t \leq 2T$ . The energy is  $E = A^2 T = (2)^2(0.5 \times 10^{-3}) = 2 \times 10^{-3}$  J. Then  $\eta_{\max} = 2E/N_0 = 2(2 \times 10^{-3})/(2 \times 10^{-4}) = 20$ .

**CHECK**  $10 \log_{10} 20 = 13.0$  dB, and  $y(T) = A^2 T = E$ , as the general result requires.

### ⊗ COMMON ERROR

Use  $N_0 = 2 \times 10^{-4}$  W/Hz in  $2E/N_0$ , not  $N_0/2$ . Using  $N_0/2$  in place of  $N_0$  gives 40, twice the true value.

## 2.2 From waveform to number

Both waveforms of a binary baseband system are multiples of one shape, so a single unit-energy function carries both. With  $\psi(t) = 1/\sqrt{T_b}$  on the bit interval, polar NRZ is  $s_m(t) = s_m\psi(t)$  with  $s_0 = -A\sqrt{T_b}$  and  $s_1 = +A\sqrt{T_b}$ . Both carry energy  $E_b = A^2T_b$ , so  $A\sqrt{T_b} = \sqrt{E_b}$  and the two waveforms have become two *numbers*,  $\pm\sqrt{E_b}$ , on one axis.

This axis is a signal space of one dimension, the axis of  $\psi(t)$ . The point  $s_0 = -\sqrt{E_b}$  stands for the waveform  $s_0(t)$ , and  $s_1 = +\sqrt{E_b}$  for  $s_1(t)$ .

### THE TWO SYMBOLS AS POINTS

$$s_m = \int_0^{T_b} s_m(t) \psi(t) dt = \pm\sqrt{E_b}, \quad d = s_1 - s_0 = 2\sqrt{E_b}$$

A larger distance  $d$  means noise must move the received point further before it crosses to the wrong symbol.

The demodulator can be built two ways. The **matched filter** convolves with  $\psi(T_b - t)$  and samples at  $T_b$ . The **correlator** multiplies by  $\psi(t)$  and integrates over the interval. Put  $t = T_b$  in the matched-filter output, and the convolution integral becomes the correlator integral, for any shape of  $\psi$ .

### THE TWO DEMODULATORS AGREE AT $t = T_b$

$$h(t) = \psi(T_b - t)$$

$$y(t) = \int_{-\infty}^{\infty} x(\tau) \psi(T_b - t + \tau) d\tau \implies y(T_b) = \int_0^{T_b} x(\tau) \psi(\tau) d\tau$$

This equality holds at  $t = T_b$  for every basis shape  $\psi(t)$ , not only for a rectangle.

For the rectangular  $\psi$  used in polar NRZ, the two demodulators agree over the whole bit, not only at  $t = T_b$ . The matched-filter output is the ramp  $y(t) = s_mt/\sqrt{T_b}$  for  $0 \leq t \leq T_b$ , and the correlator output at time  $t$  is the same running integral  $\int_0^t x(\tau)\psi(\tau) d\tau$ .

### ⚠ A DIFFERENT BASIS SHAPE

For a shape such as a half-sine  $\psi$ , the running matched-filter output and the running correlator output differ before  $t = T_b$ . Only at  $t = T_b$  do the two demodulators agree, because that is where the convolution and the correlation cover the same interval.

### THE DECISION STATISTIC

$$y = \int_0^{T_b} x(\tau)\psi(\tau) d\tau = s_m \underbrace{\int_0^{T_b} \psi^2}_{=1} + \underbrace{\int_0^{T_b} w\psi}_{n} = s_m + n$$

The noise term  $n$  is Gaussian, because it is a linear operation on a Gaussian process.

Find the variance of  $n$  from the autocorrelation of white noise. Write  $n^2$  as a double integral, substitute the two-sided density, and use the sifting property of  $\delta(\tau - u)$ .

#### THE NOISE VARIANCE, STEP BY STEP

$$\begin{aligned} E[n^2] &= \int_0^{T_b} \int_0^{T_b} E[w(\tau)w(u)] \psi(\tau)\psi(u) d\tau du \\ &= \int_0^{T_b} \int_0^{T_b} \frac{N_0}{2} \delta(\tau - u) \psi(\tau)\psi(u) d\tau du \\ &= \frac{N_0}{2} \int_0^{T_b} \psi^2(\tau) d\tau = \frac{N_0}{2} \end{aligned}$$

The inner integral sifts  $\delta(\tau - u)$  against  $\psi(u)$ , leaving  $\psi(\tau)$ . The unit energy of  $\psi$  then makes the answer  $N_0/2$ , independent of the interval length.

## 2.3 The decision and its error probability

#### WHAT THE DETECTOR IS GIVEN

$$\begin{aligned} \sigma_n^2 &= \frac{N_0}{2} \\ y = s_m + n &\sim \mathcal{N}\left(s_m, \frac{N_0}{2}\right) \end{aligned}$$

The two-sided convention arrives here unchanged. Reading the density as one-sided makes every error probability in the course 3 dB too optimistic, and nothing in the algebra shows it.

The detector decides  $s_1$  when  $y > \lambda$ . Write each conditional error as a Gaussian tail, using  $s_0 = -\sqrt{E_b}$ ,  $s_1 = +\sqrt{E_b}$  and  $\sigma = \sqrt{N_0/2}$ .

#### THE CONDITIONAL ERRORS, WITH THE SUBSTITUTION SHOWN

$$\begin{aligned} P(\text{err} \mid s_0) &= \int_{\lambda}^{\infty} \frac{1}{\sqrt{\pi N_0}} e^{-(y+\sqrt{E_b})^2/N_0} dy \\ &= \int_{(\lambda+\sqrt{E_b})/\sigma}^{\infty} \frac{1}{\sqrt{2\pi}} e^{-z^2/2} dz = Q\left(\frac{\lambda + \sqrt{E_b}}{\sigma}\right) \\ P(\text{err} \mid s_1) &= \int_{-\infty}^{\lambda} f_Y(y \mid s_1) dy = Q\left(\frac{\sqrt{E_b} - \lambda}{\sigma}\right) \end{aligned}$$

The substitution  $z = (y + \sqrt{E_b})/\sigma$  turns the lower limit  $y = \lambda$  into  $z = (\lambda + \sqrt{E_b})/\sigma$ , which is the argument of  $Q$ . The second line follows the same way with  $z = (\sqrt{E_b} - y)/\sigma$ .

The average error  $P_e(\lambda)$  weights each conditional error by its prior. Differentiate with respect to  $\lambda$  by the Leibniz rule, set the result to zero, and the two prior-weighted densities must be equal there.

## THE OPTIMAL THRESHOLD, DERIVED

$$P_e(\lambda) = P(s_0) P(\text{err} | s_0) + P(s_1) P(\text{err} | s_1)$$


$$\frac{dP_e}{d\lambda} = -P(s_0) f_Y(\lambda | s_0) + P(s_1) f_Y(\lambda | s_1) = 0$$

$$P(s_0) e^{-(\lambda + \sqrt{E_b})^2 / N_0} = P(s_1) e^{-(\lambda - \sqrt{E_b})^2 / N_0}$$


$$4\lambda\sqrt{E_b} = N_0 \ln \frac{P(s_0)}{P(s_1)}$$

$$\lambda_{\text{opt}} = \frac{N_0}{4\sqrt{E_b}} \ln \frac{P(s_0)}{P(s_1)}$$

The common factor  $1/\sqrt{\pi N_0}$  cancels from the equal-density equation. Taking logarithms and expanding the two squares  $(\lambda + \sqrt{E_b})^2$  and  $(\lambda - \sqrt{E_b})^2$  leaves only the term  $4\lambda\sqrt{E_b}$ , since the  $\lambda^2$  and  $E_b$  terms cancel. Equal priors put the threshold at the midpoint. If  $s_0$  is more likely, the threshold moves in the positive direction, enlarging the decision region for  $s_0$ .



**FIGURE 2.3** Equal priors: the threshold sits midway and the shaded decision regions are symmetric.



**FIGURE 2.4**  $P(s_0) = 0.7$ : the more likely symbol's curve is taller and the crossing has moved towards the less likely one.

The Gaussian tail used above is defined by an integral, and it has no closed form. A few of its values are used throughout the course.

## THE Q FUNCTION

$$Q(x) = \frac{1}{\sqrt{2\pi}} \int_x^\infty e^{-z^2/2} dz = \frac{1}{2} \operatorname{erfc}\left(\frac{x}{\sqrt{2}}\right)$$

$Q(x)$  is the probability that a Gaussian variable of mean 0 and variance 1 exceeds  $x$ . Three values recur:  $Q(1) = 0.159$ ,  $Q(2) = 0.0228$ ,  $Q(3) = 1.35 \times 10^{-3}$ .

With equal priors the threshold is at the origin,  $\lambda = 0$ , and both conditional errors become the same Gaussian tail.

## THE RESULT OF THE CHAPTER


$$\frac{\sqrt{E_b}}{\sigma} = \frac{\sqrt{E_b}}{\sqrt{N_0/2}} = \sqrt{\frac{2E_b}{N_0}}$$

$$P_b = Q\left(\sqrt{\frac{2E_b}{N_0}}\right)$$

It depends on  $E_b/N_0$  and on nothing else — not on the amplitude, not on the bit duration, not on the pulse shape. Doubling the amplitude and quartering the duration change neither the energy per bit nor the answer.

### △ ANTIPODAL AND ORTHOGONAL SIGNALS

Antipodal signaling gives  $Q\left(\sqrt{2E_b/N_0}\right)$ . On-off or orthogonal signaling gives  $Q\left(\sqrt{E_b/N_0}\right)$  and needs 3 dB more energy. For on-off signaling, half the symbols have zero energy. Therefore, average bit energy is half the nonzero-symbol energy.



**FIGURE 2.5** Bit error probability against  $E_b/N_0$ . Past about 8 dB every extra decibel is worth roughly an order of magnitude in error rate.

---

**EXAMPLE 2.2 – UNEQUAL PRIORS**

- GIVEN** A binary PAM system with correlator output  $y = \pm\sqrt{E_b} + n$ , where  $P(s_1) = 0.3$ ,  $E_b = 1$  and  $N_0 = 0.1$ .
- FIND** The optimal threshold and the average error probability there.
- METHOD** Threshold from the log-ratio of the priors. Each conditional error from a Gaussian tail. Average by weighting.
- SOLUTION**  $\lambda = \frac{0.1}{4} \ln \frac{0.7}{0.3} = 0.0212$  and  $\sigma = \sqrt{0.05} = 0.2236$ . Then  $P(\text{err} | s_0) = Q(4.567) = 2.475 \times 10^{-6}$  and  $P(\text{err} | s_1) = Q(4.377) = 6.005 \times 10^{-6}$ , so  $P_e = 0.7(2.475) + 0.3(6.005)$  in units of  $10^{-6}$ , giving  $3.534 \times 10^{-6}$ .
- CHECK** Leaving the threshold at zero would give  $Q(\sqrt{20}) = 3.872 \times 10^{-6}$ . The ratio  $3.872/3.534 = 1.096$ , so moving the threshold improves the answer by about 10 per cent. A real gain and a small one. This is what a shift of a tenth of a standard deviation buys.
-

## 2.4 Intersymbol interference

Everything above assumed an ideal channel. A real bandlimited channel spreads each pulse in time.


Therefore, one pulse can enter adjacent symbol intervals. Write the received signal as a train of the overall pulse  $p$ . Sampling at  $t_i = iT_b$  separates the wanted pulse from intersymbol interference.

WHERE THE INTERFERENCE COMES FROM


$$y(t_i) = \underbrace{\mu a_i}_{\text{wanted}} + \underbrace{\mu \sum_{k \neq i} a_k p((i-k)T_b)}_{\text{intersymbol interference}} + n(t_i)$$

The middle term is not noise. It is caused by the data itself, and raising the transmit power raises it by the same factor, so more power does not help. At high signal-to-noise ratio it is the only thing limiting the system.

An **eye pattern** shows this interference. Divide the received waveform into bit-length segments. Align the segments with the clock and draw them together. The opening height gives the noise margin. Its width gives the permitted sampling-time error. Crossing slope shows timing sensitivity, and crossing spread shows timing jitter. A closed eye has no sampling time that gives correct decisions for every bit pattern.



**FIGURE 2.6** A wide-open eye: a pulse that decays quickly. Every trace passes close to  $\pm 1$  at the centre.



**FIGURE 2.7** A slowly decaying pulse. The opening has narrowed and the crossings have scattered, with the noise unchanged.

A first-order RC lowpass channel makes the interference concrete. Its transfer function has one parameter, the 3 dB bandwidth  $B$ .

THE CHANNEL AND ITS RESPONSE TO ONE BIT

$$H(f) = \frac{1}{1 + jf/B}, \quad \tau = \frac{1}{2\pi B}$$

$$r(T_b) = 1 - q, \quad q = e^{-2\pi B T_b}$$

$\tau$  is the time constant of the channel. A single bit reaches only the fraction  $1 - q$  of its own level by the end of the bit. The rest arrives after the bit ends, as a decaying tail.

A bit that ended  $m$  bits ago still contributes to the present sample, because its tail has not fully decayed.

## ONE EARLIER BIT'S SHARE OF THE PRESENT SAMPLE, AND THE WORST CASE

$$(1 - q)q^m$$

$$\sum_{m=1}^{\infty} (1 - q)q^m = q$$

The sum is a geometric series and adds to  $q$ . When every earlier bit opposes the present one, the sample shrinks from  $1 - q$  to  $1 - 2q$ , and the eye opening is  $2(1 - 2q)$ .

The eye closes when the opening reaches zero. Set  $1 - 2q = 0$  and solve for the bandwidth.

## EYE CLOSURE

$$1 - 2q = 0 \implies e^{-2\pi BT_b} = \frac{1}{2} \implies BT_b = \frac{\ln 2}{2\pi} = 0.110$$

Below  $BT_b = 0.110$  some bit patterns cross zero at the sampling instant, and decisions fail even without noise. At  $BT_b = 0.25$ ,  $q = 0.208$ , so  $1 - q = 0.792$  and  $1 - 2q = 0.584$ . At  $BT_b = 0.3$ ,  $q = 0.152$  and the opening  $2(1 - 2q)$  is 1.39.

## EXAMPLE 2.3 – A SAMPLE WITH A BIT-PATTERN HISTORY

- GIVEN** Bits 00011101 sent after a line idle at the level of a 0 ( $a_k = -1$ ), through an RC channel with  $BT_b = 0.25$ , so  $q = 0.208$ .
- FIND** The sample at the end of the seventh bit,  $y_7$ .
- METHOD** Add the bit's own share  $(1 - q)$  or  $-(1 - q)$  to the tails of every earlier bit, each weighted by  $(1 - q)q^m$ .
- SOLUTION** The seventh bit is a 0, contributing  $-(1 - q)$ . The three 1s before it (bits four to six) contribute  $(1 - q)(q + q^2 + q^3)$ . Every bit before that, and the idle line, is a 0 and contributes  $-(1 - q) \sum_{m \geq 4} q^m$ . So  $y_7 = -(1 - q) + (1 - q)(q + q^2 + q^3) - (1 - q) \sum_{m \geq 4} q^m = -1 + 2q - 2q^4 = -0.588$ .
- CHECK** The sample is negative, so the receiver still decides 0 correctly. The result depends on the whole bit history through the geometric tails, not on the previous bit alone.

## ⊗ COMMON ERROR

Use the full history of bits, not only the previous bit. Each earlier bit still contributes through its own tail  $(1 - q)q^m$ , however small.

## 2.5 Nyquist's criterion and the raised cosine

The interference vanishes exactly when the overall pulse is zero at every sampling instant but its own. Sampling  $p$  at those instants and transforming turns that requirement into a statement about the spectrum.



## NYQUIST'S CRITERION FOR DISTORTIONLESS TRANSMISSION

$$p((i - k)T_b) = \begin{cases} 1, & i = k \\ 0, & i \neq k \end{cases}$$

$$R_b \sum_n P(f - nR_b) = 1, \quad R_b = \frac{1}{T_b}$$

In words: the replicas of the pulse spectrum, spaced by the symbol rate, must add to a constant. The simplest spectrum that does it is a rectangle of width  $2W$  with  $W = R_b/2$ , the **Nyquist bandwidth**, whose pulse is  $\text{sinc}(2Wt)$ .

✓ THE RATE A BANDWIDTH SUPPORTS

A channel of bandwidth  $W$  carries at most  $2W$  symbols per second with no interference. This is the counterpart of the sampling theorem, reached from the other end of the same argument.


The sinc pulse of the ideal Nyquist channel is impractical. Its terms fall only as  $1/(\pi|k|)$ , so the sum of their sizes grows like  $\sum 1/k$ . For example,  $\text{sinc}(0.1) = 0.984$  is barely smaller than 1. A small timing error still collects interference from many neighbours at once, because so many terms are involved. The fix is to widen the spectrum and taper its edges while keeping the tiling property.

## THE RAISED COSINE


$$P(f) = \begin{cases} \frac{1}{2W}, & |f| < f_1 \\ \frac{1}{4W} \left[ 1 + \cos \frac{\pi(|f| - f_1)}{2W - 2f_1} \right], & f_1 \leq |f| < 2W - f_1 \\ 0, & |f| \geq 2W - f_1 \end{cases}$$

$$p(t) = \text{sinc}\left(\frac{t}{T_b}\right) \frac{\cos(\pi\alpha t/T_b)}{1 - 4\alpha^2 t^2/T_b^2}, \quad f_1 = W(1 - \alpha)$$

$W = R_b/2$  and  $\alpha$  runs from 0 to 1. The sinc factor in  $p(t)$  keeps the zero crossings at  $t = iT_b$ , so the criterion still holds. For  $\alpha > 0$  the second factor falls as  $1/t^2$ , so the pulse tails fall as  $1/|t|^3$ . The price is bandwidth:  $B_T = W(1 + \alpha) = \frac{R_b}{2}(1 + \alpha)$ , an excess of  $\alpha W$  over the Nyquist bandwidth  $W$ .



**FIGURE 2.8** The spectrum at  $\alpha = 0, 0.5$  and  $1$ . All three tile the axis at spacing  $2W$ , so all three give zero interference.



**FIGURE 2.9** Their pulses. All three vanish at every non-zero multiple of  $T_b$ . The tails differ by orders of magnitude.

#### EXAMPLE 2.4 – FITTING A RATE INTO A CHANNEL

- GIVEN** A channel of bandwidth 48 kHz is to carry 64 kbit/s with raised-cosine shaping.
- FIND** The Nyquist bandwidth and the largest roll-off that fits.
- METHOD**  $W = R_b/2$ , then  $(1 + \alpha)W \leq B$ .
- SOLUTION**  $W = 32$  kHz, and  $(1 + \alpha)(32) \leq 48$  gives  $\alpha \leq 0.5$ . At  $\alpha = 0.5$  the signal uses the whole 48 kHz, with an excess of 16 kHz over the Nyquist bandwidth.
- CHECK** At  $\alpha = 0$ , the signal needs only 32 kHz and still fits. However, its pulse decays as  $1/t$ , and its ideal filter cannot be built. Using the available bandwidth gives a pulse that decays as  $1/t^3$ . The spectral efficiency is  $64/48 = 1.33$  bit/s/Hz, below the theoretical maximum of 2.

#### EXAMPLE 2.5 – THE BANDWIDTH OF A RAISED-COSINE LINK

- GIVEN** A link sends  $R_b = 20$  kb/s with raised-cosine pulses and  $\alpha = 0.5$ .
- FIND**  $W$ ,  $f_1$  and  $B_T$ .
- METHOD**  $W = R_b/2$ , then  $f_1 = W(1 - \alpha)$  and  $B_T = W(1 + \alpha)$ .
- SOLUTION**  $W = 20/2 = 10$  kHz.  $f_1 = 10(1 - 0.5) = 5$  kHz.  $B_T = 10(1 + 0.5) = 15$  kHz.
- CHECK**  $B_T - W = W - f_1 = 5$  kHz, so the roll-off is symmetric about  $W$ .

#### COMMON ERROR

Use  $W = R_b/2 = 10$  kHz, not  $W = R_b = 20$  kHz. The wrong  $W$  gives  $B_T = 30$  kHz, twice the true value.

The raised-cosine filter can be split between the transmitter and the receiver. Each half is a square root of the raised cosine.

## THE ROOT-RAISED-COSINE SPLIT

$$H_T(f) H_R(f) = P(f), \quad H_T(f) = H_R(f) = \sqrt{P(f)}$$

For a real, even  $\sqrt{P(f)}$ ,  $H_R = H_T^*$ , so the receive filter is matched to the transmitted pulse. The link then has both the smallest error probability and zero interference. At  $\alpha = 0.5$  the raised cosine is at half height at  $f = W$ , so  $\sqrt{2W P(W)} = \sqrt{0.5} = 0.707$ .

## 2.6 Summary

**TABLE 2.1** Summary of Chapter 2: baseband transmission and the matched filter.

| RESULT                   | STATEMENT                                                          | ANCHOR      |
|--------------------------|--------------------------------------------------------------------|-------------|
| Matched filter           | $h_{\text{opt}}(t) = g(T - t)$                                     | PS CH8.3.2  |
| What it achieves         | $\eta_{\text{max}} = 2E/N_0$ , independent of the pulse shape      | PS CH8.3.2  |
| Decision statistic       | $y = s_m + n$ , $n \sim \mathcal{N}(0, N_0/2)$                     | PS CH8.3.1  |
| Optimal threshold        | $\lambda = \frac{N_0}{4\sqrt{E_b}} \ln \frac{P(s_0)}{P(s_1)}$      | PS CH8.3.3  |
| Antipodal error          | $P_b = Q\left(\sqrt{2E_b/N_0}\right)$                              | PS CH8.3.3  |
| On-off error             | $P_b = Q\left(\sqrt{E_b/N_0}\right)$ , three decibels worse        | PS CH8.3.3  |
| RC-channel interference  | worst case $\sum_m (1 - q)q^m = q$ , $q = e^{-2\pi B T_b}$         | PS CH10.1.1 |
| Eye closure              | opening $2(1 - 2q)$ vanishes at $B T_b = \ln 2 / (2\pi) = 0.110$   | PS CH10.1.1 |
| Nyquist criterion        | $R_b \sum_n P(f - nR_b) = 1$                                       | PS CH10.3.1 |
| Nyquist bandwidth        | $W = R_b/2$ , the least bandwidth with zero interference           | PS CH10.3.1 |
| Raised cosine            | $B_T = W(1 + \alpha)$                                              | PS CH10.3.1 |
| Root-raised-cosine split | $H_T(f) = H_R(f) = \sqrt{P(f)}$ , matched and free of interference | PS CH10.5.1 |

Two waveforms have become two points on a line, and the error probability has turned out to depend on the distance between them. Chapter 3 asks what happens when there are more than two waveforms, and finds that the same picture works with more axes.

## CHAPTER

## 3

# Geometric representation of signal waveforms

Chapter 2 wrote two opposite waveforms as two points on a line. This chapter writes any set of waveforms as a set of points. Energy becomes a squared length, and the energy of a difference becomes a squared distance. The receiver of Chapter 4 works on these points.

## 3.1 Signals as vectors

In Chapter 2 the two waveforms were opposites, so one shape  $\psi(t)$  carried both. Now take two waveforms on  $[0, T]$  that take only the values  $\pm 1$ . The first,  $s_0(t)$ , is  $+1$  on the first half and  $-1$  on the second. The second,  $s_1(t)$ , is  $+1$  on the outer quarters and  $-1$  on the middle half.

Neither waveform is a multiple of the other. No single function  $\psi(t)$  writes both as  $s_m\psi(t)$ , so the one-number receiver of Chapter 2 does not apply. The receiver instead computes one number for each waveform.

### TWO CORRELATORS

$$y_0 = \int_0^T x(t) s_0(t) dt, \quad y_1 = \int_0^T x(t) s_1(t) dt$$

The pair  $(y_0, y_1)$  is a point in a plane. The rest of this chapter describes that plane.

Multiply the two waveforms and integrate. The product is  $+1$  on two quarters of the interval and  $-1$  on the other two, so the areas cancel.

### THE PRODUCT INTEGRATES TO ZERO

$$\int_0^T s_0(t) s_1(t) dt = \frac{T}{2} - \frac{T}{2} = 0$$

Two signals whose product integrates to zero are called **orthogonal**.




FIGURE 3.1  $s_0(t)$ FIGURE 3.2  $s_1(t)$ 

FIGURE 3.3 Their product: +1 on two quarters and -1 on two.

Vectors give the pattern to copy. A vector written against unit axes is the list of its coordinates,  $\mathbf{a} = (a_1, \dots, a_N)$ . Its length and its angle to another vector come from that list.

#### INNER PRODUCT AND LENGTH, FOR VECTORS AND FOR SIGNALS

$$\langle \mathbf{a}, \mathbf{b} \rangle = \sum_{k=1}^N a_k b_k, \quad \|\mathbf{a}\| = \sqrt{\langle \mathbf{a}, \mathbf{a} \rangle}$$

$$\langle x, y \rangle = \int_{-\infty}^{\infty} x(t) y(t) dt, \quad \|x\|^2 = \int_{-\infty}^{\infty} x^2(t) dt = E_x$$

For signals the sum over entries becomes an integral over time. The squared length of a signal is its energy.

Axes for signals are functions with unit energy that are orthogonal in pairs. Such a set is called **orthonormal**.

#### AN ORTHONORMAL SET

$$\int_{-\infty}^{\infty} \psi_j(t) \psi_k(t) dt = \begin{cases} 1, & j = k \\ 0, & j \neq k \end{cases}$$

The first case says each function has unit energy. The second says any two of them are orthogonal.

#### ① ORTHOGONAL SIGNALS

Pulses that never overlap are orthogonal. Where one pulse is nonzero, the other is zero. Therefore, their product is zero everywhere.

A pulse  $\psi(t) = c$  on  $[0, 2]$  has energy  $\int_0^2 c^2 dt = 2c^2$ . Unit energy needs  $2c^2 = 1$ , so  $c = 1/\sqrt{2} = 0.707$ .

With the axes fixed, a waveform is written against them as a vector is. One integral for each axis takes the waveform apart. This step is called **analysis**.

## ANALYSIS AND SYNTHESIS

$$s_{ij} = \int_0^T s_i(t) \psi_j(t) dt, \quad j = 1, \dots, N$$

$$s_i(t) = \sum_{j=1}^N s_{ij} \psi_j(t), \quad \mathbf{s}_i = (s_{i1}, \dots, s_{iN})$$

The second line, **synthesis**, builds the waveform back from its  $N$  numbers. It is exact when every signal of the set is a combination of the  $\psi_j$ . The list  $\mathbf{s}_i$  is the **signal vector**.

For example, take  $\psi_1 = 1$  on  $[0, 1)$  and  $\psi_2 = 1$  on  $[1, 2)$ . Let  $s(t) = 3$  on  $[0, 1)$  and  $s(t) = -1$  on  $[1, 2)$ . Each coordinate is one integral over the interval where its axis is nonzero.

## THE COORDINATES OF ONE WAVEFORM

$$s_1 = \int_0^1 3 \cdot 1 dt = 3$$

$$s_2 = \int_1^2 (-1) \cdot 1 dt = -1$$

So  $\mathbf{s} = (3, -1)$ , and  $s(t) = 3\psi_1(t) - \psi_2(t)$ .

The **analyzer** is a bank of  $N$  correlators. Correlator  $j$  multiplies the waveform by  $\psi_j(t)$  and integrates over  $[0, T]$ . Its output is the coordinate  $s_{ij}$ .

The **synthesizer** does the reverse. It scales each  $\psi_j(t)$  by  $s_{ij}$  and adds the results. So the transmitter can build every waveform of the set from  $N$  basis functions.

 NUMBER OF CORRELATORS

The analyzer needs one correlator for each basis function, not one for each waveform. A set of  $M = 8$  waveforms that spans  $N = 2$  dimensions needs 2 correlators.

The translation keeps inner products. The proof takes three moves. Write both signals in the basis. Move the integral inside both sums. Then use orthonormality: each cross term gives 0 and each matching term gives 1.

## INNER PRODUCTS ARE PRESERVED

$$\begin{aligned}
\int_{-\infty}^{\infty} x(t) y(t) dt &= \int_{-\infty}^{\infty} \left( \sum_{j=1}^N x_j \psi_j(t) \right) \left( \sum_{k=1}^N y_k \psi_k(t) \right) dt \\
&= \sum_{j=1}^N \sum_{k=1}^N x_j y_k \int_{-\infty}^{\infty} \psi_j(t) \psi_k(t) dt \\
&= \sum_{k=1}^N x_k y_k = \langle \mathbf{x}, \mathbf{y} \rangle
\end{aligned}$$

An integral over two waveforms has become a sum over  $N$  pairs of numbers.

Check it on  $x = 2\psi_1 + \psi_2$  and  $y = \psi_1 - \psi_2$ , with the two unit pulses as basis. The product  $x(t)y(t)$  is 2 on  $[0, 1)$  and  $-1$  on  $[1, 2)$ .

## THE SIGNED AREA AND THE COORDINATES AGREE

$$\int_0^2 x(t) y(t) dt = 2 - 1 = 1, \quad x_1 y_1 + x_2 y_2 = 2(1) + 1(-1) = 1$$

Two special cases follow. Put  $y = x$  to get the energy. Apply the result to the difference  $s_i - s_k$ , whose vector is  $\mathbf{s}_i - \mathbf{s}_k$ , to get a distance.

## ENERGY AND DISTANCE

$$\begin{aligned}
E_i &= \int_0^T s_i^2(t) dt = \sum_{j=1}^N s_{ij}^2 = \|\mathbf{s}_i\|^2 \\
d_{ik}^2 &= \|\mathbf{s}_i - \mathbf{s}_k\|^2 = \int_0^T (s_i(t) - s_k(t))^2 dt
\end{aligned}$$

Energy is the squared distance from a point to the origin. The energy of a difference is the squared distance between two points.

Noise moves the received point. Two points far apart are hard to confuse, so the distance  $d_{ik}$  decides the error rate. Chapter 4 derives the rule.

For example,  $\mathbf{s}_1 = (1, 1)$  and  $\mathbf{s}_2 = (1, -1)$  differ by  $(0, 2)$ . So  $d_{12} = \sqrt{0^2 + 2^2} = 2$ , and the energy of  $\mathbf{s}_1 - \mathbf{s}_2$  is 4.

**EXAMPLE 3.1 – A BASIS BY INSPECTION**

- GIVEN** Four signals on  $[0, 2)$ . Each is  $+1$  or  $-1$  on  $[0, 1)$  and  $+1$  or  $-1$  on  $[1, 2)$ , giving all four sign pairs.
- FIND** An orthonormal basis, the four signal vectors and the number of basis functions.
- METHOD** Every signal is constant on the same two intervals. So read the basis off those pieces, then check unit energy and orthogonality.
- SOLUTION** Take  $\psi_1 = 1$  on  $[0, 1)$  and  $\psi_2 = 1$  on  $[1, 2)$ . Each has energy 1, and  $\int \psi_1 \psi_2 dt = 0$  because the pulses never overlap. Each coordinate is the height on that half times its width 1. So  $\mathbf{s}_1 = (1, 1)$ ,  $\mathbf{s}_2 = (1, -1)$ ,  $\mathbf{s}_3 = (-1, 1)$ ,  $\mathbf{s}_4 = (-1, -1)$ , and  $N = 2$ .
- CHECK** From the vectors, each energy is  $1^2 + 1^2 = 2$ . From the waveforms,  $\int_0^2 (\pm 1)^2 dt = 2$  as well.

**⊗ COMMON ERROR**


Use a unit-energy function as an axis, not  $\mathbf{s}_1$  itself.  $\mathbf{s}_1$  has energy 2, so every coordinate on it comes out a factor  $\sqrt{2}$  wrong.

## 3.2 Constellations

The **constellation diagram** draws the signal vectors in the space of their basis. It has one point for each waveform and one axis for each basis function.

Three things are read off it. The distance from the origin to a point is  $\sqrt{E_i}$ . The distance between two points is the root of the energy of their difference. The number of axes is the number of correlators the receiver needs.





**FIGURE 3.4** The four signals of Example 3.1 as a constellation. Every point lies on the circle of radius  $\sqrt{E} = \sqrt{2}$ , and neighbours are  $d = 2$  apart.


In this square the smallest distance is  $d_{\min} = 2$ , between neighbours such as  $(1, 1)$  and  $(1, -1)$ . The diagonal pairs are  $2\sqrt{2} = 2.83$  apart.

Three binary signal sets can now be compared by the distance between their two points. Each set has the same average energy per bit,  $E_b$ .


**Antipodal** signals satisfy  $s_2(t) = -s_1(t)$ . They need one axis, and the points  $\pm\sqrt{E_b}$  are  $d = 2\sqrt{E_b}$  apart. Polar NRZ and BPSK are antipodal.

**Orthogonal** signals satisfy  $\langle s_1, s_2 \rangle = 0$ . They need two axes, and the points  $(\sqrt{E_b}, 0)$  and  $(0, \sqrt{E_b})$  are  $d = \sqrt{2E_b}$  apart. PPM and FSK are orthogonal.


**On-off** signals send 0 or  $s(t)$  with equal priors. The average energy is  $E_b$ , so  $s(t)$  has energy  $2E_b$ . The points are 0 and  $\sqrt{2E_b}$ , again  $d = \sqrt{2E_b}$  apart.



**FIGURE 3.5** Antipodal: one axis.  
Drawn in units of  $\sqrt{E_b}$ .



**FIGURE 3.6** Orthogonal: two axes.  
Drawn in units of  $\sqrt{E_b}$ .



**FIGURE 3.7** On-off: one point at the origin.  
Drawn in units of  $\sqrt{E_b}$ .

Find the energy each set needs to reach the same distance  $d$ . Square the two distance formulas and set them equal.

#### ENERGY FOR EQUAL DISTANCE

$$4E_b^{\text{anti}} = d^2 = 2E_b^{\text{orth}}$$

$$\frac{E_b^{\text{orth}}}{E_b^{\text{anti}}} = 2 = 3.01 \text{ dB}$$


Orthogonal and on-off signalling need twice the energy of antipodal signalling for the same distance. This is the 3 dB gap between the error probabilities  $Q\left(\sqrt{2E_b/N_0}\right)$  and  $Q\left(\sqrt{E_b/N_0}\right)$  of Chapter 2, where  $Q$  is the Gaussian tail.

A carrier gives two axes. A cosine and a sine at the same frequency  $f_c$  are orthonormal over  $[0, T]$  when each holds whole cycles there.

#### THE TWO CARRIER AXES

$$\psi_1(t) = \sqrt{\frac{2}{T}} \cos(2\pi f_c t), \quad \psi_2(t) = \sqrt{\frac{2}{T}} \sin(2\pi f_c t), \quad 0 \leq t \leq T$$

$f_c T$  is a whole number, so each function holds whole cycles in  $[0, T]$ .



**FIGURE 3.8** The two axes with  $T = 1$  and  $f_c T = 3$ :  $\psi_1$  solid and  $\psi_2$  dashed. Each holds whole cycles in  $[0, T]$ .

Check unit energy first. Use  $2 \cos^2 a = 1 + \cos 2a$ , then integrate term by term.

## UNIT ENERGY

$$\begin{aligned}
 \int_0^T \psi_1^2 dt &= \frac{2}{T} \int_0^T \cos^2(2\pi f_c t) dt \\
 &= \frac{1}{T} \int_0^T [1 + \cos(4\pi f_c t)] dt \\
 &= 1 + \frac{\sin(4\pi f_c T)}{4\pi f_c T} = 1
 \end{aligned}$$

The sine is zero because  $4\pi f_c T$  is a whole multiple of  $2\pi$ . The same steps with  $2 \sin^2 a = 1 - \cos 2a$  give unit energy for  $\psi_2$ .

Then check orthogonality. Use  $2 \cos a \sin a = \sin 2a$ .

## THE COSINE AND THE SINE ARE ORTHOGONAL

$$\begin{aligned}
 \int_0^T \psi_1 \psi_2 dt &= \frac{2}{T} \int_0^T \cos(2\pi f_c t) \sin(2\pi f_c t) dt \\
 &= \frac{1}{T} \int_0^T \sin(4\pi f_c t) dt \\
 &= \frac{1 - \cos(4\pi f_c T)}{4\pi f_c T} = 0
 \end{aligned}$$

The product holds  $2f_c T$  whole cycles, and  $\cos(4\pi f_c T) = 1$ .

A carrier of energy  $E$  and phase  $\theta$  is one point in this plane. Expand the cosine of a difference to find its coordinates.

A CARRIER WITH PHASE  $\theta$ 

$$\begin{aligned}
 s(t) &= \sqrt{\frac{2E}{T}} \cos(2\pi f_c t - \theta) \\
 &= \sqrt{\frac{2E}{T}} [\cos \theta \cos(2\pi f_c t) + \sin \theta \sin(2\pi f_c t)] \\
 &= \sqrt{E} \cos \theta \psi_1(t) + \sqrt{E} \sin \theta \psi_2(t)
 \end{aligned}$$

The point is  $(\sqrt{E} \cos \theta, \sqrt{E} \sin \theta)$ , on the circle of radius  $\sqrt{E}$ . At  $\theta = 90^\circ$  it is  $(0, \sqrt{E})$ , because  $\cos(x - 90^\circ) = \sin x$ .

## ① ORTHOGONAL CARRIERS

Two sinusoids are orthogonal over  $T$  when each holds a whole number of cycles in  $T$  and the numbers differ. Wi-Fi spaces its subcarriers  $\Delta f = 312.5$  kHz apart. So each holds whole cycles in one symbol of  $T = 3.2 \mu\text{s}$ .

### EXAMPLE 3.2 – FOUR CARRIER WAVEFORMS

- GIVEN** For  $0 \leq t \leq T$  and whole  $f_c T$ :  $s_{1,2}(t) = \mp \sqrt{2/T} \cos(2\pi f_c t) + \sqrt{2/T} \sin(2\pi f_c t)$  and  $s_{3,4}(t) = \mp \sqrt{2/T} \cos(2\pi f_c t) - \sqrt{2/T} \sin(2\pi f_c t)$ .
- FIND** A basis, the four signal vectors, their energies and  $d_{\min}$ .
- METHOD** Every waveform is already a sum of  $\psi_1$  and  $\psi_2$  above. So the basis is found by inspection, and the coefficients are the coordinates.
- SOLUTION** Each waveform is  $s_i(t) = s_{i1}\psi_1(t) + s_{i2}\psi_2(t)$  with  $s_{ij} = \pm 1$ . So  $\mathbf{s}_1 = (-1, 1)$ ,  $\mathbf{s}_2 = (1, 1)$ ,  $\mathbf{s}_3 = (-1, -1)$  and  $\mathbf{s}_4 = (1, -1)$ . Each energy is  $1 + 1 = 2$ . Neighbours differ by 2 in one coordinate, so  $d_{\min} = 2$ .
- CHECK** The four points form the square of Example 3.1. The waveforms differ, and the constellation is the same.

#### ⊗ COMMON ERROR

Use  $\pm 1$  as the coordinate, not  $\pm \sqrt{2/T}$ . The factor  $\sqrt{2/T}$  belongs to the basis function  $\psi_j$ , so it is already inside the axis.

The pulse set of Example 3.1 and the carrier set of Example 3.2 share one constellation. Sets like these are called **geometrically equivalent**.

Geometrically equivalent sets need the same receiver. They also have the same error probability in white Gaussian noise, because both follow from the points alone.

#### ⚠ BANDWIDTH

The constellation does not fix the bandwidth. The pulse set occupies frequencies near  $f = 0$ , and the carrier set occupies frequencies near  $f_c$ . Bandwidth follows from the waveform shapes.

$M$  carriers of equal energy at equally spaced phases form **M-ary phase shift keying**, or M-PSK. Every point lies on one circle.

#### THE M-PSK SIGNAL SET

$$s_i(t) = A \cos\left(2\pi f_c t - \frac{2\pi i}{M}\right), \quad i = 0, \dots, M-1$$

$$\mathbf{s}_i = \sqrt{E} \left( \cos \frac{2\pi i}{M}, \sin \frac{2\pi i}{M} \right), \quad E = \frac{A^2 T}{2}$$

The second line is the carrier result above with  $\theta = 2\pi i/M$  and  $A = \sqrt{2E/T}$ .

Neighbouring points are  $2\pi/M$  apart in angle. Take the difference of  $\mathbf{s}_0$  and  $\mathbf{s}_1$ , square its length, and use  $1 - \cos 2a = 2 \sin^2 a$ .

## THE DISTANCE BETWEEN NEIGHBOURS


$$\begin{aligned}
 d_{\min}^2 &= E \left[ \left(1 - \cos \frac{2\pi}{M}\right)^2 + \sin^2 \frac{2\pi}{M} \right] \\
 &= E \left[ 2 - 2 \cos \frac{2\pi}{M} \right] \\
 &= 4E \sin^2 \frac{\pi}{M}
 \end{aligned}$$

$$d_{\min} = 2\sqrt{E} \sin \frac{\pi}{M}$$


The middle step uses  $\cos^2 a + \sin^2 a = 1$ . Each doubling of  $M$  adds one bit a symbol and brings neighbours closer.

For 8-PSK at  $E = 1$ ,  $d_{\min} = 2 \sin(\pi/8) = 2(0.383) = 0.765$ . QPSK at  $E = 2$  gives  $d_{\min} = 2\sqrt{2} \sin(\pi/4) = 2\sqrt{2}(0.707) = 2$ , the square of Example 3.2.

Square grids of points, called QAM, carry more bits a symbol. At average energy 1,  $d_{\min}$  is 2 for BPSK, 0.632 for 16-QAM and 0.309 for 64-QAM.



**FIGURE 3.9** Example 3.2 as QPSK: four points on the circle of radius  $\sqrt{2}$ , with  $d_{\min} = 2$ .



**FIGURE 3.10** 8-PSK at  $E = 1$ : eight points on the unit circle. Neighbours are 0.765 apart.

### 3.3 The Gram–Schmidt procedure

So far each basis was found by inspection. The **Gram–Schmidt procedure** finds one for any set of  $M$  waveforms. It takes the signals in turn and keeps only what is new in each.

Start with the first signal and scale it to unit energy.

## STEP 1

$$E_1 = \int s_1^2(t) dt, \quad \psi_1(t) = \frac{s_1(t)}{\sqrt{E_1}}$$

The first axis is the first signal scaled to unit energy. The coordinate of  $s_1$  on it is  $s_{11} = \sqrt{E_1}$ .

For each later signal  $s_k$ , find its coordinates on the axes found so far. Subtract those parts. Then scale the nonzero remainder to unit energy.

#### STEP $k$

$$s_{ki} = \int s_k(t) \psi_i(t) dt, \quad g_k(t) = s_k(t) - \sum_{i=1}^{k-1} s_{ki} \psi_i(t)$$

$$\psi_k(t) = \frac{g_k(t)}{\sqrt{E_{g_k}}}, \quad E_{g_k} = \int g_k^2(t) dt$$

The remainder  $g_k(t)$  is orthogonal to every earlier axis, so  $\psi_k$  is a new axis.

#### STOP RULE

If  $g_k(t) = 0$ , then  $s_k$  is a combination of earlier signals and adds no axis. So  $N \leq M$ , with  $N = M$  only when no signal is a combination of the others.

The energy of a remainder follows from the energy result. With one earlier axis,  $g_2$  is orthogonal to  $\psi_1$ . So the energy of  $s_2$  splits into two squared lengths.

#### THE ENERGY OF THE REMAINDER

$$E_2 = s_{21}^2 + E_{g_2} \implies E_{g_2} = E_2 - s_{21}^2$$

For example,  $E_2 = 25$  and  $s_{21} = 3$  give  $E_{g_2} = 25 - 3^2 = 16$ .

Example 3.3 runs the procedure on three rectangular pulses. The third pulse is the first one followed by the second.




FIGURE 3.11  $s_1$




FIGURE 3.12  $s_2$




FIGURE 3.13  $s_3 = s_1 + s_2$


### EXAMPLE 3.3 – THREE PULSES, TWO AXES

- GIVEN**  $s_1(t) = 1$  on  $[0, 2]$ ,  $s_2(t) = 1$  on  $[2, 3]$  and  $s_3(t) = 1$  on  $[0, 3]$ . Each is zero elsewhere.
- FIND** An orthonormal basis, the three signal vectors and the constellation.
- METHOD** Gram–Schmidt needs no guess about the basis. Normalise the first signal. For each later signal, subtract its parts along the axes found so far and normalise the remainder.
- STEP 1**  $E_1 = \int_0^2 1^2 dt = 2$ , so  $\psi_1(t) = 1/\sqrt{2}$  on  $[0, 2]$  and  $s_{11} = \sqrt{2}$ .
- STEP 2**  $s_{21} = \int s_2 \psi_1 dt = 0$ , because the two never overlap. So  $g_2 = s_2$ , its energy is 1, and  $\psi_2(t) = s_2(t)$ .
- STEP 3**  $s_{31} = \int_0^2 1 \cdot \frac{1}{\sqrt{2}} dt = \sqrt{2}$  and  $s_{32} = \int_2^3 1 \cdot 1 dt = 1$ . Then  $g_3 = s_3 - \sqrt{2} \psi_1 - \psi_2 = 0$ , so no third axis is added.
- SOLUTION**  $\mathbf{s}_1 = (\sqrt{2}, 0)$ ,  $\mathbf{s}_2 = (0, 1)$  and  $\mathbf{s}_3 = (\sqrt{2}, 1)$ , with  $N = 2$ .
- CHECK** Energies from the vectors are 2, 1 and 3. From the waveforms, height 1 over lengths 2, 1 and 3 gives the same values. Three waveforms need only two axes, because  $s_3 = s_1 + s_2$ .

#### ⊗ COMMON ERROR

Use  $\psi_1 = 0$  on  $[2, 3]$ , not  $\psi_1 = 1/\sqrt{2}$  there. The integral for  $s_{31}$  then runs over  $[0, 2]$  only, and  $s_{31} = \sqrt{2}$ .

The constellation of Example 3.3 has two axes and three points.



**FIGURE 3.14** Two axes carry three signals. The point furthest from the origin is  $\mathbf{s}_3$ , whose energy is 3.

Example 3.4 needs three axes for four signals. Its pieces overlap, so no basis can be read off at once.

### EXAMPLE 3.4 – FOUR SIGNALS, THREE AXES


- GIVEN**  $s_1 = 1$  on  $[0, 2)$ .  $s_2 = 1$  on  $[0, 1)$  and  $-1$  on  $[1, 2)$ .  $s_3 = -1$  on  $[0, 1)$  and  $1$  on  $[1, 3)$ .  $s_4 = 1$  on  $[0, 3)$ . Each is zero elsewhere.
- FIND** The basis, the four signal vectors and the number of dimensions  $N$ .
- METHOD** Run Gram–Schmidt in the order  $s_1, s_2, s_3, s_4$ . Each coordinate is a sum of piece heights times piece widths.
- STEP 1**  $E_1 = \int_0^2 1^2 dt = 2$ , so  $\psi_1 = s_1/\sqrt{2}$ .
- STEP 2**  $s_{21} = \frac{1}{\sqrt{2}}(1 - 1) = 0$ . So  $g_2 = s_2$ , with energy 2, and  $\psi_2 = s_2/\sqrt{2}$ .
- STEP 3**  $s_{31} = \frac{1}{\sqrt{2}}(-1 + 1) = 0$  and  $s_{32} = \frac{1}{\sqrt{2}}(-1 - 1) = -\sqrt{2}$ . Then  $g_3 = s_3 + \sqrt{2}\psi_2 = s_3 + s_2$ , which is 1 on  $[2, 3)$  and zero elsewhere. Its energy is 1, so  $\psi_3 = g_3$ .
- STEP 4**  $s_{41} = \frac{1}{\sqrt{2}}(1 + 1) = \sqrt{2}$ ,  $s_{42} = \frac{1}{\sqrt{2}}(1 - 1) = 0$  and  $s_{43} = \int_2^3 1 dt = 1$ . Then  $g_4 = s_4 - \sqrt{2}\psi_1 - \psi_3 = 0$ , so  $s_4$  adds no axis.
- SOLUTION**  $\mathbf{s}_1 = (\sqrt{2}, 0, 0)$ ,  $\mathbf{s}_2 = (0, \sqrt{2}, 0)$ ,  $\mathbf{s}_3 = (0, -\sqrt{2}, 1)$  and  $\mathbf{s}_4 = (\sqrt{2}, 0, 1)$ , with  $N = 3$ .
- CHECK** Energies from the vectors are 2, 2, 3 and 3, equal to  $\int s_i^2 dt$ . Also  $\mathbf{s}_1 + \mathbf{s}_2 + \mathbf{s}_3 = \mathbf{s}_4$ , matching  $s_4 = s_1 + s_2 + s_3$ .

#### ⊗ COMMON ERROR

Count one axis for each nonzero remainder, not one for each signal. Here  $g_4 = 0$ , so  $N = 3$ , not 4.

The four vectors of Example 3.4 are drawn in three dimensions below, seen from an angle.





**FIGURE 3.15** Four signals need three axes.  $s_4$  sits one unit above  $s_1$ , along  $\psi_3$ .

The basis is not unique. Taking the signals in another order in Gram–Schmidt gives another orthonormal basis of the same space. The new axes are the old ones turned or reflected.

The coordinates change. The number of axes, the energies, the inner products and the distances do not, because each is an integral of the waveforms.

#### UNCHANGED BY A CHANGE OF BASIS

$$N, \quad \|s_i\|^2 = E_i, \quad \langle s_i, s_k \rangle, \quad \|s_i - s_k\|$$

For example, turn the axes of Example 3.1 by  $45^\circ$ . The new first axis is  $\psi'_1 = (\psi_1 + \psi_2)/\sqrt{2}$ , and the new second axis is  $\psi'_2 = (\psi_2 - \psi_1)/\sqrt{2}$ .

#### THE NEW COORDINATES OF $s_1 = (1, 1)$

$$\langle s_1, \psi'_1 \rangle = \frac{1+1}{\sqrt{2}} = \sqrt{2}$$

$$\langle s_1, \psi'_2 \rangle = \frac{-1+1}{\sqrt{2}} = 0$$

All the length  $\sqrt{2}$  of  $s_1$  now lies on  $\psi'_1$ . Its energy is still 2.

### 3.4 Summary

**TABLE 3.1** Summary of Chapter 3: the geometric representation of signal waveforms.

| RESULT                   | STATEMENT                                                                                       | ANCHOR     |
|--------------------------|-------------------------------------------------------------------------------------------------|------------|
| Orthonormal set          | $\int \psi_j \psi_k dt = 1$ if $j = k$ , else 0                                                 | PS CH8.1   |
| Analysis                 | $s_{ij} = \int_0^T s_i \psi_j dt$ , one correlator for each basis function                      | PS CH8.1   |
| Synthesis                | $s_i(t) = \sum_j s_{ij} \psi_j(t)$                                                              | PS CH8.1   |
| Inner products preserved | $\int xy dt = \sum_k x_k y_k$                                                                   | PS CH8.1   |
| Energy                   | $E_i = \ \mathbf{s}_i\ ^2$                                                                      | PS CH8.1   |
| Distance                 | $d_{ik}^2 = \ \mathbf{s}_i - \mathbf{s}_k\ ^2 = \int (s_i - s_k)^2 dt$                          | PS CH8.1   |
| Constellation            | one point for each waveform, one axis for each basis function                                   | PS CH8.1   |
| Binary sets              | antipodal $d = 2\sqrt{E_b}$ , orthogonal and on-off $d = \sqrt{2E_b}$ , a 3 dB gap              | PS CH8.2   |
| Carrier axes             | $\sqrt{2/T} \cos(2\pi f_c t)$ and $\sqrt{2/T} \sin(2\pi f_c t)$ , orthonormal for whole $f_c T$ | PS CH8.6.1 |
| QPSK                     | $(\pm 1, \pm 1)$ , energy 2, $d_{\min} = 2$                                                     | PS CH8.6.1 |
| M-PSK                    | $d_{\min} = 2\sqrt{E} \sin(\pi/M)$                                                              | PS CH8.6.1 |
| Geometric equivalence    | same constellation, same receiver and error probability, bandwidth not fixed                    | PS CH8.1   |
| Gram–Schmidt             | $g_k = s_k - \sum_{i < k} s_{ki} \psi_i$ , and $\psi_k = g_k / \sqrt{E_{g_k}}$                  | PS CH8.1   |
| Dimension                | $N \leq M$ , and a zero remainder adds no axis                                                  | PS CH8.1   |
| Change of basis          | $N$ , energies and distances unchanged                                                          | PS CH8.1   |

Every waveform set is now a set of points, with energy as squared length and the energy of a difference as squared distance. Chapter 4 builds the receiver on these points. It correlates to find the received point and picks the nearest signal point. Its error probability depends only on the distances between the points.

## CHAPTER

## 4

# The optimal receiver in additive white Gaussian noise

A transmitter picks one of  $M$  signals and sends it. The channel adds noise. The receiver has to name the signal. Chapter 3 turned the signals into points. This chapter turns the receiver into a rule about those points, and the rule is simple: choose the point nearest to what arrived.

## 4.1 What the receiver keeps

The received signal is  $r(t) = s_i(t) + n(t)$  over one symbol interval. The receiver has  $N$  correlators, one for each basis function, and each returns one number.

### THE OBSERVATION VECTOR

$$r_k = \int_0^T r(t) \psi_k(t) dt = s_{ik} + n_k$$

$$\mathbf{r} = \mathbf{s}_i + \mathbf{n} = (r_1, \dots, r_N)$$

The signal was built from the  $N$  basis functions, so the correlators capture all of it. The noise was not: the part of it outside the signal space, written  $n_0(t)$ , is thrown away.

### ✓ NOISE OUTSIDE THE SIGNAL SPACE

The component  $n_0(t)$  contains no signal because every signal lies in the basis span. It is also independent of the retained coordinates. Therefore, it cannot help the receiver identify the transmitted signal. The receiver still keeps all noise components inside the signal space.

Each  $n_k$  is a projection of a Gaussian process onto a fixed function, so it is Gaussian with zero mean. The useful part is what happens between two of them: using  $E[n(\tau)n(u)] = \frac{N_0}{2} \delta(\tau - u)$  and orthonormality,  $E[n_j n_k]$  is  $N_0/2$  when  $j = k$  and zero otherwise. Uncorrelated jointly Gaussian variables are independent, so the noise components are independent, each  $\mathcal{N}(0, N_0/2)$ .

### ① NOISE GEOMETRY

Every axis has the same variance, and the axes are independent. Therefore, the noise cloud is circular in two dimensions and spherical in  $N$  dimensions. This symmetry gives the nearest-point decision rule.

## 4.2 The decision rule

The receiver should choose the signal that is most likely given what it saw. By Bayes' rule that means maximising  $P(s_i)f_r(\mathbf{r} | s_i)$  — the prior times the likelihood. This is the **MAP** rule, and no rule has a smaller error probability. If all  $M$  signals are equally likely the priors cannot change the answer, and what is left is the **ML** rule: maximise the likelihood alone.

Substitute the noise density into the likelihood. Then take its logarithm. The logarithm is increasing, so it does not change the maximizing signal. It converts the product into a sum and isolates the term that depends on  $i$ .

### MINIMUM-DISTANCE DETECTION

$$\ln f_r(\mathbf{r} | s_i) = -\frac{N}{2} \ln(\pi N_0) - \frac{1}{N_0} \|\mathbf{r} - \mathbf{s}_i\|^2$$

$$\hat{s} = \arg \min_i \|\mathbf{r} - \mathbf{s}_i\|^2 \quad (\text{ML})$$

$$\hat{s} = \arg \min_i \left\{ \|\mathbf{r} - \mathbf{s}_i\|^2 - N_0 \ln P(s_i) \right\} \quad (\text{MAP})$$

Select the signal point with the smallest metric. For unequal priors, the prior term changes each distance metric. A more likely symbol receives a larger decision region.

Expanding the squared distance gives the form a receiver is actually built in. The term  $\|\mathbf{r}\|^2$  is the same for every  $i$  and drops out. Turning the minimum into a maximum and dividing by two leaves the **correlation metric**.

### THE RECEIVER AS IT IS BUILT

$$\hat{s} = \arg \max_i \left\{ \mathbf{r} \cdot \mathbf{s}_i - \frac{E_i}{2} + \frac{N_0}{2} \ln P(s_i) \right\}$$

And  $\mathbf{r} \cdot \mathbf{s}_i = \int_0^T r(t)s_i(t) dt$ , so the receiver can correlate against the waveforms directly and never compute coordinates. If the signals are equally likely **and** have equal energy, both corrections vanish and the rule is: take the largest correlation.

### ⚠ UNEQUAL SIGNAL ENERGIES

Keep  $-E_i/2$  when signal energies differ. Without it, a large  $\mathbf{s}_i$  makes the correlation metric favor a high-energy signal. This error makes an on-off receiver select "one" too often. Equal priors remove only the prior term.


## 4.3 Decision regions

Collecting the observations that give the same answer divides the space into  $M$  regions,  $R_i = \{\mathbf{r} : \|\mathbf{r} - \mathbf{s}_i\| \leq \|\mathbf{r} - \mathbf{s}_j\| \text{ for all } j\}$ . Three facts describe them, and all three follow from the rule being "nearest point".


1. A boundary between two points is **perpendicular** to the line joining them.

2. With equal priors it crosses that line exactly **halfway**.
3. With unequal priors it moves, and **the region of the less likely signal shrinks**.


A decision boundary is the perpendicular bisector of two signal points. Only nearest neighbors contribute boundaries. An interior point has a bounded decision region. An outer point has an unbounded region and usually fewer nearest neighbors.



**FIGURE 4.1** Two points, equal priors: the boundary is halfway.



**FIGURE 4.2** The left symbol four times more likely: its region has grown.



**FIGURE 4.3** Four points, four boundaries, each perpendicular to the pair it separates.

For two equally likely points a distance  $d$  apart, the boundary is  $d/2$  from each. An error happens when the noise along the line joining them carries the observation across, and the noise on any one axis is  $\mathcal{N}(0, N_0/2)$ .

#### THE BINARY RESULT, FROM THE PICTURE

$$P_e = Q\left(\frac{d/2}{\sqrt{N_0/2}}\right) = Q\left(\sqrt{\frac{d^2}{2N_0}}\right)$$

$$\mu = \frac{d}{2} + \frac{N_0}{2d} \ln \frac{P(\mathbf{s}_1)}{P(\mathbf{s}_0)}$$

The second line is where the boundary sits when the priors are unequal, measured from the first point along the line. Equal priors give  $\mu = d/2$ .

#### ✓ BINARY ERROR PROBABILITY

The binary error probability depends only on the distance between the two signal points. Antipodal points are  $2\sqrt{E_b}$  apart. On-off or orthogonal points are  $\sqrt{2E_b}$  apart. The factor  $\sqrt{2}$  gives the 3 dB difference from Chapter 2.

## 4.4 The union bound

For more than two signals, the exact error is an  $N$ -dimensional integral over each decision region. A region can have many faces. A simple closed form is usually unavailable. The union bound gives a computable upper bound.

Suppose  $\mathbf{s}_k$  was sent, and let  $A_{kj}$  be the event that the observation is closer to  $\mathbf{s}_j$  than to  $\mathbf{s}_k$ . An error happens exactly when at least one of those occurs, and the probability of a union is at most the sum of the probabilities. Each term is a two-point question whose answer is already known.

## THE UNION BOUND AND ITS THREE USABLE FORMS

$$P(\mathbf{s}_k \rightarrow \mathbf{s}_j) = Q\left(\sqrt{\frac{d_{kj}^2}{2N_0}}\right)$$

$$P_e \leq \frac{1}{M} \sum_k \sum_{j \neq k} Q\left(\sqrt{\frac{d_{kj}^2}{2N_0}}\right)$$

$$P_e \leq (M-1)Q\left(\sqrt{\frac{d_{\min}^2}{2N_0}}\right), \quad P_e \approx N_{\min}Q\left(\sqrt{\frac{d_{\min}^2}{2N_0}}\right)$$

$N_{\min}$  is the *average* number of points at the minimum distance, and need not be an integer. The last form is the one used in practice.

One more tightening is available, and it costs nothing. To land nearer a different point the observation must leave its own region, and it leaves through a **face**. A piece of boundary shared with one particular neighbour. A point that shares no face with the region cannot be the first one reached. Therefore, the union need only run over the neighbours that bound the region. Write  $\mathcal{N}(k)$  for those.

## THE INTELLIGENT UNION BOUND

$$P(\text{error} \mid \mathbf{s}_k) \leq \sum_{j \in \mathcal{N}(k)} Q\left(\sqrt{\frac{d_{kj}^2}{2N_0}}\right)$$


Still an upper bound, because leaving the region means crossing one of its faces. It is not the nearest-neighbour form: this one counts *faces* and bounds, that one counts *points at  $d_{\min}$*  and approximates. They agree whenever every face sits at  $d_{\min}$ , and part company when a face is shared with a point further away.

## ⚠ UNION-BOUND GAP

Pairwise error events can overlap, so their sum can count one observation more than once. The bound can exceed one at low signal-to-noise ratio. At high ratios, the overlaps become small and the bound approaches the exact error probability.

### EXAMPLE 4.1 – FOUR BOUNDS ON ONE CONSTELLATION

- GIVEN** Four equally likely points at  $(\pm d/2, \pm d/2)$ : neighbours  $d$  apart, diagonals  $d\sqrt{2}$ .
- FIND** The symbol error probability by each of the four forms.
- METHOD** Take one point, list its distances to the other three, and add one  $Q$  for each. Then ask which of those three actually bound its region. Symmetry makes every point give the same answer.
- SOLUTION** General:  $P_e \leq 2Q\left(\sqrt{d^2/2N_0}\right) + Q\left(\sqrt{2d^2/2N_0}\right)$ . Intelligent (the region has two faces, both at  $d$ ):  $P_e \leq 2Q\left(\sqrt{d^2/2N_0}\right)$ . Nearest neighbours ( $d_{\min} = d$ ,  $N_{\min} = 2$ ):  $P_e \approx 2Q\left(\sqrt{d^2/2N_0}\right)$ . Minimum distance ( $M - 1 = 3$ ):  $P_e \leq 3Q\left(\sqrt{d^2/2N_0}\right)$ .
- CHECK** Put  $d^2/2N_0 = 9$ , so  $Q(3) = 1.35 \times 10^{-3}$  and  $Q(4.243) = 1.10 \times 10^{-5}$ . The four answers are  $2.71 \times 10^{-3}$ ,  $2.70 \times 10^{-3}$ ,  $2.70 \times 10^{-3}$  and  $4.05 \times 10^{-3}$ : the diagonal term is worth 0.4%, and pretending it is a nearest neighbour costs 50%. The middle two agree here because both faces sit at  $d_{\min}$ , and only one of them is a bound. All four are the same  $Q$  with a different count in front, so none of them moves the curve sideways.



**FIGURE 4.4** The constellation, its four regions, and the observations the receiver sees when the top-right point is sent. The exact error probability is the fraction of that cloud outside its own region. The bound adds three separate two-point questions and counts the overlaps twice.

## 4.5 Summary

**TABLE 4.1** Summary of Chapter 4: the optimal receiver in additive white Gaussian noise.

| RESULT           | STATEMENT                                                                                      | ANCHOR     |
|------------------|------------------------------------------------------------------------------------------------|------------|
| Observation      | $\mathbf{r} = \mathbf{s}_i + \mathbf{n}$ , each $n_k \sim \mathcal{N}(0, N_0/2)$ , independent | PS CH8.4.1 |
| MAP rule         | minimise $\ \mathbf{r} - \mathbf{s}_i\ ^2 - N_0 \ln P(\mathbf{s}_i)$                           | PS CH8.4.1 |
| ML rule          | minimise $\ \mathbf{r} - \mathbf{s}_i\ ^2$ : choose the nearest point                          | PS CH8.4.1 |
| Receiver         | maximise $\mathbf{r} \cdot \mathbf{s}_i - E_i/2 + \frac{N_0}{2} \ln P(\mathbf{s}_i)$           | PS CH8.4.1 |
| Regions          | perpendicular bisectors. The less likely region shrinks                                        | PS CH8.4.1 |
| Binary           | $P_e = Q\left(\sqrt{d^2/2N_0}\right)$                                                          | PS CH8.3.3 |
| Union bound      | $P_e \leq \frac{1}{M} \sum_k \sum_{j \neq k} Q(\cdot)$                                         | PS CH8.4.2 |
| Intelligent form | sum over the neighbours that give $R_k$ a face                                                 | PS CH8.4.2 |
| In practice      | $P_e \approx N_{\min} Q\left(\sqrt{d_{\min}^2/2N_0}\right)$                                    | PS CH8.4.2 |

Two parameters describe the nearest-neighbor approximation. The minimum distance  $d_{\min}$  controls the  $Q$ -function argument. The average neighbor count  $N_{\min}$  is a multiplier. Chapter 5 compares these values for practical constellations at fixed energy and bits per symbol.



## CHAPTER

## 5

# Digital modulation methods

A carrier has an amplitude, a phase and a frequency. Keying one of them, or two at once, puts bits on the carrier. Each scheme of this chapter is a set of points, and the receiver of Chapter 4 decides among them. What changes from scheme to scheme is where the points sit, how many bits each carries, and how much band the carrier needs.

## 5.1 Putting bits on a carrier

A baseband signal  $s(t)$  has its spectrum near  $f = 0$ . Multiplying it by a carrier  $\cos(2\pi f_c t)$  moves that spectrum to  $\pm f_c$ .

### MODULATION SHIFTS THE SPECTRUM

$$u(t) = s(t) \cos(2\pi f_c t) \implies U(f) = \frac{1}{2}S(f - f_c) + \frac{1}{2}S(f + f_c)$$

$$\int s^2(t) \cos^2(2\pi f_c t) dt = \frac{1}{2} \int s^2(t) dt + \frac{1}{2} \int s^2(t) \cos(4\pi f_c t) dt \approx \frac{1}{2} E_s$$

Each copy keeps the shape of  $S(f)$  at half the height. The second integral nearly vanishes when  $f_c \gg W$ , so the carrier halves the energy.

A baseband band  $W$  becomes a passband from  $f_c - W$  to  $f_c + W$ . For example,  $W = 5$  kHz on a 40 kHz carrier occupies 35 to 45 kHz, a band of  $2W = 10$  kHz.

Two baseband numbers can share one carrier frequency. The IQ modulator puts  $I$  on the cosine and  $Q$  on the sine.

### THE IQ MODULATOR

$$s(t) = I \cos(2\pi f_c t) - Q \sin(2\pi f_c t) = A \cos(2\pi f_c t + \theta)$$

$$A = \sqrt{I^2 + Q^2}, \quad \theta = \text{atan2}(Q, I)$$

Over many carrier cycles the cosine and the sine are orthogonal. A correlator on the cosine sees  $I$  alone, and one on the sine sees  $Q$  alone. The point  $(I, Q) = (-1, +1)$  gives  $\theta = 135^\circ$ .

Three binary schemes follow from keying one quantity. Binary phase-shift keying (BPSK) sends the carrier or its negative. Binary frequency-shift keying (BFSK) sends one of two tones. Binary amplitude-shift keying (BASK), also called on-off keying, sends the carrier or nothing.

## THE THREE BINARY SCHEMES

$$\text{BPSK: } s_{1,0}(t) = \pm \sqrt{\frac{2E_b}{T_b}} \cos(2\pi f_c t), \quad d_{\min} = 2\sqrt{E_b}$$

$$\text{BFSK: } s_i(t) = \sqrt{\frac{2E_b}{T_b}} \cos(2\pi f_i t), \quad d_{\min} = \sqrt{2E_b}$$

$$\text{BASK: } s_1(t) = \sqrt{\frac{2E}{T_b}} \cos(2\pi f_c t), \quad s_0(t) = 0, \quad d = \sqrt{E} = \sqrt{2E_b}$$


BPSK has two antipodal points. BFSK has two orthogonal points. BASK has a point at the origin and one at  $\sqrt{E}$ , with average energy  $E_b = E/2$ .

The two BFSK tones are orthogonal only for certain spacings  $\Delta f = f_1 - f_0$ . Their correlation over one bit, when  $f_0 \gg 1/T_b$ , is a sinc.

## CORRELATION OF TWO TONES

$$\rho = \frac{1}{E_b} \int_0^{T_b} s_0(t) s_1(t) dt \approx \frac{\sin(2\pi \Delta f T_b)}{2\pi \Delta f T_b}$$

$\rho = 0$  first at  $\Delta f = 1/(2T_b)$ , the least spacing for coherent BFSK. The lowest value,  $\rho = -0.217$ , falls at  $\Delta f = 0.715/T_b$ .




**FIGURE 5.1** The correlation of two BFSK tones against their spacing. The first zero is at  $\Delta f = 1/(2T_b)$ .

Each scheme gives a binary error probability through Chapter 4,  $Q(\sqrt{d^2/2N_0})$ . Here  $Q(x) = \frac{1}{2} \text{erfc}(x/\sqrt{2})$  is the Gaussian tail.

## BINARY ERROR PROBABILITIES

$$\text{BPSK: } P_b = Q\left(\sqrt{\frac{2E_b}{N_0}}\right), \quad \text{BFSK, BASK: } P_b = Q\left(\sqrt{\frac{E_b}{N_0}}\right)$$

Half the squared distance costs a factor 2 in energy, or 3 dB. At  $P_b = 10^{-5}$  BPSK needs 9.6 dB and BFSK or BASK 12.6 dB.



**FIGURE 5.2** Bit error of BPSK (solid) and of BFSK and BASK (dashed). The curves are 3 dB apart.

### EXAMPLE 5.1 – A BINARY LINK

- GIVEN** A link receives  $P = 4 \times 10^{-15}$  W at  $R_b = 100$  kb/s, with  $N_0 = 4 \times 10^{-21}$  W/Hz.
- FIND** The bit error of BPSK and of BFSK.
- METHOD** The energy a bit is power times bit time,  $E_b = P/R_b = 4 \times 10^{-20}$  J. So  $E_b/N_0 = 10$ , or 10 dB.
- SOLUTION** BPSK:  $P_b = Q(\sqrt{20}) = 3.87 \times 10^{-6}$ . BFSK:  $P_b = Q(\sqrt{10}) = 7.83 \times 10^{-4}$ .
- CHECK** BFSK needs twice the energy for the same distance. It would match BPSK at  $8 \times 10^{-15}$  W.

#### ⊗ COMMON ERROR

Use  $E_b = P/R_b$ , not  $P$ , over  $N_0$ . The ratio  $P/N_0 = 10^6$  Hz is not a signal-to-noise ratio.

## 5.2 Phase-shift keying

M-ary PSK puts  $M$  points on a circle of radius  $\sqrt{E_s}$ . Each symbol carries  $k = \log_2 M$  bits, and  $E_s = kE_b$ .

### M-PSK AND ITS NEIGHBOUR DISTANCE

$$s_m(t) = \sqrt{\frac{2E_s}{T}} \cos\left(2\pi f_c t + \frac{2\pi m}{M}\right), \quad m = 0, \dots, M-1$$

$$d_{\min}^2 = E_s + E_s - 2E_s \cos \frac{2\pi}{M} = 4E_s \sin^2 \frac{\pi}{M}$$

The cosine rule on two neighbours, then  $1 - \cos 2x = 2 \sin^2 x$ . At  $M = 2$  this is BPSK. QPSK with  $E_s = 2$  has  $d_{\min} = 2$ .




FIGURE 5.3 QPSK with Gray labels.




FIGURE 5.4 8-PSK with Gray labels.




FIGURE 5.5 16-PSK: the wedges narrow.

QPSK is two BPSK signals, one on the cosine and one on the sine. The carriers are orthogonal, so each bit sees its own BPSK link.

#### QPSK

$$P_b = Q\left(\sqrt{\frac{2E_b}{N_0}}\right), \quad P_e = 1 - (1 - P_b)^2 \approx 2P_b$$

QPSK carries twice the bits of BPSK in the same band, at the same bit error.

The receiver uses two correlators,  $y_1$  on  $\psi_1 = \sqrt{2/T} \cos(2\pi f_c t)$  and  $y_2$  on  $\psi_2 = -\sqrt{2/T} \sin(2\pi f_c t)$ . All points have equal energy, so the nearest point is the one with the nearest phase to  $\theta = \text{atan2}(y_2, y_1)$ . An 8-PSK receiver that measures  $50^\circ$  picks  $45^\circ$ .


Each point has two neighbours at  $d_{\min}$ . The nearest-neighbour form of Chapter 4 gives the symbol error.

#### M-PSK SYMBOL ERROR

$$P_e \approx 2Q\left(\sqrt{\frac{2E_s}{N_0}} \sin \frac{\pi}{M}\right)$$

$$\frac{E_{s,8}}{E_{s,4}} = \frac{\sin^2(\pi/4)}{\sin^2(\pi/8)} = 3.41 \text{ (5.33 dB)}$$

Going from QPSK to 8-PSK at the same  $d_{\min}$  costs 5.33 dB of symbol energy. Per bit that is  $5.33 - 10 \log_{10} 1.5 = 3.57$  dB. For large  $M$  the cost tends to 6 dB a doubling.



**FIGURE 5.6** Symbol error of M-PSK from the nearest-neighbour form, exact for  $M = 2$ .

A symbol error nearly always lands on a neighbour. Gray labels make neighbours differ in one bit,  $g = i \oplus \lfloor i/2 \rfloor$ . Then one symbol error costs one bit of  $k$ .

#### BITS FROM SYMBOLS, WITH GRAY LABELS

$$P_b \approx \frac{P_e}{\log_2 M}$$

Natural binary labels put 011 beside 100, and that symbol error costs three bits. With Gray labels, 8-PSK at  $P_e = 3 \times 10^{-3}$  gives  $P_b \approx 10^{-3}$ .

#### EXAMPLE 5.2 – 8-PSK

**GIVEN** 8-PSK with Gray labels at  $E_b/N_0 = 10$  dB.

**FIND** The symbol error  $P_e$  and the bit error  $P_b$ .

**METHOD** 10 dB is a ratio of 10, and each symbol carries 3 bits, so  $E_s/N_0 = 30$ . The argument of  $Q$  is  $\sqrt{2(30)} \sin(\pi/8) = 2.96$ .

**SOLUTION**  $P_e \approx 2Q(2.96) = 2(1.52 \times 10^{-3}) = 3.0 \times 10^{-3}$  and  $P_b \approx P_e/3 = 1.0 \times 10^{-3}$ .

**CHECK** Each of the two neighbours contributes one  $Q$  term. The sent point sits inside a wedge of  $\pm 22.5^\circ$ .

#### ⊗ COMMON ERROR

Use  $E_s = 3E_b$ , not  $E_b$ , inside  $Q$ . With  $E_b$  the argument is 1.71 and  $P_e$  comes out as 0.087.

A receiver whose carrier phase is off by  $\varphi$  sees every point turned by  $\varphi$ . M-PSK looks the same after a turn of  $2\pi/M$ , so a receiver can lock to any of  $M$  phases. At  $\varphi = 90^\circ$  QPSK looks perfect, yet every decision is a neighbour.

Differential encoding puts each bit in the change of phase. The receiver compares each symbol with the one before, and a constant phase error cancels.

## DIFFERENTIAL PSK

$$\theta_n = \theta_{n-1} + \pi b_n \pmod{2\pi}, \quad \hat{b}_n = 1 \text{ when } \mathbf{y}_n \cdot \mathbf{y}_{n-1} < 0$$

$$P_b = \frac{1}{2} e^{-E_b/N_0}$$

The bits 1 0 1 1 from  $\theta_0 = 0$  end at  $\theta_4 = \pi$ . At  $10^{-5}$  binary DPSK needs 10.34 dB against 9.59 dB for BPSK, a price of 0.75 dB. At 10 dB,  $P_b = \frac{1}{2} e^{-10} = 2.27 \times 10^{-5}$ .

## △ ERRORS IN PAIRS

One badly received symbol spoils two comparisons, with the symbol before and the one after. For  $M \geq 4$ , differential detection costs about 3 dB over coherent PSK.

### 5.3 Amplitude and quadrature

M-ary amplitude-shift keying (M-ASK), also called PAM, puts  $M$  equally spaced amplitudes on one axis. Neighbours are  $d$  apart.

## M-ASK

$$s_m = (2m - 1 - M) \frac{d}{2}, \quad m = 1, \dots, M$$

$$E_s = \frac{d^2}{4M} \sum_{m=1}^M (2m - 1 - M)^2 = \frac{(M^2 - 1) d^2}{12}$$

$$P_e = \frac{2(M-1)}{M} Q\left(\sqrt{\frac{6E_s}{(M^2-1)N_0}}\right)$$

The odd squares sum to  $M(M^2 - 1)/3$ . Inner points have two neighbours and the end points one. Each doubling of  $M$  costs about 6 dB.




FIGURE 5.7 4-ASK on one axis. The two end regions run off to infinity.

### EXAMPLE 5.3 – FOUR-LEVEL ASK

|                 |                                                                                                                                                                                          |
|-----------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>GIVEN</b>    | 4-ASK with levels $\pm A, \pm 3A$ at $E_s/N_0 = 25$ .                                                                                                                                    |
| <b>FIND</b>     | The symbol error $P_e$ .                                                                                                                                                                 |
| <b>METHOD</b>   | $E_s = A^2(9 + 1 + 1 + 9)/4 = 5A^2$ and $d_{\min} = 2A$ , so $d_{\min}^2/2N_0 = 2E_s/5N_0 = 10$ .<br>The end points have 1 neighbour and the inner points 2, so $\bar{N}_{\min} = 1.5$ . |
| <b>SOLUTION</b> | $P_e \approx 1.5 Q(\sqrt{10}) = 1.5(7.83 \times 10^{-4}) = 1.17 \times 10^{-3}$ .                                                                                                        |
| <b>CHECK</b>    | The M-ASK formula with $M = 4$ gives the same: $\frac{2(3)}{4} = 1.5$ and $\frac{6(25)}{15} = 10$ .                                                                                      |

#### ⊗ COMMON ERROR

Use  $\bar{N}_{\min} = 1.5$ , not 2. The two end points have one neighbour each.

Quadrature amplitude modulation (QAM) runs one ASK signal on the cosine and another on the sine. Square M-QAM is two  $\sqrt{M}$ -level ASK axes at right angles.

#### SQUARE QAM

$$s(t) = I \cos(2\pi f_c t) - Q \sin(2\pi f_c t), \quad I, Q \in \{\pm \frac{d}{2}, \pm \frac{3d}{2}, \dots\}$$

$$E_s = 2 \cdot \frac{((\sqrt{M})^2 - 1)d^2}{12} = \frac{(M - 1)d^2}{6}$$

$$P_e \approx 4 \left(1 - \frac{1}{\sqrt{M}}\right) Q\left(\sqrt{\frac{3E_s}{(M-1)N_0}}\right)$$


16-QAM with  $d = 2$  has  $E_s = 10$ . Its 4 corners have 2 neighbours, its 8 edge points 3, and its 4 inner points 4. The average is  $48/16 = 3$ .

A symbol is right only when both axes are right. That gives the exact symbol error of square QAM.


#### EXACT SQUARE QAM

$$P_e = 1 - (1 - P_{\sqrt{M}})^2, \quad P_{\sqrt{M}} = 2 \left(1 - \frac{1}{\sqrt{M}}\right) Q\left(\sqrt{\frac{3E_s}{(M-1)N_0}}\right)$$

Expanding gives  $2P_{\sqrt{M}} - P_{\sqrt{M}}^2$ , and the nearest-neighbour form keeps only  $2P_{\sqrt{M}}$ . At a fixed  $d_{\min}$ ,  $E_s$  grows as  $M - 1$ , about 3 dB for each extra bit.



**FIGURE 5.8** 16-QAM and its decision regions. The boundaries sit halfway between levels.



**FIGURE 5.9** Exact symbol error of square QAM for  $M = 4$ , 16 and 64.

#### EXAMPLE 5.4 – 16-QAM

**GIVEN** 16-QAM with  $d_{\min} = 2$  and  $E_s/N_0 = 80$ , about 19 dB.

**FIND** The energy  $E_s$ , the symbol error and the bit error with Gray labels.

**METHOD**  $E_s = (M-1)d^2/6 = 15(4)/6 = 10$ . Then  $d_{\min}^2/2N_0 = 3E_s/15N_0 = E_s/5N_0 = 16$ , and  $\bar{N}_{\min} = 3$ .

**SOLUTION**  $P_e \approx 3Q(4) = 9.5 \times 10^{-5}$  and  $P_b \approx P_e/4 = 2.4 \times 10^{-5}$ .

**CHECK** The grid  $\pm 1, \pm 3$  on both axes gives  $E_s = 10$  directly. The boundaries are the lines at 0 and  $\pm 2$ .

#### ⊗ COMMON ERROR

Use  $\bar{N}_{\min} = 3$ , not 4. Only the four inner points have four neighbours.

A square grid is not the only way to place eight or sixteen points. Four eight-point sets with  $d_{\min} = 2$  have average energies 6, 6.83, 6 and 4.73. The best of them puts four points on an inner square and four on the axes at  $1 + \sqrt{3}$ . It saves  $10 \log_{10}(6/4.73) = 1.03$  dB over the  $2 \times 4$  rectangle.

At the same average energy, QAM spreads its points over the plane and PSK keeps them on a circle. The ratio of their squared distances measures the gain of QAM.

#### QAM AGAINST PSK

$$R_M = \frac{d_{\text{QAM}}^2}{d_{\text{PSK}}^2} = \frac{6E_s/(M-1)}{4E_s \sin^2(\pi/M)} = \frac{3}{2(M-1) \sin^2(\pi/M)}$$

The gain is 1.65, 4.20, 7.02 and 9.95 dB at  $M = 8, 16, 32$  and 64. At  $M = 4$  the two sets coincide.



## 5.4 Frequency-shift keying and orthogonal signals

M-ary FSK sends one of  $M$  tones spaced so that all are orthogonal. Each tone is one axis of an  $M$ -dimensional space, with its point at  $\sqrt{E_s}$  on that axis.

### M-FSK AND ORTHOGONAL SIGNALS

$$s_m(t) = \sqrt{\frac{2E_s}{T}} \cos(2\pi(f_c + m \Delta f)t), \quad \Delta f = \frac{1}{2T}$$

$$\|\mathbf{s}_i - \mathbf{s}_j\|^2 = 2E_s, \quad P_e \leq (M-1) Q\left(\sqrt{\frac{E_s}{N_0}}\right)$$

Every point is a neighbour of every other, so 8-FSK has 7 neighbours at one distance. Adding tones adds bits without bringing the points closer.

A wrong symbol is any of the other  $M - 1$  with equal chance. Each bit of the label is then wrong in  $2^{k-1}$  of them.

### BIT ERROR OF ORTHOGONAL SIGNALS

$$P_b = \frac{2^{k-1}}{2^k - 1} P_e$$

At  $P_b = 10^{-5}$ ,  $M = 2$  needs 12.6 dB and  $M = 64$  about 6.1 dB. Each doubling of  $M$  lowers the energy per bit needed.

### ⚠ A FLOOR

The gain has a limit. As  $M$  grows,  $P_b \rightarrow 0$  only when  $E_b/N_0 > \ln 2$ , or  $-1.6$  dB. Chapter 6 shows why no scheme can do better.


A noncoherent receiver does not know the carrier phase. For each tone it uses a cosine and a sine correlator and keeps the envelope, which does not depend on the phase.

### NONCOHERENT BFSK

$$\ell_i = \sqrt{y_{c,i}^2 + y_{s,i}^2}, \quad \Delta f = \frac{1}{T}$$

$$P_b = \frac{1}{2} e^{-E_b/2N_0}$$

The tones must stay orthogonal for every phase, which takes twice the coherent spacing. At  $10^{-5}$  noncoherent BFSK needs 13.4 dB against 12.6 dB coherent. That is twice the energy of binary DPSK.



**FIGURE 5.10** From left: coherent BPSK (solid), binary DPSK, coherent BFSK and noncoherent BFSK.

## 5.5 Bandwidth and the choice of scheme

With a rectangular pulse, the spectrum of PSK or QAM is a  $\text{sinc}^2$  of width set by the symbol time  $T = kT_b$ . At a fixed bit rate, more bits a symbol give a narrower spectrum.


### SPECTRUM AND BAND OF EACH FAMILY

$$S(f) \propto T \text{sinc}^2(fT), \quad \text{main lobe } \frac{2}{T} = \frac{2R_b}{k}$$

$$\text{PAM (SSB): } W = \frac{R_b}{2 \log_2 M}, \quad \text{PSK, QAM: } W = \frac{R_b}{\log_2 M}, \quad \text{orthogonal: } W = \frac{MR_b}{2 \log_2 M}$$

Here  $\text{sinc } x = \sin(\pi x)/(\pi x)$ . The QPSK main lobe is half as wide as that of BPSK. 16-QAM at 10 Mb/s needs about  $10/4 = 2.5$  MHz. Orthogonal signals need  $M$  dimensions a symbol, so their band grows with  $M$ .

QPSK can swing through the origin when both  $I$  and  $Q$  change sign. Offset QPSK delays  $Q$  by  $T_b$ , so only one axis changes at a time and the envelope stays above  $1/\sqrt{2}$ . Minimum-shift keying (MSK) turns the phase by  $\pm\pi/2$  each bit at a steady rate. It is BFSK at  $\Delta f = 1/(2T_b)$  with a continuous phase, and its envelope is constant.



**FIGURE 5.11** Spectra of offset QPSK (dashed) and MSK (solid). The MSK main lobe reaches  $0.75/T_b$  against  $0.5/T_b$ , and its side lobes fall faster.

A scheme is chosen by what the link is short of. The bandwidth efficiency  $r = R_b/W$  places each family on a plane against the  $E_b/N_0$  it needs.

**TABLE 5.1** Each family on the bandwidth–power plane at  $M = 16$  and  $P_e = 10^{-5}$ .

| FAMILY           | $E_b/N_0$ AT $P_e = 10^{-5}$ , $M = 16$ | $r = R_b/W$ | REGION            |
|------------------|-----------------------------------------|-------------|-------------------|
| PAM (SSB)        | 23.1 dB                                 | 8           | bandwidth-limited |
| PSK              | 18.1 dB                                 | 4           | bandwidth-limited |
| QAM              | 14.0 dB                                 | 4           | bandwidth-limited |
| Orthogonal (FSK) | 7.7 dB                                  | 0.5         | power-limited     |

PAM, PSK and QAM have  $r > 1$  and pay energy for each extra bit, QAM the least. Orthogonal signals have  $r < 1$  and pay in band. No scheme can sit left of the curve  $E_b/N_0 = (2^r - 1)/r$ , which Chapter 6 derives.

Adaptive modulation uses this trade in real time. The receiver measures  $E_s/N_0$ , and the transmitter picks the largest set whose bit error meets the target.

**TABLE 5.2** The signal-to-noise ratio each set of an adaptive link needs for  $P_b = 10^{-5}$ .

| SET     | BITS A SYMBOL | $E_s/N_0$ FOR $P_b = 10^{-5}$ |
|---------|---------------|-------------------------------|
| BPSK    | 1             | 9.6 dB                        |
| QPSK    | 2             | 12.6 dB                       |
| 16-QAM  | 4             | 19.5 dB                       |
| 64-QAM  | 6             | 25.6 dB                       |
| 256-QAM | 8             | 31.5 dB                       |

At  $E_s/N_0 = 22$  dB the link chooses 16-QAM. Each step of two bits costs about 6 dB.

## The link budget

The error rate of a scheme is set by  $E_b/N_0$ . A link budget turns that ratio into watts, antennas and kilometres. It works in decibels, so products become sums.

A power in dBm is in decibels above 1 mW,  $P_{\text{dBm}} = 10 \log_{10}(P/1 \text{ mW})$ . A gain or a loss in dB adds to a power in dBm. Two powers in dBm are never added.

Every receiver hears thermal noise. At the reference temperature  $T_0 = 290 \text{ K}$  its density is  $kT_0$ , where  $k$  is Boltzmann's constant. The receiver adds noise of its own, counted by the noise figure  $F \geq 1$ .

### THERMAL NOISE AND THE NOISE FIGURE

$$N_0 = kT_0F, \quad kT_0 = (1.38 \times 10^{-23})(290) = 4.00 \times 10^{-21} \text{ W/Hz}$$

$$10 \log_{10} \frac{4.00 \times 10^{-21} \text{ W/Hz}}{10^{-3} \text{ W}} = -174 \text{ dBm/Hz}, \quad \text{NF} = 10 \log_{10} F$$

A receiver that adds no noise has  $F = 1$ , or  $\text{NF} = 0 \text{ dB}$ . A typical radio receiver has  $\text{NF}$  between 3 and 8 dB.

Here  $kT_0F$  is the one-sided density  $N_0$ . This course writes white noise with the two-sided PSD  $N_0/2$ , which is 3 dB lower,  $-177 \text{ dBm/Hz}$  with  $F = 1$ . It covers negative as well as positive frequencies, so a band of width  $B$  collects  $N_0B$  either way.

### NOISE POWER IN A BAND

$$N = N_0B = kT_0FB$$

$$N_{\text{dBm}} = -174 + \text{NF} + 10 \log_{10} B$$

For  $B = 10 \text{ MHz}$ ,  $10 \log_{10} 10^7 = 70$ . With  $\text{NF} = 5 \text{ dB}$  the noise floor is  $N = -174 + 5 + 70 = -99 \text{ dBm}$ . Ten times the band raises it by 10 dB.

The sensitivity  $P_{\min}$  is the least received power that meets the target error. The energy a bit is the received power times the bit time,  $E_b = P_r/R_b$ . So  $E_b/N_0 = P_r/(R_bN_0)$ , and solving for  $P_r$  at the required ratio gives the sensitivity.

### RECEIVER SENSITIVITY

$$P_{\min} = \left( \frac{E_b}{N_0} \right)_{\text{req}} R_b N_0 = \left( \frac{E_b}{N_0} \right)_{\text{req}} R_b kT_0 F$$

$$P_{\min, \text{dBm}} = -174 + \text{NF} + 10 \log_{10} R_b + \left( \frac{E_b}{N_0} \right)_{\text{req, dB}}$$

The band does not appear. QPSK at 10 Mb/s needs  $E_b/N_0 = 9.6 \text{ dB}$  for  $P_b = 10^{-5}$ , so with  $\text{NF} = 5 \text{ dB}$  it needs  $-174 + 5 + 70 + 9.6 = -89.4 \text{ dBm}$ .

The received power comes from the transmit power, the two antennas and the path. In free space the Friis formula gives it. The antenna gains  $G_t$  and  $G_r$  are measured against an antenna that radiates equally in every direction, and  $\lambda = c/f_c$  is the wavelength.

## THE FRIIS FORMULA


$$P_r = P_t G_t G_r \left( \frac{\lambda}{4\pi d} \right)^2$$

$$P_{r,\text{dBm}} = P_{t,\text{dBm}} + G_{t,\text{dBi}} + G_{r,\text{dBi}} - L_p, \quad L_p = 20 \log_{10} \frac{4\pi d}{\lambda}$$

The loss  $L_p$  grows with  $d^2$ , so each doubling of  $d$  costs  $20 \log_{10} 2 = 6$  dB. At 2.4 GHz,  $\lambda = 0.125$  m and  $L_p = 20 \log_{10}(4\pi \cdot 1000/0.125) = 100.0$  dB at 1 km.

The link margin is  $P_r - P_{\min}$ . It is kept for fading, walls, rain and ageing, which the free-space model leaves out. The range of a link is the largest  $d$  at which the margin is still met.

Take  $P_t = 20$  dBm and two 10 dBi antennas at 2.4 GHz. At 1 km,  $P_r = 20 + 10 + 10 - 100.0 = -60.0$  dBm, which is 29.4 dB above the QPSK sensitivity of  $-89.4$  dBm. Keeping a 10 dB margin allows  $L_p = 119.4$  dB, a range of 9.3 km.



**FIGURE 5.12** Received power against distance for Example 5.5, with each sensitivity plus the 15 dB margin. The crossings give the ranges.

### EXAMPLE 5.5 – A LINK BUDGET

- GIVEN** A 5.8 GHz link has a band  $B = 25$  MHz with roll-off  $\alpha = 0.25$ . It has  $P_t = 20$  dBm,  $G_t = G_r = 12$  dBi,  $NF = 7$  dB and needs a 15 dB margin. For  $P_b = 10^{-5}$ , QPSK needs  $E_b/N_0 = 9.6$  dB and 16-QAM 13.4 dB.
- FIND** The bit rate, the sensitivity and the range of each scheme.
- METHOD** The band fixes the symbol rate  $R_s = B/(1 + \alpha)$ . The sensitivity follows from  $R_b$  and  $NF$ . The allowed loss is  $L_p = P_t + G_t + G_r - P_{\min} - \text{margin}$ , and inverting  $L_p = 20 \log_{10}(4\pi d/\lambda)$  gives  $d = (\lambda/4\pi) 10^{L_p/20}$ .
- SOLUTION**  $R_s = 25/1.25 = 20$  Msym/s, so QPSK carries 40 Mb/s and 16-QAM 80 Mb/s. Then  $10 \log_{10}(40 \times 10^6) = 76.0$  and  $10 \log_{10}(80 \times 10^6) = 79.0$ . QPSK:  $P_{\min} = -174 + 7 + 76.0 + 9.6 = -81.4$  dBm and  $L_p = 20 + 24 + 81.4 - 15 = 110.4$  dB. 16-QAM:  $P_{\min} = -174 + 7 + 79.0 + 13.4 = -74.6$  dBm and  $L_p = 20 + 24 + 74.6 - 15 = 103.6$  dB. With  $\lambda = 3 \times 10^8 / 5.8 \times 10^9 = 0.0517$  m,  $\lambda/4\pi = 4.12 \times 10^{-3}$  m. So QPSK reaches  $d = 4.12 \times 10^{-3} \cdot 10^{110.4/20} = 1.36$  km and 16-QAM  $d = 4.12 \times 10^{-3} \cdot 10^{103.6/20} = 0.62$  km.
- CHECK** The two sensitivities differ by  $-74.6 - (-81.4) = 6.8$  dB: 3.8 dB of  $E_b/N_0$  and 3.0 dB of bit rate. A loss 6.8 dB smaller is a range  $10^{6.8/20} = 2.19$  times longer, and  $1.36/0.62 = 2.19$ .

#### ⊗ COMMON ERROR

Use  $20 \log_{10}$ , not  $10 \log_{10}$ , to turn a loss into range. A loss 6.8 dB smaller is a factor 2.2 in range, not 4.8, because  $L_p$  grows with  $d^2$ .

## 5.6 Summary

**TABLE 5.3** Summary of Chapter 5: digital modulation methods.

| SCHEME           | $d_{\min}^2$         | $\bar{N}_{\min}$    | ERROR PROBABILITY                                       | ANCHOR            |
|------------------|----------------------|---------------------|---------------------------------------------------------|-------------------|
| BPSK, QPSK       | $4E_b$               | 1                   | $P_b = Q(\sqrt{2E_b/N_0})$                              | PS CH8.6.1, 8.6.3 |
| BFSK, BASK       | $2E_b$               | 1                   | $P_b = Q(\sqrt{E_b/N_0})$                               | PS CH8.3.3, 9.5   |
| Binary DPSK      | none                 | none                | $P_b = \frac{1}{2}e^{-E_b/N_0}$                         | PS CH8.6.5        |
| M-PSK            | $4E_s \sin^2(\pi/M)$ | 2                   | $P_e \approx 2Q(\sqrt{2E_s/N_0} \sin(\pi/M))$           | PS CH8.6.3        |
| M-ASK            | $12E_s/(M^2 - 1)$    | $2(M - 1)/M$        | $\frac{2(M-1)}{M} Q(\sqrt{6E_s/((M^2 - 1)N_0)})$        | PS CH8.5.3        |
| Square M-QAM     | $6E_s/(M - 1)$       | $4(1 - 1/\sqrt{M})$ | $4(1 - \frac{1}{\sqrt{M}}) Q(\sqrt{3E_s/((M - 1)N_0)})$ | PS CH8.7.3        |
| M orthogonal     | $2E_s$               | $M - 1$             | $P_e \leq (M - 1)Q(\sqrt{E_s/N_0})$                     | PS CH9.1.2        |
| Noncoherent BFSK | none                 | none                | $P_b = \frac{1}{2}e^{-E_b/2N_0}$                        | PS CH9.5.3        |

Every scheme of this chapter is a set of points read by the receiver of Chapter 4. Its error rate follows from  $d_{\min}$  and  $\bar{N}_{\min}$  at the chosen energy, and its band from the bits a symbol. Chapter 6 asks how many bits a second any scheme can carry in a given band and power.

## CHAPTER

## 6

# An introduction to information theory

The previous chapters started with a given bit stream and transmitted it through a channel. This chapter studies the source of those bits. Entropy measures the average information from the source. It also gives the minimum average rate for lossless source coding.

## 6.1 The information in one symbol

A **discrete memoryless source** emits one of  $K$  symbols each time, with fixed probabilities  $p_1, \dots, p_K$ , chosen independently of what came before. How much is learnt when one arrives? If it was certain, nothing. If it was almost impossible, a great deal.

### SELF-INFORMATION

$$I(s_k) = \log_a \frac{1}{p_k} = -\log_a p_k$$

The base sets the unit:  $a = 2$  gives **bits**,  $a = e$  gives **nats**,  $a = 10$  gives **Hartleys**. This course uses base two throughout.

### ① THREE PROPERTIES, AND WHAT FORCES THE LOGARITHM

$I(s_k) \geq 0$ , because a probability is at most one and its logarithm at most zero.

$I(s_k) \geq I(s_j)$  **when**  $p_k \leq p_j$ : rarer means more informative.

$I(s_k s_j) = I(s_k) + I(s_j)$  **for independent symbols**, because their probabilities multiply and the logarithm turns a product into a sum. That third property is the one that rules out every function except a logarithm.

### ✓ ONE HALVING IS ONE BIT

$-\log_2 \frac{1}{2} = 1$ , so every halving of a probability adds exactly one bit. A symbol of probability  $1/1000$  is about ten halvings away from certainty, so it carries about 10 bits. Most estimates in this chapter can be done that way, without a calculator.

## 6.2 Entropy

Self-information describes one symbol. Average it over the alphabet, weighting each symbol by how often it happens, and the result describes the source.




## ENTROPY


$$H(S) = E[I(s_k)] = - \sum_{k=1}^K p_k \log_2 p_k \quad \text{bits a symbol}$$

$$0 \leq H(S) \leq \log_2 K$$

Zero when one symbol has probability one — nothing is ever in doubt. At the top,  $\log_2 K$ , when all  $K$  are equally likely: putting  $p_k = 1/K$  into the sum gives  $\sum \frac{1}{K} \log_2 K = \log_2 K$ .



**FIGURE 6.1** The entropy of a binary source. One bit at  $p = \frac{1}{2}$ , nothing at either end, and flat near the top — a slightly unfair coin is almost as informative as a fair one.



**FIGURE 6.2** The standard example. The left bar of each pair is what the symbol carries. The right bar is that weighted by how often it happens. The three right bars add to  $H(S)$ .

### EXAMPLE 6.1 — THE ENTROPY OF A THREE-SYMBOL SOURCE

**GIVEN**  $S = \{s_1, s_2, s_3\}$  with probabilities 0.7, 0.2, 0.1.

**FIND** The entropy.

**SOLUTION**  $H(S) = -0.7 \log_2 0.7 - 0.2 \log_2 0.2 - 0.1 \log_2 0.1 = 0.3602 + 0.4644 + 0.3322 = 1.1568$  bits a symbol.

**CHECK**  $\log_2 3 = 1.585$ , and 1.1568 is below it, as it must be for a source that is not uniform. Numbering the three symbols would cost 2 bits each, so plain numbering wastes almost 0.85 bits every symbol. Recovering that is the whole of source coding.

Two numbers get confused here and should not be.  $\log_2 K$  is the most a source of this size *could* carry.  $\lceil \log_2 K \rceil$  is what a fixed-length code *costs*. The first gap is the source being uneven; the second is rounding.

## 6.3 Extended sources

Nothing forces a coder to work one symbol at a time. Group them in  $n$ s and treat each block as one symbol of a new alphabet. That is the  $n$ -th **extension**, written  $S^n$ , and it has  $K^n$  symbols.

## EXTENSION

$$H(S^n) = n H(S)$$

The source is memoryless, so the symbols in a block are independent and their information adds. This is the third property of self-information, applied  $n$  times.

 **EXAMPLE 6.2 – THE SAME SOURCE, TWO AT A TIME**

|                 |                                                                                                                                                                                                                                                           |
|-----------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>GIVEN</b>    | The source of Example 6.1, extended by two.                                                                                                                                                                                                               |
| <b>FIND</b>     | $H(S^2)$ .                                                                                                                                                                                                                                                |
| <b>METHOD</b>   | $S^2$ has $3^2 = 9$ symbols with probabilities<br>0.49, 0.14, 0.07, 0.14, 0.04, 0.02, 0.07, 0.02, 0.01.                                                                                                                                                   |
| <b>SOLUTION</b> | Summing $-p \log_2 p$ over all nine gives 2.3136 bits a block.                                                                                                                                                                                            |
| <b>CHECK</b>    | $2 \times 1.1568 = 2.3136$ . The long way and the short way agree, and per symbol nothing has changed — 2.3136 over two symbols is 1.1568 each. What changes is how much of a whole bit gets wasted in rounding, and section 6.6 turns that into a bound. |

 **ONLY BECAUSE IT IS MEMORYLESS**

If the source had memory. As English does, where  $q$  is followed by  $u$ . The block probabilities would not be products, and  $H(S^n)$  would be *less* than  $nH(S)$ . That difference is exactly the redundancy real compressors live on, and it is outside this course.

## 6.4 What a code costs

A source encoder turns each symbol into a string of bits, its **codeword**. The codewords need not all be the same length, and the good idea of this chapter is that they should not be. Short ones for common symbols, long ones for rare.

## AVERAGE LENGTH AND EFFICIENCY

$$\bar{L} = \sum_{k=1}^K p_k l_k, \quad \eta = \frac{L_{\min}}{\bar{L}} = \frac{H(S)}{\bar{L}} \leq 1$$

The **source-coding theorem** says  $\bar{L} \geq H(S)$  for any code from which the symbols can be recovered exactly. So  $L_{\min} = H(S)$ : the entropy is not merely a measure of information, it is a limit on how few bits will carry it.

 **SOURCE CODING IS NOT CHANNEL CODING**

Source coding removes bits the message does not need. Channel coding adds bits back so that errors can be found and fixed. They pull in opposite directions, they are done in that order, and this course covers only the first.

Written English gives a concrete case. Its entropy is estimated at about 1.3 bits a letter, while a typical letter-by-letter variable-length code reaches  $\bar{L} = 4.22$ , so  $\eta = 0.31$ . Morse code is the same idea by hand: one dot for  $e$ , four symbols for  $z$ .

## 6.5 Codes that can be read back

Short codewords are useful only when the receiver can separate them. A code is **uniquely decodable** if each coded bit string has one source-symbol sequence. A **prefix code** has no codeword that begins another codeword. This stronger condition permits immediate decoding when the last codeword bit arrives. A prefix code is also **instantaneous**.


**TABLE 6.1** Three codes for the same four symbols.

| SYMBOL | CODE I | CODE II | CODE III |
|--------|--------|---------|----------|
| $s_1$  | 0      | 0       | 0        |
| $s_2$  | 1      | 10      | 01       |
| $s_3$  | 00     | 110     | 011      |
| $s_4$  | 11     | 111     | 0111     |

Code I is not a prefix code and is not uniquely decodable either: the string 00 is both  $s_3$  and  $s_1s_1$ . Code II is a prefix code. Code III is not a prefix code, since 0 begins all three of the others.

### △ CODE III

Code III is uniquely decodable because each codeword starts with 0 and then contains only 1s. However, it is not instantaneous. After 011, the decoder must wait for the next bit to distinguish  $s_3$  from the start of  $s_4$ .



**FIGURE 6.3** Code II. Every symbol is at a leaf, so no path to one passes through another. That is what the prefix property looks like.



**FIGURE 6.4** Code III. Every symbol sits on one path, each hanging off the node before it. Nothing is at a leaf but the last, and that is why the decoder must wait.

## 6.6 The Kraft inequality, and how close a code can get

Before selecting codewords, determine whether their lengths can satisfy the prefix condition. Treat the binary tree as one unit. A codeword of length  $l$  uses a fraction  $2^{-l}$  of the tree. These fractions cannot sum to more than one.

## KRAFT INEQUALITY

$$\sum_{k=1}^K 2^{-l_k} \leq 1$$

The three Kraft sums are 1.5, 1, and 0.9375. Code I fails, so no prefix code has its lengths. Code II uses the tree completely. Code III satisfies the inequality but is not itself a prefix code. Thus, the inequality is necessary but not sufficient for given codewords.

## HOW CLOSE A PREFIX CODE GETS

$$H(S) \leq \bar{L} < H(S) + 1$$

$$H(S) \leq \frac{L_n}{n} < H(S) + \frac{1}{n} \implies \lim_{n \rightarrow \infty} \frac{L_n}{n} = H(S)$$

The ideal length for symbol  $k$  is  $-\log_2 p_k$ , almost never a whole number. Therefore, each length is rounded up and the rounding costs under one bit. Applying the same bound to the  $n$ -th extension spreads that one bit over  $n$  symbols.

## ✔ DYADIC PROBABILITIES

If every probability has the form  $p_k = 2^{-l_k}$ , the distribution is **dyadic**. No codeword length requires rounding. Then  $\bar{L}$  and  $H(S)$  equal the same sum. Therefore,  $\bar{L} = H(S)$ .

## ⚠ BLOCK-CODE SIZE

The coding gap decreases as  $1/n$ , but the block alphabet grows as  $K^n$ . A gap of 0.05 bit per symbol needs  $n = 20$ . For a three-symbol source, this block contains  $3^{20} = 3.5 \times 10^9$  possible messages.

## 6.7 Huffman coding

The bound says a good code exists. Huffman coding builds one, and it builds the best one: no prefix code on single symbols has a smaller average length.

## ① THE ALGORITHM

1. List the symbols in order of decreasing probability.
  2. Take the two least likely, label one 0 and the other 1, and merge them into one symbol whose probability is their sum. Re-sort.
  3. Repeat until two symbols remain, and label those 0 and 1.
- Each codeword is the labels along the path back to its symbol.


**EXAMPLE 6.3 – THE STANDARD FIVE-SYMBOL SOURCE****GIVEN**  $p = 0.4, 0.2, 0.2, 0.1, 0.1$ .**MERGING**  $0.1 + 0.1 = 0.2$ . Then the two smallest are 0.2 and 0.2, giving 0.4. Then 0.2 and 0.4 give 0.6. Then 0.4 and 0.6 finish it.**SOLUTION** Lengths 2, 2, 2, 3, 3, so  $\bar{L} = 0.4(2) + 0.2(2) + 0.2(2) + 0.1(3) + 0.1(3) = 2.2$  bits a symbol.**EFFICIENCY**  $H(S) = 2.1219$  bits, so  $\eta = 2.1219/2.2 = 0.9645$  — the code spends 3.68% more than the source strictly needs.**CHECK**  $2.1219 \leq 2.2 < 3.1219$ : the two-sided bound holds. A fixed-length code would have cost  $\lceil \log_2 5 \rceil = 3$  bits, so Huffman saved 0.8 bits a symbol.

Two Huffman choices are free. Either symbol in a merged pair can receive 0. A merged symbol can also occupy different positions during a probability tie. These choices give different codes with the same minimum average length. Their codeword-length variances can differ.


**VARIANCE OF THE CODEWORD LENGTH**

$$\sigma^2 = \sum_{k=1}^K p_k (l_k - \bar{L})^2$$

For the example: placing the merged symbol high gives lengths 2, 2, 2, 3, 3 and  $\sigma^2 = 0.16$ . Placing it low gives 1, 2, 3, 4, 4, the same  $\bar{L} = 2.2$ , and  $\sigma^2 = 1.36$ .



**FIGURE 6.5 Merged symbol placed high.** Lengths 2, 2, 2, 3, 3, average 2.2, variance 0.16. The tree is nearly balanced.



**FIGURE 6.6 Merged symbol placed low.** Lengths 1, 2, 3, 4, 4, the same average 2.2, variance 1.36. The tree is a ladder.

**✓ MINIMUM LENGTH VARIANCE**

Variable codeword lengths make a buffer fill and empty at changing rates. Smaller length variance reduces these changes. During a probability tie, place the merged symbol as high as possible. This rule gives the minimum-variance Huffman code.

**6.8 Lempel–Ziv coding**

Huffman coding has one practical weakness, and it is not its length. It needs the probabilities *before* it can build the tree, and for a stream arriving over a wire nobody knows them in advance. A **universal** code is

one that reaches the entropy without being told the source, and the Lempel–Ziv algorithm is the one in use everywhere.

#### ① THE ALGORITHM

Read the stream once. Each time, take the **shortest run of bits not seen before** and store it in a dictionary. Because it is the shortest new one, everything but its last bit is already stored. So it is sent as a **pointer** to that earlier entry followed by the one new bit, the **innovation**. The decoder builds the same dictionary from the same blocks in the same order. Therefore, the dictionary is never transmitted.

#### 🔗 EXAMPLE 6.4 – PARSING AND SENDING A STREAM

|                 |                                                                                                                                                                                                                                                                                                                                        |
|-----------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>GIVEN</b>    | The stream 0 1 00 011 1 . . . , with 0 and 1 held in the dictionary at positions 1 and 2.                                                                                                                                                                                                                                              |
| <b>METHOD</b>   | Parse left to right into pieces not seen before, then send each piece as (position of its start, new bit).                                                                                                                                                                                                                             |
| <b>SOLUTION</b> | 00 takes position 3: its start 0 is at position 1 and its new bit is 0, so with four-bit blocks it goes as 001 0. Next 011 takes position 4: its start 01 is at position 4... so it is sent as 100 1.                                                                                                                                  |
| <b>DECODING</b> | Receive 1101. The last bit is the innovation 1. The first three bits, 110, give pointer 6. Therefore, append 1 to dictionary entry 6. The decoder already contains this entry.                                                                                                                                                         |
| <b>CHECK</b>    | Seven pieces at four bits each cost 28 bits where the raw stream was 18. The method <i>loses</i> on a short stream, and that is not a fault: the dictionary has to be paid for before it can pay back. In practice the block is 12 bits, giving $2^{12} = 4096$ entries, and a long file compresses to roughly two thirds of its size. |

#### ✅ OPTIMAL AGAINST UNIVERSAL

Huffman is optimal but not universal: no prefix code on single symbols beats it, and it cannot start until the probabilities are known. Lempel–Ziv is universal but reaches the limit only in the long run. That trade is the whole difference between them, and it is why the second is what compresses an archive.

## 6.9 The discrete memoryless channel

The first part of this chapter studied the source. The second part studies the channel. A **discrete memoryless channel** maps one symbol from a finite input alphabet to a finite output alphabet. The current output depends only on the current input.

## THE CHANNEL, AND WHAT THE TRANSMITTER ADDS

$$p(y_k | x_j) = P(Y = y_k | X = x_j), \quad \sum_{k=0}^{K-1} p(y_k | x_j) = 1 \text{ for every } j$$

$$p(x_j, y_k) = p(y_k | x_j) p(x_j), \quad p(y_k) = \sum_{j=0}^{J-1} p(y_k | x_j) p(x_j)$$

The transition probabilities collected into a matrix, one row per input, are the **channel matrix**. Every row sums to one, because something must come out when a symbol goes in. The columns do not, and expecting them to is the usual first mistake. The **input distribution**  $p(x_j)$  is not part of the channel — it belongs to the transmitter, and it is chosen.

## i THE BINARY SYMMETRIC CHANNEL

Two inputs, two outputs, and one number. The probability  $p$  that a bit is flipped, called the **crossover probability**. Its matrix is  $\begin{bmatrix} 1-p & p \\ p & 1-p \end{bmatrix}$ . It is not an abstraction invented for this chapter. The binary receiver of chapter 2, seen from outside, *is* a binary symmetric channel with  $p = Q(\sqrt{2E_b/N_0})$ . With equally likely inputs the output is equally likely whatever  $p$  is, even at  $p = \frac{1}{2}$  where the channel is destroying everything. Therefore, a balanced output is no evidence that anything survived.

## 6.10 Mutual information

Before anything arrives, the uncertainty about the input is  $H(X)$ . Then one output symbol arrives, and it rarely settles the question but it does change the odds. What remains is an entropy like any other, averaged over which output actually came.

## CONDITIONAL ENTROPY, AND THE INFORMATION THAT GOT THROUGH

$$H(X | Y) = \sum_k H(X | Y = y_k) p(y_k) = - \sum_k \sum_j p(x_j, y_k) \log_2 p(x_j | y_k)$$

$$I(X; Y) = H(X) - H(X | Y) = H(Y) - H(Y | X)$$

$$H(X, Y) = H(X) + H(Y) - I(X; Y)$$

Read the middle line in words: **how much doubt the arrival removed**, in bits, per use of the channel. The second form is the one used, because  $H(Y | X)$  comes straight off the channel matrix while  $H(X | Y)$  needs Bayes' rule first.

### ① THREE PROPERTIES

**Symmetry.**  $I(X; Y) = I(Y; X)$ . Bayes' rule gives  $p(x_j | y_k)/p(x_j) = p(y_k | x_j)/p(y_k)$ , and substituting turns one sum into the other. What the output says about the input equals what the input says about the output — which is why the quantity is called *mutual*.

**Non-negativity.**  $I(X; Y) \geq 0$ , with equality exactly when  $X$  and  $Y$  are independent. An observation never leaves you knowing less than before.

**Joint entropy.** Adding  $H(X)$  and  $H(Y)$  counts the shared part twice, so it is subtracted once. That is the whole content of the third line.

### 🔗 EXAMPLE 6.5 – THE BINARY SYMMETRIC CHANNEL AT $p = 0.1$

|                 |                                                                                                                                                                                                                                                                                                                                                                                                             |
|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>GIVEN</b>    | A BSC with $p = 0.1$ and equally likely inputs.                                                                                                                                                                                                                                                                                                                                                             |
| <b>FIND</b>     | $H(X)$ , $H(Y   X)$ , $H(Y)$ and $I(X; Y)$ .                                                                                                                                                                                                                                                                                                                                                                |
| <b>METHOD</b>   | $H(Y   X)$ comes off the matrix: whichever symbol goes in, the output distribution is $(0.9, 0.1)$ in some order. $H(Y)$ needs the output distribution first.                                                                                                                                                                                                                                               |
| <b>SOLUTION</b> | $H(X) = 1$ bit. $H(Y   X) = H(0.1) = -0.1 \log_2 0.1 - 0.9 \log_2 0.9 = 0.4690$ bits. The output is equally likely, so $H(Y) = 1$ bit, and $I(X; Y) = 1 - 0.4690 = 0.5310$ bits per use.                                                                                                                                                                                                                    |
| <b>CHECK</b>    | One bit was offered and just over half a bit arrived. The missing 0.4690 bits were not delayed or corrupted. They were destroyed, and no receiver however clever recovers them. The joint entropy is $1 + 1 - 0.5310 = 1.4690$ bits, and at $p = 0.25$ the shared part falls to 0.1887 while the total rises to 1.8113. A noisier channel does not destroy uncertainty, it moves it out of the shared part. |

### ⚠ THE TWO CONDITIONAL ENTROPIES ARE NOT THE SAME THING

$H(Y | X)$  is the uncertainty about the *output* given the input, and for the BSC it is  $H(p)$  whatever the transmitter does. A property of the channel alone.  $H(X | Y)$  is the uncertainty about the *input* given the output, and it depends on the input distribution too.  $I(X; Y) = I(Y; X)$  is a statement about one number. It does not make the two ends interchangeable.

## 6.11 Channel capacity

Mutual information measures one transmitter on one channel. Change how often each symbol is sent and the number moves. The channel is fixed and the input distribution is the engineer's to choose. Therefore, take the best choice. What comes out then depends on the channel matrix alone. This occurs because the one free thing has been optimised away. **capacity is a property of the channel, and mutual information is not.**




## CAPACITY, AND THE CAPACITY OF THE BSC


$$C = \max_{\{p(x_j)\}} I(X; Y) \quad \text{bits per channel use}$$

$$C_{\text{BSC}} = 1 - H(p), \quad H(p) = -p \log_2 p - (1 - p) \log_2 (1 - p)$$

For the BSC,  $H(Y | X) = H(p)$  whatever the transmitter does, and  $H(Y) \leq 1$  bit with equality when the output is equally likely — which equally likely inputs deliver. So the maximum sits at  $p(x_0) = \frac{1}{2}$  and the two pieces subtract. The unit is bits per *use* of the channel, not bits per second. Multiply by the number of uses a second to reach a rate.



**FIGURE 6.7** Capacity of the binary symmetric channel. The capacity is one bit at  $p = 0$  and  $p = 1$ . At  $p = 1$ , the receiver restores every bit by inversion. Capacity is zero at  $p = \frac{1}{2}$ , where the output is independent of the input.



**FIGURE 6.8** The Z-channel of Example 6.6. Its mutual information peaks at  $q = 0.6$ , not at a half, which is what an asymmetric channel does: the transmitter should favour the symbol that survives.

The curve is flat near  $p = 0$ : a channel with one error in a thousand has capacity 0.9886 bits, so the first errors cost almost nothing. It then falls away steeply — at  $p = 0.11$  the capacity is already 0.500. Halving the error probability of an already-good channel buys very little, and the effort belongs where the curve is steep.

## EXAMPLE 6.6 — THE CAPACITY OF THE Z-CHANNEL

- GIVEN** A 0 always arrives as a 0. A 1 arrives correctly half the time and as a 0 otherwise. Write  $P(X = 0) = q$ .
- FIND** The capacity, and the input distribution that achieves it.
- METHOD** Nothing is symmetric, so the equally likely input is no longer the right guess. Form  $I(X; Y)$  as a function of  $q$  and maximise it.
- SOLUTION**  $P(Y = 0) = q + \frac{1}{2}(1 - q) = \frac{1}{2}(1 + q)$ , and  $H(Y | X) = q(0) + (1 - q)(1) = 1 - q$  because a transmitted 0 leaves nothing in doubt. Subtracting gives  $I(X; Y) = q - \frac{1}{2}(1 + q) \log_2 (1 + q) - \frac{1}{2}(1 - q) \log_2 (1 - q)$ . Setting the derivative to zero collapses the logarithmic terms to  $\frac{1}{2} \log_2 \frac{1 - q}{1 + q} = -1$ , so  $\frac{1 - q}{1 + q} = \frac{1}{4}$  and  $q^* = 0.6$ .
- CHECK**  $C = 0.3219$  bits per channel use, and  $0.3219 = \log_2 \frac{5}{4}$  exactly — a check on the arithmetic that costs nothing. The optimum is not the balanced input: the transmitter should send the reliable symbol three times in five. A transmitter that guesses  $q = 0.5$  still gets 0.3113 bits, losing about 3%.

### ✓ THE CHANNEL CODING THEOREM

If the transmission rate satisfies  $R_b < C$ , there is a coding scheme whose probability of error is as small as required. If  $R_b > C$ , there is not — no scheme, however long or however clever. **An error-free data rate can never exceed the capacity.** The theorem says a code exists. It does not say what the code is, how long its blocks must be, or what the decoder costs. Finding codes that come close and can also be decoded took the fifty years after it was proved.

## 6.12 The bandlimited channel

Everything above counted symbols. A real channel is given instead as a bandwidth in hertz, an average transmitted power and a noise density. Its capacity is one of the most quoted results in engineering.

### THE INFORMATION CAPACITY LAW

$$C = B \log_2 \left( 1 + \frac{P}{N_0 B} \right) \quad \text{bits per second}$$

$$\frac{C}{B} = \log_2 \left( 1 + \frac{E_b C}{N_0 B} \right) \implies \frac{E_b}{N_0} = \frac{2^{C/B} - 1}{C/B}$$

$B$  is bandwidth,  $P$  is average transmitted power, and  $N_0 B$  is in-band noise power. Use  $P = E_b C$ , where power equals energy per bit times bit rate. Divide by  $B$  to obtain the bandwidth efficiency  $C/B$ .


### ① READ THE TWO KNOBS

$C$  grows **linearly** with bandwidth and only **logarithmically** with power. Doubling the bandwidth at fixed noise density roughly doubles the rate. Doubling the power adds one bit per second per hertz at best and much less when the ratio is already large. Bandwidth is the better buy, and it is the one that is scarce and regulated. At  $C/B = 1$  the requirement is  $E_b/N_0 = 1$ , which is 0 dB. At  $C/B = 2$  it is 1.5, which is 1.76 dB.

### THE SHANNON LIMIT

$$\lim_{x \rightarrow 0} \frac{2^x - 1}{x} = \ln 2, \quad \left. \frac{E_b}{N_0} \right|_{\min} = \ln 2 = 0.693 = -1.59 \text{ dB}$$

Spend bandwidth freely — let  $C/B \rightarrow 0$  — and the energy per bit a system needs falls, but not to nothing. No system of any kind communicates reliably below  $-1.59$  dB: not a better code, not a better modulation, not a better receiver.



**FIGURE 6.9** Bandwidth efficiency against energy per bit. Every working system sits below the curve and to the right of the line. The region to the left of  $-1.59$  dB has never been occupied and never will be. Climbing from one bit per hertz to six costs about 14 dB, and the climb steepens the whole way.

#### ⚠ A FLOOR THAT IS APPROACHED AND NEVER TOUCHED

Reaching the limit needs infinite bandwidth, and the rate per hertz goes to zero on the way. Coherent binary PSK needs about 9.6 dB for an error probability of  $10^{-5}$ , so it sits some 11 dB above the floor. Closing that gap is what channel coding was invented for. This course stops at the uncoded schemes, which is where the gap is widest and easiest to see.

## 6.13 Summary

**TABLE 6.2** Summary of Chapter 6: information, entropy and source coding.

| RESULT                | STATEMENT                                                | ANCHOR      |
|-----------------------|----------------------------------------------------------|-------------|
| Self-information      | $I(s_k) = -\log_2 p_k$                                   | PS CH12.1.1 |
| Entropy               | $H(S) = -\sum_k p_k \log_2 p_k$                          | PS CH12.1.1 |
| Bounds                | $0 \leq H(S) \leq \log_2 K$                              | PS CH12.1.1 |
| Extension             | $H(S^n) = nH(S)$                                         | PS CH12.1.1 |
| Average length        | $\bar{L} = \sum_k p_k l_k, \eta = H(S)/\bar{L}$          | PS CH12.2   |
| Source-coding theorem | $\bar{L} \geq H(S)$ , so $L_{\min} = H(S)$               | PS CH12.2   |
| Kraft                 | $\sum_k 2^{-l_k} \leq 1$ : necessary, not sufficient     | PS CH12.3   |
| Prefix bound          | $H(S) \leq \bar{L} < H(S) + 1$                           | PS CH12.2   |
| Huffman               | optimal, not unique. High placement gives least variance | PS CH12.3.1 |

Chapter 1 turned a waveform into bits. Chapters 2 to 5 got those bits across a channel and counted the errors. This chapter asked how few bits there needed to be in the first place, and answered with one number that the source itself decides. Everything between the two is engineering; the entropy is not.

## APPENDIX

## A

# Summary of formulas

Everything the course establishes, in the order it establishes it. Nothing here is derived — where a result needs an argument, the argument is in the chapter named beside it.

## A.1 From an analog signal to bits — Chapter 1

### SAMPLING AND RECONSTRUCTION

$f_s > 2W$  (the sampling theorem,  $W$  the highest frequency present)

$$x(t) = \sum_{n=-\infty}^{\infty} x(nT_s) \operatorname{sinc}\left(\frac{t - nT_s}{T_s}\right)$$

Below the Nyquist rate the replicas of the spectrum overlap and the overlap cannot be undone.  $\operatorname{sinc}(x) = \sin(\pi x)/(\pi x)$  throughout this course.

### UNIFORM QUANTIZATION

$$\Delta = \frac{2V}{L} = \frac{2V}{2^n}, \quad |e| \leq \frac{\Delta}{2}$$

$$\sigma_q^2 = \frac{\Delta^2}{12}, \quad \operatorname{SQNR}|_{\text{dB}} = 6.02n + 1.76$$

The 1.76 assumes a full-scale sinusoid. The formula is an approximation at small  $n$ . At three bits it gives 19.82 dB where the measured value is 19.09 dB, and the gap halves with each extra bit.

**TABLE A.1** Companding and the PCM bit rate.

| RESULT     | STATEMENT                                                                                                  | CHAPTER |
|------------|------------------------------------------------------------------------------------------------------------|---------|
| Companding | $\mu$ -law and A-law compress before quantizing so that the signal-to-noise ratio is flat across the range | 1       |
| PCM rate   | $R = nf_s$ bits a second for $n$ bits a sample                                                             | 1       |

## A.2 Baseband transmission — Chapter 2

### THE MATCHED FILTER

$$h(t) = s(T - t), \quad \left( \frac{S}{N} \right)_{\max} = \frac{2E}{N_0}$$

The matched filter maximizes the signal-to-noise ratio at the sampling instant. The maximum depends on pulse energy, not pulse shape.

### BINARY ERROR PROBABILITY AT BASEBAND

$$P_b = Q\left(\sqrt{\frac{2E_b}{N_0}}\right) \text{ (antipodal)}, \quad P_b = Q\left(\sqrt{\frac{E_b}{N_0}}\right) \text{ (on-off, orthogonal)}$$

### NYQUIST CRITERION FOR ZERO INTERSYMBOL INTERFERENCE

$$\sum_k P\left(f + \frac{k}{T}\right) = T \quad \text{for all } f$$

$$B = \frac{1 + \alpha}{2T}, \quad 0 \leq \alpha \leq 1$$

The raised cosine meets the criterion for every roll-off  $\alpha$ . At  $\alpha = 0$  the bandwidth is the Nyquist minimum  $1/2T$  and the pulse decays slowly. At  $\alpha = 1$  it is twice that and the pulse decays quickly.

## A.3 Signal space — Chapter 3

### A SIGNAL AS A POINT

$$s_i(t) = \sum_{k=1}^N s_{ik} \psi_k(t), \quad s_{ik} = \int_0^T s_i(t) \psi_k(t) dt$$

$$E_i = \|\mathbf{s}_i\|^2 = \sum_{k=1}^N s_{ik}^2, \quad d_{ij} = \|\mathbf{s}_i - \mathbf{s}_j\|$$

The basis  $\{\psi_k\}$  is orthonormal and comes from the Gram–Schmidt procedure applied to the signal set. Energy becomes a squared length and difference becomes a distance, which is the move the rest of the course rests on.

## A.4 The optimal receiver — Chapter 4

### THE DECISION RULE

$$\hat{s} = \arg \min_i \left\{ \|\mathbf{r} - \mathbf{s}_i\|^2 - N_0 \ln P(\mathbf{s}_i) \right\} \quad (\text{MAP})$$

$$\hat{s} = \arg \min_i \|\mathbf{r} - \mathbf{s}_i\|^2 \quad (\text{ML, equal priors})$$

With equal priors the rule is minimum distance. The equivalent correlation form is to maximise  $\mathbf{r} \cdot \mathbf{s}_i - E_i/2$ .

### ERROR PROBABILITY

$$P(\mathbf{s}_k \rightarrow \mathbf{s}_j) = Q \left( \sqrt{\frac{d_{kj}^2}{2N_0}} \right)$$

$$P_e \leq \frac{1}{M} \sum_k \sum_{j \neq k} Q \left( \sqrt{\frac{d_{kj}^2}{2N_0}} \right), \quad P_e \approx N_{\min} Q \left( \sqrt{\frac{d_{\min}^2}{2N_0}} \right)$$

The first result is exact for two points. The second is the union bound. The third is its nearest-neighbor form. Here,  $N_{\min}$  is the average number of nearest neighbors and can be noninteger. The loose bound needs only  $M$  and  $d_{\min}$ .

## A.5 Digital modulation — Chapter 5

**TABLE A.2** Minimum squared distance and number of nearest neighbours for each scheme.

| SCHEME            | $d_{\min}^2$          | $N_{\min}$                      |
|-------------------|-----------------------|---------------------------------|
| BPSK              | $4E_b$                | 1                               |
| BFSK, BASK        | $2E_b$                | 1                               |
| $M$ -PSK          | $4E_s \sin^2(\pi/M)$  | 2                               |
| $M$ -PAM          | $12E_s/(M^2 - 1)$     | $2(M - 1)/M$                    |
| $M$ -QAM (square) | $6E_s/(M - 1)$        | 3 at $M = 16$ , 3.5 at $M = 64$ |
| $M$ -FSK          | $2E_s$ for every pair | $M - 1$                         |

### READING THE TABLE

$$P_e \approx N_{\min} Q \left( \sqrt{\frac{d_{\min}^2}{2N_0}} \right), \quad E_s = (\log_2 M) E_b$$

Convert once between symbol and bit energy. BFSK and BASK need 3.01 dB more than BPSK for the same error probability. Doubling  $M$  costs approximately 6 dB in PAM. Moving from 4-PSK to 8-PSK costs 5.33 dB. At the same energy, 16-QAM gains 9.29 dB over 16-PAM.

## A.6 Information theory — Chapter 6

### INFORMATION AND ENTROPY

$$I(s_k) = -\log_2 p_k, \quad H(S) = -\sum_{k=1}^K p_k \log_2 p_k$$

$$0 \leq H(S) \leq \log_2 K, \quad H(S^n) = n H(S)$$

The upper bound is reached when all  $K$  symbols are equally likely. The extension result holds because the source is memoryless.

### SOURCE CODING

$$\bar{L} = \sum_{k=1}^K p_k l_k, \quad \eta = \frac{H(S)}{\bar{L}} \leq 1$$

$$\sum_{k=1}^K 2^{-l_k} \leq 1, \quad H(S) \leq \bar{L} < H(S) + 1$$

The Kraft inequality is necessary but not sufficient for a prefix code. Over the  $n$ -th extension the upper bound becomes  $H(S) + 1/n$ , so  $L_n/n \rightarrow H(S)$ .

### HUFFMAN CODES

$$\sigma^2 = \sum_{k=1}^K p_k (l_k - \bar{L})^2$$

Huffman is optimal in average length and is not unique. Placing a merged symbol as high as possible on a tie gives the minimum-variance code among the optimal ones.

## APPENDIX

## B

## The laboratories

*The course has four laboratories, and each one takes a result the chapters derive on paper and asks you to measure it instead. This appendix runs all four. Every curve, cloud and staircase on the pages that follow was computed when this page was drawn. The noise was generated, the filter was applied, the errors were counted. So what you see is the outcome of a run and not a drawing of one.*

That matters for one reason above all. A formula tells you what should happen. A measurement tells you what did. Where the two agree you have learnt that the derivation is sound. Where they disagree you have learnt something better: which assumption in the derivation the experiment broke. Each of the four sections below ends on that disagreement, because it is the part of the laboratory worth carrying away.

Your numerical results will differ from these examples. Each group receives a different input number, so its waveform, bit pattern, and source statistics differ. Random noise also changes between runs. Compare curve shapes, gaps, trends, and expected directions instead of individual sample values.

### ✓ LABORATORY SUMMARY

**B.1** builds a uniform quantizer, measures SQNR, and encodes the samples as a polar-NRZ waveform. **B.2** measures the bit error rate of a matched-filter receiver and compares it with the Chapter 2 formula. **B.3** measures the symbol error rate of sixteen-point QAM and compares it with the Chapter 4 bound. **B.4** builds a Huffman code and measures its compression.


### B.1 Quantization, the signal-to-quantization-noise ratio and PCM

The first laboratory applies the complete Chapter 1 chain. Start with a continuous waveform and sample it at the Nyquist rate. Quantize the samples with a uniform quantizer. Measure the ratio of signal power to quantization-error power. Encode each sample as a binary word and draw the polar-NRZ waveform. Then double the number of levels and repeat the measurements.

The waveform is  $x(t) = f_1 \sin(2\pi f_1 t) + f_2 \cos(2\pi f_2 t)$ . Each group receives integer values for  $f_1$  and  $f_2$ . Here,  $f_1 = 3$  and  $f_2 = 4$ , so the Nyquist rate is 8 samples per second. A two-second interval then contains only seventeen samples.


The quantizer itself is four lines. Find the smallest and largest sample. Divide the distance between them into  $L$  equal cells. Therefore, the step is  $\Delta = (x_{\max} - x_{\min})/L$ . Decide which cell each sample falls in. Replace it by the middle of that cell. This is the value that minimises the error inside the cell when nothing is known about where in the cell the sample sits.






**FIGURE B.1** The first second of the run. The pale line is  $x(t)$ . Stems show samples  $x_n$  taken every  $1/8$  s. Filled circles show quantized values  $\hat{x}_n$  for  $L = 8$ . Dotted lines show the eight representation levels with spacing  $\Delta = 1.640$  V.

With  $L = 8$  each sample needs  $R = \log_2 8 = 3$  bits, and at  $f_s = 8$  samples a second the stream leaves the encoder at  $R_b = Rf_s = 24$  bit/s. At  $L = 16$  it is 32 bit/s. That is the price of the second experiment, and it is worth naming before the reward is measured: a third more bits a second.



**FIGURE B.2** The quantizer itself, drawn by feeding it a thousand values across its range. Eight treads, each  $\Delta = 1.640$  V wide, each one tread high.




**FIGURE B.3** The first four samples encoded and sent. Each sample becomes a three-bit word for its cell, and each bit becomes one bit interval of a polar NRZ waveform. High for a one, low for a zero.

#### WHAT THE LABORATORY MEASURES

$$\text{SQNR} = \frac{E[X^2]}{E[(X - \hat{X})^2]} \longrightarrow \text{SQNR}|_{\text{dB}} = 10 \log_{10} \text{SQNR}$$

Both averages use the available samples. The numerator is the sample mean-square value. The denominator is the mean-square quantization error. Chapter 1 models this denominator as  $\Delta^2/12$ . Here, it is measured directly.

On this waveform the measurement gives 17.80 dB at  $L = 8$  and 23.83 dB at  $L = 16$ . The difference is 6.03 dB. This is the six decibels a bit that Section 1.4 predicts, arrived at by counting. That agreement is the main result of the laboratory, and it holds for a reason that has nothing to do with this particular waveform. Doubling  $L$  halves  $\Delta$ , halving  $\Delta$  quarters  $\Delta^2/12$ , and a factor of four is 6.02 dB.



**FIGURE B.4** Measured against modelled, for one to six bits a sample, both computed from the seventeen samples the laboratory takes. The dashed line is the small-step model  $10 \log_{10}(P_X/(\Delta^2/12))$  and the circles are the ratio actually measured. The circles rise about six decibels a bit, as they should. But they sit below the line by between 1.0 and 2.9 dB, and the gap neither closes nor settles as  $R$  grows. Something is wrong, and the next note says what.

#### ⊗ SEVENTEEN SAMPLES IS NOT A POPULATION

The measured points and the modelled line disagree by up to 2.9 dB, and the gap does not shrink as  $L$  grows. It is tempting to blame the model, and Section 1.4 gives a real reason it could be blamed. The error is not quite uniform across a cell. But measure the same waveform with two thousand samples instead of seventeen and the gap falls to less than 0.6 dB everywhere. The model was right. The estimate was noisy. Both  $E[X^2]$  and  $E[(X - \hat{X})^2]$  are averages, and an average over seventeen numbers has a spread of its own. This is the error to name in your report. Do not draw a conclusion about a model from a sample too small to test it.


#### ⚠ SAMPLING EXACTLY AT THE NYQUIST RATE

The waveform here has a 4 Hz component and the laboratory samples at exactly 8 Hz. This is the boundary the sampling theorem is stated at rather than inside. At exactly twice its frequency, a cosine is sampled at the same two points of every cycle. Therefore, that component contributes the same alternating  $\pm 4$  to every sample and none of its shape survives. The reconstruction is still correct here because the component is a cosine and lands on its peaks. Move the phase and it would not be. Chapter 1 asks for  $f_s > 2W$  and means the strict inequality.


## B.2 The matched filter and the bit error rate

The second laboratory builds the Chapter 2 receiver. Convert a bit stream into a waveform and add white Gaussian noise. Apply the matched filter and sample its output once per bit. Compare each sample with the decision threshold. Then compare the measured error rate with  $Q(\sqrt{2E_b/N_0})$ .

The signaling is antipodal. The pulse  $\psi(t) = 1/\sqrt{T_b}$  has unit energy over one bit interval. A bit scales this pulse by  $\pm A\sqrt{T_b}$ . Thus, the transmitted waveform is constant at  $+A$  or  $-A$  during each interval. Its bit energy is  $E_b = A^2 T_b$ . Add sample noise with variance  $N_0/2$  and use  $10 \log_{10}(E_b/N_0)$ .




**FIGURE B.5** Sixteen bits at  $E_b/N_0 = 2$  dB. The clean square wave is the transmitted  $s(t)$ . The hairline around it is  $x(t) = s(t) + w(t)$ . This is everything the receiver is given. Nothing about the square wave is visible in the hairline at this noise level, and that is the honest picture. The receiver does not see the signal, it computes with it.



**FIGURE B.6** The matched-filter output for the same sixteen bits, read once at the end of every bit interval. The dashed line is the threshold  $\lambda = 0$ . This is where equal priors put it. Fifteen of the sixteen readings are on the correct side of it. The eleventh is not, and it is drawn in red. At 2 dB the formula expects about one wrong bit in twenty-seven, and this run produced one in sixteen.

One run of sixteen bits settles nothing. One error could as easily have been none or three. The second part of the laboratory therefore drops the picture and repeats the experiment. Five thousand bits at each signal-to-noise ratio from 0 to 5 dB in quarter-decibel steps, counting errors and dividing by five thousand.



**FIGURE B.7** Measured bit error rate against the formula, five thousand bits a point. The line is  $Q(\sqrt{2E_b/N_0})$  and the circles are counted errors. Nowhere on the sweep do the two differ by more than 0.005, and yet the circles clearly wander further from the line towards the right. The next note is about why those two statements are both true.

#### ⚠ MONTE CARLO SCATTER

Counting  $k$  errors in  $N$  bits gives a standard spread of approximately  $\sqrt{p(1-p)/N}$ . At 0 dB,  $p \approx 0.079$ , and five thousand bits give a spread of 0.004. At 5 dB, the absolute spread decreases, but it becomes a larger fraction of  $p$ . A logarithmic plot shows this relative scatter. Measuring probabilities near  $10^{-6}$  therefore requires millions of trials.

#### ⊗ THREE-DECIBEL CONVENTION ERRORS


Two convention errors each give a factor of two. First, the sample-noise variance is  $N_0/2$  for a two-sided density  $N_0/2$ . Using  $N_0$  shifts the measured curve by 3 dB. Second, the formula  $Q(\sqrt{2E_b/N_0})$  requires antipodal signaling. On-off signaling instead uses  $Q(\sqrt{E_b/N_0})$ . A parallel 3 dB shift usually indicates one of these errors.

## B.3 Sixteen-point QAM and the union bound


The third laboratory uses a two-dimensional sixteen-point square constellation. Add independent noise on each axis. The receiver selects the nearest point. Compare the measured symbol error rate with the nearest-neighbor approximation from Section 4.4.

Write each point as  $s_I + js_Q$ , with coordinates from  $\{-3, -1, 1, 3\}$ . These units give  $E_s = 10$  and  $d_{\min} = 2$ . Each symbol carries four bits, so  $E_b = E_s/4 = 2.5$ . Section 5.4 gives  $d_{\min}^2 = 6E_s/(M - 1) = 4$ . This result agrees with the point spacing.

The same constellation gives the optimal thresholds. Independent axes and equal level spacing produce three vertical and three horizontal boundaries. Each axis uses  $\lambda \in \{-2, 0, 2\}$ . Thus, nearest-point detection reduces to nearest-level detection on each axis.



**FIGURE B.8**  $E_b/N_0 = 6$  dB. The clouds touch, so a large fraction of the symbols land across a boundary. The measured symbol error rate here is 0.108: about one symbol in nine is decided wrongly.




**FIGURE B.9**  $E_b/N_0 = 11$  dB. Five decibels more energy a bit, and the clouds have pulled apart into sixteen separate blobs. The measured rate falls to 0.0022, about fifty times better.

Twelve hundred received symbols are drawn in each picture so that the clouds can be seen. The rates quoted beneath them do not come from those twelve hundred. A rate of 0.0022 measured on twelve hundred symbols would be three errors, and three is not a measurement. They come from the sweep below. This uses fifty thousand symbols at 6 dB and a quarter of a million at 11 dB. Choosing how many symbols to run is part of the experiment, and Section B.2 said why.

#### WHAT THE BOUND PREDICTS

$$P_e \approx N_{\min} Q \left( \sqrt{\frac{d_{\min}^2}{2N_0}} \right), \quad N_{\min} = 3, \quad d_{\min}^2 = 4$$

$N_{\min}$  is the average number of nearest neighbours: four corner points have two each, eight edge points three, and four inner points four, and  $(4 \cdot 2 + 8 \cdot 3 + 4 \cdot 4)/16 = 3$ . It is an average over the constellation and it does not have to be a whole number.



**FIGURE B.10** Measured symbol error rate against the nearest-neighbour approximation. The number of symbols is raised as the rate falls. Fifty thousand at the left, four hundred thousand at the right. So that every circle rests on a few hundred errors. The circles sit below the line at the left and join it by about 8 dB. That gap is not an error in either the simulation or the formula. It is what the approximation is.

#### ✓ MEASURED ERROR AND THE UNION BOUND

The union bound adds all pairwise error probabilities. These events overlap, so the sum can count one noise vector more than once. The bound is therefore larger than the exact union probability. At low signal-to-noise ratio, overlap makes the bound loose. At high ratios, nearest-neighbor errors dominate and overlap becomes small. Remaining differences between simulated points and the bound can come from finite trial counts.

#### ⊗ SYMBOL AND BIT ENERGY

For sixteen-point QAM,  $E_s = 4E_b$ . Convert between these energies once when calculating  $N_0$ . Do not calculate  $N_0$  from one energy and use the other in the  $Q$  function. This error shifts the complete curve by  $10 \log_{10} 4 = 6.02$  dB.


## B.4 Huffman coding and how much it compresses

The fourth laboratory studies lossless source coding. A source emits symbols with known probabilities. Entropy gives the minimum average bits per symbol. Huffman coding gives the best single-symbol prefix code. The laboratory measures both values.


The source alphabet is the ten digits. Your group counts how often each digit occurs in a number it is given and divides by how many digits there are. This gives a probability for each. The case run here uses the eleven digits 1 2 3 4 5 6 5 4 3 2 1. Five digits occur twice and one occurs once. Therefore, five symbols have probability  $2/11$ , one has  $1/11$ , and four have probability zero and take no codeword at all.

### ⊗ DIVIDING BY THE WRONG TOTAL

The probabilities must come from dividing each count by the *number of symbols*. Dividing by anything else. The sum of the digit values, say. Gives a set of numbers that does not add up to one, and everything downstream is then quietly wrong. The entropy is not an entropy, the codebook is built for a source that does not exist, and the efficiency can come out above 100%. Print the sum of your probability vector and confirm it is one before you compute anything from it. It is one line, and it catches the only mistake in this laboratory that produces plausible numbers instead of an error message.



**FIGURE B.11** The source statistics  $p_i$  over the ten-digit alphabet. Four digits do not occur, and a symbol of probability zero is left out of both the entropy and the codebook.



**FIGURE B.12** The code the algorithm builds. Reading a path from the root, left is a 0 and right is a 1. The digit at each leaf is the symbol that path spells.


This source has entropy  $H = 2.550$  bits per symbol. Its Huffman code has average length  $\bar{L} = 2.636$ , so  $\eta = 96.7\%$ . First, check the Section 6.6 bound  $H \leq \bar{L} < H + 1$ . Here,  $2.550 \leq 2.636 < 3.550$ . Second, compare  $\bar{L}$  with the three-bit fixed length for six symbols and the four-bit length for ten symbols.

### ⚠ A TIE IN THE ALGORITHM IS NOT A MISTAKE


Whenever two nodes have the same probability, the algorithm may merge either, and different choices give different codebooks with the same average length. Your codewords will not match the ones drawn above and need not. What must match is  $\bar{L}$ , because Huffman is optimal and the optimal average length is unique even when the code is not. If two groups get different average lengths for the same statistics, one of them has an error. If they get different codebooks, neither of them does. Section 6.7 develops the tie-breaking rule that also minimises the variance of the codeword length.

The second part encodes one thousand symbols from the same distribution. Four-bit fixed-length coding uses 4000 bits. Huffman coding uses 2621 bits, so the measured compression is 34.5%. The average length predicts  $1 - \bar{L}/4 = 34.1\%$ . These values need not match exactly because the finite sequence is one random sample. A large difference can indicate an incorrect codebook.

The third part asks what the source statistics themselves are worth. Ten counts are drawn from a binomial trial with 50 attempts and success probability  $\rho$ , then normalised into a distribution. At  $\rho = 0.01$  almost every attempt fails, so most counts come out zero and the surviving symbols are few. At  $\rho = 0.99$  almost every attempt succeeds, so all ten counts come out near 50 and the distribution is nearly flat.



**FIGURE B.13**  $\rho = 0.01$ . Five symbols survive and the rest have probability zero.  $H = 2.322$  bits,  $\bar{L} = 2.400$  bits.



**FIGURE B.14**  $\rho = 0.99$ . All ten symbols occur about equally often.  $H = 3.322$  bits,  $\bar{L} = 3.395$  bits.

**TABLE B.1** Entropy, average codeword length, efficiency and compression for the three sources.

| SOURCE           | $H$   | $\bar{L}$ | $\eta$ | COMPRESSION AGAINST 4 BITS |
|------------------|-------|-----------|--------|----------------------------|
| The digit source | 2.550 | 2.636     | 96.7%  | 34.1%                      |
| $\rho = 0.01$    | 2.322 | 2.400     | 96.7%  | 40.0%                      |
| $\rho = 0.99$    | 3.322 | 3.395     | 97.8%  | 15.1%                      |

#### ✓ EFFICIENCY AND COMPRESSION

The coding efficiency changes from 96.7% to 97.8%, while compression decreases from 40% to 15%. Efficiency measures the gap between the code length and the source entropy. Compression compares the code length with a four-bit fixed-length code. At  $\rho = 0.99$ , the source is nearly uniform and has entropy 3.322 bits. Therefore, little lossless compression remains possible.



#### Digital Communications · Lecture Notes

| VERSION | DATE              | CHANGES        |
|---------|-------------------|----------------|
| v0      | 24 September 2026 | First edition. |

© 2026 [huguryildiz.com](http://huguryildiz.com) · Course content: CC BY-NC-SA 4.0