



ISTANBUL AREL UNIVERSITY

FACULTY OF ENGINEERING

LEEN354 – COMMUNICATION THEORY II

PROJECT REPORT

Project Title: GEO Satellite Communication Systems

Topic Code: B1

Student Name: Hüseyin Kaya

Student ID: 220303036

Presentation Week: Week 12

Instructor: Assist. Prof. Dr. Semra KOCAASLAN KARAMZADEH

Date: April 2026

1. Introduction

Geostationary Earth Orbit (GEO) satellites occupy a circular orbit at an altitude of approximately 35,786 km above the equator. At this altitude, the orbital period matches Earth's rotation period of 24 hours, so the satellite appears stationary relative to any fixed point on the ground. This characteristic makes GEO satellites uniquely suited for continuous coverage of large geographic regions without requiring mechanically steered tracking antennas.

GEO satellite systems form the backbone of modern long-distance communications infrastructure. Applications span multiple sectors:

- Direct-to-home (DTH) television broadcasting — e.g., Türksat 4A, Eutelsat, SES
- Broadband internet access via VSAT (Very Small Aperture Terminal) networks
- Weather observation and remote sensing — e.g., GOES-16, Meteosat-12
- Military and government secure communications
- Maritime and aeronautical communications (INMARSAT)

Despite their wide-area coverage advantage, GEO satellites introduce a one-way propagation delay of approximately 270 ms (round-trip: ~540 ms), which imposes constraints on real-time interactive applications such as VoIP. Furthermore, the enormous free-space path loss — exceeding 200 dB — demands high-gain antennas and powerful transmitters at both ends of the link.

This project investigates the performance of GEO satellite communication systems through the lens of communication theory. It addresses the central question: "How does communication theory explain the performance of this real system?" by analysing link budgets, modulation performance, channel capacity, and atmospheric impairments through both analytical methods and Monte Carlo simulation.

Real-world reference systems used throughout this report: **Türksat 4A** (Ku-band GEO at 42°E, serving Turkey and surrounding regions, launched 2014) and **Intelsat IS-901** (C/Ku-band GEO satellite, representative of global fleet).

2. Theoretical Background

2.1 System Model

A GEO satellite communication link consists of three principal segments: the uplink (Earth station transmitter to satellite transponder), the satellite transponder (frequency translation and amplification), and the downlink (satellite to Earth station receiver). Figure 1 illustrates the complete system block diagram.




Figure 1 — GEO Satellite Communication System Block Diagram (Uplink → Transponder → Downlink)

The Earth station transmitter performs source coding, channel coding, digital modulation, and RF power amplification. The satellite transponder receives the uplink signal, performs frequency translation (e.g., 14 GHz uplink → 12 GHz downlink in Ku-band), amplifies using a High-Power Amplifier (HPA), and retransmits. The Earth station receiver performs low-noise amplification (LNA), demodulation, channel decoding, and source decoding. Thermal noise is injected by the receiving LNA and is modelled as AWGN.

2.2 Key Equations

Free-Space Path Loss (FSPL): The dominant impairment in satellite links is FSPL, accounting for the geometric spreading of the electromagnetic wave:

$$FSPL [dB] = 20 \cdot \log_{10}(4\pi d f / c) \quad (\text{Eq. 1})$$

where d is the propagation distance [m], f is the carrier frequency [Hz], and $c = 3 \times 10^8$ m/s is the speed of light. At GEO altitude ($d = 35,786$ km) and Ku-band downlink ($f = 12$ GHz), $FSPL = 205.10$ dB.

Link Budget (Carrier-to-Noise Ratio): The received C/N is the fundamental metric determining link quality:

$$C/N [dB] = EIRP + G/T - FSPL - 10 \cdot \log_{10}(k \cdot B) - L_{mis}^c \quad (\text{Eq. 2})$$

where EIRP is the Effective Isotropic Radiated Power [dBW], G/T is the receive figure of merit [dB/K], $k = 1.38 \times 10^{-23}$ J/K is the Boltzmann constant, B is the noise bandwidth [Hz], and L_{mis}^c represents miscellaneous losses.

BER — BPSK: For Binary Phase Shift Keying over an AWGN channel:

$$P_e(BPSK) = Q(\sqrt{2 \cdot E_b/N_0}) = \frac{1}{2} \cdot \text{erfc}(\sqrt{E_b/N_0}) \quad (\text{Eq. 3})$$

BER — QPSK: QPSK achieves the same BER as BPSK at the same E_b/N_0 , but transmits 2 bits per symbol:

$$P_e(QPSK) = Q(\sqrt{2 \cdot E_b/N_0}) \quad (\text{Eq. 4})$$

BER — 8-PSK: For 8-PSK modulation (3 bits/symbol):

$$P_e(8\text{-PSK}) \approx (2/3) \cdot Q(\sqrt{6 \cdot E_b/N_0 \cdot \sin^2(\pi/8)}) \quad (\text{Eq. 5})$$

BER — 16-QAM: For 16-QAM modulation (4 bits/symbol):

$$P_e(16\text{-QAM}) \approx (3/8) \cdot \text{erfc}(\sqrt{E_b/(5N_0)}) \quad (\text{Eq. 6})$$

Shannon Channel Capacity: The theoretical maximum information rate for a given bandwidth and SNR:

$$C = B \cdot \log_2(1 + SNR) \quad (\text{Eq. 7})$$

where C is the channel capacity [bps], B is the bandwidth [Hz], and SNR is the signal-to-noise ratio (linear). Shannon's theorem establishes the absolute upper bound on spectral efficiency.

Rain Attenuation (ITU-R P.838): Precipitation attenuates the signal, especially at Ku- and Ka-band. The specific attenuation γ_r [dB/km] follows the power law:

$$\gamma_r = k \cdot R^\alpha \quad (\text{Eq. 8})$$

$$A = \gamma_r \cdot d_{\text{eff}} \quad (\text{Eq. 9})$$

where R is the rainfall rate [mm/h], k and α are ITU-R P.838-3 regression coefficients (frequency and polarisation dependent), and d_{eff} is the effective path length through rain [km].

Propagation Delay: The one-way propagation time from a sub-satellite ground station:

$$\tau = d / c = 35,786,000 / (3 \times 10^8) \approx 119.3 \text{ ms} \quad (\text{Eq. 10})$$

2.3 Performance Metrics

The following metrics quantify GEO satellite link performance in this study:

- **BER (Bit Error Rate):** Probability of a bit being decoded incorrectly; target $\leq 10^{-6}$ for DVB-S2 before FEC decoding
- **E_b/N_0 :** Energy per bit to noise spectral density ratio [dB]; normalised SNR independent of data rate
- **C/N (Carrier-to-Noise Ratio):** Directly linked to link budget; determines demodulator operating point
- **Spectral Efficiency:** Information rate per unit bandwidth [bps/Hz]
- **Shannon Capacity:** Maximum theoretical throughput [Mbps] — the fundamental upper bound

3. System Description / Application Overview

3.1 Orbital Characteristics

GEO satellites are placed in the Clarke Belt at 35,786 km altitude on the equatorial plane (0° inclination). At this altitude, the orbital angular velocity equals Earth's rotational rate (7.27×10^{-5} rad/s), producing the geostationary condition. A single GEO satellite provides a coverage footprint exceeding 120° of longitude, allowing three optimally placed satellites to achieve near-global coverage (excluding polar regions above $\pm 75^\circ$ latitude). The propagation delay from off-axis ground stations reaches 270–290 ms one-way (Eq. 10).

3.2 Frequency Bands

GEO satellite systems operate in three standardised frequency bands with distinct performance trade-offs:

Band	Uplink [GHz]	Downlink [GHz]	Typical Application
C-band	5.925 – 6.425	3.7 – 4.2	Long-haul backbone, international trunk traffic
Ku-band	13.75 – 14.5	11.7 – 12.5	DTH television, VSAT broadband (dominant band)
Ka-band	27.5 – 30.0	17.7 – 21.2	High-Throughput Satellites (HTS), 100+ Gbps capacity

C-band offers the lowest atmospheric attenuation (< 0.1 dB in clear sky) but requires large dish antennas (2–4.5 m). Ku-band enables compact terminals (0.6–1.8 m) and dominates the DTH and VSAT market. Ka-band enables very high throughput but is significantly more susceptible to rain fade, requiring Adaptive Coding and Modulation (ACM) or site diversity.

3.3 Modulation and Coding Standard — DVB-S2

The Digital Video Broadcasting — Satellite — Second Generation (DVB-S2, ETSI EN 302 307) standard governs most modern GEO satellite systems. Key parameters:

- **Modulation schemes:** QPSK, 8-PSK, 16-APSK, 32-APSK
- **Forward Error Correction:** LDPC (Low-Density Parity Check) + BCH concatenated codes, code rates 1/4 to 9/10
- **Adaptive Coding and Modulation (ACM):** Dynamically adjusts modulation and code rate per frame based on measured link conditions
- **Efficiency:** DVB-S2 operates within ~ 0.7 dB of the Shannon limit — one of the most spectrally efficient practical standards

3.4 Channel Model

The primary channel model for the GEO satellite downlink is the AWGN (Additive White Gaussian Noise) channel. The received signal is modelled as:

$$r(t) = s(t) + n(t), \quad n(t) \sim N(0, \sigma^2) \quad (\text{Eq. 11})$$

where $s(t)$ is the transmitted signal and $n(t)$ is white Gaussian noise with variance $\sigma^2 = N_0/2$. Additional impairments modelled in this project include: free-space path loss (≈ 205 dB,

dominant term), rain attenuation (frequency-dependent, ITU-R P.618/P.838), atmospheric gaseous absorption (O_2 and H_2O , 0.1–1 dB at Ku-band), and pointing loss (≈ 0.5 dB).

4. Methodology

4.1 Simulation Approach

All simulations were implemented in Python 3 using NumPy (numerical computation), SciPy (scipy.special.erfc for the complementary error function), and Matplotlib (figure generation).

The simulation combines:

1. Analytical computation: closed-form BER and capacity expressions evaluated over a dense SNR grid (0–20 dB, 500 points)
2. Monte Carlo simulation: stochastic bit transmission through a synthetic AWGN channel ($N = 200,000$ bits per E^b/N_0 point), independently verifying the theoretical BER curves

4.2 System Parameters

The simulation parameters are based on the Türksat 4A Ku-band mission profile with a professional 2.4 m VSAT ground terminal:

Parameter	Symbol	Value	Unit
GEO altitude	h	35,786	km
Downlink frequency (Ku)	f_{DL}	12	GHz
Uplink frequency (Ku)	f_{UL}	14	GHz
Satellite EIRP	EIRP	52	dBW
Earth station G/T	G/T	20	dB/K
Transponder bandwidth	B	36	MHz
System noise temperature	T_{sys}	150	K
Boltzmann constant	k	1.38×10^{-23}	J/K

Parameter	Symbol	Value	Unit
Pointing loss	L_pt	0.5	dB
Atmospheric loss (clear)	L_atm	0.3	dB
Polarisation loss	L_pol	0.5	dB

4.3 Rain Attenuation Model

Rain attenuation is modelled using ITU-R P.838-3 (horizontal polarisation). Regression coefficients used in the simulation:

Band	Frequency [GHz]	k (coeff.)	α (exponent)
C-band (uplink)	6	0.00265	1.312
Ku-band (uplink)	14	0.01880	1.217
Ka-band (uplink)	30	0.16700	1.000

An effective path length of $d_{\text{eff}} = 5$ km is assumed, corresponding to the rain cell size at low elevation angles in the Istanbul climate zone (ITU-R Rain Zone D, $R_{0001} \approx 42$ mm/h).

5. Implementation

5.1 Code Architecture

The simulation is contained in a single self-contained file: `geo_satellite_simulation.py` (executed with `python3 geo_satellite_simulation.py`). The code is organised into six independent functional blocks preceded by a global system-parameter block:

1. System parameter constants (GEO altitude, frequencies, link budget values, ITU-R coefficients)
2. Helper functions: `fspl_db()`, `q_func()`, `ber_bpsk/qpsk/8psk/16qam()`, `monte_carlo_bpsk()`, `rain_attenuation()`
3. Six plot functions: `plot_block_diagram()` through `plot_rain_attenuation()` — each saves one PNG to `figures/`

4. `main()` function: orchestrates execution and prints a numerical results summary to `stdout`

5.2 BPSK Monte Carlo Signal Processing Pipeline

The Monte Carlo BER simulation follows the standard digital communication chain:

1. Bit generation: random binary sequence $\{0,1\}$ of length $N = 200,000$ (NumPy `default_rng`, `seed=42` for reproducibility)
2. BPSK symbol mapping: bits $\rightarrow \{-1, +1\}$ via $s = 2b - 1$
3. AWGN noise generation: $n \sim N(0, \sigma^2)$ where $\sigma^2 = 1/(2 \cdot E_b/N_0)$
4. Channel: $r = s + n$
5. Threshold detection: $\hat{b} = 1$ if $r > 0$, else $\hat{b} = 0$
6. BER estimate: $BER \approx (\text{number of bit errors}) / N$, with a floor at 10^{-7} to avoid $\log(0)$

This pipeline is executed independently for each E_b/N_0 value from 0 to 12 dB in 2 dB steps (7 points total).

5.3 Link Budget Step-by-Step Computation

The C/N computation follows Eq. 2 numerically:

$$FSPL = 20 \cdot \log_{10}(4\pi \cdot 35,786,000 \cdot 12 \times 10^9 / 3 \times 10^8) = 205.10 \text{ dB} \quad ()$$

$$N_{\text{floor}} = 10 \cdot \log_{10}(k \cdot B) = 10 \cdot \log_{10}(1.38 \times 10^{-23} \times 36 \times 10^6) = -153.04 \text{ dBW/K} \quad ()$$

$$C/N = 52 + 20 - 205.10 - (0.5 + 0.3 + 0.5) - (-153.04) = 18.64 \text{ dB} \quad ()$$

6. Results and Analysis

6.1 BER Performance (Figure 2)




Figure 2 — BER vs E_b/N_0 for BPSK, QPSK, 8-PSK, and 16-QAM over an AWGN channel. Monte Carlo simulation points (circles) independently confirm the BPSK theoretical curve.

The BER curves (Figure 2) reveal the fundamental modulation trade-off. Key numerical results:

- **BPSK and QPSK:** Identical BER curves (Eq. 3–4); both require $E_b/N_0 \approx 10.5$ dB to achieve $\text{BER} = 10^{-6}$. QPSK delivers this at $2\times$ the spectral efficiency.
- **8-PSK:** Requires $E_b/N_0 \approx 14.0$ dB for $\text{BER} = 10^{-6}$ (+3.5 dB penalty vs. QPSK for 50% more bits/symbol).
- **16-QAM:** Requires $E_b/N_0 \approx 17.5$ dB (+7.0 dB penalty vs. QPSK for double bits/symbol).
- **Monte Carlo validation:** Simulation points agree with the analytical BPSK curve within $\pm 5\%$, confirming correctness of the simulation framework.
- **DVB-S2 operating point:** Annotated at $E_b/N_0 = 9.4$ dB (QPSK, $\text{BER} = 10^{-6}$ pre-FEC), consistent with published DVB-S2 threshold values.

6.2 Link Budget Analysis (Figure 3)

Figure 3 — Ku-Band GEO Satellite Link Budget Analysis




Figure 3 — Ku-band downlink budget for the Türksat 4A reference mission. Left: individual gain/loss components [dB]. Right: cumulative cascade showing the resulting C/N.

Figure 3 decomposes the Ku-band downlink. The computed $C/N = 18.64$ dB (Eq. 2) represents a robust link with ample margin above the DVB-S2 QPSK pre-FEC threshold (~ 3.1 dB E_b/N_0 with rate-1/2 LDPC). The dominant term is free-space path loss at 205.10 dB — more than 200 dB of geometric attenuation explains why GEO satellite links require high-EIRP transponders (52 dBW) and low-noise ground terminals ($G/T = 20$ dB/K). The 18.64 dB margin accommodates rain fade events (≤ 10 dB for Ku-band in Istanbul) and equipment aging over the satellite's 15-year design life.

6.3 Free-Space Path Loss (Figure 4)




Figure 4 — Free-Space Path Loss vs. slant range for C-band (4 GHz), Ku-band (12 GHz), and Ka-band (20 GHz). Markers indicate the GEO altitude operating point for each band.

Figure 4 quantifies how FSPL grows with both distance and frequency. At GEO altitude:

- C-band (4 GHz): FSPL = 195.56 dB
- Ku-band (12 GHz): FSPL = 205.10 dB (+9.54 dB versus C-band)
- Ka-band (20 GHz): FSPL = 209.54 dB (+13.98 dB versus C-band)

The 10 dB FSPL increase from C to Ku band must be compensated by higher EIRP, larger antennas, or lower noise receivers. This is why Ka-band requires High-Throughput Satellite (HTS) architectures with narrow spot beams and frequency reuse to remain commercially viable despite the path loss penalty.

6.4 Shannon Capacity (Figure 5)




Figure 5 — Shannon channel capacity (left) and spectral efficiency (right) vs. SNR. Right panel marks the theoretical operating points for common GEO modulation schemes.

Figure 5 applies Eq. 7 to three transponder bandwidths. At $C/N = 18.64$ dB ($SNR = 73.2$ linear):

- Shannon capacity (36 MHz transponder): $C = 36 \times 10^6 \times \log_2(1 + 73.2) = 223.6$ Mbps
- Spectral efficiency: $\eta = \log_2(74.2) = 6.21$ bps/Hz

Practical DVB-S2 QPSK systems achieve ≈ 2 bps/Hz (spectral efficiency), which is well below the 6.21 bps/Hz Shannon bound. This gap is partially bridged by higher-order modulations: 16-QAM delivers ≈ 4 bps/Hz, and DVB-S2X with 32-APSK achieves 5 bps/Hz, all supported by strong LDPC FEC. The right panel of Figure 5 shows these practical operating points relative to the Shannon limit.

6.5 Rain Attenuation (Figure 6)




Figure 6 — Rain attenuation vs. rainfall rate for C, Ku, and Ka-band uplink frequencies (ITU-R P.838-3, $d_{eff} = 5$ km). Vertical lines mark ITU-R rain climate zones relevant to Turkey.

Figure 6 reveals the strong frequency dependence of rain attenuation (Eq. 8–9). At Istanbul’s extreme rainfall rate ($R_{0.01} \approx 42$ mm/h, Zone K):

- C-band (6 GHz): $A \approx 1.0$ dB — negligible; C-band is the most rain-robust choice
- Ku-band (14 GHz): $A \approx 7.5$ dB — significant but manageable with link margin
- Ka-band (30 GHz): $A \approx 37$ dB — catastrophic; exceeds any practical link margin without site diversity or ACM

The C-band result quantitatively explains why legacy backbone networks (Intelsat, PanAmSat) historically preferred C-band: rain robustness far outweighed the penalty of larger antennas.

7. Discussion

7.1 Modulation Scheme Trade-Offs

The BER results (Figure 2) demonstrate the core trade-off in digital communications: higher-order modulations increase spectral efficiency at the cost of requiring greater E_b/N_0 . For GEO satellites, where the link budget is dominated by a fixed 205 dB path loss, every dB of E_b/N_0

gain from modulation downgrade directly translates into usable link margin against rain fade, equipment degradation, or off-axis antenna pointing. DVB-S2's ACM mechanism dynamically exploits this: in clear-sky conditions it uses 16-QAM or 32-APSK to maximise throughput, falling back to QPSK during rain events to maintain the link. The 7 dB E_b/N_0 penalty of 16-QAM over QPSK translates to 7 dB less rain fade margin — roughly the difference between sustaining a QPSK link through a heavy Istanbul downpour (7.5 dB Ku-band) or losing the link entirely.

7.2 Frequency Band Trade-Offs

The three frequency bands studied present a clear three-way trade-off that explains their real-world adoption patterns:

- **C-band:** Rain-robust (≤ 10 dB attenuation even in extreme events), but spectrum congestion with terrestrial microwave, large antennas required, limited spectrum (500 MHz total)
- **Ku-band:** Compact terminals (0.6 m dish), moderate rain risk manageable with 10–15 dB link margin, most widely deployed commercial band
- **Ka-band:** Enormous spectrum (2.5 GHz+), enables HTS with 100–500 Gbps fleet capacity, but severe rain fade at high rainfall rates requires site diversity or deep link margins

7.3 Analytical vs. Simulation Comparison

The Monte Carlo BER estimates (Figure 2, circles) agree with the analytical BPSK curve (Eq. 3) within $\pm 5\%$ across all tested E_b/N_0 values. Statistical scatter is larger at high E_b/N_0 ($BER < 10^{-5}$) where fewer bit errors occur per simulation run — a known limitation of Monte Carlo at low error rates. Increasing the simulation from 200,000 to 10 million bits would reduce variance by $\sqrt{50} \approx 7\times$, at proportionally higher computation time. For the purposes of validating the theoretical model, 200,000 bits provides sufficient statistical confidence at the error rates of practical interest (10^{-3} to 10^{-5}).

7.4 Parameter Sensitivity

Sensitivity analysis of the link budget (Eq. 2) reveals the most impactful parameters:

5. FSPL (205 dB): A 1 dB change in slant range (e.g., off-axis ground station) maps directly to 1 dB change in C/N. This is the most critical and uncontrollable parameter.
6. G/T: Upgrading from a 2.4 m dish ($G/T = 20$ dB/K) to a 4.5 m dish ($G/T \approx 26$ dB/K) adds 6 dB of margin at the cost of terminal size and cost.
7. Rain attenuation: At Ka-band, a 30 mm/h rain event causes ≈ 25 dB fade, exceeding any practical non-diversity link margin. Site diversity separating ground stations by 20 km reduces joint probability of outage by $\sim 10\times$.

8. Conclusion

This project demonstrated how communication theory provides a rigorous and complete framework for analysing GEO satellite system performance. Four principal findings emerge:

7. Free-space path loss of 205 dB (Ku-band, 35,786 km) is the dominant link impairment, requiring 52 dBW EIRP satellites and 20 dB/K ground terminals to maintain C/N = 18.64 dB — directly derivable from Eq. 1 and Eq. 2.
8. BER analysis (Figure 2) confirms that BPSK and QPSK achieve identical error probability per Eq. 3–4 while QPSK doubles spectral efficiency, explaining its selection as the DVB-S2 baseline modulation. $BER = 10^{-6}$ requires $E^b/N_0 \geq 10.5$ dB.
9. Shannon's theorem (Eq. 7) reveals that a 36 MHz Ku-band transponder can theoretically deliver 223.6 Mbps, while practical DVB-S2 QPSK achieves ≈ 70 Mbps — a gap that higher-order modulations with LDPC coding continue to narrow.
10. Rain attenuation (Eq. 8–9) quantifies why Ka-band experiences 5–15 $\times$ greater fading than C-band for the same rainfall: $\alpha > 1$ in the power-law model causes super-linear growth with rainfall rate. This explains the industry's structural reliance on ACM and site diversity for Ka-band HTS systems.

Together, these results answer the central project question: communication theory — specifically the link budget equation, Shannon's capacity theorem, Q-function based modulation analysis, and ITU-R empirical models — completely explains GEO satellite performance limits and guides every major practical design decision.

9. Future Work

Several extensions would enhance the depth and realism of this analysis:

3. Channel Coding Performance: Simulating DVB-S2 LDPC+BCH codes would demonstrate post-FEC BER, quantifying the coding gain ($\sim 8\text{--}9$ dB for rate-1/2 LDPC) and closing the gap between Shannon's bound and practical operation.
4. Adaptive Coding and Modulation (ACM): Implementing a time-varying rain channel with real Istanbul rainfall statistics and simulating DVB-S2X ACM frame selection would demonstrate link availability improvements from $\sim 99.5\%$ (fixed QPSK) to $\sim 99.9\%$.
5. LEO/MEO Comparison: A quantitative comparison against Starlink-class LEO constellations (altitude ≈ 550 km, delay ≈ 2 ms, FSPL ≈ 170 dB) would contextualise the GEO latency/coverage trade-off with numerical precision.
6. Phased Array Beamforming: Modelling multi-beam HTS satellites with frequency reuse would extend the capacity analysis to fleet-level throughput (100–500 Gbps), relevant to next-generation systems such as Eutelsat KONNECT VHTS and Viasat-3.
7. Nonlinear HPA Modelling: Including Saleh-model AM/AM and AM/PM distortion curves for the satellite High-Power Amplifier would quantify spectral regrowth and adjacent-channel interference — a critical multi-carrier transponder design constraint.

10. References

- [1] J. G. Proakis and M. Salehi, Digital Communications, 5th ed. New York, NY, USA: McGraw-Hill, 2008.
- [2] S. Haykin, Communication Systems, 4th ed. Hoboken, NJ, USA: John Wiley & Sons, 2001.
- [3] ETSI, "Digital Video Broadcasting (DVB); Second generation framing structure, channel coding and modulation systems for Broadcasting, Interactive Services, News Gathering and other broadband satellite applications (DVB-S2)," EN 302 307, v1.2.1, Aug. 2009.
- [4] ITU-R, "Propagation data and prediction methods required for the design of Earth-space telecommunication systems," Recommendation ITU-R P.618-13, 2017.

- [5] ITU-R, "Specific attenuation model for rain for use in prediction methods," Recommendation ITU-R P.838-3, 2005.
- [6] ITU-R, "Characteristics of precipitation for propagation modelling," Recommendation ITU-R P.837-7, 2017.
- [7] T. Pratt, J. Allnutt, and C. Bostian, Satellite Communications, 2nd ed. Hoboken, NJ, USA: John Wiley & Sons, 2003.
- [8] G. Maral and M. Bousquet, Satellite Communications Systems, 5th ed. Chichester, UK: John Wiley & Sons, 2009.
- [9] Türksat A.Ş., "Türksat 4A Technical Characteristics," 2014.
- [10] MIT OpenCourseWare, "Principles of Digital Communication I," 6.450, 2006.
- [11] Python Software Foundation, NumPy v1.24, SciPy v1.11, Matplotlib v3.7, 2024.
- [12] Anthropic, "Claude AI Assistant," claude-sonnet-4-5, Anthropic PBC, 2025. [AI language model used for technical writing assistance]. Available: <https://claude.ai>
- [13] OpenAI, "ChatGPT AI Assistant," GPT-4o, OpenAI, 2025. [AI language model used for content verification and cross-referencing]. Available: <https://chatgpt.com>