

ikePon

ユーザーマニュアル / User Manual

v1.4.0

日本語マニュアルは次のページから始まります。
English manual starts on the second half of this document.

ikePon v1.4 ユーザーマニュアル

1. アプリケーション概要

ikePon は、イベント・ステージ現場向けのポン出しアプリです。

- 最大 8 バンク × 16 パッド (計 128 ファイル) の登録に対応
- 動画・静止画の表示に対応
- パッド個別の音量設定・ループ設定が可能
- 動画、BGM、SE で個別に音量調整が可能
- イベントで PA 側での音量調整がしやすいよう、BGM・動画と SE をそれぞれステレオ出力の L と R に割り振る PA セパレートモード搭載
- マウスでの操作、キーボードショートカットに加えて、MIDI コントローラーでの操作に対応

項目	仕様
対応 OS	Windows 10/11 x64
動作要件	.NET 9 デスクトップランタイム (ダウンロード)
開発環境	C# / WPF / .NET 9
オーディオエンジン	NAudio (WASAPI Shared モード)
映像エンジン	LibVLCSharp
プロジェクトファイル	.ikp (JSON 形式)
設定ファイル	%APPDATA%\ikePon\settings.json

2. 画面構成



メイン画面

画面は大きく **5つのエリア** に分かれています。

エリア	場所	内容
メニューバー	最上部	ファイル操作・編集・設定
グローバルエリア	メニュー直下	ALL CUT / ALL FADE / PAUSE / LOCK / FULL SCR / DISPLAY の 6 ボタンとインフォメーション表示
KEYPAD	左側	4×4 パッドボタン（1 バンクあたり 16 個）
BANK	右上	バンク A～H の切り替えボタン
MIXER	右下	MOVIE / BGM / SE / MASTER の 4 本フェーダー

3. メニュー操作

プロジェクトファイル（.ikp）に全パッドのファイル登録情報・バンク設定・ミキサー値を保存します。

操作	メニュー	ショートカット
新規プロジェクト	ファイル → 新規プロジェクト	Ctrl+N
プロジェクトを開く	ファイル → 開く…	Ctrl+O
上書き保存	ファイル → 上書き保存	Ctrl+S
名前を付けて保存	ファイル → 名前を付けて保存…	—
元に戻す	編集 → 元に戻す	Ctrl+Z
やり直し	編集 → やり直し	Ctrl+Y
全体設定を開く	設定 → 全体設定…	Ctrl+E

ヒント： `.ikp` ファイルをメインウィンドウにドラッグ&ドロップして開くことができます。また、拡張子 `ikp` を関連付けすることにより、`.ikp` ファイルのダブルクリックで `ikePon` が起動してプロジェクトを直接読み込みます。

4. パッドの設定と登録

4.1 ファイルの登録

音声・動画・静止画ファイルを **パッドにドラッグ&ドロップ** するか、パッドを **右クリック** → **詳細設定…** でファイルを選択します。

対応フォーマット：

種別	拡張子
音声	<code>.mp3</code> <code>.wav</code> <code>.flac</code> <code>.ogg</code> <code>.aac</code> <code>.m4a</code>
動画	<code>.mp4</code> <code>.mov</code> <code>.mkv</code> <code>.avi</code> <code>.wmv</code>
静止画	<code>.jpg</code> <code>.jpeg</code> <code>.png</code> <code>.bmp</code> <code>.gif</code> <code>.webp</code> <code>.tiff</code> <code>.tif</code>

動画・静止画ファイルを登録すると、カテゴリが自動的に **MOV** に設定されます。

4.2 パッド詳細設定ダイアログ

パッドを **右クリック** → **詳細設定…** で開きます。



パッド詳細設定

項目	説明
ファイル名（フルパス）	登録されているファイルのパス。別ファイルへの変更は D&D で可。✕ でクリア
カテゴリ	BGM / SE / MOV を選択
表示名	パッド上に表示する名前（空欄ならファイル名）
パッド背景色	8 色から選択（初期値：ダークグレー）
音量	このパッドのみの音量（100% = 標準、0～500%）
再生開始位置	途中から再生する場合の開始タイムスタンプ。通常時は 0.00.00
再生終了位置	途中で終了する場合のタイムスタンプ（空欄 = ファイル末尾）
ループ再生開始位置	ループ時の折り返し先（空欄 = 先頭から）
最後まで再生した後	そのまま終了 / 最終フレームで停止（MOV のみ） / ループ（SE 以外）
再生中タップ	フェードアウト / カットアウト / 一時停止・再開（SE は選択不可）


4.3 「最後まで再生した後」の動作

設定	動作
そのまま終了	再生終了後、スタンバイ画像に戻る（BGM は無音になる）
最終フレームで停止	最終フレームで静止して映像を表示し続ける（MOV のみ）。パッドは黄色点滅状態になる
ループ	ループ再生開始位置（または先頭）に戻って繰り返す（SE 以外で有効）

4.4 パッドの並べ替え (D&D 入れ替え)

アイドル状態のパッドをクリックしたままドラッグすると、別のパッドへ設定を丸ごと入れ替えることができます。LOCK ON 時は無効です。

4.5 パッドボタンの見方



左上の **カテゴリバッジ** はパッドのカテゴリを示します：

バッジ	カテゴリ
MOV	MOVIE（動画・静止画）
BGM	BGM（音楽・環境音など）
SE	SE（効果音：常に最初から再再生）

カテゴリバッジの右の ● は再生中タップ設定を示します（SE カテゴリ時は非表示）：

● の色	再生中タップ設定
赤 ●	カットアウト（即座に停止）
青 ●	フェードアウト（デフォルト）
緑 ●	一時停止・再開（SE は選択不可）

右上の **再生後動作バッジ** はパッドのタップで循環変更でき、再生終了後の動作を示します：

アイコン	再生後動作
■（グレー四角）	そのまま終了（デフォルト）
（縦 2 本線）	最終フレームで停止（MOV のみ有効）
⌂（ループ矢印）	ループ再生（SE 以外で有効）

パッド枠のカラー状態

状態	ボーダー色	意味
待機中 (Idle)	グレー	再生待機
再生中 (Playing)	黄色	再生中
フェードアウト中	黄色 → グレー補間	フェードアウト中
一時停止中	黄色 (じんわり点滅)	PAUSE 中、または MOV の最終フレームで停止中
行方不明 (Missing)	赤点滅	ファイルが見つからない

右クリックメニュー

待機中のパッド：

メニュー項目	動作
詳細設定…	パッド詳細設定ダイアログを開く
コピー	パッドの全設定をコピー
ペースト	コピーした設定を貼り付け
削除	パッドの設定を初期化

再生中のパッド、および MOV の「最終フレームで停止」中のパッド：

メニュー項目	動作
フェードアウト	フェードアウトして停止 (MOV 一時停止中・最終フレーム停止中は映像のみフェード)
カットアウト	即座に停止
一時停止／再開	一時停止・再開 (SE カテゴリ、最終フレーム停止中は無効)

5. 再生操作

5.1 キーボードでの操作

パッドキーのレイアウトは以下のとおりです (キーボード上の位置に対応)。

1	2	3	4	← 上段 (パッド 1~4)
Q	W	E	R	← 2段目 (パッド 5~8)
A	S	D	F	← 3段目 (パッド 9~12)
Z	X	C	V	← 下段 (パッド 13~16)

5.2 再生中タップの動作

パッド詳細設定の「再生中タップ」によって、再生中のパッドを再度押したときの挙動が変わります。

設定	MOVIE / BGM
フェードアウト（デフォルト）	フェードアウトして停止
カットアウト	即座に停止
一時停止・再開	一時停止 → 再押しで再開

SE カテゴリ： 再生中タップの設定は選択不可です。SE は再生中に再度タップすると常に最初から再再生されます。

同カテゴリの別パッドを再生した場合： 旧パッドを即座に停止して新パッドを再生します。

5.3 プログレスバーによるシーク

再生中にパッド下部の **プログレスバー** をクリックすると、クリックした位置に即ジャンプします。音声と映像は同時にシークされます。

また、パッド左下の **時間表示** をドラッグ・ホイール操作することでもシークできます。

5.4 インターロック

同一パッドへの連打（デフォルト 500 ms 以内）は無視されます（設定で変更可）。

6. グローバル操作

6.1 ALL CUT（赤ボタン / **ESC**）

全パッドを即座に一括停止します。ボーダーが黄色にフラッシュし、動画も同時に停止します。MOV の「最終フレームで停止」状態も解除されます。

6.2 ALL FADE（青ボタン / **Space**）

再生中の全パッドをフェードアウトで停止します。MOV の「最終フレームで停止」状態のパッドがある場合も有効で、映像をフェードアウトします（音声は無音のまま）。

6.3 PAUSE（緑ボタン / **Enter**）

MOVIE・BGM カテゴリの全再生中パッドを一時停止します（SE は対象外）。

- 一時停止中：PAUSEボタンのボーダーが黄色になり、一時停止中の各パッドがじんわり点滅
- もう一度押すと全パッドを再開（PAUSEボタンのボーダーが緑に戻る）
- 一時停止中に該当パッドの再生が終了した場合、PAUSE 状態は自動解除されます

6.4 LOCK（暗赤ボタン / **9 キー**）

操作ロックをトグルします。ON 時はボーダーが黄色に変わります。

LOCK ON 時に制限される操作：

- パッドのカテゴリ変更・ループ設定変更・D&D 入れ替え・ファイルの D&D 割り当て
- アイドル状態のパッドの右クリックメニュー（再生中・最終フレーム停止中は右クリック可）
- バンクの D&D 入れ替え・右クリックメニュー
- FULL SCR・DISPLAY の変更

ミキサー部（フェーダー・MU・メモリ）は LOCK ON 中も操作できます。

6.5 FULL SCR（暗緑ボタン / 0 キー）

動画ウィンドウの全画面/ウィンドウモードをトグルします。操作後 1 秒間グレースアウトし、連打を防止します。LOCK ON 時は無効です。

6.6 DISPLAY（暗緑ボタン / - キー）

動画ウィンドウを表示・非表示でトグルします。操作後 3 秒間グレースアウトし、連打を防止します。LOCK ON 時は無効です。

- DISPLAY が **OFF** の状態でも動画・静止画パッドをトリガーできます（音声は通常通り再生）。DISPLAY を ON にすると映像が即座に表示されます

7. バンク（BANK）の使い方

7.1 バンクの構成

8 つのバンク（A～H）がそれぞれ 16 個のパッドを持ちます。バンクキーのレイアウト：

7	8	← バンク A, E
U	I	← バンク B, F
J	K	← バンク C, G
M	,	← バンク D, H ※ カンマキー

現在選択中のバンクは **黄色のボーダー** でハイライトされます。

7.2 バンクの切り替え


- **再生中のパッドがない場合**：バンクキーを押すと即座に切り替わります
- **再生中のパッドがある場合（MOV の最終フレーム停止中を含む）**：切り替えを拒否し、インフォメーションに「再生中のバンク切り替えは出来ません」と表示されます

7.3 バンクの並べ替え（D&D 入れ替え）

バンクボタンをクリックしたままドラッグすると、別のバンクへ内容を丸ごと入れ替えることができます。再生中のパッドがある場合は入れ替えできません。LOCK ON 時は無効です。

7.4 バンク詳細設定

バンクボタンを **右クリック** → **詳細設定...** で開きます。



バンク詳細設定

項目	説明
表示名	バンクボタンに表示する名前
背景色	バンクボタンの背景色（8 色から選択）

7.5 バンク右クリックメニュー

メニュー項目	動作
詳細設定…	バンク詳細設定ダイアログを開く
コピー	バンク詳細設定およびバンク内 16 パッドの全設定をコピー
ペースト	バンク詳細設定およびバンク内 16 パッドの全設定を貼り付け
削除	バンク詳細設定およびバンク内の全パッドを初期化（確認あり）

8. ミキサー（MIXER）の使い方

4 本の縦フェーダーで各カテゴリの音量を調整します。

フェーダー	カテゴリ	ラベル色
MOVIE	動画・静止画	紫
BGM	BGM	青
SE	SE	緑
MASTER	全体	グレー

最終出力音量 = パッド音量 × カテゴリフェーダー × MASTER フェーダー

8.1 フェーダー操作

操作	動作
ドラッグ	フェーダー値を変更（0～127）
マウスホイール	1 ステップずつ変更
Shift + ホイール	10 ステップずつ変更

スケール：0 = 無音、100 = ±0 dB（標準）、127 = 最大（約 +2.1 dB）

8.2 メモリーボタン（M1～M3）

各フェーダーに M1～M3 の 3 つのメモリーボタンがあります。

操作	動作
クリック（未登録）	現在のフェーダー値を登録
クリック（登録済み）	記憶した値へフェード移動
右クリック	フェード移動 / 即座に移動 / 再登録 / 削除

8.3 MU ボタン（ミュート）

各フェーダー下の **MU** ボタンを押すとカテゴリをミュート（ボーダーが黄色で ON 状態を表示）します。

9. 動画ウィンドウ

9.1 ウィンドウ操作

- ウィンドウの位置・サイズはアプリ終了時に自動保存され、次回起動時に復元されます
- **ダブルクリック** でも全画面/ウィンドウモードのトグルができます

9.2 スタンバイ画像

映像が再生されていない間、設定したスタンバイ画像を表示できます（全体設定 → スタンバイ画像）。未設定の場合は黒画面になります。

9.3 黒画面検出

DISPLAY ON 中に、何らかのトラブルで映像もスタンバイ画像も表示されていない状態（黒画面）を検出した場合、インフォメーションエリアにオレンジ色の警告が表示されます。映像が復帰すると自動消去されます。

9.4 既知の動作

映像再生中にウィンドウの端をドラッグしてサイズを変更すると、一瞬白い背景が見えることがあります。映像エンジン（LibVLC）の D3D11 バッファ更新タイミングによるもので、仕様の範囲です。イベント本番中にウィンドウサイズを変更することは通常ないため、実用上の影響はありません。

10. スマートリロケート（自動ファイル再リンク）

プロジェクトファイル読み込み時に素材ファイルが見つからない（ドライブ変更やフォルダ移動など）場合、**自動的に素材を再検索して再リンク** します。

10.1 自動探索（フェーズ 1）

次の場所を順番に自動検索します（最大 30 秒・10 万ファイルで打ち切り）。

1. プロジェクトファイルと同じフォルダおよびその全サブフォルダ
2. 前回ファイルを読み込んだフォルダ

インフォメーションエリアにリアルタイムで進捗が表示されます：

行方不明のファイルを自動再検索中... (2/5本) フォルダ走査中...

自動探索が完了すると結果が表示されます：

3 本の行方不明ファイルを自動修復しました。

同名ファイルが複数見つかった場合、元のパスの **親フォルダ名** まで一致するものを優先します。

10.2 手動起点による一括解決（フェーズ 2）

自動探索で見つからないファイルがある場合、ダイアログが表示されます。**1 つのファイルを手動で指定** すると、そのフォルダを起点に残りのファイルも一括で再リンクを試みます。

10.3 行方不明ファイルの表示

最終的に再リンクできなかったパッドは **赤点滅のボーダー** と **[未リンク]** バッジ で表示され、再生は無効になります。

11. 全体設定ダイアログ（**Ctrl+E**）



設定

項目	説明	デフォルト
言語 / Language	表示言語の切り替え（日本語 / English）。変更は再起動後に反映	日本語
フェードアウト時間	パッド音声・映像のフェードアウト、フェーダーのフェード移動、ALL FADE のフェード秒数（共通）	2.0 秒
スタンバイ画像	動画ウィンドウの背景画像（D&D で設定、 ☐ でクリア）	なし（黒画面）
フェードイン時間	スタンバイ画像の表示フェードイン時間	1.0 秒
PAセパレートモード	ON にすると BGM+MOV → L チャンネル、SE → R チャンネルで出力	OFF
MIDI 入力デバイス	MIDIコントローラーを選択（詳細は「13. MIDIコントローラー機能」を参照）	なし（無効）
連打防止時間	同一パッドの連打を無視する時間	500 ms
WASAPI レイテンシ	オーディオバッファサイズ（変更後は再起動が必要）	30 ms
プリロード上限	プリロードする最大ファイル長（変更後は再起動が必要）	10 秒

注意： 言語・オーディオ設定（WASAPI レイテンシ・プリロード上限）を変更して OK を押すと、再起動確認が表示されます。☐ で即座にアプリを再起動します。

12. キーボードショートカット一覧

パッドキー

キー	パッド番号
1 2 3 4	1～4
Q W E R	5～8
A S D F	9～12
Z X C V	13～16

バンクキー

キー	バンク
7 / 8	A / E
U / I	B / F
J / K	C / G
M / ，	D / H

アクションキー

キー	動作
ESC	ALL CUT（全パッドを即座に停止）
Space	ALL FADE（全パッドをフェードアウト）
Enter	PAUSE ALL（MOVIE/BGM を一時停止・再開）
9	LOCK トグル
0	FULL SCR トグル
-	DISPLAY トグル
Y	各種確認で YES
N	各種確認で NO

メニューショートカット

キー	動作
Ctrl+N	新規プロジェクト
Ctrl+O	プロジェクトを開く
Ctrl+S	上書き保存
Ctrl+Z	元に戻す
Ctrl+Y	やり直し
Ctrl+E	全体設定ダイアログを開く

13. MIDIコントロール機能

MIDIコントローラー（ドラumpパッドやグリッドコントローラーなど）を接続することで、離れた場所からでもパッドのトリガーやミキサー操作をハンズフリーで行えます。舞台袖からのキュー出しや、大型コントローラーを使った演出操作に最適です。

13.1 MIDIデバイスの接続と設定

1. MIDIコントローラーを PC に USB 接続します
2. **Ctrl+E** で設定ダイアログを開きます
3. 「**MIDI 入カデバイス**」のプルダウンから使用するデバイスを選択します

設定は自動的に保存されます。次回起動時も同じデバイスが選択されます。

ヒント： MIDIコントローラーを抜き差しした場合は、設定ダイアログを一度閉じて開き直し、デバイスを再選択してください。

13.2 AKAI MPD226 での使用例

AKAI MPD226 のような 16 パッド (4×4) 型コントローラーは、ikePon との相性が特に良好です。本体の **PAD BANK (A/B/C)** を切り替えることで、パッドトリガー・グローバル操作・ミキサー操作をすべて手元でコントロールできます。



AKAI MPD226

PAD BANK	担当エリア	ノート番号
PAD BANK A	パッド 1～16 のトリガー	36～51
PAD BANK B	グローバル操作 & バンク切り替え	52～67
PAD BANK C	ミキサーのメモリ呼び出し & ミュート	68～83

13.3 ノートマッピング詳細

PAD BANK A : パッドトリガー (ノート 36～51)

MIDIコントローラーの 4×4 グリッドが、ikePon の 16 パッドに 1 対 1 で対応します。物理パッドの「**左下 = パッド 13**、**右上 = パッド 4**」という配置 (多くのドラムパッドコントローラーの標準レイアウト) です。

```
[48:パッド 1 ][49:パッド 2 ][50:パッド 3 ][51:パッド 4 ] ← 上段
[44:パッド 5 ][45:パッド 6 ][46:パッド 7 ][47:パッド 8 ]
[40:パッド 9 ][41:パッド10 ][42:パッド11 ][43:パッド12 ]
[36:パッド13 ][37:パッド14 ][38:パッド15 ][39:パッド16 ] ← 下段
```

パッドを叩くと、キーボードのパッドキーを押したときと同じ動作をします。ベロシティ（強弱）は音量に影響しません。

PAD BANK B : グローバル操作 & バンク切り替え（ノート 52～67）

[64:BANK A][65:BANK B][66:BANK C][67:BANK D] ← 上段（バンク A～D）
 [60:BANK E][61:BANK F][62:BANK G][63:BANK H] （バンク E～H）
 [56:LOCK][57:FULL SCR][58:DISPLAY][59:（予備）]
 [52:ALL CUT][53:ALL FADE][54:PAUSE][55:（予備）] ← 下段

ボタン	動作
ALL CUT（52）	全パッドを即座に停止
ALL FADE（53）	全パッドをフェードアウトで停止
PAUSE（54）	MOVIE/BGM を一時停止・再開
LOCK（56）	操作ロックのトグル
FULL SCR（57）	動画ウィンドウの全画面トグル
DISPLAY（58）	動画ウィンドウの表示／非表示トグル
BANK A～H（64～67, 60～63）	バンクを切り替え

PAD BANK C : ミキサー操作（ノート 68～83）

各列が MOVIE / BGM / SE / MASTER の各フェーダーに対応します。

[80:MOVIE M1][81:BGM M1][82:SE M1][83:MASTER M1] ← 上段（メモリ 1）
 [76:MOVIE M2][77:BGM M2][78:SE M2][79:MASTER M2] （メモリ 2）
 [72:MOVIE M3][73:BGM M3][74:SE M3][75:MASTER M3] （メモリ 3）
 [68:MOVIE MU][69:BGM MU][70:SE MU][71:MASTER MU] ← 下段（ミュート）

- **MU（ミュート）**：該当チャンネルをミュート ON/OFF します
- **M1～M3（メモリ）**：ミキサーの M1～M3 ボタンと同じ動作をします（値を登録、または呼び出し）

13.4 CC（コントロールチェンジ）によるフェーダー操作

外部コントローラーの物理フェーダーやノブを使って、ikePon のミキサーフェーダーをリアルタイムに操作できます。

CC 番号	対応フェーダー
CC 16	MOVIE フェーダー
CC 17	BGM フェーダー
CC 18	SE フェーダー
CC 19	MASTER フェーダー

CC の値（0～127）がそのままフェーダー値に反映されます（CC 値 100 = ±0 dB）。

MPD226 での設定例：MPD226 のフェーダー 1～4 を CC 16～19 にアサインすると、アプリのミキサーを物理フェーダーで直接操作できます。CC アサインの変更は MPD226 本体の Edit モードで行います。

14. 更新履歴

バージョン	日付	内容
v1.4.0	2026-07-14	映像ウィンドウのレターボックス・ピラーボックス白フラッシュを根本修正（VideoView 常時表示化）。ループ再生・音声同期の安定性向上。DISPLAY OFF 状態で動画パッドをトリガーした際の音声即時再生を修正。カットアウト実行時は連打防止（インターロック）の対象外に変更。DISPLAY は毎回 OFF 状態で起動するよう変更（前回状態の引き継ぎを廃止）。アプリ終了確認をポップアップからインフォメーションエリア表示に変更。二重起動防止機能を追加
v1.3.0	2026-07-11	初版リリース

ikePon v1.4 User Manual

1. Application Overview

ikePon is a sound/video cue player designed for events and stage productions.

- Supports up to 8 banks × 16 pads (128 files total)
- Supports video and still-image display
- Per-pad volume and loop settings
- Independent volume control for Movie, BGM, and SE
- PA Separate mode: routes BGM+MOV to the Left channel and SE to the Right channel for easy PA-side mixing
- Mouse, keyboard shortcuts, and MIDI controller input support

Item	Specification
OS	Windows 10/11 x64
Requirements	.NET 9 Desktop Runtime (Download)
Framework	C# / WPF / .NET 9
Audio Engine	NAudio (WASAPI Shared mode)
Video Engine	LibVLCSharp
Project File	.ikp (JSON format)
Settings File	%APPDATA%\ikePon\settings.json

2. Screen Layout



Main Screen

The screen is divided into **5 areas**:

Area	Location	Content
Menu Bar	Top	File, Edit, Settings menus
Global Area	Below menu	ALL CUT / ALL FADE / PAUSE / LOCK / FULL SCR / DISPLAY buttons + information display
KEYPAD	Left	4×4 pad buttons (16 pads per bank)
BANK	Upper right	Bank A–H selection buttons
MIXER	Lower right	MOVIE / BGM / SE / MASTER faders

3. Menu Operations

Project files (`.ikp`) store all pad file assignments, bank settings, and mixer values.

Action	Menu	Shortcut
New Project	File → New Project	Ctrl+N
Open Project	File → Open...	Ctrl+O
Save	File → Save	Ctrl+S
Save As	File → Save As...	—
Undo	Edit → Undo	Ctrl+Z
Redo	Edit → Redo	Ctrl+Y
Open Settings	Settings → Settings...	Ctrl+E

Tip: You can open `.ikp` files by dragging them onto the main window. You can also associate the `.ikp` extension with ikePon so that double-clicking an `.ikp` file launches the app and loads the project directly.

4. Pad Settings and Registration

4.1 Registering Files

Drag and drop an audio, video, or still-image file onto a pad, or right-click a pad and select **Details...** to choose a file.

Supported formats:

Type	Extensions
Audio	<code>.mp3</code> <code>.wav</code> <code>.flac</code> <code>.ogg</code> <code>.aac</code> <code>.m4a</code>
Video	<code>.mp4</code> <code>.mov</code> <code>.mkv</code> <code>.avi</code> <code>.wmv</code>
Image	<code>.jpg</code> <code>.jpeg</code> <code>.png</code> <code>.bmp</code> <code>.gif</code> <code>.webp</code> <code>.tiff</code> <code>.tif</code>

When a video or image file is registered, the category is automatically set to **MOV**.

4.2 Pad Details Dialog

Open by right-clicking a pad and selecting **Details...**



Pad Details

Item	Description
File Path	Path of the registered file. Drag & drop to change; ✕ to clear
Category	Select BGM / SE / MOV
Display Name	Name shown on the pad (blank = filename)
Pad Color	Choose from 8 colors (default: dark gray)
Volume	Per-pad volume (100% = standard, 0–500%)
Start Position	Timestamp to start playback mid-file (normally 0:00:00)
End Position	Timestamp to stop playback (blank = end of file)
Loop Start Position	Loop return point (blank = from beginning)
After Playback	Stop / Freeze Last Frame (MOV only) / Loop (non-SE)
Tap While Playing	Fade Out / Cut Out / Pause/Resume (SE not available)

4.3 After Playback Behavior

Setting	Behavior
Stop	Returns to standby image after playback ends
Freeze Last Frame	Freezes and holds the last video frame (MOV only). The pad shows yellow blinking
Loop	Loops from the loop start position (or beginning) (non-SE only)

4.4 Rearranging Pads (Drag & Drop Swap)

Click and drag an idle pad to swap its settings with another pad. Disabled when LOCK is ON.

4.5 Understanding the Pad Button

[BGM] [●]100%[■]

Display Name

00:00/ 01:23[1]

Progress bar

← Category / Tap mode / Volume / After-play

← Time / Key badge

← Click to seek

The **category badge** (top-left) indicates the pad category:

Badge	Category
MOV	MOVIE (video / still image)
BGM	BGM (music, ambient sound, etc.)
SE	SE (sound effect: always plays from the beginning)

The ● next to the category badge shows the tap behavior (hidden for SE):

● Color	Tap While Playing Setting
Red ●	Cut Out (instant stop)
Blue ●	Fade Out (default)
Green ●	Pause/Resume (SE not available)

The **after-play badge** (top-right) cycles through states when you tap the pad:

Icon	After Playback
■ (gray square)	Stop (default)
(two lines)	Freeze Last Frame (MOV only)
↺ (loop arrow)	Loop (non-SE only)

Pad Border States

State	Border Color	Meaning
Idle	Gray	Ready to play
Playing	Yellow	Currently playing
Fading Out	Yellow → Gray blend	Fading out
Paused / Frozen	Yellow (slow blink)	Paused, or MOV frozen on last frame
Missing	Red blink	File not found

Right-Click Menu

Idle pad:

Item	Action
Details...	Open pad details dialog
Copy	Copy all pad settings
Paste	Paste copied settings
Delete	Reset pad settings

Playing pad, or MOV pad frozen on last frame:

Item	Action
Fade Out	Fade out and stop (for paused/frozen MOV: fades video only, audio stays silent)
Cut Out	Stop immediately
Pause/Resume	Pause or resume (SE and frozen pads: disabled)

5. Playback Operations

5.1 Keyboard Operation

Pad key layout (matches keyboard position):

1	2	3	4	← Top row (pads 1–4)
Q	W	E	R	← 2nd row (pads 5–8)
A	S	D	F	← 3rd row (pads 9–12)
Z	X	C	V	← Bottom row (pads 13–16)

5.2 Tap While Playing

The **Tap While Playing** setting in pad details controls what happens when you press a playing pad again:

Setting	MOVIE / BGM
Fade Out (default)	Fade out and stop
Cut Out	Stop immediately
Pause/Resume	Pause → press again to resume

SE Category: Tap while playing cannot be set. Tapping an SE pad while it's playing always restarts from the beginning.

Playing a different pad in the same category: The previous pad is stopped immediately and the new pad begins.

5.3 Seeking with the Progress Bar

During playback, **click the progress bar** at the bottom of the pad to jump to that position. Audio and video seek simultaneously.

You can also **drag or scroll the time display** (bottom-left) to seek.

5.4 Interlock

Rapid re-triggering of the same pad (within 500 ms by default) is ignored. This duration can be changed in Settings.

6. Global Operations

6.1 ALL CUT (Red button / **ESC**)

Stops all pads instantly. The border flashes yellow and video is also stopped. MOV "Freeze Last Frame" state is also cleared.

6.2 ALL FADE (Blue button / **Space**)

Fades out all playing pads. Also works when a MOV pad is in "Freeze Last Frame" state — the video fades out while audio remains silent.

6.3 PAUSE (Green button / **Enter**)

Pauses all playing MOVIE and BGM pads (SE is not affected).

- While paused: the PAUSE button border turns yellow; each paused pad shows a slow yellow blink
- Press again to resume all pads (button border returns to green)
- If all paused pads stop playing naturally, PAUSE state is automatically cleared

6.4 LOCK (Dark-red button / **9**)

Toggles the operation lock. Border turns yellow when ON.

Actions restricted when LOCK is ON:

- Category change, loop setting change, D&D pad swap, D&D file assignment
- Right-click menu on idle pads (right-click is still available on playing or frozen pads)

- Bank D&D swap and right-click menu
- FULL SCR and DISPLAY changes

The Mixer (faders, MU, memory buttons) remains fully operational when LOCK is ON.

6.5 FULL SCR (Dark-green button /)

Toggles the video window between full-screen and windowed mode. Grays out for 1 second after use to prevent rapid toggling. Disabled when LOCK is ON.

6.6 DISPLAY (Dark-green button /)

Shows or hides the video window. Grays out for 3 seconds after use. Disabled when LOCK is ON.

- You can trigger video/image pads even when DISPLAY is **OFF** (audio plays normally). Turning DISPLAY ON will immediately show the video.

7. Banks

7.1 Bank Layout

8 banks (A–H), each with 16 pads. Bank key layout:

7	8	← Banks A, E
U	I	← Banks B, F
J	K	← Banks C, G
M	,	← Banks D, H (comma key)

The currently selected bank is highlighted with a **yellow border**.

7.2 Switching Banks


- **No pads playing:** Pressing a bank key switches immediately
- **Pads are playing (including MOV frozen on last frame):** Switch is blocked; “Cannot switch banks while playing” appears in the info area

7.3 Rearranging Banks (Drag & Drop Swap)

Click and drag a bank button to swap its entire contents with another bank. Disabled while any pad is playing. Disabled when LOCK is ON.

7.4 Bank Details Dialog

Right-click a bank button and select **Details...**



Bank Details

Item	Description
Display Name	Name shown on the bank button
Background Color	Button background color (choose from 8 colors)

7.5 Bank Right-Click Menu

Item	Action
Details...	Open bank details dialog
Copy	Copy bank settings and all 16 pad settings
Paste	Paste bank settings and all 16 pad settings
Delete	Reset bank settings and all pads (with confirmation)

8. Mixer

4 vertical faders for per-category volume control.

Fader	Category	Label Color
MOVIE	Video / Still image	Purple
BGM	BGM	Blue
SE	SE	Green
MASTER	Overall	Gray

Final output volume = Pad volume × Category fader × MASTER fader

8.1 Fader Operations

Action	Result
Drag	Change fader value (0–127)
Mouse wheel	Change by 1 step
Shift + wheel	Change by 10 steps

Scale: 0 = silent, 100 = ± 0 dB (standard), 127 = maximum ($\sim +2.1$ dB)

8.2 Memory Buttons (M1–M3)

Each fader has 3 memory buttons (M1–M3).

Action	Result
Click (empty)	Store current fader value
Click (stored)	Fade to stored value
Right-click	Fade / Instant move / Overwrite / Delete

8.3 MU Button (Mute)

Press the **MU** button below each fader to mute that category (yellow border indicates mute is ON).

9. Video Window

9.1 Window Operations

- Window position and size are saved automatically when the app closes, and restored on next launch
- Double-click** the video window to toggle full-screen / windowed mode

9.2 Standby Image

When no video is playing, you can display a standby image (Settings → Standby Image). If not set, the window shows a black screen.

9.3 Black Screen Detection

If the DISPLAY is ON but neither video nor a standby image is visible (black screen due to an error), an orange warning appears in the info area. It clears automatically when the display recovers.

9.4 Known Behaviors

When dragging the window border to resize while video is playing, a brief white background may flash. This is caused by the video engine (LibVLC) D3D11 buffer update timing and is within expected behavior. Since window resizing is not typically performed during a live event, this has no practical impact.

10. Smart Relocate (Auto Re-link)

When a project file is loaded and source files cannot be found (e.g., drive change or folder moved), the app **automatically searches and re-links** them.

10.1 Auto Search (Phase 1)

The following locations are searched in order (stops after 30 seconds or 100,000 files):

1. The same folder as the project file and all its subfolders
2. The last folder where a file was manually selected

Real-time progress is shown in the info area:

Searching for missing files... (2/5) Scanning folders...

When complete:

Auto-repaired 3 missing file(s).

If multiple files with the same name are found, the one whose **parent folder** matches the original path is preferred.

10.2 Manual Resolution (Phase 2)

If files remain missing after auto-search, a dialog prompts you to **manually specify one file**. The app then uses that folder as a starting point to attempt re-linking the rest.

10.3 Missing File Display

Pads that could not be re-linked are shown with a **red blinking border** and a **[Missing]** badge; playback is disabled.

11. Settings Dialog (`Ctrl+E`)



Settings

Item	Description	Default
Language	Switch display language (日本語 / English). Takes effect after restart	Japanese
Fade Out Duration	Fade duration for pad audio/video, fader moves, and ALL FADE (shared)	2.0 sec
Standby Image	Background image for the video window (drag & drop to set;  to clear)	None (black)
Fade In Duration	Fade-in time for the standby image	1.0 sec
PA Separate Mode	ON routes BGM+MOV → Left channel, SE → Right channel	OFF
MIDI Input Device	Select a MIDI controller (see section 13 for details)	None
Rapid Fire Prevention	Ignore interval for repeated presses on the same pad	500 ms
WASAPI Latency	Audio buffer size (restart required after change)	30 ms
Preload Limit	Maximum file length to preload (restart required after change)	10 sec

Note: If you change the Language or Audio settings (WASAPI Latency / Preload Limit) and press OK, a restart confirmation appears. Press  to restart the app immediately.

12. Keyboard Shortcuts

Pad Keys

Key	Pad Number
   	1–4
   	5–8
   	9–12
   	13–16

Bank Keys

Key	Bank
 / 	A / E
 / 	B / F
 / 	C / G
 / 	D / H

Action Keys

Key	Action
ESC	ALL CUT (stop all pads instantly)
Space	ALL FADE (fade out all pads)
Enter	PAUSE ALL (pause/resume MOVIE/BGM)
9	Toggle LOCK
0	Toggle FULL SCR
-	Toggle DISPLAY
Y	Confirm (YES)
N	Cancel (NO)

Menu Shortcuts

Key	Action
Ctrl+N	New Project
Ctrl+O	Open Project
Ctrl+S	Save
Ctrl+Z	Undo
Ctrl+Y	Redo
Ctrl+E	Open Settings dialog

13. MIDI Control

By connecting a MIDI controller (drum pad, grid controller, etc.), you can trigger pads and control the mixer hands-free from a distance. Ideal for stage-side cuing or large-controller setups.

13.1 Connecting and Configuring a MIDI Device

1. Connect your MIDI controller to the PC via USB
2. Open the Settings dialog with **Ctrl+E**
3. Select your device from the **MIDI Input Device** dropdown

The setting is saved automatically and restored on next launch.

Tip: If you disconnect and reconnect the MIDI controller, close and reopen the Settings dialog and reselect the device.

13.2 Example: AKAI MPD226

A 16-pad (4×4) controller like the AKAI MPD226 works exceptionally well with ikePon. By switching the **PAD BANK (A/B/C)** on the device, you can control pad triggers, global operations, and mixer

functions from a single controller.



AKAI MPD226

PAD BANK	Function	Note Numbers
PAD BANK A	Trigger pads 1–16	36–51
PAD BANK B	Global operations & bank selection	52–67
PAD BANK C	Mixer memory recall & mute	68–83

13.3 Note Mapping Details

PAD BANK A: Pad Triggers (Notes 36–51)

The 4×4 grid maps 1-to-1 to ikePon’s 16 pads. Layout: **bottom-left = pad 13**, **top-right = pad 4** (standard drum pad controller layout).

```
[48:Pad 1 ][49:Pad 2 ][50:Pad 3 ][51:Pad 4 ] ← Top row
[44:Pad 5 ][45:Pad 6 ][46:Pad 7 ][47:Pad 8 ]
[40:Pad 9 ][41:Pad10 ][42:Pad11 ][43:Pad12 ]
[36:Pad13 ][37:Pad14 ][38:Pad15 ][39:Pad16 ] ← Bottom row
```

Hitting a pad behaves the same as pressing the corresponding keyboard key. Velocity has no effect on volume.

PAD BANK B: Global Operations & Bank Selection (Notes 52–67)

```
[64:BANK A ][65:BANK B ][66:BANK C ][67:BANK D ] ← Top row (Banks A–D)
[60:BANK E ][61:BANK F ][62:BANK G ][63:BANK H ]      (Banks E–H)
[56:LOCK   ][57:FULL SCR][58:DISPLAY ][59:(spare) ]
[52:ALL CUT][53:ALL FADE][54:PAUSE   ][55:(spare) ] ← Bottom row
```

Button	Action
ALL CUT (52)	Stop all pads instantly
ALL FADE (53)	Fade out all pads
PAUSE (54)	Pause/resume MOVIE/BGM
LOCK (56)	Toggle operation lock
FULL SCR (57)	Toggle video window full-screen
DISPLAY (58)	Toggle video window visibility
BANK A–H (64–67, 60–63)	Switch bank

PAD BANK C: Mixer Operations (Notes 68–83)

Each column corresponds to MOVIE / BGM / SE / MASTER.

```
[80:MOVIE M1][81:BGM M1][82:SE M1][83:MASTER M1] ← Top row (Memory 1)
[76:MOVIE M2][77:BGM M2][78:SE M2][79:MASTER M2]      (Memory 2)
[72:MOVIE M3][73:BGM M3][74:SE M3][75:MASTER M3]      (Memory 3)
[68:MOVIE MU][69:BGM MU][70:SE MU][71:MASTER MU] ← Bottom row (Mute)
```

- **MU (Mute):** Toggle mute for that channel
- **M1–M3 (Memory):** Same as the M1–M3 buttons in the mixer (store or recall a value)

13.4 CC (Control Change) for Fader Control

Use physical faders or knobs on your controller to control ikePon's mixer faders in real time.

CC Number	Fader
CC 16	MOVIE fader
CC 17	BGM fader
CC 18	SE fader
CC 19	MASTER fader

CC values (0–127) map directly to fader values (CC 100 = ± 0 dB).

MPD226 example: Assign faders 1–4 to CC 16–19 on the MPD226 to control ikePon's mixer with physical faders. Use the MPD226's Edit mode to change CC assignments.

14. Change History

Version	Date	Notes
v1.4.0	2026-07-14	Fundamentally fixed letterbox/pillarbox white flash (VideoView always-on approach). Improved loop playback and audio sync stability. Fixed: audio now plays immediately when a video pad is triggered while DISPLAY is OFF. Cut Out actions are now exempt from interlock (rapid-fire prevention). DISPLAY always starts in OFF state (previous state no longer carried over). App-quit confirmation moved from popup dialog to info area. Added double-launch prevention.
v1.3.0	2026-07-11	Initial release