

ERICSSON

RAN Parameter Recommendation

LTE RAN

Copyright

© Ericsson AB 2019. All rights reserved. No part of this document may be reproduced in any form without the written permission of the copyright owner.

Doc Number:

Revision:

Disclaimer

The contents of this document are subject to revision without notice due to continued progress in methodology, design and manufacturing. Ericsson shall have no liability for any error or damage of any kind resulting from the use of this document.



215/006 51-LZA 701 6014

AB1

1. Purpose

This document describes the parameter

2. Scope

This document lists the activation recommendations, parameter names and preferred

3. Structure

This file contains the following sheets:

3.1. Heading

It contains document number and revision

3.2. General description (this sheet)

3.3. Recommended feature state

The following information is presented for

Feature name
Value Package
License Control MO DU radio Node
License Control MO Baseband-based Node
featureState Recommended value

3.4. LTE recommended parameters

The following information is presented for the parameters:

Feature name:

MOC Class
Parameter name
Recommended value
Comments

ters and features recommended for a robust and consistent network performance.

ommendation and gives information about the recommended parameter setting for LTE features for L19Q1 release and values.

:

on version, besides copyright and a disclaimer.

or the feature activation and deactivation:

The name of the feature.
The value package that the feature belongs to.
The licensed control MO used in the DU radio node.
The licensed control MO used in the baseband-based node.
The feature state recommendation, activated or deactivated. Recommendation is based on Live Network measurements. Ericsson on what features should be activated and what features should be deactivated to have a robust network performance.

The name of the feature where the parameter is used.

The MO class.
Attribute name as defined in the MOM.
The recommended value is based on Live Network measurements. It reflects suggestions and recommendations from Ericsson to achieve robust network performance in the most common scenarios. The character '*' means the parameter should be configured according to the network conditions.
The additional comments about the parameter configuration.

Feature Name	Feature Identity
256 QAM Downlink	FAJ 121 4422
Interference Rejection Combining	FAJ 121 0780
ICIC - Autonomous Resource Allocation	FAJ 121 1074
Automated Cell Capacity Estimation	FAJ 121 3031
Mobility Control at Poor Coverage	FAJ 121 3013
Antenna System Monitoring	FAJ 121 3040
Priority Paging	FAJ 121 3081
Downlink Frequency-Selective Scheduling	FAJ 121 2053
Uplink Frequency-Selective Scheduling	FAJ 121 1799
64-QAM Uplink	FAJ 121 4363
Dynamic Uplink Resource allocation	FAJ 121 4619
Data-Aware Uplink Scheduling	FAJ 121 4757
Enhanced PDCCH Link Adaptation	FAJ 121 3051
Prioritized SR scheduling	FAJ 121 4300
Inactivity-triggered PUCCH release at high load	FAJ 121 4302
PDCCH Power Boost	FAJ 121 3057
Adaptive RLC Poll-Retransmission	FAJ 121 4570
Uplink Scheduling Control for Out-of-Coverage UEs	FAJ 121 4524
Dynamic Random Access Backoff	FAJ 121 4299
Dynamic UE admission control	FAJ 121 4301
Release Inactive UE at High Load Handover	FAJ 121 4296
Variable SR and CQI Periodicity	FAJ 121 2056
Prioritization of VOLTE in Access Barring	FAJ 121 4329
Progressive Access Barring	FAJ 121 4746
Load-Based Access Barring	FAJ 121 3093
Dynamic Load Control	FAJ 121 3083
Quad Antenna Uplink Performance Package	FAJ 121 1744
Downlink Coordinated Multi-Point	FAJ 121 4223
Uplink Coordinated Multi-point Reception	FAJ 121 3043
Inter-Frequency Load Balancing	FAJ 121 3009
Best Neighbor Relations for Intra-LTE Load Management	FAJ 121 3028
Coverage-Adapted Load Management	FAJ 121 3077
UE Throughput aware IFLB	FAJ 121 4219
Limited Uplink-Aware IFLB	FAJ 121 4406
IFLB Activation Threshold	FAJ 121 3058
Dynamic PUCCH	FAJ 121 4377
UE Level Oscillating Handover Minimization	FAJ 121 1885
Automated RACH root sequence allocation	FAJ 121 2026
Automated Mobility Optimization	FAJ 121 3035
Automated Neighbor Relations	FAJ 121 0497
PCI Conflict Reporting	FAJ 121 1898
Overlaid Cell Detection	FAJ 121 3078
Ericsson Lean Carrier	FAJ 121 4471

Uplink-Triggered Inter-Frequency Mobility	FAJ 121 1797
Carrier Aggregation	FAJ 121 3046
3CC DL Carrier Aggregation Extension	FAJ 121 3084
Carrier Aggregation FDD-TDD	FAJ 121 4252
Supplemental Downlink for Carrier Aggregation	FAJ 121 3068
Uplink Carrier Aggregation	FAJ 121 4425
Dynamic SCell Selection for Carrier Aggregation	FAJ 121 3063
4CC DL Carrier Aggregation	FAJ 121 4466
5CC DL Carrier Aggregation Extension	FAJ 121 4467
Carrier Aggregation-Aware IFLB	FAJ 121 3075
Configurable SCell Priority	FAJ 121 4701
Inter-eNodeB Carrier Aggregation	FAJ 121 4469
Elastic RAN	FAJ 121 4608
4x2 Quad Antenna Downlink Performance Package	FAJ 121 3041
4x4 Quad Antenna Downlink Performance Package	FAJ 121 3076
Minimum Rate Proportional Fair Scheduler	FAJ 121 0920
Relative Priority Scheduling	FAJ 121 2037
Advanced Differentiation for resource fair scheduling	FAJ 121 4415
Differentiated Admission Control	FAJ 121 1787
Dynamic GBR Admission Control	FAJ 121 1748
Multi-Target RRC Connection Re-establishment	FAJ 121 3023
Service-Specific HARQ	FAJ 121 4645
Inter-RAT Offload to WCDMA	FAJ 121 3048
Best Neighbor Relations for WCDMA IRAT Offload	FAJ 121 3065
Load-based distribution at release	FAJ 121 4338
Service Specific Load Management	FAJ 121 3047
Admission Control	FAJ 121 1857
Inter-Frequency Offload	FAJ 121 3061
Admission Triggered Offload	FAJ 121 3100
Coverage-Triggered Inter-Frequency Session Continuity	FAJ 121 0797
Coverage-Triggered WCDMA Session Continuity	FAJ 121 3004
Coverage-Triggered GERAN Session Continuity	FAJ 121 0495
PLMN-Specific Access Barring	FAJ 121 4916
QoS-Aware Scheduler	FAJ 121 0859
Instant uplink access with skip tx uplink padding	FAJ 121 4831
ASGH-Supported InstantUplinkAccess	FAJ 121 4960

Feature Introduced in	Value Package Name
L16A GA	LTE Base Package
L11B GA	LTE Base Package
L14B CP1	LTE Base Package
L14A IP5	LTE Base Package
L13B GA	LTE Base Package
L14B IP4	LTE Base Package
L14B IP4	LTE Base Package
L13A GA	LTE Base Package
L12A ICP4	LTE Base Package
L16A.4	LTE Base Package
L17.Q1 GA	LTE Base Package
L17.Q3 GA	LTE Base Package
L13B IP4	High Load Handling
L15B IP3	High Load Handling
L15B IP12, L16A.4	High Load Handling
L14A GA	High Load Handling
L16A.2	High Load Handling
L16A.2	High Load Handling
L15B IP8	High Load Handling
L16B GA	High Load Handling
L15B CP1-1	High Load Handling
L15B GA	High Load Handling
L16A GA	High Load Handling
L17.Q3 GA	High Load Handling
L14B IP11	High Load Handling
L14B IP5	High Load Handling
L14B GA	4-Way Receiver Diversity
L15B IP8	CoMP
N/A	CoMP
N/A	Multi-carrier Load Management
Restricted	Multi-carrier Load Management
L14B IP2	Multi-carrier Load Management
L15B IP2	Multi-carrier Load Management
L17A GA	Multi-carrier Load Management
L14A IP3	Multi-carrier Load Management
L16B.5	Uplink Spectrum Adaptations
L12A GA	Self-Organizing Networks
L15B GA	Self-Organizing Networks
N/A	Self-Organizing Networks
L16B GA	Self-Organizing Networks
L12B GA	Self-Organizing Networks
L16B GA	Self-Organizing Networks
L17A GA	Ericsson Lean Carrier

L17.Q4.C2	LTE Base Package
L14A IP3	Carrier Aggregation
L14B IP4	Carrier Aggregation
L15B IP3	Carrier Aggregation
L14A IP11	Carrier Aggregation
L16B.1	Carrier Aggregation
L18.Q3.6	Carrier Aggregation
N/A	Carrier Aggregation
N/A	Carrier Aggregation
L14B IP4	Advanced Carrier Aggregation
L17A GA, L17.Q1.1	Advanced Carrier Aggregation
L17.Q1.6-4 L17.Q2.5-2	Advanced Carrier Aggregation
N/A	Elastic RAN
L14A IP3	4x2 Downlink MIMO
N/A	4x4 Downlink MIMO
L12A GA	Differentiated Mobile Broadband
L13A IP6	Differentiated Mobile Broadband
L15B IP8	Differentiated Mobile Broadband
L14A IP10	Differentiated Mobile Broadband
L15B IP1	VoLTE Performance
L17.Q3.C1, L17.Q4.2	VoLTE Performance
L17.Q3.5	VoLTE Performance
L13B IP8	LTE Offload to WCDMA
L16B.10	LTE Offload to WCDMA
L17.Q3 GA	Multi-Carrier Load Management
L14A GA	Service-Based Mobility
L11A GA	LTE Base Package
L14A GA	Inter-Vendor Load Management
L16A.5	Service-Based Mobility
L12B CP1	LTE Base Package
L14B GA (For TDD only)	LTE Base Package
L11B ICP4	LTE Base Package
L18.Q4 GA	Mission Critical High Load Handling
L16B GA	LTE Base Package
	Latency Reduction
	Latency Reduction

[illegible]

FAJ 801 0400
FAJ 801 0405
FAJ 801 0405
FAJ 801 0405
FAJ 801 0405
FAJ 801 0405
FAJ 801 0405
FAJ 801 0405
FAJ 801 0405
FAJ 801 0564
FAJ 801 0564
FAJ 801 0564
FAJ 801 0568
FAJ 801 0401
FAJ 801 0560
FAJ 801 0409
FAJ 801 0409
FAJ 801 0409
FAJ 801 0409
FAJ 801 0444
FAJ 801 0444
FAJ 801 0444
FAJ 801 0421
FAJ 801 0421
FAJ 801 0427
FAJ 801 0433
FAJ 801 0400
FAJ 801 0416
FAJ 801 0433
FAJ 801 0400
FAJ 801 0400
FAJ 801 0400
FAJ 801 1016
FAJ 801 0400
FAJ 801 1012
FAJ 801 1012

License Control MO DU radio Node
OptionalFeatureLicense=DI256Qam
OptionalFeatureLicense=Irc
OptionalFeatureLicense=AutoCellCapEstFunction
OptionalFeatureLicense=MobCtrlAtPoorCov
OptionalFeatureLicense=AntSystemMonitoring
OptionalFeatureLicense=PriorityPaging
OptionalFeatureLicense=DIFss
OptionalFeatureLicense=UIFss
OptionalFeatureLicense=UI64Qam
OptionalFeatureLicense=UIDynamicResourceAllocation
OptionalFeatureLicense=DataAwareUplinkScheduling
OptionalFeatureLicense=EnhancedPdcchLa
OptionalFeatureLicense=PrioritizedSrScheduling
OptionalFeatureLicense=InactTrigPUCCHRelAtHighLoad
OptionalFeatureLicense=PdcchPowerBoost
OptionalFeatureLicense=AdaptiveRLCPollRetransmission
OptionalFeatureLicense=UISchedContlForOocUes
OptionalFeatureLicense=DynamicRABackoff
OptionalFeatureLicense=DynamicUeAdmCtrl
OptionalFeatureLicense=RelInactiveUeAtHighLoadHo
OptionalFeatureLicense=VarSrCqiPeriodicity
OptionalFeatureLicense=PrioOfVolteInAccessBarring
OptionalFeatureLicense=ProgressiveAccessBarring
OptionalFeatureLicense=LoadBasedAccessBarring
OptionalFeatureLicense=DynamicLoadControl
OptionalFeatureLicense=QuadAntUIPerfPkg
OptionalFeatureLicense=DIComp
OptionalFeatureLicense=UIComp
OptionalFeatureLicense=InterFrequencyLoadBalancing
OptionalFeatureLicense=BnrIntraLteLM
OptionalFeatureLicense=CoverageAdaptedLm
OptionalFeatureLicense=UeThroughputAwareIfb
OptionalFeatureLicense=LimitedUplinkAwareIFLB
OptionalFeatureLicense=IFLBActivationThreshold
OptionalFeatureLicense=DynamicPucch
OptionalFeatureLicense=HoOscCtrlUE
OptionalFeatureLicense=AutoRachRsAlloc
OptionalFeatureLicense=AutomatedMobilityOptimization
OptionalFeatureLicense=Anr
OptionalFeatureLicense=Pci
OptionalFeatureLicense=OverlaidCellDetection
OptionalFeatureLicense=EricssonLeanCarrier

OptionalFeatureLicense=UITrigInterFreqMob
OptionalFeatureLicense=CarrierAggregation
OptionalFeatureLicense=ThreeDlCarrierAggregation
OptionalFeatureLicense=CarrierAggregationFddTdd
OptionalFeatureLicense=SUPPLEMENTARYDLONLYCELL
OptionalFeatureLicense=UplinkCarrierAggregation
OptionalFeatureLicense=DynamicScellSelection
OptionalFeatureLicense=FourDlCarrierAggregation
OptionalFeatureLicense=FiveDlCarrierAggregation
OptionalFeatureLicense=CarrierAggregationAwareIFLB
OptionalFeatureLicense=ConfigurableScellPrio
OptionalFeatureLicense=InterENBCarrierAggregation
OptionalFeatureLicense=ElasticRAN
OptionalFeatureLicense=QuadAntDlPerfPkg
OptionalFeatureLicense=QuadAntDlPerfPkg4x4
OptionalFeatureLicense=Pfs
OptionalFeatureLicense=Rps
OptionalFeatureLicense=AdvancedDiffForResourceFairSch
OptionalFeatureLicense=DifferentiatedAdmissionControl
OptionalFeatureLicense=DynamicGbrAdmCtrl
OptionalFeatureLicense=MultiTargetRrcConnReest
OptionalFeatureLicense=ServiceSpecificHARQ
OptionalFeatureLicense=InterRatOffloadToUtran
OptionalFeatureLicense=BnrIratOffload
OptionalFeatureLicense=LoadBasedDistributionAtRelease
OptionalFeatureLicense=ServiceSpecificLoadMgmt
OptionalFeatureLicense=InterFrequencyOffload
OptionalFeatureLicense=AdmissionTriggeredOffload
OptionalFeatureLicense=InterFreqSessionContinuity
OptionalFeatureLicense=WcdmaSessionContinuity
OptionalFeatureLicense=GsmSessionContinuity
OptionalFeatureLicense=PLMNSpecificAccessBarring
OptionalFeatureLicense=QoS Aware Scheduler
OptionalFeatureLicense=InstantUplinkAccess
OptionalFeatureLicense=ASGHSupportedIUA

License Control MO Baseband-based Node	featureState Recommended value
FeatureState=CXC4011969	ACTIVATED
FeatureState=CXC4010319	ACTIVATED
	ACTIVATED
FeatureState=CXC4011373	ACTIVATED
FeatureState=CXC4011345	ACTIVATED
FeatureState=CXC4011422	ACTIVATED
FeatureState=CXC4011711	ACTIVATED
FeatureState=CXC4011255	DEACTIVATED
FeatureState=CXC4011074	DEACTIVATED
FeatureState=CXC4011946	ACTIVATED
FeatureState=CXC4012036	ACTIVATED
FeatureState=CXC4012129	ACTIVATED
FeatureState=CXC4011482	ACTIVATED
FeatureState=CXC4011938	ACTIVATED
FeatureState=CXC4011941	DEACTIVATED
FeatureState=CXC4011515	ACTIVATED
FeatureState=CXC4012018	ACTIVATED
FeatureState=CXC4012003	ACTIVATED
FeatureState=CXC4011937	ACTIVATED
FeatureState=CXC4011940	ACTIVATED
FeatureState=CXC4011939	ACTIVATED
FeatureState=CXC4011258	ACTIVATED
FeatureState=CXC4011942	ACTIVATED
FeatureState=CXC4012120	ACTIVATED
FeatureState=CXC4011807	ACTIVATED
FeatureState=CXC4011713	DEACTIVATED
FeatureState=CXC4011056	ACTIVATED
FeatureState=CXC4011913	ACTIVATED
FeatureState=CXC4011444	ACTIVATED
FeatureState=CXC4011319	ACTIVATED
FeatureState=CXC4011370	ACTIVATED
FeatureState=CXC4011698	ACTIVATED
FeatureState=CXC4011911	ACTIVATED
FeatureState=CXC4011966	ACTIVATED
FeatureState=CXC4011554	ACTIVATED
FeatureState=CXC4011955	ACTIVATED
FeatureState=CXC4011157	ACTIVATED
FeatureState=CXC4011246	ACTIVATED
FeatureState=CXC4011376	ACTIVATED
FeatureState=CXC4010620	ACTIVATED
FeatureState=CXC4011183	ACTIVATED
FeatureState=CXC4011699	DEACTIVATED
FeatureState=CXC4011984	ACTIVATED

FeatureState=CXC4011072	DEACTIVATED
FeatureState=CXC4011476	ACTIVATED
FeatureState=CXC4011714	ACTIVATED
FeatureState=CXC4011922	ACTIVATED
FeatureState=CXC4011567	ACTIVATED
FeatureState=CXC4011973	ACTIVATED
FeatureState=CXC4011559	ACTIVATED
FeatureState=CXC4011980	ACTIVATED
FeatureState=CXC4011981	ACTIVATED
FeatureState=CXC4011666	ACTIVATED
FeatureState=CXC4012097	DEACTIVATED
FeatureState=CXC4011983	ACTIVATED
FeatureState=CXC4012034	DEACTIVATED
FeatureState=CXC4011427	ACTIVATED
FeatureState=CXC4011667	ACTIVATED
FeatureState=CXC4011033	ACTIVATED
FeatureState=CXC4011251	ACTIVATED
FeatureState=CXC4011967	ACTIVATED
FeatureState=CXC4011062	ACTIVATED
FeatureState=CXC4011060	ACTIVATED
FeatureState=CXC4011366	ACTIVATED
FeatureState=CXC4012070	ACTIVATED
FeatureState=CXC4011478	DEACTIVATED
FeatureState=CXC4010512	DEACTIVATED
FeatureState=CXC4011944	ACTIVATED
FeatureState=CXC4011477	ACTIVATED
	ACTIVATED
FeatureState=CXC4011557	DEACTIVATED
FeatureState=CXC4011814	DEACTIVATED
FeatureState=CXC4010770	ACTIVATED
FeatureState=CXC4010616	ACTIVATED
FeatureState=CXC4010618	ACTIVATED
FeatureState=CXC4012278	DEACTIVATED
FeatureState=CXC4010959	ACTIVATED
FeatureState=CXC4012209	DEACTIVATED
FeatureState=CXC4012313	DEACTIVATED

[illegible]

The Uplink-Triggered Inter-Frequency Mobility feature can be used in scenarios where there are uplink problems.

The Configurable SCell Priority feature is recommended as deactivated because specific tuning is required for each eNodeB to use the priority differentiation, which is not intended for this parameter recommendation.

The Elastic RAN feature is an advanced solution for scenarios that require fast coordination. The Elastic RAN feature has special requirements regarding the transport network architecture.

The PLMN-Specific Access Barring feature allows to prioritize barring of different PLMNs in high load scenarios.

NODE TYPE: Baseband

PRODUCT: CXP2020013/1 R72G03

DELIVERY PACKAGES: 19.Q2/2.4

Model	MO Class Name	Parameter Name
ENodeBFunction	AdmissionControl	admNrRrcDifferentiationThr
ENodeBFunction	AdmissionControl	arpBasedPreEmptionState
ENodeBFunction	AdmissionControl	dlAdmDifferentiationThr
ENodeBFunction	AdmissionControl	dlAdmOverloadThr
ENodeBFunction	AdmissionControl	dlTransNwBandwidth
ENodeBFunction	AdmissionControl	nrOfPaConnReservationsPerCell
ENodeBFunction	AdmissionControl	nrOfRbReservationsPerPaConn
ENodeBFunction	AdmissionControl	paArpOverride
ENodeBFunction	AdmissionControl	resourceReservationForPAMax

ENodeBFunction	AdmissionControl	ulAdmDifferentiationThr
ENodeBFunction	AdmissionControl	ulAdmOverloadThr
ENodeBFunction	AdmissionControl	ulTransNwBandwidth
ENodeBFunction	AdmissionControl	zzzTemp20
ENodeBFunction	AdmissionControl	zzzTemp21
ENodeBFunction	AmoFunction	amoAllowedInterVendor
ENodeBFunction	AnrFunction	cellRelHoAttRateThreshold
ENodeBFunction	AnrFunction	maxNoPciReportsEvent
ENodeBFunction	AnrFunction	maxTimeEventBasedPciConf
ENodeBFunction	AnrFunction	pciConflictDetectionEcgiMeas

ENodeBFunction	AnrFunction	pciConflictMobilityEcgiMeas
ENodeBFunction	AnrFunction	perEcgiMeasPlmnWhiteList
ENodeBFunction	AnrFunction	plmnWhiteListEnabled
ENodeBFunction	AnrFunction	probCellDetectLowHoSuccThres
ENodeBFunction	AnrFunction	probCellDetectLowHoSuccTime
ENodeBFunction	AnrFunction	probCellDetectMedHoSuccThres
ENodeBFunction	AnrFunction	probCellDetectMedHoSuccTime
ENodeBFunction	AnrFunction	problematicCellPolicy
ENodeBFunction	AnrFunction	removeNcellTime

ENodeBFunction	AnrFunction	removeNenbTime
ENodeBFunction	AnrFunction	removeNrelTime
ENodeBFunction	AnrFunctionEUTran	anrEutranInterFMeasReportDecr
ENodeBFunction	AnrFunctionEUTran	anrEutranInterFMeasReportIncr
ENodeBFunction	AnrFunctionEUTran	anrEutranInterFMeasReportMax
ENodeBFunction	AnrFunctionEUTran	anrEutranInterFMeasReportMin
ENodeBFunction	AnrFunctionEUTran	anrInterFreqState
ENodeBFunction	AnrFunctionEUTran	anrIntraFreqState
ENodeBFunction	AnrFunctionEUTran	anrUesEUTraIntraFDecr
ENodeBFunction	AnrFunctionEUTran	anrUesEUTraIntraFIncrAnr
ENodeBFunction	AnrFunctionEUTran	anrUesEUTraIntraFIncrHo
ENodeBFunction	AnrFunctionEUTran	anrUesEUTraIntraFMax

ENodeBFunction	AnrFunctionEUTran	anrUesEUtraIntraFMin
ENodeBFunction	AnrFunctionEUTran	anrUesThreshInterFDecr
ENodeBFunction	AnrFunctionEUTran	anrUesThreshInterFIncrAnr
ENodeBFunction	AnrFunctionEUTran	anrUesThreshInterFIncrHo
ENodeBFunction	AnrFunctionEUTran	anrUesThreshInterFMax
ENodeBFunction	AnrFunctionEUTran	anrUesThreshInterFMin
ENodeBFunction	AnrFunctionEUTran	cellAddRsrpThresholdEutran
ENodeBFunction	AnrFunctionEUTran	cellAddRsrqThresholdEutran
ENodeBFunction	AnrFunctionEUTran	hoAllowedEutranPolicy
ENodeBFunction	AnrFunctionEUTran	x2SetupPolicy
ENodeBFunction	AnrFunctionGeran	anrGeranMeasReportDecr
ENodeBFunction	AnrFunctionGeran	anrGeranMeasReportIncr
ENodeBFunction	AnrFunctionGeran	anrGeranMeasReportMax
ENodeBFunction	AnrFunctionGeran	anrGeranMeasReportMin

ENodeBFunction	AnrFunctionGeran	anrGeranMeasReportRacIncr
----------------	------------------	---------------------------

ENodeBFunction	AnrFunctionGeran	anrStateGsm
----------------	------------------	-------------

ENodeBFunction	AnrFunctionUtran	anrStateUtran
----------------	------------------	---------------

ENodeBFunction	AnrFunctionUtran	anrUtranMeasReportAcIncr
----------------	------------------	--------------------------

ENodeBFunction	AnrFunctionUtran	anrUtranMeasReportDecr
----------------	------------------	------------------------

ENodeBFunction	AnrFunctionUtran	anrUtranMeasReportIncr
----------------	------------------	------------------------

ENodeBFunction	AnrFunctionUtran	anrUtranMeasReportMax
----------------	------------------	-----------------------

ENodeBFunction	AnrFunctionUtran	anrUtranMeasReportMin
----------------	------------------	-----------------------

ENodeBFunction	AnrFunctionUtran	cellAddEcNoThresholdUtranDelta
----------------	------------------	--------------------------------

ENodeBFunction	AnrFunctionUtran	cellAddRscpThresholdUtranDelta
----------------	------------------	--------------------------------

ENodeBFunction	AnrPciConflictDrxProfile	anrPciConflictDrxInactivityTimer
----------------	--------------------------	----------------------------------

ENodeBFunction	AnrPciConflictDrxProfile	anrPciConflictLongDrxCycle
----------------	--------------------------	----------------------------

ENodeBFunction	AnrPciConflictDrxProfile	anrPciConflictOnDurationTimer
----------------	--------------------------	-------------------------------

ENodeBFunction	CarrierAggregationFunction	caPreemptionThreshold
----------------	----------------------------	-----------------------

ENodeBFunction	CarrierAggregationFunction	caPreference
----------------	----------------------------	--------------

ENodeBFunction	CarrierAggregationFunction	caRateAdjustCoeff
----------------	----------------------------	-------------------

ENodeBFunction	CarrierAggregationFunction	caUsageLimit
----------------	----------------------------	--------------

ENodeBFunction	CarrierAggregationFunction	dynamicSCellSelectionMethod
----------------	----------------------------	-----------------------------

ENodeBFunction	CarrierAggregationFunction	enhancedSelectionOfMimoAndCa
----------------	----------------------------	------------------------------

ENodeBFunction	CarrierAggregationFunction	fourLayerMimoPreferred
----------------	----------------------------	------------------------

ENodeBFunction	CarrierAggregationFunction	pdccchEnhancedLaForVolte
ENodeBFunction	CarrierAggregationFunction	sCellActDeactDataThres
ENodeBFunction	CarrierAggregationFunction	sCellActDeactDataThresHyst
ENodeBFunction	CarrierAggregationFunction	sCellActDeactUIDataThresh
ENodeBFunction	CarrierAggregationFunction	sCellActDeactUIDataThreshHyst
ENodeBFunction	CarrierAggregationFunction	sCellActProhibitTimer
ENodeBFunction	CarrierAggregationFunction	sCellDeactDelayTimer

ENodeBFunction	CarrierAggregationFunction	sCellDeactOutOfCoverageTimer
----------------	----------------------------	------------------------------

ENodeBFunction	CarrierAggregationFunction	sCellDeactProhibitTimer
----------------	----------------------------	-------------------------

ENodeBFunction	CarrierAggregationFunction	sCellScheduleSinrThres
----------------	----------------------------	------------------------

ENodeBFunction	CarrierAggregationFunction	sCellSelectionMode
----------------	----------------------------	--------------------

ENodeBFunction	CarrierAggregationFunction	waitForAdditionalSCellOpportunity
----------------	----------------------------	-----------------------------------

ENodeBFunction	CarrierAggregationFunction	waitForBetterSCellRep
----------------	----------------------------	-----------------------

ENodeBFunction	CarrierAggregationFunction	waitForCaOpportunity
----------------	----------------------------	----------------------

ENodeBFunction	DataRadioBearer	dIMaxRetxThreshold
----------------	-----------------	--------------------

ENodeBFunction	DataRadioBearer	tPollRetransmitDI
----------------	-----------------	-------------------

ENodeBFunction	DataRadioBearer	tPollRetransmitUl
ENodeBFunction	DataRadioBearer	ulMaxRetxThreshold
ENodeBFunction	ENodeBFunction	dIMaxWaitingTimeGlobal
ENodeBFunction	ENodeBFunction	enabledUlTrigMeas
ENodeBFunction	ENodeBFunction	interEnbCaTunnelDscp
ENodeBFunction	ENodeBFunction	measuringEcgiWithAgActive
ENodeBFunction	ENodeBFunction	mtRreWithoutNeighborActive
ENodeBFunction	ENodeBFunction	releaseInactiveUesInactTime
ENodeBFunction	ENodeBFunction	releaseInactiveUesMpLoadLevel
ENodeBFunction	ENodeBFunction	rrcConnReestActive
ENodeBFunction	ENodeBFunction	tRelocOverallValue
ENodeBFunction	ENodeBFunction	tS1HoCancelTimer
ENodeBFunction	ENodeBFunction	timeAndPhaseSynchAlignment

ENodeBFunction	EUtranCellFDD	acBarringPresence.acBarringPriorityMmtelV ideo
ENodeBFunction	EUtranCellFDD	acBarringPresence.acBarringPriorityMmtelV oice
ENodeBFunction	EUtranCellFDD	acBarringPresence.acBarringPriorityMoData
ENodeBFunction	EUtranCellFDD	acBarringPresence.acBarringPriorityMoSign aling
ENodeBFunction	EUtranCellFDD	acBarringSkipForMmtelVideo
ENodeBFunction	EUtranCellFDD	acBarringSkipForMmtelVoice
ENodeBFunction	EUtranCellFDD	acBarringSkipForSms
ENodeBFunction	EUtranCellFDD	allocThrPucchFormat1
ENodeBFunction	EUtranCellFDD	allocTimerPucchFormat1
ENodeBFunction	EUtranCellFDD	alpha
ENodeBFunction	EUtranCellFDD	bsrThreshold
ENodeBFunction	EUtranCellFDD	caPrioThreshold

ENodeBFunction	EUtranCellFDD	cceDynUeAdmCtrlOverloadThr
ENodeBFunction	EUtranCellFDD	cceDynUeAdmCtrlRetDiffThr
ENodeBFunction	EUtranCellFDD	cellBarred
ENodeBFunction	EUtranCellFDD	cellCapMaxCellSubCap
ENodeBFunction	EUtranCellFDD	cellCapMinCellSubCap
ENodeBFunction	EUtranCellFDD	cellCapMinMaxWriProt
ENodeBFunction	EUtranCellFDD	cellDownlinkCaCapacity
ENodeBFunction	EUtranCellFDD	cellRange
ENodeBFunction	EUtranCellFDD	cellSubscriptionCapacity
ENodeBFunction	EUtranCellFDD	cfraEnable

ENodeBFunction	EUtranCellFDD	channelSelectionSetSize
ENodeBFunction	EUtranCellFDD	cioLowerLimitAdjBySon
ENodeBFunction	EUtranCellFDD	cioUpperLimitAdjBySon
ENodeBFunction	EUtranCellFDD	commonSrPeriodicity
ENodeBFunction	EUtranCellFDD	crsGain
ENodeBFunction	EUtranCellFDD	deallocThrPucchFormat1
ENodeBFunction	EUtranCellFDD	deallocTimerPucchFormat1
ENodeBFunction	EUtranCellFDD	dl256QamEnabled
ENodeBFunction	EUtranCellFDD	dlBlerTargetEnabled
ENodeBFunction	EUtranCellFDD	dlDynUeAdmCtrlOverloadThr
ENodeBFunction	EUtranCellFDD	dlDynUeAdmCtrlRetDiffThr
ENodeBFunction	EUtranCellFDD	dlInterferenceManagementActive

ENodeBFunction	EUtranCellFDD	dynUeAdmCtrlFilterConst
ENodeBFunction	EUtranCellFDD	elcLongDrxCycle
ENodeBFunction	EUtranCellFDD	enableServiceSpecificHARQ
ENodeBFunction	EUtranCellFDD	estCellCapUsableFraction
ENodeBFunction	EUtranCellFDD	harqOffsetDL
ENodeBFunction	EUtranCellFDD	harqOffsetUL
ENodeBFunction	EUtranCellFDD	hoOptAdjThresholdAbs
ENodeBFunction	EUtranCellFDD	hoOptAdjThresholdPerc
ENodeBFunction	EUtranCellFDD	hoOptStatNum
ENodeBFunction	EUtranCellFDD	hoOptStatTime
ENodeBFunction	EUtranCellFDD	isDLOnly
ENodeBFunction	EUtranCellFDD	lbTpNonQualFraction
ENodeBFunction	EUtranCellFDD	lbTpRankThreshMin
ENodeBFunction	EUtranCellFDD	lbabDecr
ENodeBFunction	EUtranCellFDD	lbabIncr

ENodeBFunction	EUtranCellFDD	lbabMinBarringFactor
ENodeBFunction	EUtranCellFDD	lbabMinBarringFactorPrio1
ENodeBFunction	EUtranCellFDD	lbabMinBarringFactorPrio2
ENodeBFunction	EUtranCellFDD	lbabPeriod
ENodeBFunction	EUtranCellFDD	lbabThreshRejectRateHigh
ENodeBFunction	EUtranCellFDD	lbabThreshRejectRateLow
ENodeBFunction	EUtranCellFDD	lbabThreshTimeHigh
ENodeBFunction	EUtranCellFDD	lbabThreshTimeLow
ENodeBFunction	EUtranCellFDD	networkSignallingValueCa
ENodeBFunction	EUtranCellFDD	noOfChannelSelectionSets
ENodeBFunction	EUtranCellFDD	noOfPucchCqiUsers
ENodeBFunction	EUtranCellFDD	noOfPucchFormat3PrbPairs
ENodeBFunction	EUtranCellFDD	noOfUllImprovedUe
ENodeBFunction	EUtranCellFDD	outOfCoverageSrTimerPeriodicity

ENodeBFunction	EUtranCellFDD	outOfCoverageThreshold
ENodeBFunction	EUtranCellFDD	pZeroNominalPucch
ENodeBFunction	EUtranCellFDD	pZeroNominalPusch
ENodeBFunction	EUtranCellFDD	pdccchCfiMode
ENodeBFunction	EUtranCellFDD	pdccchOuterLoopInitialAdj
ENodeBFunction	EUtranCellFDD	pdccchOuterLoopInitialAdjPCell
ENodeBFunction	EUtranCellFDD	pdccchOuterLoopInitialAdjVolte
ENodeBFunction	EUtranCellFDD	pdccchOuterLoopUpStep
ENodeBFunction	EUtranCellFDD	pdccchOuterLoopUpStepPCell
ENodeBFunction	EUtranCellFDD	pdccchOuterLoopUpStepVolte
ENodeBFunction	EUtranCellFDD	pdccchPowerBoostMax
ENodeBFunction	EUtranCellFDD	pdccchTargetBler
ENodeBFunction	EUtranCellFDD	pdccchTargetBlerPCell
ENodeBFunction	EUtranCellFDD	pdccchTargetBlerVolte

ENodeBFunction	EUtranCellFDD	pdschTypeBGain
ENodeBFunction	EUtranCellFDD	preambleInitialReceivedTargetPower
ENodeBFunction	EUtranCellFDD	puschPwrOffset64qam
ENodeBFunction	EUtranCellFDD	qQualMin
ENodeBFunction	EUtranCellFDD	qRxLevMin
ENodeBFunction	EUtranCellFDD	srDetectHighThres
ENodeBFunction	EUtranCellFDD	srProcessingLevel
ENodeBFunction	EUtranCellFDD	systemInformationBlock3.sNonIntraSearch
ENodeBFunction	EUtranCellFDD	systemInformationBlock3.sNonIntraSearchP
ENodeBFunction	EUtranCellFDD	systemInformationBlock3.sNonIntraSearchQ
ENodeBFunction	EUtranCellFDD	systemInformationBlock3.sNonIntraSearchv920Active
ENodeBFunction	EUtranCellFDD	systemInformationBlock3.threshServingLowQ

ENodeBFunction	EUtranCellFDD	tReorderingAutoConfiguration
ENodeBFunction	EUtranCellFDD	tTimeAlignmentTimer
ENodeBFunction	EUtranCellFDD	threshServingLow
ENodeBFunction	EUtranCellFDD	ulDynUeAdmCtrlOverloadThr
ENodeBFunction	EUtranCellFDD	ulDynUeAdmCtrlRetDiffThr
ENodeBFunction	EUtranCellFDD	ulImprovedUeSchedLastEnabled
ENodeBFunction	EUtranCellFDD	ulInterferenceManagementActive
ENodeBFunction	EUtranCellFDD	ulSCellPriority
ENodeBFunction	EUtranCellFDD	ulSchedCtrlForOocUesEnabled
ENodeBFunction	EUtranCellFDD	ulTrigActive
ENodeBFunction	EUtranCellRelation	amoAllowed
ENodeBFunction	EUtranCellRelation	coverageIndicator
ENodeBFunction	EUtranCellRelation	isRemoveAllowed
ENodeBFunction	EUtranCellRelation	lbBnrAllowed
ENodeBFunction	EUtranCellRelation	lbCovIndicated

ENodeBFunction	EUtranCellRelation	loadBalancing
ENodeBFunction	EUtranCellRelation	sCellCandidate
ENodeBFunction	EUtranCellRelation	sCellPriority
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringForCsfbPresence
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringForMmtelVideoPresence
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringForMmtelVoicePresence
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringForMoDataPresence
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringForMoSignPresence
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringPriorityCsfb
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringPriorityMmtelVideo
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringPriorityMmtelVoice
ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringPriorityMoData

ENodeBFunction	EUtranCellTDD	acBarringPresence.acBarringPriorityMoSignaling
----------------	---------------	--

ENodeBFunction	EUtranCellTDD	bsrThreshold
----------------	---------------	--------------

ENodeBFunction	EUtranCellTDD	caPrioThreshold
----------------	---------------	-----------------

ENodeBFunction	EUtranCellTDD	cellSubscriptionCapacity
----------------	---------------	--------------------------

ENodeBFunction	EUtranCellTDD	cioLowerLimitAdjBySon
----------------	---------------	-----------------------

ENodeBFunction	EUtranCellTDD	cioUpperLimitAdjBySon
----------------	---------------	-----------------------

ENodeBFunction	EUtranCellTDD	dl256QamEnabled
ENodeBFunction	EUtranCellTDD	dlBlerTargetEnabled
ENodeBFunction	EUtranCellTDD	elcLongDrxCycle

ENodeBFunction	EUtranCellTDD	enableServiceSpecificHARQ
ENodeBFunction	EUtranCellTDD	estCellCapUsableFraction

ENodeBFunction	EUtranCellTDD	harqOffsetDI
----------------	---------------	--------------

ENodeBFunction	EUtranCellTDD	harqOffsetUI
----------------	---------------	--------------

ENodeBFunction	EUtranCellTDD	hoOptAdjThresholdAbs
----------------	---------------	----------------------

ENodeBFunction	EUtranCellTDD	hoOptAdjThresholdPerc
----------------	---------------	-----------------------

ENodeBFunction	EUtranCellTDD	hoOptStatNum
----------------	---------------	--------------

ENodeBFunction	EUtranCellTDD	hoOptStatTime
ENodeBFunction	EUtranCellTDD	lbabDecr
ENodeBFunction	EUtranCellTDD	lbabIncr
ENodeBFunction	EUtranCellTDD	lbabMinBarringFactor
ENodeBFunction	EUtranCellTDD	lbabMinBarringFactorPrio1
ENodeBFunction	EUtranCellTDD	lbabMinBarringFactorPrio2
ENodeBFunction	EUtranCellTDD	lbabPeriod
ENodeBFunction	EUtranCellTDD	lbabThreshRejectRateHigh
ENodeBFunction	EUtranCellTDD	lbabThreshRejectRateLow
ENodeBFunction	EUtranCellTDD	lbabThreshTimeHigh
ENodeBFunction	EUtranCellTDD	lbabThreshTimeLow
ENodeBFunction	EUtranCellTDD	noOfChannelSelectionSets
ENodeBFunction	EUtranCellTDD	noOfPucchCqiUsers
ENodeBFunction	EUtranCellTDD	noOfPucchFormat3PrbPairs
ENodeBFunction	EUtranCellTDD	noOfUllImprovedUe
ENodeBFunction	EUtranCellTDD	outOfCoverageSrTimerPeriodicity
ENodeBFunction	EUtranCellTDD	outOfCoverageThreshold

ENodeBFunction	EUtranCellTDD	systemInformationBlock3.sNonIntraSearch
ENodeBFunction	EUtranCellTDD	systemInformationBlock3.sNonIntraSearchP
ENodeBFunction	EUtranCellTDD	systemInformationBlock3.sNonIntraSearchQ
ENodeBFunction	EUtranCellTDD	systemInformationBlock3.sNonIntraSearchv920Active
ENodeBFunction	EUtranCellTDD	systemInformationBlock3.threshServingLowQ
ENodeBFunction	EUtranCellTDD	tReorderingAutoConfiguration
ENodeBFunction	EUtranCellTDD	tTimeAlignmentTimer
ENodeBFunction	EUtranCellTDD	ulImprovedUeSchedLastEnabled
ENodeBFunction	EUtranCellTDD	ulSchedCtrlForOocUesEnabled
ENodeBFunction	EUtranCellTDD	ulTrigActive
ENodeBFunction	EUtranFreqRelation	allowedMeasBandwidth
ENodeBFunction	EUtranFreqRelation	amoAllowed
ENodeBFunction	EUtranFreqRelation	anrMeasOn
ENodeBFunction	EUtranFreqRelation	caFreqPriority
ENodeBFunction	EUtranFreqRelation	caFreqProportion
ENodeBFunction	EUtranFreqRelation	caTriggeredRedirectionActive

ENodeBFunction	EUtranFreqRelation	cellReselectionPriority
ENodeBFunction	EUtranFreqRelation	interFreqMeasTypeUISinr
ENodeBFunction	EUtranFreqRelation	lbA5Thr1RsrpFreqOffset
ENodeBFunction	EUtranFreqRelation	lbActivationThreshold
ENodeBFunction	EUtranFreqRelation	lbBnrPolicy
ENodeBFunction	EUtranFreqRelation	threshXHigh
ENodeBFunction	EUtranFreqRelation	threshXLow
ENodeBFunction	ExternalENodeBFunction	eSCellCapacityScaling
ENodeBFunction	ExternalENodeBFunction	ulTrigHoSupport
ENodeBFunction	ExternalEUtranCellFDD	isRemoveAllowed
ENodeBFunction	ExternalEUtranCellTDD	isRemoveAllowed
ENodeBFunction	GeranFreqGroupRelation	anrMeasOn
ENodeBFunction	GeranFreqGroupRelation	cellReselectionPriority
ENodeBFunction	IdleModePrioAtRelease	highLoadThreshold
ENodeBFunction	IdleModePrioAtRelease	lowLoadThreshold
ENodeBFunction	IdleModePrioAtRelease	lowMediumLoadThreshold
ENodeBFunction	IdleModePrioAtRelease	mediumHighLoadThreshold
ENodeBFunction	IdleModePrioAtRelease	mediumLoadThreshold

ENodeBFunction	lmeisvProfile	elc320msDrxEnabled
ENodeBFunction	LoadBalancingFunction	lbCaCapHysteresis
ENodeBFunction	LoadBalancingFunction	lbCaThreshold
ENodeBFunction	LoadBalancingFunction	lbCeiling
ENodeBFunction	LoadBalancingFunction	lbDiffCaOffset
ENodeBFunction	LoadBalancingFunction	lbHitRateEUtranAddThreshold
ENodeBFunction	LoadBalancingFunction	lbHitRateEUtranMeasUeIntensity
ENodeBFunction	LoadBalancingFunction	lbHitRateEUtranMeasUeThreshold
ENodeBFunction	LoadBalancingFunction	lbHitRateEUtranRemoveThreshold
ENodeBFunction	LoadBalancingFunction	lbMeasScalingLimit
ENodeBFunction	LoadBalancingFunction	lbRateOffsetCoefficient
ENodeBFunction	LoadBalancingFunction	lbRateOffsetLoadThreshold
ENodeBFunction	LoadBalancingFunction	lbThreshold
ENodeBFunction	LoadBalancingFunction	lbUeEvaluationTimer

ENodeBFunction	Paging	nB
ENodeBFunction	QciProfileOperatorDefined	absPrioOverride
ENodeBFunction	QciProfileOperatorDefined	pdb
ENodeBFunction	QciProfileOperatorDefined	priority
ENodeBFunction	QciProfileOperatorDefined	priorityFraction
ENodeBFunction	QciProfileOperatorDefined	schedulingAlgorithm
ENodeBFunction	QciProfileOperatorDefined	serviceType

ENodeBFunction	QciProfilePredefined	absPrioOverride
ENodeBFunction	QciProfilePredefined	pdb
ENodeBFunction	QciProfilePredefined	priority
ENodeBFunction	QciProfilePredefined	priorityFraction
ENodeBFunction	QciProfilePredefined	schedulingAlgorithm
ENodeBFunction	QciProfilePredefined	serviceType
ENodeBFunction	Rcs	tInactivityTimer
ENodeBFunction	ReportConfigA5	hysteresisA5RsrqOffset
ENodeBFunction	ReportConfigA5	timeToTriggerA5Rsrq
ENodeBFunction	ReportConfigA5Anr	a5Threshold1RsrpAnrDelta
ENodeBFunction	ReportConfigA5Anr	a5Threshold1RsrqAnrDelta

ENodeBFunction	ReportConfigA5Anr	a5Threshold2RsrpAnrDelta
ENodeBFunction	ReportConfigA5Anr	a5Threshold2RsrqAnrDelta
ENodeBFunction	ReportConfigA5Anr	hysteresisA5
ENodeBFunction	ReportConfigA5Anr	timeToTriggerA5
ENodeBFunction	ReportConfigA5Ultrig	a5Threshold2Rsrp
ENodeBFunction	ReportConfigA5Ultrig	hysteresisA5
ENodeBFunction	ReportConfigA5Ultrig	reportIntervalA5
ENodeBFunction	ReportConfigA5Ultrig	timeToTriggerA5
ENodeBFunction	ReportConfigB2Cdma2000	hysteresisB2RsrqOffset
ENodeBFunction	ReportConfigB2Cdma2000	timeToTriggerB2Rsrq
ENodeBFunction	ReportConfigB2Geran	hysteresisB2RsrqOffset
ENodeBFunction	ReportConfigB2Geran	timeToTriggerB2Rsrq

ENodeBFunction	ReportConfigB2GeranUITrig	b2Threshold2Geran
ENodeBFunction	ReportConfigB2GeranUITrig	hysteresisB2
ENodeBFunction	ReportConfigB2GeranUITrig	reportIntervalB2

ENodeBFunction	ReportConfigB2GeranUITrig	timeToTriggerB2
----------------	---------------------------	-----------------

ENodeBFunction	ReportConfigB2Utra	hysteresisB2RsrqOffset
----------------	--------------------	------------------------

ENodeBFunction	ReportConfigB2Utra	timeToTriggerB2Rsrq
----------------	--------------------	---------------------

ENodeBFunction	ReportConfigB2UtraUITrig	b2Threshold2EcNoUtra
----------------	--------------------------	----------------------

ENodeBFunction	ReportConfigB2UtraUITrig	b2Threshold2RscpUtra
----------------	--------------------------	----------------------

ENodeBFunction	ReportConfigB2UtraUITrig	hysteresisB2
----------------	--------------------------	--------------

ENodeBFunction	ReportConfigB2UtraUITrig	reportIntervalB2
----------------	--------------------------	------------------

ENodeBFunction	ReportConfigB2UtraUITrig	timeToTriggerB2
----------------	--------------------------	-----------------

ENodeBFunction	ReportConfigEUltraBestCell	a3offset
----------------	----------------------------	----------

ENodeBFunction	ReportConfigEUltraBestCell	timeToTriggerA3
----------------	----------------------------	-----------------

ENodeBFunction	ReportConfigEUltraBestCellAnr	a3offsetAnrDelta
----------------	-------------------------------	------------------

ENodeBFunction	ReportConfigEUltraBestCellAnr	hysteresisA3
----------------	-------------------------------	--------------

ENodeBFunction	ReportConfigEUltraBestCellAnr	timeToTriggerA3
----------------	-------------------------------	-----------------

ENodeBFunction	ReportConfigEUtralFBestCell	a3RsrqOffset
----------------	-----------------------------	--------------

ENodeBFunction	ReportConfigEUtralFBestCell	hysteresisA3RsrqOffset
----------------	-----------------------------	------------------------

ENodeBFunction	ReportConfigEUtralFBestCell	timeToTriggerA3Rsrq
----------------	-----------------------------	---------------------

ENodeBFunction	ReportConfigEutraInterFreqLb	a5Threshold1Rsrp
----------------	------------------------------	------------------

ENodeBFunction	ReportConfigEutraInterFreqLb	a5Threshold2Rsrp
----------------	------------------------------	------------------

ENodeBFunction	ReportConfigEutraInterFreqLb	a5Threshold2Rsrq
----------------	------------------------------	------------------

ENodeBFunction	ReportConfigEutraInterFreqLb	hysteresisA5
----------------	------------------------------	--------------

ENodeBFunction	ReportConfigSCellA1A2	a1a2ThresholdRsrp
----------------	-----------------------	-------------------

ENodeBFunction	ReportConfigSCellA1A2	a1a2ThresholdRsrpBidir
----------------	-----------------------	------------------------

ENodeBFunction	ReportConfigSCellA1A2	a1a2ThresholdRsrq
----------------	-----------------------	-------------------

ENodeBFunction	ReportConfigSCellA1A2	hysteresisA1A2Rsrp
----------------	-----------------------	--------------------

ENodeBFunction	ReportConfigSCellA1A2	hysteresisA1A2RsrpBidirectional
----------------	-----------------------	---------------------------------

ENodeBFunction	ReportConfigSCellA1A2	hysteresisA1A2Rsrq
----------------	-----------------------	--------------------

ENodeBFunction	ReportConfigSCellA1A2	timeToTriggerA1
----------------	-----------------------	-----------------

ENodeBFunction	ReportConfigSCellA1A2	timeToTriggerA2
----------------	-----------------------	-----------------

ENodeBFunction	ReportConfigSCellA1A2	triggerQuantityA1A2
----------------	-----------------------	---------------------

ENodeBFunction	ReportConfigSCellA6	a6offset
ENodeBFunction	ReportConfigSCellA6	hysteresisA6
ENodeBFunction	ReportConfigSCellA6	timeToTriggerA6
ENodeBFunction	ReportConfigSCellA6	triggerQuantityA6
ENodeBFunction	ReportConfigSearch	a1a2SearchThresholdRsrp
ENodeBFunction	ReportConfigSearch	a1a2SearchThresholdRsrq
ENodeBFunction	ReportConfigSearch	a1a2UISearchThreshold
ENodeBFunction	ReportConfigSearch	a2CriticalThrQci1RsrpOffset
ENodeBFunction	ReportConfigSearch	a2CriticalThrQci1RsrqOffset
ENodeBFunction	ReportConfigSearch	a2CriticalThresholdRsrp
ENodeBFunction	ReportConfigSearch	a2CriticalThresholdRsrq
ENodeBFunction	ReportConfigSearch	a2OuterSearchThrRsrpOffset

ENodeBFunction	ReportConfigSearch	a2OuterSearchThrRsrqOffset
ENodeBFunction	ReportConfigSearch	a2UICriticalThreshold
ENodeBFunction	ReportConfigSearch	hysteresisA1A2SearchRsrp
ENodeBFunction	ReportConfigSearch	hysteresisA1A2SearchRsrq
ENodeBFunction	ReportConfigSearch	hysteresisA1A2UISearch
ENodeBFunction	ReportConfigSearch	hysteresisA2CriticalRsrp
ENodeBFunction	ReportConfigSearch	hysteresisA2CriticalRsrq
ENodeBFunction	ReportConfigSearch	hysteresisA2OuterSearchRsrp
ENodeBFunction	ReportConfigSearch	hysteresisA2OuterSearchRsrq
ENodeBFunction	ReportConfigSearch	hysteresisA2UICritical
ENodeBFunction	ReportConfigSearch	inhibitA2SearchConfig
ENodeBFunction	ReportConfigSearch	timeToTriggerA1Search
ENodeBFunction	ReportConfigSearch	timeToTriggerA1SearchRsrq
ENodeBFunction	ReportConfigSearch	timeToTriggerA1UISearch
ENodeBFunction	ReportConfigSearch	timeToTriggerA2Critical
ENodeBFunction	ReportConfigSearch	timeToTriggerA2CriticalRsrq

ENodeBFunction	ReportConfigSearch	timeToTriggerA2OutSearch
ENodeBFunction	ReportConfigSearch	timeToTriggerA2OutSearchRsrq
ENodeBFunction	ReportConfigSearch	timeToTriggerA2Search
ENodeBFunction	ReportConfigSearch	timeToTriggerA2SearchRsrq
ENodeBFunction	ReportConfigSearch	timeToTriggerA2UICritical
ENodeBFunction	ReportConfigSearch	timeToTriggerA2UISearch
ENodeBFunction	RlfProfile	n310
ENodeBFunction	RlfProfile	n311
ENodeBFunction	RlfProfile	t301
ENodeBFunction	RlfProfile	t310
ENodeBFunction	RlfProfile	t311
ENodeBFunction	Rrc	t301
ENodeBFunction	Rrc	t304

ENodeBFunction	Rrc	t311
ENodeBFunction	SectorCarrier	radioTransmitPerformanceMode
ENodeBFunction	SectorCarrier	ulForcedTimingAdvanceCommand
ENodeBFunction	SignalingRadioBearer	dlMaxRetxThreshold
ENodeBFunction	SignalingRadioBearer	tPollRetransmitDL
ENodeBFunction	SignalingRadioBearer	tPollRetransmitUL
ENodeBFunction	SignalingRadioBearer	ulMaxRetxThreshold
ENodeBFunction	UeMeasControl	bothA5RsrpRsrqCheck
ENodeBFunction	UeMeasControl	checkA2SearchLevel

ENodeBFunction	UeMeasControl	excludeInterFreqAtCritical
ENodeBFunction	UeMeasControl	inhibitB2RsrqConfig
ENodeBFunction	UeMeasControl	lowPrioMeasThresh
ENodeBFunction	UeMeasControl	maxMeasInterFreqEUtra
ENodeBFunction	UeMeasControl	maxNoMeasReportsInact
ENodeBFunction	UeMeasControl	sMeasure
ENodeBFunction	UeMeasControl	searchEffortTime
ENodeBFunction	UeMeasControl	targetA2UISearchOffset
ENodeBFunction	UeMeasControl	ueMeasurementsActiveCDMA2000
ENodeBFunction	UeMeasControl	ueMeasurementsActiveGERAN
ENodeBFunction	UeMeasControl	ueMeasurementsActiveIF
ENodeBFunction	UeMeasControl	ueMeasurementsActiveUTRAN
ENodeBFunction	UeMeasControl	ulSinrOffset
ENodeBFunction	UtranFreqRelation	anrMeasOn
ENodeBFunction	UtranFreqRelation	cellReselectionPriority



1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1
1
1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

1

Parameter Description

Highest allowed fraction of non-privileged RRC connections that might be admitted without ARP based differentiation. When fraction of RRC connected users versus available capacity exceeds this threshold, only RRC connections that setup bearers with high ARP priority are admitted. Other RRC connections may only be admitted if preemption is possible. The fraction is given with respect to the maximum capacity after privileged access resource reservation has been subtracted.

Activates or deactivates the Allocation and Retention Priority (ARP) based pre-emption function. The value of the attribute is irrelevant when no valid license key is installed for the Differentiated Admission Control feature.

If both Dynamic GBR Admission Control and Differentiated Admission Control are licensed and activated:

Sets the highest allowed downlink radio resource utilization ratio for the GBR bearers with lower ARP priority in radio bearer admission. Applies to each resource considered by Dynamic GBR Admission Control.

If Dynamic GBR Admission Control is licensed and activated but Differentiated Admission Control is not licensed or not activated:

Sets the highest allowed downlink radio resource utilization ratio for the GBR bearers in radio bearer admission. Applies to each resource considered by Dynamic GBR Admission Control.

Sets the highest allowed downlink radio resource utilization ratio for admission of a GBR radio bearer. Applies to each resource considered by Dynamic GBR Admission Control. Resource utilization is checked against this threshold for all new, re-established or incoming handover GBR bearer requests.

Downlink transport network bandwidth for LTE.

Number of privileged access connections to be reserved per cell.

Number of Radio Bearers to be reserved per privileged access connection. This includes SRB1, SRB2 and DRBs.

The eNB interprets Allocation Retention Priority Levels, received from the Core Network, between 1 and paArpOverride (inclusive) as Privileged Access.

The value zero will disable Privileged Access ARP override.

Activates or deactivates the Resource Reservation for Privileged Access.

If both Dynamic GBR Admission Control and Differentiated Admission Control are licensed and activated:

Sets the highest allowed uplink radio resource utilization ratio for the GBR bearers with lower ARP priority in radio bearer admission. Applies to each resource considered by Dynamic GBR Admission Control.

If Dynamic GBR Admission Control is licensed and activated but Differentiated Admission Control is not licensed or not activated:

Sets the highest allowed uplink radio resource utilization ratio for the GBR bearers in radio bearer admission. Applies to each resource considered by Dynamic GBR Admission Control.

Sets the highest allowed uplink radio resource utilization ratio for admission of a GBR radio bearer. Applies to each resource considered by Dynamic GBR Admission Control. Resource utilization is checked against this threshold for all new, re-established or incoming handover GBR bearer requests.

Uplink transport network bandwidth for LTE.

Temporary attributes are intended for temporary solutions, and their usage may vary depending on the installed software. It is strongly recommended to only set the attributes that correspond to a desired functionality and leave all other temporary attributes set to default value. Information in the descriptions about what attributes are in use may be overridden by the information in CPI Info documents. Note that a later release may use another attribute to control the functionality previously provided by a temporary attribute, or may remove the functionality altogether. In these cases, the change is documented in the NIR.

Unit: 0.001

Temporary attributes are intended for temporary solutions, and their usage may vary depending on the installed software. It is strongly recommended to only set the attributes that correspond to a desired functionality and leave all other temporary attributes set to default value. Information in the descriptions about what attributes are in use may be overridden by the information in CPI Info documents. Note that a later release may use another attribute to control the functionality previously provided by a temporary attribute, or may remove the functionality altogether. In these cases, the change is documented in the NIR.

Unit: 0.001

Whether or not AMO function is allowed for inter-vendor cell relations.

The ANR criteria to add or remove MO neighbor relation. A candidate neighbor relation is internally evaluated before creation as MO if the daily HO attempt rate exceeds the threshold. If the value is set to 0, MO cell relations must be immediately created regardless of the HO attempt rate. The condition to remove a relation from the MOM also depends on the attribute removeNrelTime.

Defines a maximal value of reports that any UE has to provide the ANR function with on event based measurements, that is used to measure on EUTRAN neighbors.
Special Value: 0 means infinity.

Defines a maximal time that any UE has to assist ANR function with event based measurements, that is used to measure on EUTRAN neighbors.
Special Value: 0 means infinity.

Controls if ECGI measurements are requested in order to detect PCI conflicts.

Controls if ECGI measurements are requested prior to hand over, in case a PCI conflict is detected.
Turns periodic ECGI measurements on or off for ANR Whitelist PLMN IDs for EUTRAN.
If true, ANR Whitelist PLMN ID for EUTRAN is enabled.

Specifies the threshold. Together with `probCellDetectLowHoSuccTime` it controls when `EUtranCellRelation::hoSuccLevel` changes from MEDIUM to LOW and conversely.

Note: The handover statistics status must be $\leq$ the `AnrFunction::probCellDetectLowHoSuccThres` at least the `AnrFunction::probCellDetectLowHoSuccTime` time before `hoSuccLevel` is changed from MEDIUM to LOW. The handover statistics status must be $>$ the `AnrFunction::probCellDetectLowHoSuccThres` at least the `AnrFunction::probCellDetectLowHoSuccTime/2` before the `hoSuccLevel` is changed from LOW to MEDIUM.

Only applicable when `AnrFunction::problematicCellPolicy` is set to `AUTO_DETECT` or `AUTO_DETECT_AND_BAR`.

Specifies the time. Together with `probCellDetectLowHoSuccThreas` it controls when `EUtranCellRelation::hoSuccLevel` changes from MEDIUM to LOW and conversely.

Only applicable when `AnrFunction::problematicCellPolicy` is set to `AUTO_DETECT` or `AUTO_DETECT_AND_BAR`.

Specifies the threshold. Together with `AnrFunction::probCellDetectMedHoSuccTime` it controls when `EUtranCellRelation::hoSuccLevel` changes from HIGH to MEDIUM and conversely.

Note: The handover statistics status must be $\leq$ the `AnrFunction::probCellDetectMedHoSuccThres` at least the `AnrFunction::probCellDetectMedHoSuccTime` time before `hoSuccLevel` is changed from HIGH to MEDIUM. The handover statistics status must be $>$ the `AnrFunction::probCellDetectMedHoSuccThres` at least the `AnrFunction::probCellDetectMedHoSuccTime/2` before the `hoSuccLevel` is changed from MEDIUM to HIGH.

Only applicable when `AnrFunction::problematicCellPolicy` is set to `AUTO_DETECT` or `AUTO_DETECT_AND_BAR`.

Specifies the time. Together with `probCellDetectMedHoSuccThres` it controls when `EUtranCellRelation::hoSuccLevel` changes from HIGH to MEDIUM and conversely.

Only applicable when `AnrFunction::problematicCellPolicy` is set to `AUTO_DETECT` or `AUTO_DETECT_AND_BAR`.

Specifies if detection of problematic cell is activated or not.

The length of time that neighbor cells without any neighbor relations remain in the RBS. 1000 means no automatic removal is performed. If set to 0, the neighbor cell MO is removed within 1 minute. Ericsson strongly recommend that value 0 shall not be used, due to the fact that when setting this value to 0, this might lead to that X2 connections are removed together with all external cells and are setup once again every minute this causes one a network level a huge pressure one the nodes.

The length of time that neighbor RBSs without any neighbor cells remain in the RBS. 1000 means no automatic removal is performed. If set to 0, the neighbor RBS MO is removed within 1 minute.

The maximum time that a neighbor relation can fall short of the cellRelationHoRateThreshold before MO is removed from the MOM. A removed cell relation is still evaluated in RBS as a candidate neighbor relation as long as there is at least one PCI or CGI reported for removeNrelTime.

1000 means no automatic removal is performed. If set to 0, the neighbor relation MO is removed within 1 minute. Value 0 must not be used, because new CGI measurements are already performed for any relation not used for handover after 1 minute.

Decrease in the target number of periodic measurement reports for each EUTranFreqRelation each time an ANR EUTRAN measurement report is received with only known neighbor cells. Note that the unit is decMeasurementReport. Thus, the given number of measurement reports is divided by 10.

Increase in the target number of periodic measurement reports for each EUTranFreqRelation each time an ANR EUTRAN measurement report is received with unknown neighbor EUTRAN cells. Note that the unit is decMeasurementReport. Thus, the given number of measurement reports is divided by 10.

Maximum target number of periodic measurement reports each hour for each EUTranFreqRelation. The number of measurement reports can deviate from the target.

Note that the unit is decMeasurementReport. Thus, the given number of measurement reports is divided by 10.

Minimum target number of periodic measurement reports each hour for each EUTranFreqRelation. The number of measurement reports can deviate from the target.

Note that the unit is decMeasurementReport. Thus, the given number of measurement reports is divided by 10.

Activates or deactivates the Automated Neighbor Relation (ANR) function support for Inter frequency LTE for one RBS. The value of the attribute is irrelevant when no valid license key is installed for the ANR feature.

Activates or deactivates the Automated Neighbor Relation (ANR) function support for Intra frequency LTE for one RBS. The value of the attribute is irrelevant when no valid license key is installed for the ANR feature.

This parameter defines the decrease in the target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN intra-frequency neighbour cell reports, every time a neighbour cell report is received with only known neighbour cells.

This parameter defines the increase in the target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN intra-frequency neighbour cell reports, every time a neighbour cell report for ANR is received with unknown neighbour cells.

This parameter defines the increase in the target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN intra-frequency neighbour cell reports, every time a neighbour cell report for HO is received with unknown neighbour cells.

This parameter defines the maximum target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN intra-frequency neighbour cell reports. The actual number of UEs with these thresholds may deviate from the target.

This parameter defines the minimum target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN intra-frequency neighbour cell reports. The actual number of UEs with these thresholds may deviate from the target.

This parameter defines the decrease in the target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN inter-frequency neighbor cell reports, every time a neighbor cell report is received with only known neighbor cells.

This parameter defines the increase in the target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN inter-frequency neighbor cell reports, every time a neighbor cell report for ANR is received with unknown neighbor cells.

This parameter defines the increase in the target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN inter-frequency neighbor cell reports, every time a neighbor cell report for HO is received with unknown neighbor cells.

This parameter defines the maximum target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN inter-frequency neighbor cell reports. The actual number of UEs with these thresholds may deviate from the target.

This parameter defines the minimum target number of UEs in each cell, that are assigned ANR specific thresholds for EUTRAN inter-frequency neighbor cell reports. The actual number of UEs with these thresholds may deviate from the target.

Threshold value for reported power for a cell to be automatically added as neighbor.

Threshold value for reported quality for a cell to be automatically added as neighbor.

Starting value of the parameter isHoAllowed when a EUTranCellRelation is created by ANR (Automatic Neighbor Relations) or X2.

Indicates if X2 is to be set up when an ExternalENodeBFunction that is not in the x2BlackList is created by ANR (Automatic Neighbor Relations).

The decrease in the target number of measurement reports per GeranFrequencyGroupRelation each time an Automated Neighbor Relations (ANR) GERAN measurement report is received with only known neighbor cells. Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Defines the increase in the target number of measurement reports per GeranFrequencyGroupRelation each time an Automated Neighbor Relations (ANR) GERAN measurement report is received with unknown neighbor GERAN cells or an unknown cell found in GERAN mobility report.

Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

The maximum target number of measurement reports per hour for each GeranFrequencyGroupRelation. The number of measurement reports may deviate from the target.

Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

The minimum target number of measurement reports per hour for each GeranFrequencyGroupRelation. The number of measurement reports may deviate from the target.

Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Defines the increase in the target number of measurement reports for each GeranFreqGroupRelation each time a PCI measurement report is received with known cell but the corresponding RAC missing.
Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Activates or deactivates the Automated Neighbor Relations (ANR) function support for GSM for one RBS. The value of the attribute is irrelevant when no valid license key is installed for the ANR feature.

Activates or deactivates the Automated Neighbor Relation (ANR) function support for Utran for one RBS. The value of the attribute is irrelevant when no valid license key is installed for the ANR feature.

Defines the increase in the target number of measurement reports for each UtranFreqRelation/UtranTDDFreqRelation each time a PCI measurement report is received with known cell but the corresponding LAC or RAC missing.
Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Defines the decrease in the target number of measurement reports for each UtranFreqRelation/UtranTDDFreqRelation each time an Automated Neighbor Relations (ANR) UTRAN measurement report is received with only known neighbor cells.
Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Defines the increase in the target number of measurement reports for each UtranFreqRelation/UtranTDDFreqRelation each time an Automated Neighbor Relations (ANR) UTRAN measurement report is received with unknown neighbor UTRAN cells.
Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Defines the maximum target number of measurement reports per hour for each UtranFreqRelation/UtranTDDFreqRelation. The number of measurement reports may deviate from the target.
Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

Defines the minimum target number of measurement reports per hour for each UtranFreqRelation/UtranTDDFreqRelation. The number of measurement reports may deviate from the target.
Please note that the unit is decMeasurementReport. Thus, the given number of measurement reports will be divided by 10.

This parameter together with b2Threshold2EcNoUtra specifies "Ratio of energy per modulation bit to noise spectral density" threshold value for reported EcNo for a cell to be automatically added as neighbor. The equation for calculating the EcNo threshold is $b2Threshold2EcNoUtra + cellAddEcNoThresholdUtranDelta$.

This parameter together with b2Threshold2RscpUtra specifies "The Received Signal Code Power" (RSCP) threshold value for reported power for a cell to be automatically added as neighbor. The equation for calculating the RSCP threshold is $b2Threshold2RscpUtra + cellAddRscpThresholdUtranDelta$.

The number of consecutive PDCCH subframes after successfully decoding a PDCCH that indicates an initial UL or DL user data transmission for this UE. Attribute is only used to read CGI for ANR PCI conflict cell. TS36.331 ch. 6.3.2, RRC parameter drx-InactivityTimer.

Value longDrxCycle indicates the number of subframes. Attribute is only used to read CGI for ANR PCI conflict.

The number of consecutive PDCCH subframes at DRX Cycle initialization. Attribute is only used to read CGI for ANR PCI conflict cell. TS36.331 ch. 6.3.2, RRC parameter onDurationTimer.

Configures resource consumption margin in percentage. This stops configuring new SCells when there is total resource usage on a DU or Basedband.

Total number of connected UEs + total number of configured SCells > Maximum RRC Connected Users * (100 - caPreemptionThreshold) / 100

Maximum of RRC Connected Users is a DU or Baseband hardware capacity limit which can be found in CPI LTE Supported Capacity and Configurations.

Preference between downlink and uplink carrier aggregation.

Used to adjust factor of CC rate for CA UEs, which is used in scheduler's proportional fairness algorithm. A smaller value gives CA UE a greater advantage over non-CA UE.
Value 0 sets rate as 0 and this is for testing purpose only; values 1 - 4 set the rate as fraction of the cell rate in increased order; value 5 sets cell based rate; values 6 - 9 set the rate as cell rate plus rate influence from other CCs in increased order; value 10 sets the rate as aggregated rate of all CCs .

The value configures the number of SCell connections which can be in use for carrier aggregation. A secondary cell (SCell) costs in memory the same as a primary cell (PCell) for each UE. It is preferred to avoid limiting SCell connections with caUsageLimit, and use caPreemptionThreshold instead.

Method used to select SCell candidates.

Used to enable enhanced selection of four layer MIMO and carrier aggregation. Secondary cell is not added if effective bandwidth is reduced. If effective bandwidth is not changed, tie-breaking rule is governed by fourLayerMimoPreferred. Effective bandwidth includes the number of DL PRBs and DL MIMO layer capability of the UE in all serving cells.

Whether or not SCell is added when there is no change in effective bandwidth. Applies when enhanced selection of four layer MIMO and carrier aggregation is enabled. If set to true, SCell is not added, otherwise SCell is added.

Enables CA when VoIP (or PTT) and enhanced PDCCH Link Adaptation on FDD PCell are both active. Not used for TDD PCells.

One or more SCells can be activated if minimum time needed to transmit all bits in all priority queues of UE is higher than `sCellActDeactDataThres`.

When deciding the activation of one SCell, minimum time needed to transmit all bits is calculated as the number of bits in all priority queues, divided by the number of bits that can be transmitted in one TTI by all active serving cells prior to activation decision. This is computed as though the UE is given all resources in those cells. If the condition for activating one SCell is satisfied, a second SCell is also considered for activation but the minimum time needed to transmit all bits is now calculated by considering the added capacity of the first new SCell that is already considered for activation.

For FDD, the unit "number of DL subframes" is equivalent to ms, but for TDD UL/DL subframe configuration 1, there are 6 DL subframes in 10ms, and for UL/DL subframe configuration 2, there are 8 DL subframes in 10ms.

"-1" means the data-triggered activation condition is always satisfied even with no data in the buffer, and also that the data-triggered deactivation condition is never satisfied.

If the minimum time needed to transmit all bits in all priority queues of a UE is less than or equal to `sCellActDeactDataThres` minus `sCellActDeactDataThresHyst`, then deactivation of one component carrier is considered.

Minimum time needed to transmit all bits is calculated as number of bits in all priority queues, divided by the number of bits that can be transmitted in one TTI by all active serving cells after deactivation decision. This is computed as though the UE is given all resources in those cells.

For FDD, the unit "number of DL subframes" is equivalent to ms, but for TDD UL/DL subframe configuration 1, there are 6 DL subframes in 10ms, and for UL/DL subframe configuration 2, there are 8 DL subframes in 10ms.

If `sCellActDeactDataThres` is set to "-1", the data-triggered deactivation condition is never satisfied and the value of `sCellActDeactDataThresHyst` is ignored.

If the minimum time needed to transmit all bits in all priority queues in UL of a UE is higher than `sCellActDeactULDataThresh`, activation of one or more secondary cells is considered.

If minimum time needed to transmit all bits in all priority queues in UL of a UE is less than `sCellActDeactULDataThresh` minus `sCellActDeactULDataThreshHyst`, deactivation of one CC is considered.

Activation prohibit timer. No new SCell activation is allowed while this timer is running.

One SCell is deactivated if minimum time needed to transmit all bits in all priority queues of a UE is less than or equal to `sCellActDeactDataThres` minus `sCellActDeactDataThresHyst` for a duration of `sCellDeactDelayTimer`.

SCell is deactivated if:

- wideband DL SINR remains below sCellScheduleSinrThres, or
- no Channel State Information is received by the eNB for a duration of sCellDeactOutOfCoverageTimer.

Deactivation can be deferred, for example by sCellDeactProhibitTimer.

"-1" means the SCell is not deactivated due to the SINR condition.

Deactivation prohibit timer. No new SCell deactivation is allowed while this timer is running.

No data is scheduled on SCell if wideband SINR is lower than sCellScheduleSinrThres. If SINR remains below threshold, SCell is deactivated when sCellDeactOutOfCoverageTimer expired.

Selects behavior of selecting SCell candidates beyond first candidate.

Warning: There is a risk when using UN_ACK_SIMULTANEOUS_SCELL_SELECTION since UE does not send A1 measurement report for coverage confirmation.

Controls the length of time that elapses until a UE is reconsidered for additional SCell configuration after the eNB was unable to configure this UE with more than one SCell.

"-1" means wait forever.

Changed value can take effect related to the next SCell configuration during the ongoing connection.

Controls time eNodeB waits after reception of an A2 measurement report until SCell is deconfigured. If an A6 measurement report is received on an allowed SCell candidate before timer expires, an SCell swap is performed. Value -1 means wait forever.

Controls the length of time that elapses until a UE is considered once again for SCell configuration after the eNB was not able to configure this UE with a suitable SCell.

"-1" means wait forever.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

Maximum number RLC re-transmissions in DL before stopping and indicating to RRC that the RLC threshold is reached.

Time lapsed before request for new poll if no STATUS report arrives for the Sequence Number that is contained in the DL RLC Data PDU where the poll bit is set.

Time lapsed before request for new poll if no STATUS report arrives for the Sequence Number that is contained in the UL RLC Data PDU where the poll bit is set.

Maximum number RLC re-transmissions in UL before stopping and indicating to RRC that the RLC threshold is reached.

The targeted maximum allowed time between scheduling occasions of a DL bearer. A bearer that is not scheduled within the specified time is given higher priority. Value 0 means that the higher priority is never applied. It is recommended to set the value $\leq$ than the PDB. A value that is set too low can affect other services with higher priority.

Enables or disables the UL SINR max measurements and event triggers for the UL quality. Only has effect if license for Uplink-Triggered Inter-Frequency Mobility is not installed.

DSCP value used for outgoing inter-eNB CA packets on X2.

It is recommended to set this to the same value as "QCI9 - Non-GBR TCP Default Bearer", as inter-eNB CA benefits should be treated as opportunistic and not allowed to interfere with baseline LTE performance.

Configures use of autonomous gap as method of CGI measurement. If enabled, capable UEs are configured to use autonomous gap for CGI measurement to target LTE or UTRAN cell.

Enables or disables the RRC Connection Reestablishment in source cell when there is no target neighbor cell information.

Inactivity time value to be used to decide release of inactive UEs at handover.

Minimum MP load level at which inactive UEs are released at handover.

Indicates if the feature RRC Connection Reestablishment is ACTIVATED or DEACTIVATED.

Supervision timer of the outgoing S1/X2/intra-eNodeB handover execution procedure according to 3GPP TS 36.413 and TS 36.423.

If the feature Multi-Target RRC Connection Re-establishment is active this timer also supervises the Context Fetch procedure.

The timeout time for receiving HANDOVER CANCEL ACKNOWLEDGE after RBS sent HO CANCEL message to MME. Value specifies supervision time of outgoing S1 HO Cancellation according to procedure described in 3GPP TS 36.413 section 8.4.5.

If set to true, any time and phase synchronization accuracy-dependent feature is deactivated or degraded if its time and phase synchronization accuracy is not fulfilled.

The targeted maximum allowed time between scheduling occasions of an UL bearer. A bearer that is not scheduled within the specified time is given higher priority. Value 0 means that the higher priority is never applied. It is recommended to set the value $\leq$ than the PDB. A value that is set too low can affect other services with higher priority.

This parameter indicates if two way relations shall be setup during X2 setup and eNB configuration. The RBS creates a two-way relation for each entry in the received neighbour information that contains a relation to a source cell. Neighbour information is sent in X2 setup and eNB configuration. Neighbour information is eUtranCellRelations per source cell from the sending node.

Temporary attributes are intended as temporary solutions. Their usage can vary depending on the installed software. It is strongly recommended to only set the attributes that correspond to a desired functionality and leave all other temporary attributes set to default value. Information in the descriptions about what attributes are in use can be overridden by the information in CPI documents. Note that a later release can use another attribute to control functionality previously provided by a temporary attribute, or can remove functionality altogether. In these cases, the change is documented in the NIR.

Specifies presence of the following IEs:

- ac-BarringInfo
- ssac-BarringForMMTEL-Voice-r9
- ssac-BarringForMMTEL-Video-r9
- ac-BarringForCSFB-r10
- ac-BarringSkipForMMTELVoice-r12
- ac-BarringSkipForMMTELVideo-r12
- ac-BarringSkipForSMS-r12 in SIB2

Presence of IE ac-BarringForCSFB-r10 in SIB2.

Presence of IE ssac-BarringForMMTEL-Video-r9 in SIB2.

Presence of IE ssac-BarringForMMTEL-Voice-r9 in SIB2.

Presence of IE ac-BarringForMO-Data in SIB2.

Presence of IE ac-BarringForMO-Signalling in SIB2.

Priority Level of CSFB Access Class used by Progressive Access Barring algorithm.

Priority Level of MMTEL Video Access Class used by Progressive Access Barring algorithm.

Priority Level of MMTEL Voice Access Class used by Progressive Access Barring algorithm.

Priority Level of MO Data Access Class used by Progressive Access Barring algorithm.

Priority Level of MO Signaling Access Class used by Progressive Access Barring algorithm.

Indicates whether or not access attempts for MMTEL video from UEs are to skip Access Class Barring functionality.

Indicates whether or not access attempts for MMTEL voice from UEs are to skip Access Class Barring functionality.

Indicates whether or not access attempts for SMS over SGs or SMS over IP from UEs are to skip Access Class Barring functionality.

Threshold in terms of number of remaining SR resources available for the cell. Below this threshold, allocTimerPucchFormat1 for allocation of an additional PUCCH format 1 PRB pair is triggered. Occurs if feature Dynamic PUCCH is activated. Value 0 means the dynamic PUCCH allocation/deallocation operation for this cell is disabled.

A guard time. After this time, a PUCCH format 1 PRB pair is allocated if threshold allocThrPucchFormat1 is still passed.

The pathloss compensation factor for power control of the Physical Uplink Shared Channel (PUSCH).

Threshold used to help identify data-aware UL scheduling UEs. If $BSR \geq bsrThreshold$, UE becomes candidate UE for UL improvement.

Threshold number of SCells configured by Carrier Aggregation (CA) users with this cell as PCell. When number of SCells configured for UEs connected in this PCell is higher than caPrioThreshold, following rules apply:

- For Configurable SCell Priority, all frequency carriers configured for CA are assumed to have equal priority regardless of configured values.
- For Global SCell Evaluation, all SCell relations from PCell are handled equally regardless of threshold for number of SCell UEs.

Highest allowed control channel element radio resource utilization ratio for admission of a non-privileged UE. Resource utilization is checked against this threshold for all new, re-established, or incoming handover RRC connections.

Highest allowed control channel element radio resource utilization ratio for admission of a new non-privileged UE. Resource utilization is checked against this threshold for all new RRC connections.

Indicates if the cell is barred and should not be accessible to random UEs.

Maximum value for the estimated cell capacity.

Minimum value for the estimated cell capacity.

Write protection that prevents feature Automated Cell Capacity Estimation from changing the value on parameters cellCapMinCellSubCap and cellCapMaxCellSubCap.

If set to true, feature Automated Cell Capacity Estimation cannot reset cellCapMinCellSubCap and cellCapMaxCellSubCap at cell unlock.

If set to false, feature Automated Cell Capacity Estimation can change cellCapMinCellSubCap and cellCapMaxCellSubCap at cell unlock.

Normalized downlink cell capacity available for use by carrier aggregation. The value is used to calculate the aggregated capacity of a UE's possible aggregation possibilities, for example by the CA Aware IFLB feature.

Defines the maximum distance from the base station where a connection to a UE can be setup and/or maintained.

Normalized subscription capacity of the cell. The value represents the total capacity of the cell used for traffic load balancing purposes.

This parameter controls if Contention Free Random Access (CFRA, known as non-contention based random access in 3GPP term) shall be enabled or not. When enabled, a portion of random access preambles should be allocated for CFRA and CFRA can be used for incoming HO and PDCCH ordered uplink re-sync.

Determines the number of Channel Selection (CS) PUCCH resources in a CS set.

Set to 1 when all SCell candidates are configured with transmission mode 1 or 2. Set to 2 when at least one SCell candidate is configured with transmission mode 3 or higher.

Indicates the lower limit value of cellIndividualOffsetEUTran range that the SON function is allowed to adjust.

Indicates the upper limit value of cellIndividualOffsetEUTran range that the SON function is allowed to adjust.

Common SR periodicity, used for all UEs.

Sets the DL power of the Cell specific Reference Signal (CRS) relatively a reference level defined by the power of the PDSCH type A resource elements. If crsGain is +3dB, the CRS power is 3dB higher than that of a PDSCH type A resource element.

The settings crsGain=4.77db and 6dB are mapped to 3dB. These settings are not supported.

PDSCH type A resource elements are located in symbols that do not contain CRS.

Threshold in terms of number of remaining SR resources available for the cell. Above this threshold, deallocTimerPucchFormat1 for deallocation of a PUCCH format 1 PRB pair is triggered. Occurs if feature Dynamic PUCCH is activated.

A guard time. After this time, a PUCCH format 1 PRB pair is deallocated if threshold deallocThrPucchFormat1 is still passed.

Enable or disable 256 QAM support in DL.

Turns on/off Configurable DL BLER Target.

Highest allowed DL radio resource utilization ratio for admission of a non-privileged UE. Applies to each DL resource considered by Dynamic UE Admission Control. Resource utilization is checked against this threshold for all new, re-established, or incoming handover RRC connections.

Highest allowed DL radio resource utilization ratio for admission of a new non-privileged UE. Applies to each DL resource considered by Dynamic UE Admission Control. Resource utilization is checked against this threshold for all new RRC connections.

Specifies if the downlink interference management is enabled or disabled.

Time constant of the exponential-weighted moving average filter applied to the radio resource utilization ratios considered by Dynamic UE Admission Control.

Long DRX cycle for ELC. Value of `elcLongDrxCycle` is in number of sub-frames.

Enable/disable service-specific HARQ on cell level. Function must have valid license.

Scaling factor for the estimated cell subscription capacity. Can be used to reduce the traffic load balancing attraction of the cell. Used if traffic handling capacity of the cell is constrained by circumstances the ACCE feature is unable to capture. An example of such a circumstance is at limited UL capacity in a TDD cell.

When the attribute is value is set to 0, the corresponding cell uses the value `cellSubscriptionCapacity` as the Cell Subscription Capacity value for the cell. This bypasses the automatically estimated Cell Subscription Capacity value for the cell.

Offset used when `tReorderingDL` is calculated by automatic configuration. $tReorderingDL = 'Max\ number\ of\ HARQ\ for\ DL' * HARQ\text{-}interval + harqOffsetDL$.

Offset used when `tReorderingUL` is calculated by automatic configuration. $tReorderingUL = 'Max\ number\ of\ HARQ\ for\ UL' * HARQ\text{-}interval + harqOffsetUL$.

The absolute threshold value for adjusted handover failure rate required to adjust handover parameters.

The permillage threshold value for adjusted handover failure rate required to adjust handover parameters.

The minimal number of handovers required by the handover optimization function before adjusting handover parameters.

The operational cycle of the handover optimization function.

Indicates if the cell is operated with downlink only and with no uplink.

The fraction of non-qualified UEs at UE selection for throughput aware load balancing. In case throughput aware UE selection is enabled, this parameter sets a target size for the fraction of UE to be disqualified for load balancing due to insufficient relative gain when moving UE from source to target cell.

Special value 0 means that the throughput aware UE selection for this cell is disabled.

The minimum threshold for the relative gain at throughput aware load balancing. A negative value may allow for some throughput loss for the individual UE, if the load balancing criteria requires so. Higher values may increase the fraction of non-qualified UEs at UE selection for throughput aware load balancing and may cause the load balancing to stall.

Special value -100 means the lower boundary for the threshold is disabled.

How fast the Access Class Barring probability is decreased, that is how fast `acBarringFactor` in SIB2 is increased when the cell load is decreased.

How fast the Access Class Barring probability is increased, that is how fast `acBarringFactor` in SIB2 is decreased when the cell load is increased.

Minimum barring factor for Load-Based Access Barring algorithm or priority level 0 for one of the following algorithms:

- Progressive Access Barring
- Progressive Barring of Special Access Classes
- PLMN-Specific Access Barring

Priority level 1 minimum barring factor for one of the following algorithms:

- Progressive Access Barring
- Progressive Barring of Special Access Classes
- PLMN-Specific Access Barring

Priority level 2 minimum barring factor for one of the following algorithms:

- Progressive Access Barring
- Progressive Barring of Special Access Classes
- PLMN-Specific Access Barring

Minimum time for how often the acBarringFactor in SIB2 can be changed.

RRC Connection Reject Ratio threshold above which Load-Based Access Barring increases access class barring probability or Progressive Access Barring, or PLMN-Specific Access Barring proceeds to higher priority.

RRC Connection Reject Ratio threshold below which Load-Based Access Barring decreases access class barring probability or Progressive Access Barring, or PLMN-Specific Access Barring recedes to lower priority.

Time period to measure RRC Connection Reject Ratio against threshold lBabThreshRejectRateHigh.

Time period to measure RRC Connection Reject Ratio against threshold lBabThreshRejectRateLow.

Enables additional spectrum emission requirements for CA according to 3GPP TS 36.101, table 6.2.4A-1.

The number of channel selection PUCCH resource sets (CS sets) to reserve in each cell for secondary cell HARQ feedback. To conserve PUCCH resource, this attribute can be set to 0 if the cell is not used as PCell for Carrier Aggregation.

The number of Channel Quality Indicator (CQI) resources available on the PUCCH channel.
For 1.4 MHz system bandwidth the recommended value is 50.

Number of PUCCH Format 3 PRB pairs.

Number of data-aware UL-scheduling UEs that can be improved at allocation of PDCCH and PUSCH.

Repetition rate of UL sparse grants that are eNodeB-triggered to Out Of Coverage (OOC) UEs.

Threshold for when UE is considered to be Out Of Coverage (OOC). If the number of OOC trigger events is greater than or equal to the threshold, the UE is in the OOC state; if the number of OOC trigger events is less than the threshold, the UE is not in the OOC state.

The nominal component of the UE transmit power for Physical Uplink Control Channel (PUCCH).

The nominal component of the UE transmit power for Physical Uplink Shared Channel (PUSCH).

Controls the CFI (Control Format Indicator) used for the control region. `cfiMode` maps to CFI as described under enumerations. For DL BW of 1400 kHz, values of CFI = 1, 2 and 3 map to 2, 3, and 4 control region symbols respectively. Other BW, CFI maps directly to number of control region symbols.

Initial value for PDCCH outer loop adjustment for UEs that do not have a secondary cell configured and do not have any bearer mapped to a QCI with serviceType of VoIP or PTT. In TDD, this parameter applies only to UEs configured with HARQ-ACK bundling.

Initial value for primary cell PDCCH outer loop adjustment in case of carrier aggregation. This applies to UEs that have at least one secondary cell configured and do not have a bearer mapped to a QCI with serviceType of VoIP or PTT. In TDD, this parameter is not used.

Initial value for PDCCH outer loop adjustment for UEs with any bearer mapped to a QCI with serviceType VoIP or PTT. In TDD, this parameter applies only to UEs which are configured with HARQ-ACK bundling.

PDCCH outer loop up step size for UEs that do not have any secondary cell configured and do not have a bearer mapped to a QCI with serviceType of VoIP or PTT. In TDD, this parameter applies only to UEs configured with HARQ-ACK bundling.

PDCCH outer loop up step size for primary cells in case of carrier aggregation. This applies to UEs that have at least one secondary cell configured and do not have any bearer mapped to a QCI with serviceType of VoIP or PTT. In TDD, this parameter is not used.

PDCCH outer loop up step size for UEs with any bearer mapped to a QCI with serviceType VoIP or PTT. In TDD, this parameter applies only to UEs which are configured with HARQ-ACK bundling.

Maximum power boost applied to UE-specific PDCCHs that require more CCEs than the maximum available CCE aggregation level. If UE-specific PDCCHs require equal or less, an automatic power boost algorithm is applied. Attribute `pdccchPowerBoostMax` does not affect those PDCCHs.

If set to 0, there is no PDCCH power boost of the maximum CCE aggregation level. PDCCH coverage is not increased but the feature still optimizes the PDCCH power setting for PDCCHs that require equal or less CCEs than the maximum CCE aggregation level. This still allows for higher PDCCH capacity.

PDCCH target error rate for UEs that do not have any secondary cell configured and do not have any bearer mapped to a QCI with serviceType of VoIP or PTT. In TDD, this parameter applies only to UEs which are configured with HARQ-ACK bundling.

PDCCH target error rate for primary cells in case of carrier aggregation. This applies to UEs that have at least one secondary cell configured and do not have any bearer mapped to a QCI with serviceType of VoIP or PTT. In TDD, this parameter is not used.

PDCCH target error rate for UEs with any bearer mapped to a QCI with serviceType VoIP or PTT. In TDD, this parameter applies only to UEs which are configured with HARQ-ACK bundling.

Sets the DL power of the PDSCH type B resource elements relatively the PDSCH type A resource elements. Values pdschTypeBGain=(0,1,2,3) define the gains (5/4,1,3/4,1/2) respectively, corresponding to the multi-antenna scenario specified in 3GPP TS 36.213.

Example: If the pdschTypeBGain is 3 (gain=1/2), the power of the PDSCH type B resource elements is a factor 1/ 2 of the power of the PDSCH type A resource elements.

PDSCH type A resource elements are located in symbols that do not contain cell specific reference signals (CRS). PDSCH type B resource elements are located in symbols that contain CRS.

Initial preamble power value in dBm, according to 3GPP specification 36.331 and 36.321.

Power offset to the target-received PUSCH Power Spectral Density (PSD) for 64-QAM-capable UEs. Used to control the received SINR target.
It is used to enable maximum throughput for 64QAM, which in some configurations is not possible otherwise, see dependencies.

Specifies the minimum required quality level (RSRQ) in the cell in dB.

Corresponds to Qqualmin in TS 36.304, sent in SIB1. Value 0 means that it is not sent and UE applies in such case the (default) value of negative infinity for Qqualmin.

The required minimum received Reference Symbol Received Power (RSRP) level in the E-UTRA frequency for cell reselection. Corresponds to parameter Qrxlevmin in 3GPP TS 36.304. This attribute is broadcast in SIB1.

Defines how many dB higher than the original SR detection threshold can be used as high SR detection threshold. Used together with srProcessingLevel to reduce false SR detection.

Defines how many SRs eNodeB must receive in a row in order to process it. Used together with srDetectHighThres to reduce false SR detection.

Specifies the threshold when inter-frequency and inter RAT measurements are required.

Corresponds to SNonIntraSearchP in TS 36.304

Value 1000 means that the parameter is not present in System Information Block 3 and the UE applies the default value of infinity for SNonIntraSearchP.

Parameter "SnonIntraSearchP" in TS 36.304. See descriptions under s-NonIntraSearch.

s-NonIntraSearchQ-r9

Parameter "SnonIntraSearchQ" in TS 36.304. If the field is not present, the UE applies the (default) value of 0 dB for SnonIntraSearch.

Enables sending of sNonIntraSearch v920 parameters in SIB3

Parameter "ThreshServing, LowQ" in TS 36.304.

Value 1000 means the parameter is not included in system information.

Enable automatic configuration of tReorderingDL and tReorderingUL. Configuration is based on HARQ-interval together with an offset defined by $\text{harqOffsetDL/harqOffsetUL.tReordering} \geq \text{'Max number of HARQ'} * \text{HARQ-interval} + \text{harqOffset}$, where closest higher or equal allowed value is used.

This configuration is only applied to UM bearers. AM bearers will still use tReorderingUL and tReorderingDL from QciProfilePredefined or QciProfileOperatorDefined.

A timer used for supervision and control of uplink synchronization. Special value: 0 means infinity.

Specifies the threshold that the signal strength of the serving cell must be below for cell reselection towards a lower priority Inter-Frequency or Inter-RAT frequency.
Corresponds to ThreshServingLowP in TS 36.304.

Highest allowed UL radio resource utilization ratio for admission of a non-privileged UE. Applies to each UL resource considered by Dynamic UE Admission Control. Resource utilization is checked against this threshold for all new, re-established, or incoming handover RRC connections.

Highest allowed UL radio resource utilization ratio for admission of a new non-privileged UE. Applies to each UL resource considered by Dynamic UE Admission Control. Resource utilization is checked against this threshold for all new RRC connections.

Whether or not UL scheduler is enabled to force allocation of PRBs to Data-Aware, UL-Scheduling UEs last.

Specifies if uplink interference management is enabled or disabled.

Relative priority in initial SCell selection for cells that can be configured with UL Carrier Aggregation. Applicable where several SCells are initially configured simultaneously. Lowest value has highest priority.

Enables feature UL Scheduling Control for Out Of Coverage (OOC) UEs.

Specifies if outgoing uplink-triggered mobility actions are enabled or disabled in the cell.
Used when Uplink-Triggered Inter-Frequency Mobility is enabled. The parameter has effect if Mobility Control in Poor Coverage is enabled and mobCtrlAtPoorCovActive is set to true in the cell.

Whether or not AMO function is allowed. Used to turn off AMO function on cell relation level.

Following options are possible for coverage area of cell indicated by relation:

- Whether coverage area has approximately same coverage area (overlap) as this cell.
- Whether coverage area fully covers this cell.
- Whether coverage area is fully contained in this cell.

Value influences SCell priority in Dynamic SCell Selection for Carrier Aggregation.

Indicates if the Automated Neighbor Relations (ANR) function is allowed to remove this object. It does not restrict operator removal of the object. Objects created by ANR have this parameter set to true initially.

Specifies if the feature Best Neighbor Relations for Intra-LTE Load Management is allowed to automatically change the loadBalancing attribute for this EUTRAN cell relation.

Determines if the cell relation has high hitRate towards the source cell.

The attribute is automatically updated when the feature Overlaid Cell Detection is operable.

This attribute indicates whether Inter-Frequency Load Balancing is ALLOWED or NOT_ALLOWED or if Inter-Frequency Offload shall be applied from the current cell to the cell indicated by the cell relation.

SCell candidate status.

The value indicates whether the cell indicated by parameter cellrelation can be used as SCell for UEs using this cell as their PCell. The SCell can be either local to the eNodeB, or on a remote eNodeB.

Used for selecting an SCell within a frequency carrier. The SCell with highest priority is selected during initial blind SCell selection. 0 means lowest priority. -1 means the cell is excluded from blind SCell selection.

Presence of IE ac-BarringForCSFB-r10 in SIB2.

Presence of IE ssac-BarringForMMTEL-Video-r9 in SIB2.

Presence of IE ssac-BarringForMMTEL-Voice-r9 in SIB2.

Presence of IE ac-BarringForMO-Data in SIB2.

Presence of IE ac-BarringForMO-Signalling in SIB2.

Priority Level of CSFB Access Class used by Progressive Access Barring algorithm.

Priority Level of MMTEL Video Access Class used by Progressive Access Barring algorithm.

Priority Level of MMTEL Voice Access Class used by Progressive Access Barring algorithm.

Priority Level of MO Data Access Class used by Progressive Access Barring algorithm.

Priority Level of MO Signaling Access Class used by Progressive Access Barring algorithm.

Threshold used to help identify data-aware UL scheduling UEs. If $BSR \geq bsrThreshold$, UE becomes candidate UE for UL improvement.

Threshold number of SCells configured by Carrier Aggregation (CA) users with this cell as PCell. When number of SCells configured for UEs connected in this PCell is higher than $caPrioThreshold$, following rules apply:

- For Configurable SCell Priority, all frequency carriers configured for CA are assumed to have equal priority regardless of configured values.
- For Global SCell Evaluation, all SCell relations from PCell are handled equally regardless of threshold for number of SCell UEs.

Normalized subscription capacity of the cell. The value represents the total capacity of the cell used for traffic load balancing purposes.

Indicates the lower limit value of $cellIndividualOffsetEUTran$ range that the SON function is allowed to adjust.

Indicates the upper limit value of $cellIndividualOffsetEUTran$ range that the SON function is allowed to adjust.

Enable or disable 256 QAM support in DL.

Turns on/off Configurable DL BLER Target.

Long DRX cycle for ELC. Value of $elcLongDrxCycle$ is in number of sub-frames.

Enable/disable service-specific HARQ on cell level. Function must have valid license.

Scaling factor for the estimated cell subscription capacity. Can be used to reduce the traffic load balancing attraction of the cell. Used if traffic handling capacity of the cell is constrained by circumstances the ACCE feature is unable to capture. An example of such a circumstance is at limited UL capacity in a TDD cell.

When the attribute is value is set to 0, the corresponding cell uses the value $cellSubscriptionCapacity$ as the Cell Subscription Capacity value for the cell. This bypasses the automatically estimated Cell Subscription Capacity value for the cell.

Offset used when $tReorderingDL$ is calculated by automatic configuration. $tReorderingDL = 'Max\ number\ of\ HARQ\ for\ DL' * HARQ\ interval + harqOffsetDL$.

Offset used when $tReorderingUL$ is calculated by automatic configuration. $tReorderingUL = 'Max\ number\ of\ HARQ\ for\ UL' * HARQ\ interval + harqOffsetUL$.

The absolute threshold value for adjusted handover failure rate required to adjust handover parameters.

The permillage threshold value for adjusted handover failure rate required to adjust handover parameters.

The minimal number of handovers required by the handover optimization function before adjusting handover parameters.

The operational cycle of the handover optimization function.

How fast the Access Class Barring probability is decreased, that is how fast acBarringFactor in SIB2 is increased when the cell load is decreased.

How fast the Access Class Barring probability is increased, that is how fast acBarringFactor in SIB2 is decreased when the cell load is increased.

Minimum barring factor for Load-Based Access Barring algorithm or priority level 0 for one of the following algorithms:

- Progressive Access Barring
- Progressive Barring of Special Access Classes
- PLMN-Specific Access Barring

Priority level 1 minimum barring factor for one of the following algorithms:

- Progressive Access Barring
- Progressive Barring of Special Access Classes
- PLMN-Specific Access Barring

Priority level 2 minimum barring factor for one of the following algorithms:

- Progressive Access Barring
- Progressive Barring of Special Access Classes
- PLMN-Specific Access Barring

Minimum time for how often the acBarringFactor in SIB2 can be changed.

RRC Connection Reject Ratio threshold above which Load-Based Access Barring increases access class barring probability or Progressive Access Barring, or PLMN-Specific Access Barring proceeds to higher priority.

RRC Connection Reject Ratio threshold below which Load-Based Access Barring decreases access class barring probability or Progressive Access Barring, or PLMN-Specific Access Barring recedes to lower priority.

Time period to measure RRC Connection Reject Ratio against threshold lBabThreshRejectRateHigh.

Time period to measure RRC Connection Reject Ratio against threshold lBabThreshRejectRateLow.

The number of channel selection PUCCH resource sets (CS sets) to reserve in each cell for secondary cell HARQ feedback. To conserve PUCCH resource, this attribute can be set to 0 if the cell is not used as PCell for Carrier Aggregation.

The number of Channel Quality Indicator (CQI) resources available on the PUCCH channel.
For TDD Subframe Assignment 1 the recommended value is 64.

Number of PUCCH Format 3 PRB pairs.

Number of data-aware UL-scheduling UEs that can be improved at allocation of PDCCH and PUSCH.

Repetition rate of UL sparse grants that are eNodeB-triggered to Out Of Coverage (OOC) UEs.

Threshold for when UE is considered to be Out Of Coverage (OOC). If the number of OOC trigger events is greater than or equal to the threshold, the UE is in the OOC state; if the number of OOC trigger events is less than the threshold, the UE is not in the OOC state.

Specifies the threshold when inter-frequency and inter RAT measurements are required.

Corresponds to SNonIntraSearchP in TS 36.304

Value 1000 means that the parameter is not present in System Information Block 3 and the UE applies the default value of infinity for SNonIntraSearchP.

Parameter "SnonIntraSearchP" in TS 36.304. See descriptions under s-NonIntraSearch.

s-NonIntraSearchQ-r9

Parameter "SnonIntraSearchQ" in TS 36.304. If the field is not present, the UE applies the (default) value of 0 dB for SnonIntraSearch.

Enables sending of sNonIntraSearch v920 parameters in SIB3

Parameter "ThreshServing, LowQ" in TS 36.304.

Value 1000 means the parameter is not included in system information.

Enable automatic configuration of tReorderingDL and tReorderingUL. Configuration is based on HARQ-interval together with an offset defined by $\text{harqOffsetDL/harqOffsetUL.tReordering} \geq \text{'Max number of HARQ'} * \text{HARQ-interval} + \text{harqOffset}$, where closest higher or equal allowed value is used.

This configuration is only applied to UM bearers. AM bearers will still use tReorderingUL and tReorderingDL from QciProfilePredefined or QciProfileOperatorDefined.

A timer used for supervision and control of uplink synchronization. Special value: 0 means infinity.

Whether or not UL scheduler is enabled to force allocation of PRBs to Data-Aware, UL-Scheduling UEs last.

Enables feature UL Scheduling Control for Out Of Coverage (OOC) UEs.

Specifies if outgoing uplink-triggered mobility actions are enabled or disabled in the cell.

Used when Uplink-Triggered Inter-Frequency Mobility is enabled. The parameter has effect if Mobility Control in Poor Coverage is enabled and mobCtrlAtPoorCovActive is set to true in the cell.

The maximum allowed measurement bandwidth on a carrier frequency.

Note: The values indicate the number of resource blocks and correspond to the channel bandwidth 1,4MHz, 3MHz, 5MHz, 10MHz, 15MHz, 20MHz respectively specified in 3GPP TS 36.104.

Whether or not AMO function is allowed. Used to turn off AMO function on frequency relation level.

ANR performs measurement on the referenced frequency if this parameter is set to true. Otherwise, ANR does not perform any measurements on this frequency.

Prioritizes EUTRAN frequency carriers from which to pick SCells for carrier aggregation. 0 means lowest priority. -1 means the frequency is excluded from SCell selection.

In conjunction with caPrioThreshold the value sets a threshold for the number of SCells on this frequency carrier that can be configured using prioritized SCell selection. A normalized value is applied. When frequency carriers have same priority, SCells are selected on the carrier with the lowest proportional SCell utilization.

Parameter used to specify whether or not CA triggered redirection is activated from the current cell towards a certain frequency.

Absolute priority of carrier frequency used by cell reselection procedure. Corresponds to parameter priority in 3GPP TS 36.304, Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) procedures in idle mode.

Value 0 means lowest priority. UE behavior when no value is entered is specified in 3GPP TS 36.304.
Value -1 means frequency is excluded from SIB5 and IdleModeMobilityControlInfo.

The type of event based measurements used for inter-frequency LTE measurements when the measurements are uplink triggered.

The frequency-relation specific offset for the absolute threshold a5Threshold1Rsrp, RSRP threshold1 for event A5, used for Inter-frequency load balancing.

The minimum target cell load (subscription ratio) the source cell takes into account when determining the amount of load balancing action to a cell using this carrier frequency.

Specifies the policy for updating the loadBalancing attribute by the feature Best Neighbor Relations for Intra-LTE Load Management. The policy is valid for all cell relations corresponding to this EUTranFreqRelation.

The threshold used by the UE when reselecting towards the higher priority frequency X from the current serving frequency. Each frequency of E-UTRAN can have a specific threshold. Refer to the parameter Thresx,high in 3GPP TS 36.304.

The threshold used in reselection towards frequency X priority from a higher priority frequency. Each frequency of E-UTRAN can have a specific threshold. Corresponds to parameter Thresx,low in 3GPP TS 36.304.

Scaling factor for SCell subscription capacity. Used to decrease CA attraction of cells belonging to indicated eNodeB if cell is used as external SCell for CA.

Configures whether uplink triggered handover is allowed to this external eNodeB or not. This parameter has only effect if no X2 interface is configured or the external node does not support the ULTRIG feature.

Indicates if the Automated Neighbor Relations (ANR) function is allowed to remove this object. The setting does not restrict operator removal of the object. Objects created by ANR have this attribute set to true initially.

Indicates if the Automated Neighbor Relations (ANR) function is allowed to remove this object. It does not restrict operator removal of the object. Objects created by ANR have this parameter set to true initially.

ANR performs measurement on the referenced frequency if this parameter is set to true. Otherwise, ANR does not perform any measurements on this frequency.

Absolute priority of the radio access technology. 0 means lowest priority. Corresponds to parameter priority in 3GPP TS 36.304.

Threshold value for when the distribution model at high load is used.

Threshold value for when the distribution model at low load is used.

Threshold value for when the distribution model at low-medium load is used.

Threshold value for when the distribution model at medium-high load is used.

Threshold value for when the distribution model at medium load is used.

If set to true, 320ms long DRX cycle is configured to ELC UE.

Capacity related hysteresis value considered when checking the capacity criterion for both load balancing of CA capable UEs and CA triggered redirection.

The maximum load in the target cell in order to redirect a CA capable UE to that target cell. The maximum load in the current cell in order to apply the capacity criterion when load balancing a CA capable UE.

The maximum load (subscription ratio) difference taken into account in load balancing action.

The maximum load difference between the target cell and the source cell in order to redirect a CA capable UE to that target cell. The maximum load difference between the source cell and the target cell in order to apply the capacity criterion when load balancing a CA capable UE.

EUTRAN cell relations with a lbHitRate value greater than this threshold are considered suitable for load management.

Specifies the number of UE measurements for lbHitRate estimation (per cell and Load Balancing cycle) for each E-UTRAN frequency.

Specifies the required minimum number of connected users in the (source) cell to allow initiation of UE measurements for lbHitRate estimation on E-UTRAN frequencies.

EUTRAN cell relations with a lbHitRate value lower than this threshold are NOT considered suitable for load management.

Scaling factor for the required number of UE candidates needed for load balancing measurements to meet the load balancing target.

Note: The minimum value of the attribute is internally limited to 10.

Coefficient of rate-dependent load balancing offset. Moderates how much the load balancing must be offset towards a cell with higher capacity.

Specifies the threshold for the source and target cell average load, above which the rate offset is set to zero.

The minimum load (subscription ratio) difference to trigger load balancing action.

Timer to initiate evaluation of a UE for load balancing measurement. The timer is started at UE Context Setup. If value = 0 the timer is not started, and UEs will only be evaluated for load balancing measurement at UE Context Setup.

Used to calculate the number and position of Paging Occasions (PO) and Paging Frames (PF).

The numerical value of nB depends on the value of the defaultPagingCycle (T) and can be set to one of the following values:
 $4T, 2T, T, T/2, T/4, T/8, T/16, T/32$.

When nB is set to $T, 2T$ or $4T$, it determines the number of POs per PF, and the PO position in PF.

When nB is set to a value smaller than T , it affects the System Frame Number of the PF, the position of PO in the PF, and also distribution of UE into groups with the same PF.

When nB is set to smaller value, amount of groups is smaller, but amount of UEs inside each groups is larger. When nB is set to a larger value, amount of groups is larger but amount of UEs inside each groups is smaller.

If categoryMAccess is enabled and $nBBr$ is set to the default value (NOT_PRESENT) then further restrictions apply. If highestSupportedCeLevelBr = 0 then nB should be selected from the following available options ($T, T/2, T/4, T/8, T/16, T/32$) due to the half duplex nature of Cat-M devices. If highestSupportedCeLevelBr = 1 then nB should be selected from the following available options ($T/8, T/16, T/32$) due to repetitions.

Indicates if the data radio bearer is subject to Absolute Priority Override.

The contribution from eNodeB to the Packet Delay Budget (PDB) for a QCI. Packet delays outside eNodeB e.g. in the transport network are excluded. For more information about PDB refer to TS 23.203

Decimal part of QCI-related priority.
Fractional part of priority is defined by priorityFraction attribute.

Fractional part of QCI-related priority.
Decimal part of priority is defined by priority attribute.

Specifies which scheduling algorithm is to be used for a certain QCI.

Indicates the service that the bearer is used for.
ServiceType PTT and MC_SIGNALING cannot be set on QciProfileOperatorDefined MO.

Indicates if the data radio bearer is subject to Absolute Priority Override.

The contribution from eNodeB to the Packet Delay Budget (PDB) for a QCI. Packet delays outside eNodeB e.g. in the transport network are excluded. For more information about PDB refer to TS 23.203.

Decimal part of QCI-related priority.
Fractional part of priority is defined by priorityFraction attribute.

Fractional part of QCI-related priority.
Decimal part of priority is defined by priority attribute.
Specifies which scheduling algorithm is to be used for a certain QCI.

Indicates the service that the bearer is used for.

The time a UE can be inactive before it is released.

86400s = 24 hours

Special values:
0 is used to turn off the use of this timer. This means that a UE will not be released due to inactivity.

Offset to obtain the Hysteresis for A5 measurement for trigger quantity RSRQ. $\text{hysteresisA5Rsrq} = \text{hysteresisA5} + \text{hysteresisA5RsrqOffset}$

Time-to-trigger value for event A5 with trigger quantity RSRQ. If set to -1, this attribute is not used for report configuration.

This parameter together with a5Threshold1Rsrp specifies "The Reference Signal Received Power (RSRP) threshold1 value for eventA5." . The equation for calculating the RSRP threshold1 value for ANR is $\text{a5Threshold1Rsrp} + \text{a5Threshold1RsrpAnrDelta}$. Only used if triggerQuantityA5 onReportConfigA5 MO is set to RSRP.

This parameter together with a5Threshold1Rsrq specifies "The Reference Signal Received Quality (RSRQ) threshold1 value for eventA5." . The equation for calculating the RSRQ threshold1 value for ANR is $\text{a5Threshold1Rsrq} + \text{a5Threshold1RsrqAnrDelta}$. Only used if triggerQuantityA5 onReportConfigA5 MO is set to RSRQ.

This parameter together with `a5Threshold2Rsrp` specifies "The Reference Signal Received Power (RSRP) threshold2 value for eventA5." . The equation for calculating the RSRP threshold2 value for ANR is $a5Threshold2Rsrp - a5Threshold2RsrpAnrDelta$. Only used if `triggerQuantityA5` on `ReportConfigA5` MO is set to RSRP.

This parameter together with `a5Threshold2Rsrq` specifies "The Reference Signal Received Quality (RSRQ) threshold2 value for eventA5." . The equation for calculating the RSRQ threshold2 value for ANR is $a5Threshold2Rsrq - a5Threshold2RsrqAnrDelta$. Only used if `triggerQuantityA5` on `ReportConfigA5` MO is set to RSRQ.

The hysteresis value for the eventA5 measurement.

The time-to-trigger value for the eventA5 measurement.

The Reference Signal Received Power (RSRP) threshold2 value for eventA5.

The hysteresis value for the eventA5.

The interval for event triggered periodical reporting for A5 event.

Time-to-trigger value for event A5.

Offset to obtain the Hysteresis for B2 measurement for trigger quantity RSRQ. $hysteresisB2Rsrq = hysteresisB2 + hysteresisB2RsrqOffset$

Time-to-trigger value for event B2 with trigger quantity RSRQ. If set to -1, attribute is not used for report configuration.

Offset to obtain the Hysteresis for B2 measurement for trigger quantity RSRQ. $hysteresisB2Rsrq = hysteresisB2 + hysteresisB2RsrqOffset$

Time-to-trigger value for event B2 with trigger quantity RSRQ. If set to -1, attribute is not used for report configuration.

The Signal Quality in the ThresholdGERAN, threshold2 value for eventB2.

The hysteresis value for the event B2.

The interval for event triggered periodical reporting for B2 event.

Time-to-trigger value for event B2.

Offset to obtain the Hysteresis for B2 measurement for trigger quantity RSRQ. $\text{hysteresisB2Rsrq} = \text{hysteresisB2} + \text{hysteresisB2RsrqOffset}$

Time-to-trigger value for event B2 with trigger quantity RSRQ. If set to -1, this attribute is not used for report configuration.

Ratio of energy per modulation bit to noise spectral density in the ThresholdUTRA, threshold2 value for eventB2.

Not applicable for UTRA TDD.

Used when UeMeasControl::measQuantityUtraFDD is set to ECNO.

Received Signal Code Power in the ThresholdUTRA, threshold2 value for eventB2.

Also present for UTRA TDD.

Used when UeMeasControl::measQuantityUtraFDD is set to RSCP.

The hysteresis value for the event B2.

The interval for event triggered periodical reporting for B2 event.

Time-to-trigger value for event B2.

The offset value for eventA3.

The time-to-trigger value for eventA3.

The offset value for eventA3. Dependent on triggerQuantityA3 on MO ReportConfigEutraBestCell and is a delta towards a3offset on triggerQuantityA3, The a3offset used in the ANR measure is calculated as a3offset (on ReportConfigEutraBestCell) - a3offset AnrDelta

The hysteresis value for eventA3.

The time to trigger value for eventA3.

Offset to obtain the A3Offset for inter-frequency A3 measurement for trigger quantity RSRQ. $a3OffsetRsrq = a3offset + a3RsrqOffset$

Offset to obtain the Hysteresis for inter-frequency A3 measurement for trigger quantity RSRQ. $hysteresisA3Rsrq = hysteresisA3 + hysteresisA3RsrqOffset$

Time-to-trigger value for event A3 with trigger quantity RSRQ. If set to -1, this attribute is not used for report configuration.

The Reference Signal Received Power (RSRP) threshold1 value for eventA5.

The Reference Signal Received Power (RSRP) threshold2 value for eventA5.

The Reference Signal Received Quality (RSRQ) threshold2 value for eventA5.

The hysteresis value for the eventA5 measurement.

The Reference Signal Received Power (RSRP) threshold value for events A1 and A2.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

RSRP threshold value for events A1 and A2 below which UL CA is not configured.

The Reference Signal Received Quality (RSRQ) threshold value for events A1 and A2.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The hysteresis value for RSRP in events A1 and A2 measurements for SCell.

Hysteresis value for RSRP in events A1 and A2 measurements below which UL CA is not configured.

The hysteresis value for RSRQ in events A1 and A2 measurements.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The time-to-trigger value for measurement in event A1.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The time-to-trigger value for measurement in event A2.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The quantity that triggers the eventA2 and eventA1 for SCell measurements.

The offset value for event A6.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The hysteresis value for event A6.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The time-to-trigger value for event A6.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The quantity that triggers the event.

Changed value may take effect related to the next SCell configuration during the ongoing connection.

The Reference Signal Received Power (RSRP) threshold value for events A1Search and A2Search.

If Multi-Layer Service Triggered Mobility feature is enabled QCI offsets in QciProfilePredefined configuration is overridden by this feature QCI configuration.

The Reference Signal Received Quality (RSRQ) threshold value for events A1Search and A2Search.

If Multi-Layer Service Triggered Mobility feature is enabled QCI offsets in QciProfilePredefined configuration is overridden by this feature QCI configuration.

UL-normalized SINR max threshold value for events A1 UL and A2 UL search.

Configuring this parameter to a value greater than 320 rarely allows UEs into Uplink Good Coverage zone.

QCI1 offset (used also for QCIs with serviceType PTT or MC_SIGNALING) on cell level for threshold a2CriticalThresholdRsrp and RSRP threshold value for events A2Critical.

QCI1 offset (used also for QCIs with serviceType PTT or MC_SIGNALING) on cell level for threshold a2CriticalThresholdRsrq and RSRQ threshold value for events A2Critical.

RSRQ thresholds are configured in 0.5 dB steps according to 3GPP TS36.331. Use multiples of 5 for this attribute. Other values are rounded down to closest lower multiple of 5.

The Reference Signal Received Power (RSRP) threshold value for event A2Critical.

The Reference Signal Received Quality (RSRQ) threshold value for event A2Critical.

Offset for threshold a1a2SearchThresholdRsrp to configure RSRP threshold value for events A2OuterSearch.

Offset for threshold `a1a2SearchThresholdRsrq` to configure RSRQ threshold value for events `A2OuterSearch`. Note: RSRQ thresholds are configured in 0.5dB steps according to 3GPP TS36.331. Use multiples of 5 for this attribute. Other values are rounded down to the closest lower multiple of 5.

UL-normalized SINR max threshold value for event `A2 UL critical`.

The hysteresis value for RSRP in events `A1Search` and `A2Search` measurements.

The hysteresis value for RSRQ in events `A1Search` and `A2Search` measurements.

Hysteresis value for UL events `A1 UL search` and `A2 UL search` measurements.

The hysteresis value for RSRP in event `A2Critical` measurement.

The hysteresis value for RSRQ in event `A2Critical` measurement.

Hysteresis value for RSRP in events `A2OuterSearch` measurements.

Hysteresis value for RSRQ in events `A2OuterSearch` measurements.

Hysteresis value for UL event `A2 UL critical` measurements.

Inhibit type of `A2Search` Report configuration.

Time-to-trigger value for measurement in event `A1Search`. If `timeToTriggerA1SearchRsrq` is -1, this attribute is used for both RSRP and RSRQ. But if not set to -1, this attribute is used only for RSRP.

Time-to-trigger value for measurement in event `A1Search` with trigger quantity RSRQ. The value -1 means that this attribute is not used for report configuration.

Time-to-trigger value for UL measurement in event `A1 UL search`.

Time-to-trigger value for measurement in event `A2Critical`. If `timeToTriggerA2CriticalRsrq` is -1, this attribute is used for both RSRP and RSRQ. But if not set to -1, this attribute is used only for RSRP.

Time-to-trigger value for measurement in event `A2Critical` with trigger quantity RSRQ. The value -1 means that this attribute is not used for report configuration.

Time-to-trigger value for measurement in event A2OuterSearch. If timeToTriggerA2OutSearchRsrq is -1, this attribute is used for both RSRP and RSRQ. But if not set to -1, this attribute is used only for RSRP.

Time-to-trigger value for measurement in event A2OuterSearch with trigger quantity RSRQ. The value -1 means that this attribute is not used for report configuration.

Time-to-trigger value for measurement in event A2Search. If timeToTriggerA2SearchRsrq is -1, this attribute is used for both RSRP and RSRQ. But if not set to -1, this attribute is used only for RSRP.

Time-to-trigger value for measurement in event A2Search with trigger quantity RSRQ. The value -1 means that this attribute is not used for report configuration.

Time-to-trigger value for UL measurement in event A2 UL critical.

Time-to-trigger value for UL measurement in event A2 UL search.

Maximum number of consecutive "out of sync" indications received from lower layers.

Maximum number of consecutive "in-sync" indications received from lower layers.

UE timer to supervise a response to RRC Connection Reestablishment Request (according to 3GPP TS 36.331), during a radio connection re-establishment procedure. The UE returns to Idle and optionally starts to reconnect over NAS when the timer expires.

Waiting time for radio link failure.
Used by the UE.

UE timer triggered at radio link failure to supervise the period where the UE tries to re-establish the radio connection, either by performing RRC Connection Reestablishment (according to 3GPP TS 36.331), or by finding a suitable cell on another RAT. The UE returns to Idle and optionally starts to reconnect over NAS when the timer expires.

UE timer to supervise a response to RRC Connection Reestablishment Request (according to 3GPP TS 36.331), during a radio connection re-establishment procedure. The UE returns to Idle and optionally starts to reconnect over NAS when the timer expires.
Provided to the UE by System Information.

UE timer to supervise successful handover completion according to 3GPP TS 36.331.

UE timer triggered at radio link failure to supervise the period where the UE tries to re-establish the radio connection, either by performing RRC Connection Reestablishment (according to 3GPP TS 36.331), or by finding a suitable cell on another RAT. The UE returns to Idle and optionally starts to reconnect over NAS when the timer expires.

Provided to the UE by System Information.

A desired radio transmit operating mode, which is tailored to achieve good throughput performance for a given highest modulation in downlink.

Forced additional value for Timing Advance Command in Random Access Response according to 3GPP TS 36.213.

Maximum number RLC re-transmissions in DL before stopping and indicating to RRC that the RLC threshold is reached.

Time lapsed before request for new poll if no STATUS report arrives for the Sequence Number that is contained in the DL RLC Data PDU where the poll bit is set.

Time lapsed before request for new poll if no STATUS report arrives for the Sequence Number that is contained in the UL RLC Data PDU where the poll bit is set.

Maximum number RLC re-transmissions in UL before stopping and indicating to RRC that the RLC threshold is reached.

Enables checking the second value - RSRP or RSRQ - in an A5 Target Good Enough measurement report triggered by RSRQ or RSRP respectively.

If set to true, handover occurs only if both the RSRP_target and RSRQ_target conditions are met. This setting increases the impact of EUTRANFreqRelation::qOffsetFreq, EUTRANCellRelation::cellIndividualOffsetEUTRAN and EUTRANCellRelation::cellIndividualOffsetEUTRANQci1. This is because these offsets appear in both the RSRP and RSRQ equations and they do not have additional offsets to allow independent adjustment for RSRP and RSRQ. Furthermore, RSRQ has a much smaller range than RSRP, so changing these offsets has a bigger impact on RSRQ triggering than on RSRP triggering. It is therefore recommended that these offsets be changed in +/-1dB steps only, as bigger steps can have a severe impact on behavior.

Disables or enables functionality of Level Based Search Zone Transitions. If enabled, eNodeB checks reported RSRP or RSRQ level of A2 Search or A2 Outer Search measurement to trigger measurement and mobility action.

If set, E-UTRA Inter-frequencies must be excluded when eNodeB selects the highest priority frequency at A2Critical.

Disables or enables configuration of B2-RSRQ if event A2Search-RSRQ is triggered when the UE enters the search zone.

Frequency priority threshold to specify the low priority measurement group from connectedModeMobilityPrio or voicePrio in search zone. Those less than this threshold are put in low priority measurement group and can be configured after event A2OuterSearch is triggered from UE.

The number of measurements that can be concurrently performed by the UE on E-UTRA frequencies other than the serving cell frequency.

Maximal value of reports that any UE must provide any system functions, based on periodical measurements, that are used to measure on EUTran, Utran and Geran neighbors.

Special Value: 0 means infinity.

Primary cell (PCell) quality threshold controlling whether or not the UE is required to perform measurements of intra-frequency, inter-frequency and inter-RAT neighboring cells.

Value "0" indicates to disable s-Measure.

Corresponds to s-Measure in TS 36.331.

Time used in feature Mobility Control at Poor Coverage to determine if measured frequencies must be excluded for mobility action at critical threshold.

Special value: 0 means infinity.

If ULTRIG is enabled, timer is also applicable for UL-triggered measurements.

Offset value above a1a2UISearchThreshold that UL SINR in target cell must reach for handover to be allowed. Used when feature Uplink-Triggered Inter-Frequency Mobility is enabled. Configured in target cell.

Activates or deactivates CDMA2000 measurements for mobility purposes when Mobility Control at Poor Coverage feature is enabled.

Activates or deactivates GERAN measurements for mobility and soft lock of cells purposes when feature Mobility Control at Poor Coverage is enabled.

Activates or deactivates EUTRAN inter-frequency measurements for mobility and soft lock of cells purposes when feature Mobility Control at Poor Coverage is enabled.

Activates or deactivates UTRAN measurements for mobility and soft lock of cells purposes when feature Mobility Control at Poor Coverage is enabled.

Offset value above UL SINR in source cell that estimated UL SINR in target cell must reach for handover to be allowed. Used when feature UL-Triggered Inter-Frequency Mobility is enabled. Configured in source cell.

ANR performs measurement on the referenced frequency if this parameter is set to true. Otherwise, ANR does not perform any measurements on this frequency.

The absolute priority of the carrier frequency used by the cell reselection procedure. Corresponds to parameter priority in 3GPP TS 36.304.

Value 0 means lowest priority. The UE behavior when the field is empty if applicable, is specified in 3GPP TS 36.304.

Data Type

int32

enum ActivationVals

int32

int32

int32

int32

int32

int32

enum ActivationVals

int32

int32

int32

int32

int32

boolean
int32

int32

int32

boolean

boolean
boolean
boolean

int32

int32

int32

int32

enum EUtranProbCellPolicyVals

int32

int32

int32

int32

int32

int32

int32

enum ActivationVals

enum ActivationVals

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

boolean

boolean

int32

int32

int32

int32

int32

enum ActivationVals

enum ActivationVals

int32

int32

int32

int32

int32

int32

int32

enum DrxInactivityTimer

enum LongDrxCycle

enum OnDurationTimer

int32

enum CaPreference

int32

int32

enum DynamicSCellSelectionMethod

boolean

boolean

boolean

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum SCellSelectionMode

int32

int32

int32

int32

int32

int32

int32

int32

boolean

int32

boolean

boolean

int32

enum HoNotAllowedMpLoadLevel

boolean

int32

int32

boolean

int32

boolean

int32

boolean

enum AcBarringMode

enum AcBarringMode

enum AcBarringMode

enum AcBarringMode

enum AcBarringMode

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

boolean

boolean

boolean

int32

int32

int32

int32

int32

int32

int32

enum CellBarred

int32

int32

boolean

int32

int32

int32

boolean

int32

int32

int32

int32

int32

int32

int32

boolean

boolean

int32

int32

boolean

int32

enum ElcLongDrxCycle

boolean

int32

int32

int32

int32

int32

int32

int32

boolean

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum NetworkSignallingValueCa

int32

int32

int32

int32

int32

int32

int32

int32

enum CfiMode

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum SrProcessingLevel

int32

int32

int32

boolean

int32

boolean

int32

int32

int32

int32

boolean

boolean
int32

boolean

boolean

boolean
enum SupportedCoverage

boolean

boolean

boolean

enum LoadBalancingVals

enum SCellCandidate

int32

enum AcBarringMode

enum AcBarringMode

enum AcBarringMode

enum AcBarringMode

enum AcBarringMode

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

enum AcBarringPriorityLevel

int32

int32

int32

int32

int32

boolean

boolean

enum ElcLongDrxCycle

boolean

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

boolean

int32

boolean

int32

boolean

boolean

boolean

int32

boolean

boolean

int32

int32

boolean

int32

enum InterFreqMeasType

int32

int32

enum EUtranLbBnrPolicyVals

int32

int32

int32

enum ExternalUITrigHoSupport

boolean

boolean

boolean

int32

int32

int32

int32

int32

int32

boolean
int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum NBValue

enum AbsPrioOverride

int32

int32

int32

enum SchedulingAlgorithm

enum ServiceType

enum AbsPrioOverride

int32

int32

int32

enum SchedulingAlgorithm

enum ServiceType

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum ReportInterval

int32

int32

int32

int32

int32

int32

int32

enum ReportInterval

int32

int32

int32

int32

int32

int32

enum ReportInterval

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum TriggerQuantity

int32

int32

int32

enum TriggerQuantity

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum InhibitA2SearchConfig

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

int32

enum RadioOperatingMode

int32

int32

int32

int32

int32

boolean

boolean

boolean

boolean

int32

int32

int32

int32

int32

int32

boolean

boolean

boolean

boolean

int32

boolean

int32

Range and Values

Default Value

0..1000

750

DEACTIVATED
ACTIVATED

DEACTIVATED

0..1000

500

0..1000

950

0..20000

1000

0..20

1

0..10

4

0..15

7

DEACTIVATED
ACTIVATED

DEACTIVATED

0..1000	500
---------	-----

0..1000	950
---------	-----

0..20000	1000
----------	------

0..1000	1000
---------	------

0..1000	1000
---------	------

0..200	true
	0

0..100	15
--------	----

0..1440	30
---------	----

false

		false true false
1..99		10
1..30		10
2..100		50
1..30		4
OFF AUTO_DETECT AUTO_DETECT_AND_BAR		OFF
0..1000		30

0..10007

0..10007

0..10001

0..100010

0..1000100

0..10005

DEACTIVATED
ACTIVATEDDEACTIVATED

DEACTIVATED
ACTIVATEDACTIVATED

0..100010

0..100020

0..1000100

0..1000

0..100	0
0..1000	10
0..1000	20
0..1000	100
0..100	0
0..100	0
-1440..0	-1150
-1920..0	-1530
	true
	true
0..1000	1
0..1000	10
0..1000	100
0..1000	5

0..1000	20
---------	----

DEACTIVATED	DEACTIVATED
ACTIVATED	
DEACTIVATED	DEACTIVATED
ACTIVATED	
0..1000	20

0..1000	1
---------	---

0..1000	10
---------	----

0..1000	100
---------	-----

0..1000	5
---------	---

-100..100	-10
-----------	-----

-10..10	-1
---------	----

PSF1
PSF2
PSF40
PSF50
PSF60
PSF80
PSF100
PSF200
PSF300
PSF500
PSF750
PSF1280
PSF3
PSF1920
PSF2560
PSF0
PSF4
PSF5
PSF6
PSF8
PSF10
PSF20
PSF30

PSF20

SF10
SF20
SF512
SF640
SF1024
SF1280
SF2048
SF2560
SF32
SF40
SF64
SF80
SF128
SF160
SF256
SF320

SF320

PSF1
PSF2
PSF40
PSF50
PSF60
PSF80
PSF100
PSF200
PSF3
PSF4
PSF5
PSF6
PSF8
PSF10
PSF20
PSF30

PSF5

0..100

50

NONE
DL
UL

NONE

0..10

10

0..65535

65535

ROUND_ROBIN
PRIORITIZED
PRIORITIZED_AUTOMATIC
GLOBAL_EVALUATION

ROUND_ROBIN

false

false

false

-1..5000

100

0..5000

90

0..5000

100

0..5000

90

0..5000

10

0..5000

50

-1..5000 100

0..5000 200

-200..300 0

ACK_SEQUENTIAL_SCELL_SELECTION
UN_ACK_SIMULTANEOUS_SCELL_SELECTION
ACK_SIMULTANEOUS_SCELL_SELECTION
ACK_SEQUENTIAL_SCELL_SELECTION

-1..60000 10000

-1..32000 1000

-1..60000 10000

1..1 2..2 3..3 4..4 6..6 8..8 16..16 32..32 8

5..5 10..10 15..15 20..20 25..25 30..30 35..35 40..40 45..45 50..50 80
55..55 60..60 65..65 70..70 75..75 80..80 85..85 90..90 95..95
100..100 105..105 110..110 115..115 120..120 125..125 130..130
135..135 140..140 145..145 150..150 155..155 160..160 165..165
170..170 175..175 180..180 185..185 190..190 195..195 200..200
205..205 210..210 215..215 220..220 225..225 230..230 235..235
240..240 245..245 250..250 300..300 350..350 400..400 450..450
500..500

5..5 10..10 15..15 20..20 25..25 30..30 35..35 40..40 45..45 50..50 80
55..55 60..60 65..65 70..70 75..75 80..80 85..85 90..90 95..95
100..100 105..105 110..110 115..115 120..120 125..125 130..130
135..135 140..140 145..145 150..150 155..155 160..160 165..165
170..170 175..175 180..180 185..185 190..190 195..195 200..200
205..205 210..210 215..215 220..220 225..225 230..230 235..235
240..240 245..245 250..250 300..300 350..350 400..400 450..450
500..500

1..1 2..2 3..3 4..4 6..6 8..8 16..16 32..32 8

0..500 0

false

0..63 14

false

true

0..32767 1

NOT_HIGH_LOAD VERY_HIGH_LOAD
HIGH_LOAD
VERY_HIGH_LOAD

false

1..32000 5

1..30 3

false

0..500

0

true

-2000000000

false

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

false

false

false

0..2000

50

0..36000

50

0..0 4..4 5..5 6..6 7..7 8..8 9..9 10..10

10

0..32767

0

0..65535

300

0..1000

600

0..1000

500

BARRED
NOT_BARRED

NOT_BARRED

0..1000000

1500

0..1000000

500

false

0..1000000

0

1..100

15

0..1000000

1000

false

1..2	2
-24..0	-3
0..24	4
5..5 10..10 20..20	10
-300..-300 -200..-200 -100..-100 0..0 177..177 300..300 477..477 600..600	0
0..2000	100
0..36000	6000
0..1000	true false 600
0..1000	500
	false

0..10000	3000
SF40 SF320	SF40
0..100	false 100
-20..20	3
-20..20	3
0..32767	5
0..1000	50
1..32767	200
1..32767	24
	false
0..0 20..80	35
-100..-100 -60..60	-20
5..100	5
5..100	5

0..100	0
0..100	0
0..100	0
0..4095	120
0..1000	200
0..1000	20
0..4095	30
0..4095	30
CA_NS_01 CA_NS_02 CA_NS_03 CA_NS_31 CA_NS_04 CA_NS_05 CA_NS_06 CA_NS_07 CA_NS_08	CA_NS_31
0..0 4..12	4
0..4000	160
0..3	1
0..5	1
40..40 80..80 160..160 320..320 640..640 960..960 1280..1280	320

1..63 20

-127..-96 -117

-126..24 -103

CFI_STATIC_BY_BW	CFI_STATIC_BY_BW
CFI_STATIC_1	
CFI_STATIC_2	
CFI_STATIC_3	
CFI_AUTO_MAXIMUM_2	
CFI_AUTO_MAXIMUM_3	

-200..200 -70

-200..200 -70

-200..200 -70

0..100 8

0..100 6

0..100 6

0..6 0

1..200 24

1..200 22

1..200 22

0..0 1..1 2..2 3..3	0
-120..-90	-110
0..8	0
-34..-3 0..0	0
-140..-44	-140
0..300	70
NO_ADDITIONAL_SR_NEEDED TWO_SR_FOR_LOW_THRESHOLD_SR_PROCESSING TWO_SR_FOR_ALL_SR_PROCESSING	NO_ADDITIONAL_SR_NEEDED
0..62 1000..1000	0
0..62	0
0..31	0
	false
0..31 1000..1000	1000

	false
0..0 500..500 750..750 1280..1280 1920..1920 2560..2560 5120..5120 10240..10240	0
0..62	0
0..1000	600
0..1000	500
	true
0..5	true 5
	true
	true
NONE COVERS OVERLAP CONTAINED_IN	true NONE
	false
	true
	false

NOT_ALLOWED
ALLOWED
OFFLOAD
IFO_AND_IFLB

NOT_ALLOWED

NOT_ALLOWED
ALLOWED
AUTO
ONLY_ALLOWED_FOR_DL

AUTO

-1..7

7

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

OFF
MANUAL
AUTO

OFF

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

PRIORITY0
PRIORITY1
PRIORITY2
PRIORITY3
PRIORITY4

PRIORITY0

0..32767

0

0..65535

300

0..1000000

1000

-24..0

-3

0..24

4

SF40
SF320

true
false
SF40

0..100

false
100

-20..20

3

-20..20

3

0..32767

5

0..1000

50

1..32767

200

1..32767	24
5..100	5
5..100	5
0..100	0
0..100	0
0..100	0
0..4095	120
0..1000	200
0..1000	20
0..4095	30
0..4095	30
0..0 4..12	6
0..4000	16
0..3	1
0..5	1
40..40 80..80 160..160 320..320 640..640 960..960 1280..1280	320
1..63	20

0..62 1000..1000	0
0..62	0
0..31	0
	false
0..31 1000..1000	1000
	false
0..0 500..500 750..750 1280..1280 1920..1920 2560..2560 5120..5120 10240..10240	0
	true
	true
	true
6..6 15..15 25..25 50..50 75..75 100..100	6
	true
	true
-1..7	4
0..100	100
	true

-1..7

7

EVENT_A5
EVENT_A3

EVENT_A5

0..100

0

0..1000

0

NOT_ALLOWED
AUTO
LB_ONLY
OFFLOAD_ONLY
IFO_AND_IFLB

AUTO

0..62

4

0..62

0

0..100

100

NO_ULTRIG_HO
ULTRIG_HO_NO_UL_EVAL

NO_ULTRIG_HO

false

false

true

0..7

5

0..16000

800

0..16000

0

0..16000

200

0..16000

600

0..16000

400

		false
0..100		20
0..16000		800
10..2000		200
0..1000		100
1..100		15
1..100		10
1..1000		10
0..99		2
1..100		30
0..1000		320
0..16000		500
0..1000		30
0..360		90

T4
T2
T
T1_2
T1_4
T1_8
T1_16
T1_32

T

NO_OVERRIDE
HI_PRIO_OVERRIDE

NO_OVERRIDE

0..500

80

0..14

0..9

0

RESOURCE_FAIR
EQUAL_RATE
PROPORTIONAL_FAIR_HIGH
PROPORTIONAL_FAIR_MEDIUM
PROPORTIONAL_FAIR_LOW
MAXIMUM_C_OVER_I
DELAY_BASED

RESOURCE_FAIR

UNDEFINED
VOIP
IMS_SIGNALING
PTT
MC_SIGNALING

UNDEFINED

NO_OVERRIDE
HI_PRIO_OVERRIDE

NO_OVERRIDE

0..500

0

0..14

0..9

0

RESOURCE_FAIR
EQUAL_RATE
PROPORTIONAL_FAIR_HIGH
PROPORTIONAL_FAIR_MEDIUM
PROPORTIONAL_FAIR_LOW
MAXIMUM_C_OVER_I
DELAY_BASED

RESOURCE_FAIR

UNDEFINED
VOIP
IMS_SIGNALING
PTT
MC_SIGNALING

UNDEFINED

0..0 10..86400

61

-150..150

0

-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 -1
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-10..10

1

-10..10

10

-10..10	1
-10..10	10
0..150	10
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	640
-140..-44	-140
0..150	10
MS_120 MS_240 MIN_30 MIN_60 MS_2048 MS_480 MS_640 MS_1024 MS_5120 MS_10240 MIN_1 MIN_6 MIN_12	MS_2048
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	640
-150..150	0
-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	-1
-150..150	0
-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	-1

-110..-47

-110

0..150

10

MS_120
MS_240
MIN_30
MIN_60
MS_2048
MS_480
MS_640
MS_1024
MS_5120
MS_10240
MIN_1
MIN_6
MIN_12

MS_2048

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

640

-150..150

0

-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 -1
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-240..0

-240

-120..-24

-115

0..150

10

MS_120
MS_240
MIN_30
MIN_60
MS_2048
MS_480
MS_640
MS_1024
MS_5120
MS_10240
MIN_1
MIN_6
MIN_12

MS_2048

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 640
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-150..150 30

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 40
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-10..10 3

0..150 10

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 640
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-150..150 0

-150..150 0

-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 -1
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-140..-44	-44
-140..44	-44
-195..-30	-195
0..150	10
-140..-44	-126
-140..-44	-140
-195..-30	-165
0..150	10
0..150	20
0..150	15
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	40
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	40
RSRP RSRQ	RSRP

-150..150 30

0..150 10

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 40
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

RSRP RSRP
RSRQ

-140..-44 -134

-195..-30 -165

-150..450 -150

-100..100 0

-240..240 0

-140..-44 -140

-195..-30 -195

-100..0 0

-240..0	0
-150..450	-150
0..150	20
0..150	15
0..150	20
0..150	10
0..150	10
0..150	20
0..150	15
0..150	20
NOT_INHIBIT INHIBIT_A2SEARCH_RSRQ INHIBIT_A2SEARCH_RSRP	NOT_INHIBIT
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	640
-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	-1
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	40
0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	40
-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 320..320 480..480 512..512 640..640 1024..1024 1280..1280 2560..2560 5120..5120	-1

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 40
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 -1
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 40
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

-1..-1 0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 -1
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 40
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

0..0 40..40 64..64 80..80 100..100 128..128 160..160 256..256 40
320..320 480..480 512..512 640..640 1024..1024 1280..1280
2560..2560 5120..5120

1..1 2..2 3..3 4..4 6..6 8..8 10..10 20..20 20

1..1 2..2 3..3 4..4 5..5 6..6 8..8 10..10 1

100..100 200..200 300..300 400..400 600..600 1000..1000 400
1500..1500 2000..2000

0..0 50..50 100..100 200..200 500..500 1000..1000 2000..2000 2000

1000..1000 3000..3000 5000..5000 10000..10000 15000..15000 3000
20000..20000 30000..30000

100..100 200..200 300..300 400..400 600..600 1000..1000 400
1500..1500 2000..2000

50..50 100..100 150..150 200..200 500..500 1000..1000 2000..2000 1000

1000..1000 3000..3000 5000..5000 10000..10000 15000..15000 3000
20000..20000 30000..30000

DEFAULT
QAM_64_BOOST
QAM_256_BOOST
MAX_POWER_CLASS

DEFAULT

0..10 0

1..1 2..2 3..3 4..4 6..6 8..8 16..16 32..32 8

5..5 10..10 15..15 20..20 25..25 30..30 35..35 40..40 45..45 50..50 80
55..55 60..60 65..65 70..70 75..75 80..80 85..85 90..90 95..95
100..100 105..105 110..110 115..115 120..120 125..125 130..130
135..135 140..140 145..145 150..150 155..155 160..160 165..165
170..170 175..175 180..180 185..185 190..190 195..195 200..200
205..205 210..210 215..215 220..220 225..225 230..230 235..235
240..240 245..245 250..250 300..300 350..350 400..400 450..450
500..500

5..5 10..10 15..15 20..20 25..25 30..30 35..35 40..40 45..45 50..50 80
55..55 60..60 65..65 70..70 75..75 80..80 85..85 90..90 95..95
100..100 105..105 110..110 115..115 120..120 125..125 130..130
135..135 140..140 145..145 150..150 155..155 160..160 165..165
170..170 175..175 180..180 185..185 190..190 195..195 200..200
205..205 210..210 215..215 220..220 225..225 230..230 235..235
240..240 245..245 250..250 300..300 350..350 400..400 450..450
500..500

1..1 2..2 3..3 4..4 6..6 8..8 16..16 32..32 8

false

true

false

false

0..7

0

1..7

7

0..100

1

-140..-44 0..0

0

0..1200

40

-150..150

20

true

true

true

true

-150..150

30

true

0..7

6

MultiplicationFactor	Unit	Resolution	ReadOnly	Restricted	Mandatory

0.001			N	N	N
-------	--	--	---	---	---

			N	N	N
--	--	--	---	---	---

0.001			N	N	N
-------	--	--	---	---	---

0.001			N	N	N
-------	--	--	---	---	---

	Mbps		N	N	N
--	------	--	---	---	---

			N	N	N
--	--	--	---	---	---

			N	N	N
--	--	--	---	---	---

			N	N	N
--	--	--	---	---	---

			N	N	N
--	--	--	---	---	---

0.001		N	N	N
0.001		N	N	N
	Mbps	N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
	number of messages	N	N	N
	minutes	N	N	N
		N	N	N

		N	N	N
		N	N	N
		N	N	N
0.01		N	N	N

	Days	N	N	N
0.01		N	N	N

	Days	N	N	N
		N	N	N
	day	N	N	N

day	N	N	N
day	N	N	N
DecMeasurementReports	N	N	N
DecMeasurementReports	N	N	N
DecMeasurementReports	N	N	N
DecMeasurementReports	N	N	N
	N	N	N
	N	N	N
centiUE	N	N	N
centiUE	N	N	N
centiUE	N	N	N
UE	N	N	N

0.1	UE	N	N	N
	centiUE	N	N	N
	centiUE	N	N	N
	centiUE	N	N	N
	UE	N	N	N
	UE	N	N	N
	dBm	N	N	N
	dB	N	N	N
	DecMeasurementReports	N	N	N
	DecMeasurementReports	N	N	N
0.01	DecMeasurementReports	N	N	N
	DecMeasurementReports	N	N	N

0.1	DecMeasurementReports		N	N	N
			N	N	N
			N	N	N
	DecMeasurementReports		N	N	N
	DecMeasurementReports		N	N	N
	DecMeasurementReports		N	N	N
0.1					
	dB	5	N	N	N
	dB		N	N	N

N

N

N

N

N

N

N N N

1 percent

N N N

N N N

N N N

UE SCell
instances

N N N

N N N

N N N

N N N

		N	N	N
0.1	Number of DL subframes	N	N	N

0.1	Number of DL subframes	N	N	N
-----	------------------------------	---	---	---

0.1	Number of UL subframes	N	N	N
-----	------------------------------	---	---	---

0.1	Number of UL subframes	N	N	N
-----	------------------------------	---	---	---

ms	N	N	N
----	---	---	---

ms	N	N	N
----	---	---	---

0.1	ms	N	N	N
	ms	N	N	N
	dB	N	N	N
		N	N	N
	ms	N	N	N
	ms	N	N	N
	ms	N	N	N
		N	N	N
	ms	N	N	N

ms	N	N	N
	N	N	N
ms	N	N	N
	N	N	N
	N	N	N
	N	N	N
	N	N	N
s	N	N	N
	N	N	N
	N	N	N
s	N	N	N
s	N	N	N
	N	N	N

ms

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

N

		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
		N	N	N
100	ms	N	N	N
0.1	.	N	N	N
100	Bytes	N	N	N
		N	N	N

0.001		N	N	N
0.001		N	N	N
		N	N	N
kbps	20	N	N	N
kbps	20	N	N	N
		N	N	N
		N	N	N
		N	N	N
km		N	N	N
		N	N	N
		N	N	N

		N	N	N
	dB	N	N	N
	dB	N	N	N
	ms	N	N	N
0.01	dB	N	N	N

		N	N	N
100	ms	N	N	N
		N	N	N
		N	N	N
0.001		N	N	N

0.001		N	N	N
		N	N	N

	ms		N	N	N
			N	N	N
			N	N	N
	Percent		N	N	N
	ms		N	N	N
	ms		N	N	N
			N	N	N
0.1	%		N	N	N
			N	N	N
	hour		N	N	N
			N	N	N
0.01			N	N	N
0.01			N	N	N
	%	5	N	N	N
	%	5	N	N	N

0.1	%	5	N	N	N
	%	5	N	N	N
	%	5	N	N	N
	s		N	N	N
	%		N	N	N
	%		N	N	N
	s		N	N	N
	s		N	N	N
			N	N	N
	CS sets		N	N	N
0.1			N	N	N
			N	N	N
			N	N	N
	ms		N	N	N

[illegible]

[illegible]

			N	N	N
	ms		N	N	N
	dB	2	N	N	N
0.001			N	N	N
0.001			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

N	N	N
---	---	---

		N	N	N
100	Bytes	N	N	N
		N	N	N
		N	N	N
	dB	N	N	N
	dB	N	N	N
		N	N	N
		N	N	N
		N	N	N
	Percent	N	N	N
		N	N	N
	ms	N	N	N
	ms	N	N	N
		N	N	N
0.1	%	N	N	N
		N	N	N

	hour		N	N	N
	%	5	N	N	N
	%	5	N	N	N
	%	5	N	N	N
	%	5	N	N	N
	%	5	N	N	N
	s		N	N	N
	%		N	N	N
0.1					
0.1	%		N	N	N
	s		N	N	N
	s		N	N	N
	CS sets		N	N	N
			N	N	N
			N	N	N
	ms		N	N	N
			N	N	N

[illegible]

[illegible]

			N	N	N
0.01			N	N	N
0.001			N	N	N
0.001			N	N	N
0.001			N	N	N
0.01			N	N	N
0.1			N	N	N
			N	N	N
0.01			N	N	N
0.1			N	N	N
0.001		20	N	N	N
0.001			N	N	N
0.001			N	N	N
	s	30	N	N	N

N

N

N

N

N

N

ms

N

N

N

N

N

Y

N

N

N

N

N

N

N

N

N

			N	N	N
	ms		N	N	N
			N	N	Y
			N	N	N
			N	N	N
			N	N	N
	s		N	N	N
0.1	dB	5	N	N	N
	ms		N	N	N
	dB		N	N	N
0.1	dB	5	N	N	N

	dB		N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
	ms		N	N	N
	dBm		N	N	N
0.1	dB	5	N	N	N
			N	N	N
	ms		N	N	N
0.1	dB	5	N	N	N
	ms		N	N	N
0.1	dB	5	N	N	N
	ms		N	N	N

0.1	dBm		N	N	N
	dB	5	N	N	N
			N	N	N

0.1	ms		N	N	N
	dB	5	N	N	N
	ms		N	N	N

0.1	dB	5	N	N	N
	dBm		N	N	N
	dB	5	N	N	N

N N N

ms N N N

0.1 dB 5 N N N

ms N N N

dB N N N

0.1 dB 5 N N N

ms N N N

0.1 dB 5 N N N

0.1 dB 5 N N N

ms N N N

[illegible]

0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
	ms		N	N	N
			N	N	N
	dBm		N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
	dB		N	N	N
0.1	dB		N	N	N
	dBm		N	N	N
0.1	dB	5	N	N	N
	dB		N	N	N

0.1	dB		N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
0.1	dB	5	N	N	N
			N	N	N
	ms		N	N	N
	ms		N	N	N
	ms		N	N	N
	ms		N	N	N

0.52	ms	N	N	N
		N	N	N
	microsecond	N	N	N
		N	N	N
	ms	N	N	N
	ms	N	N	N
		N	N	N
		N	N	N
		N	N	N

			N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
	dBm		N	N	N
0.1	s		N	N	N
0.1	dB	5	N	N	N
			N	N	N
			N	N	N
			N	N	N
			N	N	N
0.1	dB	5	N	N	N
			N	N	N
			N	N	N

Persistent	SystemCreated
N	Y

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
N	Y

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
N	Y
N	Y

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N

Y

N

Y

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N Y

N Y

N Y

N Y

N Y

N Y

N Y

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
N	N

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N N

N N

N N

N N

N N

N N

N N

N N

N N

N N

N N

N N

N N

N N

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
N	N

N	N
---	---

N	N
---	---

N	N
N	N

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
N	N
N	N

N	N
N	N

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N
N	N

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
N	N

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

N	N
---	---

[illegible]

N

Y

N

N

N

N

N

N

N

N

N

N

N

N

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	N
---	---

N	N
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	Y
---	---

N	N
---	---

N	N
---	---

Change Take Effect

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

Object unlocked

Object unlocked

Object unlocked

At node restart

New connection

Cell lock/unlock

At node restart

New connection or next SCell configuration.

New connection

New connection

At the next initial SCell selection during the ongoing connection

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

New connection

Ongoing connection

New connection or next SCell configuration.

Ongoing connection

Cell lock/unlock

Cell lock/unlock

New connection.

New connection.

Next tunnel setup

New connection

New connection

New connection

Ongoing connection

New connection

New connection or next SCell configuration.

Object unlocked

Cell lock/unlock

Object unlocked

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock
Next cell unlock

Object unlocked

New connection

New connection

New connection

New connection

Object unlocked

Object disabled/enabled

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Object unlocked

Object unlocked

Object unlocked

Object unlocked

Object unlocked

Object unlocked

Object unlocked

Cell lock/unlock

Object unlocked

Object unlocked

Object unlocked

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

New connection

Cell lock/unlock

Object unlocked
New connection

Cell lock/unlock

Changed value will take effect in relation to the next SCell configuration during the ongoing connection. When going from state NOT_ALLOWED to ALLOWED the SCell will not be available at re-selection for ongoing connections.

New connection or next SCell configuration.

New connection or next SCell configuration.

Cell lock/unlock

Next cell unlock

New connection

New connection

New connection

New connection

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

New connection

Cell lock/unlock

Cell lock/unlock

New connection

New connection or next SCell configuration.

New connection or next SCell configuration.

New connection

New connection

Ongoing connection

New connection

New connection
New connection

New connection

New connection

New connection

After all the cells in the RBS have been locked, and subsequently been unlocked.

New connection

Cell lock/unlock

New connection

New connection

New connection

Cell lock/unlock

New connection

Cell lock/unlock

New connection

New connection

New connection

Cell lock/unlock

New connection.

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

Ongoing connection

Changed value may take effect related to the next SCell configuration during the ongoing connection.

Ongoing connection

Ongoing connection

New connection. Also during ongoing connection, related to next SCell configuration during the connection.

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

Ongoing connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

New connection

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

Cell lock/unlock

New connection.

New connection.

New connection

New connection

New connection

New connection

New connection

New connection

New connection.

New connection

New connection

New connection

New connection

New connection

New connection

New connection

Disturbances

Changing this attribute can impact accessibility at high load.

Changing this attribute can impact accessibility at high load.

Extreme settings can turn off CA for the eNB.

Changing this attribute can cause significantly higher drop rate.

Lowering the value of this attribute can cause significantly higher drop rate.

Changing this attribute can affect performance of all data bearers. A value that is set too low can affect other services with higher priority. A value that is set too high can cause Dynamic UE Admission Control to fail in keeping the cell stable at overload.

Changing this attribute can also affect other X2 traffic than CA packets.

Changing this attribute can cause loss of traffic.

Changing this attribute can affect traffic.

Changing this attribute can affect performance of all data bearers. A value that is set too low can affect other services with higher priority. A value that is set too high can cause Dynamic UE Admission Control to fail in keeping the cell stable at overload.

Changing this attribute can cause loss of traffic.

Changing this attribute can block Video calls.

Changing this attribute can block VoLTE calls.

Changing this attribute can block sms.

Changing this attribute can affect traffic.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests
- rejected non-privileged RRC connection re-establishment requests and rejected non-privileged incoming handover requests.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests.

Changing this attribute to BARRED blocks all traffic in the cell.

Changes may affect traffic.

Low values reduce cell capacity.

Changing this attribute can stop outgoing HO.

Changing this attribute can stop outgoing HO.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests
- rejected non-privileged RRC connection re-establishment requests and rejected non-privileged incoming handover requests.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests
- rejected non-privileged RRC connection re-establishment requests and rejected non-privileged incoming handover requests.

Changing this attribute can cause loss of traffic.

Changing this attribute can stop outgoing HO.

Changing this attribute can stop outgoing HO.

Changes may affect traffic.

Changing this attribute can cause loss of traffic.

Cell runs new set-up procedure. All cell-connected UEs are released and connected again.

Changes may affect traffic.

Changes may affect traffic.

Changes can affect traffic.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests
- rejected non-privileged RRC connection re-establishment requests and rejected non- privileged incoming handover requests.

Changing this attribute can affect the following:

- the number of RRC-connected users
- cell throughput and the number of rejected non-privileged RRC connection requests.

Changes may affect traffic

Low values reduce cell capacity.

Changing this attribute can stop outgoing HO.

Changing this attribute can stop outgoing HO.

Changing this attribute can cause loss of traffic.

Changing this attribute can stop outgoing HO.

Changing this attribute can stop outgoing HO.

Cell runs new set-up procedure. All cell-connected UEs are released and connected again.

Changing this attribute can cause loss of traffic.

Changing this attribute can affect traffic

Changing this attribute can affect traffic.

Changing this attribute can affect traffic.

Changing this attribute can affect traffic.

Changing this attribute can affect traffic.

Changing this attribute can affect traffic.

Changing this attribute can affect traffic

Changing this attribute can affect traffic

Changing this attribute can cause loss of traffic.

Changing this attribute can affect traffic

Changing this attribute can cause loss of traffic.

Changing this attribute can affect traffic

Changing this attribute can cause loss of traffic.

Changing this attribute can affect traffic

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can cause loss of traffic.

Changing this attribute can affect traffic

Changing this attribute can affect traffic

Changing this attribute can affect traffic

Changing this attribute can affect traffic

Lowering the value can increase drop rate.

Increasing the value can increase drop rate.

Lowering the value can increase drop rate.

Lowering the value can increase drop rate.

Lowering the value can increase drop rate.

Lowering the value can increase drop rate.

Lowering the value can stop outgoing HO.

Lowering the value can increase drop rate.

High values can cause high drop rate.

Low values can cause high drop rate.

Changing this attribute can affect UE battery consumption and user throughput.

High values can stop outgoing HO.

Changing this attribute to false can cause loss of traffic. Blocks measurement based mobility to CDMA2000.

Changing this attribute to false can cause loss of traffic. Blocks measurement based mobility to GERAN.

Changing this attribute to false can cause loss of traffic. Blocks measurement based IF mobility.

Changing this attribute to false can cause loss of traffic. Blocks measurement based mobility to UTRAN.

Dependencies

$dlAdmDifferentiationThr \leq dlAdmOverloadThr$

$dlAdmOverloadThr \geq dlAdmDifferentiationThr$

Max value for DU radio nodes is 1000.

Applicable only if resourceReservationForPState is set to ACTIVATED.
 $nrOfPaConnReservationsPerCell \geq nrOfPaConnHpaReservPerCell$.

Applicable only if resourceReservationForPState is set to ACTIVATED.

$paArpOverride \geq paArpOverrideHpa$.

$ulAdmDifferentiationThr \leq ulAdmOverloadThr$

$ulAdmOverloadThr \geq ulAdmDifferentiationThr$

Max value for DU radio nodes is 1000.

probCellDetectMedHoSuccThres > probCellDetectLowHoSuccThres.

probCellDetectMedHoSuccThres > probCellDetectLowHoSuccThres.

$\text{anrEutranInterFMeasReportMax} \geq \text{anrEutranInterFMeasReportMin}.$

$\text{anrEutranInterFMeasReportMin} \leq \text{anrEutranInterFMeasReportMax}.$

Only applicable when following apply:

- 3CC Carrier Aggregation Extension and UL Carrier Aggregation are enabled.
- sCellSelectionMode is UN_ACK_SIMULTANEOUS_SCELL_SELECTION or ACK_SIMULTANEOUS_SCELL_SELECTION.
- Not applied to Global SCell Evaluation.

Only takes effect when Dynamic SCell Selection for Carrier Aggregation and Configurable SCell Priority features, Global SCell Evaluation feature, or both are active.

Only takes effect when Dynamic SCell Selection is active.

Only takes effect when Dynamic SCell Selection is active.

Only takes effect when Carrier Aggregation FAJ 121 3046 and Enhanced PDCCH Link Adaptation FAJ 121 3051 are active, and a VoIP or PTT bearer exists for a UE.

$sCellActDeactDataThreshHyst \leq sCellActDeactDataThres$ when $sCellActDeactDataThres$ is not equal to -1

$sCellActDeactDataThreshHyst \leq sCellActDeactDataThres$ when $sCellActDeactDataThres$ is not equal to -1

$sCellActDeactUIDataThreshHyst \leq sCellActDeactUIDataThresh$

$sCellActDeactUIDataThreshHyst \leq sCellActDeactUIDataThresh$

$sCellActDeactDataThreshHyst \leq sCellActDeactDataThres$

Only takes effect when Dynamic SCell Selection for Carrier Aggregation and 3CC DL Carrier Aggregation Extension are active.

Only used for Resource Fair Scheduling algorithm. Only relevant if the license for Dynamic UE Admission Control is present and the feature is active.

This attribute is effective only when ANR for LTE or UTRAN feature is activated.

This attribute is only effective when feature Multi-Target RRC Connection Reestablishment is activated.

Only used for Resource Fair Scheduling algorithm. Only relevant if the license for Dynamic UE Admission Control is present and the feature is active.

If Scheduling Request resources limitation pool for privileged access connections is activated in eNodeB, threshold for allocation of an additional PUCCH format 1 PRB pair by dynamic PUCCH must be higher than number of resources in limitation pool.
(allocThrPucchFormat1 > AdmissionControl::limitSrNonPa)

Only applicable when Configurable SCell Priority is active with following apply:

- dynamicSCellSelectionMethod is set to PRIORITIZED.
- dynamicSCellSelectionMethod is set to GLOBAL_EVALUATION.

$\text{cceDynUeAdmCtrlOverloadThr} \geq \text{cceDynUeAdmCtrlRetDiffThr}$

$\text{cceDynUeAdmCtrlRetDiffThr} \leq \text{cceDynUeAdmCtrlOverloadThr}$

$\text{cellCapMinCellSubCap} < \text{cellCapMaxCellSubCap}$

$\text{cellCapMinCellSubCap} < \text{cellCapMaxCellSubCap}$

Applicable only when attribute noOfChannelSelectionSets > 0.

Only SCell candidates with TM mode resource requirements that match the CS set size are considered for carrier aggregation.

For 1.4 MHz: Only valid inputs are 10 and 20.

The crsGain only takes effect if the configured number of antenna ports used in a sector is 2, 4, or 8. In the one port case, crsGain is hardcoded to 0dB.

$$dlDynUeAdmCtrlOverloadThr \geq dlDynUeAdmCtrlRetDiffThr$$
$$dlDynUeAdmCtrlRetDiffThr \leq dlDynUeAdmCtrlOverloadThr$$

Feature Ericsson Lean Carrier is present active.

Must be false if catm1SupportEnabled is true.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when feature Load-Based Access Barring or feature Progressive Access Barring is activated.

Only takes effect when feature Progressive Access Barring is activated.

Only takes effect when feature Progressive Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when 3CC Carrier aggregation Extension Feature (FAJ 121 3084) is enabled.

Changing the value of pZeroNominalPusch, might have impact on the setting of puschPwrOffset64Qam. See puschPwrOffset64Qam for how that attribute depends on pZeroNominalPusch.

pdccchCfiMode cannot equal CFI_STATIC_1 while dlChannelBandwidth = 1400, 3000, or 5000 kHz since there would be insufficient CCEs to transmit a PDCCH for common channel messages such as SIB1 or SI. Certain values of pdccchCfiMode that allow high CFI values may be disallowed when the combination of attributes pdccchCfiMode, dlChannelBandwidth, noOfPucchCqiUsers, and noOfPucchSrUsers require too many corresponding PUCCH HARQ-ARQ resources.

The pdschTypeBGain=0 (gain=5/4) is not allowed if crsGain=1.77,3.0, 4.77,6.0 dB. This combination causes over allocation of DL mean radio power and attribute pdschTypeBGain is set to 1 (gain=1).

The pdschTypeBGain only takes effect if the configured number of antenna ports is 2,4, or 8. In the one port case, the power of resource elements for PDSCH type A and B is equal.

Only relevant if the license for 64-QAM Uplink is present and the feature is active.

For 2Rx, pZeroNominalPusch + puschPwrOffset64qam needs to be -100 dBm or higher to achieve maximum throughput.

puschPwrOffset64Qam should be set to 0 when both UL 64QAM and UL MU-MIMO are enabled in eNB.

The field is mandatory present if the Struct Member threshServingLowQ in SIB3 is used in systemInformationBlockType3.

Including in system information depends on parameter sNonIntraSearchv920Active.

Including in system information depends on parameter sNonIntraSearchv920Active.

$\text{ulDynUeAdmCtrlOverloadThr} \geq \text{ulDynUeAdmCtrlRetDiffThr}$

$\text{ulDynUeAdmCtrlRetDiffThr} \leq \text{ulDynUeAdmCtrlOverloadThr}$

Applicable when 3CC Carrier aggregation Extension Feature (FAJ 121 3084) is enabled and sCellSelectionMode is equal to UN_ACK_SIMULTANEOUS_SCELL_SELECTION or ACK_SIMULTANEOUS_SCELL_SELECTION.

Only applicable when Configurable SCell Priority is active with following apply:

- dynamicSCellSelectionMethod is set to PRIORITIZED.
- dynamicSCellSelectionMethod is set to GLOBAL_EVALUATION.

Only applicable when Configurable SCell Priority is active with following apply:

- dynamicSCellSelectionMethod is set to PRIORITIZED.
- dynamicSCellSelectionMethod is set to GLOBAL_EVALUATION.

Feature Ericsson Lean Carrier is present active.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when feature Load-Based Access Barring or feature Progressive Access Barring is activated.

Only takes effect when feature Progressive Access Barring is activated.

Only takes effect when feature Progressive Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when Load-Based Access Barring is activated.

Only takes effect when either of the following conditions is satisfied:
3CC Carrier aggregation Extension Feature (FAJ 121 3084) is enabled, or nonCaAnModeF3Enable is true.

Including in system information depends on parameter sNonIntraSearchv920Active.

Including in system information depends on parameter sNonIntraSearchv920Active.

Only applicable when Configurable SCell Priority is active with following apply:

- dynamicSCellSelectionMethod is set to PRIORITIZED.
- dynamicSCellSelectionMethod is set to GLOBAL_EVALUATION.

Only applicable when Configurable SCell Priority is active with following apply:

- dynamicSCellSelectionMethod is set to PRIORITIZED.
- dynamicSCellSelectionMethod is set to GLOBAL_EVALUATION.

Value must be unique and not already used by other RAT, that is, equal priorities between RATs are not supported.
Value -1 cannot be assigned if this EUTranFreqRelation MO is associated with frequency equal to parent cell frequency.

The value must be unique and not already used by other RAT, i.e. equal priorities between RATs are not supported.

Only relevant if license Ericsson Lean Carrier is present and feature is active.

$\text{lbDiffCaOffset} > \text{lbThreshold}$

$\text{lbHitRateEUTranAddThreshold} > \text{lbHitRateEUTranRemoveThreshold}$

$\text{lbHitRateEUTranAddThreshold} > \text{lbHitRateEUTranRemoveThreshold}$

nB=T4 can not be used in combination with specialSubframePattern = 5 on MO EUTRANCellTDD, see 3GPP TS 36.213.

Only relevant if the license for QoS Aware Scheduler is present and the feature is active.

Only relevant if the license for QoS Aware Scheduler is present and active.

$(\text{priority} + \text{priorityFraction}) > 0 \text{ AND } (\text{priority} * 10 + \text{priorityFraction}) \leq 140$

$(\text{priority} + \text{priorityFraction}) > 0 \text{ AND } (\text{priority} * 10 + \text{priorityFraction}) \leq 140$

Only relevant if the license for QoS Aware Scheduler is present and the feature is active. The value DELAY_BASED can only be used if the attribute serviceType has value VOIP.

Changes to this parameter take effect only if the license for QoS Aware Scheduler is present and the feature is active.

Only relevant if the license for QoS Aware Scheduler is present and the feature is active.

Only relevant if the license for QoS Aware Scheduler is present and active.

$(\text{priority} + \text{priorityFraction}) > 0 \text{ AND } (\text{priority} * 10 + \text{priorityFraction}) \leq 140$

$(\text{priority} + \text{priorityFraction}) > 0 \text{ AND } (\text{priority} * 10 + \text{priorityFraction}) \leq 140$

Only relevant if the license for QoS Aware Scheduler is present and the feature is active. The value DELAY_BASED can only be used if the attribute serviceType has value VOIP.

Changes to this parameter take effect only if the license for QoS Aware Scheduler is present and the feature is active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Not pure dependence towards parameter on ReportConfigA5 Mo, but there should be a check that this attribute and corresponding attribute on ReportConfigA5 MO together sends out a valid number to the UE

Not pure dependence towards parameter on ReportConfigA5 Mo, but there should be a check that this attribute and corresponding attribute on ReportConfigA5 MO together sends out a valid number to the UE

Not pure dependence towards parameter on ReportConfigA5 Mo, but there should be a check that this attribute and corresponding attribute on ReportConfigA5 MO together sends out a valid number to the UE

Not pure dependence towards parameter on ReportConfigA5 Mo, but there should be a check that this attribute and corresponding attribute on ReportConfigA5 MO together sends out a valid number to the UE

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Not pure dependence towards parameter on ReportConfigEUTraBestCell Mo, but there should be a check that this attribute and corresponding attribute on ReportConfigEUTraBestCell MO together sends out a valid number to the UE

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

hysteresisA1A2RsrpBidirectional applies. When a1a2ThresholdRsrpBidir is less than or equal to a1a2ThresholdRsrp, the capability to remove UL separately from DL is disabled.

When a1a2ThresholdRsrpBidir is less than or equal to a1a2ThresholdRsrp, the capability to remove UL separately from DL is disabled.

`a1a2UISearchThreshold >= a2UICriticalThreshold`

a1a2UISearchThreshold >= a2UICriticalThreshold

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

Feature Mobility Control at Poor Coverage must be active.

This attribute is only effective when feature Mobility Control at Poor Coverage is activated.

Feature Mobility Control at Poor Coverage must be active.

The value must be unique and not already used by other RAT, i.e. equal priorities between RATs are not supported.

Deprecated	Recommended Value	Recommended Value Comment
------------	-------------------	---------------------------

750

DEACTIVATED

500

950

Deployment dependent. Set to correspond to transport network interface speed.

5

5

7

ACTIVATED

500

950

Deployment dependent. Set to correspond to transport network interface speed.

Deprecated 1000

Deprecated 1000

false
10

15

30

true

true
true
false

Set to TRUE to prevent mobility
towards cells with PLMN IDs that are
not white-listed.

10

10

50

4

AUTO_DETECT_AND_BAR

14

7

7

1

10

0

This recommendation is only valid if the Inter-Frequency Load Balancing feature is activated.

0

This recommendation is only valid if the Inter-Frequency Load Balancing feature is activated.

ACTIVATED

ACTIVATED

10

20

100

0

0

10

20

100

0

This recommendation is only valid if the Mobility Control at Poor Coverage feature is activated.

0

-1150

-1530

true

true

1

10

100

5

20

ACTIVATED

ACTIVATED

20

1

10

100

5

-10

-1

PSF20

SF320

PSF5

50

DL

10

65535

PRIORITIZED

true

false

true

100

90

100

90

10

50

680
MAX(240,
3*CarrierAggregationFunction.sCellDe
actProhibitTimer + 80) ms

200

0

ACK_SIMULTANEOUS_SCELL_SELEC
TION

10000

50

10000

16

80

80

16

500

false

14

true

true

1

VERY_HIGH_LOAD

true

Deprecated 5

3

true

500

true

1

true

OFF

AUTO

AUTO

AUTO

AUTO

PRIORITY0

PRIORITY1

PRIORITY1

PRIORITY0

PRIORITY0

false

true

true

50

50

10

0

300

900

700

Requires network-specific configuration. Set to NOT_BARRED, except for DL-only carriers.

100000

1000

true

Recommended to be set as the EUTRANCellFDD::dlChannelBandwidth* 1.7. The EUTRANCellFDD::dlChannelBandwidth parameter is expressed in kHz and may be different for each carrier

15

Recommended to be set as the EUTRANCellFDD::dlChannelBandwidth* 1.7. The EUTRANCellFDD::dlChannelBandwidth parameter is expressed in kHz and may be different for each carrier

true

Setting depends on transmission mode. See CPI for setting instructions.

-3

4

10

0

For 4Tx, the value can be set to 3dB as a simple way to maintain the same cell boundaries as legacy 2TX with all other settings being the same. This is not recommended for greenfield deployment as the drawback of setting to 3dB increased CRS interference over legacy 2TX which can totally negate any possible realizable 4x2 gain over 2TX. This may be less of a concern for 4x4 with its higher peak throughput. Please see CPI 4x2 and CPI 4x4 for details.

100

6000

true

false

950

850

true

3000

SF40

true

100

May require tuning if layers have
different coverage

3

3

5

50

200

24

Requires network-specific
configuration. Set to FALSE, except for
DL-only carriers.

35

-20

5

5

0

0

0

30

100

20

30

30

CA_NS_31

4

Set to 0 for cells that are not PCells.

320

1

1

320

20

-117

For 4RX, the value can be reduced by 3 dB.

-103

For 4RX, the value can be reduced by 3 dB.

CFI_AUTO_MAXIMUM_3

-70

-70

-70

8

6

6

0

24

22

22

0

If the EUTRANCellFDD.crsGain parameter for 4Tx is changed to a value greater than 0 dB, this parameter must be changed to 1.

-110

0

0

-124

70

TWO_SR_FOR_LOW_THRESHOLD_S
R_PROCESSING

4

4

0

false

1000

true

0

0

For the capacity layers,
EUTranCellFDD:: threshServingLow is
recommended to be set to 2

950

850

TRUE

true

5

true

true

true

NONE

This parameter has no effect when
CarrierAggregationFunction.dynamicSC
ellSelectionMethod is set to
PRIORITIZED.

true

true

false

NOT_ALLOWED

ALLOWED

4

OFF

AUTO

AUTO

AUTO

AUTO

PRIORITY0

PRIORITY1

PRIORITY1

PRIORITY0

PRIORITY0

0

300

Recommended to be set as the
EUTRANCellFDD::dlChannelBandwidth*
1.7. The
EUTRANCellFDD::dlChannelBandwidth
parameter is expressed in kHz and may
be different for each carrier

-3

4

true

false

SF40

true

100

May require tuning if layers have
different coverage

3

3

5

50

200

24

5

5

0

0

0

30

100

20

30

30

6

128

1

1

320

20

4

4

0

false

1000

true

0

TRUE

true

true

6

This setting is mandatory for all cells that have neighboring cells with the Ericsson Lean Carrier feature enabled.

true

true

4

100

true

4

EVENT_A5

0

0

AUTO

4

0

100

NO_ULTRIG_HO

true

true

true

2

800

0

200

600

400

false

20

800

200

100

15

1

2

2

30

320

1500

30

90

T1_16

For QCI5, the recommended value is HI_PRIO_OVERRIDE; For other QCI, the recommended value is NO_OVERRIDE.

QCI1 is recommended to configure NO_OVERRIDE and scheduling algorithm is DBS.

If Delay Based Scheduling is activated, for QCI1, the recommended value is 80 (Default 0).

For QCI1,the recommended value is 1
For QC15,the recommended value is 2
Dynamic GBR admission control is needed to ensure that QCI5 are not starved by high load on QCI1.

0

If Delay Based Scheduling is activated, for QCI1, the recommended value is DELAY_BASED.

If Delay Based Scheduling is activated, for QCI1, the recommended value is VOIP.

For QCI5, the recommended value is HI_PRIO_OVERRIDE; For other QCI, the recommended value is NO_OVERRIDE.

QCI1 is recommended to configure NO_OVERRIDE and scheduling algorithm is DBS.

If Delay Based Scheduling is activated, for QCI1, the recommended value is 80 (Default 0).

For QCI1, the recommended value is 1
For QCI5, the recommended value is 2
Dynamic GBR admission control is needed to ensure that QCI5 are not starved by high load on QCI1.

0

If Delay Based Scheduling is enabled, for QCI1, the recommended value is DELAY_BASED.

If Delay Based Scheduling is enabled, for QCI1, the recommended value is VOIP.

10

0

-1

1

10

1

10

10

640

-95

30

MS_2048

640

0

-1

0

-1

-90

20

MS_2048

320

0

-1

-240

-115

10

MS_2048

640

30

320

3

10

640

0

0

-1

-44 For the coverage layers, this parameter is recommended to be set to the amount of EUTRAN-CellFDD.qRxLevMin + 80 dB, this is -44 dBm.
For the capacity layers, this parameter is recommended to be set to -124 dBm.

-112 EUTRAN-CellFDD.qRxLevMin + 12dB

-150

10

-124

Uplink Carrier Aggregation feature is recommended as activated, hence the bandwidth-based formula in Uplink Carrier Aggregation Feature Description should be used (e.g. a1a2ThresholdRsrp+9 dB, +9 dB is based on 3 MHz Pcell, 20 MHz SCell).

-115

10

20

15

40

40

RSRP

30

10

40

RSRP

-115

Set equal to the maximum of the ReportConfigA5.a5Threshold1Rsrp and ReportConfigB2Geran/ReportConfigB2Utran.b2Threshold1Rsrp values being used for coverage-triggered IFHO or IRAT handover.

-195

If RSRQ triggering is required, set equal to the maximum of the ReportConfigA5.a5Threshold1Rsrq and ReportConfigB2Geran/ReportConfigB2Utran.b2Threshold1Rsrq values being used for coverage-triggered IFHO or IRAT handover.

30

0

Set to 3 dB for more stable and sustainable voice performance.

0

Set to 3 dB for more stable and sustainable voice performance.

-126

-195

0

Set to -3 dB if outer search zone for RSRP is used.

0

-90

20

15

20

10

10

20

15

20

INHIBIT_A2SEARCH_RSRQ

640

-1

320

512

-1

40

Set same as timeToTriggerA2Search.
When using the recommendation this
parameter has no effect as outer
search is not used.

-1

40

-1

320

320

20

1

400

2000

3000

400

1000

3000

QAM_256_BOOST

0

16

80

80

16

false

true

false

false

Set to TRUE to prevent RSRQ-triggered mobility to UTRAN. This parameter has no effect when the recommended value is set.

0

7

1

0

40

It is recommend to configure shorter value than
UeMeasControl.a5B2MobilityTimer

20

true

true

true

true

40

true

3

Recommended Range

Class Path

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AdmissionControl/

//ManagedElement/ENodeBFunction/AmoFunction/
//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/
//ManagedElement/ENodeBFunction/AnrFunction/
//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/
//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/
//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/
//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionEUTran/
//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionGeran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionGeran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionGeran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionGeran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionGeran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionGeran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrFunction/AnrFunctionUtran/

//ManagedElement/ENodeBFunction/AnrPciConflictDrxProfile/

//ManagedElement/ENodeBFunction/AnrPciConflictDrxProfile/

//ManagedElement/ENodeBFunction/AnrPciConflictDrxProfile/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/CarrierAggregationFunction/

//ManagedElement/ENodeBFunction/RadioBearerTable/DataRadioBearer/

//ManagedElement/ENodeBFunction/RadioBearerTable/DataRadioBearer/

//ManagedElement/ENodeBFunction/RadioBearerTable/DataRadioBearer/

//ManagedElement/ENodeBFunction/RadioBearerTable/DataRadioBearer/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/
//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/
//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/EUtranCellRelation/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/
//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/EUtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtraNetwork/ExternalENodeBFunction/

//ManagedElement/ENodeBFunction/EUtraNetwork/ExternalENodeBFunction/

//ManagedElement/ENodeBFunction/EUtraNetwork/ExternalENodeBFunction/ExternalEUtranCellFDD/

//ManagedElement/ENodeBFunction/EUtraNetwork/ExternalENodeBFunction/ExternalEUtranCellTDD/

//ManagedElement/ENodeBFunction/EUtranCellFDD/GeranFreqGroupRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/GeranFreqGroupRelation/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/IdleModePrioAtRelease/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/IdleModePrioAtRelease/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/IdleModePrioAtRelease/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/IdleModePrioAtRelease/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/IdleModePrioAtRelease/

//ManagedElement/ENodeBFunction/ImeisvTable/ImeisvProfile/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/LoadBalancingFunction/

//ManagedElement/ENodeBFunction/Paging/

//ManagedElement/ENodeBFunction/QciTable/QciProfileOperatorDefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfileOperatorDefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfileOperatorDefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfileOperatorDefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfileOperatorDefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfileOperatorDefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfilePredefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfilePredefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfilePredefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfilePredefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfilePredefined/

//ManagedElement/ENodeBFunction/QciTable/QciProfilePredefined/

//ManagedElement/ENodeBFunction/Rcs/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/ReportConfigA5Anr/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/ReportConfigA5Anr/

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/ReportConfigA5Anr/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/ReportConfigA5Anr/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/ReportConfigA5Anr/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5/ReportConfigA5Anr/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5ULTrig/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5ULTrig/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5UlTrig/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigA5UITrig/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2Cdma2000/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2Cdma2000/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2Geran/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2Geran/
```

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2GeranUITrig/
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2GeranUITrig/
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2GeranUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2GeranUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2Utra/
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2Utra/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2UtraUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2UtraUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2UtraUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2UtraUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigB2UtraUITrig/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraBestCell/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraBestCell/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraBestCell/ReportConfigEUtraBestCellAnr/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraBestCell/ReportConfigEUtraBestCellAnr/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraBestCell/ReportConfigEUtraBestCellAnr/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraIFBestCell/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraIFBestCell/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraIFBestCell/

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraInterFreqLb/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraInterFreqLb/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraInterFreqLb/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigEUtraInterFreqLb/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA1A2/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA6/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA6/
```

```

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA6/

```

```

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSCellA6/

```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```

```
//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/
```


//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/ReportConfigSearch/

//ManagedElement/ENodeBFunction/RlfProfile/

//ManagedElement/ENodeBFunction/RlfProfile/

//ManagedElement/ENodeBFunction/RlfProfile/

//ManagedElement/ENodeBFunction/RlfProfile/

//ManagedElement/ENodeBFunction/RlfProfile/

//ManagedElement/ENodeBFunction/Rrc/

//ManagedElement/ENodeBFunction/Rrc/

//ManagedElement/ENodeBFunction/Rrc/

//ManagedElement/ENodeBFunction/SectorCarrier/

//ManagedElement/ENodeBFunction/SectorCarrier/

//ManagedElement/ENodeBFunction/RadioBearerTable/SignalingRadioBearer/

//ManagedElement/ENodeBFunction/RadioBearerTable/SignalingRadioBearer/

//ManagedElement/ENodeBFunction/RadioBearerTable/SignalingRadioBearer/

//ManagedElement/ENodeBFunction/RadioBearerTable/SignalingRadioBearer/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UeMeasControl/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UtranFreqRelation/

//ManagedElement/ENodeBFunction/EUtranCellFDD/UtranFreqRelation/



Feature

Differentiated Admission Control

Differentiated Admission Control

Differentiated Admission Control

Differentiated Admission Control

Admission Control

Differentiated Admission Control

Admission Control

Admission Control

Admission Control

Differentiated Admission Control

Differentiated Admission Control

Admission Control

Differentiated Admission Control

Differentiated Admission Control

Automated Mobility Optimization
Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations
Automated Neighbor Relations
Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Carrier Aggregation

4CC DL Carrier Aggregation Extension

Carrier Aggregation

Carrier Aggregation

Configurable SCell Priority

Configurable SCell Priority

Configurable SCell Priority

Carrier Aggregation

Carrier Aggregation

Carrier Aggregation

Uplink Carrier Aggregation

Uplink Carrier Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Carrier Aggregation

Dynamic SCell Selection for Carrier
Aggregation

3CC DL Carrier Aggregation Extension

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Radio Bearer Service

Radio Bearer Service

Radio Bearer Service

Radio Bearer Service

Dynamic UE Admission Control

Uplink-Triggered Inter-Frequency Mobility

Inter-eNodeB Carrier Aggregation

Automated Neighbor Relations

Multi-Target RRC Connection Re-establishment

Release Inactive UE at High Load Handover

Release Inactive UE at High Load Handover

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Ericsson Lean Carrier

Dynamic UE Admission Control

PCI Conflict Reporting

PCI Conflict Reporting

Idle Mode Support

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Prioritization of VoLTE in Access Barring

Prioritization of VoLTE in Access Barring

Prioritization of VoLTE in Access Barring

Dynamic PUCCH

Dynamic PUCCH

Power Control

Data-Aware Uplink Scheduling

Configurable SCell Priority

Dynamic UE Admission Control

Dynamic UE Admission Control

Supplemental Downlink for Carrier
Aggregation

Automated Cell Capacity Estimation

Automated Cell Capacity Estimation

Automated Cell Capacity Estimation

Limited-Uplink-Aware IFLB

Random Access

Inter-Frequency Load Balancing

Random Access

Carrier Aggregation

Automated Mobility Optimization

Automated Mobility Optimization

Variable SR and CQI Periodicity

Power Control

Dynamic PUCCH

Dynamic PUCCH

256-QAM Downlink

Ericsson Lean Carrier

Dynamic UE Admission Control

Dynamic UE Admission Control

ICIC - Autonomous Resource Allocation

Dynamic UE Admission Control

Ericsson Lean Carrier

Service Specific HARQ

Limited-Uplink-Aware IFLB

Service Specific HARQ

Service Specific HARQ

Automated Mobility Optimization

Automated Mobility Optimization

Automated Mobility Optimization

Automated Mobility Optimization

Supplemental Downlink for Carrier
Aggregation

UE Throughput-Aware IFLB

UE Throughput-Aware IFLB

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Uplink Carrier Aggregation

Carrier Aggregation

Ericsson Lean Carrier

4CC DL Carrier Aggregation Extension

Data-Aware Uplink Scheduling

Uplink Scheduling Control for Out-of-Coverage UEs

Uplink Scheduling Control for Out-of-Coverage UEs

Scheduler

Dynamic Uplink Resource Allocation

Scheduler

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

PDCCH Power Boost

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

Enhanced PDCCH Link Adaptation

Power Control

Random Access

64-QAM Uplink

Idle Mode Support

Idle Mode Support

Idle Mode Support

Idle Mode Support

Idle Mode Support

Idle Mode Support

Idle Mode Support

Service Specific HARQ

Inactivity-Triggered PUCCH Release at High Load

Idle Mode Support

Dynamic UE Admission Control

Dynamic UE Admission Control

Data-Aware Uplink Scheduling

ICIC - Autonomous Resource Allocation
Uplink Carrier Aggregation

Uplink Scheduling Control for Out-of-Coverage UEs

Uplink-Triggered Inter-Frequency Mobility

Automated Mobility Optimization
Configurable SCell Priority

Automated Neighbor Relations

Best Neighbor Relations for Intra-LTE Load Management

Coverage-Adapted Load Management

Inter-Frequency Load Balancing

Carrier Aggregation

Configurable SCell Priority

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Progressive Access Barring

Data-Aware Uplink Scheduling

Configurable SCell Priority

Inter-Frequency Load Balancing

Automated Mobility Optimization

Automated Mobility Optimization

256-QAM Downlink
Ericsson Lean Carrier
Ericsson Lean Carrier

Service Specific HARQ
Limited-Uplink-Aware IFLB

Service Specific HARQ

Service Specific HARQ

Automated Mobility Optimization

Automated Mobility Optimization

Automated Mobility Optimization

Automated Mobility Optimization

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Load-Based Access Barring

Carrier Aggregation

Ericsson Lean Carrier

4CC DL Carrier Aggregation Extension

Data-Aware Uplink Scheduling

Uplink Scheduling Control for Out-of-Coverage UEs

Uplink Scheduling Control for Out-of-Coverage UEs

Idle Mode Support

Idle Mode Support

Idle Mode Support

Idle Mode Support

Idle Mode Support

Service Specific HARQ

Ericsson Lean Carrier

Data-Aware Uplink Scheduling

Uplink Scheduling Control for Out-of-Coverage UEs

Uplink-Triggered Inter-Frequency Mobility

Ericsson Lean Carrier

Automated Mobility Optimization

Automated Neighbor Relations

Configurable SCell Priority

Configurable SCell Priority

Carrier Aggregation-Aware IFLB

Idle Mode Support

Uplink-Triggered Inter-Frequency Mobility

Inter-Frequency Load Balancing

IFLB Activation Threshold

Best Neighbor Relations for Intra-LTE Load Management

Idle Mode Support

Idle Mode Support

Carrier Aggregation-Aware IFLB

Uplink-Triggered Inter-Frequency Mobility

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Coverage-Triggered GERAN Session Continuity

Load-based Distribution at Release

Load-based Distribution at Release

Load-based Distribution at Release

Load-based Distribution at Release

Load-based Distribution at Release

Ericsson Lean Carrier
Carrier Aggregation-Aware IFLB

Carrier Aggregation-Aware IFLB

Inter-Frequency Load Balancing

Carrier Aggregation-Aware IFLB

Best Neighbor Relations for Intra-LTE Load
Management

Best Neighbor Relations for Intra-LTE Load
Management

Best Neighbor Relations for Intra-LTE Load
Management

Best Neighbor Relations for Intra-LTE Load
Management

Coverage-Adapted Load Management

Inter-Frequency Load Balancing

Inter-Frequency Load Balancing

Inter-Frequency Load Balancing

UE Throughput-Aware IFLB

Ericsson Lean Carrier

QoS-Aware Scheduler

Delay-Based Scheduling and Grant
Estimation

QoS-Aware Scheduler

QoS-Aware Scheduler

Delay-Based Scheduling and Grant
Estimation

Delay-Based Scheduling and Grant
Estimation

QoS-Aware Scheduler

Delay-Based Scheduling and Grant
Estimation

QoS-Aware Scheduler

QoS-Aware Scheduler

Delay-Based Scheduling and Grant
Estimation

Delay-Based Scheduling and Grant
Estimation

Radio Bearer Service

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

UE Level Oscillating Handover Minimization

Ericsson Lean Carrier

Automated Neighbor Relations

Automated Neighbor Relations

Automated Neighbor Relations

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Inter-Frequency Load Balancing

Inter-Frequency Load Balancing

Inter-Frequency Load Balancing

Inter-Frequency Load Balancing

Dynamic SCell Selection for Carrier
Aggregation

Uplink Carrier Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Uplink Carrier Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier
Aggregation

Dynamic SCell Selection for Carrier Aggregation

Dynamic SCell Selection for Carrier Aggregation

Dynamic SCell Selection for Carrier Aggregation

Dynamic SCell Selection for Carrier Aggregation

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Uplink-Triggered Inter-Frequency Mobility

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

Multi-Target RRC Connection Re-establishment

256-QAM Downlink

Uplink Coordinated Multi-Point Reception

Radio Bearer Service

Radio Bearer Service

Radio Bearer Service

Radio Bearer Service

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Automated Neighbor Relations

Automated Neighbor Relations

Inter-Frequency Load Balancing

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Mobility Control at Poor Coverage

Uplink-Triggered Inter-Frequency Mobility

Automated Neighbor Relations

Coverage-Triggered WCDMA Session
Continuity