

Custom Arduino
Variant: [No Variations]

8/30/2023
V 1I1

RELEASED 30-AUG-2023

Page	Index	Page	Index	Page	Index	Page	Index
1	COVER PAGE	11		21		31	
2	BLOCK DIAGRAM	12		22		32	
3	28PINS SCHEMATIC	13		23		33	
4	REVISION HISTORY	14		24		34	
5		15		25		35	
6		16		26		36	
7		17		27		37	
8		18		28		38	
9		19		29		39	
10		20		30		40	

DESIGN CONSIDERATIONS


DESIGN NOTE:
Example text for informational
design notes.

DESIGN NOTE:
Example text for cautionary
design notes.

DESIGN NOTE:
Example text for debug notes.

DESIGN NOTE:
Example text for critical
design notes.


LAYOUT NOTE:
Example text for critical
layout guidelines.



Levin Tech		www.levintech-bd.com	
Title:	Custom Arduino	Variant:	[No Variations]
Page Contents:	[01] - COVER PAGE.SchDoc		Checked by
Size:	DWG NO		Revision: V 1I1
Date:	8/30/2023	*	Sheet 1 of 5

Custom Arduino


(Block Diagram)




Levin Tech		www.levintech-bd.com	
Title:	Custom Arduino		Variant: [No Variations]
Page Contents:	[02] - BLOCK DIAGRAM.SchDoc		Checked by
Size:	DWG NO		Revision: V III
Date: 8/30/2023	*		Sheet 2 of 5

28 Pins - Schematics


micro USB




POWER




POWER PADS




POWER LED




USER LED




RESET (16U2)



RESET (328P)



USER BUTTON




DESIGN NOTE:
This board supports 5V or 3V3 voltage level on the IO pins:
1) 5V IO - Fit everything as defined in this schematic. NF means, do not fit this component.
2) 3.3V IO - Remove R27, Fit R28, *Replace Y1 (change from 16MHz to 10MHz), *Replace Y2 (change from 16MHz to 8MHz).
3) Both 5V and 3V3, selected through JP4 - Remove R27, Remove R28, Fit JP4, *Replace Y1 (change from 16MHz to 10MHz), *Replace Y2 (change from 16MHz to 8MHz).
*Note: The 16MHz crystals are not recommended for 3.3V operation. We need to adjust their values, that's why the change.
IMPORTANT: Once you change the crystal value, you may need to re-compile your source code.


DESIGN NOTE:
About JP3:
1) DebugWire support - Short 1&2. This was added to support possible debugWire debugging (programming?) of 328P through 16U2. In this case, the 16U2 needs to have a correct firmware and has to behave as a debugWire tool.
2) ISP programmer mode - Short 2&3. In this case, take a cable and connect J5 & J6 together. Upload AVRISP MKII firmware into 16U2 and you can program 328P. Example of AVRISP MKII firmware can be found at LUFA projects: <http://www.fourvallecubicle.com/LUFA.php> (Tip: remap LEDs of the default AVRISP MKII LUFA project to the RX and TX LEDs on the 28Pin board)
3) ISP header - Short 3 & 4. In this mode, the ICSP1 header is used as a standard ISP header

DESIGN NOTE:
About JP1:
1) Autoreset Enabled - Short 1&2. In this case, 16U2 is used to reset 328P when firmware inside 328P is updated from Arduino IDE.
2) 16U2 DFU mode Enabled - Short 2&3. 16U2 HWB pin is sampled by 16U2 during RESET. If pulled low, then after Reset the 16U2 will go into DFU mode (it's the mode when you can flash 16U2 firmware through USB and Atmel Flip software: <http://www.atmel.com/tools/flip.aspx>).

3V3 LDO



Power Selection




DESIGN NOTE:
This board can be powered from micro USB connector (J7) or a single +3.3V power rail (through J1 pin 4). If +3.3V is used, fit R26 and R28. In this case, JP4 & R27 must NOT be fitted, otherwise the board may be damaged.

DIP SOCKET



MOUNTING HOLES



Mounting holes 7.4mm pad 3.2mm drill
BOARD MOUNTING HOLES
ONE IN EACH CORNER

FIDUCIALS



LAYOUTNOTE:
1) Route all the POWER tracks with minimum track width 0.4mm.
2) Route all the other tracks by 0.4mm and change them by the end of the design to 0.2mm. To change all of them at once, use this filter "(not InNet('+'*)) and not InNet('GND')) and IsTrack and (OnLayer('L1') or OnLayer('L2'))" and then set 0.2mm width in PCB Inspector panel.

Levin Tech		www.levintech-bd.com	
Title:	Custom Arduino	Variant:	[No Variations]
Page Contents:	[03] - 28PINS SCHEMATIC.SchDoc	Checked by	
Size:	DWG NO	Revision:	V III
Date:	8/30/2023	Designed By	Imrul Kais Khan
Sheet	3	of	5

1	2	3	4	5	6	7	8																																									
REVISION HISTORY																																																
A								A																																								
B								B																																								
C								C																																								
D	<table><tr><td colspan="2">Levin Tech</td><td colspan="6">www.levintech-bd.com</td></tr><tr><td>Title:</td><td colspan="2">Custom Arduino</td><td colspan="5">Variant: [No Variations]</td></tr><tr><td>Page Contents:</td><td colspan="4">[04] - REVISION HISTORY.SchDoc</td><td colspan="3">Checked by</td></tr><tr><td>Size:</td><td colspan="5">DWG NO</td><td colspan="2">Revision: V III</td></tr><tr><td>Date:</td><td colspan="2">8/30/2023</td><td colspan="2">*</td><td colspan="3">Sheet 4 of 5</td></tr></table>							Levin Tech		www.levintech-bd.com						Title:	Custom Arduino		Variant: [No Variations]					Page Contents:	[04] - REVISION HISTORY.SchDoc				Checked by			Size:	DWG NO					Revision: V III		Date:	8/30/2023		*		Sheet 4 of 5			D
Levin Tech		www.levintech-bd.com																																														
Title:	Custom Arduino		Variant: [No Variations]																																													
Page Contents:	[04] - REVISION HISTORY.SchDoc				Checked by																																											
Size:	DWG NO					Revision: V III																																										
Date:	8/30/2023		*		Sheet 4 of 5																																											
1	2	3	4	5	6	7	8																																									