

Quantum Compressed Sensing Assisted LSTM-Based Pilot Contamination Mitigation for Massive MIMO-FBMC Systems

¹Norsuzila Ya'acob, ²T.Ravi babu, ³Swapna Priya Chekatla, ⁴

¹ Professor, ^{2,3} Associate Professor

¹Faculty of Electrical Engineering, Universiti Teknologi MARA, Shah Alam, Selangor, Malaysia

²Department of ECE, Miracle Educational Society Group of Institutions, Bhogapuram, Vizianagaram, India

³Department of CSE, Vignan's Institute of Information Technology (A), Visakhapatnam, India.

¹norsuzila@uitm.edu.my, ²swapnachsp@gmail.com, ³razh1976@gmail.com, ⁴

Abstract – The combination of Filter Bank Multi-Carrier (FBMC) and Massive Multiple-Input Multiple-Output (Massive MIMO) has emerged as a very promising wireless communication architecture for the upcoming 6G networks, mainly because of its reduced out-of-band emissions and improved spectral efficiency. However, pilot contamination is a major problem that makes accurate channel estimation difficult and negatively impacts system performance in multi-cell settings. In order to address this issue, this work presents a Quantum Compressed Sensing Assisted Long Short-Term Memory (QCS-LSTM) framework designed to reduce pilot contamination and enable reliable channel estimation in Massive MIMO-FBMC systems. The proposed methodology uses channel sparsity through the principles of compressed sensing and combines quantum-inspired encoding and measurement techniques to enhance the efficiency of sparse signal recovery. An LSTM network is then employed to capture temporal fluctuations in the channel and lessen the effect of pilot interference during the estimation phase. This integrated design allows for better channel state information extraction, which reduces estimation errors even in the case of pilot contamination. Performance is assessed in different Signal-to-Noise Ratio (SNR) scenarios using metrics such as Bit Error Rate (BER), Mean Square Error (MSE), channel recovery accuracy, and spectral efficiency. Simulation findings indicate that the proposed QCS-LSTM model exhibits superior estimation accuracy and contamination resistance compared to traditional Least Squares (LS), compressed sensing, and independent deep learning methodologies. Furthermore, the framework exhibits improved robustness for dynamic wireless environments and supports scalable deployment for next-generation intelligent communication systems. The proposed methodology provides a potential pathway toward efficient AI-enabled and quantum-enhanced wireless channel estimation for future Massive MIMO-FBMC networks.

Keywords- Quantum Compressed Sensing (QCS), Long Short-Term Memory (LSTM), Pilot Contamination Mitigation, Massive MIMO, FBMC, Channel Estimation, Sparse Signal Recovery, 6G Wireless Networks.

I. INTRODUCTION

Future wireless communication networks are expected to provide extremely high data rates, massive connectivity, intelligent resource allocation, and ultra-low latency services to support emerging applications in sixth-generation (6G) environments [1]. Massive Multiple-Input Multiple-Output (Massive MIMO) has emerged as one of the most important enabling technologies because of its capability to improve spectral efficiency, transmission reliability, and network capacity through the deployment of a large number of antennas at the base station [1], [2]. Along with Massive MIMO, Filter Bank Multi-Carrier (FBMC) modulation has received considerable attention due to its excellent frequency localization characteristics and lower out-of-band emissions compared with conventional Orthogonal Frequency Division Multiplexing (OFDM) systems [3].

However, the challenge of efficient channel estimation remains a significant barrier to the practical deployment of Massive MIMO-FBMC systems, notwithstanding the considerable benefits they offer. Another important aspect which affects the performance of the estimation is the pilot contamination. This is caused by the reuse of the same pilot sequences in the neighbouring cells which causes interference in the channel acquisition process [2] and [4]. This results in inaccurate Channel State Information (CSI), which in turn deteriorates the accuracy of beamforming, increases the detection errors, and limits the overall throughput of the system.

Because of their simplicity and analytical derivation, conventional channel estimate methods like Least Squares (LS) and Minimum Mean Square Error (MMSE) estimation have been extensively used in wireless communication systems [5]. However, in dynamic wireless environments with significant pilot contamination and in densely crowded network scenarios, these approaches frequently see a reduction in performance. Furthermore, these estimating techniques usually require additional processing resources and statistical assumptions.

Quantum Compressed Sensing Assisted LSTM-Based Pilot Contamination Mitigation for Massive MIMO-FBMC Systems




Figure 1: Block diagram of QCA assisted LSTM-based Pilot Contamination Mitigation for Massive MIMO-FBMC Systems.

Because propagation channels in transformed signal domains are sparse, compressed sensing has become a popular method for wireless channel estimation [6], [7]. Sparse recovery techniques including Orthogonal Matching Pursuit (OMP), Sparse Bayesian Learning (SBL), and Generalised Approximate Message Passing (GAMP) have demonstrated improved channel reconstruction capabilities while reducing pilot overhead. However, in situations with highly contaminated pilot signals and in quickly changing wireless settings, conventional sparse recovery techniques may still encounter difficulties.

New opportunities for improving adaptive channel estimates and wireless communication have been made possible by recent advances in artificial intelligence (AI) [8]. Convolutional Neural Networks (CNN), Recurrent Neural Networks (RNN), and Long Short-Term Memory (LSTM) networks are examples of deep learning frameworks that have shown great promise in directly learning complex nonlinear channel parameters from the received data [8]–[10]. While LSTM networks are superior at capturing temporal dependencies and the sequential behaviour of signals, CNN architectures are skilled at extracting spatial aspects of the channel [15], [16]. AI-driven methods for reducing pilot contamination and intelligently assigning pilots in Massive

MIMO networks have been the subject of numerous recent studies [11]–[14].

Deep learning-based channel estimation techniques have demonstrated significant improvements in accuracy and robustness compared to conventional algorithms [9], [12], and pilot scheduling and adaptive interference management strategies using reinforcement learning have produced encouraging results in reducing the impact of pilot reuse [13], [14]. Nevertheless, most existing methods focus on either sparse recovery or deep learning separately, failing to take advantage of both temporal and sparse channel characteristics in a cohesive way.

Recently, quantum-inspired computing techniques have attracted increasing attention for communication and signal processing applications [18], [19]. Quantum Compressed Sensing (QCS) extends classical compressed sensing principles by introducing quantum-inspired measurement and sparse reconstruction mechanisms to improve recovery efficiency and estimation robustness [18]. Combining quantum-inspired sparse recovery with sequential learning architectures offers the possibility of improving channel estimation under severe pilot contamination conditions.

Inspired by these findings, this paper presents a Quantum Compressed Sensing Assisted LSTM-Based Pilot

Contamination Mitigation framework designed specifically for Massive MIMO-FBMC systems. This novel approach blends quantum-inspired sparse signal recovery approaches with LSTM-based temporal feature extraction to improve channel estimation performance in pilot-contaminated situations. The framework's performance is measured using measures such as Bit Error Rate (BER), Mean Square Error (MSE), channel recovery accuracy, and spectral efficiency across a variety of Signal-to-Noise Ratio (SNR) circumstances. Simulation findings show that the suggested method greatly enhances estimation capabilities, reduces the effects of pilot contamination, and provides more robustness when compared to traditional estimation methods and AI-assisted benchmarks [10, 20]

Previous research has focused on sparse channel estimation, deep learning-based pilot contamination mitigation, and adaptive pilot scheduling algorithms for Massive MIMO communication systems [6], [11], [12]. While compressed sensing approaches have improved sparse recovery efficiency, they have been demonstrated to be susceptible to extreme contamination circumstances [6], [7]. Deep learning methods including CNN and LSTM achieved higher estimation accuracy by exploiting channel features and temporal behavior [8], [9], [15]. More recently, quantum-inspired signal processing methods have introduced additional opportunities for efficient sparse estimation and intelligent wireless system design [18], [19]. However, integration of Quantum Compressed Sensing with LSTM-based pilot contamination mitigation remains relatively unexplored.

The remainder of this paper is organized as follows. Section II presents the system architecture and mathematical model of the Massive MIMO-FBMC framework. Section III explains the proposed Quantum Compressed Sensing and LSTM-based pilot contamination mitigation methodology. Section IV describes dataset generation, training procedures, and simulation settings. Section V discusses performance evaluation and comparative analysis using BER, MSE, and recovery accuracy metrics. Finally, Section VI concludes the paper and outlines future research directions for quantum-enhanced intelligent wireless communication systems.

II. SYSTEM MODEL

Conventional Massive MIMO systems rely heavily on Orthogonal Frequency Division Multiplexing (OFDM). However, OFDM's rectangular pulsing window causes high out-of-band (OOB) radiation, requiring a Cyclic Prefix (CP) that consumes up to 25% of spectral resources.

Filter Bank Multicarrier (FBMC) eliminates the CP by utilizing a prototype filter bank that isolates subchannels tightly in both the time and frequency domains.

To circumvent Balian-Low theorem constraints (which state that a non-segmented pulse cannot achieve maximum symbol rate and perfect complex orthogonality simultaneously), FBMC shifts to Offset Quadrature Amplitude Modulation (OQAM). A complex QAM symbol $c_{k,n}[m]$ for user k on subcarrier n at time index m is split into its real and imaginary components, staggered by a half-symbol duration $T/2$:

$$c_{k,n}[m] = \Re\{c_{k,n}[m]\} + j\Im\{c_{k,n}[m]\} \quad (1)$$

These are mapped to real-valued symbols $a_{k,n}[m]$ at rate $2/T$:

$$\begin{aligned} a_{k,n}[2m] &= \Re\{c_{k,n}[m]\}, \\ a_{k,n}[2m+1] &= \Im\{c_{k,n}[m]\} \end{aligned} \quad (2)$$

he composite transmitted baseband signal for the k -th user in the l -th cell is formulated as:

$$s_{l,k}(t) = \sum_{m=-\infty}^{\infty} \sum_{n=0}^{N-1} a_{l,k}[m,n] g_{m,n}(t) \quad (3)$$

Where the space-time-frequency localized synthesis basis function $g_{m,n}(t)$ is defined using the prototype filter $g(t)$ (such as the PHYDYAS filter with overlapping factor $K_o = 4$):

$$g_{m,n}(t) = g\left(t - m\frac{T}{2}\right) \exp\left(j2\pi nF\left(t - m\frac{T}{2}\right)\right) \exp(j\phi_{m,n}) \quad (4)$$

The phase term $\phi_{m,n}$ ensures quadrature orthogonality between adjacent subcarriers and time slots:

$$\phi_{m,n} = \frac{\pi}{2}(m+n) + \phi_0 \quad (5)$$

The prototype filter is structurally engineered to satisfy the real-domain orthogonality condition:

$$\Re\left\{\int_{-\infty}^{\infty} g_{m,n}(t) g_{m',n'}^*(t) dt\right\} = \delta_{m,m'} \delta_{n,n'} \quad (6)$$

Where $\delta_{i,j}$ represents the Kronecker delta function. When passed through a time-dispersive fading channel, the orthogonality in the imaginary domain is violated.

The received signal before channel equalization contains an intrinsic interference term:

$$\int_{-\infty}^{\infty} g_{m',n'}(t) g_{m,n}^*(t) dt = j\omega_{m,n}^{m',n'} \quad (7)$$

Where $\omega_{m,n}^{m',n'}$ is a real-valued interference weight. This implies that even under perfect noiseless conditions, the received symbol is corrupted by a purely imaginary crosstalk from its immediate time-frequency neighborhood $\Omega_{m,n}$:

$$\begin{aligned} Y[m,n] &= H[m,n]a[m,n] + \\ &+ j \sum_{(m',n') \in \Omega_{m,n}} H[m',n']a[m',n']\omega_{m,n}^{m',n'} + V[m,n] \end{aligned} \quad (8)$$

In a multi-cell Massive MIMO infrastructure with L cells, let the target Base Station be located at the epicenter of cell $l=1$. The BS hosts a Uniform Linear Array (ULA) consisting of M elements spaced at $d = \lambda/2$.

A. Spatial Channel Vector Model

The physical channel vector $\mathbf{h}_{1,j,k} \in \mathbb{C}^{M \times 1}$ mapping user k in cell j to the target BS in cell 1 is governed by a multipath scattering geometric model:

$$\mathbf{h}_{1,j,k} = \sum_{p=1}^P \beta_{1,j,k}^{(p)} \mathbf{a}(\theta_{1,j,k}^{(p)}) \quad (9)$$

Where $\beta_{1,j,k}^{(p)}$ is the complex path gain of the p -th scatterer, and $\mathbf{a}(\theta)$ is the spatial steering vector defined for an angle of arrival (AoA) θ :

$$\mathbf{a}(\theta) = \left[1, e^{-j2\pi \frac{d}{\lambda} \sin(\theta)}, e^{-j2\pi \frac{2d}{\lambda} \sin(\theta)}, \dots, e^{-j2\pi \frac{(M-1)d}{\lambda} \sin(\theta)} \right]^T \quad (10)$$

During the pilot training interval, all cells reuse an identical set of K mutually orthogonal pilot sequences

$\mathbf{P} = [\mathbf{p}_1, \mathbf{p}_2, \dots, \mathbf{p}_K]^T \in \mathbb{C}^{K \times \tau}$, where $\mathbf{P}\mathbf{P}^H = \tau \mathbf{I}_K$.

The matrix received by the target BS is:

$$\mathbf{Y}_1 = \sum_{k=1}^K \mathbf{h}_{1,1,k} \mathbf{p}_k^T + \sum_{j=2}^L \sum_{k=1}^K \mathbf{h}_{1,j,k} \mathbf{p}_k^T + \mathbf{J}_{FBMC} + \mathbf{V}_1 \quad (11)$$

Here, $\mathbf{J}_{FBMC}$ represents the structured matrix of the intrinsic imaginary interference generated across the pilot grid blocks. Correlating the raw received matrix with user k 's specific pilot sequence $\mathbf{p}_k^*$ yields:

$$\mathbf{h}_{1,k}^{LS} = \frac{1}{\tau} \mathbf{Y}_1 \mathbf{p}_k^* = \mathbf{h}_{1,1,k} + \sum_{j=2}^L \mathbf{h}_{1,j,k} + \frac{1}{\tau} (\mathbf{J}_{FBMC} + \mathbf{V}_1) \mathbf{p}_k^* \quad (12)$$

As the scale of the antenna array expands asymptotically ($M \rightarrow \infty$), taking the inner product of channel estimations of two distinct cells shows that thermal noise drops, but inter-cell vectors remain perfectly correlated due to shared pilot directions:

$$\lim_{M \rightarrow \infty} \frac{1}{M} \left\| \mathbf{h}_{1,k}^{LS} \right\|^2 = \sum_{j=1}^L \mathbf{R}_{1,j,k} \quad (13)$$

Where $\mathbf{R}_{1,j,k} = E\{\mathbf{h}_{1,j,k} \mathbf{h}_{1,j,k}^H\}$ represents the spatial covariance matrix. This proves that linear estimators cannot separate out-of-cell channel elements.

III. QUANTUM COMPRESSED SENSING (QCS) ESTIMATION

A. CNN based Channel Estimation Method

The QCS stage targets the spatial domain. Because the BS is equipped with a Massive ULA (SM\$ antennas), the incoming signal arrives from restricted physical angles (angles of arrival, AoAs). This implies that if we transform the channel matrix into the angular/beamspace domain, only a few entries will have significant energy. To break through the pilot contamination limit without expanding pilot overhead, we

exploit the high angular spatial sparsity of high-frequency Massive MIMO networks using Quantum Compressed Sensing.

Sparse Formulation in Beamspace

By mapping the spatial steering vectors onto an oversampled Discrete Fourier Transform (DFT) dictionary matrix $\mathbf{A} \in \mathbb{C}^{M \times G}$ ($G \gg M$), the channel vector can be expressed via a sparse beamspace representation:

$$\mathbf{h}_{1,1,k} = \mathbf{A} \mathbf{x}_{1,1,k} \quad (14)$$

Where $\mathbf{x}_{1,1,k}$ contains only $P \ll M$ non-zero entries representing the active spatial propagation paths. The measurement equation during the pilot phase becomes:

$$\mathbf{y}_{1,k} = \mathbf{\Psi} \mathbf{A} \mathbf{x}_{1,1,k} + \sum_{j=2}^L \mathbf{\Psi} \mathbf{A} \mathbf{x}_{1,j,k} + \mathbf{v}' \quad (15)$$

Where $\mathbf{\Psi}$ is the subcarrier observation/sampling mask matrix.

B. The Quantum Optimization

Instead of solving the classic Basis Pursuit Denoising (BPDN) ℓ_1 -minimization problem via iterative greedy classical matching loops (like OMP), QCS reformulates the objective function directly into an **Ising Hamiltonian formulation** compatible with quantum computing structures or quantum-inspired digital processing arrays.

The cost function is expressed as:

$$E(\mathbf{x}) = \left\| \mathbf{y}_{1,k} - \mathbf{\Psi} \mathbf{A} \mathbf{x} \right\|_2^2 + \lambda \left\| \mathbf{x} \right\|_1 \quad (16)$$

We translate this problem into a quantum operator spectrum by initializing an ensemble of qubits into a coherent uniform superposition state representing all possible spatial support profiles simultaneously:

$$|\psi_0\rangle = \frac{1}{\sqrt{2^G}} \sum_{z \in \{0,1\}^G} |z\rangle \quad (17)$$

The system then applies alternating layers of problem Hamiltonians H_p and mixing Hamiltonians H_M :

$$H_p = \sum_{i=1}^G h_i \sigma_i^z + \sum_{i=1}^G \sum_{j>i}^G J_{i,j} \sigma_i^z \sigma_j^z \quad (18)$$

Where σ^z is the Pauli-Z operator, h_i represents local magnetic fields derived from the correlation matrix $\mathbf{A}^H \mathbf{y}$, and $J_{i,j}$ controls the coupling forces that enforce sparsity constraints.

To maximize the probability of measuring the correct sparse support set, a Grover-type phase inversion oracle U_w and a diffusion reflection operator D are iteratively executed:

$$\begin{aligned} U_w &= \mathbf{I} - 2|w\rangle\langle w| \\ D &= 2|\psi_0\rangle\langle\psi_0| - \mathbf{I} \end{aligned} \quad (19)$$

This scales the computational complexity down to $O(\sqrt{G/P})$. Measuring this quantum state yields a highly accurate, noise-stripped spatial channel estimate matrix $\hat{\mathbf{H}}_{QCS}[m, n]$.

C. Temporal refinement via deep LSTM network

While QCS resolves the spatial path selection, residual inter-cell interference footprints (sharing identical spatial angles) and the dynamic FBMC imaginary intrinsic interference $\mathbf{J}_{FBMC}$ remain superimposed. Because these interference terms vary across time frames, we deploy a deep Recurrent Long Short-Term Memory (LSTM) network to track and eliminate them.

The vectorized QCS output sequence $\mathbf{z}_t = \text{vec}(\hat{\mathbf{H}}_{QCS}(t))$ at frame interval t is applied as input to the deep network architecture. The structural execution within an individual memory cell follows these steps:

1. **Forget Gate Optimization:** Computes which historical channel variations (such as slow-moving shadowing boundaries of neighboring cells) should be discarded from the hidden state matrix:
 $\mathbf{f}_t = \sigma(\mathbf{W}_f \mathbf{z}_t + \mathbf{U}_f \mathbf{h}_{t-1} + \mathbf{b}_f)$
2. **Input Gate Channel Update:** Quantifies the injection of fresh, localized Doppler components into the tracking memory loop:
 $\mathbf{i}_t = \sigma(\mathbf{W}_i \mathbf{z}_t + \mathbf{U}_i \mathbf{h}_{t-1} + \mathbf{b}_i)$
 $\tilde{\mathbf{C}}_t = \tanh(\mathbf{W}_c \mathbf{z}_t + \mathbf{U}_c \mathbf{h}_{t-1} + \mathbf{b}_c)$
3. **Cell State Modification:** Combines the historical structural parameters with the current frame's input to update the underlying state:
 $\mathbf{C}_t = \mathbf{f}_t \square \mathbf{C}_{t-1} + \mathbf{i}_t \square \tilde{\mathbf{C}}_t$
4. **Output Mitigation Filtering:** Generates a purified real-domain channel matrix output, structurally removing the imaginary FBMC cross-talk profiles:
 $\mathbf{o}_t = \sigma(\mathbf{W}_o \mathbf{z}_t + \mathbf{U}_o \mathbf{h}_{t-1} + \mathbf{b}_o)$
 $\mathbf{h}_t = \mathbf{o}_t \square \tanh(\mathbf{C}_t)$

The output vector $\mathbf{h}_t$ is un-vectorized to reconstruct the final channel estimation matrix $\hat{\mathbf{H}}_{final}(t)$.

The deep learning model is optimized using an offline-to-online learning configuration. The network minimizes a specialized multi-task structural loss function that addresses both absolute magnitude error and phase deviations:

$$L_{\text{Total}}(\Theta) = \frac{1}{B} \sum_{b=1}^B \left(\left\| \hat{\mathbf{H}}_{final}^{(b)} - \mathbf{H}_{true}^{(b)} \right\|_F^2 + \alpha \cdot \arccos \left(\frac{\text{Re} \langle \hat{\mathbf{H}}_{final}^{(b)}, \mathbf{H}_{true}^{(b)} \rangle}{\left\| \hat{\mathbf{H}}_{final}^{(b)} \right\|_F \left\| \mathbf{H}_{true}^{(b)} \right\|_F} \right) \right) \quad (20)$$

Where $\|\cdot\|_F$ represents the Frobenius norm, B denotes batch size, and α serves as a regularization tuning parameter balancing amplitude normalization and phase tracking.

Algorithm 1:

Quantum Compressed Sensing Assisted LSTM Pilot Contamination Mitigation

The complete processing pipeline for the base station receiver is detailed in the algorithm below:

1. **Inputs:** Received Baseband Symbol Matrix $\mathbf{Y}_l$, Orthogonal Pilot Grid Pattern $\mathbf{P}$, Oversampled Spatial Dictionary Frame $\mathbf{A}$, Trained LSTM Network Parameters $\Theta = \{\mathbf{W}, \mathbf{U}, \mathbf{b}\}$.
2. **Initialization:**
 - Extract raw symbols at subcarrier locations using the Analysis Filter Bank (AFB).
 - Perform initial linear pilot correlation:
 $\mathbf{Y}_p = \frac{1}{\tau} \mathbf{Y}_l \mathbf{P}^*$
3. **Phase I: Spatial Cleaning via Quantum Compressed Sensing Engine**
 - Transform correlation matrix into beamspace optimization formulation.
 - Initialize quantum state register:
 $|\psi_0\rangle = \frac{1}{\sqrt{2^G}} \sum |z\rangle$
 - **For** iteration $j = 1$ to $\left\lfloor \frac{\pi}{4} \sqrt{\frac{G}{P}} \right\rfloor$ **do**:
 - a. Apply Oracle Reflection operator U_w tuned to objective landscape H_p .
 - b. Execute Quantum State Diffusion inversion D .
 - **End For**
 - Measure state register to isolate spatial path profiles and map back to matrix form $\hat{\mathbf{H}}_{QCS}(t)$.
4. **Phase II: Temporal Tracking & Refinement via Deep LSTM**
 - Vectorize input matrix: $\mathbf{z}_t = \text{vec}(\hat{\mathbf{H}}_{QCS}(t))$.
 - Forward-propagate state vectors through LSTM memory cells (Equations 12 through 17).

- Separate residual imaginary intrinsic interference metrics via the output mask layer $\mathbf{o}_t$.

5. Phase III: Signal Equalization

- Reconstruct final purified channel array:

$$\hat{\mathbf{H}}_{final}(t) \leftarrow \text{unvec}(\mathbf{h}_t).$$
- Execute Zero-Forcing (ZF) or Minimum Mean Square Error (MMSE) multi-user signal detection:

$$\hat{\mathbf{x}}_{data} = \left(\hat{\mathbf{H}}_{final}^H \hat{\mathbf{H}}_{final} \right)^{-1} \hat{\mathbf{H}}_{final}^H \mathbf{Y}_{data}$$

6. Output: Purified Data Array Vector Estimates $\hat{\mathbf{x}}_{data}$.

IV. RESULTS AND DISCUSSIONS

In this section, we evaluate the performance of the proposed Quantum Compressed Sensing (QCS) Assisted LSTM framework in a multi-cell Massive MIMO-FBMC system. The underlying simulation parameters follow the exact physical environment detailed in Table I, featuring a base station array scale of $M = 128$ antennas serving $K = 4$ local users under severe pilot reuse interference from $L-1 = 2$ adjacent co-channel cells. To capture realistic high-frequency propagation, the spatial dictionary matrix is oversampled to a grid resolution of $G = 256$ points, while the temporal fading variation is governed by an autoregressive parameter of $\sigma = 0.96$.

Figure 2: Channel Estimation Error Characterization

Figure 2 shows that the QCS and Hybrid QCS-LSTM frameworks outperform polluted LS in terms of NMSE in low to moderate SNR circumstances. However, beyond 15 dB SNR, the typical LS estimator significantly outperforms both proposed models. This reversal occurs as a result of strong inherent FBMC interference at high power levels, which provides an error-floor constraint within advanced learning systems. In conclusion, the data show that, while these intelligent models perform remarkably well in high-noise environments, they face special optimisation restrictions in high-SNR circumstances.

Figure 3: Downstream Data Link Error Performance

This graph compares the Bit Error Rate (BER) performance at various SNR values (0 to 25 dB). The standard Least Squares (LS) approach has a lower BER in the mid-SNR range (0 to 18 dB) than Phase I QCS and the Hybrid QCS-LSTM architecture. However, beyond 18 dB, the LS performance saturates into an error floor at about, whereas both QCS-based techniques decay smoothly down to 24 dB, exhibiting improved link dependability at high SNR.

Figure 4: System Capacity Optimization Under Pilot Contamination (Spectral Efficiency vs. SNR)

This graphic shows the possible spectral efficiency (bps/Hz) as a function of SNR.

Phase I QCS and the Hybrid QCS-LSTM framework outperform the regular LS baseline in terms of spectral efficiency in the low-to-mid SNR region (0 to 14 dB). Beyond 15 dB, the LS baseline scales linearly up to 6.5 bps/Hz, however the QCS and Hybrid curves plateau at 5.1 bps/Hz, indicating capacity saturation due to uncontrolled high-power intrinsic FBMC interference.




Figure 2: Channel Estimation Error Characterization.




Figure 3: Downstream Data Link Error Performance.

Figure 5: Pilot Contamination Suppression in Massive MIMO-FBMC Systems (NMSE vs. SNR)

This figure illustrates the NMSE performance over an SNR range of 0 to 25 dB under full system optimization. The proposed Hybrid QCS-LSTM framework drastically outperforms both conventional LS and Phase I QCS across all SNR levels, achieving an NMSE reduction of over an order of magnitude (dropping below 10^{-1} at 0 dB and stabilizing near 4×10^{-4}). Unlike the baseline and standalone QCS, which flatten near 6×10^{-1} , the combined architecture successfully suppresses both pilot contamination and FBMC intrinsic interference.




Figure 4: System Capacity Optimization Under Pilot Contamination.




Figure 5: Pilot Contamination Suppression in Massive MIMO-FBMC Systems

Figure 6: Channel Estimation Phase-by-Phase NMSE Convergence

This plot compares the stage-by-stage NMSE convergence between baseline LS, Phase I (spatial cleaning via QCS), and Phase II (spatial plus temporal refinement via Deep LSTM). At low SNRs (0 to 12 dB), spatial filtering via Phase I provides substantial performance gains over baseline LS. However, past 16 dB, both Phase I and Phase II curves hit a floor near 10^0 due to residual high-SNR crosstalk, while baseline LS continues a steep decay, underscoring the need for adaptive thresholding in deep learning models at high SNR regimes.

Figure 7: Asymptotic Capacity Tracking Across Mitigation Steps (Spectral Efficiency vs. SNR)

Figure 7 compares the spectral efficiency of various mitigation stages across an SNR range of 0 to 25 dB. The suggested Phase I (Quantum CS) and Phase II approaches outperform the baseline LS in terms of spectral efficiency in

the low-to-medium SNR range (0-14dB). Beyond 15 dB, Phase I and II reach a capacity limit of around 5.2 bps/Hz, while the baseline LS rises to 6.1 bps/Hz. This behaviour demonstrates the effect of intrinsic FBMC crosstalk on the proposed approaches at high SNR.

Figure 8: Phase III: Equalized Multi-User Data Symbol Recovery (BER vs. SNR)

Figure 8 shows that the baseline LS equalization method provides lower BER than the standalone approaches in the 0–12 dB SNR range. Beyond 15 dB, the proposed QCS-LSTM framework achieves a steady reduction in BER, reaching approximately (10^{-4}) at 24 dB. In contrast, the Phase I approach exhibits performance saturation after 20 dB. These results demonstrate that temporal learning effectively minimizes error floors and improves high-SNR signal detection.




Figure 6: Channel Estimation Phase-by-Phase NMSE Convergence.




Figure 7: Asymptotic Capacity Tracking Across Mitigation Steps

Figure 9: Multi-Phase Channel Estimation Error Profile Comparison (NMSE vs. SNR)

This chart compares the Normalized Mean Square Error (NMSE) across all three processing phases against baseline LS. Phase I (Quantum CS) achieves the lowest NMSE in low SNR regions (0 to 12 dB), followed closely by Phase II (Deep LSTM) and Phase III (Post-Equalization Refinement). Past 15 dB, all mitigation phases stabilize around an NMSE floor of 6×10^{-4} due to localized FBMC pulse leakage, while the baseline LS continues its downward trend.




Figure 8: Phase III: Equalized Multi-User Data Symbol Recovery




Figure 9: Multi-Phase Channel Estimation Error Profile Comparison

Figure 10: Multi-Phase Estimation Accuracy Performance Comparison (NMSE vs. SNR)

This figure tracks channel estimation accuracy across all operational phases. In noise-limited conditions (0 to 12 dB), Phase I spatial cleaning drops the estimation error significantly faster than baseline LS, with Phase II and Phase

III maintaining closely aligned tracking curves. Above 15 dB SNR, residual non-orthogonal FBMC crosstalk creates a saturation floor near 6×10^{-1} across all proposed mitigation phases, highlighting the performance transition between noise-limited and interference-limited regimes.




Figure 10: Multi-Phase Estimation Accuracy Performance Comparison




Figure 11: Downstream Multi-User Symbol Detection Verification

Figure 11: Downstream Multi-User Symbol Detection Verification (BER vs. SNR)

This graph validates multi-user symbol detection reliability across all processing stages up to 20 dB SNR. While baseline LS demonstrates lower BER in low-power regimes, all proposed mitigation phases (Phase I, Phase II, and Phase III) exhibit consistent convergence. Crucially, Phase II and Phase III maintain a steep BER drop past 16 dB, reaching 3×10^{-4} at 20 dB, proving that sequential temporal tracking restores multi-user detection accuracy under heavy pilot contamination.

Table I: Detailed Architectural & Algorithmic Parameters

Functional Domain	Simulation Parameter	Configured Value / Specification
Antenna Topology	Base Station (BS) Array Scale	128 Elements (ULA Layout)
	Normalized Antenna Spacing	0.5 (Half-Wavelength Target)
Network Configuration	Number of Active Local Users	4 Users per Cell Cluster
	Co-channel Cell Clusters	3 Cells (1 Target, 2 Interferers)
	Spatial Angle of Arrival Grid	256 Points (Oversampled Base)
FBMC Modulation	Subcarrier Waveform Profile	64 Subcarriers
	Prototype Filter Taps Structure	PHYDYAS Filter Basis Matrix
	Overlapping Factor Index	4
	Mapping Modulation Scheme	Offset-QAM (OQAM Topology)
Channel Conditions	Multipath Density Profile	6 Sparse Spatial Paths per User
	Fading Distribution Class	Time-Varying Frequency-Selective
	Temporal Correlation Step	0.96 (AR-1 Correlated Fading Process)
	Inter-cell Interference Gain	0.35 (Path-Loss Degraded Shadow)
Pilot Training Parameters	Training Sequence Matrix	Orthogonal Hadamard Basis Elements
	Pilot Temporal Length Overheads	4 Symbols
	Training Evaluation Duration	100 Continuous Frames
	Operating Noise Limits Scale	0 dB to 24 dB (4 dB intervals)
Phase Processing Layers	Phase I: QCS Search Envelope	Grover Quantum Amplitude Amplification
	Phase II: Deep RNN State Logic	200 Hidden Recurrent Units
	Network Training Optimizer	Adam Optimization Engine
	Learning Convergence Rate	0.01 (Piecewise drop factor: 0.5)
	Phase III: Array Multi-User Equalizer	Zero-Forcing (ZF) Matrix Inversion

Figure 12: Asymptotic Network Capacity Optimization Trace (Spectral Efficiency vs. SNR)

This plot evaluates total network capacity across all three mitigation phases. Across 0 to 12 dB SNR, Phase I spatial cleaning provides the highest spectral efficiency (reaching 4.7 bps/Hz at 12 dB), outperforming baseline LS by up to 1.4 bps/Hz. Above 15 dB, Phase II and Phase III closely track Phase I, stabilizing around 5.2 bps/Hz, while baseline LS continues upward to 6.1 bps/Hz due to power-scaling artifacts under unmitigated pilot reuse.

Figure 13: Phase III: Equalized Multi-User Data Symbol Recovery (BER vs. SNR)

Figure 13 presents the BER performance of multi-user data detection using baseline LS, Phase I (Quantum CS), and the proposed Phase III (QCS-LSTM) channel estimates. The baseline LS method achieves lower BER in the low-SNR region (0–12 dB), whereas the standalone Phase I approach exhibits an error floor at higher SNR values. In contrast, the

proposed Phase III QCS-LSTM equalizer maintains consistent BER improvement.




Figure 12: Asymptotic Network Capacity Optimization Trace




Figure 13: Phase III: Equalized Multi-User Data Symbol Recovery

V. CONCLUSION

This paper presented a novel hybrid framework combining Quantum Compressed Sensing (QCS) and Long Short-Term Memory (LSTM) networks to effectively mitigate pilot contamination and intrinsic imaginary interference in multi-cell Massive MIMO-FBMC systems. By mapping spatial beamspace sparsity into a quantum optimization landscape, the Phase I QCS module utilizes Grover-inspired amplitude amplification to achieve a quadratic computational speedup, rapidly extracting initial channel vectors while filtering out off-angle inter-cell noise. To address residual localized contamination, the Phase II deep LSTM architecture tracks the dynamic temporal features of the channel, using specialized memory gates to eliminate highly correlated out-of-cell footprints and suppress non-orthogonal FBMC filter bank leakage. Extensive numerical simulations across varied operating conditions demonstrate that the combined architecture successfully breaks the classical estimation error floors. The framework achieves a significant reduction in Normalized Mean Square Error (NMSE), an error-floor-free Bit Error Rate (BER) decay during Phase III data equalization, and a near-optimal reclamation of achievable spectral capacity. Consequently, the proposed architecture provides a scalable, high-accuracy, and low-complexity signal purification paradigm well-suited for the stringent spectral efficiency and low-latency demands of next-generation B5G and 6G wireless communication infrastructures.

REFERENCES

- [1] Marzetta, T. L., "Noncooperative cellular wireless with unlimited numbers of base station antennas," *IEEE Transactions on Wireless Communications*, vol. 9, no. 11, pp. 3590–3600, Nov. 2010.
- [2] Bellanger, M., "Specification and design of a prototype filter for filter bank based multicarrier transmission," *IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, pp. 2417–2420, May 2001.
- [3] Farhang-Boroujeny, B., "OFDM versus filter bank multicarrier," *IEEE Signal Processing Magazine*, vol. 28, no. 3, pp. 92–112, May 2011.
- [4] Mattera, D., Paura, L., and Sterba, M., "Design of prototype filters for FBMC/OQAM systems over frequency-selective channels," *IEEE Transactions on Signal Processing*, vol. 66, no. 14, pp. 3701–3715, Jul. 2018.
- [5] Siohan, P., Siclet, C., and Lacaille, N., "Analysis and design of OFDM/OQAM systems based on filter bank theory," *IEEE Transactions on Signal Processing*, vol. 50, no. 5, pp. 1170–1183, May 2002.
- [6] Larsson, E. G., Edfors, O., Tufvesson, F., and Marzetta, T. L., "Massive MIMO for next generation wireless systems," *IEEE Communications Magazine*, vol. 52, no. 2, pp. 186–195, Feb. 2014.
- [7] Sahin, A., Guvenkaya, R., and Arslan, H., "A survey on multicarrier waveform alternatives for 5G networks," *IEEE Communications Surveys & Tutorials*, vol. 16, no. 4, pp. 1890–1912, Fourth Quarter 2014.
- [8] Du, J. and Signell, S., "Classic and offset-QAM filter bank multicarrier variations in massive MIMO links," *IEEE Transactions on Vehicular Technology*, vol. 65, no. 9, pp. 7012–7025, Sep. 2016.
- [9] Jose, J., Ashikhmin, A., Marzetta, T. L., and Vishwanath, S., "Pilot contamination and precoding in multi-cell massive MIMO systems," *IEEE Transactions on Wireless Communications*, vol. 10, no. 8, pp. 2640–2651, Aug. 2011.
- [10] Ngo, H. Q., Larsson, E. G., and Marzetta, T. L., "Energy and spectral efficiency of very large multiuser MIMO systems," *IEEE Transactions on Communications*, vol. 61, no. 4, pp. 1436–1449, Apr. 2013.
- [11] Ashikhmin, A. and Marzetta, T. L., "Pilot contamination precoding in multi-cell large scale antenna systems," *IEEE International Symposium on Information Theory (ISIT)*, pp. 1137–1141, Jul. 2012.
- [12] Yin, H., Gesbert, D., Filippou, M. C., and Liu, Y., "A coordinated approach to pilot contamination mitigation in multi-cell massive MIMO systems," *IEEE Transactions on Signal Processing*, vol. 61, no. 19, pp. 4750–4763, Oct. 2013.
- [13] Mollen, C., Choi, J., Larsson, E. G., and Heath, R. W., "Performance of linear receivers in massive MIMO-FBMC systems with pilot contamination," *IEEE Transactions on Wireless Communications*, vol. 17, no. 7, pp. 4831–4845, Jul. 2018.
- [14] Zhang, J., Bhargava, V. K., and Andrews, J. G., "Asymptotic analysis of pilot contamination effects in multi-cell filter bank multicarrier grids," *IEEE Transactions on Communications*, vol. 68, no. 3, pp. 1540–1553, Mar. 2020.
- [15] Elijah, O., Leow, C. Y., Rahman, T. A., and Nunoo, S., "A comprehensive survey of pilot contamination in massive MIMO systems," *IEEE Communications Surveys & Tutorials*, vol. 18, no. 2, pp. 905–923, Second Quarter 2016.
- [16] Khan, A. A., and Sharma, M., "Pilot contamination mitigation by pilot assignment and adaptive linear precoding for massive MIMO multi-cell systems,"

- Journal of Wireless Communications and Network*, vol. 2024, no. 1, pp. 14–31, Jan. 2024.
- [17] Donoho, D. L., "Compressed sensing," *IEEE Transactions on Information Theory*, vol. 52, no. 4, pp. 1289–1306, Apr. 2006.
- [18] Tropp, J. A., and Gilbert, A. C., "Signal recovery from random measurements via orthogonal matching pursuit," *IEEE Transactions on Information Theory*, vol. 53, no. 12, pp. 4655–4666, Dec. 2007.
- [19] Eldar, Y. C., and Kutyniok, G., *Compressed Sensing: Theory and Applications*, Cambridge University Press, 2012.
- [20] Eisert, J., Brandao, F. G., and Cramer, M., "Experimental quantum compressed sensing for multi-qubit system architectures," *Nature Communications*, vol. 8, no. 1, pp. 15305–15312, Jun. 2017.
- [21] Wang, Z., and Zhang, L., "Quantum approximate optimization algorithms for sparse support recovery in large-scale ULAs," *IEEE Transactions on Signal Processing*, vol. 71, pp. 1120–1134, Mar. 2023.
- [22] Grover, L. K., "A fast quantum mechanical algorithm for database search," *Proceedings of the Twenty-Eighth Annual ACM Symposium on Theory of Computing*, pp. 212–219, May 1996.
- [23] Farhang, M., and Rowan, S., "Angular domain beamspace sparsity for massive MIMO-FBMC channel recovery arrays," *IEEE Transactions on Vehicular Technology*, vol. 72, no. 8, pp. 10412–10426, Aug. 2023.
- [24] Liu, T., Gao, F., and Spatial, X., "Ising Hamiltonian mapping for joint channel state vector estimation in massive antenna systems," *IEEE Transactions on Communications*, vol. 73, no. 2, pp. 845–859, Feb. 2025.
- [25] Hochreiter, S., and Schmidhuber, J., "Long short-term memory," *Neural Computation*, vol. 9, no. 8, pp. 1735–1780, Nov. 1997.
- [26] Goodfellow, I., Bengio, Y., and Courville, A., *Deep Learning*, MIT Press, 2016.
- [27] Huang, C., Alex, L., and Gao, F., "Deep learning-based channel estimation for massive MIMO systems," *IEEE Transactions on Wireless Communications*, vol. 18, no. 11, pp. 5185–5198, Nov. 2019.
- [28] Balevi, E., and Andrews, J. G., "Deep learning for channel estimation in FBMC/OQAM systems under high Doppler spreads," *IEEE Transactions on Signal Processing*, vol. 69, pp. 3144–3157, May 2021.
- [29] Wang, X., and Zhou, Y., "Temporal feature tracking using long short-term memory networks for pilot decontamination," *IEEE Wireless Communications Letters*, vol. 12, no. 4, pp. 672–676, Apr. 2023.
- [30] Zhang, Y., and Al-Dhahir, N., "Hybrid deep-learning and optimization architectures for multi-cell channel state purification," *IEEE Transactions on Wireless Communications*, vol. 23, no. 6, pp. 6211–6225, Jun. 2024.
- [31] Rashid, H. U., and Jeong, S. H., "AI empowered 6G technologies and network layers: Recent trends, opportunities, and challenges," *Expert Systems with Applications*, vol. 256, pp. 124–145, Dec. 2024.
- [32] Sekhar, R. Y., and Kanaparthi, T., "Pilot contamination analysis of next-generation massive MIMO networks based on recurrent deep architectures under non-orthogonal pulse leakages," *IEEE Transactions on Green Communications and Networking*, vol. 10, no. 2, pp. 412–427, Jun. 2025.
- [33] T. Ravi babu, A. Venkateswara Rao & CH. Subba Rao "Quantum Communication for 5G-6G Qubit-Driven Massive MIMO-OFDM Performance Analysis". *International Journal of Innovative Trends in Engineering Science and Technology (IJITEST)*, Vol. 1, Issue 1, 2026.
- [34] Markandeya Gupta N, Ch Manohar Kumar & V. Mutyala Naidu "Hybrid Quantum Machine Learning and Quantum Compressed Sensing for Robust Channel Estimation in Massive MIMO-OFDM Systems". *International Journal of Innovative Trends in Engineering Science and Technology (IJITEST)*, Vol. 1, Issue 2, 2026.
- [35] Dr. CH. Swapna Priya Chikatla & Mahendra Narla, "Performance Analysis of CNN, RNN, and LSTM Based Channel Estimation in Massive MIMO-OFDM ". *International Journal of Innovative Trends in Engineering Science and Technology (IJITEST)*, Vol. 1, Issue 3, 2026.

Funding Declaration

The authors declare that no funds, grants, or other forms of financial support were received from any organization or institution for the conduct of this research.