

Rockchip Developer Guide PCIE EP Standard Card APIs

ID: RK-KF-YF-C52

Release Version: V3.3.0

Release Date: 2025-08-15

Security Level: ☐Top-Secret ☐Secret ☐Internal ☒Public

DISCLAIMER

THIS DOCUMENT IS PROVIDED "AS IS". ROCKCHIP ELECTRONICS CO., LTD. ("ROCKCHIP") DOES NOT PROVIDE ANY WARRANTY OF ANY KIND, EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY, COMPLETENESS, MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANY REPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME DUE TO THE UPGRADES OF THE PRODUCT OR ANY OTHER REASONS.

Trademark Statement

"Rockchip", "瑞芯微", "瑞芯" shall be Rockchip's registered trademarks and owned by Rockchip. All the other trademarks or registered trademarks mentioned in this document shall be owned by their respective owners.

All rights reserved. ©2025. Rockchip Electronics Co., Ltd.

Beyond the scope of fair use, neither any entity nor individual shall extract, copy, or distribute this document in any form in whole or in part without the written approval of Rockchip.

Rockchip Electronics Co., Ltd.

No.18 Building, A District, No.89, software Boulevard Fuzhou, Fujian, PRC

Website: www.rock-chips.com

Customer service Tel: +86-4007-700-590

Customer service Fax: +86-591-83951833

Customer service e-Mail: fae@rock-chips.com

Preface

Overview

This document explains the use of the RK PCIe standard EP development package and introduces the relevant APIs.

Product Version

Chipset	Kernel Version
All main chips supporting RK PCIe EP	Linux 6.1, 5.10, 4.19, RT-Thread v5.1.x, v4.1.x

Note:

- Only RT-Thread support is implemented on the RK PCIe EP side

Intended Audience

This document (this guide) is mainly intended for:

Technical support engineers

Software development engineers

Revision History

Version	Author	Date**	Change Description
V1.0.0	yp.xiao, Kever Yang, Jon Lin	2023-03-07	Initial version
V1.1.0	yp.xiao	2023-05-22	Updated SDK API and some configuration instructions
V1.2.0	yp.xiao	2023-06-15	Added EP card firmware compilation, burning, and OTA upgrade instructions Added application exception instructions Updated <code>struct pcie_dev_st</code> structure to support timeout configuration, PCIE speed acquisition, RC DMA configuration.
v1.3.0	Jon Lin	2023-10-07	Added pcie.bin instructions
v1.4.0	yp.xiao, Jon Lin	2023-10-23	Updated SDK API Added EP acceptance criteria section Updated dual storage instructions Updated PCIE BIN instructions
v1.5.0	Jon Lin	2024-05-23	Updated PHY Mode settings
v1.6.0	Jon Lin	2024-09-18	Added user-mode test demo - pcie_speed_test performance reference, added BAR1/5 support
v1.7.0	yp.xiao, Jon Lin	2025-01-24	chips_connect development package added OSAL, compatible with Windows version
v1.8.0	Jon Lin	2025-02-12	Optimized EP startup solution instructions, modified layout issues
v2.0.0	Jon Lin	2025-03-09	Added RK chip interconnection independent power supply solution instructions
v3.0.0	Jon Lin	2025-05-14	Adjuster note to EP card specifications, optimized EP Boot instructions, added data transfer principle instructions, added user layer multi-application instructions
v3.1.0	Jon Lin	2025-07-12	Added RK1820
v3.2.0	Jon Lin	2025-08-11	Independently output Chips Connect APIs documentation
v3.3.0	Jon Lin	2025-08-15	Add err_event, pcie_is_alive and hardware_reset apis

Contents

Rockchip Developer Guide PCIE EP Standard Card APIs

1. Chips Connect API Reference
 - 1.1 PCIe Linux Root Complex
 - 1.1.1 rk_pcie_get_pci_bus_addresses
 - 1.1.2 rk_pcie_device_init
 - 1.1.3 rk_pcie_device_deinit
 - 1.1.4 rk_pcie_task_create
 - 1.1.5 rk_pcie_task_destroy
 - 1.1.6 rk_pcie_boot_init
 - 1.1.7 rk_pcie_boot_deinit
 - 1.1.8 rk_pcie_boot_download_firmware
 - 1.1.9 rk_pcie_boot_run
 - 1.1.10 rk_pcie_get_ep_info
 - 1.1.11 rk_pcie_get_user_cmd
 - 1.1.12 rk_pcie_get_buff
 - 1.1.13 rk_pcie_send_buff
 - 1.1.14 rk_pcie_get_bar1_user_buffer
 - 1.1.15 rk_pcie_get_bar5_user_buffer
 - 1.1.16 rk_pcie_set_bar_inbound_cpu_addr
 - 1.1.17 rk_pcie_release_buff
 - 1.1.18 rk_pcie_get_buff_max_size
 - 1.1.19 rk_pcie_get_ep_mode
 - 1.1.20 Rescanning PCI Devices
 - 1.1.21 rk_pcie_send_msg_to_ep_bus
 - 1.1.22 rk_pcie_get_msg_for_task_id
 - 1.1.23 rk_pcie_get_ep_obj_info
 - 1.1.24 rk_pcie_get_ep_err_event_count
 - 1.1.25 rk_pcie_is_alive
 - 1.1.26 rk_pcie_device_hardware_reset
 - 1.1.27 Data Types
 - 1.1.27.1 RK_PCIE_HANDLES
 - 1.1.27.2 EBuff_Type
 - 1.1.27.3 ETask_Msg_Type
 - 1.1.27.4 PCIe Buffer Node
 - 1.1.27.5 PCIe Device Bus
 - 1.1.27.6 PCIe EP Device Mode
 - 1.1.27.7 pcie_dev_attr_st
 - 1.1.27.8 PCIe Task Attribute Structure
 - 1.1.27.9 pcie_task_msg_st
 - 1.1.27.10 pcie_ep_obj_info_for_user
 - 1.1.27.11 pcie_err_event_count
 - 1.2 PCIe Windows EP
 - 1.2.1 Data Types
 - 1.2.1.1 RK_PCIE_TASK_ATTR
 - 1.2.1.2 RK_PCIE_DESTROY_TASK
 - 1.2.1.3 RK_PCIE_IOCTL_STATUS
 - 1.2.1.4 RK_PCIE_TASK_MSG
 - 1.2.1.5 RK_PCIE_BUFF_NODE
 - 1.2.1.6 RK_PCIE_DEV_MODE
 - 1.2.1.7 RK_PCIE_TASK_INFO

1.2.1.8 RK_PCIE_DOWNLOAD_FIRMWARE

1.3 PCIE Endpoint

- 1.3.1 rk_pcie_device_init
- 1.3.2 rk_pcie_device_deinit
- 1.3.3 rk_pcie_task_create
- 1.3.4 rk_pcie_task_destroy
- 1.3.5 rk_pcie_set_ep_info
- 1.3.6 rk_pcie_get_user_cmd
- 1.3.7 rk_pcie_get_bar1_user_buffer
- 1.3.8 rk_pcie_get_bar5_user_buffer
- 1.3.9 rk_pcie_set_bar_inbound_cpu_addr
- 1.3.10 rk_pcie_get_buff
- 1.3.11 rk_pcie_send_buff
- 1.3.12 rk_pcie_release_buff
- 1.3.13 rk_pcie_get_buff_max_size
- 1.3.14 rk_pcie_get_msg_for_bus
- 1.3.15 rk_pcie_send_msg_to_rc_task
- 1.3.16 Data Types
 - 1.3.16.1 EBuff_Type
 - 1.3.16.2 ETask_Msg_Type
 - 1.3.16.3 PCIE Buffer Node
 - 1.3.16.4 pcie_task_msg_st

1.4 Error Codes

1. Chips Connect API Reference

1.1 PCIe Linux Root Complex

1.1.1 rk_pcie_get_pci_bus_addresses

[Description]

Retrieve all matching PCI device bus addresses in the system.

[Syntax]

```
int rk_pcie_get_pci_bus_addresses(int vendor_id, int device_id, struct pcie_dev_bus
*pci_bus)
```

[Parameters]

Parameter Name	Description	Input/Output
vendor_id	PCIe Vendor Identifier	Input
device_id	PCIe Product Identifier	Input
pci_bus	PCI device bus address struct	Output

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes .

[Example]

Please refer to the example in [rk_pcie_device_init](#).

[Related Topics]

[rk_pcie_get_pci_bus_addresses](#)

1.1.2 rk_pcie_device_init

[Description]

Initialize the PCIe device.

[Syntax]

```
RK_PCIE_HANDLES rk_pcie_device_init(struct pcie_dev_attr_st *dev)
```

[Parameters]

Parameter Name	Description	Input/Output
dev	PCIe device configuration structure	Input

[Return Values]

Return Value	Description
Non-NULL	Success
NULL	Failure

[Example]

```
#define VENDOR_ID          0x1d87
#define DEVICE_ID          0x356a

struct pcie_dev_bus dev_bus;
struct pcie_dev_attr_st dev_attr;
RK_PCIE_HANDLES rk_handle;
int ret;

ret = rk_pcie_get_pci_bus_addresses(VENDOR_ID, DEVICE_ID, &dev_bus);
if (ret != 0) {
    printf("get pci bus address fail\n");
    return -1;
}

printf("ep dev max num : %d\n", dev_bus.dev_max_num);
if (dev_bus.dev_max_num == 0) {
    printf("no ep device, exit ... \n");
} else {
    // Initialize PCIe device
    dev_attr.using_rc_dma = 0; // Disable RC DMA, use EP DMA transfer
    dev_attr.rc_dma_chn = 0;
    dev_attr.vendor_id = VENDOR_ID;
    dev_attr.device_id = DEVICE_ID;
    dev_attr.use_dma_only_in_rc = 0;
    // Select the first matching device
    memcpy(dev_attr.pci_bus_address, dev_bus.pci_bus_address[0],
strlen(dev_bus.pci_bus_address[0]));

    // Initialize EP device
    rk_handle = rk_pcie_device_init(&dev_attr);
    if (rk_handle == NULL) {
```

```

        printf("pcie device init fail:%s \n", dev_attr.pci_bus_address);
        return -1;
    }

    // Deinitialize PCIe device, release resources
    ret = rk_pcie_device_deinit(rk_handle, 0);
    if (ret != 0) {
        printf("pcie deinit device fail....ret = %d\n", ret);
        return -1;
    }
}

```

[Related Topics]

[rk_pcie_device_deinit](#)

1.1.3 rk_pcie_device_deinit

[Description]

Deinitialize the PCIe device and release resources.

[Syntax]

```
int rk_pcie_device_deinit(RK_PCIE_HANDLES handles, int en_remove)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
en_remove	Release resources and remove the device	Input

[Return Value]

Return Value	Description
0	Normal
Non-zero	Exception, please refer to Error Codes

[Example]

Please refer to the example in [rk_pcie_device_init](#).

[Related Topics]

[rk_pcie_device_init](#)

1.1.4 rk_pcie_task_create

[Description]

Create a task based on attributes, allocate corresponding memory, and manage BUFFs. This interface will block and wait for the EP device to call the task creation interface.

[Syntax]

```
int rk_pcie_task_create(RK_PCIE_HANDLES handles, struct pcie_task_attr_st *task)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
task	PCIe Task configuration structure	Input

[Return Values]

Return Value	Description
Greater than 0	Normal, task_id
Less than 0	Exception, please refer to Error Codes

[Example]

```
// Select the first matching device
rc_ctx.rk_handle = rk_pcie_device_init(&rc_ctx.dev_attr);
if (rc_ctx.rk_handle == NULL) {
    printf("pcie device init fail:%s \n", rc_ctx.dev_attr.pci_bus_address);
    return -1;
}

rc_ctx.task_attr.send_buff_num = 5; // Number of send buffers
rc_ctx.task_attr.send_buff_size = 1048576; // Size of send buffer
rc_ctx.task_attr.recv_buff_num = 5; // Number of receive buffers
rc_ctx.task_attr.recv_buff_size = 8294408 ; // Size of receive buffer
rc_ctx.task_attr.wait_timeout_ms = -1; // Blocking wait
rc_ctx.task_id = rk_pcie_task_create(rc_ctx.rk_handle, &rc_ctx.task_attr);
if (rc_ctx.task_id < 0) {
    printf("pcie init create task fail...\n");
    return -1;
}

rk_pcie_get_ep_mode(rc_ctx.rk_handle, &rc_ctx.devmode);
printf("ep ap init, dev mode: %d, submode: %d\n", rc_ctx.devmode.mode,
rc_ctx.devmode.submode);
```

```
ret = rk_pcie_task_destroy(rc_ctx.rk_handle, rc_ctx.task_id);
if (ret != 0) {
    printf("pcie destroy task fail....ret = %d\n", ret);
    return -1;
}
```

[Related Topics]

[rk_pcie_task_destroy](#)

[Note]

This interface depends on `rk_pcie_dev_init`, and `rk_pcie_dev_init` must be called first to initialize the device before task initialization.

1.1.5 rk_pcie_task_destroy

[Description]

Deinitialize the Task, releasing the memory and BUFF management resources associated with the Task.

[Syntax]

```
int rk_pcie_task_destroy(RK_PCIE_HANDLES handles, int task_id)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
task_id	Task ID	Input

[Return Values]

Return Value	Description
0	Normal
Non-zero	Failure, please refer to Error Codes .

[Example]

Please refer to the example in [rk_pcie_ap_init](#).

[Related Topics]

[rk_pcie_ap_init](#)

1.1.6 rk_pcie_boot_init

[Description]

Initializes PCIE BOOT.

[Syntax]

```
int rk_pcie_boot_init(RK_PCIE_HANDLES handles)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input

[Return Values]

Return Value	Description
0	Normal
Non-zero	Failure, see Error Codes .

[Example]

```
// Initialize PCIE device
rc_ctx.rk_handle = rk_pcie_device_init(&rc_ctx.dev_attr);
if (rc_ctx.rk_handle == NULL) {
    printf("device init fail \n");
    return -1;
}

// Initialize PCIE Boot
ret = rk_pcie_boot_init(rc_ctx.rk_handle);
if (ret != 0) {
    printf("pcie boot init ep fail....ret = %d\n", ret);
    return -1;
}

// pcie boot
rk_pcie_boot_download_firmware_list(&rc_ctx, &pcie_boot_info, &pcie_boot_ini);

// ep boot
rk_ep_boot_download_firmware_list(&rc_ctx, &ep_boot_info, &ep_boot_ini);

// Release PCIE Boot resources
ret = rk_pcie_boot_deinit(rc_ctx.rk_handle);
if (ret != 0) {
    printf("pcie boot deinit ep fail....ret = %d\n", ret);
    return -1;
}
```

```
}  
  
printf("download ep end\n");
```

[Related Topics]

[rk_pcie_boot_deinit](#)

[Note]

This interface depends on `rk_pcie_dev_init`, you must call `rk_pcie_dev_init` to initialize the device before proceeding with boot initialization.

1.1.7 rk_pcie_boot_deinit

[Description]

Deinitializes the PCIe BOOT.

[Syntax]

```
int rk_pcie_boot_deinit(RK_PCIE_HANDLES handles)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input

[Return Values]

Return Value	Description
0	Normal
Non-zero	Failure, please refer to Error Codes .

[Example]

[rk_pcie_boot_init](#)

[Related Topics]

[rk_pcie_boot_init](#)

1.1.8 rk_pcie_boot_download_firmware

[Description]

Download the PCIE BOOT firmware.

[Syntax]

```
int rk_pcie_boot_download_firmware(RK_PCIE_HANDLES handles, unsigned char *firmware, size_t
firmware_size, unsigned long remote_load_addr)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
firmware	Firmware data	Input
firmware_size	Size of firmware	Input
remote_load_addr	Remote firmware load address	Input

[Return Values]

Return Value	Description
0	Normal
Non-zero	Failure, please refer to Error Codes .

[Example]

```
int rk_ep_download_firmware(struct rc_context_st *rc_ctx, char *firmware, unsigned long
load_addr)
{
    int fd;
    unsigned long len;
    unsigned long size = 1024 * 1024;
    void *buffer = malloc(size);
    int ret;
    fd = open(firmware, O_RDONLY);
    if (fd == -1) {
        printf(" open %s file error, ret = %d \n", firmware, fd);
        return -1;
    }

    while ((len = read(fd, buffer, size)) > 0) {
        ret = rk_pcie_boot_download_firmware(rc_ctx->rk_handle, buffer, len, load_addr);
        if (ret != 0) {
            return -1;
        }

        load_addr += len;
    }

    close(fd);
    return 0;
}
```

[Related Topics]

[rk_ep_download_firmware](#)

1.1.9 rk_pcie_boot_run

[Description]

Boot the PCIe BOOT firmware.

[Syntax]

```
int rk_pcie_boot_run(RK_PCIE_HANDLES handles)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input

[Return Values]

Return Value	Description
0	Normal
Non-zero	Failure, please refer to Error Codes .

[Example]

[rk_pcie_boot_init](#)

[Related Topics]

[rk_pcie_boot_run](#)

1.1.10 rk_pcie_get_ep_info

[Description]

Retrieve EP status information, with a maximum support of 96KB.

[Syntax]

```
int rk_pcie_get_ep_info(RK_PCIE_HANDLES handles, void *status, size_t status_size)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
status	void pointer, status structure defined by the user	Output
status_size	Size of the status structure	Input

[Return Values]

Return Value	Description
0	Normal
Non-zero	Failure, please refer to Error Codes .

[Example]

```
struct ep_info_st {
    unsigned int link_status;
    unsigned int temp;
    long long timestamp;
    unsigned char cpu_load;
    unsigned char npu_load;
    unsigned char gpu_load;
};

long long timestamp;
while(1) {
    ret = rk_pcie_get_ep_info(rc_ctx.rk_handle, ep_info, sizeof(struct ep_info_st));
    if(timestamp == ep_info->timestamp) {
        printf("EP device status is abnormal \n");
        break;
    }
    timestamp = ep_info->timestamp;
}
```

[Related Topics]

[rk_pcie_get_ep_info](#)

1.1.11 rk_pcie_get_user_cmd

[Description]

Obtain a memory pointer at a specific location of BAR0 for user-defined command areas. Supports up to 256KB.

[Syntax]

```
void *rk_pcie_get_user_cmd(RK_PCIE_HANDLES handles)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input

[Return Value]

Return Value	Description
Non-NULL	Normal, pointer to custom command area
NULL	Error

[Example]

```
struct user_cmd_st {
    unsigned int max_chn;
    unsigned int width;
    unsigned int height;
    unsigned int codecid;
    unsigned int output_id;
    unsigned int init;
};

user_cmd = (struct user_cmd_st *)rk_pcie_get_user_cmd(rc_ctx.rk_handle);
user_cmd->max_chn = rc_ctx.max_chn;
user_cmd->width = rc_ctx.width;
user_cmd->height = rc_ctx.height;
user_cmd->codecid = rc_ctx.codecid;
user_cmd->output_id = 1; //0:RGB888 1:BGRA8888
user_cmd->init = 1;
```

[Related Topics]

[rk_pcie_get_user_cmd](#)

1.1.12 rk_pcie_get_buff

[Description]

Obtain an available PCIe buffer.

[Syntax]

```
struct pcie_buff_node *rk_pcie_get_buff(RK_PCIE_HANDLES handles, int task_id, enum
EBuff_Type type)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
task_id	Task ID	Input
type	PCIe Buff Type	Input

[Return Values]

Return Value	Description
Non-NULL	Pointer to available Buff
NULL	No available Buff pointer

[Example]

```
node = rk_pcie_get_buff(ctx->rk_handle, ctx->task_id, E_RECV); //Obtain an available receive
BUF
if (node) {
    if (check_info(node->vir_addr + node->size - CHECK_SIZE) == 0) { //Verify the BUF data
is correct
        pthread_mutex_unlock(&ctx->mutex_stream_speed);
        ctx->stream_speed_index++;
        pthread_mutex_unlock(&ctx->mutex_stream_speed);
        memset(node->vir_addr + node->size - CHECK_SIZE, 0, CHECK_SIZE);
    } else {
        printf("check data ===== error \n");
        for (int i = 0; i < CHECK_SIZE; i++) {
            unsigned char *p = node->vir_addr + node->size - CHECK_SIZE;
            printf("%d ", p[i]);
        }
        printf("\ncheck data ===ssss=====node->size = %d===== error \n", (int)node-
>size);
    }
    rk_pcie_release_buff(ctx->rk_handle, ctx->task_id, node); //Release BUF
} else {
    usleep(1000);
}
```

[Related Topics]

[rk_pcie_release_buff](#)

1.1.13 rk_pcie_send_buff

[Description]

Sends the PCIe buffer, and blocks until DMA transfer is completed.

[Syntax]

```
int rk_pcie_send_buff(RK_PCIE_HANDLES handles, int task_id, struct pcie_buff_node *pbuff)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
task_id	Task ID	Input
pbuff	PCIE Buffer pointer	Input

[Return Value]

Return Value	Description
0	Send successful, indicating that the data has been transferred via DMA.
Non-zero	Failure, please refer to Error Codes .

[Example]

```
node = rk_pcie_get_buff(ctx->rk_handle, ctx->task_id, E_SEND); // Get an available send
buffer
if (node) {
    node->size = buffer_size;
    // Operate on the buffer, write data
    memcpy(node->vir_addr, mptr, node->size);
    add_check_info(node->vir_addr + node->size - CHECK_SIZE);
    rk_pcie_send_buff(ctx->rk_handle, ctx->task_id, node); // Send to the other end
    index++;
} else {
    usleep(1000);
}
```

[Related Topics]

[rk_pcie_send_buff](#)

1.1.14 rk_pcie_get_bar1_user_buffer

[Description]

Obtaining the virtual mapping address of bar1.

[Syntax]

```
void *rk_pcie_get_bar1_user_buffer(RK_PCIE_HANDLES handles)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Handle of all matching devices	Input

[Return Values]

Return Value	Description
void *	Virtual address
NULL	Failure, see Error Codes .

1.1.15 rk_pcie_get_bar5_user_buffer

[Description]

Obtains the virtual mapping address of bar1.

[Syntax]

```
void *rk_pcie_get_bar5_user_buffer(RK_PCIE_HANDLES handles)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Handle of all matching devices	Input

[Return Values]

Return Value	Description
void *	Virtual address
NULL	Failure, see Error Codes .

1.1.16 rk_pcie_set_bar_inbound_cpu_addr

[Description]

Set BAR inbound mapping.

[Syntax]

```
u_int64_t rk_pcie_set_bar_inbound_cpu_addr(RK_PCIE_HANDLES handles, u_int32_t atu_index,
u_int64_t cpu_address, u_int32_t size)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Handle of all matching devices	Input
atu_index	ATU index	Input
cpu_address	Mapped CPU address	Input
size	Mapping size limit	Input

[Return Values]

Return Value	Description
cpu_address	Returns CPU address

1.1.17 rk_pcie_release_buff

[Description]

Release the PCIE buffer.

[Syntax]

```
int rk_pcie_release_buff(RK_PCIE_HANDLES handles, int task_id, struct pcie_buff_node *pbuff)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Handle for all matching devices	Input
task_id	Task ID	Input
pbuff	Pointer to PCIE Buffer	Input

[Return Values]

Return Value	Description
0	Successfully released
Non-zero	Failure, see Error Codes .

[Example]

[rk_pcie_get_buff](#)

[Related Topics]

[rk_pcie_release_buff](#)

1.1.18 rk_pcie_get_buff_max_size

[Description]

Obtaining the maximum size supported by the buffer.

[Syntax]

```
long rk_pcie_get_buff_max_size(RK_PCIE_HANDLES handles, int task_id, enum EBuff_Type type)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Handle of all matching devices	Input
task_id	Task ID	Input
type	Type of PCIE Buffer	Input

[Return Values]

Return Value	Description
Greater than or equal to 0	Buffer size
Less than 0	Failure, see Error Codes

[Example]

```
long buffer_size = rk_pcie_get_buff_max_size(ctx->rk_handle, ctx->task_id, E_SEND);
```

[Related Topics]

[rk_pcie_get_buff_max_size](#)

1.1.19 rk_pcie_get_ep_mode

[Description]

Retrieve the current operating mode of the EP device, supporting status acquisition from loader, kernel, application, and other modes. Mode information can be obtained in rk_pcie_rc.h

[Syntax]

```
int rk_pcie_get_ep_mode(RK_PCIE_HANDLES handles, struct pcie_dev_mode *devmode)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
devmode	Device mode structure	Output

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes

[Example]

```

struct rc_context_st {
    RK_PCIE_HANDLES rk_handle;
    struct pcie_task_attr_st dev_attr;
    struct pcie_dev_mode devmode;
}rc_ctx;

// Initialize the first matching device
rc_ctx.rk_handle = rk_pcie_device_init(&rc_ctx.dev_attr);
if (rc_ctx.rk_handle == NULL) {
    printf("device init fail \n");
    usleep(1000000);
    continue;
}

rk_pcie_get_ep_mode(rc_ctx.rk_handle, &rc_ctx.devmode);
printf("111 ep device init, dev mode: 0x%.2x, submode: 0x%.2x\n", rc_ctx.devmode.mode,
rc_ctx.devmode.submode);

```

[Related Topics]

[rk_pcie_get_ep_mode](#)

1.1.20 Rescanning PCI Devices

[Description]

Rescanning system PCI devices is necessary for EP devices to recover after an abnormal restart by removing and then rescanning the devices.

[Syntax]

```
void rk_pcie_rescan_devices(void)
```

[Parameters]

None

[Return Value]

None

[Example]

None

[Related Topics]

[rk_pcie_rescan_devices](#)

1.1.21 rk_pcie_send_msg_to_ep_bus

[Description]

Send a message to the EP side, with a maximum of 1504Bytes per message.

[Syntax]

```
int rk_pcie_send_msg_to_ep_bus(RK_PCIE_HANDLES handles, int task_id, void *data, size_t size)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
task_id	Task ID	Input
data	Message pointer	Input
size	Message length	Input

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes

[Example]

```
rc_ctx.task_attr.send_buff_num = 5;
rc_ctx.task_attr.send_buff_size = 5 * 1024 * 1024;
rc_ctx.task_attr.recv_buff_num = 5;
rc_ctx.task_attr.recv_buff_size = 5 * 1024 * 1024;
rc_ctx.task_attr.wait_timeout_ms = -1;
rc_ctx.task_id = rk_pcie_task_create(rc_ctx.rk_handle, &rc_ctx.task_attr);
```

```

if (rc_ctx.task_id < 0) {
    printf("pcie init create task fail...\n");
    return -1;
}

rk_pcie_get_ep_mode(rc_ctx.rk_handle, &rc_ctx.devmode);
printf("ep ap init, dev mode: 0x%.2x, submode: 0x%.2x\n", rc_ctx.devmode.mode,
rc_ctx.devmode.submode);

rc_ctx.user_cmd.cmd = EP_TEST_STATUS_RUN_APP;
rk_pcie_send_msg_to_ep_bus(rc_ctx.rk_handle, rc_ctx.task_id, (void *)&rc_ctx.user_cmd,
sizeof(struct task_user_cmd_st));

```

[Related Topics]

[rk_pcie_send_msg_to_ep_bus](#)

1.1.22 rk_pcie_get_msg_for_task_id

[Description]

Retrieve EP messages through Task ID

[Syntax]

```

int rk_pcie_get_msg_for_task_id(RK_PCIE_HANDLES handles, struct pcie_task_msg_st *msg, int
task_id, int timeout_ms)

```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
msg	Pointer to message structure	Output
task_id	Task ID	Input
timeout_ms	Timeout in milliseconds, -1 for blocking mode (not recommended, will wait in kernel indefinitely), recommended 100ms	Input

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes

[Example]

```

unsigned char cmd;
struct pcie_task_msg_st msg;
ret = rk_pcie_get_msg_for_task_id(rc_ctx.rk_handle, &msg, rc_ctx.task_id, 100);
if (ret == RK_PCIE_OK) {
    cmd = msg.data[0];
    printf("recv ep msg: %d \n", cmd);
    if (cmd == 10) {
        break;
    }
}
}

```

[Related Topics]

[rk_pcie_get_msg_for_task_id](#)

1.1.23 rk_pcie_get_ep_obj_info

[Description]

Retrieve basic information of the EP device

[Syntax]

```

int rk_pcie_get_ep_obj_info(RK_PCIE_HANDLES handles, struct pcie_ep_obj_info_for_user *info)

```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
info	Buffer for basic info	Output

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, see Error Codes

[Example]

```

struct pcie_ep_obj_info_for_user info;
ret = rk_pcie_get_msg_for_task_id(rc_ctx.rk_handle, &info);
if (ret == RK_PCIE_OK) {
    return ret;
}

```

1.1.24 rk_pcie_get_ep_err_event_count

[Description]

Get the PCIe EP error event count.

[Syntax]

```
int rk_pcie_get_ep_err_event_count(RK_PCIE_HANDLES handles, struct pcie_err_event_count *info)
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input
info	PCIe error event count	Output

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, refer to Error Codes

[Example]

```
struct pcie_err_event_count info;  
ret = rk_pcie_get_ep_err_event_count(rc_ctx.rk_handle, &info);  
if (ret == RK_PCIE_OK) {  
    return ret;  
}
```

1.1.25 rk_pcie_is_alive

[Description]

Check if the PCIe link is normal.

[Syntax]

```
int rk_pcie_is_alive(RK_PCIE_HANDLES handles);
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input

[Return Values]

Return Value	Description
cc_true	Link is normal
cc_false	Link is abnormal

[Example]

```
ret = rk_pcie_is_alive(rc_ctx.rk_handle);
if (!ret) {
    printf("PCIe link down\n");
    return ret;
}
```

1.1.26 rk_pcie_device_hardware_reset

[Description]

Custom kernel driver interface for hardware reset controller. The device driver needs to implement the PCIE_EP_RESET_CTRL ioctl operation. During the process, the PERST# signal will be controlled to hardware reset the EP.

[Syntax]

```
int rk_pcie_device_hardware_reset(RK_PCIE_HANDLES handles);
```

[Parameters]

Parameter Name	Description	Input/Output
handles	Device handle	Input

[Return Values]

Return Value	Description
0	Reset successful
Non-zero	Reset failed or not supported, refer to Error Codes

[Example]

Before resetting the controller, stop all PCIe transactions. For example:

```

printf("Reset beging...\n");
/* Reset Progress: Stop all transmission */
rc_ctx.recv_ep_exit = 1;
rc_ctx.send_ep_exit = 1;
for (int i = 0; i < THREADS_MAX; i++) {
    pthread_join(rc_ctx.thr_recv_ep[i], NULL);
    pthread_join(rc_ctx.thr_send_ep[i], NULL);
}
usleep(500000);

/* Reset Progress: Destroy task */
ret = rk_pcie_task_destroy(rc_ctx.rk_handle, rc_ctx.task_id);
if (ret != 0) {
    printf("pcie destroy task fail....ret = %d\n", ret);
    return -1;
}
usleep(100000);

/* Reset Progress: Hardware reset */
ret = rk_pcie_device_hardware_reset(rc_ctx.rk_handle);
if (ret != 0) {
    printf("pcie device hardware reset fail....ret = %d\n", ret);
}

/* Reset Progress: Wait for link up */
usleep(1000000);

/* Reset Progress: Deinit device */
ret = rk_pcie_device_deinit(rc_ctx.rk_handle, 1);
if (ret != 0) {
    printf("pcie deinit device fail....ret = %d\n", ret);
    return -1;
}

/* Reset Progress: Rescan PCI */
rk_pcie_rescan_devices();
printf("Reset done\n");

return 0;

```

1.1.27 Data Types

PCIE RC-related data types and data structure definitions are as follows:

- RK_PCIE_HANDLES: Defines the device handle.
- EBuff_Type: Defines the PCIE Buff type.
- ETask_Msg_Type: Defines the Task message type.
- struct pcie_buff_node: Defines the PCIE buff attribute structure.
- struct pcie_dev_bus: Defines the PCI device bus information.

- struct pcie_dev_mode: Defines the PCIE EP device mode.
- struct pcie_dev_attr_st: Defines the PCIE EP device attribute structure.
- struct pcie_task_attr_st: Defines the Task attribute structure.
- struct pcie_task_msg_st: Defines the Task message structure.
- struct pcie_ep_obj_info_for_user: Defines the PCIe basic information structure.
- struct pcie_err_event_count: Defines the PCIe error event information structure.

1.1.27.1 RK_PCIE_HANDLES

[Description]

Defines the device handle.

[Definition]

```
typedef void* RK_PCIE_HANDLES;
```

1.1.27.2 EBuff_Type

[Description]

Defines the types of PCIE Buff.

[Definition]

```
enum EBuff_Type {
    E_SEND = 0,
    E_RECV,
};
```

[Members]

Member Name	Description
E_SEND	Sending buffer.
E_RECV	Receiving buffer.

1.1.27.3 ETask_Msg_Type

[Explanation]

Defines the types of PCIE messages.

[Definition]

```
enum ETask_Msg_Type {
    E_TASK_MSG_NONE = 0,
    E_TASK_MSG_CREATE,
    E_TASK_MSG_DESTROY,
    E_TASK_MSG_USER,
    E_TASK_MSG_MAX,
};
```

[Members]

Member Name	Description
E_TASK_MSG_NONE	Default value, no significance.
E_TASK_MSG_CREATE	Task creation.
E_TASK_MSG_DESTROY	Task destruction.
E_TASK_MSG_USER	User-defined message.
E_TASK_MSG_MAX	Maximum message type.

1.1.27.4 PCIe Buffer Node

[Explanation]

Defines the PCIE buffer attribute structure.

[Definition]

```
struct pcie_buff_node{
    void *vir_addr;
    size_t phy_addr;
    size_t size;
};
```

[Members]

Member Name	Description
vir_addr	Virtual address.
phy_addr	Physical address.
size	Memory size. Sending buffer: Users need to configure the data size, which should not exceed the total buffer memory size. Receiving buffer: The size of the data sent by the other end.

1.1.27.5 PCIe Device Bus

[Explanation]

Defines the bus information for PCI devices.

[Definition]

```
struct pcie_dev_bus {  
    int dev_max_num;  
    char pci_bus_address[PCI_DEV_MAX][PCI_BUS_MAX_NAME];  
};
```

[Members]

Member Name	Description
dev_max_num	The number of devices matched by the system.
pci_bus_address	The bus address of the PCI devices.

1.1.27.6 PCIe EP Device Mode

[Description]

Defines the PCIe EP device mode.

[Definition]

```
struct pcie_dev_mode {  
    unsigned short mode;  
    unsigned short submode;  
};
```

[Members]

Member Name	Description
mode	Current mode of the PCIe EP device, with the following value ranges: <pre>#define RKEP_MODE_BOOTROM 1 #define RKEP_MODE_LOADER 2 #define RKEP_MODE_KERNEL 3 #define RKEP_MODE_FUN0 4 #define RKEP_MODE_ERR 0xffff //Device exception requires reload</pre>
submode	Status corresponding to the mode of the PCIe EP device, with the following value ranges: <pre>#define RKEP_SMODE_INIT 0 #define RKEP_SMODE_LNKRDY 1 #define RKEP_SMODE_LNKUP 2 #define RKEP_SMODE_FWDLRDY 0x10 #define RKEP_SMODE_FWDLDONE 0x11 #define RKEP_SMODE_APPRDY 0x20 #define RKEP_SMODE_APPDEINIT 0x21 #define RKEP_SMODE_ERR 0xffff</pre>

1.1.27.7 pcie_dev_attr_st

[Description]

Defines the structure of PCIE EP device attributes.

[Definition]

```
struct pcie_dev_st {
    int vendor_id;
    int device_id;
    char pci_bus_address[PCI_BUS_MAX_NAME];
    unsigned char using_rc_dma: 1;
    unsigned char rc_dma_chn: 1;
    unsigned char enable_speed: 1;
    unsigned char use_dma_only_in_rc: 1; // Only call DMA to transmit and receive data on
the RC side
};
```

[Members]

Member Name	Description
vendor_id	Vendor ID of the EP device.
device_id	Device ID of the EP device.
pci_bus_address	Bus address of the EP device.
using_rc_dma	In the RK interconnection scenario, this mode can be enabled to use RC-side DMA to increase transmission rate. It is recommended to disable this configuration in multi-EP scenarios and use EP DMA.
rc_dma_chn	RC DMA supports 2 channels, with values 0/1.
enable_speed	Enable speed statistics function. The total transmission rate of the current EP device can be viewed through cat /tmp/pcie_debug*.
use_dma_only_in_rc	Only call DMA to transmit and receive data on the RC side.

1.1.27.8 PCIe Task Attribute Structure

[Description]

Defines the structure for PCIe Task attributes.

[Definition]

```
struct pcie_task_attr_st {
    int wait_timeout_ms;
    unsigned int send_buff_num;
    size_t send_buff_size;
    unsigned int recv_buff_num;
    size_t recv_buff_size;
};
```

[Members]

Member Name	Description
wait_timeout_ms	Sets the interface timeout, -1 for blocking mode.
send_buff_num	Number of PCIE send buffers for buffer polling.
send_buff_size	Memory size of the send buffer.
recv_buff_num	Number of PCIE receive buffers for buffer polling.
recv_buff_size	Memory size of the receive buffer.

1.1.27.9 pcie_task_msg_st

[Description]

Defines the PCIE Task message structure.

[Definition]

```
struct pcie_task_msg_st {
    enum ETask_Msg_Type type;
    int task_id;
    size_t size;
    char lock;
    unsigned char data[TASK_MSG_DATA_SIZE];
};
```

[Members]

Member Name	Description
type	Type of message.
task_id	Task ID.
size	Length of message.
lock	Reserved.
data	Content of message.

1.1.27.10 pcie_ep_obj_info_for_user

[Description]

Defines the PCIE basic information structure.

[Definition]

```
struct pcie_ep_obj_info_for_user {
    unsigned int magic;
    unsigned int rc_cc_version;
    unsigned int ep_cc_version;
    unsigned int func_drv_version;
    unsigned short vid;
    unsigned int did;
    unsigned int sub_vid;
    unsigned int sub_did;
};
```

[Members]

Member Name	Description
magic	Chips Connect development package magic, 32-bit width, default value is 0x524B4550, assigned by EP kernel driver
rc_cc_version	RC Chips Connect development package version information, 32-bit width, incrementing count, for example 0x1 corresponds to V1
ep_cc_version	EP Chips Connect development package version information, 32-bit width, incrementing count, for example 0x1 corresponds to V1
func_drv_version	PCIe driver version information, 32-bit width, high eight bits redundant, the rest each 8 bits represent a version information, for example 0x00030100 corresponds to V3.1.0
vid	PCI manufacturer ID, 16-bit width
did	PCI device ID, 16-bit width
sub_vid	Subsystem manufacturer ID, 16-bit width
sub_did	Subsystem device ID, 16-bit width

1.1.27.11 pcie_err_event_count

[Description]

Defines the PCIe error event count information structure.

[Definition]

```
struct pcie_err_event_count {
    unsigned char ebuf_overflow;
    unsigned char ebuf_under_run;
    unsigned char decode_error;
    unsigned char running_disparity_error;
    unsigned char skp_os_parity_error;
    unsigned char sync_header_error;
    unsigned char ctl_skp_os_parity_error;
    unsigned char detect_ei_infer;
    unsigned char receiver_error;
    unsigned char rx_recovery_request;
    unsigned char n_fts_timeout;
    unsigned char framing_error;
    unsigned char deskew_error;
    unsigned char bad_tlp;
    unsigned char lrc_error;
    unsigned char bad_dllp;
    unsigned char replay_number_rollover;
    unsigned char replay_timeout;
    unsigned char rx_nak_dllp;
    unsigned char tx_nak_dllp;
}
```

```
unsigned char retry_tlp;  
unsigned char fc_timeout;  
unsigned char poisoned_tlp;  
unsigned char ecr_error;  
unsigned char unsupported_request;  
unsigned char completer_abort;  
unsigned char completion_timeout;  
/* The location above is hardware information and cannot be changed */  
unsigned char redundant_phase;  
};
```

[Members]

Member Name	Abbreviation	Description
ebuf_overflow	EBUF Overflow	-
ebuf_under_run	EBUF Under-run	-
decode_error	Decode Error	Packet decoding error, signal anomaly
running_disparity_error	Running Disparity Error	Disparity error in 8b/10b encoding, Gen2 signal anomaly
skp_os_parity_error	SKP OS Parity Error	SKP sequence parity error, Gen3 signal anomaly
sync_header_error	SYNC Header Error	Synchronization header error, signal issue
ctl_skp_os_parity_error	CTL SKP OS Parity Error	Controlled SKP sequence parity error, Gen3 signal anomaly
detect_ei_infer	Detect EI Infer	Detected signal crosstalk
receiver_error	Receiver Error	Receiver error
rx_recovery_request	Rx Recovery Request	RX signal receives a peripheral request to enter recovery state for signal correction
n_fts_timeout	N_FTS Timeout	Peripheral's n_FTS does not meet the standard, L0s returns to L0 abnormally and enters recovery state
framing_error	Framing Error	Frame decoding error, signal anomaly
deskew_error	Deskew Error	Deskew error, signal anomaly
bad_tlp	BAD TLP	Received erroneous TLP packet
lrc_error	LCRC Error	Link CRC error, signal anomaly
bad_dllp	BAD DLLP	Erroneous DLLP packet, signal anomaly
replay_number_rollover	Replay Number Rollover	Accumulated retransmission packets overflow replay buffer
replay_timeout	Replay Timeout	Retransmission timeout for erroneous packets
rx_nak_dllp	Rx Nak DLLP	Received a DLLP from downstream and rejected its access
tx_nak_dllp	Tx Nak DLLP	DLLP sent to downstream was rejected
retry_tlp	Retry TLP	Number of retransmitted TLP packets, can indicate error rate
fc_timeout	FC Timeout	Flow control update timeout

Member Name	Abbreviation	Description
poisoned_tlp	Poisoned TLP	Reported erroneous TLP type, possibly due to link issues or RAM bit flips
ecr_error	ECRC Error	End CRC error, signal anomaly
unsupported_request	Unsupported Request	Received an unsupported request type TLP packet, possibly due to denied peripheral access
completer_abort	Completer Abort	Device received a request from RC but encountered an internal error, requiring termination of the access request
completion_timeout	Completion Timeout	Timeout for reading peripheral-related resources, TLP return timeout
redundant_phase	Redundant Phase	Counting variable to determine if status information is continuously updating

1.2 PCIE Windows EP

Windows drivers provide various ioctl functions for applications:

ioctl	Function Description
IOCTL_RKEP_DOWNLOAD_FIRMWARE	Transfer firmware to EP
IOCTL_RKEP_BOOT_RUN	Initiate EP boot after firmware transfer
IOCTL_RKEP_CREATE_TASK	Create Task
IOCTL_RKEP_DESTROY_TASK	Release Task
IOCTL_RKEP_SEND_BUF	Send buffer to EP
IOCTL_RKEP_GET_BUF	Retrieve buffer data from EP
IOCTL_RKEP_GET_EP_MODE	Get the current mode of EP
IOCTL_RKEP_SEND_MSG_TO_EP_BUS	Send message event to EP
IOCTL_RKEP_GET_MSG_FOR_TASK_ID	Receive message event from EP

1.2.1 Data Types

PCIE RC related data types and data structure definitions are as follows:

- RK_PCIE_TASK_ATTR: Defines the Task attribute structure.
- RK_PCIE_DESTROY_TASK: Releases the Task structure.

- RK_PCIE_IOCTL_STATUS: Defines the PCIE ioctl call status structure.
- RK_PCIE_TASK_MSG: Defines the Task message structure.
- RK_PCIE_BUFF_NODE: Defines the PCIE EP BUF structure.
- RK_PCIE_DEV_MODE: Defines the PCIE EP device mode structure.
- RK_PCIE_TASK_INFO: Defines the Task information structure.
- RK_PCIE_DOWNLOAD_FIRMWARE: Defines the firmware download structure.

1.2.1.1 RK_PCIE_TASK_ATTR

[Description]

Defines the structure of PCIE Task attributes.

[Definition]

```
typedef struct _RK_PCIE_TASK_ATTR {
    int WaitTimeoutMs;
    int SendBuffNum;
    int SendBuffSize;
    int RecvBuffNum;
    int RecvBuffSize;
} RK_PCIE_TASK_ATTR, *PRK_PCIE_TASK_ATTR;
```

[Members]

Member Name	Description
WaitTimeoutMs	Sets the interface timeout, does not support blocking mode.
SendBuffNum	The number of PCIE send buffers, used for buffer polling.
SendBuffSize	The memory size of the send buffer.
RecvBuffNum	The number of PCIE receive buffers, used for buffer polling.
RecvBuffSize	The memory size of the receive buffer.

1.2.1.2 RK_PCIE_DESTROY_TASK

[Description]

Define the structure for releasing PCIE Task.

[Definition]

```
typedef struct _RK_PCIE_DESTROY_TASK {
    int TaskID;
} RK_PCIE_DESTROY_TASK, *PRK_PCIE_DESTROY_TASK;
```

[Members]

Member Name	Description
TaskID	The Task ID to be released

1.2.1.3 RK_PCIE_IOCTL_STATUS

[Description]

Defines the PCIE ioctl call status structure.

[Definition]

```
typedef struct _RK_PCIE_IOCTL_STATUS {  
    int Status;  
    char Data[0];  
} RK_PCIE_IOCTL_STATUS, *PRK_PCIE_IOCTL_STATUS;
```

[Members]

Member Name	Description
Status	The return value of the ioctl call, for details refer to the enum _RK_PCIE_RET list
Data	Data returned by ioctl

1.2.1.4 RK_PCIE_TASK_MSG

[Description]

Defines the Task message structure.

[Definition]

```
typedef struct _RK_PCIE_TASK_MSG {  
    int TaskID;  
    int Size;  
    char Data[TASK_MSG_DATA_SIZE];  
} RK_PCIE_TASK_MSG, *PRK_PCIE_TASK_MSG;
```

[Members]

Member Name	Description
TaskID	Task ID
Size	Message length, maximum length is 1504 Bytes
Data	Message content

1.2.1.5 RK_PCIE_BUFF_NODE

[Description]

Defines the PCIE EP BUF structure.

[Definition]

```
typedef struct _RK_PCIE_BUFF_NODE {
    int Size;
    int TaskID;
    int TimeOut10Ms;
    char Reserved[52]; // 64 = 52 + 4 + 4 + 4
    char Data[0];
} RK_PCIE_BUFF_NODE, *PRK_PCIE_BUFF_NODE;
```

[Members]

Member Name	Description
Size	Data length
TaskID	Task ID
TimeOut10Ms	Sets the interface timeout, does not support blocking mode. Minimum unit is 10ms
Reserved	Reserved size
Data	Data

1.2.1.6 RK_PCIE_DEV_MODE

[Description]

Defines the structure of the PCIE EP device mode.

[Definition]

```
typedef struct _RK_PCIE_DEV_MODE {
    unsigned short Mode;
    unsigned short SubMode;
} RK_PCIE_DEV_MODE, *PRK_PCIE_DEV_MODE;
```

[Members]

Member Name	Description
Mode	Current mode of the PCIE EP device, with the following possible values: #define RKEP_MODE_BOOTROM 1 #define RKEP_MODE_LOADER 2 #define RKEP_MODE_KERNEL 3 #define RKEP_MODE_FUN0 4 #define RKEP_MODE_ERR 0xffff //Device exception, reload required
SubMode	Status corresponding to the mode of the PCIE EP device, with the following possible values: #define RKEP_SMODE_INIT 0 #define RKEP_SMODE_LNKRDY 1 #define RKEP_SMODE_LNKUP 2 #define RKEP_SMODE_FWDLRDY 0x10 #define RKEP_SMODE_FWDLDONE 0x11 #define RKEP_SMODE_APPRDY 0x20 #define RKEP_SMODE_APPDEINIT 0x21 #define RKEP_SMODE_ERR 0xffff

1.2.1.7 RK_PCIE_TASK_INFO

[Description]

Defines the Task information structure.

[Definition]

```
typedef struct _RK_PCIE_TASK_INFO {  
    int TaskID;  
} RK_PCIE_TASK_INFO, *PRK_PCIE_TASK_INFO;
```

[Members]

Member Name	Description
TaskID	Task ID

1.2.1.8 RK_PCIE_DOWNLOAD_FIRMWARE

[Description]

Defines the firmware download structure.

[Definition]

```
typedef struct _RK_PCIE_DOWNLOAD_FIRMWARE {
    size_t RemoteLoadAddr;
    size_t Size;
    char Data[0];
} RK_PCIE_DOWNLOAD_FIRMWARE, *PRK_PCIE_DOWNLOAD_FIRMWARE;
```

[Members]

Member Name	Description
RemoteLoadAddr	EP device memory address
Size	Firmware length
Data	Firmware content

1.3 PCIE Endpoint

1.3.1 rk_pcie_device_init

[Description]

Initializes the PCIe device

[Syntax]

```
int rk_pcie_device_init(void)
```

[Parameters]

None

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, see Error Codes

[Example]

```
typedef struct
{
    pthread_t thr_rcv_rc;
    pthread_t thr_send_rc;
    char rcv_rc_exit;
    char send_rc_exit;
} ep_context_st;
```

```

int main(void)
{
    int ret = 0;
    struct task_context_st task_ctx[PCIE_DMA_TASK_MAX] = {0};
    struct pcie_task_msg_st msg;
    struct task_user_cmd_st *user_cmd;

    ret = rk_pcie_device_init();
    if (ret != 0) {
        printf("pcie init device error....\n");
        return -1;
    }

    while (1) {
        ret = rk_pcie_get_msg_for_bus(&msg, 100);
        if (ret) {
            printf("task_id:%d type:%d size:%ld \n", msg.task_id, msg.type, msg.size);
            switch (msg.type) {
                case E_TASK_MSG_CREATE:
                    task_create(&task_ctx[msg.task_id], msg.task_id);
                    break;
                case E_TASK_MSG_DESTROY:
                    task_destory(&task_ctx[msg.task_id], msg.task_id);
                    break;
                case E_TASK_MSG_USER: {
                    user_cmd = (struct task_user_cmd_st *)msg.data;
                    switch (user_cmd->cmd) {
                        case TASK_USER_CMD_INIT_APP:
                            app_create(&task_ctx[msg.task_id], msg.task_id);
                            break;
                        case TASK_USER_CMD_DEINIT_APP:
                            app_destory(&task_ctx[msg.task_id], msg.task_id);
                            break;
                    }
                }
                break;
                default:
                    printf("error msg type!!! \n");
                    break;
            }
        }
    }

    rk_pcie_device_deinit();

    return 0;
}

```

[Related Topics]

[rk_pcie_device_deinit](#)

1.3.2 rk_pcie_device_deinit

[Description]

Deinitialize PCIe, release resources

[Syntax]

```
int rk_pcie_device_deinit(void)
```

1.3.3 rk_pcie_task_create

[Description]

Create a Task and initialize memory and BUFF management.

[Syntax]

```
int rk_pcie_task_create(int task_id)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID, passed by message from RC end	Input

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes

[Example]

Please refer to the example in [rk_pcie_device_init](#).

[Related Topics]

[rk_pcie_device_deinit](#)

1.3.4 rk_pcie_task_destroy

[Description]

Deinitialize the Task, releasing memory, BUFF management, and other resources.

[Syntax]

```
int rk_pcie_task_destroy(int task_id)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID	Input

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, see Error Codes

[Example]

Please refer to the example in [rk_pcie_device_init](#).

[Related Topics]

[rk_pcie_device_init](#)

1.3.5 rk_pcie_set_ep_info

[Description]

Set EP status information.

[Syntax]

```
int rk_pcie_set_ep_info(void *status, size_t status_size)
```

[Parameters]

Parameter Name	Description	Input/Output
status	void pointer, status structure defined by user	Input
status_size	size of the status structure	Input

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, see Error Codes

[Example]

```

struct ep_info_st {
    unsigned int link_status;
    unsigned int temp;
    long long timestamp;
    unsigned char cpu_load;
    unsigned char npu_load;
    unsigned char gpu_load;
};

ep_info_st ep_info;
while(1) {
    ep_info.timestamp = time(NULL);
    rk_pcie_set_ep_info((void *)&ep_info, sizeof(struct ep_info_st));
}

```

[Related Topics]

[rk_pcie_get_ep_info](#)

1.3.6 rk_pcie_get_user_cmd

[Description]

Retrieve a memory pointer at a specific location in BAR0 for user-defined command areas.

[Syntax]

```
void *rk_pcie_get_user_cmd(void)
```

[Parameters]

None

[Return Value]

Return Value	Description
Non-NULL	Normal, pointer to custom command area memory
NULL	Failure

[Example]

```

struct user_cmd_st {
    unsigned int max_chn;
    unsigned int width;
    unsigned int height;
    unsigned int codec_id;
    unsigned int output_id;
    unsigned int init;
};

```

```

ep_ctx.user_cmd = rk_pcie_get_user_cmd();

while(ep_ctx.user_cmd->init != 1) {
    usleep(1000);
}

ep_ctx.video_obj.width = ep_ctx.user_cmd->width;
ep_ctx.video_obj.height = ep_ctx.user_cmd->height;
ep_ctx.video_obj.input_mode = ep_ctx.user_cmd->codecid;
ep_ctx.video_obj.output_mode = ep_ctx.user_cmd->output_id;
ep_ctx.video_obj.max_chn = ep_ctx.user_cmd->max_chn;
ep_ctx.max_chn = ep_ctx.video_obj.max_chn;

```

[Related Topics]

[rk_pcie_get_user_cmd](#)

1.3.7 rk_pcie_get_bar1_user_buffer

[Description]

Obtain the virtual mapping address of bar1.

[Syntax]

```
void *rk_pcie_get_bar1_user_buffer(void)
```

[Parameters]

None.

[Return Value]

Return Value	Description
void *	Virtual address
NULL	Failure, please refer to Error Codes .

1.3.8 rk_pcie_get_bar5_user_buffer

[Description]

Obtains the virtual mapping address of bar1.

[Syntax]

```
void *rk_pcie_get_bar5_user_buffer(void)
```

[Parameters]

None.

[Return Value]

Return Value	Description
void *	Virtual address
NULL	Failure, see Error Codes .

1.3.9 rk_pcie_set_bar_inbound_cpu_addr

[Description]

Set BAR inbound mapping.

[Syntax]

```
u_int64_t rk_pcie_set_bar_inbound_cpu_addr(u_int32_t atu_index, u_int64_t cpu_address,
u_int32_t size)
```

[Parameters]

Parameter Name	Description	Input/Output
atu_index	ATU index	Input
cpu_address	Mapped CPU address	Input
size	Mapping size limit	Input

[Return Value]

Return Value	Description
cpu_address	Returns CPU address

1.3.10 rk_pcie_get_buff

[Description]

Obtain an available PCIE buffer.

[Syntax]

```
struct pcie_buff_node *rk_pcie_get_buff(int task_id, enum EBuff_Type type)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID	Input
type	PCIE Buff Type	Input

[Return Values]

Return Value	Description
Non-NULL	Pointer to available Buff
NULL	No available Buff

[Example]

```
node = rk_pcie_get_buff(ctx->task_id, E_SEND);
if (node) {
    node->size = buffer_size;
    memset(node->vir_addr, index, node->size);
    add_check_info(node->vir_addr + node->size - CHECK_SIZE);
    rk_pcie_send_buff(ctx->task_id, node);
    index++;
} else {
    usleep(1000);
}
```

[Related Topics]

[rk_pcie_send_buff](#)

1.3.11 rk_pcie_send_buff

[Description]

Sending PCIE buffer.

[Syntax]

```
int rk_pcie_send_buff(int task_id, struct pcie_buff_node *pbuff)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID	Input
pbuff	PCIE Buffer Pointer	Input

[Return Values]

Return Value	Description
0	Successfully sent
Non-zero	Failure, see Error Codes

[Example]

[rk_pcie_get_buff](#)

[Related Topics]

[rk_pcie_get_buff](#)

1.3.12 rk_pcie_release_buff

[Description]

Releases the PCIE buffer.

[Syntax]

```
int rk_pcie_release_buff(int task_id, struct pcie_buff_node *pbuff)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID	Input
pbuff	PCIE Buff Pointer	Input

[Return Values]

Return Value	Description
0	Successfully released
Non-zero	Failure, see Error Codes

[Example]

```
node = rk_pcie_get_buff(ctx->task_id, E_RECV);
if (node) {
    if (check_info(node->vir_addr + node->size - CHECK_SIZE) == 0) {
        pthread_mutex_lock(&ctx->mutex_stream_speed);
        ctx->stream_speed_index++;
        pthread_mutex_unlock(&ctx->mutex_stream_speed);
        // if (mptr != NULL) {
        //     memcpy(mptr, node->vir_addr, node->size);
        // }
        memset(node->vir_addr + node->size - CHECK_SIZE, 0, CHECK_SIZE);
    }
}
```

```

    } else {
        printf("check data ===== error \n");
        for (int i = 0; i < CHECK_SIZE; i++) {
            unsigned char *p = node->vir_addr + node->size - CHECK_SIZE;
            printf("%d ", p[i]);
        }
        printf("\ncheck data ===ssss=====node->size = %d===== error \n", (int)node->size);
    }
    rk_pcie_release_buff(ctx->task_id, node);
} else {
    usleep(1000);
}

```

[Related Topics]

[rk_pcie_release_buff](#)

1.3.13 rk_pcie_get_buff_max_size

[Description]

Obtain the maximum supported size of the buffer.

[Syntax]

```
long rk_pcie_get_buff_max_size(int task_id, enum EBuff_Type type)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID	Input
type	PCIE Buffer Type	Input

[Return Values]

Return Value	Description
Greater than or equal to 0	buffer size
Less than 0	Failure, please refer to Error Codes

[Example]

```
long buffer_size = rk_pcie_get_buff_max_size(ctx->task_id, E_SEND);
```

[Related Topics]

[rk_pcie_get_buff_max_size](#)

1.3.14 rk_pcie_get_msg_for_bus

[Description]

Wait for the RC-side message.

[Syntax]

```
int rk_pcie_get_msg_for_bus(struct pcie_task_msg_st *msg, int timeout_ms)
```

[Parameters]

Parameter Name	Description	Input/Output
timeout_ms	Timeout period, -1 for blocking mode (not recommended, will wait indefinitely in the kernel), it is recommended to use 100ms, unit ms	Input

[Return Values]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes

[Example]

Please refer to the example in [rk_pcie_device_init](#).

[Related Topics]

[rk_pcie_device_deinit](#)

1.3.15 rk_pcie_send_msg_to_rc_task

[Description]

Send a message to the RC side

[Syntax]

```
int rk_pcie_send_msg_to_rc_task(int task_id, void *data, size_t size)
```

[Parameters]

Parameter Name	Description	Input/Output
task_id	Task ID	Input
data	Message Pointer	Input
size	Message Length	Input

[Return Value]

Return Value	Description
0	Success
Non-zero	Failure, please refer to Error Codes

[Example]

Please refer to the example in [rk_pcie_device_init](#).

[Related Topics]

[rk_pcie_device_deinit](#)

1.3.16 Data Types

PCIE RC-related data types and data structure definitions are as follows:

- EBuff_Type: Defines the PCIe Buffer type.
- ETask_Msg_Type: Defines the Task message type.
- struct pcie_buff_node: Defines the PCIe buffer attribute structure.
- struct pcie_task_msg_st: Defines the message attribute structure.

1.3.16.1 EBuff_Type

[Description]

Defines the types of PCIE Buff.

[Definition]

```
enum EBuff_Type {
    E_SEND = 0,
    E_RECV,
};
```

[Members]

Member Name	Description
E_SEND	Send buffer.
E_RECV	Receive buffer.

1.3.16.2 ETask_Msg_Type

[Description]

Defines the types of task messages.

[Definition]

```
enum ETask_Msg_Type {
    E_TASK_MSG_NONE = 0,
    E_TASK_MSG_CREATE,
    E_TASK_MSG_DESTROY,
    E_TASK_MSG_USER,
    E_TASK_MSG_MAX,
};
```

[Members]

Member Name	Description
E_TASK_MSG_NONE	Default value, no significance
E_TASK_MSG_CREATE	Create task
E_TASK_MSG_DESTROY	Destroy task
E_TASK_MSG_USER	User-defined message
E_TASK_MSG_MAX	Maximum message type

1.3.16.3 PCIe Buffer Node

[Description]

Defines the PCIe buffer attribute structure. Any modifications to this structure require changes to both RC and EP.

[Definition]

```
struct pcie_buff_node {
    void *vir_addr;
    size_t phy_addr;
    size_t size;
};
```

[Members]

Member Name	Description
vir_addr	Virtual address.
phy_addr	Physical address.
size	Memory size. Send buffer: Users need to configure the data size, which should not exceed the total buffer memory size. Receive buffer: The size of the data sent by the counterparty.

1.3.16.4 pcie_task_msg_st

[Description]

Defines the message attribute structure. This structure needs to be modified simultaneously in both RC and EP.

[Definition]

```
struct pcie_task_msg_st {  
    enum ETask_Msg_Type type;  
    int task_id;  
    size_t size;  
    char lock;  
    unsigned char data[TASK_MSG_DATA_SIZE];  
};
```

[Members]

Member Name	Description
type	Type of message.
task_id	Task ID.
size	Length of message.
lock	Reserved.
data	Content of message.

1.4 Error Codes

Error Code	Macro Definition	Description
-1	RK_PCIE_ERR_BAD	Abnormal PCIE Link
-2	RK_PCIE_ERR_UNKNOWN	System Exception
-3	RK_PCIE_ERR_NULL_PTR	Null Pointer Error
-4	RK_PCIE_ERR_MALLOC	Memory Allocation Failure
-5	RK_PCIE_ERR_OPEN_FILE	File Open Failure
-6	RK_PCIE_ERR_VALUE	Error Value
-8	RK_PCIE_ERR_TIMEOUT	Timeout Return
-10	RK_PCIE_ERR_UNSupport	Unsupported Feature
-13	RK_PCIE_ERR_HW_UNSupport	Hardware Unsupported
-15	RK_PCIE_ERR_MMAP	Mmap Failure
-65	RK_PCIE_ERR_INIT	Initialization Failure
-66	RK_PCIE_ERR_NOINIT	System Not Initialized
-68	RK_PCIE_ERR_NOMEM	Insufficient Memory
-69	RK_PCIE_ERR_OUTOF_RANGE	Parameter Out of Range