

Description of the new function of Wifi data frame reporting (2024 version):

1.1 Heartbeat Login Frame

Example: Table number 111111111111 Heartbeat frame (default period 3 minutes) EE EE EE EE 68111111111111 689104 B3 B3 B3 B3 97 16

The platform receives the heartbeat frame and needs to reply with a consistent message. If no reply is received for three consecutive times, the meter restarts the module.

1.2 645-2007 (WiFi Report and Query Data Block):

Copy the identifier: 0x028011FF

Copy function code: 0x11

Data items (BCD format)	unit	Byte count
Balance (XXXXXX.XX) (retained)	first	4 byte
Overdraft amount (XXXXXX.XX) (retained)	first	4 byte
Voltage A(XXX.X)	V	2 byte
Voltage B(XXX.X)	V	2 byte
Voltage C(XXX.XXX)	V	2 byte
Current A(XXX.XXX)	A	3 byte
Current B(XXX.XXX)	A	3 byte
Current C(XXX.XXX)	A	3 byte
Total power (XX.XXXX)	KW	3 byte
Power A(XX.XXXX)	KW	3 byte
Power B(XX.XXXX)	KW	3 byte
Power C(XX.XXXX)	KW	3 byte
Total power factor (X.XXX)		2 byte
Phase A power factor (X.XXX)		2 byte
Phase B power factor (X.XXX)		2 byte
Phase C power factor (X.XXX)		2 byte
Total electricity consumption (XXXXXX.XX)	Kwh	4 byte
Peak total electricity consumption (XXXXXX.XX)	Kwh	4 byte
Total power consumption of the peak (XXXXXX.XX)	Kwh	4 byte
Average power consumption (XXXXXX.XX)	Kwh	4 byte
Total electricity consumption (XXXXXX.XX)	Kwh	4 byte
Running status word (hex)		2 byte

		65 byte
--	--	---------

Running status description:

Bit15	Bit14	Bit13	Bit13	Bit11	Bit10	Bit9	Bit8
Protect elec- tricity							switch

state							electric relay
0: Cancel 1: Protect electricity	continue to have	continue to have	continue to have	continue to have	continue to have	continue to have	0: Close 1: Circuit breaker
Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
continue to have	continue to have	continue to have	continue to have	continue to have	continue to have	continue to have	continue to have