# 1729 Project

Ian Turner

April 13, 2021

## Quantum Computing For The Very Curious

*I will use this section document to study this essay on quantum computing. I am not quite sure how to take notes on this yet, but I will figure something out.*

### Measuring a quibit

The key takeaway from this section is that the values of $\alpha$ and $\beta$ can never be determined; in other words, they are hidden information.
**Example**



it's a single-qubit quantum circuit, with input the state $|\psi\rangle$. A NOT gate is applied, followed by a Hadmard gate. The circuit finishes with a measurement in the computational basis, denoted by the slightly enongated semi- circle. The $m$ is a classical bit denoting the measurement result 0, or 1. We use the double wire to indicate the classical bit $m$ going off and being used to do something else.

### General Single-Qubit Gates

Let's look at the most general single-qubit gate. Recall the matrix representations of the NOT and Hadamard gates:

$$X = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix}; \quad H = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$$

If the input to these gates is the quantum state $|\psi\rangle$, then the output is $|X\rangle$ and $|H\rangle$ respectively. In general, a single qubit gate can be represented as a 2x2 unitary matrix, $U$. What does it mean for a matrix $U$ to be unitary? It simply means that $U^\dagger U := (U^T)^*$. The $\dagger$ is also sometimes called the *dagger operation* , or *Hermitian conjugation*, or just the *conjugation* operation.

**Example** Let's start by checking the unitarity of the Hadamard gate, We start by computing the adjoint of H:

$$H^\dagger = \left( \left( \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right)^T \right)^*.$$

Note that taking the transpose doesn't change the matrix, since it is already symmetric. And taking the complex conjgate doesn't change anything, since all the entries are real. So we have $H^\dagger = H$, and thus $H^\dagger H = HH$. so $H$ is, indeed, unitary.

## What Does it Mean for a Matrix to be Unitary?

Can we get an intuition for what it means for a matrix to be unitary? It turns out that unitary matrices *preserve the length of their inputs*. In other words, if we take any vector $|\psi\rangle$ and compute the length $||U|\psi\rangle||$ it's always equal to the length $|||\psi\rangle||$ of the original vector.

### 0.1   The Controlled-NOT Gate



The wire with the small, filled dot on it is called the *control* qubit, for reasons which will become clear in a moment. An the wire with the larger, unfilled circle on it is called the *target* qubit.

The CNOT gate gives us 4 basic computational states:

$$\begin{aligned} |00\rangle &\to |00\rangle \\ |01\rangle &\to |01\rangle \\ |10\rangle &\to |11\rangle \\ |11\rangle &\to |10\rangle \end{aligned}$$

If you're familiar with classical programming languages, then you can think of the CNOT as a very simple kind of `if-then` statement: