

LM193,LM2903,LM293,LM393

LM193/LM293/LM393/LM2903 Low Power Low Offset Voltage Dual Comparators



Literature Number: SNOSBJ6D

LM193/LM293/LM393/LM2903

Low Power Low Offset Voltage Dual Comparators

General Description

The LM193 series consists of two independent precision voltage comparators with an offset voltage specification as low as 2.0 mV max for two comparators which were designed specifically to operate from a single power supply over a wide range of voltages. Operation from split power supplies is also possible and the low power supply current drain is independent of the magnitude of the power supply voltage. These comparators also have a unique characteristic in that the input common-mode voltage range includes ground, even though operated from a single power supply voltage.

Application areas include limit comparators, simple analog to digital converters; pulse, squarewave and time delay generators; wide range VCO; MOS clock timers; multivibrators and high voltage digital logic gates. The LM193 series was designed to directly interface with TTL and CMOS. When operated from both plus and minus power supplies, the LM193 series will directly interface with MOS logic where their low power drain is a distinct advantage over standard comparators.

The LM393 and LM2903 parts are available in National's innovative thin micro SMD package with 8 (12 mil) large bumps.


Advantages

- High precision comparators
- Reduced V_{OS} drift over temperature
- Eliminates need for dual supplies
- Allows sensing near ground
- Compatible with all forms of logic
- Power drain suitable for battery operation

Features


- Wide supply
 - Voltage range: 2.0V to 36V
 - Single or dual supplies: $\pm 1.0V$ to $\pm 18V$
- Very low supply current drain (0.4 mA) — independent of supply voltage
- Low input biasing current: 25 nA
- Low input offset current: ± 5 nA
- Maximum offset voltage: ± 3 mV
- Input common-mode voltage range includes ground
- Differential input voltage range equal to the power supply voltage
- Low output saturation voltage, : 250 mV at 4 mA
- Output voltage compatible with TTL, DTL, ECL, MOS and CMOS logic systems
- Available in the 8-Bump (12 mil) micro SMD package
- See AN-1112 for micro SMD considerations

Squarewave Oscillator




00570938

Non-Inverting Comparator with Hysteresis




00570909

Schematic and Connection Diagrams



00570902


Metal Can Package



TOP VIEW

00570903


Dual-In-Line/SOIC Package



TOP VIEW

00570901

micro SMD




Top View

00570945

micro SMD Marking

XT = Date Code



Pin A1 Corner
Pin A1 is identified by lower left corner with respect to the text.

Top View

00570946

Absolute Maximum Ratings (Note 10)

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

| | |
|---|----------------|
| Supply Voltage, V^+ | 36V |
| Differential Input Voltage (Note 8) | 36V |
| Input Voltage | -0.3V to +36V |
| Input Current ($V_{IN} < -0.3V$) (Note 3) | 50 mA |
| Power Dissipation (Note 1) | |
| Molded DIP | 780 mW |
| Metal Can | 660 mW |
| Small Outline Package | 510 mW |
| micro SMD Package | 568mW |
| Output Short-Circuit to Ground (Note 2) | Continuous |
| Operating Temperature Range | |
| LM393 | 0°C to +70°C |
| LM293 | -25°C to +85°C |

| | |
|---|-----------------|
| LM193/LM193A | -55°C to +125°C |
| LM2903 | -40°C to +85°C |
| Storage Temperature Range | -65°C to +150°C |
| Lead Temperature (Soldering, 10 seconds) | +260°C |
| Soldering Information | |
| Dual-In-Line Package | |
| Soldering (10 seconds) | 260°C |
| Small Outline Package | 215°C |
| Vapor Phase (60 seconds) | |
| Infrared (15 seconds) | 220°C |
| See AN-450 "Surface Mounting Methods and Their Effect on Product Reliability" for other methods of soldering surface mount devices. | |
| ESD rating | |
| (1.5 k Ω in series with 100 pF) | 1300V |

Electrical Characteristics

($V^+ = 5V$, $T_A = 25^\circ C$, unless otherwise stated)

| Parameter | Conditions | | LM193A | | | Units |
|---------------------------------|---|--|--------|-----|-------------|---------|
| | | | Min | Typ | Max | |
| Input Offset Voltage | (Note 9) | | | 1.0 | 2.0 | mV |
| Input Bias Current | $I_{IN}(+)$ or $I_{IN}(-)$ with Output In Linear Range, $V_{CM} = 0V$ (Note 5) | | | 25 | 100 | nA |
| Input Offset Current | $I_{IN}(+) - I_{IN}(-)$ $V_{CM} = 0V$ | | | 3.0 | 25 | nA |
| Input Common Mode Voltage Range | $V^+ = 30V$ (Note 6) | | 0 | | $V^+ - 1.5$ | V |
| Supply Current | $R_L = \infty$ $V^+ = 5V$ | | | 0.4 | 1 | mA |
| | $V^+ = 36V$ | | | 1 | 2.5 | mA |
| Voltage Gain | $R_L \geq 15 k\Omega$, $V^+ = 15V$ $V_O = 1V$ to $11V$ | | 50 | 200 | | V/mV |
| Large Signal Response Time | $V_{IN} = \text{TTL Logic Swing}$, $V_{REF} = 1.4V$ $V_{RL} = 5V$, $R_L = 5.1 k\Omega$ | | | 300 | | ns |
| Response Time | $V_{RL} = 5V$, $R_L = 5.1 k\Omega$ (Note 7) | | | 1.3 | | μs |
| Output Sink Current | $V_{IN}(-) = 1V$, $V_{IN}(+) = 0$, $V_O \approx 1.5V$ | | 6.0 | 16 | | mA |
| Saturation Voltage | $V_{IN}(-) = 1V$, $V_{IN}(+) = 0$, $I_{SINK} \leq 4 \text{ mA}$ | | | 250 | 400 | mV |
| Output Leakage Current | $V_{IN}(-) = 0$, $V_{IN}(+) = 1V$, $V_O = 5V$ | | | 0.1 | | nA |

Electrical Characteristics

($V^+ = 5V$, $T_A = 25^\circ C$, unless otherwise stated)

| Parameter | Conditions | LM193 | | | LM293, LM393 | | | LM2903 | | | Units |
|---------------------------------|--|-------|-----|-------------|--------------|-----|-------------|--------|-----|-------------|-------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| Input Offset Voltage | (Note 9) | | 1.0 | 5.0 | | 1.0 | 5.0 | | 2.0 | 7.0 | mV |
| Input Bias Current | $I_{IN}(+)$ or $I_{IN}(-)$ with Output In Linear Range, $V_{CM} = 0V$ (Note 5) | | 25 | 100 | | 25 | 250 | | 25 | 250 | nA |
| Input Offset Current | $I_{IN}(+) - I_{IN}(-)$ $V_{CM} = 0V$ | | 3.0 | 25 | | 5.0 | 50 | | 5.0 | 50 | nA |
| Input Common Mode Voltage Range | $V^+ = 30V$ (Note 6) | | 0 | $V^+ - 1.5$ | | 0 | $V^+ - 1.5$ | | 0 | $V^+ - 1.5$ | V |

Electrical Characteristics (Continued)(V⁺=5V, T_A = 25°C, unless otherwise stated)

| Parameter | Conditions | | LM193 | | | LM293, LM393 | | | LM2903 | | | Units |
|----------------------------|---|---------------------|-------|-----|-----|--------------|-----|-----|--------|-----|-----|-------|
| | | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| Supply Current | R _L =∞ | V ⁺ =5V | 0.4 | 1 | | 0.4 | 1 | | 0.4 | 1.0 | | mA |
| | | V ⁺ =36V | 1 | 2.5 | | 1 | 2.5 | | 1 | 2.5 | | mA |
| Voltage Gain | R _L ≥15 kΩ, V ⁺ =15V V _O = 1V to 11V | | 50 | 200 | | 50 | 200 | | 25 | 100 | | V/mV |
| Large Signal Response Time | V _{IN} =TTL Logic Swing, V _{REF} =1.4V V _{RL} =5V, R _L =5.1 kΩ | | 300 | | | 300 | | | 300 | | | ns |
| Response Time | V _{RL} =5V, R _L =5.1 kΩ (Note 7) | | 1.3 | | | 1.3 | | | 1.5 | | | μs |
| Output Sink Current | V _{IN} (-)=1V, V _{IN} (+)=0, V _O ≤1.5V | | 6.0 | 16 | | 6.0 | 16 | | 6.0 | 16 | | mA |
| Saturation Voltage | V _{IN} (-)=1V, V _{IN} (+)=0, I _{SINK} ≤4 mA | | 250 | 400 | | 250 | 400 | | 250 | 400 | | mV |
| Output Leakage Current | V _{IN} (-)=0, V _{IN} (+)=1V, V _O =5V | | 0.1 | | | 0.1 | | | 0.1 | | | nA |

Electrical Characteristics(V⁺ = 5V) (Note 4)

| Parameter | Conditions | LM193A | | | Units |
|---------------------------------|--|--------|-----|---------------------|-------|
| | | Min | Typ | Max | |
| Input Offset Voltage | (Note 9) | | | 4.0 | mV |
| Input Offset Current | I _{IN(+)} -I _{IN(-)} , V _{CM} =0V | | | 100 | nA |
| Input Bias Current | I _{IN(+)} or I _{IN(-)} with Output in Linear Range, V _{CM} =0V (Note 5) | | | 300 | nA |
| Input Common Mode Voltage Range | V ⁺ =30V (Note 6) | 0 | | V ⁺ -2.0 | V |
| Saturation Voltage | V _{IN} (-)=1V, V _{IN} (+)=0, I _{SINK} ≤4 mA | | | 700 | mV |
| Output Leakage Current | V _{IN} (-)=0, V _{IN} (+)=1V, V _O =30V | | | 1.0 | μA |
| Differential Input Voltage | Keep All V _{IN} 's≥0V (or V ⁻ , if Used), (Note 8) | | | 36 | V |

Electrical Characteristics(V⁺ = 5V) (Note 4)

| Parameter | Conditions | LM193 | | | LM293, LM393 | | | LM2903 | | | Units |
|---------------------------------|--|-------|-----|---------------------|--------------|-----|---------------------|--------|-----|---------------------|-------|
| | | Min | Typ | Max | Min | Typ | Max | Min | Typ | Max | |
| Input Offset Voltage | (Note 9) | | | 9 | | | 9 | | | 15 | mV |
| Input Offset Current | I _{IN(+)} -I _{IN(-)} , V _{CM} =0V | | | 100 | | | 150 | | | 200 | nA |
| Input Bias Current | I _{IN(+)} or I _{IN(-)} with Output in Linear Range, V _{CM} =0V (Note 5) | | | 300 | | | 400 | | | 500 | nA |
| Input Common Mode Voltage Range | V ⁺ =30V (Note 6) | 0 | | V ⁺ -2.0 | 0 | | V ⁺ -2.0 | 0 | | V ⁺ -2.0 | V |
| Saturation Voltage | V _{IN} (-)=1V, V _{IN} (+)=0, I _{SINK} ≤4 mA | | | 700 | | | 700 | | | 400 700 | mV |
| Output Leakage Current | V _{IN} (-)=0, V _{IN} (+)=1V, V _O =30V | | | 1.0 | | | 1.0 | | | 1.0 | μA |
| Differential Input Voltage | Keep All V _{IN} 's≥0V (or V ⁻ , if Used), (Note 8) | | | 36 | | | 36 | | | 36 | V |

Note 1: For operating at high temperatures, the LM393 and LM2903 must be derated based on a 125°C maximum junction temperature and a thermal resistance of 170°C/W which applies for the device soldered in a printed circuit board, operating in a still air ambient. The LM193/LM193A/LM293 must be derated based on a 150°C maximum junction temperature. The low bias dissipation and the "ON-OFF" characteristic of the outputs keeps the chip dissipation very small (P_D≤100 mW), provided the output transistors are allowed to saturate.

Note 2: Short circuits from the output to V⁺ can cause excessive heating and eventual destruction. When considering short circuits to ground, the maximum output current is approximately 20 mA independent of the magnitude of V⁺.

Note 3: This input current will only exist when the voltage at any of the input leads is driven negative. It is due to the collector-base junction of the input PNP transistors becoming forward biased and thereby acting as input diode clamps. In addition to this diode action, there is also lateral NPN parasitic transistor action

Electrical Characteristics (Continued)

on the IC chip. This transistor action can cause the output voltages of the comparators to go to the V^+ voltage level (or to ground for a large overdrive) for the time duration that an input is driven negative. This is not destructive and normal output states will re-establish when the input voltage, which was negative, again returns to a value greater than $-0.3V$.

Note 4: These specifications are limited to $-55^{\circ}C \leq T_A \leq +125^{\circ}C$, for the LM193/LM193A. With the LM293 all temperature specifications are limited to $-25^{\circ}C \leq T_A \leq +85^{\circ}C$ and the LM393 temperature specifications are limited to $0^{\circ}C \leq T_A \leq +70^{\circ}C$. The LM2903 is limited to $-40^{\circ}C \leq T_A \leq +85^{\circ}C$.

Note 5: The direction of the input current is out of the IC due to the PNP input stage. This current is essentially constant, independent of the state of the output so no loading change exists on the reference or input lines.

Note 6: The input common-mode voltage or either input signal voltage should not be allowed to go negative by more than $0.3V$. The upper end of the common-mode voltage range is $V^+ - 1.5V$ at $25^{\circ}C$, but either or both inputs can go to $36V$ without damage, independent of the magnitude of V^+ .

Note 7: The response time specified is for a 100 mV input step with 5 mV overdrive. For larger overdrive signals 300 ns can be obtained, see typical performance characteristics section.

Note 8: Positive excursions of input voltage may exceed the power supply level. As long as the other voltage remains within the common-mode range, the comparator will provide a proper output state. The low input voltage state must not be less than $-0.3V$ (or $0.3V$ below the magnitude of the negative power supply, if used).

Note 9: At output switch point, $V_O = 1.4V$, $R_S = 0\Omega$ with V^+ from $5V$ to $30V$; and over the full input common-mode range ($0V$ to $V^+ - 1.5V$), at $25^{\circ}C$.

Note 10: Refer to RETS193AX for LM193AH military specifications and to RETS193X for LM193H military specifications.


Ordering Information

| Package | Temperature Range | Part Number | NSC Drawing |
|-------------------------------|----------------------------------|----------------|-------------|
| 8-Pin Metal Can | $-55^{\circ}C$ to $125^{\circ}C$ | LM193H* | H08C |
| | | LM193H/883 | |
| | | LM193H-MLS | |
| | | LM193AH-MLS | |
| | | LM193AH-QMLV** | |
| | | LM193AH | |
| | | LM193AH/883 | |
| | $-25^{\circ}C$ to $85^{\circ}C$ | LM293H | |
| | $0^{\circ}C$ to $70^{\circ}C$ | LM393H | |
| 8-Pin Ceramic DIP | $-55^{\circ}C$ to $125^{\circ}C$ | LM193J/883* | J08A |
| | | LM193AJ/883 | |
| | | LM193AJ-QMLV** | |
| | | LM193AJ-MLS | |
| 8-Pin Molded DIP | $0^{\circ}C$ to $70^{\circ}C$ | LM393N | N08E |
| | $-40^{\circ}C$ to $85^{\circ}C$ | LM2903N | |
| 8-Pin SOIC | $0^{\circ}C$ to $70^{\circ}C$ | LM393M | M08A |
| | $-40^{\circ}C$ to $85^{\circ}C$ | LM393MX | |
| | | LM2903M | |
| | | LM2903MX | |
| 8-Bump (12 mils) micro SMD | $0^{\circ}C$ to $70^{\circ}C$ | LM393TL | TLA08AAA |
| | $-40^{\circ}C$ to $85^{\circ}C$ | LM393TLX | |
| | | LM2903ITL | |
| | | LM2903ITLX | |


Note: * Also available per LM38510/11202

Note: ** See STD Mil DWG 5962-94526


Typical Performance Characteristics LM193/LM293/LM393, LM193A



00570925




00570926




00570927

Response Time for Various Input Overdrives — Negative Transition



00570928


Response Time for Various Input Overdrives — Positive Transition



00570929


Typical Performance Characteristics LM2903

Supply Current




00570930

Input Current




00570931

Output Saturation Voltage




00570932

Response Time for Various Input Overdrives — Negative Transition



00570933

Response Time for Various Input Overdrives — Positive Transition



00570934

Application Hints

The LM193 series are high gain, wide bandwidth devices which, like most comparators, can easily oscillate if the output lead is inadvertently allowed to capacitively couple to the inputs via stray capacitance. This shows up only during the output voltage transition intervals as the comparator change states. Power supply bypassing is not required to solve this problem. Standard PC board layout is helpful as it reduces stray input-output coupling. Reducing the input resistors to $< 10 \text{ k}\Omega$ reduces the feedback signal levels and finally, adding even a small amount (1.0 to 10 mV) of positive feedback (hysteresis) causes such a rapid transition that oscillations due to stray feedback are not possible. Simply socketing the IC and attaching resistors to the pins will cause input-output oscillations during the small transition intervals unless hysteresis is used. If the input signal is a pulse waveform, with relatively fast rise and fall times, hysteresis is not required.

All input pins of any unused comparators should be tied to the negative supply.

The bias network of the LM193 series establishes a drain current which is independent of the magnitude of the power supply voltage over the range of from $2.0 V_{DC}$ to $30 V_{DC}$.


It is usually unnecessary to use a bypass capacitor across the power supply line.

The differential input voltage may be larger than V^+ without damaging the device (Note 8). Protection should be provided to prevent the input voltages from going negative more than $-0.3 V_{DC}$ (at 25°C). An input clamp diode can be used as shown in the applications section.

The output of the LM193 series is the uncommitted collector of a grounded-emitter NPN output transistor. Many collectors can be tied together to provide an output OR'ing function. An output pull-up resistor can be connected to any available power supply voltage within the permitted supply voltage range and there is no restriction on this voltage due to the magnitude of the voltage which is applied to the V^+ terminal of the LM193 package. The output can also be used as a simple SPST switch to ground (when a pull-up resistor is not used). The amount of current which the output device can sink is limited by the drive available (which is independent of V^+) and the β of this device. When the maximum current limit is reached (approximately 16mA), the output transistor will come out of saturation and the output voltage will rise very rapidly. The output saturation voltage is limited by the approximately $60\Omega r_{SAT}$ of the output transistor. The low offset voltage of the output transistor (1.0mV) allows the output to clamp essentially to ground level for small load currents.


Typical Applications $(V^+=5.0 V_{DC})$

Basic Comparator




00570935

Driving CMOS




00570936

Driving TTL




00570937

Squarewave Oscillator



00570938


Pulse Generator



00570939

* For large ratios of $R1/R2$, $D1$ can be omitted.


Crystal Controlled Oscillator



00570940

Typical Applications ($V^+ = 5.0\text{ V}_{DC}$) (Continued)


Two-Decade High Frequency VCO



00570941


$V^* = +30\text{ V}_{DC}$
 $+250\text{ mV}_{DC} \leq V_C \leq +50\text{ V}_{DC}$
 $700\text{Hz} \leq f_o \leq 100\text{kHz}$

Basic Comparator




00570906

Non-Inverting Comparator with Hysteresis




00570909

Inverting Comparator with Hysteresis



00570910

Output Strobing




* OR LOGIC GATE
 WITHOUT PULL-UP RESISTOR

00570911


Typical Applications ($V^+=5.0\text{ V}_{\text{DC}}$) (Continued)

AND Gate




00570912

OR Gate




00570913

Large Fan-in AND Gate




00570914

Limit Comparator




00570915

Comparing Input Voltages of Opposite Polarity



00570916


ORing the Outputs



00570917


Typical Applications ($V^+=5.0\text{ V}_{\text{DC}}$) (Continued)

Zero Crossing Detector (Single Power Supply)




00570921

One-Shot Multivibrator




00570922

Bi-Stable Multivibrator




00570924

One-Shot Multivibrator with Input Lock Out




00570923

Zero Crossing Detector



00570943


Comparator With a Negative Reference



00570944

Typical Applications ($V^+=5.0\text{ V}_{\text{DC}}$) (Continued)


Time Delay Generator



00570907


Split-Supply Applications ($V^+=+15\text{ V}_{\text{DC}}$ and $V^-=-15\text{ V}_{\text{DC}}$)

MOS Clock Driver




00570942

Physical Dimensions inches (millimeters) unless otherwise noted




Metal Can Package (H)
NS Package Number H08C




Ceramic Dual-In-Line Package
NS Package Number J08A

Physical Dimensions inches (millimeters) unless otherwise noted (Continued)




SOIC Package
NS Package Number M08A






Molded Dual-In-Line Package (N)
NS Package N08E

Physical Dimensions

inches (millimeters) unless otherwise noted (Continued)



LAND PATTERN RECOMMENDATION



TLA08XXX (Rev A)

NOTE: UNLESS OTHERWISE SPECIFIED

1. EPOXY COATING
2. 63Sn/37Pb EUTECTIC BUMP
3. RECOMMEND NON-SOLDER MASK DEFINED LANDING PAD.
4. PIN A1 IS ESTABLISHED BY LOWER LEFT CORNER WITH RESPECT TO TEXT ORIENTATION REMAINING PINS ARE NUMBERED COUNTERCLOCKWISE.
5. XXX IN DRAWING NUMBER REPRESENTS PACKAGE SIZE VARIATION WHERE X_1 IS PACKAGE WIDTH, X_2 IS PACKAGE LENGTH AND X_3 IS PACKAGE HEIGHT.
6. REFERENCE JEDEC REGISTRATION MO-211, VARIATION BC.

8-Bump (12 mil) micro SMD Package
NS Package TLA08AAA

$X_1 = 1.514\text{mm}$ $X_2 = 1.514\text{mm}$ $X_3 = 0.600\text{mm}$

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT AND GENERAL COUNSEL OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



**National Semiconductor
Corporation**
Americas
Email: support@nsc.com

www.national.com

**National Semiconductor
Europe**

Fax: +49 (0) 180-530 85 86
Email: europe.support@nsc.com
Deutsch Tel: +49 (0) 69 9508 6208
English Tel: +44 (0) 870 24 0 2171
Francais Tel: +33 (0) 1 41 91 8790

**National Semiconductor
Asia Pacific Customer
Response Group**

Response Group
Tel: 65-2544466
Fax: 65-2504466
Email: ap.support@nsc.com

**National Semiconductor
Japan Ltd.**

Tel: 81-3-5639-7560
Fax: 81-3-5639-7507

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

| | |
|------------------------|--|
| Audio | www.ti.com/audio |
| Amplifiers | amplifier.ti.com |
| Data Converters | dataconverter.ti.com |
| DLP® Products | www.dlp.com |
| DSP | dsp.ti.com |
| Clocks and Timers | www.ti.com/clocks |
| Interface | interface.ti.com |
| Logic | logic.ti.com |
| Power Mgmt | power.ti.com |
| Microcontrollers | microcontroller.ti.com |
| RFID | www.ti-rfid.com |
| OMAP Mobile Processors | www.ti.com/omap |
| Wireless Connectivity | www.ti.com/wirelessconnectivity |

Applications

| | |
|-------------------------------|--|
| Communications and Telecom | www.ti.com/communications |
| Computers and Peripherals | www.ti.com/computers |
| Consumer Electronics | www.ti.com/consumer-apps |
| Energy and Lighting | www.ti.com/energy |
| Industrial | www.ti.com/industrial |
| Medical | www.ti.com/medical |
| Security | www.ti.com/security |
| Space, Avionics and Defense | www.ti.com/space-avionics-defense |
| Transportation and Automotive | www.ti.com/automotive |
| Video and Imaging | www.ti.com/video |

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated