

1. What does the AUTOEND bit in the CR2 register do? Why don't you want to use it when you'll be needing a restart condition?
  - a. Forces stop vs restart.
2. This lab used standard-mode 100 kHz I2C speed. What values would you write in the TIMINGR if we were using 400 kHz fast-mode?
  - a. PRESC → 0 SCLL → 0x9 SCLH → 0x3 SDADEL → 0x1 SCLDEL → 0x3
3. This lab used blocking code. To implement it completely as non-blocking you would replace all of the wait loops with interrupts. Most flags in the I2C peripheral can trigger an interrupt if the proper enable bit is set. Find the interrupt enable bits that match the following flags: The Inter-Integrated Circuit (I2C) Interface 17 • TC • NACKF • TXIS (transmit interrupt) • ARLO
  - a. TC → I2C\_CR1 Bit 6 NACKF → I2C\_CR1 Bit 4 TXIS → I2C\_CR1 Bit 1 ARLO → I2C\_CR1 Bit 7
4. The gyro can operate in three full-scale/measurement ranges, measured in degrees-per-second (dps). What are these three ranges?
  - a. 245, 500, or 2000
5. What is the I2C address of the gyro when the SDO pin is low? The lab has the pin set high, read the I2C section of the gyro datasheet
  - a. 1101000b