

BOSCH  ROBERT BOSCH (AUSTRALIA) PTY. LTD. A.B.N. 48 004 315 626	PRODUCTION TEST SPECIFICATION FOA Barra Body Electronics Module High and Low Series	F005 VP 0067 Page 1 of 29
--	--	-------------------------------------

	Department	Date	Signature
Drawn	EGE3JEV	19/3/03	
Checked	EGE3MS	19/3/03	
Approved	EGE3	19-3-03	

1. ALTERATION LIST

Issue	ECR Number	Alteration	By	Valid From	Checked
11	V001361	To support Mask 1 Version 13 Motorola Software with Mask2 Version 5 Atmel Software: Sect 12.1: Add check to confirm Version Number and Release Date being V13 dated 6/8/2002 Sect 12.3: Remove Gang Programmer Motorola Flash Microcomputer Checksum since using Mask Motorola Microcomputer Sect15: Add Checksum for Mask Microcomputer as \$C73C at EEprom address \$0938	EGE3-JEV	19/3/03	EGE3-JEV
10	V001184	To support correct Internal P&A part number: Sect15: Update FordPartNumberPrefix(4) (\$0800) Change P&A from BA18 to 3R23 in ascii for both OE and P&A. Note: External housing P&A label will use BA18. Update FordPartNumberSuffix(2) (\$0804) for Low Series from AA to AB and High Series from BA to BB by changing data from 0000 to 0001 for Low Series and 0200 to 0201 for High Series for both OE and P&A. Note: External housing P&A label will use Suffix B for High Series and Suffix A for Low Series. Update Final Tester ID(3) (\$0806) to show the Final Tester Inventory No.	EGE3-JEV	11/11/02	EGE3-JEV
9	V001177	To support Version 14 Software: Sect 10: For Quiescent current measurement, get the BEM into sleep (Stop) mode by setting the following: Turn supply on, wait 500ms before enabling CCP. Set RAM CrashKey_uwl at address \$C8 and \$C9 to \$55 and \$AA. Set Bit 4 of RAM BEMMainFlags_uhl at address \$52 to 1. BEM will go into STOP mode within 200ms. Sect 12.3: Update checksum for Production Programmer of standalone Motorola Microprocessor for Version 14 software to \$89BC74 (8bit) and \$458A0DDD (16 bit). Sect15: Update FordPartNumberSuffix(2) (\$0804) for Low Series from AA to AB and High Series from BA to BB by changing data from 0000 to 0001 for Low Series and 0200 to 0201 for High Series. Update DSTEncryptionKeyChecksum (\$084B) from 5 bytes to 1 byte (LSB)	EGE3-JEV	6/11/02	EGE3-JEV
8	V001170	To support changes required for Barra BEM P&A: Sect 12.3: Update BEM Variant to include the following note "For P&A, seven EEprom locations are to be modified (See Sect 15) at addresses \$800-\$803, \$840, \$870 and \$8EB. The auto EEprom download is applicable only for OE, therefore the Final Tester or ICT will have to write and verify the specific P&A data" Sect15: Update EEprom Table with the following changes required for P&A: - FordPartNumberPrefix (\$0800-\$0803) - Change OE: '3R23' to P&A: 'BA18' - DSTPlantMode (\$0840) - Change OE: \$55 to P&A: \$00 - EECPlantMode (\$0870) - Change OE: \$55 to P&A: \$00 - Factory Mode (\$08EB) - Change OE: 'o' to P&A: 'p'	EGE3-JEV	28/10/02	EGE3-JEV

Issue Number:	11 (DV1600)	Valid from:	19 March 2003	Print Date:	19 March 2003
---------------	-------------	-------------	---------------	-------------	---------------

© THIS DRAWING IS THE EXCLUSIVE PROPERTY OF ROBERT BOSCH (AUSTRALIA) PTY. LTD. WITHOUT THEIR CONSENT IT MAY NOT BE REPRODUCED OR GIVEN TO THIRD PARTIES. DEV04407.1